



(51) International Patent Classification:

G10L 21/038 (2013.01) *G10L 25/69* (2013.01)

(21) International Application Number:

PCT/EP2018/025082

(22) International Filing Date:

29 March 2018 (29.03.2018)

(25) Filing Language:

English

(26) Publication Language:

English

(30) Priority Data:

17164360.4 31 March 2017 (31.03.2017) EP
17189999.0 07 September 2017 (07.09.2017) EP

(71) Applicants: **FRAUNHOFER-GESELLSCHAFT ZUR FÖRDERUNG DER ANGEWANDTEN FORSCHUNG E.V.** [DE/DE]; Hansastraße 27c, 80686 München

(DE). **FRIEDRICH-ALEXANDER-UNI VERSITÄT ERLANGEN-NÜRNBERG** [DE/DE]; Schlossplatz 4, 91054 Erlangen (DE).

(72) **Inventors:** **GAMPP, Patrick**; Sieglitzhofer Str, 28, 91054 Erlangen (DE). **UHLE, Christian**; Hoher Rain 28, 92289 Ursensollen (DE). **DISCH, Sascha**; Wilhelmstraße 70, 90766 Fürth (DE). **KARAMPOURNIOTIS, Antonios**; Mendelstrasse 25, 90429 Nurnberg (DE). **HAVENSTEIN, Julia**; Gostenhofer Hauptstrasse 58, 90443 Nornberg (DE). **HELLMUTH, Oliver**; Am Ruhstein 29, 91054 Buckenhof (DE). **HERRE, Jürgen**; Rathberger Straße 10a, 91054 Erlangen (DE). **PROKEIN, Peter**; Walburgastraße 13, 91056 Erlangen (DE).

(74) **Agent:** **KÖNIG, Andreas**; SCHOPPE, ZIMMERMANN, STÖCKELER, ZINKLER, SCHENK & PARTNER mbB, Radlkoferstraße 2, 81373 München (DE).

(54) Title: APPARATUS AND METHODS FOR PROCESSING AN AUDIO SIGNAL




Fig. 14

(57) **Abstract:** An apparatus for processing an audio signal comprises a separator for separating a first portion of a spectrum of the audio signal from a second portion of the spectrum of the audio signal, the first portion having a first signal characteristic and the second portion having a second signal characteristic. The apparatus comprises a first bandwidth extender for extending a bandwidth of the first portion using first parameters associated with the first signal characteristic, for obtaining a first extended portion and comprises a second bandwidth extender for extending a bandwidth of the second portion using second parameters associated with the second signal characteristic, for obtaining a second extended portion. The apparatus comprises a combiner configured for using the first extended portion and the second extended portion for obtaining an extended combined audio signal.



(81) Designated States (*unless otherwise indicated, for every kind of national protection available*): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DJ, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IR, IS, JO, JP, KE, KG, KH, KN, KP, KR, KW, KZ, LA, LC, LK, LR, LS, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

(84) Designated States (*unless otherwise indicated, for every kind of regional protection available*): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, KM, ML, MR, NE, SN, TD, TG).

Published:

— with international search report (Art. 21(3))

Apparatus and Methods for Processing an Audio Signal

Description

5

In multi-media applications, audio signals are often coded using dedicated perceptual coding methods like MPEG1/2 Layer 3 ("mp3"), MPEG2/4 Advanced audio coding (AAC), etc. When decoding the encoded audio signal diverse processing methods may be applied so as to reconstruct the audio signal that was originally encoded. However, due to lossy coding operations such as perceptually adapted quantization or parametric coding techniques such as Spectral Bandwidth Replication (SBR), it is possible to obtain artifacts in the decoded audio signal that might be disturbing.

10

15

For quite a long time, perceptual audio coders have been developed to foremost preserve the perceptual quality of the original signals. If the coded and non-coded signal is perceptually indistinguishable, this property is called "perceptual transparency".

20

However, transparency can only be achieved if the available bitrate (i.e. the amount of data used) is high enough. In recent years, it was realized that, at low bitrates, perceptual pleasantness becomes more important than closeness to the original in a transparency sense. Therefore, well-established perceptual coding schemes like MP3 or AAC may sound sub-optimal to date compared to modern coding approaches targeting perceptual pleasantness.

25

In the following, some coding artifacts are briefly described.

The Birdies Artifact

30

At low bitrate transform coding, often the quantizers for the coding of the spectral lines have to be set to a very coarse precision, such that their dynamic range is poly adapted to the signal. As a result, many spectral lines are quantized to 0 by the dead-zone of the quantizer or to the value 1, corresponding to the first quantizer step. Over time, spectral lines or groups of lines might toggle between 0 and 1, thereby introducing unwanted temporal modulation. This artifact is called "Birdies" being reminiscent of a bird's twitter.

35

Therefore, this strong time-varying presence of spectral holes and spectral islands is unwanted codec behavior leading to objectionable perceptual artifacts, see [2] and [3].

Bandwidth Limitation

Another well-known coding artifact is bandwidth limitation. If, at low bitrate coding
5 conditions, the available bit budget is insufficient to accommodate the needed precision
for transparency, legacy codecs often introduced a static low-pass to limit the audio
bandwidth. This may lead to a dull and muffled sound impression, see [2] and [3].

Tonal Spike Artifact

10

This artifact appears in connection with artificial bandwidth extension methods such as
spectral band replication (SBR), see [4], when the tonal-to-noise ratio has been
overestimated. In this case tonal components are recreated with too much energy which
leads to a metallic sound, see [3].

15

Beating Artifact

As well as the tonal spike artifact, the beating artifact appears in conjunction with artificial
bandwidth extension. Beating creates the perception of roughness and emerges from two
20 tonal components with close frequency distance which can be caused by the copy up as
used in SBR, see [3].

Therefore, it is an aim to detect, if the audio signal was subjected to a processing that is
capable of introducing artifacts and/or to reduce such artifacts.

25

An example for a processing method that may be a source for artifacts is the Spectral
Band Replication (SBR) being a semi-parametric method for extending the bandwidth of
an audio signal on the decoder side. In a first step, parts of the transmitted lowpass signal
spectrum are replicated by copying the spectral coefficients from the lower to the higher
30 frequency region. In a second step, the spectral envelope is adjusted. The adjustment of
the spectral envelope is performed such that the coarse shape of the spectrum matches a
given target, whereas the fine structure remains unmodified.

The detection of SBR is desired because from the obtained information it can be
35 concluded that

1. The signals have been compressed by means of perceptual audio coding (i.e., lossy). That follows that an application of enhancement methods addressing the above mentioned artefact types are appropriate.
- 5 2. The sound quality of the signal can potentially be improved by dedicated methods for reducing the audibility of artifacts that have been introduced by the SBR. Such methods benefit from the knowledge about the start frequency at which SBR is in effect.
- 10 The starting frequency at which SBR is in effect is of interest for post-processings that improve the sound quality by mitigating artifacts introduced by SBR. Therefore, there is a need for detecting SBR and for estimating the start frequency of SBR. In particular, it is a desire to determine whether such enhancement is desired or not. It is, for example, not appropriate for signals of high sound quality, because the enhancement can degrade the
15 sound quality when the audio signal is of high sound quality.

A method for the detection of SBR is described in US 9,117,440 B2. The described method operates on sub-band signals that are computed using a filterbank or time-frequency transform. It then quantifies the relationship between multiple sub-bands by
20 means of cross-correlation, i.e., by multiplying the corresponding samples and accumulating these products over time.

Another example for a source of artifacts is bandwidth reduction (BR) which is also referred to as bandwidth limitation (BL). When the bandwidth is severely limited, a
25 degradation of the sound quality is perceived and a quality enhancement is desired. Such quality improvement may comprise a bandwidth extension (BWE), which should only be applied if needed, i.e. when the natural bandwidth of the signals has been artificially severely reduced. A method for BWE that uses an estimation of the bandwidth is described in [1]. The bandwidth is estimated by detecting the highest frequency present in
30 the signal at any given time. This method is prone to false positive detection errors, because an audio signal can have a limited bandwidth by nature as the mechanism that generated the signal has only generated energy at lower frequencies.

Summing up, perceptual audio coders are widely used, when storage space or streaming
35 bandwidth for audio content is limited. If the applied compression rate is very high (and

the used data rate after compression is very low), several coding artifacts are introduced that degrade the perceived audio quality.

5 Therefore, it is an object of the invention to provide for an enhancing identification of audio signals comprising a characteristic being obtained by artifact prone audio processing and/or to provide for a concept to reduce such artifacts through application of dedicated post-processings on such audio material.

This object is achieved by the subject matter according to the independent claims.

10

According to a first aspect, the inventors have found out that by using a local maximum signal being derived from the audio signals and by determining a similarity between segments of the local maximum signal, a secure and efficient identification of a characteristic related to a spectral enhancement processing may be obtained such that a
15 respective post-processing may be implemented for the respective audio signal so as to reduce, for example, the tonal spike artifact and/or the beating artifact. Based on the evaluation of the signal, a side-information indicating the implemented audio processing may be not required such that a blind operation of the module is possible.

20 According to an embodiment of the first aspect, an apparatus for determining a predetermined characteristic related to a spectral enhancement processing of an audio signal comprises a deriver configured for obtaining a spectrum of the audio signal and for deriving information related to a fine structure of the spectrum. The apparatus comprises a determiner configured for determining a similarity in the fine structure of the spectrum. The
25 apparatus further comprises a processor for providing an information indicating that the audio signal comprises the predetermined characteristic dependent on an evaluation of the similarity. For comparing a similarity between the segments of the information related to the fine structure, a low amount of computational effort may be required. Further, a precise and secure determination of similar segments indicating that a spectral
30 enhancement processing may have been performed, may be obtained.

According to a further embodiment of the first aspect, a method for determining a predetermined characteristic related to a spectral enhancement processing of an audio signal comprises obtaining a spectrum of the audio signal and deriving information related
35 to a fine structure of the spectrum. The method comprises determining a similarity in the fine structure such as between segments of the information related to the fine structure

and comprises providing an information indicating that the audio signal comprises the predetermined characteristic dependent on an evaluation of the similarity.

5 According to a further embodiment of the first aspect, a non-transitory storage medium has stored there on a computer program having a program code for performing, when running on a computer, such a method.

10 According to a second aspect, the inventors have found out that by evaluating a spectrum of an audio signal with respect to a slope of the spectrum, a secure and efficient characterization of the audio signal so as to comprise a characteristic related to an artificial bandwidth limitation processing may be obtained so as to enable a respective post-processing, for example to reduce or eliminate a birdies artifact and/or a bandwidth limitation artifact. Based on the evaluation of the signal, a side-information indicating the implemented audio processing may be not required such that a blind operation of the
15 module is possible.

According to an embodiment of the second aspect, an apparatus for determining a predetermined characteristic related to an artificial bandwidth limitation processing of an audio signal comprises a slope evaluator configured for evaluating a slope of a spectrum
20 of the audio signal to obtain a slope evaluation result. The apparatus further comprises a processor for providing an information indicating that the audio signal comprises the predetermined characteristic dependent on an evaluation of the slope evaluation result. By basing the evaluation if the audio signal comprises a characteristic related to an artificial bandwidth limitation processing on the slope of the spectrum, e.g., a falling edge
25 of the spectrum, a precise detection of the artificial bandwidth limitation processing may be obtained whilst using a low computational effort.

According to another embodiment of the second aspect a method for determining a predetermined characteristic related to an artificial bandwidth limitation processing of an
30 audio signal comprises evaluating a slope of a spectrum of the audio signal to obtain a slope evaluation result. The method comprises providing an information indicating that the audio signal comprises the predetermined characteristic dependent on an evaluation of the slope evaluation result.

According to an embodiment of the second aspect a non-transitory storage medium has a stored there on a computer program having a program code for performing, when running on a computer, such a method.

- 5 Both, the first and second aspect allow for discriminating between audio signals or frames thereof being subjected to a respective processing and audio signals or frames thereof which have been un-subjected so as to avoid post-processing of un-subjected frames.

- 10 According to a third aspect the inventors have found that by performing a bandwidth extension for different portions having different signal characteristics of an audio signal differently, enhancement of the different portions and/or characteristics may be performed independently from each other so as to obtain a combined signal with a high quality comprising enhanced first portions and enhances second portions. Processing the different signal characteristics differently may allow for adapting the processing based on
15 the respective characteristics.

- According to an embodiment of the third aspect, an apparatus for processing an audio signal comprises a separator for separating a first portion of a spectrum of the audio signal from a second portion of the spectrum of the audio signal. The first portion has a
20 first signal characteristic and the second portion has a second signal characteristic. The apparatus comprises a first bandwidth extender for extending a bandwidth of the first portion using first parameters associated with the first signal characteristic, for obtaining a first extended portion. The apparatus comprises a second bandwidth extender for extending a bandwidth of the second portion using second parameters associated with the
25 second signal characteristic, for obtaining a second extended portion. The apparatus further comprises a combiner configured for using the first extended portion and the second extended portion for obtaining an extended combined audio signal. This may allow for enhancing the different portions having different signal characteristics independent from each other so as to obtain a combined audio signal with a high quality.

30

- According to another embodiment of the third aspect a method for processing an audio signal comprises separating a first portion of a spectrum of the audio signal from a second portion of the spectrum of the audio signal, the first portion having a first signal characteristic and the second portion having a second signal characteristic. The method
35 comprises extending a bandwidth of the first portion using first parameters associated with the first signal characteristic, for obtaining a first extended portion. The method comprises

extending a bandwidth of the second portion using a second parameter associated with the second signal characteristic, for obtaining a second extended portion. The method further comprises using the first extended portion and the second extended portion for obtaining an extended combined audio signal.

5

According to another embodiment of the third aspect a non-transitory storage medium has stored there on a computer program having a program code for performing, when running on a computer, such a method.

10 According to a fourth aspect, the inventors have found that by phase-shifting a portion of an audio signal with respect to a different portion of the audio signal, a perceived roughness may be reduced. In particular, a portion that might be generated or copied for extending the bandwidth may be phase-shifted when compared to an un-extended spectrum.

15

According to an embodiment of the fourth aspect an apparatus for processing an audio signal comprises an anti-roughness filter for phase-shifting at least a portion of the audio signal so as to obtain a phase-shifted signal. The apparatus comprises a high-pass filter configured for filtering the phase-shifted signals so as to obtain a first filtered signal. The
20 apparatus comprises a low-pass filter configured for a filtering the audio signal so as to obtain a second filtered signal. The apparatus comprises a combiner configured for combining the first filtered signal and the second filtered signal so as to obtain an enhanced audio signal. The apparatus allows for phase-shifting portions left by the high-pass filter when compared to portions left by the low-pass filter such that the first filtered
25 signal may comprise phase-shifted portions when compared to the audio signal, the second filtered signal respectively. This may allow for obtaining a low roughness in the combined signal.

According to another embodiment of the fourth aspect a method for processing an audio
30 signal comprises phase-shifting at least a portion of the audio signal so as to obtain a phase-shifted signal. The method comprises filtering the phase-shifted signals using a high-pass filter so as to obtain a first filtered signal. The method further comprises filtering the audio signal using a low-pass filter so as to obtain a second filtered signal. The method further comprises combining the first filtered signal and the second filtered signal
35 so as to obtain an enhanced audio signal.

According to another embodiment of the fourth aspect a non-transitory storage medium has stored there on a computer program having a program code for performing, when running on a computer, such a method.

5 Further embodiments of the present invention are defined in the dependent claims.

For a more complete understanding of the present disclosure, and the advantages therein, reference is now made to the following descriptions taking into conjunction with the accompanying drawings, in which:

10

Fig. 1 shows a schematic block diagram of an apparatus for determining a predetermined characteristic related to a spectral enhancement processing of an audio signal, according to an embodiment of the first aspect;

15

Fig. 2a shows a schematic graph illustrating an example spectrum according to an embodiment of the first aspect, that may be derived from an audio signal from which the spectrum of Fig. 1 may be obtained;

20

Fig. 2b shows a schematic example diagram of the local maximum signal over the same frequency abscissa as in Fig. 2a according to an embodiment of the first aspect;

25

Fig. 3 shows a schematic graph according to an embodiment of the first aspect for determining the similarity using a determination rule;

Fig. 4 shows an example of a post-processed similarity function according to an embodiment of the first aspect, illustrated as filtered value thereof;

30

Fig. 5 shows a schematic block diagram of an apparatus according to an embodiment of the first aspect comprising a frequency estimator;

Fig. 6a shows a schematic graphical representation of an example local similarity matrix according to an embodiment of the first aspect;

35

Fig. 6b shows a schematic diagram of a line of the matrix illustrated in Fig. 6a according to an embodiment of the first aspect;

- Fig. 7 shows a schematic block diagram of an apparatus according to an embodiment of the first aspect, comprising a spectrum calculator;
- 5 Fig. 8 shows a schematic flow chart of a method for determining a predetermined characteristic related to a spectral enhancement processing of an audio signal according to an embodiment of the first aspect;
- 10 Fig. 9 shows a schematic block diagram of an apparatus according to an embodiment of the second aspect;
- Fig. 10 shows a schematic diagram illustrating an example spectrum in connection with an embodiment of the second aspect;
- 15 Fig. 11 shows a schematic diagram of an example result of a spectral difference function according to an embodiment of the second aspect;
- Fig. 12a shows a schematic block diagram of an apparatus according to an embodiment of the second aspect, comprising an energy estimator;
- 20 Fig. 12b shows an example spectrum comprising a falling edge at a cut-off frequency according to an embodiment of the second aspect;
- 25 Fig. 12c shows a schematic block diagram of an apparatus configured for processing an audio signal which may be received from a decoder according to an embodiment of the second aspect;
- 30 Fig. 12d shows a schematic block diagram of a functionality of a processor for determining spectral weights according to an embodiment of the second aspect;
- Fig. 12e shows a schematic block diagram of a signal enhancer according to an embodiment of the second aspect, configured for reducing the Birdies artifact;

Fig. 12f shows a schematic flowchart of a method for processing an audio signal according to an embodiment of the second aspect;

5 Fig. 13a shows a schematic flow chart of a method for determining a predetermined characteristic related to an artificial bandwidth limitation processing of an audio signal, according to an embodiment of the second aspect;

10 Fig. 13b shows a schematic flow chart of a further method for determining a predetermined characteristic related to an artificial bandwidth limitation processing of an audio signal according to an embodiment of the second aspect, the method also evaluating a cut-off frequency;

15 Fig. 14 shows a schematic block diagram of an apparatus according to an embodiment of the third aspect;

Fig. 15 shows a schematic diagram illustrating an example spectrum comprising different components according to an embodiment of the third aspect;

20 Fig. 16 shows a schematic block diagram of an apparatus according to an embodiment of the third aspect;

Fig. 17a shows an example spectrum of a first portion of the audio signal, according to an embodiment of the third aspect;

25 Fig. 17b shows a schematic diagram of the first portion being extended by a number of two duplicated parts according to an embodiment of the third aspect;

30 Fig. 17c shows an example magnitude spectrum that may be obtained from an envelope shaper being configured for shaping at least the extended portions of Fig. 17b, according to an embodiment of the third aspect;

Fig. 18 shows a schematic block diagram of a spectral whitener being configured for whitening the audio signal according to an embodiment of the third aspect;

Fig. 19 shows a functionality of optional blocks being a signal analyzer and being a lookup table of the apparatus of Fig. 16, according to an embodiment of the third aspect;

5 Fig. 20 shows a schematic flowchart of a method according to an embodiment of the third aspect;

Fig. 21 shows a schematic diagram of an apparatus according to an embodiment of the fourth aspect;

10

Fig. 22 shows a schematic block diagram of an apparatus comprising a separator according to an embodiment of the fourth aspect; and

15 Fig. 23 shows a schematic flowchart of a method for processing an audio signal according to an embodiment of the third aspect.

Equal or equivalent elements or elements with equal or equivalent functionality are denoted in the following description by equal or equivalent reference numerals even if occurring in different figures.

20

It should also be noted that the embodiments described herein relate to digital signal processing. Therefore, all signals are band-limited to frequencies below half the sampling frequency due to the sampling. The (artificial) bandwidth limitation discussed herein refers to additional bandwidth limitation such that the bandwidth of the signal is smaller than the digital representation would allow.

25

The first aspect and the second aspect relate to identifying signal characteristics within an audio signal that indicate that the respective audio signal was subjected to a specific processing. By identifying the respective characteristic and parameters related thereto, appropriate actions and processing may be performed or executed so as to reduce or eliminate artifacts that might occur responsive to the processing. Therefore, reducing artifacts being possibly inserted into the processed audio signal may be understood as being related to the first aspect, the second aspect respectively.

30

35 The third and fourth aspects refer to post-processing audio signals. For post-processing audio signals so as to enhance an audio quality, information in connection with the

previously performed processing of the audio signal may be used, for example, information as derived according to the first and second aspect and/or may be used in connection with different audio signals.

5 Therefore, in the following, reference will be made first to the first and second aspect before referring to the third and fourth aspect. The scope of the first aspect is the improvement of the sound quality of audio signals, in particular of audio signals that have been coded using a lossy compression or other signal processing. Spectral Band Replication (SBR) is a method for parametric audio coding for synthesizing high-frequency
10 content of replicating parts of the audio signal spectrum from lower frequencies, typically guided by side information that is transmitted in the bitstream. The knowledge about the presence of SBR and the starting frequency at which SBR is in effect (or synonymic the cut-off frequency at which the signal has been bandlimited prior to SBR) is used or required for enhancing or improving the sound quality of audio signals. Embodiments
15 according to the first aspect provide an analysis concept for retrieving this information from an audio signal after it has been decoded without using the information in the bitstream. The described concept is able to detect SBR and other processings that copy parts of the spectrum at lower sub-band and paste them to higher frequencies. Another example except SBR for such a method is, based on the specific configuration, Intelligent
20 Gap Filling (IGF).

When compared to the method disclosed in US 9,117,440 B2, the embodiments according to the first aspect improve the robustness of the analysis with respect to modifications of the spectral envelope by analyzing and probably exclusively analyzing the
25 fine structure of the spectrum. In addition, it has less computational load, since the relationship is computed using summation of binary numbers instead of multiplication.

Fig. 1 shows a schematic block diagram of an apparatus 10 for determining a predetermined characteristic related to a spectral enhancement processing of an audio
30 signal 12, for example, a SBR, and/or an IGF. The apparatus 10 comprises a deriver 14 configured for obtaining a spectrum of the audio signal 12 and for deriving information related to a fine structure of the spectrum. The fine structure may relate to course of spectral lines within the spectrum. Such information may be represented, for example, using a local maximum signal indicating the local extrema, e.g., maxima and/or minima
35 within the spectrum. For example, the local maximum signal may have a predefined value such as a maximum value or a minimum value at a location of the local maximum and a

different value at other locations. For example, at the other locations, the local maximum signal may comprise a minimum value. Alternatively, the local maximum signal may comprise a minimum value at the local maximum and a maximum value elsewhere. Alternatively or in addition, the local maximum signal may represent both, the local
5 maxima and the local minima. Thereby, the fine structure of the spectrum may be maintained while attenuating or excluding other information. By way of non-limiting example only, embodiments described herein may refer to a local maximum signal being derived by the deriver 14.

10 For deriving the local maximum signal from the spectrum, the deriver 14 may either derive or compute or determine the spectrum from the audio signal 12. Alternatively, the deriver 14 may receive a signal containing information indicating the spectrum or the spectrum itself. Thus, the illustrated signal 12 may be a signal in the time domain or in the frequency domain. The spectrum being derived by the deriver 14 or received by the deriver 14 may
15 be, for example, a magnitude spectrum or a power spectrum. For deriving or computing such a spectrum, a short-term Fourier transform (STFT) or other suitable transforms may be used. By using the STFT, the audio signal 12 may be divided or separated in a number of suitable blocks and each block may be subjected to the STFT. This may allow to obtain a plurality of spectra of the audio signal, e.g., one spectrum for each block.

20 For example, sub-band signals may be computed using a filterbank. SBR is a processing where parts of the spectrum are replicated. The same is true for the harmonic transportation. In IGF some parts of the spectrum, for example, comprising a high-frequency range, are attenuated or set to 0 and afterwards refilled. When referring to
25 SBR, the spectral envelope may be modified whereas the fine structure of the spectrum may be maintained. Therefore, embodiments according to the first aspect propose a concept that is robust to modifications of the spectral envelope. For this purpose, the deriver 14 is configured to derive a local maximum signal from the spectrum. The local maximum signal may be defined as a vector of a specific length, e.g., according to the
30 frequency bins in the spectrum, whose elements are set to 1 at indices where the spectrum has a local maximum and set to 0 otherwise. It is to be mentioned that other rules may be applied. For example, additionally to the local maxima, local minima may be set to a specific value, e.g., 1. Alternatively or in addition, a different value, e.g., 0 or a value different from 1 may be used so as to indicate the local maxima and/or minima. This
35 processing may be similar to a whitening or flattening operation that maintains the fine structure and removes all other information. The local maximum signal may allow for

enhancing identification of similarities as the comparison may be implemented so as to focus on the structure of the compared segments.

Fig. 2a shows a schematic graph illustrating an example spectrum 16 that may be derived from the signal 12 or may be the signal 12. The abscissa illustrates the frequency index k wherein the ordinate illustrates a magnitude value $X(k)$ of the spectrum 16.

Fig. 2b shows a schematic example diagram of the local maximum signal Z over the same frequency abscissa k . At frequency bins k_1 to k_7 at which the spectrum 16 comprises local maxima 18₁ to 18₇, the local maximum function $Z(k)$ is set to a normalized maximum value such as 1 and set to a normalized minimum value such as 0 at other locations as well. The triangular shape in Fig. 2b may result from an interpolation between different frequency bins for a better understanding of the figures. The local maximum signal Z may comprise a same length as the spectrum $X(k)$. The deriver 14 may be configured for providing a signal 22 containing information indicating the local maximum signal $Z(k)$ being derived from the spectrum 16.

The apparatus 10 may comprise a determiner 24 configured for determining a similarity $C(\tau)$ between segments of the local maximum signal. For the detection of the spectral enhancement processing, the similarity between a first segment of the vector $Z(k)$, $k = k_0 \dots k_1$ and a second segment of the vector $Z(k + \tau)$ may be determined or computed by the deriver 24 as a function of the lag or shift τ . For example, the similarity $C(\tau)$ may be computed as the sum of the absolute values of the difference of the two vectors, i.e. the segments of the local maxima signal.

The segments to be compared may have the same length. The length depends on the frequency resolution at which the spectrum and the local maxima signal has been computed. The frequency resolution depends on the number of spectral coefficients that are computed. The number of coefficients for the spectrum and the local maxima signal are at least 16 or 16384 at maximum, but typically values between 256 and 4096 are chosen. The exact value may be selected depending on the sampling rate of the signal. The first segment may comprise elements of the local maxima signal vector that correspond, for example, to frequencies in the range between 2000 and 15000 Hz.

The parameter τ may vary from 1 to a maximum possible value in the signal, for example, representing the maximum frequency or a maximum search frequency, e.g., related to a cut-of frequency in the audio signal 12. This may be represented as a determination rule

$$C(\tau) = \sum_{k=k_0}^{k_1} |Z(k) - Z(k + \tau)|,$$

5

(1)

Fig. 3 shows a schematic graph according to an example that may be obtained wherein determining the similarity using the determination rule given above. An abscissa of the graph shows the lag or shift τ , wherein the ordinate shows a value of the similarity function $C(\tau)$.

By determining the similarity value $C(\tau)$ for a plurality of values of the parameter τ , the graph illustrated in Fig. 3 may be obtained. In regions 26₁ to 26₃ variations in the signal may be obtained being associated with values τ_1 , τ_2 , τ_3 respectively of the parameter τ . Those variations may comprise a local maximum and/or a local minimum within the similarity function $C(\tau)$. I.e., by shifting or applying a lag τ_1 , τ_2 , τ_3 , the similarity function may show a local maximum or minimum and therefore indicating that by shifting a respective segment by the lag τ_1 , τ_2 , τ_3 , a similar signal is obtained which may be an indicator for a spectral enhancement processing. In the example given above, the maximum lag τ is 20000 Hz.

The determiner may be configured for selecting at least one local maximum and/or local minimum from the similarity values and/or may select the values derived thereof for determining the similarity. In particular, the variations at the regions 26₁, 26₂ and 26₃ indicate a high similarity between the segments used at the shift indicated by the parameter τ_1 , τ_2 , τ_3 respectively.

Referring again to Fig. 1, the determiner 24 may be configured for providing an information or signal 28 indicating a result of the similarity, for example, values τ_1 , τ_2 , and/or τ_3 of the parameter τ or values is derived thereof. The apparatus 10 may comprise a processor 32 for providing an information 34 indicating that the audio signal 12 comprises the predetermined characteristic dependent on an evaluation of the similarity, for example, by evaluating the signal 28. Optionally, the obtained analysis function, i.e. the

similarity function, may be further processed, for example, by the determiner 24 and/or the processor 32. For example, a bandpass filtering may be executed to attenuate offset components in the similarity function and to increase the contrast of the local maxima of interest within the similarity function $C(\tau)$. The apparatus 10, e.g., the determiner 24 may
 5 comprise a filter configured for filtering the similarity values so as to obtain filtered similarity values illustrated in Fig. 4. The processor 32 may be configured to provide the information 34 so as to comprise information indicating at least one of that the audio signal was subjected to the spectral enhancement processing, a start frequency and/or an end frequency of the spectral enhancement processing.

10 Fig. 4 shows an example of a post-processed similarity function, illustrated as filtered value thereof, namely $H(C(\tau))$ on the ordinate over the abscissa showing the parameter τ . For example, a filter is implemented as an Finite Impulse Response (FIR) filter having filter coefficients $h = [-1 \ 2 \ -1]$. This means that the k -th output element of the filtered vector
 15 is computed by a linear combination of the elements at indices $k-1$, k , and $k+1$ weighted with $h(1)=-1$, $h(2) = 2$ and $h(3)=-1$. This may be represented based on the determination rule:

$$y(k) = h(1) x_{\{k-1\}} + h(2) x_{\{k\}} + h(3) x_{\{k+1\}}$$

20 The largest three local maxima at the parameter values τ_1 , τ_2 , and τ_3 are caused from the spectral enhancement processing, for example, the spectral band replication. For example, SBR processing may be detected, when a small number of local maxima with large magnitude appear in the function. A small number may refer to a number of at most
 25 15, at the most 10 or at the most 5 maxima. According to an embodiment, at most 13 local maxima are to be investigated to detect SBR according to common state-of-the-art configurations of SBR.

30 The large magnitude may refer to a value being at least 3 dB when compared to the regular signal, at least 5 dB or at least 6 dB. When referring again to Fig. 3, the local maxima in the regions 26_1 , 26_2 and 26_3 may refer to the signal beside the respective region as being noise. Such noise may be attenuated by the post-processing so as to enhance maximum determination as described in connection with Fig. 4. A large magnitude of the local maxima is defined as being larger than a threshold. The exact
 35 value of the threshold may be set, e.g., manually, to be in the range of 0.1 and 10,

depending on the number of values that have been used to computing the similarity function. Normally, a value of 5 may be used.

I.e., the processor 32 may be configured for evaluating a number of local maxima 26 of similarity values or values derived thereof and for evaluating an amplitude of the local maxima 26. The processor 32 may be configured for providing the information 34 indicating that the audio signal 12 comprises the predetermined characteristic when the number of maxima 26 that comprises at least an amplitude threshold value 27 is below a number threshold value, i.e., a number of local maxima exceeding the amplitude threshold 27 value is low enough.

In other words, Fig. 4 shows the similarity function of the post-processing. Local maxima are shown as a circle, the global maximum is highlighted by a cross. The determiner 24 may be configured for selecting the at least one local maximum from the filtered similarity values. Harmonic signals consist of one or more sinusoids with a fundamental frequency and their harmonics, i.e. partial tones whose frequencies are approximately integer multiples of a fundamental frequency. Therefore, one or more local maxima can appear in the similarity function such as an auto correlation function (ACF) To discriminate between local maxima corresponding to harmonic partial tones and SBR or other spectral enhancement processing, the search range may be set to appropriate values, being distinctly larger, for example, for SBR than for harmonic partial terms. Thus, the processor 32 may be configured for excluding harmonics of the audio signal from the evaluation of the similarity. This may be done by selecting those parts of the spectrum of the audio signal which are expected to have a low amount or even no harmonics.

Detecting the local maxima at the parameter values τ_1 , τ_2 , and τ_3 may be a sufficient indicator for the presence of the spectral enhancement processing. However, it may be of advantage to further estimate the start frequency of the spectral enhancement processing, for example, the SBR. The result of the similarity function or the local maximal may describe the shift at which a portion of the spectrum has been copied and pasted to. For completeness, the information about the start and stop frequency of the source sub-band spectrum or the destination sub-band spectrum may be of interest.

Fig. 5 shows a schematic block diagram of an apparatus 50 according to an embodiment. The apparatus 50 may be an extended version of the apparatus 10 and may further comprise a frequency estimator 36 configured for determining a start frequency and/or a

stop frequency of the spectral enhancement processing. The frequency estimator 36 may be configured for providing an information or a signal 38 comprising the respective information indicating the start frequency and/or the stop frequency. The frequency estimator 36 may be configured for using the local maximum signal $Z(k)$, e.g., by obtaining or receiving the signal 22, for determining an element similarity between an element of a first segment of the local maximum signal and a corresponding element of a second segment of the local maximum signal. The second segment may be shifted with respect to the first segment by a number of τ samples. This may be referred to as a local similarity analysis (LSA). The input may be the representation of the fine structure of the magnitude spectrum, e.g. the local maximum signal $Z(k)$. The frequency estimator 36, when executing LSA, may operate in the element-wise similarity between the k -th element in the first vector $Z(k)$ and the element at position $k+\tau$, $Z(k+\tau)$. To this end, the local similarity matrix may be computed as absolute value of the difference of the two binary numbers $Z(k)$ and $Z(k+\tau)$ according to the determination rule

$$L(k, \tau) = |Z(k) - Z(k + \tau)| \quad (2)$$

The value $L(k, \tau)$ of the local similarity matrix may then be processed by recursive averaging over time. This may be performed according to the determination rule.

$$L(k, \tau) = bL(k, \tau) + (1 - b)B(k, \tau), \quad (3)$$

where $B(k, \tau)$ denotes a buffer that stores the output of the recursive averaging from the preceding time step (frame) of the audio signal and $0 < b < 1$ is a time constant that controls the temporal averaging. Thus, the frequency estimator 36 may be configured for subjecting the element similarity of a plurality of elements for the first and second segments to a recursive averaging over time so as to obtain an averaged element similarity and for determining the start frequency and/or the end frequency using the averaged element similarity. The temporal averaging may optionally be only applied when the current frame is not silent, i.e., its energy is larger than a threshold 27 characterizing a silent frame from a non-silent frame.

A frame may be determined as being silent if its energy is smaller than a threshold, where the exact value of the threshold may be set dependent on the length of the frame and the range in which the sample values are represented. In general such threshold may be selected such that it equals the energy of a pink noise signal that is scaled to be just
 5 audible when played back with a typical sound reproduction equipment (a mobile phone or a TV set) at an average to high volume setting.

I.e., the frequency estimator may be configured for subjecting the element similarity of a plurality of elements of the first and second segments to a recursive averaging over time
 10 so as to obtain an averaged element similarity and for determining the start frequency and/or the end frequency using the averaged similarity. Each sample of the spectrum may be associated with a frame. The frequency estimator may be configured to exclude frames from the recursive averaging over time having a spectral energy below an energy threshold level 27, the energy threshold level 27 being related to a considering if the frame
 15 or spectrum is silent or not. Thereby, inconsistent results may be avoided by excluding frames being considered to be silent as those frames may also be considered to be un-subjected to audio processing.

As described in connection with Fig. 4, the result of the recursive averaging $L(k, \tau)$ may be
 20 processed by the band-pass filtering to attenuate the offset component and to increase the contrast of the local maxima of interest, e.g., by convolving each row of the matrix with a kernel such as $h = [-1 \ 2 \ -1]$.

Fig. 6a shows a schematic graphical representation of an example local similarity matrix
 25 $L(k, \tau)$, wherein an abscissa illustrates the frequency bins (positions) k and the ordinate represents the lag τ . For a better visibility, the absolute values of the matrix L are shown. The unit for the position k and lag τ are frequency bins. By non-limiting sample, one frequency bin may have a value of 46,9 Hz, wherein any other smaller or larger value may be obtained. Thus, Fig. 4 shows an example for a post-processed similarity matrix $L(k, \tau)$
 30 containing the following information:

The global similarity as described in connection with Fig. 4 can be obtained from $L(k, \tau)$ by summing along the x -axis (parameter k) and taking the absolute value of the result. Three horizontal lines 38₁, 38₂ and 38₃ in the given example correspond to the local maxima of
 35 Fig. 4. The lines 38₁, 38₂ and 38₃ may correspond to lines along which the respective value of the function $L(k, \tau)$, i.e., the sum of values, exceeds a certain threshold value, for

example, 0.1, 0.2, or 0.3 of the value range ranging from 0-1. The start position and the end position of the horizontal lines correspond to the start frequency k_{s1} , k_{s2} , k_{s3} respectively and end frequency k_{e1} , k_{e2} , k_{e3} respectively of repeated parts of the spectrum.

5

Fig. 6b shows a schematic diagram of a line of the matrix illustrated in Fig. 6a at the parameter τ_2 . In Fig. 6b, a graph 42a shows, for example, unfiltered values, wherein a graph 42b may show averaged or filtered values. For example, the graph 42b is compared to a threshold value 27 being, for example, 0.2. A range in which the local similarity matrix $L(k, \tau)$, their averaged value respectively, exceeds the threshold value 27, corresponds to the horizontal line 38₂ at index τ_2 . Alternatively or in addition, a steepness ($\Delta L(k, \tau)/k$) of the local similarity matrix may be evaluated. A steep rising edge rising with a certain value, e.g., at least 0.5, at least 1 or at least 1.5 may be identified as an edge identifying the start frequency k_{s2} . Accordingly, a respective steep and high falling edge may identify the end frequency k_{e2} . Alternatively or in addition, a temporal averaging may be executed on the input spectrum, the input spectral respectively and on the final result or results. This may allow for preventing false positive detections using the temporal averaging. A temporal averaging of the input spectral may be referred to as a pre-processing, wherein a temporal averaging of the final result may be referred to as a post-processing. A reason for preventing false positive detections is that the local maxima are typically time-variant due to partial tones. I.e., because different musical tones are played in a melody or because of harmonic changes in the music, the local maxima may vary over time. In contrast hereto, some parameters of spectral enhancement processing such as SBR may be a technical process which is typically time-invariant, e.g., an edge frequency from which the spectrum is enlarged, e.g., a cut-off frequency of a filtering performed previously, or the start and end frequencies of the frequency range that is replicated.

10

15

20

25

According to an example, for estimating the start frequency, the LSA matrix L is analyzed to identify the start position and end position of each horizontal line. The start position k_s may correspond to the start of the spectrum that has been replicated. The end position k_e may correspond to the end of the spectrum that has been replicated. The largest end position of the original spectrum that has been used for replication is the estimated value for the start frequency at which the SBR is effective. This may be, for example, k_{e3} in Fig. 6a.

35

First, the global similarity may be computed as

$$C(\tau) = \sum_{k=v_1}^{v_2} L(k, \tau), \quad (4)$$

Where v_1 and v_2 are parameters that determine a range of values $L(k, \tau)$ and may be
 5 selected, for example, so as to define the range of $L(k, \tau)$ having a value within a range of
 at least 500 Hz and at most 15 kHz.

Then, local maxima m_i , i.e., 26 in $C(\tau)$ are detected that are larger than a threshold, see,
 for example, Fig. 4. For each local maxima, the corresponding rows in $L(k, \tau)$ are
 10 analyzed. For example, the second local maximum m_2 indexes the row $R_2 = L(k, \tau_2)$ and
 is shown in Fig. 6b. For this local maximum a value of $\tau = 133$ may be valid and may start
 from $k = 74$ in accordance with Fig. 5.

The start index k_s and the end index k_e may be computed by first smoothing the
 15 respective lines R_i so as to obtain, for example, the graph 42b, e.g., by computing a
 temporal or moving average of a few adjacent values, for example, at least 3, at least 5 or
 at least 10. Then, the positions at which the smoothed line has the steepest increasing
 and decreasing slopes are detected. Alternatively or in addition, the slope exceeding a
 threshold value such as, for example, 0.2 may be a criteria for evaluating the respective
 20 line. I.e., the frequency estimator 36 may be configured for subjecting the element
 similarity of a plurality of elements of the first and second segments to a recursive
 averaging over time so as to obtain an averaged element similarity 42b and for
 determining the start frequency and/or the end frequency using the average element
 similarity 42b. Alternatively or in addition, the apparatus may be configured for performing
 25 a temporal averaging of the spectrum, of the local maximum signal or a signal derived
 thereof, wherein the processor may be configured for providing the information indicating
 that the audio signal comprises the predetermined characteristic based on a temporal
 average information of the spectrum, the local maximum signal or a signal derived thereof.

30 Referring again to Fig. 6a, there are three prominent horizontal lines 38₁, 38₂ and 38₃ for
 the given examples at indices τ_1 , τ_2 and τ_3 . The line at index τ_2 may correspond to the
 first part of the spectrum that has been replicated as showing the earliest beginning, i.e.,
 the lowest parameters k_s . The horizontal line starts at index k_{s1} and may correspond to

the lag τ_2 . Therefore, the first replicated part of the spectrum starts k_{s2} and has been copied to the index $k_{s2} + \tau_2$. By a non-limiting example, τ_1 may be 104, τ_2 may be 133 and τ_3 may be 236. k_{s2} may comprise, for example, a value of 74. Therefore, the first replicated part of the spectrum starts at index 74 and may have been copied to the index
5 74 + 133. This index therefore corresponds to the frequency at which the spectral enhancement processing (SBR) is in effect.

The frequency estimator 36 described in connection with Fig. 5 may be configured for computing the local similarity matrix or a different local similarity description. By non-
10 limiting example only, a vector or other row of values having a predetermined structure such as each row being attached to a previous row may allow for a same information. The frequency estimator 36 may determine a the local similarity description (local similarity matrix L) and may be configured for determine portions therein, e.g., lines, that indicate the bandwidth extension processing. For determining the portions indicating the
15 bandwidth extension processing, a steepness of the signal within the local similarity description and/or reaching or exceeding of the threshold value 27 may be evaluated by the frequency estimator 36.

Although having been described as evaluating rows, it is clear that the local similarity
20 matrix L may comprise a different structure, e.g., having switched rows to columns and vice versa or the like. The frequency estimator may thus be configured for determining the local similarity matrix L as the local similarity description and for determining the start frequency k_s and/or the end k_e frequency of the spectral enhancement processing using a steepness between values (e.g., adjacent values within a row or column) in rows or
25 columns and/or using an evaluation of values in the rows or columns at least reaching or even exceeding the threshold value 27.

Fig. 7 shows a schematic block diagram of an apparatus 70 extending the apparatus 10. Although being explained as extending the apparatus 10, the explanation given in
30 connection with Fig. 7 may also be used to extend the apparatus 50. The apparatus 70 may comprise a spectrum calculator 44 configured for receiving the audio signal 12 as a signal in the time domain and configured for calculating the spectrum from the audio signal 12 and to provide a signal 12' comprising the spectrum. Based thereon, the deriver 14 may be configured for receiving the spectrum 12'. Alternatively, the deriver 14 may be
35 configured to derive the spectrum 12' on its own.

The determiner 14 may comprise a filter 46 configured for filtering the similarity values so as to obtain filtered similarity values as described in connection with Figs. 3 and 4. The determiner 14 may be configured for selecting the at least one local maximum from the filtered similarity values for further consideration, for example, as row index in the similarity matrix $L(k, \tau)$. I.e., selection of a local maximum from the similarity values or values derived thereof may refer to a further use thereof for determining a start frequency and/or an end frequency of the spectral enhancement processing.

The apparatus 70 may comprise a signal enhancer 48 configured for receiving the audio signal 12 and receiving the information that the spectral enhancement processing has been performed, for example, by receiving the information 34. The signal enhancer is configured for reducing artifacts caused by the spectral enhancement processing of the audio signal using the information 34, i.e., dependent on the information indicating that the audio signal comprises the predetermined characteristic and optionally comprising further details such as the start frequency and/or the stop frequency of a replication process.

Fig. 8 shows a schematic flow chart of a method 1000 for determining a predetermined characteristic related to a spectral enhancement processing of an audio signal. The method 1000 comprises a step 1100 in which a spectrum of the audio signal is obtained and information related to a fine structure of the spectrum is derived, e.g., the local maximum signal. A step 1200 comprises determining a similarity in the fine structure between segments of the local maximum signal. A step 1300 comprises providing an information indicating that the audio signal comprises the predetermined characteristic dependent on an evaluation of the similarity.

In the following, reference will be made to the second aspect. According to the second aspect, it is in the scope to improve the sound quality of audio signals, in particular of audio signals that have been coded using lossy compression. The described concept is related to the bandwidth of audio signal which is in digital signal processing applications limited. The concept proposes a signal analysis concept detecting the presences of (artificial) bandwidth reduction (BR) and for estimating the cut-off frequency at which BL has been in operation. The obtained results are used to control subsequent processing for restoring the bandwidth by means of bandwidth extension (BWE) and also for controlling the improvement of the sound quality by other means such as filtering.

For the enhancement of the sound quality it of crucial importance to discriminate between a signal having originally a low bandwidth (e.g., a low note played on the basin) and a signal that has been band limited by means of a signal processing, e.g., due to lossy encoding or down sampling. Such discrimination is not possible by analyzing the signal "to
5 find the highest frequency present in the signal", i.e., by determining the frequency above which only negligible energy is present as described in [1]. In contrast, the second aspect proposes to evaluate additional information as described in the following.

The aim of the proposed artificial bandwidth limitation analysis (ABLA) is two-fold:

10

1). To detect the presence of bandwidth reduction (BR) in the input signal that is likely to be caused by lossy compression or other signal processing and therefore considered as an artifact. The output may be, for example, a binary variable, here referred to as D where $D = 1$ if BL has been detected and 0 otherwise.

15

2). To estimate the cut-off frequency of the bandwidth limitation. The estimated quantity is referred to f_c .

20

Fig. 9 shows a schematic block diagram of an apparatus according to an embodiment of the second aspect. The apparatus may be used for determining a predetermined characteristic related to an artificial bandwidth limitation processing of an audio signal. The apparatus 90 comprises a slope evaluator 52 configured for evaluating a slope of a spectrum of the audio signal 12, for example, the spectrum 12'. The slope evaluator 52 may be configured for providing a slope evaluation result 56. The slope evaluation result
25 56 may comprise information about a maximum, minimum or average value of the slope (envelope curve) of at least a part of the spectrum, about rising or falling edges within the spectrum or the slope thereof or other information relating to the slope 54.

30

The apparatus 90 may optionally further comprise a frequency evaluator 58 configured for evaluating a cut-off frequency f_c of the spectrum 12' of the audio signal to obtain a frequency evaluation result 62 comprising information indicating the cut-off frequency f_c .

35

The apparatus 90 comprises a processor 64 for providing an information indicating that the audio signal comprises the predetermined characteristic related to the artificial bandwidth limitation processing. The processor is configured for using the slope evaluation result for providing the information indicating that the audio signal comprises

the predetermined characteristic, i.e., the processor may provide the information dependent on the slope evaluation result. For example, this may allow for a decision whether the audio signal requires post-processing, e.g., in terms of a yes/no information or a binary decision. This may allow for excluding such frames from post-processing that are evaluated as not comprising the respective characteristic. Those frames may be identified as being unsubjected to artificial bandwidth limitation and therefore, post-processing has to be avoided. As an option, the apparatus may comprise the frequency evaluator 58 for determining the cut-off frequency. This may allow for identifying further information being used or required for post-processing, e.g., of subjected frames. Thus, optionally, the processor may be configured for providing the information indicating that the audio signal comprises the predetermined characteristic dependent on an evaluation of the slope evaluation result 56 and the frequency evaluation result 62. By evaluating the slope evaluation result 56 and the frequency evaluation result 62 for the spectrum 12' and/or for further frames of the audio signal resulting in further spectra 12', the processor 64 may derive information if the audio signal from which the spectrum 12' is derived was subjected to the artificial bandwidth limitation. For example, the slope evaluator 52 may be configured for evaluating the slope for an attenuation within the spectrum. The spectrum may be quantified or evaluated with respect to a steepness of the slope, i.e., as indicated by a roll-off factor.

By way of example, the slope evaluator 52 may be configured for evaluating an attenuation within the spectrum 12' and for providing the slope evaluation result 56 so as to indicate a measure for the attenuation. The processor 64 may be configured providing the information 66 indicating that the audio signal comprises the predetermined characteristic if the measure for the attenuation is at least a steepness threshold value. Optionally, the apparatus may comprise a resampling evaluator, for example, being a part of the processor 64 or being implemented separately. The resampling evaluator may be configured for evaluating the audio signal for a predetermined characteristic related to an up sampling. Up sampling may be implemented by using a sampling frequency, for example, a common sampling rate may be 11,025 Hz, 22,050 Hz and/or 32,000 Hz. The apparatus 90 and/or 120 may be configured to adapt frequency ranges of the slope evaluator 52 and/or of the frequency evaluator 58 based on the sampling frequency in a case where resampling is detected. By using resampling, the frequency range of the spectrum may be adapted or increased, wherein a low sampling rate may correspond to a low frequency range and a high sampling rate may allow the spectrum to contain high frequency ranges according to the Nyquist criterion. The resampling evaluator may be

configured for observing or evaluating a specific set of expected sampling rates and may evaluate, if at this frequency there is a significant decrease in the spectrum and if there is no more significant energy above. In such a case, where a steep edge in the slope as described before and an absence of significant energy above an energy threshold value is present, the energy evaluator may consider the audio signal as being resampled using the respective resampling frequency or sampling rate. The resampling evaluator may be configured for obtaining a negative evaluation result when at the determined or evaluated frequency corresponding to the sampling rate the determination rule

$$X(k) > threshold$$

applies, meaning that a value of the spectrum at the frequency k is larger than a threshold indicating that at the point k there is significant energy within the spectrum. Further the determination rule

$$X(k) < X(k + 1) - offset\ parameter$$

may apply, indicating that with increasing frequency $k + 1$ the spectrum, the energy thereof respectively, increases. This consideration may be normalized by subtracting the offset parameter, for example, 0.1, 0.2, 0.3, 0.5 or 1 dB or a different value, i.e., the spectrum has to increase more than the offset parameter for fulfilling the determination rule. This allows excluding effects caused by noise or the like. Thus, the magnitude does increase towards higher frequencies at frequency point k above a bandwidth limitation more than 0.5 dB. The threshold may be, for example, -30 dB, -40 dB, -50 dB, or -60 dB as explained above. This means, that for a negative decision there is either no steep attenuation or beyond the respective frequency value there is an increased magnitude.

A positive evaluation result indicating that the audio signal was subjected to an up sampling limiting the bandwidth at frequency index k may be determined, for example, when the spectral difference function $s(k)$ or a different suitable function as described above delivers a value exceeding or being at least a threshold value. Thus, the determination rule may apply that

$$S(k) > threshold$$

the spectral difference function may indicate a steep and strong attenuation and may therefore indicate a resampling. Therefore, when the maximum 72 in Fig. 11 is arranged at or near to an expected resampling rate/resampling frequency, the presence of a resampling may be determined.

5

Further, the attenuation may be evaluated with respect to an amount, i.e., a half of the falling edge within the spectrum. For example, the slope evaluator 52 may evaluate the slope 54 with respect to a decrease within a specific frequency range of, for example, 100 Hz, 1 kHz or 2 kHz and/or for a total amount of the decrease within the falling edge.

10

The processor 64 may be configured for deciding, if the spectrum 12' was subjected to the artificial bandwidth limitation and may further be configured for deciding at which cut-off frequency f_c said limitation was applied. Thus, the information 66 may comprise the variable D or a similar information and may further comprise information indicating the cut-off frequency, at least, when the processor 64 determines the spectrum 12' as being applied to the artificial bandwidth limitation processing.

15

Fig. 10 shows a schematic diagram illustrating an example spectrum 12' having the slope 54. The slope evaluator 52 may be configured for evaluating the slope 54 with respect to a steepness of the spectrum 12', of a falling edge 68 respectively. The slope evaluator 52 may be configured for providing the slope evaluation result 56 so as to comprise information indicating a measure for the steepness. The measure for the steepness may be obtained, for example, by linking a decrease ΔX_1 of the magnitude $X(f)$ and a frequency range Δf , for example, as the decrease ΔX_1 per frequency range Δf or in terms of a frequency range Δf used for obtaining the decrease ΔX_1 .

20

25

The processor 64 may be configured for providing the information indicating that the audio signal comprises the predetermined characteristic if the measure for the steepness is at least a steepness threshold value. The measure for the steepness may increase for rising values of the term $\Delta X_1/\Delta f$ and/or may increase for decreasing values of the term $\Delta f/\Delta X_1$. For example, the steepness threshold value may comprise a value of being equal or proportional to at least 25 dB/1 kHz, 30 dB/1 kHz, 40 dB/1 kHz or 50 dB/1 kHz or higher.

30

The slope evaluator 52 may be configured for determining a spectral difference function of the spectrum 12', for example, using a window function which only selects a part of the spectrum 12' for an evaluation. The window function may combine a plurality of frequency

35

values of the spectrum 12', the slope 54 respectively and may allow the slope evaluator 52 to determine the measure for the attenuation using results of the window function. This may also be referred to as a window filtering. By combining, e.g., subtracting, values of different windows, a measure for the steepness may be obtained. Alternatively, any other
 5 suitable process may be used to evaluate the steepness of the slope 54. Alternatively or in addition, the frequency evaluator may be configured for evaluating an attenuation between a first energy level of a first frequency band of the spectrum 12' and second energy level of a second energy band of the spectrum.

10 The first and second energy band may be, for example, a so-called low frequency band and a so-called high frequency band. The high-frequency band may be the frequency band which is expected to be silent after being low-pass filtered, for example, frequencies above 3 KHz. The low-frequency region may refer to a frequency region having frequencies below such a frequency range. Thus, the first energy band may comprise a
 15 first frequency range f_1 being low when compared to a second frequency range f_2 of the second frequency band. The slope evaluator 52 may be configured for providing the slope evaluation result 56 so as to indicate a measure for the attenuation ΔX_2 . The processor 64 may be configured for providing the information 66 if the measure for the attenuation is at least an attenuation threshold value. The attenuation threshold value may be, for
 20 example, at least 30 dB, at least 40 dB, at least 50 dB or at least 60 dB or even higher.

In other words, the attenuation may be considered as being high such that only negligible energy remains after the filtering in the high frequency band. E.g., the magnitude in the upper frequency region f_2 is below -60 dB (attenuation threshold value) smaller than the
 25 average magnitude in the pass band, i.e., the frequency region f_1 . A combination of the evaluation of the steepness of the spectrum and the evaluation of the amount of the attenuation may allow for determining that the current frame of the spectrum 12' was subjected to the artificial bandwidth limitation. Thus, if at least one or preferably both evaluations give a hint for such a processing, the variable D may be set to 1. If at least
 30 one or preferably both of the evaluation criteria are evaluated negatively, the variable D may be set to 0, i.e., it may be determined that no artificial bandwidth limitation has been applied.

In other words, the steepness of the attenuation may be quantified by comparing the
 35 spectral magnitudes in a lower sub-band f_1 and the spectral magnitudes in a higher sub-band f_2 around a frequency index k and repeating this for all frequency indices in the

range of interest. An example is the spectral difference function $S(k)$ that may be formed according to:

$$S(k) = \max X_1 - \max X_2$$

- 5 The spectral difference function $S(k)$ may quantify the attenuation as the difference of the maximum magnitude of the lower and the maximum magnitude of the higher sub-band. The parameter k may refer to a frequency index. $X(k)$ may denote a magnitude spectrum. The operation $\max$ may return the maximum value of a vector, wherein $X_1 = (x_{k-a}, \dots, x_{k-b})$ may denote a segment of the spectrum below frequency index k and
- 10 $x_2 = (x_{k+b}, \dots, x_{k+a})$ may refer to a segment of the spectrum above the frequency index k , wherein $a > b$. A length of the vector, i.e., a number of samples to be used in the vectors X_1 and/or X_2 may be, for example, 3, 5, 8, or 10 or even more. In one non-limiting embodiment, a first segment of length 7 and a second segment of length 7 is used in connection with a gap of 5 values between both segments. Accordingly, the maximum of
- 15 elements 1, 2, 3, 4, 5, 6, 7 is determined and compared to the maximum of element 13, 14, 15, 16, 17, 18, 19.

Alternatively, other functions may be used, for example, $S_2(k) = \min X_1 - \max X_2$ or a difference determined from means values of X_1 and X_2 .

20

- The frequency evaluator 58 may be configured for determining a measure for energy in a frequency band of the audio signal and for determining the cut-off frequency f_c based on the energy. For example, the frequency evaluator may evaluate energy in frequency bands with decreasing frequency values, i.e., within decreasing frequency ranges. When
- 25 referring to Fig. 10 to the upper most frequency illustrated, the frequency evaluator may, for example, determine a low amount of energy in the frequency range f_2 . While evaluating comparatively small frequency ranges of several bins or even comprising only one frequency bin, the frequency evaluator 58 may determine with decreasing frequency f and increase in the energy as indicated, the slope 54. At the cut-off frequency f_c the
- 30 frequency evaluator 58 may determine a strong increase in the energy, for example, at least 30 dB, 40 dB, 50 dB or even 60 dB when compared to the low energy level in the frequency range f_2 . Based thereon, i.e., based on the increase of energy in the frequency range, the frequency evaluator 58 may determine the cut-off frequency f_c . This may be also referred to as determining the cut-off frequency f_c as the frequency at which the sub-
- 35 band energy increases.

Fig. 11 shows a schematic diagram of an example result of the spectral difference function $S(k)$. The originate shows a result of the spectral difference function $S(k)$, wherein the abscissa shows the same frequency axis as illustrated in Fig. 10. The spectral difference function may allow for obtaining a measure for the steepness of the slope 54. A local or even global maximum 72 of the spectral difference function $S(k)$ may indicate a frequency at which the slope 54 comprises a most steep variation, i.e., where the attenuation is very steep. Therefore, this measure may alternatively or in addition be used by the frequency evaluator as a measure for the cut-off frequency f_c .

The decrease of the slope 54, and therefore the attenuation may range along the large number of samples such that the difference using a maximum value of the respective vector may provide for a sufficient accuracy. Alternatively, the spectral difference function may be determined for single frequency values, i.e., the vectors X_1 and X_2 may have a length of 1.

For enhancement of the sound quality it is of crucial importance to discriminate between a signal having originally a low bandwidth, (e.g., a low note played on the basin) and a signal that has been bandlimited by means of a signal processing, e.g., due to lossy encoding or down sampling. This is important to prevent a signal having high sound quality from any post-processing and to apply an enhancement processing only when needed, i.e., to apply subsequent bandwidth extension (BWE) only for restoring high frequency energy that has been artificially removed from the signal and not to process signals having a low bandwidth by nature. For such a purpose, the signal may be analyzed with respect to three characteristics given by the steepness of the attenuation, the amount of attenuation and the cut-off frequency. This may be performed by the following processing steps executed, for example, by an apparatus according to the second aspect.

Fig. 12a shows a schematic block diagram of an apparatus 120 according to an embodiment of the second aspect. When compared to the apparatus 90, the apparatus 120 is configured for determining the predetermined characteristic for a plurality of spectrums $12'_1$ to $12'_3$ which may be derived from a number of blocks of the audio signal. I.e., the audio signal may be divided into blocks and from each block a spectrum $12'$ may be derived. The slope evaluator 52 is configured for evaluating the slope 54 of each of the

spectrums $12_1'$ to $12_3'$. In accordance herewith, the frequency evaluator 58 is configured for evaluating each of the spectrums $12_1'$ to $12_3'$.

The processor 64 may be configured for providing the information 66 indicating that the audio signal comprises the predetermined characteristic for each of the spectrums $12_1'$ to $12_3'$. A number of blocks into which the audio signal is divided may be arbitrary. For example, a length of each block in time may be constant such that the number of blocks may be dependent on the length of the audio signal.

The apparatus 120 may comprise a filter 74 connected with the frequency evaluator 58 and configured for receiving the frequency evaluation result 62. The filter 74 may be configured for providing a filtered frequency evaluation result 62'. The processor may be configured for providing the information 66 indicating that the audio signal comprises the predetermined characteristic based on a plurality of slope evaluation results 56 for each of the spectrums $12_1'$ to $12_3'$ and/or a filtered version thereof and the filtered frequency evaluation result 62' associated with a plurality of spectrums $12_1'$ to $12_3'$ of the audio signal. The cut-off frequency used for encoding an audio signal may be essentially time-invariant, time-invariant or may be a parameter that varies rarely or infrequently over time such that a low-pass filtering, a moving maximum, a moving average or a moving median filtering implemented by the filter 74 may allow for obtaining the filtered values 62' remaining unchanged or constant or at least changing at low rates for further processing, for example, when the frequency evaluator 58 determines slightly different cut-off frequencies f_c between the different spectrums $12_1'$ to $12_3'$. I.e., a post-processing of the obtained values f_c may be performed by low-pass filtering or alternatively a different filtering.

In a similar way, artificial bandwidth limitation is usually performed for a complete audio signal or at least a large portion thereof such that it is unlikely that a change of the characteristic related to the artificial bandwidth limitation processing is present in one frame and not present or absent in a subsequent frame will occur. Therefore, the processor 64 may perform a post-processing of the variable D or a corresponding result or value, for example, using a median filtering or the like for a plurality of frames, i.e., for a plurality of spectrums $12_1'$ to $12_3'$. The processor may be configured for providing the information 66 indicating that the audio signal comprises the predetermined characteristic by providing a respective information for each of the plurality of frames of the audio signal and for providing a combined or filtered result 66' by combining the results of the frames

such that the combined result 66' is valid for the plurality of frames being subjected to the filter and influencing an output of the filter. For example, when using a median filtering, a number of frames and/or spectra 12₁' to 12₃' is considered within the respective filter, for example, a filter 76 connected to the processor 64 or being a part of the processor 64 or
5 being implemented by the processor 64. The output 66' of the filter 76 may be combined median-filtered value derived from the considered frames. Although being illustrated as a separate block, the filter 76 may be implemented or may be a part of another computing block.

10 Alternatively or in addition, the apparatus 120 may comprise a determiner 78 configured for determining an energy E of a frequency band of the spectrums 12₁' to 12₃' and for providing a signal 82 indicating a presence and/or an amount of the energy E within the respective frequency band. The signal 82 or a signal derived thereof may be provided to the processor 64 such that the processor 64 may have knowledge about the determined
15 energy. It may be of interest, if in a so-called high frequency region f_h energy is present or not. For example, a high-frequency region f_h may be a frequency region having a frequency values being at least or above 1 kHz, 2 kHz, 3 kHz, 4 kHz or a different value, i.e., different bandwidth limiting frequencies. For example, encoders may drop or discard frequencies above a certain frequency value. The frequency value may be in accordance
20 with a specific application such as 3 kHz or 4 kHz for speech-related applications.

The determiner 78 may determine, if the spectra 12₁' to 12₃' comprise energy or comprise energy above a certain threshold in the high-frequency region f_h . In a case where the determiner 78 determines that the respective spectrum 12₁' to 12₃' comprises no energy E
25 or a low amount thereof in the high-frequency region f_h , a reliable determination of the cut-off frequency and/or the attenuation may be difficult or even impossible, for example, because the respective frame does not provide for a suitable slope. When taking into account, by non-limiting example only, a silent spectrum having no energy in the complete spectrum, neither a cut-off frequency nor an attenuation of the slope 54 may be
30 determined. Such information may be provided by the signal 82. The processor may skip evaluating the actual frame or spectrum 12₁' to 12₃' and may be configured for providing the information 66 based on a previous spectrum observed or evaluated previously, if the energy E is below an energy threshold level which is considered to discriminate between relevant energy present or absent. Put into different terms, the processor may base its
35 decision on a previous frame in a case where the actual spectrum is unable to provide sufficient information.

- In an optional step, a partitioning of the audio signal/input signal into short blocks may be executed, i.e., a number of blocks may be obtained. A length of a block may be, for example, at least 0.5 ms, at least 1 ms or at least 5 ms and at most 1 second, 500 ms or 100 ms. One example interval comprises values of at least 2 ms and at most 80 ms.
- Optionally, computing a magnitude spectrum for each block, e.g., by means of a transform or a filter bank. Thus, the apparatus 19 may comprise, for example, a frequency deriver for deriving a spectrum such as a magnitude spectrum so as to provide the spectrum 12'. For each block a spectrum according or similar to the spectrum illustrated in Fig. 10 may be derived.
- Optionally, a low-pass filtering of spectral coefficients may be performed with respect to time and frequency. For example, a moving averaging or a recursive averaging may be performed, for example, by the slope evaluator 52 and/or the frequency evaluator 58 and/or a processor implementing both, the slope evaluator 52 and the frequency evaluator 58. This may allow for reducing computational loads as the attenuation and steepness of the attenuation as well as the cut-off frequency are arranged within a specific frequency range extended beyond single frequency values such that an evaluation of the frequency ranges may allow for a sufficient accuracy.
- Optionally, when the input signal is mute or does not contain energy in the high frequency region, a reliable estimate may be difficult to be obtained or may be impossible to be obtained. Therefore, the detection result of the previous frame may be used, if the maximum sub-band energy above 3 kHz is below a threshold because this frame does not contain the desired information.
- Optionally, detecting if the signal has been upsampled from a lower sampling frequency, for example, using the determiners 78. A coded signal at low bit rates is typically encoded with a low sampling frequency which can be lower than the sampling frequency at which the current processing framework operates. When up sampling or resampling after decoding has been detected, the search range of the artificial bandwidth limitation analysis (ABLA) according to the second aspect may be modified such that the highest frequency to be detected equals the encoder sampling frequency. For detecting a resampling, the detection of resampling may be carried out for a set of common sampling rates such as 11,025 Hz, 22,050 Hz, 32,000 Hz and/or 44,100 Hz. When the maximum magnitude of the spectral coefficients in a range above the half of the sampling frequency is below a

threshold, resampling may be detected. This is based on the Nyquist criterion allowing obtaining frequencies with half of the frequency value when compared to the sampling rate. Therefore, when the energy is below the threshold in the upper half, this may be caused by the used sampling rate. The following ABLA processing is then modified such that the search range is modified such that the highest frequency to be detected equals the detected encoder sampling frequency and thus allowing searching only a portion of the respective spectrum. The other portion, e.g., the upper half, may be neglected as being expected to be caused by the up sampling. The attenuation due to resampling may be larger than the attenuation of the encoding. The resampling detection may ensure that resampling is not mistakenly detected as bandwidth limitation at a lower cut-off frequency f_c .

- Computing a detection function, for example, the spectral difference function, that quantifies a steepness of the attenuation over frequency. The spectral difference function or an alternative version when compared to Fig. 11 may be used. The detection function may provide for information of a level difference between adjacent frequency bands.
- Detecting artificial bandwidth limitation (ABL) using a set of rules that evaluate the spectral difference function and the sub-band energy and a threshold parameter. Starting at the frequency index k of the upper end of the search range, the magnitude X of the spectral coefficients and the spectral difference function $S(k)$ or a similar function or quantity may be tested with respect to a set of conditions until a condition is valid or until the lower end of the search range has been reached. All the thresholds are parameters that can be adjusted to change the trade-off between false positive and false negative detections. The conditions:

1). $x(k) > threshold$; and

2). $X(k) < X(k + 1) - offset\ parameter\ AND\ x(k) greater\ threshold$,

i.e., the magnitude does increase towards higher frequencies above a BL more than the offset parameter, e.g., 0.5 dB, when the magnitudes are larger than the threshold, e.g., -60dB,

may lead to a negative detection. Conditions according to:

1). $S(k) > threshold$; and

2). Resampling has been detected

may lead to a positive detection.

- Determining the cut-off frequency f_c as the frequency at which the sub-band energy increases, for example using the frequency evaluator 58.
- 5 • Optionally, post-processing f_c by low-pass filtering, for example, using the filter 74.
- Optionally, post-processing D by median filtering, for example, by using the filter 76.

10 The apparatus 90 and/or the apparatus 120 may further comprise a signal enhancer, for example, the signal enhancer 48 being described in connection with the first aspect. The signal enhancer 48 may be configured for reducing artifacts caused by artificial bandwidth limitation processing of the audio signal dependent on the information 66 indicating that the audio signal comprises the predetermined characteristic. I.e., the signal enhancer may be adapted to artifacts being caused by the artificial bandwidth limitation.

15 In the following, reference will be made to an apparatus configured for suppressing or at least reducing the Birdies coding artifact and for improving the perceived sound quality in accordance with the second aspect. The respective apparatus or method may be used in a case when information has been derived that the audio signal
20 comprises a characteristic related to an artificial bandwidth limitation and/or to a spectral enhancement processing such as a spectral band replication. For example, the apparatus may be used in a case when at least one of artificial bandwidth limitation or spectral band replication has been detected.

25 Thus, when at least one of the artificial bandwidth limitation and the spectral enhancement processing is detected, the concept according to which the artificial bandwidth limitation is detected may be reused or may be used so as to detect steep and highly attenuated regions in the spectrum, which may be referred to as spectral gaps. A spectral gap may comprise a first and a second edge. Accordingly, a spectral
30 island may also comprise a first and a second edge, wherein between the respective edges the gap or the island may be arranged.

When referring now to Fig. 12b, there is shown an example spectrum comprising the falling edge 68 at the cut-off frequency f_c . Further, at frequency ranges below that cut-
35 off frequency f_c , an example spectral gap 202 and an example spectral islands 204 is arranged. When starting from low frequencies, first a falling edge 206₁ and afterwards

a rising edge 206₂ is arranged, wherein at frequency ranges therebetween, the spectral gap 202 may be arranged. Accordingly, the spectral island 204 may be arranged between edges 206₃ and 206₄. The edges may be located, quantified and qualified using the teachings disclosed herein for finding the edge 68, in particular, a
 5 frequency/energy evaluation may be performed.

In contrast to the cut-off frequency f_c , a location, a presence and a magnitude of the gap 202 and the island 204 as well as a number thereof may vary between frames of the audio signal. Simplified, the filling of the gap 202 and/or the attenuation of the
 10 island 204 may be performed after using a concept to find the edges 206₁ to 206₄, as was described in connection with the cut-off frequency f_c with the exception that the respective frequencies are variable. I.e., an apparatus or signal enhancer may be configured for filling a spectral gap and/or for attenuating a spectral island. Therefore, spectral weights may be used which may be determined from the audio signal itself,
 15 i.e., a side information may remain unrequired. By suppressing the Birdies coding artifact the perceived sound quality may be enhanced. The concept introduced may be used as a post-processing concept which is located after the decoder. It can work blindly without having access to the uncompressed audio signal and to other side information.

20

The concept which is described in the following so as to reduce the Birdies artifact may use a basic principle called spectral weighting or short-term spectral attenuation. Therefore, a time domain signal $X[n]$ may be transformed into its frequency domain representation $X[k,m]$, where k and m denote the frequency in timeframe index,
 25 respectively. In the embodiments described, the short-time Fourier transform (STFT) may be applied, but also other transforms may be used. The output signal Y of the spectral weighting may be given in the following equation:

$$Y[k,m] = G[k,m] \cdot X[k,m].$$

30

The time domain representation $Y[n]$ of the frequency domain signal $Y[n]$ may be computed by means of an inverse transform, in embodiments the inverse STFT. In the following, time domain signals will be denoted with small letters and frequency domain signals with capital letters. Indexes k and m or frequency domain signals will
 35 be omitted for better readability.

Fig. 12c shows a schematic block diagram of an apparatus 125 configured for processing an audio signal 91 which may be received from a decoder and which may have been subjected to artificial bandwidth limitation and/or spectral enhancing such as spectral band replication. The apparatus 125 comprises the slope evaluator 52 and the frequency evaluator 58. The slope evaluator 52 is configured for evaluating a slope of a spectrum of the audio signal 91 to obtain a slope result as described in connection with Fig. 9 and/or Fig. 12a. The frequency evaluator may be configured for evaluating at least a first and a second frequency at, for example the edges 206₁ and 206₂ and/or the edges 206₃ and/or 206₄ surrounding, bordering or fencing the respective artifact, i.e., the gap 202 and/or the spectral island 204.

The apparatus 125 comprises a processor 208 configured for determining a spectral weight G and/or W and for processing the audio signal 91 at least in a spectral region between the respective edges 206₁ and 206₂, 206₃ and 206₄ respectively, using the spectral weights G and/or W . The apparatus 125 may be configured for determining the spectral weights G and/or W for each of the frequency regions, frequency bins and/or frames of the audio signal 91. Spectral weights G may be used for forming or shaping a filling signal S to be combined with the audio signal so as to fill spectral gaps. Spectral weights W may be used so as to attenuate spectral islands. I.e., for reducing an artifact within the spectral gap 202, a fill signal F may be used. For reducing artifacts caused by the spectral island 204, spectral weights W may be used for attenuating a height of the island. For a plurality of frequency values within the respective spectral gap 202 and the respective spectral island 204, a plurality of spectral weights may be determined.

Fig. 12d shows a schematic block diagram of a functionality which may be implemented by the processor 208 for determining the spectral weights G . Spectral gaps may be defined as an abrupt decrease, i.e., at least 30dB, at least 40dB or at least 50dB of spectral magnitude areas in frequency and time domain/direction. The additional evaluation over time shows that spectral areas between harmonic of a tonal signal are not wrongly detected as spectral gaps. In [5] the detection method searches for perfect zeros in the spectral domain. This is only possible because the method is located in the decoder and has access to the same filterbank and blocking as the encoder. The described embodiments refer to a post-processing of the decoder which evaluate abrupt relative spectral changes using the difference of magnitude spectrum X and its smoothed copy of it. The signal flow for detecting both

spectral gaps and the spectral islands are illustrated in Fig. 12d. STFT or a different spectrum calculator 44 may be used for obtaining a spectral representation of the audio signal 91. An absolute value former 212 may be configured for outputting the magnitude spectrum X . A logarithm 214 is configured for transforming the magnitude spectrum X into the logarithmic domain, for using a logarithmic transformation such as

$$X' = 20 \log_{10}(X).$$

The obtained logarithmic magnitude spectrum X' may be smoothed by two low-pass filters in parallel, wherein a first low-pass filter 216a may be configured for smoothing the spectrum of the audio signal, i.e., the audio signal, in the frequency domain so as to obtain a signal Y' being smoothed in the frequency domain. A second low-pass filter 216b may be configured for smoothing the magnitude spectrum X' in the time domain so as to obtain a smooth signal Z' . Although being described as being smoothed in the logarithmic domain, the smoothing may also be performed in the linear domain or a different domain. I.e., the logarithm 214 may also be absent or may be arranged after the low-pass filters. I.e., the logarithmic magnitude spectrum X' may be smoothed by two low-pass filters, both over frequency and over time which may lead to the signals Y' and Z' , respectively. For the calculation of the special weights G , the linear values may be calculated by

$$Y = 10^{\frac{Y'}{20}}.$$

Those linear values may be compared with the magnitude spectrum X so as to obtain a frequency difference value and/or a time difference value. The relative differences Δ_t and Δ_f comparing the spectral magnitudes X to their smoothed versions over time Z' and frequency Y' may be calculated in the logarithmic domain, for example, for each spectral coefficient and for each frame by

$$\Delta_f = Y' - 20 \log_{10}(X)$$

and

$$\Delta_t = Z' - 20 \log_{10}(X)$$

wherein Δ_f refers to the frequency difference value and Δ_t refers to the time difference value.

- 5 The spectral weight calculator 218 may be configured for calculating the spectral weight G according to

$$G = \begin{cases} \Gamma & \text{if } (\Delta_f > \delta_f) \wedge (\Delta_t > \delta_t) \\ 0 & \text{otherwise} \end{cases}$$

- 10 i.e., the spectral weight G is set to a non-zero value if the frequency difference value Δ_f is greater than or equal to a frequency difference threshold Δ_f and if the time difference value Δ_t is greater than or equal to a time difference threshold value Δ_t . Although being described as requiring that the time difference values Δ_f and Δ_t are greater than their respective threshold values Δ_f , Δ_t respectively, based on other
15 threshold values or threshold values being chosen differently, the gain parameter may also be Γ when being equal to the threshold values. The following determination rule may apply:

$$\Gamma = \left(\frac{X^\alpha + \gamma(Y^\alpha - X^\alpha)}{Y^\alpha - \kappa} \right)^\beta$$

20

where Δ_f and Δ_t denote threshold parameters. α , β and γ are parameters which influence the characteristics of the spectral weight calculation. All parameters are tunable parameters. κ is a term which is used to increase the impact of the weighting and may be calculated according to the determination rule or based thereon:

25

$$\kappa = 10^{\frac{20 \log_{10}(X) + \delta_f}{20}}$$

The calculated spectral gains are smoothed over time and frequency, for example, using a low-pass filter 222a, 222b respectively. The spectral gains are subsequently used for a spectral weighting of a fill source signal S as being described in connection
30 with Fig. 12e.

Fig. 12e shows a schematic block diagram of a signal enhancer 200 configured for reducing the Birdies artifact. The processing may be done, for example, by use of the processor 208. The apparatus 200 may comprise a combiner 224 for combining a fill source signal S with the spectral weighting factors G , for example, by multiplication, so as to obtain the fill signal F . The fill signal F may comprise a structure according to which it only comprises non-zero values at locations where spectral gaps have been estimated. A further combiner 226 may be configured to combine the filler signal F with the magnitude spectrum X , for example, by a summation. I.e., the filling signal F is added to the input signal X . The fill source signal S may be obtained or generated by filtering the audio signal 91 in the time domain, which prolongs information from preceding frames. Alternatively, the filling source signal may be obtained by copying the spectral coefficients from other positions within one spectral frame, by copying spectral coefficients from another audio channel which does not exhibit a spectral gap at the responding location and/or by copying spectral coefficients from a preceding spectral frame which does not exhibit a spectral gap.

In known concepts, for example noise substitution from the Perceptual Noise Substitution (PNS) tool of the Advanced Audio Coding (AAC) are used. Noise like portions of the spectrum are substituted in the decoder by a pseudo random sequence of values scaled to match a given target energy. The process is controlled by side information. Further, a technique named noise-filling is known. Noise-filling is used in the Unified Speech and Audio Coding (USAC) codec to fill spectral holes caused by the dead-zone of the quantizer operating under constraints of a small bit budget. A pseudo-random sequence of values is used to fill these spectral zeroes. Further, a technique named Intelligent Gap Filling is known from MPEG-H and 3GPP EVS. Here, spectral gaps are filled with either noise or using spectral tiles sourced from a remote spectral location. The process is controlled by side information. The embodiments described herein differ from noise filling such that there is used a distribution of time frequency information from preceding time frames to fill spectral holes. In contrast to PNS, the filtered output signal is only filled into spectral gaps rather than entire PNS bands. In contrast to PNS and IGF (Intelligent Gap Filling) the embodiments may be used as processing non-guided, i.e., without using side information.

The apparatus 200 may comprise a spectral island weight calculator 228 which may also be implemented by the processor 208. Spectral islands contained in the signal Z

being received from the combiner 226 and being obtained by adding input spectrum X and fill signal F according to

$$Z = X + F$$

5

may be suppressed by means of spectral weighting according to

$$Y = W \cdot Z$$

- 10 As G , W are spectral weights which are recalculated for each frame m and spectral coefficient k . In order to preserve as much bandwidth as possible, the suppression of spectral islands is done after spectral gaps have been filled. Only isolated spectral islands which could not be attached to the main part of the spectrum are finally suppressed. To achieve a partial enhancement, the spectral island suppression may
15 be performed without the spectral gap filling. Alternatively, the spectral gap filling may be performed without the spectral weight calculation.

For suppressing the spectral weight calculation and for calculating the spectral weight W , the following teaching may be implemented. Spectral islands may be defined as
20 abrupt increase of spectral magnitude areas in frequency and time direction surrounded by very low spectral magnitude values. A rising of magnitudes may be, for example, at least 30dB, at least 40dB or at least 50dB. Spectral islands may be suppressed by attenuating the corresponding spectral coefficients by means of spectral weighting. For deriving the spectral weights W , a similar processing as
25 described in connection with Fig. 12d may be performed. As described for the spectral weights G , the time difference value and the frequency difference value Δ_f and Δ_t may be determined. The spectral weight W may be derived based on the determination rule:

$$W = \begin{cases} \Omega & \text{if } (\Delta_f > \delta_f) \wedge (\Delta_t > \delta_t) \wedge (Y < \delta_p) \\ 1 & \text{otherwise} \end{cases}$$

30

wherein

$$\Omega = \left(\frac{Y^\alpha + \gamma (X^\alpha - Y^\alpha)}{X^\alpha} \right)^\beta$$

Δ_p is a threshold which reflects the assumption that spectral islands are surrounded by spectral coefficients of low energy. Δ_f and Δ_t are threshold parameters. As
 5 described above, α , β and γ are tunable parameters. In consideration of the determination rule above, at ranges of the spectral island, the spectral weight Ω is determined allowing to attenuate the signal Z , Y , respectively, i.e., Ω is a value being lower than 1. In a range outside the spectral island, W is a value of 1, i.e., no attenuation is performed. The apparatus 200 may comprise a combiner 232 so as to
 10 combine the spectral weights W with the signal Z , for example, using a multiplication. A signal transformer 234 may be used so as to perform ISTFT, i.e., to obtain a time domain signal.

In other words, the Birdies suppression concept may be split into spectral gap filling
 15 and spectral island suppression. The fill signal F may be calculated by filtering a broadband fill source signal S with spectral weights G . F only contains non-zero values, where spectral gaps have been identified in X that is determined according to

$$F = G \cdot S$$

20 Fig. 12f shows a schematic flowchart of a method 1500 for processing an audio signal. The method 1500 comprises a step 1600 in which a slope of a spectrum of the audio signal is evaluated to obtain a slope relation result. A step 1700 comprises evaluating at least a first and a second frequency edge at which the spectrum
 25 comprises an edge so as to obtain a frequency evaluation result. A step 1800 comprises determining a spectral weight and processing the audio signal in a spectral region between the first and second frequency edge, using the spectral weight.

30 Fig. 13a shows a schematic flow chart of a method 2000 for determining a predetermined characteristic related to an artificial bandwidth limitation processing of an audio signal. The method 2000 comprises a step 2100 comprising evaluating a slope of a spectrum of the audio signal to obtain a slope evaluation result. A step 2200 comprises providing an information indicating that the audio signal comprises the predetermined characteristic

dependent on an evaluation of the slope evaluation result. The information 66 provided by the processor 64 may contain a variable referred to herein after as D that may be used to activate bandwidth extension processing that is applied to improve the sound quality of an audio signal, for example, using the signal enhancer. Optionally, the cut-off frequency f_c may be determined, i.e., an optional step may comprise evaluating a cut-off frequency of the spectrum of the audio signal to obtain a frequency evaluation result such that the information indicating that the audio signal comprises the predetermined characteristic may be provided dependent on the slope evaluation result and dependent on the frequency evaluation result. The cut-off frequency f_c may be used to control the bandwidth extension (BWE) by determining the frequency range at which BWE operates such that it only recovers the frequency region that is missing. This is illustrated in Fig. 13b showing a schematic flow-chart of a method 2500 according to another embodiment, the method comprising the step 2150 comprising evaluating a cut-off frequency of the spectrum of the audio signal to obtain a frequency evaluation result

The second application where ABLA, i.e., detection of the respective characteristic, may be used or required is the classification of an audio signal as a signal of low sound quality due to lossy compression. This classification can be based solely on the described analysis or by combining it with other information that can be extracted from the audio signal. Examples for additional information that can be used in this context is the width of the stereo signal or the presence of Spectral Band Replication (SBR), i.e., a method that is applied by lossy codecs. The ABLA is then used to activate other processing that improves the sound quality of signals with a lossy compression, being not restricted to BWE processing. Examples are filtering for enhancement of the stereo width and of transient signal components.

The results of the ABLA, namely the parameter D and the cut-off frequency f_c , may be used or may even be necessary for repairing such artifacts automatically without having a human operator involved. It may be of crucial importance to apply sound quality enhancement only to signals having degraded sound quality. Signals having high quality should not be processed in such a way because the sound quality can be negatively affected. Embodiments according to the second aspect allow to detect audio frames or audio signals being subjected to the artificial bandwidth limitation with a high precision. Audio signals have a natural bandwidth that is determined by the sound generating process. The bandwidth can change due to various technical processes, including bandwidth limitation that is applied for capturing, storing,

processing and transmission of the signal. Bandwidth limitation is a low-pass filtering having the characteristics of a very steep attenuation, a very high attenuation and a cut-off frequency as described above.

5 In the following, reference will be made to the third and fourth aspect of the present invention referring to a concept for bandwidth extending a bandwidth limited signal in the third aspect, for example, responsive to having determined artificial bandwidth limitation according to the second aspect. Thus, embodiments according to the third aspect may be used as signal enhancer in connection with the second aspect.

10

The concept according to the third aspect aims to suppress several coding artifacts to improve the perceived sound quality. The technical steps may be implemented as post-processing and may be partially implemented using software that may be used by the decoder. The concept may work blindly without having access to the
 15 uncompressed audio signal and to other side information. The low bitrate coding enhancement processing according to the third aspect comprises or even essentially consists of a post-processor that introduces or enhances perceptual pleasantness related to concepts to unguided post-processing of audio material that has been precoded by heritage perceptual coders. Thereby, the precoded audio material can
 20 profit from modern concepts of perceptual pleasantness.

The embodiments which are described in connection with the third and fourth aspect may use a basic principle called spectral weighting or short-term spectral attenuation. Therefore, a time domain signal $x[n]$ is transformed to its frequency domain
 25 representation $X[k,m]$ where k and m donate the frequency and timeframe index, respectively. According to embodiments, a short-time Fourier transform (STFT) may be applied, but also other transforms may be used. The output signal Y of the spectral weighting may be given by the following equation

$$30 \quad Y[k,m] = G[k,m] \cdot X[k,m],$$

wherein the time domain representation $y[n]$ of the frequency domain signal $Y[k,m]$ may be computed by means of an inverse transform, for example, an inverse STFT, i.e., ISTFT. In the following sections, time domain signals may be denoted with small letters and frequency domain signals with capital letters. Indices k and m or frequency
 35 domain signals will be omitted for better readability. The spectral weighting will be

explained in more detail in connection with an aspect being referred to as a spectral weighting in which details for the spectral weights $G[k,m]$ are explained.

Fig. 14 shows a schematic block diagram of an apparatus 140 according to an embodiment of the third aspect. The apparatus 140 is configured for processing an audio signal and may receive the spectrum 12' of the audio signal for the processing. The apparatus 140 may be configured for receiving the time domain representation of the audio signal, i.e., the audio signal 12 and may derive the spectrum 12', for example, the apparatus 140 may comprise the spectrum calculator 44 for such a purpose.

The apparatus 140 comprises a separator 92 for separating a first portion 91'a of a spectrum 91' of an audio signal 91 from a second portion 91'b of the spectrum 91' of the audio signal 91. The first portion 91'a has a first signal characteristic and the second portion 91'b has a second signal characteristic. The audio signal 91 may be received by the apparatus 91 in the time domain and/or in the frequency domain and may be, for example, bandwidth-limited using a cut-off frequency f_c and may be subjected to post-processing. One main feature of the third aspect relating to the bandwidth extension is that the input signal may be split into different characteristics such as transient and sustained signal portions which are treated independently by applying different parameter settings for the modules in each part.

The first and the second signal characteristic may differ from each other by way of different perceptions and/or by different characteristics in the frequency range. Although the embodiments are not limited hereto, the first and the second signal characteristics may be complementary to each other, i.e., by removing, excluding or subtracting one signal characteristic from the common spectrum 91', the remaining portion forms the other characteristic. By way of a non-limiting example, the first signal characteristic may be a middle frequency range of the spectrum and the second signal characteristic may be a side frequency range of the spectrum. Alternatively, the first signal characteristic may be a direct signal characteristic of the audio signal and the second signal characteristic may be an ambient signal characteristic of the audio signal. According to another embodiment, the first signal characteristic may be a tonal characteristic of the audio signal and the second signal characteristic may be a sustained signal characteristic of the audio signal which may be referred to as transient or the like. Alternatively, the first signal characteristic may

be a speech characteristic of the audio signal and the second signal characteristic may be a non-speech characteristic of the audio signal. Other signal characteristics are also possible. Further, it is possible to form combinations thereof, i.e., to combine two or more of the above identified characteristics. The first and second portions 91'a and 91'b may comprise a comparable or same bandwidth, starting frequency and stop frequency and may form, when being combined with each other the spectrum 91' again. I.e., the splitting or separation may be done by means of transient-sustained signal decomposition. Alternatively or in addition, other decomposition rules or methods are possible, such as mid-side signal decomposition, direct-ambient signal decomposition or foreground/background decomposition and/or speech-non-speech decomposition, etc.

The apparatus 140 may comprise a first bandwidth extender 94_1 for extending a bandwidth of the first portion 91'a using first parameters 96_1 associated with the first signal characteristic for obtaining a first extended portion 98a. The apparatus 140 further comprises a second bandwidth extender 94_2 for extending a bandwidth of the second portion 91'b using second parameters 96_2 associated with the second signal characteristic for obtaining a second extended portion 98b. Bandwidth extension may comprise forming additional parts or frequency portions in the spectrum to be combined with the original signal. This may include a copy and/or a generation of such further frequency regions by transposing, spectral stretching or generation of overtones through application of a non-linearity. By using a first and a second bandwidth extender, the different signal characteristics present in the different portions 91'a and 91'b may be considered differently by the respective bandwidth extender 94_1 and 94_2 . For example, a bandwidth of a copied portion, a number of copies, an alternation of copies, a spectral shaping of a signal being obtained and/or frequency characteristics of spectral portions being artificially generated may vary between different signal characteristics which may be considered by using different sets of parameters 96_1 and 96_2 in connection with the different signal characteristics. This allows for a high adaptation of the bandwidth extension to the signal characteristic.

Although having described the apparatus 140 as comprising a first and a second bandwidth extender for considering a first and a second signal characteristic, an apparatus according to further embodiments may be configured for subjecting more than two, for example, three, four, five or even a higher number, to different

bandwidths extensions. Such an apparatus may comprise corresponding numbers of bandwidth extenders but may also use one bandwidth extender for at least two bandwidths extensions, for example, when sequentially processing different signal characteristics. Accordingly, the apparatus 140 may be implemented by implementing
5 one bandwidth extender 94 and for adapting the bandwidth extender with different parameters 96_1 and 96_2 sequentially while processing the different portions 91'a and 91'b sequentially.

The apparatus 140 comprises a combiner 102 configured for using the first and
10 second extended portions 98a and 98b for obtaining an extended combined audio signal 104. The extended portions 98a and 98b may be received from the combiner 102 as a time domain representation such that the combined audio signal 104 may also be in the time domain. Alternatively, the extended portions 98a and 98b may be received by the combiner in the frequency domain such that the combined audio
15 signal 104 may also be in the frequency domain so as to be converted to the time domain afterwards. Alternatively, the combiner 102 may be configured to transform each of the single portions 98a and 98b or a combined version thereof into the time domain and for providing the combined audio signal 104 in the time domain.

20 Fig. 15 is a schematic diagram illustrating an example spectrum comprising different components 106a and 106b. For example, the component 106a may be related to a transient signal of the spectrum, for example, obtained by a snare drum. Such signals may have a higher correlation within one spectral frame and may also have a higher bandwidth than a sustained signal, for example, indicated by the spectral portion 106,
25 which may relate to a human voice. In Fig. 15, it may be seen that the transient portion 106a has considerably more bandwidth than the portion 106b, for example, a singing voice.

Fig. 16 shows a schematic block diagram of an apparatus 160 according to an
30 embodiment of the third aspect. In the following, reference will be made to the audio signal and the signals derived thereof. The audio signal may be present and/or processed in the time domain and/or in the frequency domain, wherein both variants may be transformed with respect to each other by a frequency to time conversion or a time to frequency conversion. Thus, when referring to the audio signal, this may refer
35 to the time domain representation and to the frequency domain representation synonymously acceptable being explained explicitly otherwise.

The apparatus 160 comprises the separator 92 being configured for receiving the frequency domain representation 91' of the audio signal 91. For this purpose the apparatus 160 may comprise the spectrum calculator 44 for obtaining the frequency domain representation 91' from the time domain representation.

The separator 92 may comprise a transient suppressor 108 configured for receiving the audio signal, for example, the frequency domain representation thereof, and for reducing transient portions in the audio signal 91 so as to obtain a first modified audio signal. The separator 92 may be configured for obtaining the first portion 98a based on the first modified audio signal. According to an embodiment, the first portion 98a corresponds to the first modified audio signal. According to another embodiment, a processing of the first modified portion is performed, for example, a filtering, amplification, attenuation or the like.

The separator 92 may comprise a subtractor 112 for subtracting the first modified audio signal, the first portion 91'a for example, from the audio signal 91 so as to obtain a second modified signal. According to an embodiment, the second modified signal is the second portion 91'b. As described for the first portion 91'a, the second portion 91'b may also be obtained based on a processing of the obtained subtraction result. Thus, by removing the first portion 91'a from the audio signal 91, the second portion 91'b may be obtained. By obtaining the first modified signal and by subtracting it from the audio signal so as to obtain the second modified signal, decomposition of the audio signal into the two portions may be performed.

The separator 92 may be configured to operate in the frequency domain or in the time domain and to process the audio signal 91 such that the transient suppressor 108 reduces or eliminates transient and/or tonal portions for each subband of a spectrum of the audio signal 91. This may lead to less or even no processing for subbands comprising little or non-transient or little or non-tonal (i.e. noisy) portions. The transient suppressor 108 may comprise a transient processing stage, a tonal processing stage and/or a combining stage so as to process one of the characteristics to be separated by suppressing them or by amplifying them. The frequency domain representation of the audio signal 91 may comprise a multitude of subbands (frequency bands), wherein the transient processing stage and/or the tonal processing stage are configured to process each of the frequency bands. Alternatively, the spectrum obtained by frequency conversion of the audio signal

91 may be reduced, i.e., cut, to exclude certain frequency ranges or frequency bands from further processing, such as frequency bands containing the selected characteristic or missing the selected characteristic. This may allow for a reduced computational effort and thus for faster and/or a more precise processing.

5

The transient processing stage may be configured to determine for each of the processed frequency bands, if the frequency band comprises transient portions. The tonal processing stage may be configured to determine for each of the frequency bands, if the audio signal 91 comprises tonal portions in the frequency band. The transient processing stage may be configured to determine at least for the frequency bands comprising transient portions spectral weighting factors, wherein the spectral weighting factors are associated with the respective frequency band and may allow to attenuate/exclude or amplify the respective portions. Transient and tonal characteristics may be identified by spectral processing. A level of transiency and/or tonality may be measured by the transient processing stage and/or the tonal processing stage of the separator 92 and may be converted to a spectral weight. The separator 92 may be configured to determine spectral weighting factors at least for frequency bands comprising the tonal portions. The spectral weighting factors may comprise a multitude of possible values, the magnitude of the spectral weighting factors indicating an amount of transient and/or tonal portions in the frequency band.

10

15

20

The spectral weighting factors may comprise an absolute or relative value. For example, the absolute value may comprise a value of energy of transient and/or tonal sound in the frequency band. Alternatively, the spectral weighting factors may comprise the relative value such as a value between 0 and 1, the value 0 indicating that the frequency band comprises no or almost no transient or tonal portions and the value 1 indicating the frequency band comprising a high amount or completely transient and/or tonal portions. The spectral weighting factors may comprise one of a multitude of values such as a number of 3, 5, 10 or more values (steps), e.g., (0, 0.3 and 1), (0.1, 0.2, ..., 1) or the like. A size of the scale, a number of steps between a minimum value and a maximum value may at least zero but preferably at least one and more preferably at least five. Preferably, the multitude of values of the spectral weights comprises at least three values comprising a minimum value, a maximum value and a value that is between the minimum value and the maximum value. A higher number of values between the minimum value and the maximum value may allow for a more continuous weighting of each of the frequency bands. The minimum value and the maximum value may be scaled to a scale between 0

25

30

35

and 1 or other values. The maximum value may indicate a highest or lowest level of transiency and/or tonality.

A combining stage of the separator 92 may be configured to combine the spectral weights for each of the frequency bands with the audio signal. The separator 92 may be configured to apply the combined spectral weights to each of the frequency bands. For example the spectral weights may be multiplied with spectral values of the audio signal 91 in the processed frequency band.

By suppressing or excluding some portions/characteristics from the audio signal 91, a first modified signal missing the respective characteristic but comprising the other characteristic may be obtained. By subtracting the signal from the audio signal an inverse signal comprising the suppressed characteristic and missing the characteristic of the first modified signal may be obtained by way of the second modified signal.

In the following, reference will be made to an example configuration of the bandwidth extenders 94_1 and 94_2 . Each of the bandwidth extenders 94_1 and 94_2 may comprise a duplicator 114 for duplicating at least a part of the respective portion, may comprise an envelope shaper 116 shaping at least the extended portions generated by the duplicator, may comprise a whitener 118 for equalizing at least the extended portions and/or may comprise an anti-roughness filter 122 for phase-shifting at least a portion of the extended portion. Each of these elements may be arranged together with other referenced elements. Alternatively, some or all of those elements may be absent and/or may be substituted by other elements. For example, instead of a copying performed by the duplicator, an artificial generation of a bandwidth may be implemented by the bandwidth extender, such that a bandwidth generator may substitute the duplicator 114. Alternatively, a shaping or whitening of the spectrum may be dismissed and/or other processing may be used. Further, the anti-roughness filter 122 is optional. Although being illustrated as filtering a respective signal in the time domain by being supplied with the output of an inward short-term Fourier transform block 124, the anti-roughness filter may be configured for operating in the frequency-domain and may therefore be arranged before a respective inverse short-term Fourier transform block 124. Thus, further to the arranged blocks, also an order thereof may be varied.

Each of the bandwidth extenders 94_1 and 94_2 may comprise a respective first and second duplicator 114_1 and 114_2 . The duplicators 114_1 and 114_2 are configured for duplicating at least a part of the respective first or second portion $91'a$ and $91'b$ and for combining at least one version of the duplicated part of the first portion, the second
 5 portion respectively with the first portion, the second portion $91'a$, $91'b$, respectively, so as to obtain a respective extended portion $126a$, $126b$, respectively.

When referring now to Fig. 17a, there is shown an example spectrum of the first portion $91'a$, wherein the explanation given refers to the second portion $91'b$ without
 10 any limitation. The portion $91'a$ may have a relevant energy or amplitude $|X|$ below the cut-off frequency f_c and may comprise a low amount of energy or even no energy above the cut-off frequency f_c . The spectrum may decrease with an increase in frequency. In other words, Fig. 17a shows the magnitude spectrum $|X|$ of a band-limited signal. The cut-off frequency is denoted as f_c .

15 Fig. 17b shows a schematic diagram of the first portion $91'a$ being extended by a number of two duplicated parts 128_1 and 128_2 . Each of the duplicated parts 128_1 and 128_2 may be a copy of a frequency band w of the first portion $91'a$ being copied to a frequency range unoccupied by the portion $91'a$, i.e., to frequency ranges above the
 20 cut-off frequency f_c , wherein preferably the duplicated portions 128_1 and 128_2 are combined so as to directly order on the original signal, i.e., the first portion $91'a$. Fig. 17b therefore illustrates how the copy-up is performed. Complex spectral coefficients are shifted from a so-called source patch w in the frequency interval $[f_c-w, f_c]$ to destination patches in the intervals $[f_c, f_c+w, f_c+2w]$, etc., i.e., to $[f_c(n-1)w, f_c+nw]$ for
 25 each n , wherein n is a variable ranging from 1 to the number of patches or number of copies being inserted. The number n being 2 by non-limiting example in Fig. 17b and a width Df_w of the duplicating portion may be adjusted by the apparatus 160 independently for each of the bandwidth extenders 94_1 and 94_2 . I.e., how often the source patch w is shifted may depend on the desired bandwidth and/or a number of
 30 patches, wherein both may be a tunable parameter. As on the decreasing magnitude of the spectrum, steps or discontinuities at locations where the patch is attached may occur.

The copied part of the first and second portion may range from a first intermediate
 35 frequency, for example, f_{copy1} of the first portion $91'a$ to a maximum frequency f_c of the first portion. Accordingly, the copied part of the second portion may comprise a

second frequency range ranging from a same or different intermediate frequency of the second portion 91'b to a maximum frequency of the second portion which may also be the cut-off frequency f_c . Based on different intermediate frequencies, the width Df_w may be different. For obtaining a same resulting bandwidth, therefore, a number
 5 of patches may also vary between the different bandwidth extenders.

For avoiding unwanted artifacts, the first bandwidth extender may comprise a first envelope shaper 116₁ and the second bandwidth extender 94₂ may comprise a second envelope shaper 116₂. The envelope shapers 116₁ and 116₂ may be
 10 configured for shaping at least the extended portion, i.e., frequency portions above the cut-off frequency f_c . Shaping the envelope, i.e., performing a spectral envelope shaping, may be used as frequently, magnitude spectra are not flat, they tend to fall in magnitude towards higher frequencies as illustrated in Fig. 17a. Fig. 17b visualizes the magnitude spectrum when copy-up is performed without further adaptations.
 15 Abrupt transitions in the magnitude spectrum may appear at frequencies f_c , f_c+w , ..., f_c+kw . This may lead to a piercingly bright sound perception which shall be prevented by the envelope shapers 116₁ and 116₂.

To avoid such effects, the spectral tilt T as shown in Fig. 17b may be estimated by
 20 calculating the slope $|X|$ which has been fitted by means of linear regression to the logarithmic spectrum of the source patch which comprises the frequency interval $[f_c-w, f_c]$. Each patch w may be attenuated by a value kT , i.e., the higher the patch is copied into the frequency range, the higher the attenuation may be. k may be a natural number and may be the so-called patch order, which starts from 1 and is increased
 25 for each additional patch which is shifted and may thus correspond to n mentioned before.

In other words, Fig. 17b shows a copy-up of spectral coefficients without envelope shaping. The source for copy-up is from the interval $[f_c-w, f_c]$, where w is the patch
 30 width. During analog shaping, the magnitude of the copied target patches in the interval $[f_c, f_{c+2w}]$ is attenuated by a multiple of T , which stands for the spectral tilt.

Fig. 17c shows an example magnitude spectrum 132a that may be obtained from the envelope shaper 116₁ being configured for shaping at least the extended portions
 35 126₁. Based on the interpolation, the magnitudes of the copied portions 128₁ and 128₂ may be shaped or attenuated so as to obtain a homogenous spectrum. Fig. 17c

shows the magnitude spectrum of the envelope shaping with patch order 2, wherein the patch order may comprise any value of 1 or higher. Each of the bandwidth extenders 49₁ and 49₂ may comprise a whitener for equalizing at least the extended first portion, the extended second portion, respectively. Spectral whitening may be
 5 done by raising spectral values and lowering spectral peaks.

For a better understanding, Fig. 18 shows a schematic block diagram of a spectral whitener being configured for whitening the audio signal 91 independently. The whitener may comprise the spectrum calculator 44 so as to obtain a spectrum of the
 10 audio signal. The whitener 134 may be configured for comparing the magnitude $X[k,m]$ of each spectral coefficient and timeframe to a smoothed version $Y[k,m]$, where k is the spectral coefficient index and m the frame index. $Y[k,m]$ may be derived by smoothing logarithmic spectral magnitudes over frequency. Subsequently, these logarithmic values may be transformed to the linear domain using a
 15 determination rule according to

$$Y = 10^{\frac{Y_l}{20}}$$

Real valued spectral weights $G[k,m]$ may be computed as described by the
 20 determination rule:

$$G = \begin{cases} \left(\frac{Y^{\alpha_1} + \gamma_1 (X^{\alpha_1} - Y^{\alpha_1})}{X^{\alpha_1}} \right)^{\beta_1} & \text{if } X \geq Y \\ \left(\frac{X^{\alpha_2} + \gamma_2 (Y^{\alpha_2} - X^{\alpha_2})}{X^{\alpha_2}} \right)^{\beta_2} & \text{if } X < Y \end{cases}$$

Again, index k and m are omitted for a better readability. α_1 , α_2 , β_1 , β_2 , γ_1 , γ_2 are tunable parameters that may be adapted for each of the whiteners 118₁ and 118₂
 25 independently. The whitener may comprise a calculator 126 for calculating absolute values of the spectrum. Those values may be referred to as X , wherein the values are ones provided to a calculator 138 for calculating any spectral weights G and are ones provided to a smoothing path 142 so as to obtain the smoothed version Y . A frequency converter 144 may be configured for transforming the result into a time
 30 domain. When referring now to Fig. 16, there may be seen that the whitener 118₁ and 118₂ may already operate in the frequency domain such that the respective whitener

may be implemented without the spectrum calculator 44 and/or the frequency converter 144 or the like.

Each of the bandwidth extenders 94_1 and 94_2 may comprise a respective anti-roughness filter 122_1 , 122_2 , respectively, for phase-shifting at least a portion of the extended first portion, of the extended second portion, respectively. This may either be executed as phase-shifting the copied portions 128_1 and 128_2 and/or the shaped versions $128'_1$, $128'_2$ thereof and/or the whitened versions 146a and 146b, respectively. I.e., the anti-roughness filter is configured for phase-shifting the respective extended portion or signal the right thereof so as to obtain a phase-shifted signal. The anti-roughness filter 122_1 and 122_2 may be configured for applying different phase-shifts to the respective signal to be filtered. By using the phase shift, a phase-shift of the copied portion or the extended portion with respect to the original signal may be obtained. Alternatively, the anti-roughness filter may perform a phase-shift to the complete signal provided. This may be implemented, for example, when the respective core portion is substituted afterwards by a non-phase-shifted portion as will be described in the following. The anti-roughness filter 122_1 and 122_2 may be implemented so as to filter a respective signal in the time domain. Therefore, an ISTFT blocks 124_1 , 124_2 may be arranged so as to provide a respective signal in the time domain. Alternatively, the anti-roughness filter 122_1 and 122_2 may be implemented so as to filter in the frequency domain. In such a case, the ISTFT blocks 124_1 and 124_2 may be absent or may be arranged after the anti-roughness filters 122_1 , 122_2 , respectively. Anti-roughness filtering may be performed to decrease the perceived roughness which is mainly evoked by the copy-up. A filter which does not affect the timbre of the signal but mainly changes the phase of the signal may be suitable here. For example, two nested allpass filters may be arranged in parallel and may be calculated in the time domain. Nested of allpass filters may be understood as $H_1(z)$ and $H_2(z)$ denoting unity-gain allpass transfer functions of a respective filter, then both $H_1(H_2(z))$ and $H_2(H_1(z))$ are allpass filters.

Optionally, each of the bandwidth extenders 94_1 and 94_2 may comprise an amplifier/attenuator 148_1 , 148_2 , respectively, for applying a gain g_t , g_s respectively for amplifying the sustained or transient portions. A result may be the extended portions 98a and 98b provided to the combiner 102. As explained above, the extended portions 98a and 98b may be obtained differently and/or by only performing some of the signal modifications explained.

In connection with the roughness filter, the apparatus 160 may comprise a high-pass filter 152 for filtering the first extended portion and the second extended portion 98a and 98b, the combined signal 102, respectively, and synonymously so as to obtain a filtered signal 154. In parallel to the bandwidth extenders 94₁ and 94₂, the audio signal 91 may be subjected to a delay 156 for compensating time delays caused by the time-to-frequency conversion in block 44 and the frequency-to-time conversion in blocks 124₁ and 124₂. The apparatus 160 may comprise a low-pass filter 158 configured for filtering the delayed audio signal. The apparatus 160 may further comprise a combiner 162 configured for combining the low-pass filtered audio signal and the signal 154. According to an embodiment, the apparatus 160 is configured to match the upper frequency (cut-off frequency X_c) of the low-pass filter 158 with a lower edge frequency of the high-pass filter 152 so as to obtain a combined homogeneous signal. In particular, the apparatus 160 may be configured to adapt the respective lower frequency of the high-pass filter 152 together with the upper edge frequency (cut-off frequency) of the low-pass filter 158 responsive to and in accordance with the determined cut-off frequency of the audio signal 91. Thus, based on the high-pass filter 152, signal portions below the cut-off frequency f_c may be dismissed or strongly attenuated such that only the extended and phase-shifted portions remain. In contrast hereto, the low-pass filter 158 may be used to dismiss, discard or strongly attenuate parts of the audio signal 91, portions thereof respectively extending beyond the cut-off frequency f_c . This allows for obtaining the extended and copied versions being phase-shifted with respect to the original audio signal 91 being only delayed so as to compensate for other delays within the bandwidth extenders, except for the anti-roughness filters 122₁ and 122₂. An obtained audio signal 164 may be an extended and optimized audio signal.

Because anti-roughness filtering shall only be applied to the bandwidth extended areas of the spectrum, the resulting signal may be high-pass filtered and added to the low-pass filtered and delayed input signal. Delay is used or needed to compensate for the delay introduced by the STFT. The cut-off frequencies of the aforementioned high-pass and low-pass filters may correspond to the cut-off frequency f_c as shown, for example, in Fig. 17a.

With respect to Fig. 19 in connection with Fig. 16, there is shown a functionality of optional blocks 166 being a signal analyzer and 168 being a lookup table of the

apparatus 160. Apparatus 160 may be a blind bandwidth extension. It may be an aim at restoring the lost bandwidth as described and without having further knowledge, for example, based on side information. The signal analyzer 166 may be configured for detecting, if the signal has been artificially band-limited or not and/or may estimate a cut-off frequency f_c of the audio signal 91. Both steps may be performed as described in connection with the artificial bandwidth limitation analysis. Both values may be updated for each frame. Thus, the audio signal 91 may comprise a plurality of frames. The apparatus 160 may comprise the signal analyzer 166 configured for analyzing for each frame, the spectrum of the audio signal 91 for a characteristic relating to an artificial bandwidth limitation of the audio signal 91 and for determining a cut-off frequency f_c in the audio signal 91.

Based on different cut-off frequencies which are schematically referred to as f_0 , f_1 , f_2 , f_3 , f_4 , respectively in Fig. 19, different parameters are being used for adapting a functionality of the duplicator 114, the shaper 116, the whitener 118 and/or the anti-roughness filter 122 may vary. For example, a parameter p may be used to adapt the respective block. As illustrated in Fig. 19, different cut-off frequencies may be associated with different parameters or different values of the same parameter. Those values may be stored in a lookup table 168 for providing the respective parameter to the respective block. In Fig. 16, dashed connections indicate that a module is controlled, for example, in real-time. An example parameter may be But here is an example: one parameter can be the bandwidth of the source patch w . This parameter may affect the bandwidth which is artificially created. Another example parameter may be a time constant of a smoothing filter which may be different for different codecs. A plurality of other examples may be used to control the blocks 114, 116, 118 and/or 122 in the frequency domain and/or time domain.

The lookup table may hold tunings for some or all of the control parameters depending on the signal analysis results. In case of the estimation of the cut-off frequency f_c , for each selected frequency f_i a perceptual tuning of the corresponding parameter may be executed which may lead to a control value p_i . It is noted that a selected value p_i may differ for the different bandwidth extenders, i.e., the apparatus 160 may be configured to adapt the respective block differently. Lookup table sampling points s_i for a bandwidth extender 94₁ or 94₂ may be given, for example, as tuples according to

$$s_i = (f_i, p_i)$$

In Fig. 19, there is shown an example for a tuning of one control parameter p for five cut-off frequencies f_0 , to f_4 . According to some examples, a parameter may be interpolated when intermediate values are appropriate. In such a case, between two sampling points in the interval $[f_i, f_{i+1}]$, linear interpolation may be executed according to:

$$p(f_c) = y_i + (f_c - f_i) \cdot \frac{y_{i+1} - y_i}{f_{i+1} - f_i}$$

An example for such interpolation values may be, for example, a width w of a respective patch as explained in connection with Figs. 17a-17c. Parameters that may remain not subjected to interpolation may be, for example, a number of patches which is limited, for example, to integer values.

The apparatus may be configured for using the first and second parameters for a frame having the characteristic relating to an artificial bandwidth limitation. For other frames, the apparatus may be configured for using third parameters for the first bandwidth extender and fourth parameters for the second bandwidth extender, e.g., for frames having a characteristic different from the characteristic relating to an artificial bandwidth limitation. Alternatively, the apparatus may be configured to deactivate the first and second bandwidth extender for the frames having a characteristic being different from the characteristic relating to an artificial bandwidth limitation. Thus, the apparatus may be configured for performing bandwidth extension for frames that are considered to comprise the respective characteristic and may treat frames that are considered to not comprise the characteristic differently by using the third and fourth parameters or to leave the respective frame untreated.

The apparatus may thus comprise a lookup-table comprising a plurality of parameters associated with a corresponding plurality of signal modification parameters such as the cut-off frequency f_c and a plurality of other parameters associated with a corresponding plurality of signal modification parameters f_c used for the first and second bandwidth extenders 94₁, 94₂ respectively. The apparatus may comprise a signal analyzer 166 for analyzing the spectrum for a modification applied

to the audio signal 91. The apparatus 160 may be configured for deriving a modification parameter associated with the modification, for example, the cut-off frequency f_c and/or a parameter relating to the steepness of the slope. The apparatus may be configured for deriving the respective first and/or second parameter using the
5 lookup-table and using the modification parameter. According to one example, the apparatus may derive the modification parameter cut-off frequency and may determine the parameter p once for the first bandwidth extender and once for the second bandwidth extender.

10 In known concepts, artificial bandwidth extension is a well-known audio coding technique. Also, unguided bandwidth extension is well-known. However, semantic decomposition prior to bandwidth extension calculation is unknown. Semantic decorrelation may be used for the purpose of spatial upmixing, not containing a copy-up or transposition functionality like inevitably found in bandwidth extension
15 applications. Therefore, the embodiments according to the third aspects differ. Another technique is known from a decorrelated bandwidth extension. Here, all high-band target spectral regions are decorrelated through dedicated decorrelators or through inserting decorrelated instances of random noise to be mutually independent. The present embodiments according to the third aspect teaches mutual decorrelation
20 of semantically decomposed signal parts whereas the known concepts just comprise the decorrelation of different spectral target regions.

Fig. 20 shows a schematic flowchart of a method 3000 according to an embodiment of the third aspect. The method 3000 comprises a step 3100 comprising separating a
25 first portion of a spectrum of the audio signal from a second portion of the spectrum of the audio signal, the first portion having a first signal characteristic and the second portion having a second signal characteristic. A step 3200 comprises extending a bandwidth of the first portion using first parameters associated with the first signal characteristic for obtaining a first extended portion. A step 3300 comprises extending
30 a bandwidth of the second portion using the second parameters associated with the second signal characteristic, for obtaining a second extended portion. A step 3400 comprises using the first extended portion and the second extended portion for obtaining an extended combined audio signal.

35 According to the fourth aspect, the anti-roughness suppression may be performed as a post-processing, for example, after having performed bandwidth extension with a

different concept. Thus, the anti-roughness suppression or anti-roughness filtering may be used so as to reduce artifacts, for example, in connection with the signal enhancer 48 when having determined that artificial bandwidth limitation has been performed and that the respective extension has also been performed.

5

Fig. 21 shows a schematic diagram of an apparatus 210 according to an embodiment of the fourth aspect. The apparatus 210 may be used, for example, for processing the audio signal 12 being subjected to an artificial bandwidth extension. The apparatus 210 may comprise the anti-roughness filter 122 for phase-shifting at least a portion of the audio signal 12, so as to obtain a phase-shifted signal 172. The anti-roughness filter 122 may operate, for example, in the time domain or alternatively in the frequency domain. According to an embodiment, the anti-roughness filter 122 may be configured for phase-shifting the complete audio signal 12. The apparatus 210 comprises a high-pass filter, e.g., the high-pass filter 152 for filtering the phase shifted signal 173, so as to obtain a first filtered signal 174. The apparatus 210 comprises a low-pass filter such as the low-pass filter 158 for filtering the audio signal 12 so as to obtain a second filtered signal 176. The apparatus 210 further comprises a combiner 162 for combining the signals 154 and 156 so as to obtain an enhanced audio signal 178, in which the perceived roughness is reduced. As was described in connection with the apparatus 160, the extended bandwidth is phase-shifted with respect to the audio signal 12. One aspect is to filter the audio signal 12, using the low-pass filter 158 so as to dismiss any signal portions that are above the selected filter frequency, the cut-off frequency f_c respectively. This allows reducing or limiting effects or superposition of different signal portions in the combined signal 178.

25

Fig. 22 shows a schematic block diagram of an apparatus 220 according to an embodiment of the fourth aspect. As described in connection with Fig. 16, the apparatus 220 may comprise the separator 92 for providing first and second portions 12'a and 12'b of the audio signal 12 in the frequency domain. The apparatus 220 may comprise different paths, each path comprising, by non-limiting example, a whitener 118₁, 118₂, respectively together with an anti-roughness filter 122₁, 122₂, respectively, operating by non-limiting example only, in the time domain. Alternatively or in addition, each path may comprise an amplifier/attenuator 148. Thus, the apparatus 220 may be configured for enhancing the audio signal 12 by enhancing the different portions 12'a and 12'b independently from each other. For such a purpose, the

35

apparatus 220 may comprise the signal analyzer 166 and the lookup table 168 as described in connection with Fig. 16.

In particular, the apparatus 220 may comprise the signal analyzer 166 configured for
5 determining a start frequency of bandwidth extension in the audio signal 12, the start frequency of bandwidth extension arranged between an extending bandwidth, e.g., the added patches w according to Figs. 70a-c or processed versions thereof, of the audio signal 12 and a core bandwidth, i.e., the original bandwidth such as the bandwidth of the audio signal 91.

10 In connection herewith, the apparatus may be configured to adapt a lower frequency of the high-pass filter 152 and/or an upper frequency of the low-pass filter 158 according to a start frequency of bandwidth extension in the audio signal 12. The start frequency of bandwidth extension may be received by a further channel or may be
15 determined by the signal analyzer 166.

According to an embodiment that may be combined with the independent embodiment of apparatus 210 and with each of the other embodiments of the fourth aspect, the apparatus may be configured to adapt the roughness filter and/or a signal
20 enhancer, for example, comprising the whitener 118, an envelope shaper or the like for enhancing the audio signal 12, using a start frequency of bandwidth extension in the audio signal. For example, based on the start frequency of bandwidth extension in the audio signal 12, the lookup table may provide four different parameters for each of the blocks to be adjusted, such as the whitener 118 and/or the anti-roughness filter
25 122 and/or further blocks.

According to an embodiment that may be combined with each of the other embodiments according to the fourth aspect, the anti-roughness filter 122 may be arranged in a first path and wherein the low-pass filter 158 may be arranged in a
30 second path. The second path may comprise the whitener 118 for equalizing a signal based on a signal provided to or received from the anti-roughness filter, i.e., an order or sequence of the whitener and the anti-roughness filter may be changed.

According to a further embodiment of the fourth aspect, which may be combined with
35 each of the other embodiments, the anti-roughness filter 122 may be arranged in a first path and the low-pass filter 158 may be arranged in a second path. The

apparatus 220 may comprise a signal enhancer configured to enhance the audio signal in the first path and at least partially in the frequency domain, for example, using the whitener 118 and/or the shaper 116. The second path may comprise a delay block such as the delay 156 for delaying the audio signal 12 by a delay
5 corresponding to a delay in the first path caused by a time-to-frequency conversion and a frequency-to-time conversion within a tolerance range of at most $\pm 10\%$, $\pm 5\%$ or $\pm 2\%$ and probably excluding the anti-roughness filter delay.

According to a further embodiment, which may be combined with each of the other
10 embodiments according to the fourth aspect, the anti-roughness filter 122 is a first anti-roughness filter. The apparatus comprises a separator for receiving a spectrum of the audio signal 12 and for separating a first portion 12'a of the spectrum 12' of the audio signal 12 from a second portion 12'b of the spectrum of the audio signal 12. The first portion 12'a has a first signal characteristic and the second portion 12'b has
15 a second signal characteristic. The apparatus 220 may be configured for providing the first portion 12'a to a first path having the first anti-roughness filter 122₁ and for providing the second portion 12'b to a third path having the second anti-roughness filter 122₂.

20 According to a further embodiment which may be combined with the previously mentioned embodiment, the apparatus may be configured to apply a first gain g_f to the first path and a second gain g_s to the third path.

According to a further embodiment of the fourth aspect which may be combined with
25 the previous and the penultimate embodiment, the apparatus may be configured for adjusting the first anti-roughness filter 122₁ and the second anti-roughness filter 122₂ differently from each other using a start frequency of bandwidth extension of the audio signal 12.

30 According to a further embodiment of the fourth aspect which may be combined with the last three embodiments of the fourth aspect, the separator comprises a transient suppressor, such as the transient suppressor 108 configured for receiving the audio signal 12 and for reducing transient portions in the audio signal 12 so as to obtain a first modified audio signal. The separator 92 is configured for obtaining the first
35 portion 12'a based on the first modified audio signal, for example, by using the first

modified audio signal as the first portion 12'a. The separator 92 further comprises the subtractor 112 for subtracting the first modified audio signal from the audio signal 12 so as to obtain a second modified signal. The separator 92 is configured for obtaining the second portion based on the second modified audio signal, for example, by taking
5 the second modified audio signal as the second portion 12'b.

According to a further embodiment of the fourth aspect, which may be combined with the last four embodiments, the first signal characteristic is one of a) a middle frequency range of the spectrum; b) a direct signal characteristic of the audio signal;
10 c) a tonal characteristic of the audio signal; and d) a speech characteristic of the audio signal. The second signal characteristic is according to the letters used: a) a side frequency range of the spectrum; b) an ambient signal characteristic of the audio signal; c) a sustained signal characteristic of the audio signal; and d) a non-speech characteristic of the audio signal.

15 According to a further embodiment of the fourth aspect, which may be combined with each of the other embodiments of the fourth aspect, the enhanced audio signal 164 comprises the second filtered signal being phase-shifted when compared to the first filtered signal, i.e., the upper frequency region is phase-shifted when compared to the
20 lower frequency region.

Fig. 23 shows a schematic flowchart of a method 4000 for processing an audio signal. The method 4000 comprises a step 4100 comprising phase-shifting at least a portion of the audio signal so as to obtain a phase-shifted signal. A step 4200 comprises
25 filtering the phase-shifted signal using a high-pass filter so as to obtain a first filtered signal. A step 4300 comprises filtering the audio signal using a low-pass filter so as to obtain a second filtered signal. A step 4400 comprises combining the first filtered signal and the second filtered signal so as to obtain an enhanced audio signal. In other words, the artificial bandwidth extension roughness suppression (ARS) targets
30 to reduce artifacts such as the tonal spike artifact and the beating artifact as described before. As illustrated in Fig. 22, some of the ARS methods or blocks are also used by the BWE concept which already has been described before. It has to be noted too that these common methods or concepts may be used with different parameter tunings. In the following sections, differences between the apparatus 160
35 and the apparatus 220 will be outlined.

The signal analyzer is used to activate ARS in Fig. 22 by on the one hand detecting whether the signal has been artificially bandwidth-extended or not. On the other hand, a real-time estimation of the start frequency (cut-off frequency) of the artificial bandwidth extension may be performed which has been applied to the present signal.

5 The description of the signal analyzes whether a concept may be performed according to the other aspects described herein. The signal analyzer results are forwarded to the lookup table 168 for obtaining an output thereof having included control parameters which affect the modules shown in Fig. 22. The lookup table 168 may comprise parameter tunings which were perceptually tuned for several start
10 frequencies.

The lookup table for ARS may be based on the same principle as the BWE lookup table described in connection with Fig. 16 with the difference that the dependent variable may be the estimation of the BWE start frequency. Also the parameters
15 which are controlled may differ.

Although some aspects have been described in the context of an apparatus, it is clear that these aspects also represent a description of the corresponding method, where a block or device corresponds to a method step or a feature of a method step.
20 Analogously, aspects described in the context of a method step also represent a description of a corresponding block or item or feature of a corresponding apparatus.

The inventive encoded audio signal can be stored on a digital storage medium or can be transmitted on a transmission medium such as a wireless transmission medium or
25 a wired transmission medium such as the Internet.

Depending on certain implementation requirements, embodiments of the invention can be implemented in hardware or in software. The implementation can be performed using a digital storage medium, for example a floppy disk, a DVD, a CD, a
30 ROM, a PROM, an EPROM, an EEPROM or a FLASH memory, having electronically readable control signals stored thereon, which cooperate (or are capable of cooperating) with a programmable computer system such that the respective method is performed.

35 Some embodiments according to the invention comprise a data carrier having electronically readable control signals, which are capable of cooperating with a

programmable computer system, such that one of the methods described herein is performed.

5 Generally, embodiments of the present invention can be implemented as a computer program product with a program code, the program code being operative for performing one of the methods when the computer program product runs on a computer. The program code may for example be stored on a machine readable carrier.

10 Other embodiments comprise the computer program for performing one of the methods described herein, stored on a machine readable carrier.

In other words, an embodiment of the inventive method is, therefore, a computer program having a program code for performing one of the methods described herein,
15 when the computer program runs on a computer.

A further embodiment of the inventive methods is, therefore, a data carrier (or a digital storage medium, or a computer-readable medium) comprising, recorded thereon, the computer program for performing one of the methods described herein.

20

A further embodiment of the inventive method is, therefore, a data stream or a sequence of signals representing the computer program for performing one of the methods described herein. The data stream or the sequence of signals may for example be configured to be transferred via a data communication connection, for
25 example via the Internet.

A further embodiment comprises a processing means, for example a computer, or a programmable logic device, configured to or adapted to perform one of the methods described herein.

30

A further embodiment comprises a computer having installed thereon the computer program for performing one of the methods described herein.

In some embodiments, a programmable logic device (for example a field programmable gate array) may be used to perform some or all of the functionalities of
35 the methods described herein. In some embodiments, a field programmable gate

array may cooperate with a microprocessor in order to perform one of the methods described herein. Generally, the methods are preferably performed by any hardware apparatus.

- 5 The above described embodiments are merely illustrative for the principles of the present invention. It is understood that modifications and variations of the arrangements and the details described herein will be apparent to others skilled in the art. It is the intent, therefore, to be limited only by the scope of the impending patent claims and not by the specific details presented by way of description and explanation
- 10 of the embodiments herein.

References

- [1] M. Arora, J. Lee, and S. Park, "High quality blind bandwidth extension of audio for portable player applications," in Proc. of the AES 120th Conv., 2006.

5

- [2] Markus Erne, "Perceptual audio coders "what to listen for?," in Audio Engineering Society Convention 111, Nov 2001.

- [3] Chia-Ming Chang, Han-Wen Hsu, Kan-Chun Lee, Wen-Chieh Lee, Chi-Min Liu, Shou-Hung Tang, Chung-Han Yang, and Yung-Cheng Yang, "Compression artifacts in perceptual audio coding," in Audio Engineering Society Convention 121, Oct 2006.

10

- [4] Martin Dietz, Lars Liljeryd, Kristofer Kjörling, and Oliver Kunz, "Spectral band replication, a novel approach in audio coding," in Audio Engineering Society Convention 112, Apr 2002.

15

- [5] Sascha Disch, Andreas Niedermeier, Christian R. Helmrich, Christian Neukam, Konstantin Schmidt, Ralf Geiger, Jeremie Lecomte, Florin Ghido, Frederik Nagel and Bernd Edler, "Intelligent gap filling in perceptual transform coding of audio," in Audio Engineering Society Convention 141, Sep 2016.

20

Claims

1. An apparatus for processing an audio signal, the apparatus comprising:

5

a separator (92) for separating a first portion (91'a) of a spectrum (91') of the audio signal (91) from a second portion (91'b) of the spectrum (91') of the audio signal (91), the first portion (91'a) having a first signal characteristic and the second portion (91'b) having a second signal characteristic;

10

a first bandwidth extender (94₁) for extending a bandwidth of the first portion (91'b) using first parameters (96₁) associated with the first signal characteristic, for obtaining a first extended portion (98a, 126a);

15

a second bandwidth extender (94₂) for extending a bandwidth of the second portion (91'b) using second parameters (96₂) associated with the second signal characteristic, for obtaining a second extended portion (98b, 126b); and

20

a combiner (102) configured for using the first extended portion (98a) and the second extended portion (98b) for obtaining an extended combined audio signal (104).

2. The apparatus of claim 1, wherein the first bandwidth extender (94₁) is configured for extending the bandwidth of the first portion (91'a) by adding spectral components (w) to the first portion (91'a), wherein the second bandwidth extender (94₂) is configured for extending the bandwidth of the second portion (91'b) by adding spectral components (w) to the second portion (91'b).

25

3. The apparatus of claim 1 or 2, wherein the first bandwidth extender (94₁) comprises a first duplicator (114₁) for duplicating at least a part (w, 128) of the first portion (91'a) and for combining at least one version (w) of the duplicated part (w, 117) of the first portion with the first portion (91'a) so as to obtain an extended portion (126a); and

30

- wherein the second bandwidth extender (94₂) comprises a second duplicator (114₂) for duplicating at least a part of (w, 129) the second portion (91'b) and for combining

35

at least one version of the duplicated part (w,128) of the second portion with the second portion (91'b) so as to obtain an extended portion (126b).

4. The apparatus of claim 3, wherein the part (w,128) of the first portion comprises a first frequency range (Δf_w) ranging from a first intermediate frequency (f_{copy}) of the first portion to a maximum frequency (f_c) of the first portion; and

wherein the part (w,128) of the second portion comprises a second frequency range (Δf_w) ranging from a second intermediate frequency (f_{copy}) of the second portion (91'b) to a maximum frequency (f_c) of the second portion.

5. The apparatus of claim 4 or 5, wherein the first bandwidth extender (94₁) comprises a first envelope shaper for shaping at least the duplicated part (w,128) of the extended first portion and wherein the second bandwidth extender (94₂) comprises a second envelope (116₂) shaper for shaping at least the dedicated part of the extended second portion (126b).

6. The apparatus of one of previous claims, wherein the first bandwidth extender (94₁) comprises a first whitener (118₁) for equalizing at least the duplicated part (w,128) of the extended first portion (126a) and wherein the second bandwidth extender (94₂) comprises a second whitener (118₂) for equalizing at least duplicated part (w,128) of the extended second portion (126b).

7. The apparatus of one of previous claims, wherein the first bandwidth extender (94₁) comprises a first anti-roughness filter (94, 122₁) for phase shifting at least a portion of the extended first portion (126a) and wherein the second bandwidth extender (94₂) comprises a second anti-roughness filter (122₂) for phase shifting at least a portion of the extended second portion (126b).

8. The apparatus of claim 7, wherein the first anti-roughness filter (122₁) is configured for phase shifting the first extended portion (w,128) or a signal derived thereof so as to obtain a first phase shifted signal; and

wherein the second anti-roughness filter (122₂) is configured for phase shifting the second extended portion (w,128) or a signal derived thereof, so as to obtain a second phase shifted signal.

9. The apparatus of claim 7 or 8, wherein the first anti-roughness filter (122₁) is configured for applying a first phase shift and wherein the second anti-roughness filter (122₂) is configured for applying a second phase shift.

5

10. The apparatus of one of previous claims,

wherein the first signal characteristic is one of

10

- a) a middle frequency range of the spectrum;
- b) a direct signal characteristic of the audio signal;
- c) a tonal characteristic of the audio signal; and
- d) a speech characteristic of the audio signal

15

and wherein the second signal characteristic is:

- a) side frequency range of the spectrum;
- b) an ambient signal characteristic of the audio signal;
- c) a sustained signal characteristic of the audio signal; and
- d) a non-speech characteristic of the audio signal.

20

11. The apparatus of one of previous claims, wherein the audio signal (91) comprises a plurality of frames and wherein the apparatus comprises a signal analyzer (166) configured for analyzing, for each frame, the spectrum (91') of the audio signal (91) for a characteristic relating to an artificial bandwidth limitation of the audio signal (91) and for determining a cut-off frequency (f_c) in the audio signal;

25

wherein the apparatus is configured for using the first and second parameters (96₁, 96₂) for a frame having the characteristic relating to an artificial bandwidth limitation; and

30

wherein the apparatus is configured for using third parameters for the first bandwidth extender (94₁) and fourth parameters for the second bandwidth extender (94₂) for frames having a characteristic different from the characteristic relating to an artificial bandwidth limitation; or to deactivate the first and second bandwidth extender (94₁,

35

94₂) for the frames having a characteristic being different from the characteristic relating to an artificial bandwidth limitation.

12. The apparatus of one of previous claims, wherein the apparatus comprises a
5 lookup-table (168) comprising a plurality of first parameters (p , 96) associated with a
corresponding plurality of signal modification parameters (f_1 - f_4 , f_c) and a plurality of
second parameters (p , 96₂) associated with a corresponding plurality of signal
modification parameters (f_1 - f_4 , f_c); wherein the apparatus comprises a signal
10 analyzer (166) for analyzing the spectrum (91') for a modification applied to the
audio signal (91); wherein the apparatus is configured for deriving a modification
parameter (f_1 - f_4 , f_c) associated with the modification; and for deriving the first
parameter (96₁) and the second parameter (96₂) using the lookup-table (168) and
using the modification parameter (f_1 - f_4 , f_c).

13. The apparatus of one of previous claims, wherein the separator (92) comprises:

20 a transient suppressor (108) configured for receiving the audio signal (91') and for
reducing transient portions in the audio signal (91) so as to obtain a first modified
audio signal, wherein the separator (92) is configured for obtaining the first portion
(91'a) based on the first modified audio signal;

25 a subtractor (112) for subtracting the first modified audio signal from the audio signal
(91') so as to obtain a second modified signal (91'b), wherein the separator (92) is
configured for obtaining the second portion (91'b) based on the second modified
audio signal.

14. The apparatus of one of previous claims, wherein the combiner (102) is a first
combiner, the apparatus comprising:

30 a high-pass filter (152) for filtering the first extended portion (98'a) and the second
extended portion (98'b) or for filtering the combined audio signal (104) such that a
filtered combined audio signal (154) is obtained;

35 a low-pass filter (158) for filtering the audio signal (91) so as to obtain a filtered
audio signal; and

a second combiner (162) configured for combining the filtered combined audio signal (154) and the filtered audio signal for obtaining a bandwidth extended audio signal (164).

5 15. An apparatus (210) for processing an audio signal (12), the apparatus comprising:

an anti-roughness filter (122) for phase shifting at least a portion of the audio signal (12) so as to obtain a phase shifted signal (172);

10 a high-pass filter (152) configured for filtering the phase shifted signal (172) so as to obtain a first filtered signal (174);

a low-pass filter (158) configured for filtering the audio signal (12) so as to obtain a second filtered signal (176);

15

a combiner (162) configured for combining the first filtered signal (174) and the second filtered signal (176) so as to obtain an enhanced audio signal (178).

20 16. Method (3000) for processing an audio signal, the method comprising:

separating (3100) a first portion of a spectrum of the audio signal from a second portion of the spectrum of the audio signal, the first portion having a first signal characteristic and the second portion having a second signal characteristic;

25 extending (3200) a bandwidth of the first portion using first parameters associated with the first signal characteristic, for obtaining a first extended portion;

30 extending (3300) a bandwidth of the second portion using second parameters associated with the second signal characteristic, for obtaining a second extended portion; and

using (3400) the first extended portion and the second extended portion for obtaining an extended combined audio signal.

35 17. A method (4000) for processing an audio signal, the method comprising:

phase shifting (4100) at least a portion of the audio signal so as to obtain a phase shifted signal;

5 filtering (4200) the phase shifted signal using a high-pass filter so as to obtain a first filtered signal;

filtering (4300) the audio signal using a low-pass filter so as to obtain a second filtered signal;

10 combining (4400) the first filtered signal and the second filtered signal so as to obtain an enhanced audio signal.

15 18. Non transitory storage medium having stored thereon a computer program having a program code for performing, when running on a computer, a method according to claim 16 or 17.




Fig. 1




Fig. 2a




Fig. 2b




Fig. 3




Fig. 4

5/29




Fig. 5




Fig. 6a




Fig. 6b

8/29

70




Fig. 7

9/29




Fig. 8

10/29


90

Fig. 9




Fig. 10

12/29




Fig. 11

120




Fig. 12a




Fig. 12b





Fig. 12c



200




Fig. 12e


1500

Fig. 12f

19/29


2000

Fig. 13a


2500

Fig. 13b

140




Fig. 14




Fig. 15

160




Fig. 16

23/29




Fig. 17a




Fig. 17b




Fig. 17c




Fig. 18




Fig. 19




Fig. 20




Fig. 21

220




Fig. 22

29/29


4000

Fig. 23

INTERNATIONAL SEARCH REPORT

International application No
PCT/EP2018/025082

A. CLASSIFICATION OF SUBJECT MATTER
INV. G10L21/038 G10L25/69
ADD.

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
G10L

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

EPO-Internal, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X,P	Patrick Gampp ET AL: "Methods for Low Bitrate Coding Enhancement Part I: Spectral restoration", 2017 AES International Conference on Automotive Audio, 29 August 2017 (2017-08-29), pages 1-8, XP055454104, Retrieved from the Internet: URL: http://www.aes.org/e-lib/inst/download.cfm/19193.pdf?ID=19193 [retrieved on 2018-02-26]	1-10, 13-18
Y,P	figures 4,5 section 4	11,12
X	----- US 2011/075832 A1 (TASHIRO ATSUSHI [JP]) 31 March 2011 (2011-03-31)	1-6,10, 16,18
Y	paragraphs [0033] - [0111]; figures 2-12 ----- -/-	7-9,11, 12



Further documents are listed in the continuation of Box C.



See patent family annex.

* Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier application or patent but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

15 May 2018

Date of mailing of the international search report

13/06/2018

Name and mailing address of the ISA/

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040,
Fax: (+31-70) 340-3016

Authorized officer

Tilp, Jan

INTERNATIONAL SEARCH REPORT

International application No
PCT/EP2018/025082

C(Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y	LAITINEN MIKKO-VILLE ET AL: "Phase Derivative Correction of Bandwidth-Extended Signals for Perceptual Audio Codecs", AES CONVENTION 140; MAY 2016, AES, 60 EAST 42ND STREET, ROOM 2520 NEW YORK 10165-2520, USA, 26 May 2016 (2016-05-26), XP040680719, section 5	7-9
Y	----- US 2016/329061 A1 (HEBER KEVIN ERIC [US] ET AL) 10 November 2016 (2016-11-10) figures 3,9 paragraphs [0025] - [0028] paragraphs [0067], [0068] -----	11,12

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/EP2018/025082

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 2011075832 A1	31-03-2011	CN 102034482 A	27-04-2011
		JP 5493655 B2	14-05-2014
		JP 2011075728 A	14-04-2011
		US 2011075832 A1	31-03-2011

US 2016329061 A1	10-11-2016	CN 105900170 A	24-08-2016
		EP 3092640 A1	16-11-2016
		JP 2017507348 A	16-03-2017
		KR 20160106586 A	12-09-2016
		US 2016329061 A1	10-11-2016
		WO 2015105775 A1	16-07-2015
