

(19) **DANMARK**



Patent- og
Varemærkestyrelsen

(10) **DK/EP 2582054 T3**

(12) Oversættelse af
europæisk patentskrift

-
- (51) Int.Cl.: **H 03 M 13/11 (2006.01)** **H 04 L 1/00 (2006.01)**
- (45) Oversættelsen bekendtgjort den: **2021-06-21**
- (80) Dato for Den Europæiske Patentmyndigheds bekendtgørelse om meddelelse af patentet: **2021-04-21**
- (86) Europæisk ansøgning nr.: **12188084.3**
- (86) Europæisk indleveringsdag: **2009-02-11**
- (87) Den europæiske ansøgnings publiceringsdag: **2013-04-17**
- (30) Prioritet: **2008-02-11 KR 20080012392** **2008-03-14 KR 20080023846**
- (62) Stamansøgningsnr: **09152538.6**
- (84) Designerede stater: **AT BE BG CH CY CZ DE DK EE ES FI FR GB GR HR HU IE IS IT LI LT LU LV MC MK MT NL NO PL PT RO SE SI SK TR**
- (73) Patenthaver: **Samsung Electronics Co., Ltd, 129, Samsung-ro , Yeongtong-gu , Suwon-si, Gyeonggi-do 443-742, Sydkorea**
- (72) Opfinder: **Myung, Seho, C/O Samsung Electronics Co., Ltd., 129 Samsung-ro, Yeongtong-gu, Suwon-si, 443-742 Gyeonggi-do, Sydkorea**
Kwon, Hwan-Joon, C/O Samsung Electronics Co., Ltd., 129 Samsung-ro, Yeongtong-gu, Suwon-si, 443-742 Gyeonggi-do, Sydkorea
Kim, Jae-Yoel, C/O Samsung Electronics Co., Ltd., 129 Samsung-ro, Yeongtong-gu, Suwon-si, 443-742 Gyeonggi-do, Sydkorea
Lim, Yeon-Ju, C/O Samsung Electronics Co., Ltd., 129 Samsung-ro, Yeongtong-gu, Suwon-si, 443-742 Gyeonggi-do, Sydkorea
Yun, Sung-Ryul, C/O Samsung Electronics Co., Ltd., 129 Samsung-ro, Yeongtong-gu, Suwon-si, 443-742 Gyeonggi-do, Sydkorea
Lee, Hak-Ju, C/O Samsung Electronics Co., Ltd., 129 Samsung-ro, Yeongtong-gu, Suwon-si, 443-742 Gyeonggi-do, Sydkorea
Jeong, Hong-Sil, C/O Samsung Electronics Co., Ltd. , 129 Samsung-ro, Yeongtong-gu, Suwon-si, 443-742 Gyeonggi-do, Sydkorea
- (74) Fuldmægtig i Danmark: **Patrade A/S, Ceresbyen 75, 8000 Århus C, Danmark**
- (54) Benævnelse: **Fremgangsmåde og apparat til kanalkodning og -dekodning i et kommunikationssystem under anvendelse af lavdensitetsparitetskontrolkoder**
- (56) Fremdragne publikationer:
HAGENAUER J: "RATE-COMPATIBLE PUNCTURED CONVOLUTIONAL CODES (RCPC CODES) AND THEIR APPLICATIONS", IEEE TRANSACTIONS ON COMMUNICATIONS, IEEE SERVICE CENTER, PISCATAWAY, NJ. USA, vol. 36, no. 4, 1 April 1988 (1988-04-01), pages 389-400, XP000670428, ISSN: 0090-6778, DOI: 10.1109/26.2763
PISHRO-NIK H ED - PISHRO-NIK H: "Results on Punctured LDPC Codes", INFORMATION THEORY WORKSHOP, 2004. IEEE, 1 November 2004 (2004-11-01), XP002692697,

Fortsættes ...

G. RICHTER ET AL: "Optimized Puncturing Distributions for long LDPC Codes and Different Channels", IEEE, 2006, XP002692817,
TIAN TAO ET AL: "Construction of Rate-Compatible LDPC Codes Utilizing Information Shortening and Parity Puncturing", EURASIP. JOURNAL ON WIRELESS COMMUNICATIONS AND NETWORKING, XX, XX, vol. 5, 1 January 2005 (2005-01-01), pages 789-795, XP002531349,
FEI ZESONG ET AL: "A Type-II Hybrid ARQ Scheme Based on Rate-compatible LDPC Code", COMMUNICATIONS, CIRCUITS AND SYSTEMS PROCEEDINGS, 2006 INTERNATIONAL CONFERENCE ON, IEEE, PI, 1 June 2006 (2006-06-01), pages 879-882, XP031010569, ISBN: 978-0-7803-9584-8
ANONYMOUS: "IEEE Standard for Local and metropolitan area networks Part 16: Air Interface for Fixed and Mobile Broadband Wireless Access Systems Amendment 2: Physical and Medium Access Control Layers for Combined Fixed and Mobile Operation in Licensed Bands and Corrigendum 1", INTERNET ARTICLE , 18 February 2006 (2006-02-18), XP002535900, Retrieved from the Internet:
URL:<http://standards.ieee.org/getieee802/download/802.16e-2005.pdf> [retrieved on 2009-07-08]

DESCRIPTION

Field of the Invention

[0001] The present invention relates generally to a communication system using Low-Density Parity-Check (LDPC) codes. More particularly, the present invention relates to a channel encoding/decoding method and apparatus for generating LDPC codes of a particular type.

Background to the Invention

[0002] In wireless communication systems, link performance significantly decreases due to various noises in channels, a fading phenomenon, and Inter-Symbol Interference (ISI). Therefore, in order to realize high-speed digital communication systems, which require high data throughput and reliability, such as the next-generation mobile communication, digital broadcasting, and portable internet, it is important to develop technology for overcoming the channel noises, fading, and ISI. Recently, an intensive study of an error-correcting code has been conducted as a method for increasing communication reliability by efficiently recovering distorted information.

[0003] An LDPC code is typically represented using a graph representation technique, and many characteristics can be analyzed through the methods based on graph theory, algebra, and probability theory. Generally, a graph model of channel codes is useful for description of codes, and by mapping information on encoded bits to vertexes in the graph and mapping relations between the bits to edges in the graph, it is possible to consider a communication network in which the vertexes exchange predetermined messages through the edges, thus making it possible to derive a natural decoding algorithm. For example, a decoding algorithm derived from a trellis, which can be regarded as a kind of graph, can include the well-known Viterbi algorithm and a Bahl, Cocke, Jelinek and Raviv (BCJR) algorithm.

[0004] The LDPC code is generally defined as a parity-check matrix, and can be expressed using a bipartite graph, which is referred to as a Tanner graph. The bipartite graph means that vertexes of the graph are divided into two different types, and the LDPC code is represented by the bipartite graph including vertexes, some of which are called variable nodes and the other of which are called check nodes. The variable nodes are one-to-one mapped to the encoded bits.

[0005] FIG. 1 illustrates an example of a parity-check matrix H_1 of the LDPC code including 4 rows and 8 columns. Referring to FIG. 1, because the number of columns is 8, the parity-check matrix H_1 indicates that an LDPC code that generates a length-8 codeword, and the columns are mapped to 8 encoded bits.

[0006] FIG. 2 is a diagram illustrating a Tanner graph corresponding to H_1 of FIG. 1.

[0007] Referring to FIG. 2, the Tanner graph of the LDPC code includes 8 variable nodes x_1 (202), x_2 (204), x_3 (206), x_4 (208), x_5 (210), x_6 (212), x_7 (214), and x_8 (216), and 4 check nodes 218, 220, 222, and 224. An i^{th} column and a j^{th} row in the parity-check matrix H_1 of the LDPC code are mapped to a variable node x_i and a j^{th} check node, respectively. In addition, a value of 1, i.e., a non-zero value, at the point where an i^{th} column and a j^{th} row in the parity-check matrix H_1 of the LDPC code cross each other, indicates that there is an edge between the variable node x_i and the j^{th} check node on the Tanner graph of FIG. 2.

[0008] In the Tanner graph of the LDPC code, a degree of the variable node and the check node indicates the number of edges connected to each respective node, and the degree is equal to the number of non-zero entries in a column or row corresponding to the associated node in the parity-check matrix of the LDPC code. For example, in FIG. 2, degrees of the variable nodes x_1 (202), x_2 (204), x_3 (206), x_4 (208), x_5 (210), x_6 (212), x_7 (214), and x_8 (216) are 4, 3, 3, 3, 2, 2, 2, and 2, respectively, and degrees of check nodes 218, 220, 222, and 224 are 6, 5, 5, and 5, respectively. In addition, the numbers of non-zero entries in the columns of the parity-check matrix H_1 of FIG. 1, which correspond to the variable nodes of FIG. 2, coincide with their degrees 4, 3, 3, 3, 2, 2, 2, and 2, and the numbers of non-zero entries in the rows of the parity-check matrix H_1 of FIG. 1, which correspond to the check nodes of FIG. 2, coincide with their degrees 6, 5, 5, and 5.

[0009] In order to express degree distribution for the nodes of the LDPC code, a ratio of the number of degree- i variable nodes to the total number of variable nodes is defined as f_i , and a ratio of the number of degree- j check nodes to the total number of check nodes is defined as g_j . For example, for the LDPC code corresponding to FIGs. 1 and 2, $f_2=4/8$, $f_3=3/8$, $f_4=1/8$, and $f_i=0$ for $i \neq 2, 3, 4$; and $g_5=3/4$, $g_6=1/4$, and $g_j=0$ for $j \neq 5, 6$. When a length of the LDPC code is defined as N , i.e., the number of columns is defined as N , and when the number of rows is defined as $N/2$, the density of non-zero entries in the entire parity-check matrix having the above degree distribution is computed as shown Equation (1).

$$\frac{2f_2N + 3f_3N + 4f_4N}{N \cdot N/2} = \frac{5.25}{N} \dots\dots\dots (1)$$

[0010] In Equation (1), as N increases, the density of 1's in the parity-check matrix decreases. Generally, as for the LDPC code, because the code length N is inversely proportional to the density of non-zero entries, the LDPC code with a large N has a very low density of non-zero entries. The term "low-density" in the name of the LDPC code originates from the above-mentioned relationship.

[0011] FIG. 3 schematically illustrates an LDPC code adopted as the standard technology in

Digital Video Broadcasting-Satellite transmission 2nd generation (DVB-S2), which is one of the European digital broadcasting standards.

[0012] In FIG. 3, N_1 denotes a length of an LDPC codeword, K_1 provides a length of an information word, and (N_1-K_1) provides a parity length. Further, integers M_1 and q are determined to satisfy $q=(N_1-K_1)/M_1$. Preferably, K_1/M_1 should also be an integer. For convenience, the parity-check matrix of FIG. 3 is called a first parity-check matrix H_1 .

[0013] Referring again to FIG. 3, a structure of a parity part, i.e., K_1^{th} column through $(N_1-1)^{\text{th}}$ column, in the parity-check matrix, has a dual diagonal shape. Therefore, as for degree distribution over columns corresponding to the parity part, all columns have a degree '2', except for the last column having a degree '1'.

[0014] In the parity-check matrix, a structure of an information part, i.e., 0^{th} column through $(K_1-1)^{\text{th}}$ column, is made using the following rules.

Rule 1: It generates a total of K_1/M_1 column groups by grouping K_1 columns corresponding to the information word in the parity-check matrix into multiple groups each including M_1 columns. A method for forming columns belonging to each column group follows Rule 2 below.

Rule 2: It first determines positions of '1's in each 0^{th} column in i^{th} column groups (where $i=1, \dots, K_1/M_1$). When a degree of a 0^{th} column in each i^{th} column group is denoted by D_i , if positions of rows with 1 are assumed to be

$$R_{i,0}^{(1)}, R_{i,0}^{(2)}, \dots, R_{i,0}^{(D_i)},$$

positions

$$R_{i,j}^{(k)} (k=1, 2, \dots, D_i)$$

of rows with 1 are defined as shown in Equation (2), in a j^{th} column (where $j=1, 2, \dots, M_1-1$) in an i^{th} column group.

$$R_{i,j}^{(k)} = R_{i,(j-1)}^{(k)} + q \bmod (N_1 - K_1), \quad \dots \dots \dots (2)$$

$$k=1, 2, \dots, D_i, \quad i=1, \dots, K_1/M_1, \quad j=1, \dots, M_1-1$$

[0015] According to the above rules, it can be appreciated that degrees of columns belonging to an i^{th} column group are all equal to D_i .

[0016] As a detailed example, for $N_1=30$, $K_1=15$, $M_1=5$, and $q=3$, three sequences for the information on the positions of rows with 1 for 0^{th} columns in 3 column groups can be expressed as follows. Herein, these sequences are called "weight-1 position sequences".

$$R_{1,0}^{(1)} = 0, \quad R_{1,0}^{(2)} = 1, \quad R_{1,0}^{(3)} = 2,$$

$$R_{2,0}^{(1)} = 1, \quad R_{2,0}^{(2)} = 2, \quad R_{2,0}^{(3)} = 3,$$

$$R_{2,0}^{(1)} = 0, R_{2,0}^{(2)} = 11, R_{2,0}^{(3)} = 13,$$

$$R_{3,0}^{(1)} = 0, R_{3,0}^{(2)} = 10, R_{3,0}^{(3)} = 14.$$

[0017] Regarding the weight-1 position sequence for 0th columns in each column group, only the corresponding position sequences can be expressed as follows for each column group. For example:

0 1 2

0 11 13

0 10 14.

[0018] In other words, the i^{th} weight-1 position sequence in the i^{th} line sequentially represents the information on the positions of rows with 1 for the i^{th} column group.

[0019] It is possible to generate an LDPC code having the same concept as that of a DVB-S2 LDPC code of FIG. 4, by forming a parity-check matrix using the information corresponding to the detailed example, and Rules 1 and 2.

[0020] It is known that the DVB-S2 LDPC code designed in accordance with Rule 1 and Rule 2 can be efficiently encoded using the structural shape. Respective steps in a process of performing LDPC encoding using the DVB-S2 based parity-check matrix will be described below by way of example.

[0021] In the following description, as a detailed example, a DVB-S2 LDPC code with $N_1=16200$, $K_1=10800$, $M_1=360$, and $q=15$ undergoes an encoding process. For convenience, information bits having a length K_1 are represented as $(i_0, i_1, \dots, i_{K_1-1})$, and parity bits having a length (N_1-K_1) are expressed as $(p_0, p_1, \dots, p_{N_1-K_1-1})$.

[0022] Step 1: An LDPC encoder initializes parity bits as follows:

$$p_0 = p_1 = \dots = p_{N_1-K_1-1} = 0$$

[0023] Step 2: The LDPC encoder reads information on a row where 1 is located in a column group from a 0th weight-1 position sequence out of the stored sequences indicating the parity-check matrix.

[0024] 0 2084 1613 1548 1286 1460 3196 4297 2481 3369 3451 4620 2622

$$R_{1,0}^{(1)} = 0, R_{1,0}^{(2)} = 2048, R_{1,0}^{(3)} = 1613, R_{1,0}^{(4)} = 1548, R_{1,0}^{(5)} = 1286,$$

$$R_{1,0}^{(6)} = 1460, R_{1,0}^{(7)} = 3196, R_{1,0}^{(8)} = 4297, R_{1,0}^{(9)} = 2481, R_{1,0}^{(10)} = 3369,$$

$$R_{1,0}^{(11)} = 3451, R_{1,0}^{(12)} = 4620, R_{1,0}^{(13)} = 2622.$$

[0025] The LDPC encoder updates particular parity bits p_x in accordance with Equation (3), using the read information and the first information bit i_0 . Herein, x is a value of

$$R_{1,0}^{(k)}$$

for $k = 1, 2, \dots, 13$.

$$\begin{aligned} p_0 &= p_0 \oplus i_0, & p_{2084} &= p_{2084} \oplus i_0, & p_{1613} &= p_{1613} \oplus i_0, \\ p_{1548} &= p_{1548} \oplus i_0, & p_{1286} &= p_{1286} \oplus i_0, & p_{1460} &= p_{1460} \oplus i_0, \\ p_{3196} &= p_{3196} \oplus i_0, & p_{4297} &= p_{4297} \oplus i_0, & p_{2481} &= p_{2481} \oplus i_0, & \dots \dots \dots (3) \\ p_{3369} &= p_{3369} \oplus i_0, & p_{3451} &= p_{3451} \oplus i_0, & p_{4620} &= p_{4620} \oplus i_0, \\ p_{2622} &= p_{2622} \oplus i_0 \end{aligned}$$

[0026] In Equation (3), $p_x = p_x \oplus i_0$ can also be expressed as $p_x \leftarrow p_x \oplus i_0$, and $\oplus$ represents binary addition.

[0027] Step 3: The LDPC encoder first finds out a value of Equation (4) for the next 359 information bits i_m (where $m=1, 2, \dots, 359$) after i_0 .

$$\{x + (m \bmod M_1) \times q\} \bmod (N_1 - K_1), \quad M_1 = 360, \quad m = 1, 2, \dots, 359 \quad \dots \dots \dots (4)$$

[0028] In Equation (4), x is a value of

$$R_{1,0}^{(k)}$$

for $k = 1, 2, \dots, 13$. It should be noted that Equation (4) has the same concept as Equation (2).

[0029] Next, the LDPC encoder performs an operation similar to Equation (3) using the value found in Equation (4). That is, the LDPC encoder updates $p_{\{x+(m \bmod M_1) \times q\} \bmod (N_1 - K_1)}$ for i_m . For example, for $m=1$, i.e., for i_1 , the LDPC encoder updates parity bits $p_{(x+q) \bmod (N_1 - K_1)}$ as defined in Equation (5).

$$\begin{aligned} p_{15} &= p_{15} \oplus i_1, & p_{2099} &= p_{2099} \oplus i_1, & p_{1628} &= p_{1628} \oplus i_1, \\ p_{1563} &= p_{1563} \oplus i_1, & p_{1301} &= p_{1301} \oplus i_1, & p_{1475} &= p_{1475} \oplus i_1, \\ p_{3211} &= p_{3211} \oplus i_1, & p_{4312} &= p_{4312} \oplus i_1, & p_{2496} &= p_{2496} \oplus i_1, & \dots \dots \dots (5) \\ p_{3384} &= p_{3384} \oplus i_1, & p_{3466} &= p_{3466} \oplus i_1, & p_{4635} &= p_{4635} \oplus i_1, \\ p_{2637} &= p_{2637} \oplus i_1 \end{aligned}$$

[0030] It should be noted that $q=15$ in Equation (5). The LDPC encoder performs the above process for $m=1, 2, \dots, 359$, in the same manner as shown above.

[0031] Step 4: As in Step 2, the LDPC encoder reads information of the 1st weight-1 position

sequence

$$R_{2,0}^{(k)} (k = 1, 2, \dots, 13)$$

for a 361st information bit i_{360} , and updates a particular p_x , where x is

$$R_{2,0}^{(k)}.$$

The LDPC encoder updates $p_{\{x+(m \bmod M1) \times q\} \bmod (N1-K1)}$, $m = 361, 362, \dots, 719$ by similarly applying Equation (4) to the next 359 information bits $i_{361}, i_{362}, \dots, i_{719}$ after i_{360} .

[0032] Step 5: The LDPC encoder repeats Steps 2, 3, and 4 for all groups each having 360 information bits.

[0033] Step 6: The LDPC encoder finally determines parity bits using Equation (6).

$$p_i = p_i \oplus p_{i-1}, \quad i = 1, 2, \dots, N_1 - K_1 - 1 \quad \dots \dots \dots (6)$$

[0034] The parity bits p_i of Equation (6) are parity bits that underwent LDPC encoding.

[0035] As described above, DVB-S2 performs encoding through the process of Step 1 through Step 6.

[0036] In order to apply the LDPC code to the actual communication system, the LDPC code should be designed to be suitable for the data rate required in the communication system. Particularly, not only in an adaptive communication system employing Hybrid Automatic Retransmission Request (HARQ) and Adaptive Modulation and Coding (AMC), but also in a communication system supporting various broadcast services, LDPC codes having various codeword lengths are needed to support various data rates according to the system requirements.

[0037] However, as described above, the LDPC code used in the DVB-S2 system has only two types of codeword lengths due to its limited use, and each type of the LDPC code needs an independent parity-check matrix. For these reasons, there is a long-felt need in the art for a method for supporting various codeword lengths to increase extendibility and flexibility of the system. Particularly, in the DVB-S2 system, transmission of data having several hundreds to thousands of bits is needed for transmission of signaling information. However, because only 16200 and 64800 are available for a length of the DVB-S2 LDPC code, there is a still a need for support of various codeword lengths.

[0038] In addition, because storing an independent parity-check matrix separately for each codeword length of the LDPC code reduces the overall memory efficiency, there is a demand for a scheme capable of efficiently supporting various codeword lengths from the given existing parity-check matrix, without designing a new parity-check matrix.

[0039] T. Tao et al, "Construction of Rate-Compatible LDPC Codes utilizing information shortening and parity puncturing", EURASIP Journal on Wireless Communications and

Networking 2005, pages 789-795, discloses a method for constructing rate-compatible low-density parity-check (LDPC) codes by a combination of information shortening and parity puncturing wherein density evolution is used to optimize node degree distribution for a given code rate.

[0040] WO 00/21234 discloses a method for transmitting punctured data wherein the positions of the punctured bits are equidistant throughout the frame and wherein those punctured positions are selected by dividing the number of bits in a frame by the number of bits to be punctured and selecting positions at integer values corresponding to the division.

[0041] Hagenauer J: "Rate-compatible punctured convolutional codes (rcpc codes) and their applications", IEEE transactions on communications, IEEE service center, Piscataway, NJ, USA, vol. 36, no. 4, 1 April 1988, pages 389-400, XP000670428, ISSN: 0090-6778, DOI: 10.1109/26.2763, discloses rate-compatible punctured convolutional codes which are punctured with period P.

[0042] Hossein Pishro-Nik and Faramarz Fekri, "Results on punctured LDPC codes" INFORMATION THEORY WORKSHOP, 2004. IEEE, 1 November 2004, XP-002692697, discloses a method for puncturing LDPC codes wherein the punctured positions are chosen by grouping first the variable nodes based on their grade and randomly puncturing a fraction of the variable nodes inside each group.

[0043] Jeongseok Ha and Steven W. McLaughlin, "Optimal Puncturing of Irregular Low-Density Parity-Check Codes" 2003, IEEE, pages 3110-3114, XP-002687857, discloses a rate compatible method of puncturing LDPC codes wherein variable nodes are grouped according with their degrees and a random proportion of bits in each group is punctured. Density Evolution is applied in order to calculate the optimal proportion.

SUMMARY OF THE INVENTION

[0044] It is an aim of certain embodiments of the invention to solve, mitigate or obviate, at least partly, at least one of the problems and/or disadvantages associated with the prior art.

[0045] Accordingly, the present invention has been designed to address at least the problems and/or disadvantages and to provide at least the advantages described below. An aspect of the present invention is to provide an encoding/decoding method and apparatus for generating LDPC codes having different codeword lengths from a given LDPC code, using puncturing in a communication system employing LDPC codes.

[0046] Another aspect of the present invention is to provide an encoding/decoding method and apparatus for guaranteeing the optimal performance with regard to DVB-S2 architecture in a communication system using LDPC codes.

[0047] In accordance with the present invention, there are provided a method and apparatus for encoding / decoding in a communication system using a Low-Density Parity-Check (LDPC) code as claimed in the independent claims.

[0048] Other aspects, advantages, and features of the invention will become apparent to those skilled in the art from the following detailed description, which, taken in conjunction with the annexed drawings, discloses exemplary embodiments of the invention.

BRIEF DESCRIPTION OF THE DRAWINGS

[0049] The above and other aspects, features, and advantages of the present invention will become more apparent from the following detailed description when taken in conjunction with the accompanying drawings in which:

FIG. 1 is a diagram illustrating an example of a parity-check matrix of a length-8 LDPC code;

FIG. 2 is a diagram illustrating a Tanner graph for an example of the parity-check matrix of the length-8 LDPC code;

FIG. 3 is a diagram schematically illustrating a structure of a DVB-S2 LDPC code;

FIG. 4 is a diagram illustrating an example of a parity-check matrix of a DVB-S2 LDPC code;

FIG. 5 is a block diagram illustrating a structure of a transceiver in a communication system using LDPC codes;

FIG. 6 is a diagram illustrating a first example where random puncturing is applied to the LDPC code of FIG. 4;

FIG. 7 is a diagram illustrating a second example where non-random puncturing is applied to the LDPC code of FIG. 4;

FIG. 8 is a diagram illustrating a third example where non-random puncturing is applied to the LDPC code of FIG. 4;

FIG. 9 is a flowchart illustrating a method for generating an LDPC code with a different codeword length from a parity-check matrix of a stored LDPC code according to an embodiment of the present invention;

FIG. 10 is a flowchart illustrating an LDPC decoding method in a reception apparatus when a puncturing pattern is applied, according to an embodiment of the present invention;

FIG. 11 is a block diagram illustrating a structure of a transmission apparatus that uses LDPC codes to which the puncturing and shortening proposed by the present invention is applied; and

FIG. 12 is a block diagram illustrating a structure of a reception apparatus that uses LDPC

codes to which the puncturing and shortening proposed by the present invention is applied.

[0050] Throughout the drawings, the same drawing reference numerals will be understood to refer to the same elements, features and structures.

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

[0051] Embodiments of the present invention will now be described in detail with reference to the annexed drawings. In the following description, a detailed description of known functions and configurations incorporated herein may have been omitted for clarity and conciseness when their inclusion might obscure appreciation of the invention by a person of ordinary skill in the art.

[0052] The embodiments of the present invention provide a method and apparatus for supporting LDPC codes having various codeword lengths using a parity-check matrix of a structured LDPC code of a particular type. In addition, the embodiments of the present invention provide an apparatus for supporting various codeword lengths in a communication system using LDPC codes of a particular type, and a method for controlling the same. Particularly, the embodiments of the present invention provide a method and apparatus for generating an LDPC code using a parity-check matrix of a given LDPC code, the generated LDPC code being shorter in length than the given LDPC code.

[0053] FIG. 5 is a block diagram illustrating a structure of a transceiver in a communication system using LDPC codes.

[0054] Referring to FIG. 5, a message u is input to an LDPC encoder 511 in a transmitter 510 before being transmitted to a receiver 530. The LDPC encoder 511 encodes the input message u , and outputs the encoded signal c to a modulator 513. The modulator 513 modulates the encoded signal c , and transmits the modulated signal s to the receiver 530 over a wireless channel 520. A demodulator 531 in the receiver 530 demodulates the received signal r , and outputs the demodulated signal x to an LDPC decoder 533. The LDPC decoder 533 estimates an estimation value u of the message based on the data received through the wireless channel 520.

[0055] The LDPC encoder 511 generates a parity-check matrix according to a codeword length required by a communication system, using a preset scheme. Particularly, in accordance with an embodiment of the present invention, the LDPC encoder 511 can support various codeword lengths using the LDPC code without the separate need for additional storage information.

[0056] In accordance with an embodiment of the present invention, a method of supporting

various codeword lengths uses a shortening technique and/or a puncturing technique. The term "puncturing technique" as used herein indicates a method that does not substantially transmit a specified part of an LDPC codeword after generating the LDPC codeword from a given particular parity-check matrix by performing LDPC encoding. Hence, a receiver determines that the non-transmitted part was erased.

[0057] For a better understanding of the puncturing technique, a parity-check matrix of the DVB-S2 LDPC code illustrated in FIGs. 3 and 4 will be described in more detail below.

[0058] Regarding the parity-check matrix of the DVB-S2 LDPC code illustrated in FIG. 3, its total length is N_1 , the leading part corresponds to length- K_1 information bits $(i_0, i_1, \dots, i_{K_1-1})$, and the rear part corresponds to length- (N_1-K_1) parity bits $(p_0, p_1, \dots, p_{N_1-K_1-1})$.

[0059] Generally, the puncturing technique can be applied to both the information bits and the parity bits. Although the puncturing technique and the shortening technique commonly reduce codeword lengths, the puncturing technique, unlike the shortening technique, described herein above, does not limit values of particular bits. The puncturing technique is a method for simply not transmitting particular information bits or a particular part of generated parity bits, so that a receiver can erase the corresponding bits. In other words, by simply not transmitting bits in N_p predefined positions in a generated length- N_1 LDPC codeword, the puncturing technique can obtain the same effect as that obtained by transmitting a length- (N_1-N_p) LDPC codeword. Because columns corresponding to the bits punctured in the parity-check matrix are all used intact in a decoding process, the puncturing technique is distinct from the shortening technique.

[0060] Further, according to the invention, because position information for the punctured bits can be shared or estimated in common by the transmitter and the receiver when the system is set up, the receiver may merely erase the corresponding punctured bits, before decoding.

[0061] In the puncturing technique, because a length of a codeword that the transmitter actually transmits is N_1-N_p and a length of an information word is constantly K_1 , the code rate becomes $K_1/(N_1-N_p)$, which is always greater than the first given code rate K_1/N_1 .

[0062] A description will now be made of a shortening technique and a puncturing technique suitable for the DVB-S2 LDPC code. The DVB-S2 LDPC code, as described above, is an LDPC code having a particular structure. Therefore, compared with the normal LDPC code, the DVB-S2 LDPC code is able to undergo more efficient shortening and puncturing.

[0063] For convenience of this example, it is assumed that a codeword length and an information length of an LDPC code are N_2 and K_2 , respectively. If a definition of $N_1-N_2=N_\Delta$ and $K_1-K_2=K_\Delta$ is given, it is possible to generate the LDPC code whose codeword length and information length are N_2 and K_2 , respectively, by shortening K_Δ bits and puncturing $N_p(=N_\Delta-K_\Delta)$ bits from the parity-check matrix of the DVB-S2 LDPC code. For the generated LDPC code

with $N_{\Delta} > 0$ or $K_{\Delta} > 0$, because its code rate

$$\frac{K_1 - K_{\Delta}}{N_1 - N_{\Delta}}$$

is generally different from the code rate K_1/N_1 of the DVB-S2 LDPC code, its algebraic characteristic changes. For $N_{\Delta} = K_{\Delta}$, the LDPC code is generated by not performing shortening and puncturing or by performing only shortening.

[0064] With reference to FIG. 4, a detailed description will be made of characteristics of a DVB-S2 LDPC code to which parity puncturing is applied. It is to be noted that for the DVB-S2 LDPC code of FIG. 4, $N_1=30$, $K_1=15$, $M_1=5$, and $q=3$, and a weight-1 position sequence for 0th columns in three column groups are as follows:

0 12

0 11 13

0 10 14

[0065] An i^{th} weight-1 position sequence in an i^{th} column sequentially represents the information on the positions of rows with 1 in an i^{th} column group.

[0066] FIG. 6 is a diagram illustrating a first example where random puncturing is applied to the LDPC code of FIG. 4. Because the parity bits punctured in FIG. 6 are subjected to erasure processing at a decoder, the punctured parity bits, compared with the other non-erased bits, are not greater in a performance improvement effect in an LDPC decoding process, causing a decrease in reliability. Consequently, the other bits directly connected to the punctured parity bits, which are low in reliability, also suffer from a decrease in the performance improvement effect in the decoding process. The decrease in the performance improvement effect is more significant as the number of edges directly connected to the bits punctured on the Tanner graph is greater.

[0067] In FIG. 6, for example, a 0th information bit corresponding to a 0th column is directly connected to the punctured parity bit twice, a 3rd information bit corresponding to a 3rd column is directly connected to the punctured parity bit once, and an 8th information bit corresponding to an 8th column is directly connected to the punctured parity bit three times. In this case, the 3rd, 0th, and 8th information bits are superior in the performance improvement effect in order in the decoding process. In other words, when the degrees of the variable nodes are equal to each other, the performance improvement effect is lower as the number of the connected punctured bits increases.

[0068] It can be appreciated from FIG. 6 that the number of punctured parity bits, which are

directly connected to each information word by the random puncturing pattern, is random. Therefore, there is a high probability that reliability of each information bit will also be random. In other words, while some information bits may gain higher-than-needed decoding performance, other information bits may suffer significant performance degradation. This random puncturing pattern may lead to considerable irregularity of the reliability of the information bits in the decoding process.

[0069] FIG. 7 is a diagram illustrating a second example where non-random puncturing is applied to the LDPC code of FIG. 4. More specifically, a relatively non-random puncturing pattern of a particular type is applied in the example illustrated in FIG. 7.

[0070] Referring to FIG. 7, even though the relatively non-random puncturing pattern is applied, the connections with the information bits may be irregular according to the corresponding puncturing pattern. The non-random puncturing pattern of FIG. 7 may be more irregular compared with the random puncturing pattern of FIG. 6.

[0071] In case of the LDPC code with a parity-check matrix having a particular structure like the DVB-S2 LDPC code, the connections between the information bits and the parity bits punctured according to the puncturing pattern can be significantly changed.

[0072] The embodiments of the present invention suggest a puncturing pattern that provides stable decoding performance by maximally suppressing the irregularity of the reliability of the information bits in the decoding process using the structural characteristics of the DVB-S2 LDPC code.

[0073] FIG. 8 is a diagram illustrating a third example where non-random puncturing is applied to the LDPC code of FIG. 4. In the example of FIG. 8, a puncturing pattern that maintains a constant interval of 3 between punctured parity bits because a value q is 3, which is one of the constituent variables, is applied to the parity-check matrix illustrated in FIG. 4. As can be seen in FIG. 8, each of all information bits is equally connected to 2 punctured bits.

[0074] The irregularity between the punctured bits and information bits is remarkably reduced when the interval between the punctured parity bits is set according to the value of q due to the structure of the DVB-S2 LDPC code. This is better described with reference to FIG. 3.

[0075] Referring to Rules 1 and 2 and FIG. 3, regarding each column group, positions of '1's in the first column in the corresponding column group determine positions of '1's in the remaining columns. Indexes of rows where 1 is located in the remaining columns differ exactly by a multiple of q from an index of a row where 1 is located in the first column, in regard to modulo $(N_1 - K_1)$, where N_1 denotes a length of an LDPC codeword and K_1 indicates a length of an information word. More specifically, indexes of rows where 1 is located in two consecutive columns in a particular column group differ from each other exactly by q , for modulo $(N_1 - K_1)$.

[0076] Another characteristic of the DVB-S2 LDPC code lies in a submatrix corresponding to

the parity in the parity-check matrix. Referring to FIG. 3, the parity part has a structure of a lower triangular matrix which 1 exists in all of diagonal parts, and in this structure, an i^{th} parity bit corresponds to '1' located in an i^{th} row.

[0077] Due to the structural characteristic of the DVB-S2 LDPC code, assuming that particular parity bits are punctured, if parity puncturing is repeated exactly at intervals of q , the number of edges of information bits connected to the parity bits punctured in a particular column group is regular to the utmost. For example, assuming that an i^{th} parity bit is punctured for $0 \leq i < q$ and an $(i+kq)^{\text{th}}$ parity bit is repeatedly punctured for $0 \leq k < M_1$, an information bit being connected to the i^{th} parity bit indicates that '1' exists in an i^{th} row for a column corresponding to the corresponding information bit. Therefore, it can be understood that '1' exists in the $(i+kq)^{\text{th}}$ row in a column corresponding to an information bit which is separated by k from the above information bit among the columns in a column group according to Rule 1 and Rule 2. As a result, the information bit is connected to the punctured $(i+kq)^{\text{th}}$ bit.

[0078] For the DVB-S2 LDPC code, because degrees of variable nodes corresponding to all information words are equal to each other in one column group and one and less of '1' is distributed in one row, when the puncturing pattern is applied, the information bits corresponding to one column group are connected to a same number of punctured bits. Therefore, the connections between the punctured bits and the information bits become regular, so that stabilized decoding can be expected in the decoding process.

[0079] A general process for the application of the above-described puncturing scheme can be summarized as follows. In the following summary, it is assumed that N_1 indicates a length of an LDPC codeword, each column group has M_1 columns, and N_p parity bits are subjected to puncturing. The following puncturing process is illustrated in FIG. 9.

[0080] More specifically, FIG. 9 is a flowchart illustrating a method for generating an LDPC code with a different codeword length from a parity-check matrix of a stored LDPC code according to an embodiment of the present invention.

[0081] Puncturing Step 1: A transmission apparatus generates, in step 901, an existing DVB-S2 LDPC codeword that has or has not undergone shortening.

[0082] Puncturing Step 2: The transmission apparatus determines a length N_p by which it will perform puncturing, in step 903, and calculates

$$A = \left\lfloor \frac{N_p}{M_1} \right\rfloor$$

in step 905, where $\lfloor x \rfloor$ is the maximum integer which is less than or equal to x .

[0083] Puncturing Step 3: The transmission apparatus determines parity bits $p_{i0}, p_{i1}, \dots, p_{iA-1}$

to be subjected to puncturing for $0 \leq x < A$ and $0 \leq i_x < q$ in step 907. It is assumed that for $0 \leq x < q$, values of i_x were previously determined considering the performance (herein, a relationship of $A \leq q$ is given).

[0084] Puncturing Step 4: The transmission apparatus applies puncturing to all parity bits $p_{i_x + kqB}$ for $0 \leq x < A$ and $0 \leq k < M_1$ in step 907. Here, the constant B is a preset non-zero integer.

[0085] Puncturing Step 5: The transmission apparatus additionally punctures the parity bits $p_{i_A + kqB}$ for $0 \leq k < N_p - AM_1$ in step 907. Thereafter, the transmission apparatus transmits bits except for the punctured bits in step 909.

[0086] It can be understood that in the puncturing process, AM_1 parity bits are punctured in Puncturing Step 3 and Puncturing Step 4, and $(N_p - AM_1)$ parity bits are punctured in Puncturing Step 5, resulting in a total of N_p parity bits being punctured. As to the DVB-S2 LDPC codeword transmitted after undergoing the puncturing, a reception apparatus restores a received signal to its original signal through a decoding process that will be described in more detail below referring to FIG. 10.

[0087] The following detailed example will be described for a better understanding of the puncturing process of Puncturing Step 3 through Puncturing Step 5. The DVB-S2 LDPC code used herein is a code with $N_1=16200$, $K_1=3240$, $M_1=360$, and $q=36$.

[0088] Example of Puncturing Step 1: A transmission apparatus generates the existing DVB-S2 LDPC codeword that has or has not undergone shortening.

[0089] Example of Puncturing Step 2: The transmission apparatus determines a length N_p by which it will perform puncturing, and calculates

$$A = \left\lfloor \frac{N_p}{M_1} \right\rfloor,$$

where $\lfloor x \rfloor$ is the maximum integer which is less than or equal to x .

[0090] Example of Puncturing Step 3: The transmission apparatus determines parity bits $p_{i_0}, p_{i_1}, \dots, p_{i_{A-1}}$ to be subjected to puncturing for $0 \leq x < A$ and $0 \leq i_x < 36$. For $0 \leq x < 36$, values of i_x are selected as follows using the connections between the punctured parity bits and the parity bits and the density evolution analysis method considering the case where the asymptotic performance is excellent.

27, 13, 29, 32, 5, 0, 11, 21, 33, 20, 25, 28, 18, 35, 8, 3, 9, 31, 22, 24, 7, 14, 17, 4, 2, 26, 16, 34, 19, 10, 12, 23, 1, 6, 30, 15

[0091] In the above sequence, an x^{th} weight-1 position sequence corresponds to a value of i_x for $0 \leq x < 36$.

[0092] Example of Puncturing Step 4: The transmission apparatus applies puncturing to all parity bits p_{i_x+36k} for $0 \leq x < A$ and $0 \leq k < 360$. Here, a value of B is set to 1.

[0093] Example of Puncturing Step 5: The transmission apparatus supplementally punctures parity bits p_{i_A+36k} for $0 \leq k < N_p-360 \cdot A$.

[0094] It can be understood from Examples of Puncturing Step 1 through Puncturing Step 5 that the puncturing pattern can be defined accurately when the number N_p of bits to be punctured, sequence information defining values of i_x , and a value of q are known.

[0095] When all parity bits of the DVB-S2 LDPC code applied to Examples of Puncturing Step 1 through Puncturing Step 5 are represented as $(p_0, p_1, p_2, \dots, p_{12959})$, the examples of the puncturing steps can be summarized as shown in Table 1.

Table 1

Major variables of DVB-S2 LDPC code		$N_1=16200, K_1=3240, M_1=360, q=36$						
Grouping of parity bits		Define a set P_j satisfying the following characteristics for $0 \leq j < q=36$:						
		$P_j=\{p_k \mid k \equiv j \bmod 36, 0 \leq k < 12960\}$.						
		The set P_j is a set having 360 parity bits as its entries.						
Range of N_p		Puncturing Method						
$0 \leq N_p < 12960$		For an integer $m = \left\lfloor \frac{N_p}{360} \right\rfloor$, puncture all of parity bits						
		corresponding to m parity bit sets $P_{\pi(0)}, P_{\pi(1)}, \dots, P_{\pi(m-1)}$, and additionally puncture (N_p-360m) parity bits among the parity bits corresponding to $P_{\pi(m)}$.						
		Here, π indicates a permutation function that is a puncturing pattern, and parity bits corresponding to parity bit sets are shown at the bottom of the table.						
$\pi(0)$	$\pi(1)$	$\pi(2)$	$\pi(3)$	$\pi(4)$	$\pi(5)$	$\pi(6)$	$\pi(7)$	$\pi(8)$
27	13	29	32	5	0	11	21	33
$\pi(9)$	$\pi(10)$	$\pi(11)$	$\pi(12)$	$\pi(13)$	$\pi(14)$	$\pi(15)$	$\pi(16)$	$\pi(17)$
20	25	28	18	35	8	3	9	31
$\pi(18)$	$\pi(19)$	$\pi(20)$	$\pi(21)$	$\pi(22)$	$\pi(23)$	$\pi(24)$	$\pi(25)$	$\pi(26)$
22	24	7	14	17	4	2	26	16

$\pi(27)$	$\pi(28)$	$\pi(29)$	$\pi(30)$	$\pi(31)$	$\pi(32)$	$\pi(33)$	$\pi(34)$	$\pi(35)$
34	19	10	12	23	1	6	30	15

[0096] As another embodiment of the puncturing steps, the puncturing pattern shown in Table 2 can be determined for a DVB-S2 LDPC code with $N_1=16200$, $K_1=7200$, $M_1=360$ and $q=25$.

Table 2

Major variables of DVB-S2 LDPC code		$N_1=16200, K_1=7200, M_1=360, q=25$						
Grouping of parity bits		Define a set P_j satisfying the following characteristics for $0 \leq j < q=25$:						
		$P_j=\{p_k \mid k \equiv j \bmod 25, 0 \leq k < 9000\}$.						
		The set P_j is a set having 360 parity bits as its entries.						
Range of N_p		Puncturing Method						
$0 \leq N_p < 9000$		For an integer $m = \left\lfloor \frac{N_p}{360} \right\rfloor$, puncture all of parity bits						
		corresponding to m parity bit sets $P_{\pi(0)}, P_{\pi(1)}, \dots, P_{\pi(m-1)}$, and additionally puncture (N_p-360m) parity bits among the parity bits corresponding to $P_{\pi(m)}$.						
		Here, π indicates a permutation function that is a puncturing pattern, and parity bits corresponding to parity bit sets are shown at the bottom of the table.						
$\pi(0)$	$\pi(1)$	$\pi(2)$	$\pi(3)$	$\pi(4)$	$\pi(5)$	$\pi(6)$	$\pi(7)$	$\pi(8)$
6	4	18	9	13	8	15	20	5
$\pi(9)$	$\pi(10)$	$\pi(11)$	$\pi(12)$	$\pi(13)$	$\pi(14)$	$\pi(15)$	$\pi(16)$	$\pi(17)$
17	2	24	10	22	12	3	16	23
$\pi(18)$	$\pi(19)$	$\pi(20)$	$\pi(21)$	$\pi(22)$	$\pi(23)$	$\pi(24)$	-	-
1	14	0	21	19	7	11	-	-

[0097] As described above, the embodiments of the present invention can apply the efficient puncturing technique capable of stabilizing performance of the DVB-S2 LDPC code using the structural characteristics of the DVB-S2 LDPC code, instead of applying an arbitrary puncturing technique or a simple regular puncturing technique that is commonly used for puncturing of the DVB-S2 LDPC code.

[0098] Referring again to a method for determining order of the bits punctured in Puncturing Step 3 for the DVB-S2 LDPC code, the method determines order of the punctured bits by using the density evolution analysis method and a cycle analysis method on the Tanner graph.

[0099] The puncturing technique contributes to an increased code rate because it changes a length of the LDPC codeword and also decreases the codeword length without changing a length of the information word. Therefore, the puncturing technique and also the shortening technique can be applied together to obtain the code rate and codeword length needed in the system.

[0100] As described above, when the codeword length and the information length of the LDPC code that the embodiments of the present invention intend to finally get from a given LDPC code with a codeword length N_1 and an information length K_1 using the shortening technique and the puncturing technique are denoted by N_2 and K_2 , respectively, if a definition of $N_1 - N_2 = N_\Delta$ and $K_1 - K_2 = K_\Delta$ is given, the LDPC code with the codeword length N_2 and the information length K_2 can be generated by shortening K_Δ bits and puncturing $N_p (= N_\Delta - K_\Delta)$ bits from a parity-check matrix of the LDPC code. For the generated LDPC code, puncturing and shortening lengths can be set considering N_2 and

$$\frac{K_1 - K_\Delta}{N_1 - N_\Delta},$$

because its code rate is

$$\frac{K_1 - K_\Delta}{N_1 - N_\Delta}$$

for $N_\Delta > 0$ or $K_\Delta > 0$.

[0101] FIG. 10 is a flowchart illustrating a reception method in a reception apparatus according to an embodiment of the present invention.

[0102] Referring to FIG. 10, the reception apparatus determines (or estimates) puncturing/shortening patterns from received signals in step 1001. Thereafter, the reception apparatus determines in step 1003 if there are any punctured or shortened bits.

[0103] If there are no punctured or shortened bits, the reception apparatus performs decoding in step 1009. However, if there are shortened or punctured bits, the reception apparatus delivers the puncturing/shortening patterns to an LDPC encoder 1160 in step 1005.

[0104] In step 1007, the LDPC encoder 1160 determines that punctured bits are erased bits and determines that probability that values of shortened bits will be zero (0) is 1. Thereafter, the LDPC encoder 1160 performs decoding.

[0105] A detailed example of a transmission apparatus for implementing the puncturing process of the DVB-S2 LDPC code is illustrated in FIG. 11. More specifically, FIG. 11 illustrates a block diagram of a structure of a transmission apparatus that uses punctured/shortened LDPC codes according to an embodiment of the present invention.

[0106] Referring to FIG. 11, a transmission apparatus includes a controller 1110, a shortening pattern applier 1120, an LDPC code parity-check matrix extractor 1140, an LDPC encoder 1160, and a puncturing pattern applier 1180.

[0107] The LDPC code parity-check matrix extractor 1140 extracts an LDPC code parity-check matrix that underwent shortening. The LDPC code parity-check matrix can be extracted using a memory, can be given in the transmission apparatus, or can be generated in the transmission apparatus.

[0108] The controller 1110 controls the shortening pattern applier 1120 to determine a shortening pattern according to an information length, and the shortening pattern applier 1120 inserts bits having a value of 0 in positions corresponding to the shortened bits, or removes columns corresponding to the shortened bits from a parity-check matrix of a given LDPC code. The shortening pattern can be a shortening pattern stored in a memory, generated using a sequence generator (not shown), or acquired using a density evolution analysis algorithm for a parity-check matrix and a given information length.

[0109] The LDPC encoder 1160 performs encoding based on the LDPC code that underwent shortening by the controller 1110 and the shortening pattern applier 1120.

[0110] The controller 1110 controls the puncturing pattern applier 1180. The puncturing pattern applier 1180 determines a number of parity bits to be subjected to puncturing, divides the parity bits at predetermined intervals to determine a number of puncturing bits, which are subjected to puncturing within the predetermined interval, determines positions of puncturing parity bits corresponding to the determined number of puncturing bits within the predetermined interval, and repeatedly performs puncturing on the puncturing parity bits corresponding to the determined positions at the predetermined intervals.

[0111] FIG. 12 is a block diagram illustrating a structure of a reception apparatus according to an embodiment of the present invention. More specifically, the reception apparatus illustrated in FIG. 12 receives signals transmitted from a communication system that uses DVB-S2 LDPC codes that underwent puncturing or shortening, and recovers the data the user wants, from the received signals.

[0112] Referring to FIG. 12, the reception apparatus includes a controller 1210, a shortening/puncturing pattern decision/estimation unit 1220, a demodulator 1230, and an LDPC decoder 1240.

[0113] The demodulator 1230 receives and demodulates an LDPC code that underwent shortening, and delivers the demodulated signal to the shortening/puncturing pattern decision/estimation unit 1220 and the LDPC decoder 1240.

[0114] The shortening/puncturing pattern decision/estimation unit 1220, under control of the

controller 1210, determines (or estimates) information about the puncturing or shortening pattern of an LDPC code from the demodulated signal, and delivers position information of the punctured and shortened bits to the LDPC decoder 1240. Determining or estimating the puncturing/shortening patterns in the shortening/puncturing pattern decision/estimation unit 1220 can use puncturing/shortening patterns stored in a memory, can generate puncturing/shortening patterns using a previously implemented generation method, or can obtain puncturing/shortening patterns using a density evolution analysis algorithm for a parity-check matrix and a given information length. The LDPC decoder 1240 performs erasure processing on the punctured bits and performs decoding thereon.

[0115] Further, when the transmission apparatus applies both shortening and puncturing, the shortening/puncturing pattern decision/estimation unit 1220 in the reception apparatus may carry out pattern determination or estimation on the shortening first, perform pattern determination or estimation on the puncturing first, or make pattern determination or estimation on both the shortening and puncturing.

[0116] The LDPC decoder 1240 performs decoding on the assumption that both the probability that the punctured bits would be zero (0) and the probability that the punctured bits would be 1 are equal to $1/2$. Because the probability that values of the shortened bits will be zero is 1 (i.e. 100%), the LDPC decoder 1240 determines whether or not it will allow the shortened bits to take part in its decoding operation depending on the value 1 of the probability that the shortened bits would be zero.

[0117] When the LDPC decoder 1240 gets information on a length of the DVB-S2 LDPC code shortened by the shortening/puncturing pattern decision/estimation unit 1220, it restores the user desired data from the received signals.

[0118] From the transmission apparatus illustrated in FIG. 11, it can be appreciated that the shortening is performed in the input stage of the LDPC encoder 1160 and the puncturing is performed at the output stage of the LDPC encoder 1160. However, in the reception apparatus illustrated in FIG. 12, the LDPC decoder 1240 should receive information on both the puncturing and the shortening to make the decoding possible.

[0119] As is apparent from the foregoing description, the embodiments of the present invention can generate a separate LDPC code with a different codeword length using information on the parity-check matrix given in the communication system that uses an LDPC code.

[0120] In addition, the embodiments of the present invention can optimize performance of the DVB-S2 LDPC code by employing puncturing.

[0121] It will be appreciated that embodiments of the present invention can be realized in the form of hardware, software or a combination of hardware and software. Any such software may be stored in the form of volatile or non-volatile storage such as, for example, a storage device like a ROM, whether erasable or rewritable or not, or in the form of memory such as, for

example, RAM, memory chips, device or integrated circuits or on an optically or magnetically readable medium such as, for example, a CD, DVD, magnetic disk or magnetic tape or the like. It will be appreciated that the storage devices and storage media are embodiments of machine-readable storage that are suitable for storing a program or programs comprising instructions that, when executed, implement embodiments of the present invention. Accordingly, embodiments provide a program comprising code for implementing a system or method as claimed in any one of the claims of this specification and a machine-readable storage storing such a program. Still further, such programs may be conveyed electronically via any medium such as a communication signal carried over a wired or wireless connection and embodiments suitably encompass the same.

[0122] Throughout the description and claims of this specification, the words "comprise" and "contain" and variations of the words, for example "comprising" and "comprises", means "including but not limited to", and is not intended to (and does not) exclude other moieties, additives, components, integers or steps.

[0123] Throughout the description and claims of this specification, the singular encompasses the plural unless the context otherwise requires. In particular, where the indefinite article is used, the specification is to be understood as contemplating plurality as well as singularity, unless the context requires otherwise.

[0124] Features, integers, characteristics, compounds, chemical moieties or groups described in conjunction with a particular aspect, embodiment or example of the invention are to be understood to be applicable to any other aspect, embodiment or example described herein unless incompatible therewith.

[0125] It will be also be appreciated that, throughout the description and claims of this specification, language in the general form of "X for Y" (where Y is some action, activity or step and X is some means for carrying out that action, activity or step) encompasses means X adapted or arranged specifically, but not exclusively, to do Y.

REFERENCES CITED IN THE DESCRIPTION

This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.

Patent documents cited in the description

- WO0021234A [0040]

Non-patent literature cited in the description

- **T. TAO et al.**Construction of Rate-Compatible LDPC Codes utilizing information shortening and parity puncturingEURASIP Journal on Wireless Communications and Networking, 2005, 789-795 [0039]
- Rate-compatible punctured convolutional codes (rcpc codes) and their applications**HAGENAUER** JIEEE transactions on communicationsIEEE service center19880401vol. 36, 389-400 [0041]
- Results on punctured LDPC codes**HOSSEIN PISHRO-NIKFARAMARZ FEKRI**INFORMATION THEORY WORKSHOPIEEE20041101 [0042]
- **JEONGSEOK HASTEVEN W. MCLAUGHLIN**Optimal Puncturing of Irregular Low-Density Parity-Check CodesIEEE200300003110-3114 [0043]

Patentkrav

1. Fremgangsmåde til punktering af mindst én paritetsbit i et lavdensitetsparitetskontrol (LDPC)-kodeord, ved hjælp af en sender i et udsendelsessystem, hvor LDPC-kodeordet opnås ved LDPC-kodning under anvendelse af en paritetskontrolmatrix, der har en forudbestemt struktur, hvilken struktur svarer til en, som er defineret i DVB-S2-standarden og har en længde på N_1 , en informationsdel med en informationslængde K_1 og en paritetsdel med en paritetslængde på $(N_1 - K_1)$, idet informationsdelen af paritetskontrolmatrixen har en struktur, der er defineret ved:

$$R_{i,j}^{(k)} = R_{i,(j-1)}^{(k)} + q \bmod (N_1 - K_1),$$

hvor:

$$k = 1, 2, \dots, D_i, i = 1, \dots, K_1/M_1, j = 1, \dots, M_1 - 1$$

i = indeks, der angiver den i 'te søjlegruppe,

j = indeks, der angiver den j 'te søjle i en søjlegruppe,

$$q = (N_1 - K_1)/M_1,$$

M_1 = antal søjler pr. søjlegruppe,

D_i = en grad, dvs. antal ikke-nul-poster, af en 0'te søjle i hver i 'te søjlegruppe,

$R_{i,0}^{(1)}, R_{i,0}^{(2)}, \dots, R_{i,0}^{(D_i)}$ = positioner af rækker med en værdi på 1 i en 0'te søjle i hver i 'te søjlegruppe, og

$R_{i,j}^{(k)} (k=1, 2, \dots, D_i)$ = positioner af rækker med en værdi på 1 i en j 'te søjle i en i 'te søjlegruppe,

hvor paritetsbits af LDPC-kodeordet opdeles i q paritetsbitsæt baseret på en følgende ligning:

$P_j=\{p_k \mid j \equiv k \bmod q, 0 \leq k < N_1 - K_1\}$

hvor

P_j repræsenterer et j'te paritetsbitsæt,

5 p_k repræsenterer en k'te paritetsbit, og

$0 \leq j < q,$

hvilken fremgangsmåde omfatter:

bestemmelse af et antal paritetsbits N_p , der skal punkteres,

10 bestemmelse af et antal m paritetsbitsæt, i hvilke alle paritetsbits punkteres, baseret på det antal paritetsbit, der skal punkteres, og

punktering af alle paritetsbits af m paritetsbitsæt $P_{\pi(0)}, P_{\pi(1)}, \dots, P_{\pi(m-1)}$ af q paritetsbitsæt P_j baseret på et punkteringsmønster, hvor punkteringsmønsteret bestemmes på basis af en kodehastighed K_1/N_1 af en LDPC-kode, der er tilknyttet paritetskontrolmatrixen og er tilknyttet indeks $\pi(0), \dots, \pi(m-1)$ svarende til m paritetsbitsæt $P_{\pi(0)}, P_{\pi(1)}, \dots, P_{\pi(m-1)}$,
15

hvor kodehastigheden $K_1/N_1 = 1/5$, $N_1 = 16200$, $K_1 = 3240$, $M_1 = 360$ og $q = 36$, og punkteringsmønsteret er defineret ved en følgende tabel,

$\pi(0)$	$\pi(1)$	$\pi(2)$	$\pi(3)$	$\pi(4)$	$\pi(5)$	$\pi(6)$	$\pi(7)$	$\pi(8)$
27	13	29	32	5	0	11	21	33
$\pi(9)$	$\pi(10)$	$\pi(11)$	$\pi(12)$	$\pi(13)$	$\pi(14)$	$\pi(15)$	$\pi(16)$	$\pi(17)$
20	25	28	18	35	8	3	9	31
$\pi(18)$	$\pi(19)$	$\pi(20)$	$\pi(21)$	$\pi(22)$	$\pi(23)$	$\pi(24)$	$\pi(25)$	$\pi(26)$
22	24	7	14	17	4	2	26	16
$\pi(27)$	$\pi(28)$	$\pi(29)$	$\pi(30)$	$\pi(31)$	$\pi(32)$	$\pi(33)$	$\pi(34)$	$\pi(35)$
34	19	10	12	23	1	6	30	15

2. Fremgangsmåde ifølge krav 1, der endvidere omfatter:

yderligere punktering af $(N_p - 360m)$ paritetsbits blandt paritetsbits svarende
 5 til $P_{\pi(m)}$ baseret på punkteringsmønsteret.

3. Apparat, der er indrettet til at punktere mindst én paritetsbit i et lavdensitets-
 paritetskontrol (LDPC)-kodeord, hvor LDPC-kodeordet opnås ved LDPC-kod-
 ning under anvendelse af en paritetskontrolmatrix, der har en forudbestemt
 10 struktur, hvilken struktur svarer til en, som er defineret i DVB-S2-standarden
 og har en længde på N_1 , en informationsdel med en informationslængde K_1 og
 en paritetsdel med en paritetslængde på $(N_1 - K_1)$,
 idet informationsdelen af paritetskontrolmatrixen har en struktur, der er define-
 ret ved:

15
$$R_{i,j}^{(k)} = R_{i,(j-1)}^{(k)} + q \bmod (N_1 - K_1),$$

hvor:

$$k = 1, 2, \dots, D_i, i = 1, \dots, K_1/M_1, j = 1, \dots, M_1 - 1$$

i = indeks, der angiver den i 'te søjlegruppe,

j = indeks, der angiver den j 'te søjle i en søjlegruppe,

20
$$q = (N_1 - K_1)/M_1,$$

M_1 = antal søjler pr. søjlegruppe,

D_i = en grad, dvs. antal ikke-nul-poster, af en 0'te søjle i hver i 'te søjle-
 gruppe,

25 $R_{i,0}^{(1)}, R_{i,0}^{(2)}, \dots, R_{i,0}^{(D_i)}$ = positioner af rækker med en værdi på 1 i en 0'te søjle i
 hver i 'te søjlegruppe, og

$R_{i,j}^{(k)} (k = 1, 2, \dots, D_i)$ = positioner af rækker med en værdi på 1 i en j 'te søjle i
 en i 'te søjlegruppe,

hvor paritetsbits af LDPC-kodeordet opdeles i q paritetsbitsæt baseret på en følgende ligning:

$$P_j=\{p_k \mid j \equiv k \bmod q, 0 \leq k < N_1 - K_1\}$$

hvor

5 P_j repræsenterer et j 'te paritetsbitsæt,

p_k repræsenterer en k 'te paritetsbit, og

$$0 \leq j < q,$$

idet apparatet omfatter: en punkteringsmønstreanvendelsesenhed, der er indrettet til at:

10 bestemme et antal paritetsbits N_p , der skal punkteres,

bestemme et antal m paritetsbitsæt, i hvilke alle paritetsbits punkteres, baseret på det antal paritetsbit, der skal punkteres, og

15 punktere alle paritetsbits af m paritetsbitsæt $P_{\pi(0)}, P_{\pi(1)}, \dots, P_{\pi(m-1)}$ af q paritetsbitsæt P_j baseret på et punkteringsmønster, hvor punkteringsmønstret bestemmes på basis af en kodehastighed K_1/N_1 af en LDPC-kode, der er tilknyttet paritetskontrolmatrixen og er tilknyttet indeks $\pi(0), \dots, \pi(m-1)$ svarende til m paritetsbitsæt $P_{\pi(0)}, P_{\pi(1)}, \dots, P_{\pi(m-1)}$,

hvor kodehastigheden $K_1/N_1 = 1/5$, $N_1 = 16200$, $K_1 = 3240$, $M_1 = 360$ og $q = 36$, og punkteringsmønstret er defineret ved en følgende tabel,

$\pi(0)$	$\pi(1)$	$\pi(2)$	$\pi(3)$	$\pi(4)$	$\pi(5)$	$\pi(6)$	$\pi(7)$	$\pi(8)$
27	13	29	32	5	0	11	21	33
$\pi(9)$	$\pi(10)$	$\pi(11)$	$\pi(12)$	$\pi(13)$	$\pi(14)$	$\pi(15)$	$\pi(16)$	$\pi(17)$
20	25	28	18	35	8	3	9	31
$\pi(18)$	$\pi(19)$	$\pi(20)$	$\pi(21)$	$\pi(22)$	$\pi(23)$	$\pi(24)$	$\pi(25)$	$\pi(26)$
22	24	7	14	17	4	2	26	16
$\pi(27)$	$\pi(28)$	$\pi(29)$	$\pi(30)$	$\pi(31)$	$\pi(32)$	$\pi(33)$	$\pi(34)$	$\pi(35)$

$\pi(18)$	$\pi(19)$	$\pi(20)$	$\pi(21)$	$\pi(22)$	$\pi(23)$	$\pi(24)$	$\pi(25)$	$\pi(26)$
34	19	10	12	23	1	6	30	15

4. Apparat ifølge krav 3, der endvidere omfatter:
at punkteringsmønstreanvendelsesenheden endvidere punkterer (N_p -
5 360m) paritetsbits blandt paritetsbits svarende til $P_{\pi(m)}$ baseret på punkterings-
mønstret.

5. Apparat, der er indrettet til at dekode data i et udsendelsessystem, hvilket
apparat omfatter:

10 en demodulator, der er indrettet til at demodulere et modtaget signal,
hvilket signal indbefatter data af et lavdensitetsparitetskontrol (LDPC)-
kodeord, hvor LDPC-kodeordet opnås ved LDPC-kodning under anven-
delse af en paritetskontrolmatrix, der har en forudbestemt struktur, hvil-
ken struktur svarer til en, som er defineret i DVB-S2-standarden og har
15 en længde på N_1 , en informationsdel med en informationslængde K_1 og
en paritetsdel med en paritetslængde på (N_1-K_1) ,

idet informationsdelen af paritetskontrolmatrixen har en struktur, der er
defineret ved:

$$R_{i,j}^{(k)} = R_{i,(j-1)}^{(k)} + q \bmod (N_1 - K_1),$$

20 hvor:

$$k = 1, 2, \dots, D_i, i = 1, \dots, K_1/M_1, j = 1, \dots, M_1-1$$

i = indeks, der angiver den i 'te søjlegruppe,

j = indeks, der angiver den j 'te søjle i en søjlegruppe,

$$q = (N_1-K_1)/M_1,$$

25 M_1 = antal søjler pr. søjlegruppe,

D_i = en grad, dvs. antal ikke-nul-poster, af en 0'te søjle i hver i'te søjlegruppe,

$R_{i,0}^{(1)}, R_{i,0}^{(2)}, \dots, R_{i,0}^{(D_i)}$ = positioner af rækker med en værdi på 1 i en 0'te søjle i hver i'te søjlegruppe, og

5 $R_{i,j}^{(k)} (k=1,2,\dots,D_i)$ = positioner af rækker med en værdi på 1 i en j'te søjle i en i'te søjlegruppe,

en punkteringsmønsterbeslutningsenhed, der er indrettet til at:

bestemme et punkteringsmønster ud fra det demodulerede signal, og

10 bestemme positionsinformation for punkterede paritetsbits baseret på punkteringsmønsteret, og

en LDPC-dekoder, der er indrettet til at LDPC-dekode data i det demodulerede signal baseret på positionsinformationen,

kendetegnet ved, at

15 punkteringsmønsteret bestemmes på basis af en kodehastighed K_1/N_1 for en LDPC-kode, der er tilknyttet paritetskontrolmatrixen,

positionsinformationen for de punkterede paritetsbits er knyttet til m paritetsbitsæt af q paritetsbitsæt,

hvor de q paritetsbitsæt er defineret ved:

$$P_j = \{p_k \mid j \equiv k \bmod q, 0 \leq k < N_1 - K_1\}$$

20 hvor

P_j betegner et j'te paritetsbitsæt,

p_k betegner en k'te paritetsbit, og

$$0 \leq j < q,$$

hvor punkteringsmønsteret er tilknyttet indekser $\pi(0), \dots, \pi(m-1)$ svarende til m paritetsbitsæt $P_{\pi(0)}, P_{\pi(1)}, \dots, P_{\pi(m-1)}$, i hvilke alle paritetsbits punkteres, hvor

$m = \left\lfloor \frac{N_p}{360} \right\rfloor$, idet N_p er et antal punkterede paritetsbits,

hvor kodehastigheden $K_1/N_1 = 1/5$, $N_1 = 16200$, $K_1 = 3240$, $M_1 = 360$ og $q = 36$, og punkteringsmønsteret er defineret ved en følgende tabel,

$\pi(0)$	$\pi(1)$	$\pi(2)$	$\pi(3)$	$\pi(4)$	$\pi(5)$	$\pi(6)$	$\pi(7)$	$\pi(8)$
27	13	29	32	5	0	11	21	33
$\pi(9)$	$\pi(10)$	$\pi(11)$	$\pi(12)$	$\pi(13)$	$\pi(14)$	$\pi(15)$	$\pi(16)$	$\pi(17)$
20	25	28	18	35	8	3	9	31
$\pi(18)$	$\pi(19)$	$\pi(20)$	$\pi(21)$	$\pi(22)$	$\pi(23)$	$\pi(24)$	$\pi(25)$	$\pi(26)$
22	24	7	14	17	4	2	26	16
$\pi(27)$	$\pi(28)$	$\pi(29)$	$\pi(30)$	$\pi(31)$	$\pi(32)$	$\pi(33)$	$\pi(34)$	$\pi(35)$
34	19	10	12	23	1	6	30	15

6. Apparat ifølge krav 5, hvor indekset $\pi(m)$ svarer til $P_{\pi(m)}$, i hvilket $(N_p - 360m)$ paritetsbits endvidere punkteres.

DRAWINGS

$$H_1 = \begin{bmatrix} 1 & 1 & 1 & 1 & 1 & 1 & 0 & 0 \\ 1 & 1 & 0 & 1 & 0 & 1 & 1 & 0 \\ 1 & 1 & 1 & 0 & 0 & 0 & 1 & 1 \\ 1 & 0 & 1 & 1 & 1 & 0 & 0 & 1 \end{bmatrix}$$

FIG.1




FIG.2




FIG.3




FIG.4




FIG.5




FIG.6




FIG. 7




FIG.8




FIG.9




FIG.10




FIG.11




FIG.12