




- (51) **International Patent Classification:**
H03H 11/12 (2006.01) *H03M 3/02* (2006.01)
- (21) **International Application Number:**
PCT/EP2017/050231
- (22) **International Filing Date:**
5 January 2017 (05.01.2017)
- (25) **Filing Language:** English
- (26) **Publication Language:** English
- (30) **Priority Data:**
16151107.6 13 January 2016 (13.01.2016) EP
- (71) **Applicant:** UNIVERSITÄT ZÜRICH [CH/CH]; Prorekt-
orat MNW, Rämistrasse 71, CH-8006 Zürich (CH).
- (72) **Inventors:** YANG, Minhao; 400 West 119th Street #8U,
New York, New York 10027 (US). LIU, Shih-Chii;
Winkelriedstrasse 34, CH-8006 Zürich (CH).
- (74) **Agent:** VESTERINEN, Jussi; Veni LLC, Villa de Meur-
on, Buristrasse 21, 3006 Bern (CH).
- (81) **Designated States** (unless otherwise indicated, for every
kind of national protection available): AE, AG, AL, AM,
AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY,
BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DJ, DK, DM,

DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT,
HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KH, KN,
KP, KR, KW, KZ, LA, LC, LK, LR, LS, LU, LY, MA,
MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG,
NI, NO, NZ, OM, PA, PE, PG, PH, PL, PT, QA, RO, RS,
RU, RW, SA, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY,
TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN,
ZA, ZM, ZW.

- (84) **Designated States** (unless otherwise indicated, for every
kind of regional protection available): ARIPO (BW, GH,
GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ,
TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU,
TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE,
DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU,
LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK,
SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ,
GW, KM, ML, MR, NE, SN, TD, TG).

Published:

- with international search report (Art. 21(3))
- before the expiration of the time limit for amending the
claims and to be republished in the event of receipt of
amendments (Rule 48.2(h))

(54) **Title:** BAND-PASS FILTER**Fig. 3**

(57) **Abstract:** A band-pass filter (13) is described comprising a first first-order filter stage comprising a first resistor (R1) characterised by a first impedance and connected to a first node (25), referred to as a filter input node, and, through a second node (27) to a first reactive component (C1) connected to a third node (29), the first impedance being such that a first current therethrough is dependent on the difference between the voltages at the first and second nodes (25, 27); and a second first-order filter stage comprising a second resistor (R2*) characterised by a second impedance and connected to the second node (27), and, through a fourth node (31), to a second reactive component (C2) connected to a fifth node (33). The second impedance (R2) is such that a second current therethrough is dependent on the negative of the sum of the voltages at the second and fourth nodes (27, 31). The band-pass filter (13) further comprises summing means (23) for summing the voltages at the second and fourth nodes (27, 31) to output a voltage at a sixth node (35).

Band-pass filter

TECHNICAL FIELD

The present invention relates to band-pass filter (BPF) designs to be used for example in artificial cochlea systems. The invention also relates to a data
5 processing apparatus comprising the BPF and to a method of operating the data processing apparatus.

BACKGROUND OF THE INVENTION

Filter circuits are well known, and various different configurations are known which provide different frequency responses. Generally, a filter circuit can be
10 categorised as any of a low-pass by which low frequency signals are passed, high-pass by which high frequency signals are passed, band-pass by which only signals within a certain frequency band are passed, or band-stop by which only signal frequencies outside a particular band are passed. Furthermore, within these classifications various other classifications can be made dependent upon the precise
15 filter response, for example Butterworth, Chebyshev, Bessel, or the like. Such filters may be passive filters, which means that the components have no amplifying/active (either voltage or current) elements therein, or active filters, which usually comprise one or more transistors provided with a power supply to act as an active element. Various different transistor circuits are known in the art, one of which is the source
20 follower circuit (equivalent to an emitter follower, or common collector circuit when using bipolar junction transistors). The source follower is a known basic building block for micro electronics designs, and exhibits excellent linearity. Due to this high linearity it has been proposed previously that the source follower circuit can be the basis of a high-linearity and low-power analogue filter.

25 Power consumption is an important factor to be considered when designing filter circuits. US8710921 discloses an example of a power-efficient and stable higher order low-pass filter. However, designing band-pass filters is typically more complex and there is currently a need for band-pass filters which have a very low power consumption, yet are stable and have a simple design.

30 Band-pass filters are used in various systems and fields. One such field, which is currently widely investigated, is artificial or silicon cochlea. Because human brains can process information more efficiently both in terms of power and latency even under uncontrolled conditions, increasing academic and industrial players are

investigating brain-like event-driven computing methods in an attempt to mimick the brain's capability. Artificial spiking sensors such as silicon retinas and cochleas naturally provide asynchronous event-driven outputs in response to changes in the environment and are therefore a source of sensory input to processors like silicon neural networks for real-time event-driven intelligent processing. The silicon cochlea, in particular, sees wide applications in auditory sensing applications such as mobile speech control and ambient assisted living, where chip power is the major concern. To directly utilise the energy harvested from environment for powering the chip, a low power supply is also preferred.

Figure 1 is a simplified block diagram illustrating an example of a prior art silicon cochlea system 1. In this example the on-chip silicon cochlea comprises a core 2 powered by a power source (not shown), in this example a voltage source of 0.5 V, and a 1.8 V address event representation (AER) circuitry 3, which is a protocol for asynchronously sending generated spikes off-chip. The core further comprises binaural parallel channels 5, in this example 64 channels, and a current bias generator (CBG) 7 to provide 64 geometrically scaled currents to the corresponding channels, so that the characteristic central frequencies of the channels are geometrically scaled from 20 Hz to 20 kHz, covering the frequency range of human hearing. It is to be noted that in some cases optional gain amplifiers 9 could be included on-chip. In one channel, as shown in Figure 2, there are left and right sub-channels receiving the audio signals from left and right microphones 10 but in general, the input signals to the sub-channels could come from other sources such as antennas or electrodes. A translinear loop (TLL) 11 is provided for quality factor (Q factor) tuning of bandpass filters. The TLL 11 is shared by the left and right sub-channels. The TLL 11, having a channel biasing functionality integrated with it, distributes all the current biases needed for the circuit blocks in one channel, which include two band-pass filters (BPFs) 13, two asynchronous delta modulators (ADMs) 15 used for analogue-to-spike conversion, and two asynchronous logic (AL) units 17, which generate control signals for the ADMs and communicate with the peripheral AER circuits. The generated spikes from all the channels are transmitted off-chip by the 1.8 V AER circuitry 3. Before the BPFs, there are programmable attenuators (PAs) 19 for attenuating large input signals.

The existing methods of building analogue band-pass filters eg in artificial cochlea systems are: active resistor-capacitor (active RC) filters, filters using operational transconductance amplifiers (OTAs) and more specifically OTA-capacitor (OTA-C), switched-capacitor, N-path and source-follower-based filters. The switched-

capacitor and N-path filter types are not suitable in the case of a band-pass filter bank (as used eg in artificial cochlea systems) because the central frequency is dependent on the clock frequency, which is difficult to scale with a very small scaling ratio. The active RC type is also not suitable because, for a low central frequency (in the range of kHz and below), very large and thus area-consuming resistors and capacitors are required. The source-follower-based low-pass filter has been proven to be more power-efficient than the OTA-C low-pass filter, and therefore the source-follower-based topology has been chosen to construct the BPFs used in ultra-low-power silicon cochlea systems. Currently known source-follower-based BPFs have some limitations, as explained below. For example, some BPFs have a large pass-band gain loss when two or more same unit building blocks are cascaded for high-order filters. Some other BPFs have a band-pass transfer function which is highly sensitive to input common-mode voltage, while yet other BPFs are incapable of achieving high Q values, ie quality factors larger than 0.5. Furthermore, currently known cochlea systems have relatively high power consumption.

There is thus a need for a BPF that can be used in artificial cochlea systems for example and which does not have the drawbacks mentioned above.

SUMMARY OF THE INVENTION

According to a first aspect of the invention, there is provided a band-pass filter as recited in claim 1.

The proposed band-pass filter has a simple design, yet is stable and more power-efficient than many other filter topologies, such as active RC, gm-C etc. The proposed filter can be used in various applications, such as artificial cochlea systems, wireless transceivers, analogue-to-information converters etc.

According to a second aspect of the invention, there is provided a data processing apparatus comprising the band-pass filter according to the first aspect.

According to a third aspect of the invention, there is provided a method of operating the data processing apparatus according to the second aspect.

Other aspects of the invention are recited in the dependent claims attached hereto.

BRIEF DESCRIPTION OF THE DRAWINGS

Other features and advantages of the invention will become apparent from the following description of a non-limiting exemplary embodiment, with reference to the appended drawings, in which:

- 5 • Figure 1 is a simplified block diagram of a prior art artificial cochlea system;
- Figure 2 is a simplified block diagram of one channel of the cochlea system of Figure 1;
- Figure 3 is a circuit diagram of a band-pass filter according to an
10 embodiment of the present invention;
- Figure 4 is a circuit diagram of an implementation example of the circuit of Figure 3;
- Figure 5 is a circuit diagram of a band-pass filter where multiple filter stages are cascaded to form a higher order band-pass filter;
- 15 • Figure 6 is a circuit diagram of an exemplary summing circuit which can be used in the circuit of Figure 5;
- Figure 7 is a circuit diagram of an exemplary asynchronous delta modulator, which can be used in the circuit of Figure 2; and
- 20 • Figure 8 is a time domain signal diagram showing some of the signals present in the circuit of Figure 7.

DETAILED DESCRIPTION OF AN EMBODIMENT OF THE INVENTION

An embodiment of the present invention will now be described in detail with reference to the attached figures. The invention will be described in the context of a silicon cochlea system. However, the teachings of the invention are not limited to
25 use in artificial sensory systems, such as cochlea systems. The teachings of the present invention can also be applied to wireless transceivers, asynchronous data converters, other suitable clockless systems etc. Identical or corresponding functional and structural elements which appear in different drawings are assigned the same reference numerals.

Figure 3 is a circuit diagram of a band-pass filter (BPF) 13 according to an embodiment of the present invention. This kind of BPF 13 may be used for example in the cochlea system of Figure 1. More specifically, the proposed BPF 13 may be used to implement the filtering element 13 in Figure 2. Turning back to Figure 3, the proposed BPF 13 comprises a low-pass filter (LPF) 21 and summation means 23. The LPF 21 comprises a first first-order filter stage comprising a first resistor R1 characterised by a first impedance R_1 . The first resistor R1 is connected to a first node 25, referred to as a filter input node, and, through a second node 27, to a first reactive component C1, in this example a first capacitor C1, characterised by a first capacitance C_1 . The first capacitor C1 is connected to a third node 29, which in this example is directly connected to ground. The first resistor R1 is such that a first current I_1 through it (flowing from the first node 25 to the second node 27 in the diagram) is dependent on the difference between voltages at the first and second nodes:

$$I_1 = \frac{V_{in} - V_a}{R_1}, \quad (1)$$

where V_{in} is the voltage value at the first node 25, while V_a is the voltage value at the second node 27.

The LPF 21 also comprises a second first-order filter stage comprising a second resistor R_2^* characterised by a second impedance R_2^* connected to the second node 27, and, through a fourth node 31, to a second reactive component C2, in this example a second capacitor C2 characterised by a second capacitance C_2 . The second capacitor C2 is connected to a fifth node 33. In this example the fifth node 33 is directly connected to ground. The second resistor R_2^* is such that a second current I_2 through it (from the second node 27 to the fourth node 31 in the diagram) is dependent on the negative of the sum of the voltages at the second and fourth nodes:

$$I_2 = -\frac{V_a + V_b}{R_2^*}, \quad (2)$$

where V_b is the voltage at the fourth node 31.

It is to be noted that the second resistor R_2^* is not standard. The current flowing through the second impedance R_2^* is dependent on the sum of the input and output voltages, rather than on their difference, as in a standard ohmic impedance. The second impedance is a negative impedance. The first and second first-order filter stages together form the second order LPF 21.

As is shown in Figure 3, the BPF 13 also comprises the summation means 23 for summing the voltages V_a , V_b at second and fourth nodes 27, 31 to output a

voltage at a sixth node 35. In this way a BPF can be obtained which has a simple structure and consumes very little power. As mentioned above, the proposed BPF 13 can for example be used in the cochlea system of Figure 1. The band-pass transfer function of the RC circuit is

$$\frac{V_{out}(s)}{V_{in}(s)} = \frac{\frac{C_2}{g_m} s}{\frac{C_1 C_2}{g_m^2} s^2 + \left(\frac{C_2}{g_{m2}} + \frac{C_1}{g_{m1}} - \frac{C_2}{g_{m1}} \right) s + 1}, \quad (3)$$

- 5 where g_{m1} and g_{m2} are the reciprocals, ie transconductances, of R_1 and R_2^* respectively. The central frequency f_0 and the quality factor Q of the BPF 13 are expressed as

$$f_0 = \frac{1}{2\pi} \sqrt{\frac{g_{m1} g_{m2}}{C_1 C_2}}, Q = \frac{\sqrt{\frac{g_{m1} g_{m2}}{C_1 C_2}}}{\frac{g_{m1}}{C_1} + \frac{g_{m2}}{C_2} - \frac{g_{m2}}{C_1}} \quad (4)$$

- The circuit diagram of Figure 4 illustrates one exemplary implementation of the RC circuit of Figure 3 by using a source-follower-based transistor circuit. As shown, this circuit illustration is a differential circuit. This means that there are two input nodes 25 so that the input signals at each of these nodes have a phase difference of 180 degrees. In the same manner there are two output nodes 35 so that the output signals at each of these nodes have a phase difference of 180 degrees. The illustrated circuit comprises four transistors, namely two n-type metal-oxide-
10 semiconductor field-effect transistors (MOSFETs) M1, M3 and two p-type MOSFETs M2, M4. This exemplary circuit further comprises six current sources, of which two current sources I_{2U} are directly connected to a power supply VDD, in this example a power rail, while four other current sources I_1 , I_{2D} are connected to ground. It is to be noted that the circuit illustrated in Figure 4 is just one of many possible ways of
15 implementing the RC circuit of Figure 3.
20

- It is possible to cascade any number of the LPFs 21 to obtain a higher order LPF 21. For example, by cascading two of the LPFs shown in Figures 3 or 4, a 4th order LPF is obtained. A 4th order asymmetrical BPF 13 is then obtained by summing V_a and V_b in the 2nd LPF. Figure 5 shows an example of the BPF 13, where
25 N 2nd order filter stages are cascaded. An exemplary summation circuit is illustrated in Figure 6. This summation circuit can be used in the circuit illustrated in Figure 5. It is to be noted that the summation means can be any suitable element arranged to perform a voltage summing operation. The summing means 23 could also be for

instance a programmable gain amplifier (PGA), such as a capacitive adding amplifier with programmable gain. In this case a series of LPFs 21 would be cascaded and the PGAs' inputs would all come from the last filter stage. Thus, the BPF 13 would be composed of a series of N LPFs (eg source-follower-based) and a PGA.

5 Currently known source-follower-based low-pass and band-pass filters generally have very low quality factors Q, ie less than 2. A band-pass filter bank with large quality factors is useful for distinctive frequency-related feature extraction. For large quality factors, eg $Q > 10$, the ratio of C_2/C_1 needs to be appropriately chosen to reduce variations in the central frequencies and quality factors between different BPFs
10 13. This is for example important for mitigating calibration overhead. It is to be noted that the variation of central frequency and Q can be compensated by manual calibration or on-chip automatic calibration with additional calibration circuits in the design. But in both cases, the calibration effort imposes extra labour or chip cost, and should therefore be avoided if possible. Thus, it is more cost-efficient to control the
15 variation in the central frequency and Q by design rather than by calibration. Assuming g_m is proportional to current in subthreshold operation of transistors, the method of determining the appropriate C_2/C_1 is summarised in the equation below:

$$\frac{Q + \sqrt{Q^2 + 4S_0^2 - 1}}{2S_0 + 1} \leq n \leq \sqrt{\frac{t_{ol}^2 + 2t_{ol}}{m_{is}}}, \quad (5)$$

where n is the square root of g_{m2}/g_{m1} , t_{ol} is the relative variation of the central frequency f_0 (ie f_0 becomes $t_{ol}\%$ larger or $t_{ol}\%$ smaller) caused by m_{is} , which is the
20 mismatch between the upper I_{2U} and lower current sources I_{2D} (ie the current value of I_{2U} is $m_{is}\%$ larger or smaller than the current value of I_{2D}) (see Figure 4 showing the upper and lower current sources) defining R_2^* , and S_0 is the relative sensitivity of Q to g_{m2}/g_{m1} (ie, a 1% of variation in g_{m2}/g_{m1} results in a $S_0\%$ variation in Q). The ratio C_2/C_1 can be calculated from the quality factor formula in (4) once n is determined according
25 to (5).

The above BPF 13 according to an embodiment of the present invention was described in the context of the cochlea system. The proposed cochlea system enables a wide input dynamic range and consumes ultra-low power with a low supply voltage, making it possible to power the sensor with compact integrated energy
30 harvesters. Next, further features of the present invention will be discussed, also in the context of the cochlea system.

Data converters, particularly analogue-to-digital or analogue-to-spike converters as used for example in cochlea systems can be divided into two categories: clocked and clockless. The industrial mainstream is currently the clocked type, and the clockless type is mostly still under research. Clockless converters have several advantages over clocked converters, such as a complete absence of aliasing without any anti-aliasing filters, input-activity-dependent power consumption in subsequent processing stages etc.

Both types of converters use comparators. In clocked converters, latched comparators are exclusively used nowadays instead of continuous-time comparators. Latched comparators normally use a regenerative latch with positive feedback, and require a clock signal to reset the latch after each comparison. Continuous-time comparators are normally open-loop, multi-stage amplifiers. Latched comparators are faster in comparison and more power-efficient than continuous-time comparators. However, in clockless converters, latched comparators are not readily used because of the lack of any clock. To date, the comparators used in clockless systems in literature all belong to the continuous-time type.

According to the present invention, it is proposed to exploit the benefit of latched comparators in clockless converters by forming a self-oscillation loop to generate the pseudo-clock signal, and the frequency may be adaptive to the output rate of the converters. Taking the ADM 15, also referred to as a modulator circuit, as an example where two comparators are needed for comparison with an upper and a lower threshold voltage, the principle is illustrated in Figure 7 and the exemplary timing diagram of some of the circuit signals is illustrated in Figure 8. According to this example, the self-oscillation loop is formed by a first latched comparator 41, a second latched comparator 43, a first OR gate 45, a second OR gate 47, one AND gate 49, and one delay element 51. It is to be noted that the differential signal from the output of the BPF 13 is converted into the single-ended signal V_{in-s} (see Figure 7). V_{fb} is the output of the integrator 53 as shown in Figure 7. A subtraction element 55 gives at its output $V_{adm} = V_{in-s} - V_{fb}$. V_{adm} can be regarded as the error signal between V_{in-s} and V_{fb} . In other words, the feedback signal V_{fb} tries to track the input signal V_{in-s} , and V_{adm} indicates how far away V_{fb} is from V_{in-s} . V_{adm} is thus a modulated input signal of the ADM 15. V_{fb} tracks V_{in-s} , and functionally the integrator 53 generates the tracking signal V_{fb} through control signals ϕ_H , ϕ_L , and ϕ_{rst} so that the error signal V_{adm} is ideally limited within an upper threshold V_{thH} and a lower threshold V_{thL} . The latched comparators 41, 43 compare V_{adm} with the upper threshold V_{thH} and the lower threshold V_{thL} . Whenever V_{adm} crosses above V_{thH} or below V_{thL} , a spike is generated,

and the asynchronous logic 17 controls the feedback which results in V_{adm} being pulled back towards its DC level at 0.25 V, for example. This circuitry is one of several methods of implementing the ADM 15.

When V_{adm} is below the upper threshold V_{thH} and above the lower threshold V_{thL} , and the Reset is logic 0, ie invalid, the OUT terminals of the two comparators are logic 0, and the nOUT terminals are logic '1' after the completion of comparison. Therefore the outputs of the two OR gates 45, 47 are logic 1, and the output of the AND gate 49 is logic 1. After some delay, the Reset becomes logic 1, i.e. valid, both OUT and nOUT terminals of the two comparators become logic 0, and the output of the AND gate becomes logic 0. After some delay, the Reset becomes logic 0 again, and hence the self-oscillation is formed. When V_{adm} goes above the upper threshold V_{thH} and the Reset is logic 0, the OUT terminal of the ON comparator becomes logic 1, and the nOUT terminal becomes logic 0. The OUT terminal of the OFF comparator is still logic 0, and the nOUT terminal is still logic 1. The outputs of the two OR gates 45, 47 are still logic 1, and so is the AND gate output. The self-oscillation loop still works, and the self-oscillation loop also works in the case when V_{adm} goes below the lower threshold V_{thL} .

To further save power, the time delay of the delay element 51 is controlled by the output activity of the two comparators 41, 43 and so the output of the BPF 13. Initially, when V_{adm} is below V_{thH} and above V_{thL} , both the signals ON and OFF stay at logic 0, and the control signals ϕH and ϕL are also logic 0. Therefore EN_{busy} is logic 0, and the time delay of the delay element 51 is set to a larger value, so that the frequency of the self-oscillation is low. For latched comparators and logic gates, the power consumption is proportional to their operation frequency, therefore the power is further saved. Once V_{adm} goes above V_{thH} or below V_{thL} , ON or OFF becomes logic 1, and so does ϕH or ϕL . Logic 1 ϕH or ϕL sets EN_{busy} to logic 1, and the time delay of the delay element is set to a smaller value, so that the frequency of the self-oscillation is high, to reduce the comparison delay and delay dispersion of spike generation. A timer circuit 52 starts to count time once ϕH or ϕL becomes logic 0 again. Once the time threshold of the timer 52 is crossed, EN_{busy} goes back to logic 0, and the self-oscillation frequency becomes low again. So the timer circuit 52 is arranged to detect when the output activity (given by the frequency of the ON and OFF signals) is below a threshold, while the adjustment of the delay is implemented by the delay element 51. From the description above, the frequency of the self-oscillation loop is adaptively adjusted according to the activity level of the input to the ADM 15 (threshold crossing) for further power saving.

To better understand the signal timing, a detailed timing diagram is shown in Figure 8. As shown in the timing diagram, once V_{adm} goes above V_{thH} , a ϕH pulse is generated by the asynchronous logic 17 and sent to the integrator 53, and an $nReq_{ON}$ pulse is also generated by the asynchronous logic 17 and sent to an external receiver.

5 After some time, an Ack_{ON} pulse is sent back to the asynchronous logic 17 from the external receiver, and triggers a ϕrst pulse. The consecutive ϕH and ϕrst pulses functionally increase V_{fb} by δ , and cause V_{adm} to be pulled below V_{thH} . The signal flow of an OFF event when V_{adm} goes below V_{thL} is similar. EN_{busy} stays at logic 0 when V_{adm} is below V_{thH} and above V_{thL} , and consequently the oscillation frequency of the

10 Reset signal is low. Once ϕH or ϕL becomes logic 1, EN_{busy} becomes logic 1 which is enabled by a third logic OR gate 57 in front of the timer 52, and consequently the self-oscillation frequency of the Reset signal becomes high. Once ϕH or ϕL goes back to logic 0 again, the timer 52 starts to count time. Once the time threshold of the timer 52 is crossed, EN_{busy} is set back to logic 0 again, and the self-oscillation frequency of the

15 Reset signal becomes low again.

It is of course possible to have one dynamic latched comparator with the self-oscillating loop so that a signal is compared to one threshold only, ie either V_{thH} or V_{thL} using the above example. In that case, the circuit described above would be simplified so that the second comparator 43, the second OR gate 47 and the AND

20 gate 49 could be omitted. In that case, the output of the first OR gate 45 would be directly connected to the delay element 51. Moreover, it is to be noted that the described latched comparators in a self-oscillating loop and the method of power reduction via dynamic adaptation of the self-oscillation frequency are not confined to the ADM 15 described here. It is suitable for any clockless system that needs

25 comparison. For example, it can be easily integrated into clockless level-crossing analogue-to-digital converters.

While the invention has been illustrated and described in detail in the drawings and foregoing description, such illustration and description are to be considered illustrative or exemplary and not restrictive, the invention being not limited

30 to the disclosed embodiment. Other embodiments and variants are understood, and can be achieved by those skilled in the art when carrying out the claimed invention, based on a study of the drawings, the disclosure and the appended claims.

In the claims, the word "comprising" does not exclude other elements or steps, and the indefinite article "a" or "an" does not exclude a plurality. The mere fact

35 that different features are recited in mutually different dependent claims does not

indicate that a combination of these features cannot be advantageously used. Any reference signs in the claims should not be construed as limiting the scope of the invention.

Claims

1. A band-pass filter (13) comprising:

5 a first first-order filter stage comprising a first resistor (R1) characterised by a first impedance and connected to a first node (25), referred to as a filter input node, and, through a second node (27), to a first reactive component (C1) connected to a third node (29), the first impedance being such that a first current therethrough is dependent on the difference between the voltages at the first and second nodes (25, 27) when the first current flows from the first node (25) to the second node (27);

10 a second first-order filter stage comprising a second resistor (R2*) characterised by a second impedance and connected to the second node (27), and, through a fourth node (31), to a second reactive component (C2) connected to a fifth node (33), the second impedance being such that a second current therethrough is dependent on the negative of the sum of the voltages at the second and fourth nodes (27, 31) when the second current flows from the second node (27) to the fourth node (31); and

summing means (23) for summing the voltages at the second and fourth nodes (27, 31) to output a voltage at a sixth node (35).

20 2. A band-pass filter (13) according to claim 1, wherein the first and second first-order filter stages comprise a first first-order low-pass filter and a second first-order low-pass filter respectively.

25 3. A band-pass filter (13) according to claim 2, wherein the first and second first-order low-pass filters each comprise a source-follower-based transistor circuit.

4. A band-pass filter (13) according to any one of the preceding claims, wherein the first current is given by:

$$I_1 = \frac{V_{in} - V_a}{R_1},$$

30 where I_1 is the first current, V_{in} is the voltage at the first node (25), V_a is the voltage at the second node (27), and R_1 is the first impedance, and wherein the second current is given by:

$$I_2 = -\frac{V_a + V_b}{R_2^*},$$

where I_2 is the second current, V_b is the voltage at the fourth node (27), and R_2^*

is the second impedance.

5. A band-pass filter (13) according to any one of the preceding claims, wherein the summing means (23) comprises a summing amplifier.

5

6. A band-pass filter (13) according to any one of the preceding claims, wherein the first and second reactive components (C1, C2) are capacitors.

7. A band-pass filter (13) according to claim 6, wherein the first and
10 second capacitances are such that the following conditions are fulfilled:

$$Q = \frac{\sqrt{\frac{g_{m1}g_{m2}}{C_1C_2}}}{\frac{g_{m1}}{C_1} + \frac{g_{m2}}{C_2} - \frac{g_{m2}}{C_1}},$$

where Q is a quality factor of the band-pass filter (13), C₁ is a capacitance value of the first capacitor (C1), C₂ is a capacitance value of the second capacitor (C2), g_{m1} is a reciprocal of the first impedance, and g_{m2} is a reciprocal of the second impedance; and

$$\frac{Q + \sqrt{Q^2 + 4S_0^2 - 1}}{2S_0 + 1} \leq n \leq \sqrt{\frac{t_{ol}^2 + 2t_{ol}}{m_{is}}},$$

15 where n is a square root of g_{m2}/g_{m1}, t_{ol} is the relative variation of the band-pass filter central frequency f₀ caused by m_{is}, which is mismatch between currents in first (I_{2U}) and second (I_{2D}) current sources connected to first sides of transistors (M2, M4) and second sides of the transistors (M2, M4), respectively, of a transistor circuit implementation of the band-pass filter (13), and S₀ is the relative sensitivity of Q to
20 g_{m2}/g_{m1}.

8. A band-pass filter (13) according to any one of the preceding claims, wherein more than one second-order filter stages, each comprising the first first-order filter stage and the second first-order filter stage, are cascaded to form a higher order
25 band-pass filter (13).

9. A data processing apparatus (1) comprising two or more of the band-pass filters (13) according to any one of the preceding claims.

10. A data processing apparatus (1) according to claim 9, wherein the data processing apparatus comprises a clockless modulator circuit (15) comprising a latched comparator (41, 43) and comprising a self-oscillating loop for generating a pseudo-clock signal for the modulator circuit (15).

11. A data processing apparatus (1) according to claim 10, wherein the self-oscillation loop comprises a first comparator (41), a first logic gate (45) connected to an output of the first comparator (41) for detecting completion of the comparison, and a delay element (51) connected to the first logic gate (45), the delay element (51) being connected to the first comparator (41) by a first feedback loop for providing a reset signal for the first comparator (41).

12. A data processing apparatus (1) according to claim 11, wherein the self-oscillation loop further comprises a second comparator (43), a second logic gate (47) connected to an output of the second comparator (43) for detecting completion of the comparison, and to an AND gate (49) located between the first logic gates (45) and the delay element (51), the delay element (51) being further connected to the second comparator (43) by a second feedback loop for providing a reset signal for the second comparator (43).

13. A data processing apparatus (1) according to any one of claims 10 to 12, wherein the frequency of the pseudo-clock signal is arranged to be dependent on an input signal activity of the modulator circuit (15).

25

14. A data processing apparatus (1) according to any one of claims 9 to 13, wherein the processing apparatus comprises an artificial cochlea system or an analogue-to-digital converter.

15. A method of operating the data processing apparatus (1) according to one of claims 10 to 14, the method comprising:

determining a signal level of a modulated input signal (V_{adm}) of the modulator circuit (15);

increasing the frequency of the pseudo-clock signal if the signal level exceeds a first threshold (V_{thH}) or goes below a second threshold (V_{thL}); and

decreasing the frequency of the pseudo-clock signal if the signal level is between the first and the second thresholds, wherein the frequency is decreased once

a time period given by a timer circuit (52) has lapsed after detection of the signal level between the first and the second thresholds.

1/4




Fig. 1




Fig. 2




Fig. 3

2/4




Fig. 4




Fig. 5

3/4




Fig. 6




Fig. 7




Fig. 8

INTERNATIONAL SEARCH REPORT

International application No
PCT/EP2017/050231

A. CLASSIFICATION OF SUBJECT MATTER
INV. H03H11/12 H03M3/02
ADD.

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
H03H H03M

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

EPO-Internal, WPI Data, INSPEC, COMPENDEX

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	JP 2010 093560 A (ASAHI KASEI DENSHI KK) 22 April 2010 (2010-04-22)	1-6,8,9
A	abstract paragraph [0012] - paragraph [0031]; figures 1 - 4	7
A	----- WO 2007/034222 A2 (RFDOMUS INC [US]; GLONAV UK LTD [GB]; CONTA MATTEO [US]; BASCHIROTTA A) 29 March 2007 (2007-03-29) abstract page 3, line 32 - page 9, line 18; figures 1 - 3 ----- -/-	1-9



Further documents are listed in the continuation of Box C.



See patent family annex.

* Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier application or patent but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

21 March 2017

Date of mailing of the international search report

29/05/2017

Name and mailing address of the ISA/

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040,
Fax: (+31-70) 340-3016

Authorized officer

Trafidlo, Renata

INTERNATIONAL SEARCH REPORT

International application No
PCT/EP2017/050231

C(Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	YANG M ET AL: "14.4 nW fourth-order bandpass filter for biomedical applications", ELECTRONIC LETTERS, THE INSTITUTION OF ENGINEERING AND TECHNOLOGY, vol. 46, no. 14, 8 July 2010 (2010-07-08), pages 973-974, XP006036688, ISSN: 1350-911X, DOI: 10.1049/EL:20101520 Introduction ; Proposed bandpass biquad; page 973; figures 1, 2 -----	1-9
A	CHEN Y ET AL: "0.07 mm², 2 mW, 75 MHz-IF, fourth-order BPF using source-follower-based resonator in 90 nm CMOS", ELECTRONICS LETTERS, IEE STEVENAGE, GB, vol. 48, no. 10, 10 May 2012 (2012-05-10), pages 552-554, XP006040855, ISSN: 0013-5194, DOI: 10.1049/EL.2012.0579 abstract Introduction ; BPF using SFB resonators; page 552; figure 1 -----	1-9
A	MASAKI KITSUNEZUKA ET AL: "A 30MHz 2.4GHz CMOS receiver with integrated RF filter and dynamic-range-scalable energy detector for cognitive radio", RADIO FREQUENCY INTEGRATED CIRCUITS SYMPOSIUM (RFIC), 2011 IEEE, IEEE, 5 June 2011 (2011-06-05), pages 1-4, XP032002355, DOI: 10.1109/RFIC.2011.5940629 ISBN: 978-1-4244-8293-1 B. RF filter, mixer, and baseband filter design; page 1, right-hand column - page 2, left-hand column; figures 3, 4 -----	1-9

INTERNATIONAL SEARCH REPORT

International application No.
PCT/EP2017/050231

Box No. II Observations where certain claims were found unsearchable (Continuation of item 2 of first sheet)

This international search report has not been established in respect of certain claims under Article 17(2)(a) for the following reasons:

1. ☐ Claims Nos.:
because they relate to subject matter not required to be searched by this Authority, namely:
2. ☐ Claims Nos.:
because they relate to parts of the international application that do not comply with the prescribed requirements to such an extent that no meaningful international search can be carried out, specifically:
3. ☐ Claims Nos.:
because they are dependent claims and are not drafted in accordance with the second and third sentences of Rule 6.4(a).

Box No. III Observations where unity of invention is lacking (Continuation of item 3 of first sheet)

This International Searching Authority found multiple inventions in this international application, as follows:

see additional sheet

1. ☐ As all required additional search fees were timely paid by the applicant, this international search report covers all searchable claims.
2. ☐ As all searchable claims could be searched without effort justifying an additional fees, this Authority did not invite payment of additional fees.
3. ☐ As only some of the required additional search fees were timely paid by the applicant, this international search report covers only those claims for which fees were paid, specifically claims Nos.:
4. ☒ No required additional search fees were timely paid by the applicant. Consequently, this international search report is restricted to the invention first mentioned in the claims; it is covered by claims Nos.:

1-9

Remark on Protest

- ☐ The additional search fees were accompanied by the applicant's protest and, where applicable, the payment of a protest fee.
- ☐ The additional search fees were accompanied by the applicant's protest but the applicable protest fee was not paid within the time limit specified in the invitation.
- ☐ No protest accompanied the payment of additional search fees.

FURTHER INFORMATION CONTINUED FROM PCT/ISA/ 210

This International Searching Authority found multiple (groups of) inventions in this international application, as follows:

1. claims: 1-9

A band-pass filter comprising: a first 1st-order filter stage comprising a first resistor having a first impedance and connected to a first and a second nodes, and a first reactance connected to the second node, the first node being a filter input and the first impedance being such that a first current flowing from the first to the second node is proportional to the difference between the voltages at the first and second nodes; a second 1st-order filter stage comprising a second resistor having a second impedance and connected to the second and a fourth nodes, and a second reactance connected to the fourth node, the second impedance being such that a second current flowing from the second to the fourth node is proportional to the negative of the sum of the voltages at the second and fourth nodes; summing means for summing the voltages at the second and fourth nodes to output a voltage at a sixth node; wherein the resistors are implemented with transistors and the reactances are capacitances fulfilling a predefined condition.

2. claims: 10-15

A data processing apparatus comprising two or more band-pass filters, each band-pass filter comprising: a first 1st-order filter stage comprising a first resistor having a first impedance and connected to a first and a second nodes, and a first reactance connected to the second node, the first node being a filter input and the first impedance being such that a first current flowing from the first to the second node is proportional to the difference between the voltages at the first and second nodes; a second 1st-order filter stage comprising a second resistor having a second impedance and connected to the second and a fourth nodes, and a second reactance connected to the fourth node, the second impedance being such that a second current flowing from the second to the fourth node is proportional to the negative of the sum of the voltages at the second and fourth nodes; summing means for summing the voltages at the second and fourth nodes to output a voltage at a sixth node; the data processing apparatus further comprising a clockless modulator circuit including a latched comparator and comprising a self-oscillating loop for generating a pseudo-clock signal for the modulator circuit.

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/EP2017/050231

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
JP 2010093560	A	22-04-2010	NONE

WO 2007034222	A2	29-03-2007	AT 459133 T 15-03-2010
		CN 101268612	A 17-09-2008
		EP 1927188	A2 04-06-2008
		JP 2009509447	A 05-03-2009
		KR 20080063355	A 03-07-2008
		US 2008157864	A1 03-07-2008
		WO 2007034222	A2 29-03-2007
