



"PROCESS AND SYSTEM TO DETERMINE TEMPORAL CHANGES IN RETRANSMISSION AND PROPAGATION OF SIGNALS USED TO MEASURE DISTANCES, SYNCHRONIZE ACTUATORS AND GEOREFERENCE APPLICATIONS"

5 Field of invention

The present invention addresses to a process and a system to determine changes in time, phase and frequency at a signal repeater station located at a remote and inaccessible site, being operatively  
10 associated to a set of ground-based transmitting and receiving bases, at known geodetic positions, as well as to determine temporal changes due to the signals propagation in the medium, to obtain distance measurements, navigation and geographic positioning,  
15 relative to the inaccessible repeater, and to obtain time synchronization through measurements corrected for the changes in frequency (phase delays) and in time at the remote signal repeater. This proposal provides an innovative solution for the remote determination of  
20 time changes and of signal transit times in the process of being received and retransmitted by repeater stations or transponders operating at inaccessible conditions and of the additional time changes caused by the signal propagation in the medium  
25 where the system operates.

Antecedents of the invention

The echo obtained of a signal sent forward and retransmitted is used to measure distances of remote objects. The precision of the determinations depends  
30 entirely on the knowledge and the correction of the temporal effects that occur at the repeater, caused by four principal factors: (a) velocity of propagation in the medium, (b) propagation in the cables and instruments during transmission, (c) propagation in  
35 the cables and instruments at the final reception, and

(d) in the retransmission by the remote object (repeater) which distance is to be determined.

The models describing (a) are, in general, well known for propagation in different media (terrestrial ionosphere and troposphere) as well as in space (J.W. Marini, "Correction of satellite tracking data for an arbitrary tropospheric profile", Radio Sci., 7, 223-231, 1974; J.A. Klobuchar, "Design and characteristics of the GPS ionospheric time delay algorithm for single frequency users", em PLANS '86 - Position Location and Navigation Symposium, Las Vegas, NV, Nov. 4-7, 1986, Record (A87-41351 18-17), New York, Institute of Electrical and Electronics Engineers, 1986, pp. 280-286, 1986; S.M. Hunt et al., "Equatorial atmospheric and ionospheric modeling at Kwajalein missile range", Lincoln Laboratory Journal, vol. 12, pp. 45-64, 2000; S.M. Honma, Y. Tamura e M.J. Reid, "Tropospheric delay calibrations for VERA", Publ. Astron.Soc. Japan, vol. 60, pp. 951-960, 2008; T.S. Radovanovic, "Adjustment of satellite-based ranging observations for precise positioning and deformation monitoring", PhD dissertation, Department of Geomatics Engineering, University of Calgary, Canada, UCCGR Reports Nr. 20166, 2002, and references therein). After the adequate model selection, the effect of propagation on the temporal changes need to be calculated as a function of the distance and of the angle of elevation through which the repeater is seen, which are parameters also not known in advance

Factors (b) and (c) are measured directly, experimentally with high precision.

Factor (d), however, is undetermined, since the remote object is inaccessible for direct measurements and it undergoes to changes in its internal signal propagation characteristics, which can change with

time, or for each sequence of signals utilized to determine its distance. In addition other temporal alterations due to Doppler effects and those predicted by relativity may become important for repeaters transported by satellites or spacecrafts moving rapidly in relation to a reference frame containing the points from which the distances from the remote object are intended to become determined. Other temporal changes may be considered as caused by relativistic effects when the satellite (the remote object) moves along different gravitational potential in relation to the geoid (Ashby, N., "Relativity and the global positioning system", *Physics Today*, 55, pp. 41-47, 2002; Larson, K.M. et al., "An assessment of relativistic effects for low Earth orbiters: the GRACE satellites", *Metrologia*, 44, pp. 484-490, 2007).

On the other hand, when using meteor as reflecting transponders, phase delays can be caused by the signal scattering on the ionized trails (Wislez J.-M., "Forward Scattering of Radio Waves of Meteor Trails", *Proceedings of the International Meteor Conference, Brandenburg, Alemanha*, pp.99-117, 1995).

Electromagnetic signals, such as the radio signals, can be sent to great distances by mean of transmission links. These links receive the transmission, detect it, amplify it, or not, and retransmit the radio signals o the directions of interest.

These technologies are well known and of public domain, and for this reason they will not be described here. Distant wireless transmission of information is accomplished by well known technologies using electromagnetic waves (e.m.w.) as carriers. Radio electromagnetic waves are the most widely utilized. Currently the e.m.w. wireless techniques extend to frequency bands corresponding to the infrared,

visible, ultraviolet and X-rays.

Links are used for telecommunications on longer distances. The links receive and retransmit the signals, at the same frequency, or at different  
5 frequencies. The links can be natural, such as the reflections of radio e.m.w. in terrestrial ionosphere, or by scattering on ionosphere or troposphere inhomogeneities and by reflection on ionized meteor trails in the upper atmosphere, among others.

10 An innumerable number of artificial links options have been implemented and utilized, namely a variety of repeaters, retransmitters, generically designated as transponders, installed on ground or in space, on board of a platform at an artificial satellite. At  
15 retransmission links the e.m.w. undergo phase delays caused by the electronic devices through which the signal propagates. For many applications this effect does not bring serious consequences to the signals that are being transported. They are delayed all  
20 together, for fractions of time, independently from the user. This is the case of wireless retransmissions of audio and video.

However, in intercommunication applications, such as in mobile cell phone, digital telecommunications, the  
25 signal synchronism of signals are required at the links. Reference time and frequency standards must be common and synchronized at every link of a wireless telecommunication network. The use of atomic frequency and time standards at every link would be a solution.  
30 This option, however might not be always practical, being certainly expensive.

The modern solution for such link synchronization is obtained by time standards referred to GPS satellites, or to similar constellations of geopositioning  
35 satellites. They are known as GPS clocks, that provide

accuracy and stability of the order of hundred of nanoseconds, that means, at a sufficient level to assure the reference for the electronic circuits operated at the links (T.A. Clark and R.H. Hambly, 5 "Improving the performance of low cost GPS timing receivers", 38<sup>th</sup> Annual Precise Time and Time Interval (PTTI) Meeting, Reston, Virginia, USA, 7 December, 2006).

The calculations needed to determine distances based 10 on echoes of signals transmitted and received are necessarily associated to the accurate knowledge of the phase delays, or of the temporal changes, that occur at the links, as well as the delays caused by the propagation media, in order to obtain the signals 15 propagation time corrections transported from their origin to their destination, going through the retransmission link.

The remote determination of temporal changes at the repeaters and those due to the signal propagation in 20 the media are conditions essentially required to make viable the use of systems and processes for geographic and space positioning using reference transmitters and receivers on the ground and transponders in space, as described analytically in the article by P. L. Kaufmann 25 et al., "Non recursive algorithm for remote geolocation using ranging measurements", Math. Problems in Engineering, v. 2006, pp. 1-9, Article ID79389, DOI:10.1155/MPE/2006/79389, 2006.

The determination of temporal changes at the repeater 30 and the changes due to propagation effects is essential to make viable the correct operation of the concepts exposed in the Patent of Invention PI9101270-8, "System and process of geographic positioning and navigation", granted September 30, 1997 and in its 35 Addition Certificate" C19101270-8, filed 17.05.2002;

in the Patent of Invention PI03003968-4, "System and process of geographic and space positioning" filed 8 October 2003, corresponding to PCT/BR2004/000190, "Geographic and space positioning system and process",  
5 filed 4 October 2004, which resulted, up to this date, in the following granted patents: US752877B2, on 05/05/09; RU2635934C2 on 27/08/09; and AU 2004277511, on 26/11/2010.

The phase delays caused by links components, converters, cables and electronics, in the  
10 transmission and reception of signals at the ground, can be accurately measured in laboratory and adopted for the data retransmitted by the link. However the continuous use and the remote and inaccessible  
15 location of a defined link as, for example, in a satellite, jeopardizes the maintenance of the delays previously determined and makes impossible its updating correction. In the case of transponders in satellites, the relativistic temporal effects will  
20 depend on their position in space. In the case of repetition by retransmission in meteor trails, the temporal effects will depend on the direction they occur in the sky. On the other hand many transponders carry internal processors which cause signal  
25 retardations, which can be distinct for each sequence of retransmitted signals. The difficulties become aggravated when adding imponderable signal phase changing physical effects - such as effect due to temperature variations in the electronic circuits at  
30 the repeater.

In satellites it must also be considered Doppler effects and other caused by relativity and by the gravitational potential. Thee unpredictable phase variation effects must be taken into account to assure  
35 the distance determinations by signal reflection (or

by retransmission). Time changes caused by signal propagation in the media may become significant and will depend on the adopted models and of the angles of sight of the repeaters, to be determined. The determination of these changes is a necessary condition to make feasible the application of geopositioning, navigation and time dissemination systems and processes using ground references and transponders in space, as mentioned above.

10 Summary of the invention

Taking into account the operational requirements of wireless signal transmission systems using a remote and inaccessible repeater station, and also the need of the usual accurate and instantaneous determination of the geographic positioning of the referred remote station, the present invention has the objective to define and provide a process and a system, relatively simple to be implemented and economically feasible, to provide the correct and instantaneous determination of the temporal changes, phase delays and frequency shifts, in the signals retransmission and propagation, which can contain audio, video and other information, such as coded time signals, related to a remote and inaccessible repeater station, generally moving in space.

According to the solution proposed by the present invention it is possible to determine, in any instant, the correct geographic and spatial positioning and the adjustment of time indication of a repeater station, remote and inaccessible, from the determination of time changes in retransmission and propagation of signals that the remote station, located at great distance and having a transponder (transceiver or repeater), receives from a stationary transmitter of signals, located at a known and accessible site.



According to the invention the process to determine temporal changes and phase delays at a signal repeater station, remote and inaccessible, and time delays due to signal propagation, comprises one first step to  
5 install four reference bases on the ground, at known geographic positions and visible from the repeater station. The following step consists in emission, at a reference instant and by a transmitting device provided in one of the above referred reference bases,  
10 here designated as the central base, of a coded time signal, containing the identification of there reference base that is emitting it and of the instant of emission; and the step to receive, by a receiving device installed at each one of the four bases of  
15 reference, the coded signal, which was received and retransmitted by the repeating station.

After completed the steps above mentioned, the process continues with the calculation of the difference of at least two positions for the repeater station for the  
20 same transmitted coded signal, which calculation is done utilizing at least two distinct sets of three reference bases, being known that the above mentioned difference dependent from a value of the alteration in time, phase or frequency, attributed to the repeater  
25 station. Different values for the temporal changes are then attributed systematically and arbitrarily, and calculated, for each of these values adopted, different values for the differences between the two positions. Once the above referred differences between  
30 every two respective positions for the repeater station, it is possible to identify which value, attributed to the temporal changes at the repeater, produce a minimum difference for the two positions calculated for the repeater station. The calculations  
35 involved in this phase of the process are performed in

iterative form, for example, by successive approximations, adopting various values for the temporal changes that might have happen in the signal passage by the repeater station, until a value is identified for which the difference between two calculated positions for the repeater becomes minimum. This value defined the variation in time, frequency or phase, at the repeater station, deduced from the minimum found for the difference in positions for the repeater. The distances of the four bases to the repeater can now be corrected, adopting the temporal change that has been determined. The value of the temporal change can now be used to determine the correct position of the repeater. The same iterative process can include other temporal changes due to the velocities of propagation of the signals characteristics of the medium, adopted according to known propagation models and using the elevation angles the repeater is seen from the bases, found using the same iterative procedure.

In one possible application of the process, another step is further provided to determine the coordinates of the repeater station with correction of the change in time, frequency or phase for the referred instant. In another process application, the time signals are disseminated to other points on the ground, with known geographic positions, in order to synchronize their respective clocks.

#### Brief description of the figures

The present invention will be described with reference to the attached figures, provided with the scope to illustrate, namely:

Figure 1 is a schematic perspective view, illustrating the space positioning off a signal repeater, remote and inaccessible in relation to four bases installed

on the ground at known geographic positions, with at least one of them containing a coded signals transmitter to be received and retransmitted by the repeater station in space, with the four bases  
5 containing receivers of the signals retransmitted by the repeater station, and where the position labeled by P indicates a target which coordinates are known or are to be determined, depending on the application that will be described ahead.

10 The four bases have their own means of communication to the central processing station, to where they send the time differences between the time signal retransmitted by the repeater and their respective clocks. For simplicity, the central processing station  
15 could be the same reference base where the time signals are transmitted.

Figure 2 represent a schematic view in perspective, illustrating the system of coordinates, spherical and Euclidean, used to equate the space positioning of the  
20 repeater station, illustrated in figure 1; and Figure 3 represent the four distinct positions for the repeater station, in two coordinate systems, one referred to  $x,y,z$  and another referred to  $u,v,w$ , utilized to find the position of the target P, which  
25 coordinates are to be determined.

#### Description of the invention

As mentioned before, and illustrated in the attached figure 1, the invention provide a process and a system for wireless transmission of signals, as for example  
30 digital audio or video signals, or even analog signals, with the use of a repeater station R, remote and inaccessible, which may be represented by a satellite platform or of another object or repeater device of any kind, capable to receive and retransmit,  
35 in predetermined directions, the coded time signals.

The invention here presented utilizes four reference bases A, B, C, and D, every three of them not collinear, installed on the ground (see figure 1) at known geographic positions with each one of the bases  
5 containing signal receiving devices, such as radio frequency signals, modulated digitally, for example, in audio or video, and received and retransmitted by the repeater station R in space. Time coded signals are transmitted by one of the reference bases A, B, C  
10 and D and retransmitted by the repeater station R in space back to the reference bases A, B, C, and D. According to the proposed system one of the four reference bases A, B, C, D contains one coded time signal transmitter T and one receiver REC of the  
15 signals retransmitted by the transponder provided at the remote repeater station R. To simplify the description the transmitter is associated to base A. The four reference bases A, B, C, D have receivers to receive the time coded signals retransmitted by the  
20 remote transponder at the repeater station R. With exception of base A which contains the transmitting mean T, the other bases have means to transmit the respective differences between the coded time signal received from the remote transponder and time coded  
25 signal generated in each one of them, to a central processing base E. To simplify, the reference base A (herewith called central base) can be the same base that transmits the time signals. At the central base the coded time signal received from the remote  
30 transponder is compared to the coded time signal generated at the same reference base. The four reference bases have their own precision clocks RL each one synchronized to each other.

The four reference bases A, B, C, D have their own  
35 precision clocks RL and means to compare the time

signal retransmitted by the remote transponder to the time generated locally. The reference bases process their local differences in time, and transmit them to the central base E which, for simplicity can be the same reference base A, which also have emitted the original signal transmission. The local differences in time will be transmitted to the central base by some mean of communication such as, for example, commercial telecommunication, or making use of the same remote repeating station for data communication.

The correct position for the spatial repeater station R will depend on the knowledge of the temporal changes and/or phase delay at the repeater station R and those caused by the signal propagation in the medium, needed to correct the time differences measured in relation to each three over four reference bases A, B, C, and D. The good performance of the system requires the knowledge of phase delays undergone by the signals being transmitted, in all segments and, in particular, in the coded time signal transit by the repeater station (transponder) R and those caused by propagation.

The present invention resolves the current difficulties to determine correctly and by economically feasible means, the temporal change measurements, or the phase delays, for example, undergone by the signal in the retransmission link at a repeater station R, remote and inaccessible, and in their propagation in the media involved, such as the in the terrestrial atmosphere and ionosphere, as it occurs for stations located in space, in satellite platforms.

With the adoption of four reference bases there are several possible forms to determine the temporal variation on the signal received and retransmitted by

the repeater station, or by the transponder. It can be used, for example, a more general procedure with great accuracy to determine the time changes at the repeater station R, which to not depend on the disposition of the planes containing the four reference bases A, B, C and D.

It is possible to adopt the same spherical and euclidean coordinate systems utilized by P.L. Kaufmann et al. (2006), illustrated in figure 2, which algorithm permits to equate the repeater R coordinates obtained with the reference bases A, B, C and D.

The measurements obtained by the system provide the following data, according to the nomenclature defined below:

$$AR(\delta_R) = (\Delta t_A - \delta_{At} - \delta_{Ar} - \delta_R) (c/2) - 2\Delta_{pdAR} \quad (1)$$

$$BR(\delta_R) = (\Delta t_B - \delta_{At} - \delta_{Br} - \delta_R) c - AR(\delta_R) - \Delta_{pdBR} - \Delta_{pdAR}$$

$$CR(\delta_R) = (\Delta t_C - \delta_{At} - \delta_{Cr} - \delta_R) c - AR(\delta_R) - \Delta_{pdCR} - \Delta_{pdAR}$$

$$DR(\delta_R) = (\Delta t_D - \delta_{At} - \delta_{Dr} - \delta_R) c - AR(\delta_R) - \Delta_{pdDR} - \Delta_{pdAR}$$

Where  $AR(\delta_R)$ ,  $BR(\delta_R)$ ,  $CR(\delta_R)$  and  $DR(\delta_R)$  are the distances from bases A, B, C and D to the repeater R position, respectively, expressed s a function of the temporal changes of the signals transiting by the repeater,  $\delta_R$ , to be determined;  $\Delta t_A$ ,  $\Delta t_B$ ,  $\Delta t_C$  and  $\Delta t_D$  are the time differences effectively measured at bases A, B, C and D, respectively;  $\delta_{At}$  is the time change caused by the signal passage by circuits and cables when being transmitted from base A, previously measured and known;  $\delta_{Ar}$ ,  $\delta_{Br}$ ,  $\delta_{Cr}$  and  $\delta_{Dr}$  are the time changes caused by the signal passage by circuits and cables when being received at bases A, B, C and D, respectively, previously measured and known; and  $c$  is the speed of the electromagnetic waves transporting the time coded signals, as for example radio waves, in vacuum, and  $\Delta_{pdAR}$ ,  $\Delta_{pdBR}$ ,  $\Delta_{pdCR}$  and  $\Delta_{pdDR}$  are the distance errors of

the segments AR, BR, CR and DR are temporal delays caused by the propagation of signals in the physical media (atmosphere, ionosphere).

The errors in distance above described, caused by temporal deviations due to propagation in the medium are added to the distance deviation due to the time change of the signal at the repeater,  $\delta_R$ , which is the same for the four segments AR, BR, CR and DR. The coordinates for the repeater station R, as determined for bases A, B and C are expressed by the algorithm already developed by P. L. Kaufmann et al.(2006), in the reference system illustrated in figure 2, in relation to axis x, y and z, as a function of the signal when transiting by the repeater,  $\delta_R$ , to be determined:

$$x_R(\delta_R) = \{ [AR(\delta_R)]^2 - [BR(\delta_R)]^2 + AB^2 \} / 2AB \quad (2)$$

$$y_R(\delta_R) = \{ \{ [r_1(\delta_R)]^2 - [r_2(\delta_R)]^2 \} / 2y_C \} + y_C / 2$$

$$z_R(\delta_R) = \{ [r_1(\delta_R)]^2 - [y_R(\delta_R)]^2 \}^{1/2}$$

where

$$[r_1(\delta_R)]^2 = [AR(\delta_R)]^2 - [x_R(\delta_R)]^2 \quad (3)$$

$$[r_2(\delta_R)]^2 = [CR(\delta_R)]^2 - [(x_C - x_R(\delta_R))]^2$$

IF needed to express the result in spherical coordinates, latitude, longitude and altitude for the repeater, these can be deduced by a simple inverse analytical procedure. On the other hand, with the use of the measurements obtained with the use of base D, we obtain:

$$x_R'(\delta_R) = \{ [AR(\delta_R)]^2 - [BR(\delta_R)]^2 + AB^2 \} / 2AB \quad (\text{igual } x_R(\delta_R)) \quad (4)$$

$$y_R'(\delta_R) = \{ \{ [r_1'(\delta_R)]^2 - [r_2'(\delta_R)]^2 \} / 2y_D \} + y_D / 2$$

$$z_R'(\delta_R) = \{ [r_1'(\delta_R)]^2 - [y_R'(\delta_R)]^2 \}^{1/2}$$

where

$$[r_1'(\delta_R)]^2 = [AR(\delta_R)]^2 - [x_R'(\delta_R)]^2 \quad (\text{igual a } [r_1(\delta_R)]^2)$$

(5)

$$[r_2(\delta_R)]^2 = [DR(\delta_R)]^2 - [(x_D - x'_R(\delta_R))]^2$$

The two systems of equations permit to formulate the discrepancy in the repeater's position as a function of the temporal intended to be determined, according to the following expression:

$$\begin{aligned} f(\delta_R) &= |[x_R(\delta_R), y_R(\delta_R), z_R(\delta_R)] - [x'_R(\delta_R), y'_R(\delta_R), z'_R(\delta_R)]|^2 = \\ &= [x_R(\delta_R) - x'_R(\delta_R)]^2 + [y_R(\delta_R) - y'_R(\delta_R)]^2 + \\ &+ [z_R(\delta_R) - z'_R(\delta_R)]^2 \end{aligned} \quad (6)$$

Utilizing known numerical calculation methods, such as iterative procedures, for example, by successive approximations, adopting various values for the temporal changes that might have happened in the signal passage by the repeater station, in Will be found the value of the phase delay  $\delta_R$  at the repeater station R, for which the function  $f(\delta_R)$  assumes a minimum value, which will be close to the searched value, needed for the utilization by the system considered in this invention. This procedure can be done with the simultaneous use of data from the other two sets of reference bases A,B,D and A,C,D, adopting base A as the transmitter and improving the accuracy of  $\delta_R$  determination.

The iterative described above can include the corrections of the time changes due to the propagation velocities, distinct from  $c$ , of the signals that transport the coded time information in the media represented by the low and high terrestrial atmosphere. These velocities are distinct from the speed of light  $c$  in vacuum, and its effect correspond to delays in phase of in time causing an apparent larger distance for the measured segments, as described by the equations of system (1). The respective time or phase delays correspond to



deviations in the respective segments, which can be calculated at the same time by the iterative process described before, with the determination of the elevation angles from the repeater H, as see from the  
5 bases A, B, C and D, and adopting a model to describe the respective segments deviations (as for example described by S.M. Hunt et al., "Equatorial atmospheric and ionospheric modeling at Kwajalein missile range", Lincoln Laboratory Journal, vol. 12, pp. 45-64, 2000;  
10 S.M. Honma, Y. Tamura e M.J. Reid, "Tropospheric delay calibrations for VERA", Publ. Astron.Soc. Japan., vol. 60, pp. 951-960, 2008). The process calculations are repeated adopting the deviations for the respective segments, due to propagation effects in the  
15 terrestrial atmosphere added to systems of equations (1), obtaining the correction for the time transit at the repeater added to the correction of correction for signal propagation times at all segments, allowing the calculation of the searched coordinates with great  
20 accuracy. The process and system proposed by the invention allows the remote determination of the temporal changes at the link defined by the signal repeater station and the temporal changes due to the propagation of signals in the medium, simultaneously  
25 to measurements of distance, navigation, clock synchronization and geographic positioning, for every discrete temporal sequence utilized in the procedure. To calculate the corrected distances, geographic coordinates of the repeater and of the targets and  
30 applications in time synchronization it will be used the analytical procedures described in the article of P. L. Kaufmann et al., "Non recursive algorithm for remote geolocation using ranging measurements", Math. Problems in Engineering, v. 2006, pp. 1-9, Article  
35 ID79389, DOI:10.1155/MPE/2006/79389, 2006.

The phase delays corresponding to the references bases A, B, C and D can be well determines "in loco" and are assumed as fixed and well known data, considering that such reference bases are fixed and accessible to all procedures for verifying measurements.

The solution proposed by the present invention makes the economically possible, with high degree of accuracy, the determinations of phase delays and temporal changes in the passage of time coded signals by the repeating station R (in reception and retransmission), at a remote and inaccessible location, as well as the time changes caused by propagation effects in the medium.

The temporal effects in the time coded signals in their passage by the repeater station R, and those caused the signal propagation at different elevation angle, are unknown and cannot be determined with only three bases of reference in the system, which defini only one position for the repeater R.

The process here proposed can also include steps to: emit, from the above indicated reference base at successive instants, coded signals and to obtain successive coordinates for the repeater station R, corrected in function of changes in time, phase and frequency, in the retransmission of the above said successive coded signal, in order to allow the navigation of the repeating station R, making the calculations of coordinates for the repeater shown before with system of equations (2), to which it will be introduced the time changes ( $\delta_R$ ) and  $\Delta_{pdAR}$ ,  $\Delta_{pdBR}$ ,  $\Delta_{pdCR}$  and  $\Delta_{pdDR}$  determined according to the present invention; retransmit, by the repeater station R, the coded time signals to other targets which geographic coordinates are well known (one of them represented in this application by point P in figure 1); determine

the difference between the time coded signal that arrives at target P and the time generated by its own clock,  $\Delta'_p$  allowing the correction of synchronism, following the equation (P.L. Kaufmann et al., 2006):

$$5 \quad \Delta'_p = (AR/c) + (PR/c) + \delta_{At} + \delta_{Pr} + \delta_R + \Delta_{pdPR} + \Delta_{pdAR} \\ (7)$$

where AR and PR are the measured segments,  $\delta_{At}$  and  $\delta_{Pr}$  are the temporal changes previously determined and known at the transmitter and at the target P with  
 10 known position, respectively,  $\delta_R$  and  $\Delta_{pdPR}$  are the time changes determined by the present invention. The synchronization or time correction will be  $\Delta'_p - \Delta_p$  where  $\Delta_p$  is the time difference predicted theoretically for position P.

15 The other possible step is to retransmit, by the repeater station R, the time coded signals, to the other targets with unknown position (similarly represented by the point P in figure 1), with their clocks synchronized to the clocks installed at the  
 20 four reference bases, A,B,C,D; to obtain the distances from the repeater station R to the other targets, corrected for temporal changes at retransmission and in propagation; and determine the coordinates for the targets in at least three successive instants,  
 25 adopting the corrections in time, frequency and phase. It is therefore possible to calculate the distance Of the repeater station R to the reference bases A,B,C,D and to the targets with positions to be determined, with corrections of the time changes at  
 30 retransmission and in propagation, at repeater R positions in four different instants, which positions are not in a straight line in space, defining, univocally, in any coordinate system in space, through four successive measurements, the spatial position of  
 35 the target, as it has been proposed to determine. The

analytical solution to perform these calculations can follow, for example, the algorithm published by P.L. Kaufmann et al. (2006) repeating the procedures expressed by equations (1), (2) and (3) in relation to one set of three reference bases that include base A where the transmitter is located, for four instants above referred, obtaining four spheres with distinct radii, all of them centered on the repeater, at positions and instants distinct, respectively. The interception of spheres will give the position of target P, which coordinates become determinate. The practical procedure is illustrated in figure 3 (after P.L. Kaufmann et al., 2006) where a target P, with position to be determined (A, x, y, z) is located in relation to the four distinct positions of the repeater R<sub>1</sub>, R<sub>2</sub>, R<sub>3</sub> and R<sub>4</sub>, being the last position na option when the surface of the planet itself cannot be used as a fourth reference. The operations are made by adding another system of reference as a function of the repeater's positions in R<sub>1</sub>, R<sub>2</sub>, R<sub>3</sub> and R<sub>4</sub> (see figure 3), (R<sub>1</sub>, u, v, w), where the target's coordinates u, v and w constitute the solution for the system. It has been shown by P.L. Kaufmann et al. (2006) that for three repeater's positions two solutions are found:

$$u_p = (PR_1^2 - PR_2^2 + R_1R_2^2)/2R_1R_2 \tag{8}$$

$$v_p = [(\rho_1^2 - \rho_2^2)/2 v_{R3}] + v_{R3}/2$$

$$w_p = \pm (\rho_1^2 - v_p^2)^{1/2}$$

where  $\rho_1^2 = PR_1^2 - u_p^2$  e  $\rho_2^2 = PR_3^2 - (u_{R3} - u_p)^2$ .

The uncertainty in the signal of w<sub>p</sub> is eliminated by adopting a fourth sphere to define only one position. This can be the interception with the planet's surface, taken as the fourth reference surface, or by adding one fourth position for the repeater station R<sub>4</sub>

(see figure 3), generating a respective fourth sphere with radius  $PR_4$ .

The position solution found, using known analytical procedures, can be converted into the  $(A, x, y, z)$  system  
5 by determining the position of P  $(x_P, y_P, z_P)$  in this coordinate system. In the case there are interest in expressing the results in spherical coordinates (latitude, longitude, altitude of the repeater's station), these can be found using well known  
10 analytical procedures, deduced from simple known operations.

The technical solution proposed by the present invention permits to choose the time or the hour of reference to perform the measurements, provided there  
15 is synchronism between the clocks provided at the reference bases and/or at the targets with positions are to be determined.

The technical solution proposed allows: the determination of geographic and spatial positions of  
20 targets located at distances which are within the visibility line as seen from the repeater R in space; the prediction for the adoption of a larger number of fixed reference bases A, B, C, D, covering larger geographic extensions with the use of the same  
25 repeater R in space; the prediction the adoption of more than one repeater station R in space, extending the area on the terrestrial surface to become surveyed, to define targets geopositioning; to calculate the targets geographic position with four  
30 transponders in space, separated at a distance from each other, with one single time signal interaction; and to allow the accomplishment of hundreds of successive measurements per minute of time, of one or more targets, fixed or mobile, with the use of a  
35 single repeater station R in space.

The process and system here presented can be applied to any kind of transponders or repeaters of electromagnetic waves in general in space, being artificial or natural, active or passive.

CLAIMS

1. Process to determine temporal changes in retransmission and propagation of signals, to measure distances, synchronize actuators, and georeferencing,  
5 characterized by the fact of comprehending the steps of:
- a- installing four reference bases (A,B,C,D) on the ground, every three of them not collinear, at known geographic positions and visible from the repeater  
10 station (R);
  - b- emitting, at a reference instant and from a transmitter device (T) provided a tone of the above mentioned reference bases, one time coded signal containing the identification of the emitting reference  
15 base and of the instant of emission;
  - c- receiving, in a receiver device (REC) installed at each one of the four reference bases (A,B,C,D) the coded signal, received and retransmitted by the repeater station (R);
  - 20 d- attributing, systematically, different arbitrary values to the change in time, phase or frequency, to the repeater (R) and calculate, for each one of the attributed temporal change, one respective position difference for the repeater station (R) obtained with  
25 the use of two distinct sets of three reference bases (A,B,C and A,B,D; A,B,C and B,C,D; A,B,D and B,C,D);
  - e- identifying which one of the attributed values for the temporal changes at the repeater (R) results in a minimum difference between the two positions of the  
30 repeater station (R), obtained using two distinct sets of three reference bases (A,B,C and A,B,D; A,B,C and B,C,D; A,B,D and B,C,D); and
  - f- utilizing the temporal change found in "e" to determine the position of the repeater (R).
- 35 2. Process, according to claim 1, characterized by the

fact that the difference positions for the repeater (R) station are calculated algebraically attributing certain values to the so said temporal change, in sufficiently high number of values enough to identify  
5 the so called minimum value of the comparative differences.

3. Process, in agreement with claim 2, characterized by the fact that the realization of the iterative calculations of the differences between positions of  
10 the repeater station include and correct effect caused by temporal changes due to the signal propagation characteristic of the medium in which the system operates, adopting known propagation models, and using elevation angles for the repeater station (R) as seen  
15 from the different bases (A,B,C,D) to determine the accurate and definitive position of the repeater station (R).

4. Process, in agreement with claim 3, characterized by also including another step: the determination of the  
20 repeater station (R) coordinates with corrections for changes in time, frequency or phase, for a given instant of reference.

5. Process, in agreement with any of claims 3 or 4, characterized by also including another step to  
25 disseminate time signals to other points on the ground, with know geographic positions, for synchronization of the respective clocks.

6. Process, in agreement with any of the claims 3 or 4, characterized by also including the following steps:  
30 - emit, from the said reference base and at successive instants, coded signals and to obtain successive coordinates for the repeater station (R), corrected taking into account the time, frequency or phase changes in retransmission and propagation of Said coded  
35 time signals in order to determine the navigation of



the repeater station (R);

- retransmit, by the repeater station (R), the coded time signals to other targets with unknown geographic positions, each one with their own clocks synchronized  
5 to clocks installed at the four reference bases (A,B,C,D);

- obtain distances from the repeater station (R) to the other targets, corrected for the time changes on retransmission and on the propagation in the medium;  
10 and

- determine targets' coordinates by measuring time differences at least three successive instants, with the adoption of changes in time, phase or frequency.

7. Process, in agreement with claim 6, characterized  
15 by also comprehending the step of:

- calculate the distance from the repeater station (R) to the reference bases (A,B,C,D) and to the targets with geographic positions to be determined, with corrections for the time changes at the repeater  
20 station (R) and those caused by the signal propagation in the medium, for repeater station (R) positions at four different instants, which positions are not along a single straight line, defining univocally, at a given arbitrarily selected coordinate system in space,  
25 through four successive measurements, the spatial positioning of the targets, which location are searched.

8. System to determine temporal changes in retransmission and propagation of signals, addressed  
30 for measurement of distances, synchronize actuators and georeferencing, from a remote and inaccessible repeater station (R), containing a transponder, being such system characterized by the fact of comprehending:

a- four reference bases (A,B,C,D) on the ground, every  
35 three of them not collinear, at known geographic

positions and visible from the repeater station (R);

b- one transmitting device (T) provided a tone of the bases (A) capable to emit, at a reference instant, a time coded signal containing the identification of the reference transmitting base (A) and of the instant of emission;

5 c- one receiving device (REC) installed at each one of the four reference bases (A,B,C,D) capable to receive the time coded signal, emitted by the transmitting device (T) and received and retransmitted by the repeater station (R);

10 d- precision clocks (RL) each one installed at every one of the four reference bases (A,B,C,D);

e- one central processing station (E) that receives the coded time signal, retransmitted by the by the repeater station (R), comparing it to the coded time signal generated at the emitting reference base (A) and assigning different arbitrary values for the changes in time, phase or frequency, to the repeater station (R)

15 calculating, for each of the assigned temporal changes, a respective difference between positions for the repeater station (R), obtained with use of two distinct sets of three reference (A,B,C and A,B,D; A,B,C and B,C,D; A,B,D and B,C,D), identifying which value assigned to the temporal change at the repeater (R) results in a minimum difference between the two positions found for the repeater station (R), and processing the corresponding temporal change to determine the position of the repeater station (R); and

20 f- one transmission mean or device (MT) provided at each of three reference bases (B,C,D), distinct from that transmitter that generates the coded time signal, with each transmission mean or device (MT) forwarding to the central processing station (E) the time difference between the coded time signal received from

25

30

35

the transponder at the repeater station (R) and the respective coded time signal generated at each one of the referred three reference bases (B,C,D).

9. System, according to claim 8, characterized by the  
5 fact that the central processing station (E) is defined at the emitting reference base (A), provided with a transmitter (T).

10. System, according to claim 8, characterized by the  
10 fact that the central processing station (E) is able to calculate algebraically the differences between positions of the repeater station (R), assigning certain values for the temporal changes, in sufficient number of assignments to allow the identification of the minimum value for the comparative differences.

15 11. System, according to claim 10, characterized by the fact that the repetition of the iterative calculations of differences between positions of the repeater station (R), processed by the central processing station (E), include the signal propagation velocities  
20 characteristics to the medium where they propagate, obtained from known models, and the elevation angles of the repeater station (R) as seen from the different reference bases (A,B,C,D).

12. System, according to claim 11, characterized by the  
25 fact that the central processing base (E) determine the coordinates of the repeater station (R) with correction of changes in time, frequency or phase, for the given instant of reference.

13. System, according to any one of claims 11 or 12,  
30 characterized by the fact of also include other points on the ground, with known geographic positions, for which the time signals are disseminated, for synchronization of the respective clock systems.

14. System, according to any one of claims 11 or 12,  
35 characterized by the fact of also include other targets

with unknown geographic positions and having their own clocks synchronized to the clocks installed at the four reference bases (A,B,C,D), with reference base (A) emits, at successive instants, coded time signals, with  
5 the central processing base (E) providing successive coordinates for the repeater station (R), corrected for the changes in time, phase or frequency occurred in retransmission and due to propagation of the said time coded signals, determining the navigation of the  
10 repeating station (R); with the said other targets receiving the coded time signals retransmitted by the repeater station (R) with the said central processing station (E) obtaining the distances from the repeater station (R) to the other targets corrected for the  
15 temporal changes in retransmission and in propagation in the medium, and determining the target coordinates by measuring the differences in time at least three successive instants, adopting the corrections for temporal changes in time, phase or frequency and for  
20 propagation in the medium.

15. System, according to claim 14, characterized by the fact that the central processing station (E) calculate the distance of the repeater station (R) to the reference bases (A,B,C,D) and to the targets with  
25 geographic positions to be determined, with corrections for temporal changes at the repeater station (R) and those caused by propagation in the medium, at positions of the repeater station (R) in four different instants, which positions are not in a same straight line,  
30 defining univocally, in any coordinate system in space, the searched spatial position of the target, through four successive measurements.




FIG. 1




FIG. 2



**INTERNATIONAL SEARCH REPORT**

International application No  
PCT/BR2012/000113

**A. CLASSIFICATION OF SUBJECT MATTER**  
 INV. G01S5/02 G01S13/87  
 ADD.  
 According to International Patent Classification (IPC) or to both national classification and IPC

**B. FIELDS SEARCHED**  
 Minimum documentation searched (classification system followed by classification symbols)  
 G01S

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)  
 EPO-Internal, WPI Data

**C. DOCUMENTS CONSIDERED TO BE RELEVANT**

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	WO 2004/023678 A2 (QUALCOMM INC [US]) 18 March 2004 (2004-03-18) abstract; figures 1-3B paragraph [0002] - paragraph [0013] -----	1-15
A	US 7 822 427 B1 (HOU JIONGKUAN [US]) 26 October 2010 (2010-10-26) abstract; figure 2 column 13, line 40 - column 15, line 25 -----	1,8
A	US 2004/219930 A1 (LIN IE-HONG [US]) 4 November 2004 (2004-11-04) abstract paragraph [0011] - paragraph [0015] paragraph [0064] - paragraph [0077] -----	1,8

Further documents are listed in the continuation of Box C.

See patent family annex.

\* Special categories of cited documents :

<p>"A" document defining the general state of the art which is not considered to be of particular relevance</p> <p>"E" earlier application or patent but published on or after the international filing date</p> <p>"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)</p> <p>"O" document referring to an oral disclosure, use, exhibition or other means</p> <p>"P" document published prior to the international filing date but later than the priority date claimed</p>	<p>"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention</p> <p>"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone</p> <p>"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art</p> <p>"&amp;" document member of the same patent family</p>
---	---

Date of the actual completion of the international search  16 July 2012	Date of mailing of the international search report  23/07/2012
---	--

Name and mailing address of the ISA/ European Patent Office, P.B. 5818 Patentlaan 2 NL - 2280 HV Rijswijk Tel. (+31-70) 340-2040, Fax: (+31-70) 340-3016	Authorized officer  López de Valle, J
--	---

# INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/BR2012/000113

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO 2004023678	A2	18-03-2004	
		AU 2003270408 A1	29-03-2004
		CN 1698391 A	16-11-2005
		EP 1535485 A2	01-06-2005
		EP 2187541 A2	19-05-2010
		EP 2407797 A2	18-01-2012
		JP 2005538357 A	15-12-2005
		KR 20050036991 A	20-04-2005
		US 2004048568 A1	11-03-2004
		US 2008146247 A1	19-06-2008
		US 2012094689 A1	19-04-2012
		WO 2004023678 A2	18-03-2004
US 7822427	B1	26-10-2010	NONE
US 2004219930	A1	04-11-2004	
		BR PI0408015 A	21-03-2006
		EP 1600026 A2	30-11-2005
		IL 170579 A	30-11-2010
		JP 2006520171 A	31-08-2006
		KR 20050110654 A	23-11-2005
		MX PA05009418 A	23-11-2005
		US 2004219930 A1	04-11-2004
		WO 2004080105 A2	16-09-2004