



(51) International Patent Classification:
H04B 7/04 (2006.01)

(21) International Application Number:
PCT/EP2010/057397

(22) International Filing Date:
28 May 2010 (28.05.2010)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
09290451.5 15 June 2009 (15.06.2009) EP

(71) Applicant (for all designated States except US): **ALCATEL LUCENT** [FR/FR]; 3, avenue Octave Gréard, F-75007 Paris (FR).

(72) Inventors; and

(75) Inventors/Applicants (for US only): **DARTOIS, Luc** [FR/FR]; Alcatel-Lucent France, Centre de Villarceaux, Route de Villejust, F-91620 Nozay (FR). **BETRENCOURT, Samuel** [FR/FR]; 7 rue du Capitaine Tarron, F-92140 Clamart (FR).

(74) Agent: **NICOLLE, Olivier**; Alcatel-Lucent International, 32, avenue de Kléber, F-92700 Colombes (FR).


(81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LT, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PE, PG, PH, PL, PT, RO, RS, RU, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

(84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Published:

— with international search report (Art. 21(3))

(54) Title: BASE TRANSCEIVER STATION AND ASSOCIATED METHOD FOR COMMUNICATION BETWEEN BASE TRANSCEIVER STATION AND USER EQUIPMENTS



(57) Abstract: The invention relates to a base transceiver station (BTS) for communicating with a plurality of user equipments (UE1, UE2, UE3, UE4, UE5) divided in at least two groups, said base station comprises : - an antenna element arrangement generating at least two shifted static beams (Bi, Bo) with respective down tilts for reaching the user equipments (UE1, UE2, UE3, UE4, UE5) a processing unit (25) connected to said transceiver chains (9) and having means for performing at least two linear complex combinations of up-link digital signals - means for receiving said up-link signals and for selecting per user equipment the appropriate beam based on the quality of said up-link signals in the beam flows (Fi, Fo).

Base transceiver station and associated method for communication between base transceiver station and user equipments

The invention relates to a base transceiver station comprising an antenna element
5 arrangement. The invention also relates to a method to optimize the capabilities offered by such a multiple antenna arrangement. Objective is to optimize the spectrum efficiency using real time analysis of the information extracted within the different beams used to manage the traffic within the same logical cell.

Radio communication networks are equipped with base transceiver stations
10 comprising antennas adapted to cover a predefined cell of the network and communicating with user equipments in this cell. For a given coverage requirement provided the different beams for a given spectrum resources can be optimized in order to reduce the densification requirements assuming radio resources are scarce.

Due to the constraints in term of location for the base stations, it is necessary to
15 be able to optimize the radio cell geometry ($I_i / (I_e + I_i)$ where I_i is the internal cell interference and I_e the interference coming from other cells) to offer the requested Qos per user located in the cell.

With legacy antenna system a unique downtilt which represents the inclination of the antenna in the elevation direction is calculated to provide the appropriate
20 coverage. This downtilt is either fixed or mechanically preset on site or can be remotely modified using a remote control motor able to move the antenna in the elevation direction.

New radio communication networks have the requirement to provide more efficient services in term of bit rate and in term of capacity. The constraints linked to the
25 coverage requirement using a legacy antenna system doesn't offer the flexibility to optimize the coverage / capacity compromise since coverage is always preferred to reduce the sites numbers.

To optimize the capacity / coverage requirements some new methods based on multiple antennas at a base station site have been proposed which tend to parallelize the
30 data transmission (to reach higher bit rate) while limiting the interference (to ensure

-2-

high capacity). Multiple Input Multiple Output (MIMO) and beamforming are such methods.

Further, by splitting the cell and all associated hardware either horizontally (several sectors per cell) or vertically (concentric cells), more user equipments can
5 communicate with the base station.

However, in such a solution, additional antenna arrangement and hardware are required, and then this solution can be relatively expensive.

One object of the invention is to overcome the drawback of state of the art by
10 improving communications between multiple user equipments and the base station without increasing hardware and software.

This objective is achieved according to the invention by a base transceiver station for communicating with a plurality of user equipments divided in at least two groups, said base station comprises :

- 15 – an antenna element arrangement generating at least two shifted static beams with respective down tilts for reaching the user equipments and comprising a plurality of antenna elements respectively connected to transceiver processing chains for exchanging communication signals between the base transceiver station and the user equipments, a processing unit connected to said transceiver chains and having
20 means for performing at least two linear complex combinations of digital signals received between said antenna elements and the base transceiver station for the same spectrum resources, and processing beam flows respectively associated to said generated beams, with up-link signals received from user equipments,
- means for receiving said up-link signals and for selecting per user equipment the
25 appropriate beam based on the quality of said up-link signals in the beam flows.

With such an arrangement, cell coverage is kept while reducing interferences per beam, for maximizing the performances of each group of users, without increasing hardware and software associated to the antenna element arrangement.

Compared to well beam forming features trying to identify a beam per user, the
30 same static and predefined beam is allocated to a group of users.

-3-

Moreover using the two statistic beams, the up-link performances are improved if a user equipment is received within both beams since spatial diversity decorrelates the fadings.

According further embodiments of the invention:

- 5 – said antenna element arrangement is adapted to generate an inner beam and an outer beam, wherein the inner beam reaches user equipments located close to said antenna element arrangement, and the outer beam reaches user equipments located far from said antenna element arrangement,
- 10 – the processing unit comprises means for applying complex antenna weights to said antenna elements, so that said antenna element arrangement generates beams in predefined and elevation direction,
- 15 – said base transceiver station comprises means for comparing the carrier to interference ratio between up-link signals received per beam for the same spectrum resources with a predetermined threshold, to determine the appropriate beam to be used,
- 20 – said base transceiver station comprises means to isolate said up-link signals received per beam,
- 25 – said base transceiver station is configured to identify the appropriate beam for the down-link transmission based on the appropriate beam determined for up-link transmission,
- 30 – said base transceiver station comprises a feedback channel monitoring the quality of the down-link signal to validate said beam selected for down-link transmission,
- 35 – said base transceiver station comprises means for identifying the appropriate down-link resources used per beam to be used and reused in each beam,
- 40 – said processing unit comprises means for directing beam flows with down-link signals to respective beams bound to user equipments using respective beams.

The invention also relates to a method for communication between a base transceiver station and a plurality of user equipments divided in at least two groups, said
30 base station comprises an antenna element arrangement generating at least two shifted

-4-

static beams with respective down tilts for reaching the user equipments and comprising a plurality of antenna elements respectively connected to transceiver processing chains for exchanging communication signals between the base transceiver station and the user equipments, a processing unit connected to said transceiver chains and having means for performing at least two linear complex combinations of digital signals between said antenna elements and the base transceiver station for the same spectrum resources, said method comprising following steps :

- process beam flows respectively associated to said generated beams, with up-link signals received from user equipments,
- 10 - receive said up-link signals and select per user equipment the appropriate beam based on the quality of said up-link signals in the beam flows.

According further embodiments of the invention :

- said method comprises further following steps :
 - for each beam flow, compare the carrier to interference ratio between up-link signals received per beam for the same spectrum resources with a predetermined threshold,
 - 15 • if said ratio meets or exceeds said threshold, select the beam with the highest power level at user equipment location and assign said user equipment to the selected beam,
 - 20 • otherwise combine said beams flows using a maximum ratio combining,
- said method comprises processing step such as multi-user detection, interference cancellation or direct 16QAM demodulation / modulation,
- said method comprises further processing :
 - identify the appropriate beam for the down-link transmission based on the appropriate beam determined for up-link transmission,
 - 25 • monitoring the quality of the down-link signal to validate said beam selected for down-link transmission.

Complexity of the algorithms is reduced since number of users per beam is statistically reduced. On up-link, the reduction of frequency reuse factor (I_e/I_i) and the intra cell interference reduction per beam improves the efficiency of additional

processing step.

Further details and advantages of the invention will become apparent from the exemplary embodiments explained below with reference to figures, in which:

- 5 – figure 1 shows a communication network according to the invention,
- figure 2 illustrates an antenna element arrangement of the communication network of figure 1,
- figure 3 is an example of a transceiver chain of an antenna element arrangement,
- figure 4 illustrates examples of processing of beams flows,
- 10 – figure 5 is a graph illustrating the variation of the power level of two beams projected on cell radius, and
- figure 6 is an example of multiuser detection.

In a multiuser system such as WCDMA (Wideband Code Division Multiple Access), a plurality of users are provided with a communication link from user
15 equipments, such as cellular phone or computer, to a base transceiver station BTS connected to a wired network.

Figure 1 shows an example of the present invention. Multi beam can be used to reach indoor and outdoor users in case of dense urban scenario with building. In the described embodiment, the user equipments UE1 to UE5 are separated into two groups,
20 a first group of indoor users close to the base station BTS and located in an inner cell 1, and a second group outdoor users located in an outer cell 2.

More precisely, all users are managed by the same logical cell object in the network locally divided in two spatial volumes: inner cell1 and outer cell 3,

- two first user equipments UE1 and UE2 are located near the base station BTS in the
25 inner cell 1,
- another user equipment UE3, such as a mobile phone, is located with a higher distance to the base station BTS in-between both cells 1 and 3, and
- two end user equipments UE4 and UE5 (such as a computer) are located in a building covered by the same logical cell in the outer cell 3,

30 As shown in more detail in figure 2, the base station BTS comprises an antenna

element arrangement 5, such as active antenna array or smart antennas, adapted to cover a predefined area in the network.

The antenna arrangement comprises a array of several radiating elements 7, in the simplified example of figure 2, the antenna arrangement comprises four radiating
5 elements 7.

The radiating elements 7 are here patch elements. Alternatively, dipoles may be used.

Each radiating element 7 is connected to a respective transceiver processing chain 9 for transmitting and receiving down-link/up-link communication signals to and
10 from the user equipments UE1 to UE5.

Each transceiver chain 9 comprises a respective transmitter and receiver.

A variant of transceiver processing chain 9 is shown in detail in figure 3.

The processing chain 9 receives as input a sum of baseband signal components. The digital baseband signal is converted to analog signal at module 11, upconverted at
15 module 13, filtered at module 15, pre-amplified at module 17, power controlled at module 19 and amplified at amplifier 21 in the processing chain. A part of the signal at the output of amplifier 21 is fed back for retro loop purpose and the main part of the signal is submitted to the antenna element arrangement, and reversely for the up-link signals. Matching modules 23 are responsible for distributing the input power over the
20 different antenna elements 7.

Not all modules described as part of the processing chain 9 are necessary to reach this effect so that some of these modules may be omitted.

The antenna arrangement 5 (figure 2) is also provided with a processing unit 25 connected to all of the transceiver chains 9.

25 This processing unit 25 comprises signal ports respectively coupled to the transceiver chains 9, and a linear complex combination means (not shown) of the digital signals received from transceiver chains 9 with phase shifter for altering phase difference between the several linear complex combinations, in order to form several phase shifted beams with respective down tilts, for example an inner beam Bi and an
30 outer beam Bo. Phase shifter may be adjustable to vary downtilt of the beams Bi,Bo.

Using this architecture, two or more beams Bi,Bo can be generated for reaching different user equipments UE1 to UE5 without requiring further antenna element nor antenna arrangement and reusing the same radio resources.

5 Further, effect of intra-cell interference is reducing while improving isolation of users signals seen in two groups through both beams Bi,Bo and isolation of their associated beam flows Fi,Fo containers over the Common Public Radio Interface (CPRI). Without end to end isolation gain are only available in the down-link way.

Moreover, each beam Bi,Bo may be generated in predefined elevation directions
10 to be able to reach each group of user equipment with the best accuracy. Such a solution allows maximizing the antenna arrangement gain and increasing the received signal quality preferably reducing the intra and inter-cell interference.

Further, the processing unit 25 is also adapted for sending inner Fi and outer Fo
15 flows associated to the inner Bi and the outer Bo beams to the base station modem NodeB in up-link transmission and for receiving said modem signals to be transmitted to user equipments UE1 to UE5 in down-link transmission, over the Common Public Radio Interface (CPRI) using a suitable multiple access method, such as High Speed Packet Access (HSPA).

20 The modem NodeB can assign user equipments to the inner or outer cell basing on the signal strength of the up-link signals on the dedicated physical control channel (DPCCH) of both beams flows Fi,Fo.

For that purpose, the modem comprises a comparator (not shown) for comparing for each beam flow Fi,Fo, the carrier to interference ratio (C/I) with a predetermined
25 threshold (figure 4).

Thus, in the described embodiment a method for processing multiple antenna elements comprises following steps.

The processing unit 25 (figure 2) performs a first and a second linear complex combinations of all digital signals received from transceiver chains 9. However, the
30 processing unit 25 can perform more than two linear complex combinations.

Then, the processing unit 25 applies a first phase to the first combination so that first down-link signals are transmitted in an inner beam Bi with a given down tilt such as -8° or -10° and having a main lobe covering the inner cell 1. Conversely, up-link signals are received from a reception zone defined by the main lobe (figures 1,2).

5

Similarly, the processing unit 25 applies a second phase to the second combination providing phase shift with the first combination and so that second down-link signals are transmitted in an outer beam Bo with a given down tilt such as -2° and having a main lobe covering the outer cell 3. Conversely, up-link signals are received from a reception zone defined by the main lobe.

10

The processing unit 25 may also apply to each baseband signal input to each transceiver chain, first complex weights for reaching the azimuth direction and second complex weights for reaching the elevation direction. That enables the transceiver chains 9 to control independently the different antenna elements 7 and to use different antenna element weights for each antenna element 7. The location of the user equipment (distance to the base station, azimuth angle, elevation angle) relative to the base station BTS may be reported to the base station BTS so that it can calculate the appropriate complex antenna weights to apply to the different antenna elements 7.

15

20 Up-link transmission

Referring now to up-link transmission, in which up-link signals at same frequency F1 (figure 1) are transmitted from the user equipment to the base station on a link shared by multiple users.

For each user equipment transmission, the modem NodeB receives both beams flows Fi,Fo over the CPRI. The digital signals received are isolated over the CPRI. The nodeB compares per user for each beam flow Fi,Fo for the same spectrum resources, the carrier to interference ratio (C/I) with a predetermined threshold (figure 4).

25

If the C/I ratio meets or exceeds the predetermined threshold, the user equipment is clearly centered under only one beam, then selection of the best beam is performed by a selector of the modem.

30

As illustrated in figure 5, the power level P_i of the inner beam B_i is higher than the power level P_o of the outer beam B_o close to the antenna arrangement 5. On the contrary, the power level P_o of the outer beam B_o is higher than the power level P_i of the inner beam B_i far to the antenna arrangement 5. The situation reverses itself at the crossover point 27.

The modem NodeB assigns a user equipment :

- to the inner cell 1 when the power level P_i of the inner beam B_i is higher than the power level P_o of the outer beam B_o , (left of the crossover point 27 in figure 5), by instance first user equipments UE1 and UE2, and
- 10 - to the outer cell 3 when the power level P_o of the outer beam B_o is higher than the power level P_i of the inner beam B_i , (in figure 5 right of the crossover point 27), by instance end user equipments UE4 and UE5.

Referring again to figure 4, if the C/I ratio doesn't meet or exceed the threshold, that means the user equipment is located in-between both beams B_i, B_o (such as user equipment UE3 in figure 1).

In consequence, Maximum Ratio Combining (MRC) is performed by a MRC module of the modem. In MRC, the received signals are combined based on the assumption that the interference closely approximates white Gaussian noise : each received signal is weighted by a selected weighting factor and the received signals are combined. Spatial diversity is improved for such situation since multi beam guarantee decorrelation between signals reception. Assuming 2 ways spatial diversity are available per beam, performances are equivalent to a 4 way spatial diversity system in the up-link.

Alternatively, only MRC can be performed.

Further processing of the best beam flow or the combined flow are then performed with higher signal to noise ratio (SNR) or carrier to interference ratio (C/I) and permit to extract the information content from each user equipment transmission.

Further processing may be Multi User Detection (MUD), Interference Cancellation (IC) after each connected user is associated to one beam. In the example illustrated in figure 6, a MUD module receives the inner beam flow F_i , the outer beam flow F_o and a MRC combined flow F' , and outputs several signals, here five signals S1

to S5, each of them being associated to a respective user equipment UE1 to UE5.

Moreover, various IC algorithms can reduce effective interference such as successive IC, iterative parallel IC. Spatial interference algorithm could also be used to eliminate the Bi to B0 interference contribution and vice versa.

5 In successive IC, users are ordered by their chance of successful decoding and the packet of the strongest user is decoded first. After a packet is decoded, the signal is reconstructed and subtracted from the received signal. The rest of users are ordered again for next round of decoding. The procedure is performed iteratively over all users. In general, a user decoded later benefits from cancellation of previous users and
10 encounters improved Signal to Interference and Noise Ratio.

In iterative parallel IC, multiple users are decoded and cancelled from the received signal simultaneously.

Users may also be divided into groups and then Parallel IC is performed on high priority groups to low priority groups successively.

15

Down-link transmission

Referring now to down-link transmission in which down-link signals are modulated for transmission to the beams bound for user equipments located under the beams.

20 Key objective is to split the resources per beam in down-link and also identify if these resources can be reused.

When establishing a link with user equipment, the base station estimates the best beam using the signal received from the user equipment. More precisely, the base station uses the information self learned in the up-link to identify for the down-link the
25 best candidate beam.

As described above, this estimation is based on the comparison of the C/I ratio with a predetermined threshold or MRC weighing factor analysis. Then the base station BTS redirects the down-link flow on the best beam with the highest power level.

Outer loop and user feedback equipment analysis is made by the processing unit
30 to validate the down-link beam selection since user equipment and transceiver module

do not have the same antennas gains. Feedback channel monitoring loop ensures the selection based on the up-link signal analysis do not degrade the down-link performances.

Moreover, the base station can identify on real time the best candidate down-link
5 resources (OVSF codes for example in UMTS) used per beam to be used in each predefined beams.

It will be understood by those skilled in the art that more than two groups of users may be created around a base station. The main criteria for creating groups would
10 be to define several angle values corresponding to concentric circles around the base station in which different elevation angles are used for reaching the user located between two concentric circles.

Thus, two or more beams with respective down tilts can be used simultaneously, and by adjusting the down tilts of the beams the coverage of the cell is improved and
15 interferences between cells reduced.

Indeed with this solution, an improvement of interference protection of bearers of the base station modem is noted (i.e. around 3 to 5 dB) what leads to increasing in a cell (i.e. by 50 to 70%) of the number of users that can access to these bearers over the cell coverage.

20 Moreover, there's no increase of overall needed hardware and only some modem software improvement are needed for processing both beams but don't require more processing effort.

CLAIMS

1. Base transceiver station (BTS) for communicating with a plurality of user equipments (UE1,UE2,UE3,UE4,UE5) divided in at least two groups, said
5 base station comprises :
- an antenna element arrangement generating at least two shifted static beams (Bi,Bo) with respective down tilts for reaching the user equipments (UE1,UE2,UE3,UE4,UE5) and comprising :
 - a plurality of antenna elements (7) respectively connected to
10 transceiver processing chains (9) for exchanging communication signals between the base transceiver station (BTS) and the user equipments (UE1,UE2,UE3,UE4,UE5),
 - a processing unit (25) connected to said transceiver chains (9) and having means for performing at least two linear complex
15 combinations of digital signals between said antenna elements (7) and the base transceiver station for the same spectrum resources, and processing beam flows (Fi,Fo) respectively associated to said generated beams (Bi,Bo), with up-link signals received from user equipments (UE1,UE2,UE3,UE4,UE5),
 - means for receiving said up-link signals and for selecting per user
20 equipment the appropriate beam based on the quality of said up-link signals in the beam flows (Fi,Fo).
2. Base transceiver station according to claim 1, wherein said antenna element arrangement is adapted to generate an inner beam (Bi) and an outer beam
25 (Bo), wherein the inner beam (Bi) reaches user equipments located close to said antenna element arrangement, and the outer beam (Bo) reaches user equipments located far from said antenna element arrangement.
3. Base transceiver station according to claim 1 or 2, wherein the processing unit (25) comprises means for applying complex antenna weights to said
30 antenna elements, so that said antenna element arrangement generates beams in predefined elevation direction.

4. Base transceiver station according to any of claims 1 to 3, comprising means for comparing the carrier to interference ratio (C/I) between up-link signals received per beam for the same spectrum resources with a predetermined threshold, to determine the appropriate beam to be used.
- 5 5. Base transceiver station according to any of claims 1 to 4, comprising means to isolate said up-link signals received per beam.
6. Base transceiver station according to any of claims 1 to 5, configured to identify the appropriate beam for the down-link transmission based on the appropriate beam determined for up-link transmission.
- 10 7. Base transceiver station according to claim 6, comprising a feedback channel monitoring the quality of the down-link signal to validate said beam selected for down-link transmission.
8. Base transceiver station according to claim 6 or 7, comprising means for identifying the appropriate down-link resources used per beam to be used and reused in each beam.
- 15 9. Base transceiver station according to any one of the preceding claims, wherein said processing unit (25) comprises means for directing beam flows (Fi,Fo) with down-link signals to respective beams bound to user equipments (UE1,UE2,UE3,UE4,UE5) using respective beams.
- 20 10. Method for communication between a base transceiver station and a plurality of user equipments divided in at least two groups, said base station comprises :
 - an antenna element arrangement generating at least two shifted static beams (Bi,Bo) with respective down tilts for reaching the user equipments (UE1,UE2,UE3,UE4,UE5) and comprising : - 25
 - a plurality of antenna elements (7) respectively connected to transceiver processing chains (9) for exchanging communication signals between the base transceiver station (BTS) and the user equipments (UE1,UE2,UE3,UE4,UE5),
 - 30
 - a processing unit (25) connected to said transceiver chains (9) and

-14-

having means for performing at least two linear complex combinations of digital signals between said antenna elements (7) and the base transceiver station for the same spectrum resources,

said method comprising following steps :

- 5
- process beam flows (F_i, F_o) respectively associated to said generated beams (B_i, B_o), with up-link signals received from user equipments ($UE_1, UE_2, UE_3, UE_4, UE_5$),
 - receive said up-link signals and
 - select per user equipment the appropriate beam based on the quality of
- 10 said up-link signals in the beam flows (F_i, F_o).

11. Method according to claim 10, comprising further following steps :

- for each beam flow (F_i, F_o) per user, compare the carrier to interference ratio (C/I) between up-link signals received per beam for the same spectrum resources with a predetermined threshold,
- 15
- if said ratio (C/I) meets or exceeds said threshold, select the beam with the highest power level at user equipment location and assign said user equipment to the selected beam,
 - otherwise combine said beams flows using a maximum ratio combining (MRC).

20 12. Method according to claim 10 or 11, comprising processing step such as multi-user detection (MUD), interference cancellation (IC) or direct 16QAM demodulation / modulation.

13. Method according to any of claims 10 to 12, comprising further processing :

- identify the appropriate beam for the down-link transmission based on
- 25 the appropriate beam determined for up-link transmission,
- monitoring the quality of the down-link signal to validate said beam selected for down-link transmission.





Fig.3




Fig.5





Fig.6



3/3




Fig.4

INTERNATIONAL SEARCH REPORT

International application No

PCT/EP2010/057397

A. CLASSIFICATION OF SUBJECT MATTER

INV. H04B7/04

ADD.

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, WPI Data, INSPEC

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	WO 2007/091024 A (QUINTEL TECHNOLOGY LTD [GB]; BARKER DAVID EDWIN [GB]; HASKELL PHILIP E) 16 August 2007 (2007-08-16) * abstract page 3, line 25 - line 31 page 4, line 1 - line 5 page 4, line 18 - line 23 page 5, line 5 - line 25 page 10, line 11 - line 35 page 13, line 7 - line 26 page 24, line 19 - page 25, line 18 page 32, line 1 - page 33, line 15 ----- -/--	1-13

☒ Further documents are listed in the continuation of Box C.

☒ See patent family annex.

* Special categories of cited documents:

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier document but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

"&" document member of the same patent family

Date of the actual completion of the international search

7 July 2010

Date of mailing of the international search report

26/07/2010

Name and mailing address of the ISA/

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040
Fax: (+31-70) 340-3016

Authorized officer

Lustrini, Donato

INTERNATIONAL SEARCH REPORT

International application No

PCT/EP2010/057397

C(Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	GOEUSSE F ET AL: "USERS CLUSTERING CONCEPT: DYNAMIC CONCENTRIC CELLS PERFORMANCE IN WCDMA SYSTEM" VTC 2001 SPRING. IEEE VTS 53RD. VEHICULAR TECHNOLOGY CONFERENCE. RHODES, GREECE, MAY 6 - 9, 2001; [IEEE VEHICULAR TECHNOLOGY CONFERENCE], NEW YORK, NY : IEEE, US, vol. CONF. 53, 6 May 2001 (2001-05-06), pages 2369-2373, XP001076182 ISBN: 978-0-7803-6728-9 * abstract paragraphs [001.], [002.], [003.] figures 1,2,4 -----	1-13
A	YUN S ET AL: "Spectrum efficient region-based resource allocation with fractional loading for FH-OFDMA cellular systems" ELECTRONICS LETTERS, IEE STEVENAGE, GB, vol. 41, no. 13, 23 June 2005 (2005-06-23) , pages 752-754, XP006024652 ISSN: 0013-5194 * abstract paragraph [RESOURCEMANAGEMENT] figure 1 -----	1-13

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/EP2010/057397

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO 2007091024 A	16-08-2007	EP 1989789 A2 US 2009058725 A1	12-11-2008 05-03-2009