



(19) **United States**

(12) **Patent Application Publication**

Rogers

(10) **Pub. No.: US 2001/0033649 A1**

(43) **Pub. Date: Oct. 25, 2001**

(54) **SPEAKERPHONE ACCESSORY FOR A TELEPHONE INSTRUMENT**

(75) Inventor: **Steven A. Rogers**, Alton, NH (US)

Correspondence Address:  
**WEINGARTEN, SCHURGIN, GAGNEBIN  
& HAYES, LLP**  
**TEN POST OFFICE SQUARE**  
**BOSTON, MA 02109 (US)**

(73) Assignee: **Cetacean Networks, Inc.**

(21) Appl. No.: **09/779,328**

(22) Filed: **Feb. 8, 2001**

**Related U.S. Application Data**


(63) Non-provisional of provisional application No. 60/181,099, filed on Feb. 8, 2000.


**Publication Classification**

(51) **Int. Cl.<sup>7</sup> ..... H04M 1/00**  
(52) **U.S. Cl. .... 379/388.01**


(57) **ABSTRACT**

An external speakerphone accessory system for a telephone, such as a LAN telephone, which enables the telephone user to place the speakerphone in a location that is convenient for multiple users, and which is not necessarily co-located with the attached telephone itself. The speakerphone accessory obtains all of its power, audio, and control signals from an attached telephone unit through a modified Universal Serial Bus (USB) interface, and includes a power supply system which enables it to obtain a relatively high power level from the telephone to which it is attached. The speakerphone accessory uses a delay detected between when an audio signal is received at a left hand side microphone and when that audio signal is received at a corresponding right hand side microphone to define zones of maximum sensitivity with regard to users of the speakerphone accessory. When such a delay is at least as large as a predetermined threshold, then that audio signal may be considered to be outside a zone of maximum microphone sensitivity with respect to the physical orientation of the speakerphone accessory. A top-mounted center microphone within the speakerphone accessory may also be used to further define the zones of microphone sensitivity with regard to the front or rear of the speakerphone accessory.






**FIG. 1**







**FIG. 2**

Prior Art




**FIG. 3**


Prior Art



**FIG. 4(d)**



**FIG. 5**



**FIG. 6**




FIG. 7(a)






FIG. 7(b)




**FIG. 8**





**FIG. 9(a)**



Screen record for: Frost, Jack

Instrument Serial Number: 343-547-789-2001-34

Switch: Lakeside 2

Switch Slot: 7

Switch Port: 7/24 39

Physical Location: 3-230-4

Instrument Type: SES-2

Instrument Description: Single Executive Station

Extension Number: 6255

User Record 180

User Record for LAN Phone Auto-ID

**FIG. 9(c)**

Location Record Switch: Lakeside 2

Slot: 3


Port:

1	3-230-4	Frost, Jack
2	3-230-3	Conference Room, Small
3	3-231-3	Morgon, Anna
4	4-232-1	Clayton, Jean
5	5-233-1	Brockton, George
6	6-234-1	Unassigned


Location Record 181

Location Record for LAN Phone Auto-ID


**FIG. 9(d)**



**FIG. 10**




**FIG. 11**



Internal Block Diagram for Speakerphone Accessory

**FIG. 12**



**FIG. 13**

## **SPEAKERPHONE ACCESSORY FOR A TELEPHONE INSTRUMENT**

### **CROSS REFERENCE TO RELATED APPLICATIONS**

**[0001]** This application claims priority under 35 USC §119(e) to provisional application Ser. No. 60/181,099, entitled "LOCAL AREA NETWORK (LAN) TELEPHONE INSTRUMENT SYSTEM", and filed Feb. 8, 2000.

### **STATEMENT REGARDING FEDERALLY SPONSORED RESEARCH OR DEVELOPMENT**

**[0002]** N/A

### **BACKGROUND OF THE INVENTION**

**[0003]** The present invention relates generally to accessories for telephone instruments, and more specifically to a speakerphone attachment for a telephone instrument that is directly connected to a data LAN (Local Area Network).

**[0004]** In existing systems, office telephones often feature a "hands-free" built-in speakerphone. However, the effectiveness of such built-in speakerphones is often limited because of the typical placement of the telephone within the office environment. It is often desirable to have a telephone located behind, or to the side, of a user's primary work surface. Moreover, the location of a telephone is often determined so that the primary user has access to the dialing keypad on the telephone. Such a location may result in the telephone being placed a significant distance from the usual location of visitors to the office. However, it may often be desirable for such office visitors to participate in phone calls through the speakerphone. Unfortunately, the effectiveness of existing, built in speakerphones, in such situations may be adversely affected by the relatively remote location of the office visitors from the microphone and speakers of the speakerphone. In particular, the ability of an internal speakerphone to pickup voices originating from the opposite side of a desk is often limited. It would therefore be desirable to have a speakerphone system which better supports participation of persons located at various specific positions within an office environment.

**[0005]** Additionally, the power available to many existing telephone accessories may be insufficient to provide features and/or performance that may be desired in an accessory such as a separate speakerphone accessory. Accordingly, it would be desirable to have a power supply system within a telephone accessory which enables the use of higher power levels than are typically available in existing systems.

### **BRIEF SUMMARY OF THE INVENTION**

**[0006]** Consistent with the present invention, a speakerphone accessory is disclosed, which may be used to conduct "hands-free" telephone conversations. The disclosed speakerphone accessory includes a beam-steering method, which is optimized for use of the device in a small office. The disclosed speakerphone accessory further includes a power supply system which enables the speakerphone accessory to obtain a relatively higher power level from the telephone to which it is attached than is typically obtained in existing systems. In an illustrative embodiment, the speakerphone accessory is operable to respond to an inquiry message regarding its ability to accept the higher power level. Such

an inquiry may, for example, be received from the telephone to which the speakerphone accessory is attached over data lines within a modified USB connection to the telephone. Such a modified USB connection may also be used to provide power from the telephone to the speakerphone accessory.

**[0007]** In an illustrative embodiment, the disclosed speakerphone accessory obtains all of its power, audio, and control signals from an attached telephone unit through a modified Universal Serial Bus (USB) interface. Additionally, the disclosed speakerphone accessory uses the modified USB interface as a source for 48 VDC from the attached telephone unit. The illustrative embodiment further includes a front microphone array and a rear microphone array. The front and rear microphone arrays each include separate microphones mounted on opposite sides of the respective side of the speakerphone accessory. For example, considered from the perspective of a user facing the front of the speakerphone accessory, the front microphone array includes a microphone located on the left hand side of the speakerphone accessory, as well as a microphone located on the right hand side of the speakerphone accessory. Similarly, considered from the perspective of a user facing the rear of the speakerphone accessory, the rear speakerphone array includes a microphone located on the left hand side of the speakerphone accessory, and a microphone located on the right hand side of the speakerphone accessory. The disclosed speakerphone accessory uses any detected delay between when an audio signal is received at a left hand side microphone and when that audio signal is received at a corresponding right hand side microphone to define zones of maximum sensitivity with regard to users of the speakerphone. For example, if the delay between when an audio signal is received at the left front speaker and when that audio signal is received at the right front speaker is at least as large as a predetermined threshold, then that audio signal may be considered to be outside a zone of maximum microphone sensitivity with respect to the front of the speakerphone accessory.

**[0008]** Further in the illustrative embodiment, a top microphone within the speakerphone accessory may be used to further define the zones of microphone sensitivity with regard to the front or rear of the speakerphone accessory. For example, in an embodiment in which a top microphone is located in the center of the speakerphone accessory, such a centrally located microphone may be used to focus the zones of microphone sensitivity with regard to the center of the speakerphone accessory, with regard to both the front and rear of the speakerphone accessory.

**[0009]** The zones of microphone sensitivity provided by the disclosed speakerphone accessory may be used to suppress audio from sources that are not relatively centered with respect to either the front or rear of the speakerphone accessory. Such sources may be considered "off-axis" sources. In this way, a "beam" of microphone sensitivity may be directed towards particular users by physically orienting the speakerphone accessory. Suppression of off-axis audio is performed, in the illustrative embodiment, by audio-subtraction of those received audio signals originating off-axis from the complete received audio signal.

**[0010]** Thus there is provided a speakerphone system which effectively supports participation of persons located at



various specific positions within an office environment. The disclosed speakerphone accessory may be advantageously applied to office environments in which separate offices are provided with their own doors, or to more open, "cubicle" based office environments. Additionally, the disclosed speakerphone advantageously includes a power supply system allowing use of higher power levels than are typically available in existing systems.

#### BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

[0011] The invention will be more fully understood by reference to the following detailed description of the invention in conjunction with the drawings, of which:

[0012] FIG. 1 shows a physical depiction of the LAN telephone, with an operator console accessory unit, and an internal speakerphone unit;

[0013] FIG. 2 depicts a typical Private Branch Exchange (PBX);

[0014] FIG. 3 depicts a typical LAN-PBX system;

[0015] FIGS. 4a-4d show schedule assignment for two of the disclosed LAN phones sharing the same circuit path;

[0016] FIG. 5 depicts an illustrative internal block diagram for an embodiment of the disclosed LAN telephone;

[0017] FIG. 6 depicts an illustrative schematic diagram showing an external power system for an embodiment of the disclosed LAN telephone;

[0018] FIGS. 7(a) and 7(b) show an illustrative schematic diagram for an accessory power system and interface system;

[0019] FIG. 8 shows an illustrative block diagram of an operator console accessory unit;

[0020] FIGS. 9(a), 9(b), 9(c) and 9(d) show software flowcharts and entry fields of an automatic identification system for the disclosed LAN telephone;

[0021] FIG. 10 shows a software flowchart of the disclosed control program change system;

[0022] FIG. 11 shows a physical depiction of the disclosed external speakerphone accessory;

[0023] FIG. 12 shows a block diagram of the disclosed speakerphone accessory;

[0024] FIG. 13 illustrates the beam-steering technique of the disclosed speakerphone accessory.

#### DETAILED DESCRIPTION OF THE INVENTION

[0025] All disclosures of provisional application Ser. No. 60/181,099, entitled "LOCAL AREA NETWORK (LAN) TELEPHONE INSTRUMENT SYSTEM", and filed Feb. 8, 2000, are hereby included by reference herein.

[0026] FIG. 1 shows a physical representation of an embodiment of the disclosed LAN telephone. The embodiment of the LAN telephone shown in FIG. 1 includes a base unit 6 containing electronics circuitry necessary to provide the functions associated with the base unit 6 as described herein. The base unit 6 supports a handset 2, an internal

speaker 5 for speakerphone functions, and a status display 3 for displaying user status information. The base unit 6 may be connected to a data switch via a LAN cable 1, for example by way of a conventional data cable infrastructure, such as that shown in FIG. 3. An accessory connector is provided on each side of the base unit 6, as illustrated by left accessory connector 4. Using the accessory connectors, it is possible to add a variety of accessory devices, including an operator console 7 as shown in FIG. 1, and/or an external speakerphone.

[0027] The internal circuitry of an illustrative embodiment of the base unit 6 is shown in FIG. 5. The embodiment of the disclosed LAN telephone shown in FIG. 5 is implemented as a microprocessor based system. Specifically, a microprocessor 74 is shown attached to a parallel microprocessor bus 76, which provides an interface to various components via its address and data lines. In the embodiment of FIG. 5, the microprocessor 74 may, for example, be a Reduced Instruction Set Computer (RISC) processor, using a 16 bit wide data bus. The bus 76 is also connected to a Read Only Memory (ROM) 56, Flash Memory 57, and a Read And write Memory (RAM) 58. The bus 76 further connects to USB interface circuits 55, as well as input latches 60 and output latches 62. The bus 76 additionally connects to a LAN Media Access Controller 64, a text display 63 and a Digital Signal Processor (DSP) 75.

[0028] The organization of the hardware shown in FIG. 5 advantageously permits features of the disclosed LAN telephone to be implemented using control software. For example, the microprocessor 74 may use three types of memory to store such control software: ROM 56, Flash 57 and RAM 58. The ROM 56 may be used to store the microprocessor's basic initialization program. When the LAN telephone is powered on, usually by attachment to the powered LAN cable 1, the microprocessor 74 first executes a portion of its control code that is stored in the ROM 56. The control code program stored in the ROM 56 causes the microprocessor 74 to initialize all hardware peripherals of the LAN telephone, such as the MAC 64 and the output latches 62. The control code program stored in the ROM 56 further performs a self-test of the LAN telephone. The self test includes checking the microprocessor itself, testing the RAM 58 and performing a checksum verification of the contents of ROM 56 and the Flash memory 57. The ROM 56 also contains program code operable to load the Flash memory from the MAC 64.

[0029] One of the indicators 61, for example a light emitting diode (LED), is placed on the bottom of the LAN telephone, near the LAN connector. This LED indicator is attached to a flip-flop register that automatically resets itself on each power up, thus causing the LED indicator to turn on. As the microprocessor 74 finishes its self-test, it toggles the "set" line on the flip-flop register by activating a one bit port on the output latches 62. This action causes the LED indicator to turn off. In this way, the LAN telephone's main electronics module can indicate if it is functioning properly. The control code instructions stored in the ROM 56 may, in addition, also display an "OK" message in the text display 63. However, in the event that the text display 63 malfunctions, the LED indicator will still operate.

[0030] When the microprocessor 74 finishes executing the control program code stored in the ROM 56, it then executes

control program code stored in the flash memory 57. The main body of the LAN telephone control program functionality is stored in the flash memory 57. Flash memory 57 is advantageously capable of having its contents updated or replaced. Through use of this capability of the flash memory 57, the LAN telephone can be loaded with new program code providing additional or modified functionality. Similarly, a fault or bug in the control program can be repaired, by storing a new program into the flash memory 57. If no program code is loaded in the flash memory 57, or if the program in the flash memory 57 does not yield a proper error check, then the microprocessor will enter an idle state. In this idle state, the microprocessor awaits a new control program to be downloaded into the LAN phone, for example from a LAN switch.

[0031] The RAM memory 58 is used for the storage of program variables and state information. The RAM 58 may have part or all of its memory protected via a "battery backup". In this way variable values can be maintained across a power failure.

[0032] During operation, the disclosed LAN telephone may communicate with other LAN telephones via the LAN to which it is attached. The LAN telephone uses the LAN MAC 64 to send and receive packets of data in Ethernet format. The LAN MAC 64 is connected to the LAN cable using a PHYsical interface (PHY) 65. The PHY 65 provides level and impedance translation, as well as other signal conditioning needed to send packets over a twisted pair wire. The PHY 65 is connected to the LAN Connector 67. The LAN Connector 67 may, for example, be a conventional "RJ" style connector (e.g. RJ-45). The PHY 65 uses two twisted pair wires within the cable bundle attached to the LAN Connector 67, one for transmit data and one for receive data.

[0033] In an illustrative embodiment, the disclosed LAN telephone obtains its operating power from the LAN cable 1 shown in FIG. 1, through the LAN Connector 67. This embodiment makes use of another, normally unused wire pair in the cable bundle to receive power, for example from a LAN switch. The received power is conditioned and voltage translated via the power circuit 66. This power circuit 66 is further described herein with reference to FIGS. 6 and 7.

[0034] The LAN telephone base unit 6, as shown in FIG. 1, includes a number of user buttons, shown for purposes of illustration as key switches 59 in FIG. 5. The key switches 59 may be operated by a user, in order to dial calls, and/or to access various features of the LAN telephone. The states of the key switches 59 are determined by the microprocessor 74 as it reads the contents of the input latches 60. The input latches 60 are connected to the key switches 59. In this way, more key switches can be accommodated, for a given number of input latch ports. The microprocessor 74 reads the key switches 59 periodically, for example, at times determined by an internal interrupt. The microprocessor 74 rejects spurious key transitions, only accepting those that are active for at least a minimum time.

[0035] LED indicators on the disclosed LAN telephone may be used to display call status. The microprocessor 74 may control the state of such indicators, as needed, via commands to the output latches 62.

[0036] The text display 63 in the embodiment of FIG. 5 may, for example, be a two-line Liquid Crystal Display

(LCD). The text display 63 may receive power from a circuit card within the LAN telephone. The microprocessor 74 writes messages to the text display 63 to provide assistance to the user.

[0037] Accessories may be connected to the disclosed LAN telephone via a modified Universal Serial Bus (USB) interface. In the illustrative embodiment of FIG. 5, this interface is provided via USB controllers 55, which are connected to the bus 76. The microprocessor 74 may send and receive messages and commands to accessories via this modified USB interface. The USB Controllers 55 are connected to the left 53 and right 52 accessory connectors via a power conditioning circuit 54.

[0038] Connection to the handset 2 shown in FIG. 1 is made via the DSP 75 shown in FIG. 5. The DSP 75 is an integrated processor that is optimized for manipulating analog signals that are translated into digital form. The DSP 75 is connected to the bus 76. In the embodiment of FIG. 5, the DSP 75 includes an internal dual-port RAM, which is connected to a DSP core processor and to the bus 76. In this way, the DSP 75 may be issued commands and its control program loaded by the microprocessor 74, out of the flash memory 57, over the bus 76. In the embodiment shown in FIG. 5, the DSP 75 also includes an internal ROM, which can contain a basic "Boot" program for the DSP. After initialization, the DSP 75 provides a message, via its dual-port memory, to the microprocessor 74, indicating that the DSP 75 is ready to accept its control program. The control program of the DSP 75 is loaded into DSP memory, by the microprocessor 74, prior to the LAN telephone entering a "Ready" state. In the Ready state, the LAN telephone is ready to accept and place telephone calls.

[0039] The DSP 75 is further shown connected to the analog inputs and outputs via Analog to Digital (A to D) and Digital to Analog (D to A) converters 73. The converters 73 translate the analog, voltage-based signal into a digital signal. In the embodiment shown in FIG. 5, the A to D and D to A converters 73 are combined into one package, providing two-way translation. The handset 2 (FIG. 1), and a headset (not shown), are connected to the base unit via the handset connector 71 and headset connector 70 shown in FIG. 5. The internal speaker 69 and internal microphone 68 shown in FIG. 5 are directly connected to the DSP 75 via a signal conditioning element 72. The signal conditioning element 72 also provides an interface to the handset connector 71 and the headset connectors 70. The signal conditioning element 72 provides signal limiting, gain or attenuation, filtering, and power, as needed.

[0040] To initiate or receive telephone calls, the LAN telephone receives control messages from a switch or telephone server, via the LAN to which it is connected. These messages and associated responses are used to initiate telephony sessions. For example, when a call is in progress, speech audio is received by the microphone of the handset 2, and conveyed through signal conditioning element 72 and converter 73 to the DSP 75. The speech audio is thus sampled and converted into a stream of digital numbers ("samples") by the A-D functionality of the converters 73. Each such number represents the voltage of the received microphone speech signal. The DSP 75 then places these samples in its internal RAM and signals the microprocessor 74 when an appropriate number of samples are ready for

processing. At this point, the microprocessor 74 reads the samples, places them into a packet format consistent with a LAN protocol and the IP (Internet Protocol) protocol, and sends this resulting packet to the LAN switch, via the MAC 64. The resulting packet may, for example, be what is referred to as an "IP over Ethernet" format packet. The DSP 75 may also employ a "compression" algorithm, whereby the number of speech signal samples conveyed to the switch may be reduced. In such an embodiment, as a result of the compression, the microprocessor 74 will have a smaller set of data items to transmit to the distant telephone. Various specific conventional compression algorithms may be employed in this regard. The effectiveness of a given compression algorithm is usually inversely proportional to the quality of the resulting speech, after it is "de-compressed" by the distant telephone. While the microprocessor 74 is accepting speech sample data from the DSP 75 and sending it to the distant telephone via the MAC 64 and LAN switch, it simultaneously must perform the receive function. That is, the microprocessor 74 simultaneously processes received data packets, from the distant telephone, via the LAN switch and the MAC 64. These received packets contain voice data from the distant telephone. The microprocessor 74 accepts these packets, extracts the voice data contained therein, and then transfers the extracted voice data to the DSP 75. The DSP 75 then takes the voice samples, decompresses them if necessary, and provides them to the converter 73, for output to the handset 2 through the handset connector 71. The receive process and transmit process provided through the microprocessor 74 must operate simultaneously, so that voice samples are accepted from and delivered to the A-to-D and D-to-A functions of the converters 73 on time. Normal, uncompressed telephony voice uses a sample rate of 8 kilo-hertz. Thus, the DSP 75 must receive one sample and output one sample every 125 microseconds, in order to support normal telephone speech.

[0041] As mentioned above, prior attempts at implementing a LAN telephone have encountered problems with packet contention. Packet contention may result when packets from other LAN users can be transmitted simultaneously with voice packets, potentially causing interference with the voice packets. Under such circumstances, voice packets may even be lost, causing an audible break in the received speech. In the disclosed LAN telephone this problem is avoided through operation with the disclosed LAN switch, which has extended capability to handle packets with "real-time" delivery needs. The disclosed LAN telephone incorporates a system for transmitting speech data packets such that they will not interfere with packets from other real-time devices on the network.

[0042] The disclosed system includes what is referred to herein as "packet scheduling", and the technology upon which it is based is referred to as "Time Based Routing" or "TBR." In the disclosed system, the LAN switch maintains time synchronization with the LAN telephone via the transmission of a framing message referred to as a "heartbeat packet". The heartbeat packet is used to "lock" the LAN telephone's internal clock to an internal clock of the switch. In this way all LAN telephones in the system (as well as other real-time devices) are able to maintain synchronization with one another. With system wide synchronization thus established, the LAN telephones can operate in connection with schedules which define the reception and transmission of real-time packets.

[0043] FIGS. 4a-4d illustrate schedule assignment for two of the disclosed LAN telephones, which may also be referred to as "IP phones", and which share the same circuit path. The disclosed scheduling system is based on the occurrence of schedules. Schedules are expected time periods during which packet transmissions and/or receptions for one or more packet flows. Schedules occur independently at each switch within the network. A given schedule may apply to the transmit and receive functions of all ports within a switch, or to a subset of the transmit and/or receive functions of one or more ports within a switch. Accordingly, a given switch may operate based on a single schedule, or on multiple schedules. Schedules may be repeated continuously. Alternatively, each schedule may be triggered explicitly in response to a trigger event, as further described below.

[0044] An illustrative schedule interval 40 is shown in FIG. 4(a). Within a schedule interval, packet flow offsets define the beginnings of packets or packet groups associated with packet flows. Packet flows define sets of packets associated with real-time applications, such as would be used to establish a telephone call or session. Accordingly, a packet flow associated with a telephone call or session may be identified by some set of packet header field values that are common to all packets within that packet flow.

[0045] Packet flows are typically unidirectional, and accordingly may be associated with either the transmit or receive function of a switch or telephone instrument. In the case where a packet flow offset is associated with a transmit function, that packet flow offset defines a time within a schedule interval at which transmission of one or more packets for the associated packet flow may be initiated. In the case where a packet flow offset is associated with a receive function, that packet flow offset defines a point in time within a schedule interval at which reception of one or more packets for the associated packet flow may be expected.

[0046] For a given packet flow, different packet flow offsets are established for each switch along the path between a first telephone instrument and a second telephone instrument. The set of offset values associated with a packet flow for all switches along such a path defines a schedule for that packet flow (also referred to as a "packet flow schedule"). A packet flow schedule may also include a schedule interval duration and packet length. A time period within the schedule interval associated with a given packet flow schedule is referred to as the packet flow schedule period.

[0047] As shown in FIG. 4(a), the beginning and/or the end of the schedule interval 40 is defined by the heartbeat packet 41. For example, at the end of the schedule interval 40, the LAN switch may transmit a heartbeat 41 to all of its ports. In an illustrative embodiment, the heartbeat packet 41 is timed to conclude just as the next schedule interval commences. Thus the heartbeat packet 41, when received, allows the disclosed LAN telephone to synchronize its internal clock and schedule interval with the LAN switch. When the LAN telephone establishes a telephone session, it obtains schedule information from a call agent, which is implemented as software executing on a server system, for example attached to or co-existing with the LAN switch. The call agent is operable to communicate with the switch and negotiate schedules for real-time packet traffic.

[0048] After a schedule is established, the call agent sends the relevant schedule information to the LAN telephone. The

LAN telephone is then permitted to send telephone voice packets, one or more together in each burst, at regular intervals. These packets are transmitted in accordance with the schedule information given to the LAN Telephone by the call agent. By transmitting the packets only in accordance with the schedule information provided by the call agent, contention between LAN telephones is eliminated. The call agent thus assigns different schedules for each LAN telephone session traversing a common circuit path.

**[0049]** FIG. 4(b) shows a schedule assignment for a first LAN telephone session with respect to a schedule interval within a first LAN telephone. As part of establishing a packet flow schedule for the telephone session, the call agent has assigned a first packet flow offset for the first LAN telephone that defines the voice packet data transmission 42, as well as a second packet flow offset defining the voice packet data transmission 43. Thus the voice data packets from a first LAN telephone "A" are actually transmitted in accordance with the first packet flow offset and second packet flow offset, as shown by the voice packet(s) data "A1"42 and "A2"43 in FIG. 4(b). For purposes of illustration, the first LAN telephone "A" is transmitting telephone voice data in an uncompressed format, that is, at 8 thousand samples per second.

**[0050]** In FIG. 4(c) a schedule interval for transmission of data is shown for a second LAN Telephone "B". As shown in FIG. 4(c), the call agent has assigned LAN telephone "B" different packet flow offsets within the schedule interval from those assigned to LAN telephone "A". It is not necessary for the LAN switch, or call agent to always assign different packet flow offsets to different LAN telephones. This is only necessary when multiple LAN telephones require a session which must traverse a common circuit. In the example shown in FIGS. 4(a)-4(d), LAN telephones "A" and "B" both communicate with the WAN link. Thus, different packet flow offsets are needed. The call agent has assigned LAN Telephone "B" packet flow offsets resulting in transmission of voice packet(s) data B144 and voice packet(s) data B2. Because schedule intervals are defined on a per port basis with respect to the LAN switch, and the LAN telephone "A" and LAN telephone "B" are connected to the LAN switch via different ports, LAN telephone "A"'s packet data is not seen on LAN Telephone "B"'s schedule interval, and vice versa.

**[0051]** FIG. 4(d) shows the transmission schedule interval for the LAN switch port connected to the WAN interface. Because the sessions for LAN telephone "A" and the LAN telephone "B" pass through the WAN interface, the LAN switch must provide voice data from both LAN telephone "A" and LAN telephone "B" to the WAN Server. Because LAN telephone "A" and LAN telephone "B" have individually assigned packet flow offsets that do not conflict, there is never a situation when the voice packet traffic from one LAN telephone interferes with that from another LAN telephone.

**[0052]** It should be noted that internal to the LAN switch, the handling of LAN traffic is absolute. This means that for a given packet flow offset within a given schedule interval, the switch can "set" the connection. All other traffic destined for a port, at the time of the packet flow offset, must be queued and sent after the scheduled packet flow has concluded. This has two principal benefits: (1) the switch

prevents any other network traffic from interfering with the LAN telephone traffic, and (2) the switch is able to handle a great deal more traffic, for any given amount of packet processing bandwidth. The latter benefit also means that much larger switches can be built, than would otherwise be possible.

**[0053]** When the predetermined amount of data that is to be transmitted at a given packet flow offset has been completely transmitted, if there is no other scheduled data to be transmitted, other unscheduled traffic may be transmitted. For example, if the amount of data to be transmitted at a given packet flow offset is defined in terms of a number of packets, then the switch will count such packets as they are transmitted. When the last packet has traversed the switch, the LAN switch opens the relevant circuit for any other packet traffic that may be queued for the particular destination port. The switch may also allow new packets to enter the switch and be routed in the normal fashion, if such actions would not interfere with other scheduled traffic.

**[0054]** In one embodiment, the disclosed LAN telephone receives it power from the LAN cabling to which it is attached. LAN cables typically have four, individual twisted pair wires per station cable. One pair is used for transmit data, received by the LAN telephone from the LAN switch. Another pair is used for receive data, transmitted from the LAN telephone to the LAN Switch. Two other pairs are often unused or reserved for future expansion. In one embodiment of the disclosed LAN telephone, the unused pairs are doubled up, and used to send power to the LAN telephone instrument, from the switch, or from a power source co-located with the switch. In this way, the disclosed LAN telephone does not need to have an additional power supply, with inconvenient cords. In addition, multiple LAN telephones may be operated by a single supply, which can have battery-backup and thus provide power in the event of a power failure.

**[0055]** An illustrative embodiment of the disclosed LAN telephone power supply system is shown in FIG. 6. The data signals and power come into the telephone circuit card 81 via the LAN Connector 80. In a typical LAN installation, twisted pairs 1 and 2 are used for data, leaving pairs 3 and 4 free for power. In the embodiment of FIG. 6, the power is delivered as 48 VDC. Alternatively, the delivered power could be other voltages, or even AC. However, in some embodiments, 48 VDC is most convenient. The voltage is high so that the current required is as low as possible, for a given power level, since  $P=I*V$  where  $P$ =Power,  $I$ =Current, and  $V$ =Voltage. Typical LAN cable is 24 gauge (AWG) which has a limited current handling capability. At 48 VDC, such conventional cable could deliver a maximum of 24 watts at 500 milliamps of current. Since the power cable is doubled up, it is actually possible to double the power delivered, to 48 Watts. This is more than enough to operate the LAN telephone and attached accessories.

**[0056]** As the power enters the LAN telephone circuit card 81, it connects first to a surge arrester 82. This device, or combination of devices, is used to prevent stray surges from damaging the LAN telephone or propagating to the accessories. The power is then buffered via a low-pass filter network 83. The network 83 is commonly used to filter out any signals, such as data signals, which may have coupled to the power lines. Finally, the power is connected to a 48

VDC to 5 VDC power supply **84**, of the DC-DC converter type. The power supply **84** is used to provide the proper supply voltages to the LAN telephone. These voltages include, for example, 5 VDC and 3.3 VDC, and may include others as well. The DC-DC converter **84** is a switching device, which may transfer nearly all of the input power for use by the LAN Telephone. Further in an illustrative embodiment, the input 48 VDC may also be provided to the accessory power system, after suppression of any surges.

[0057] The disclosed LAN telephone, unlike most other telephones, is capable of supporting a variety of accessories. These accessories include an operator console and an external speakerphone unit. The accessory system is designed for future expansion. In order to facilitate the expansion selection, the LAN telephone uses the Universal Serial Bus (USB) to communicate with the accessories. USB is a relatively simple, fast (1.5 to 480 megabits per second), and standardized bus used for computer devices. In contrast, the disclosed LAN telephone uses a modified USB for interconnection of telephone accessories to the disclosed LAN telephone. One difficulty with the existing USB is that it has only a limited capability to provide power to a connected device. As it is generally known, USB has two wires in the cable, which supply 5 VDC. Current is limited to 0.5 Amp. Additionally, any given device can only use 0.1 Amp. USB allows devices to be chained, so all chained devices must share the same power. This means that the maximum power available is 2.5 Watts, with 0.5 Watt for each device. This is too little for many potential devices. For instance, a typical LED indicator uses 20 milli-Amps. Accordingly, an accessory using the existing USB could have five LEDs, and nothing else. The operator console **7** of FIG. **1**, could easily have 20 or even 100 such LEDs, and require other power as well. Moreover, a speaker phone unit could easily exceed the 2.5 Watt maximum, even if it used all of the USB power. For this reason the disclosed LAN telephone provides a unique, dual-voltage accessory power system. The disclosed dual-voltage accessory power system allows the LAN telephone to alternatively supply power at 48 VDC, instead of 5 VDC, thus increasing the power consumption by a factor of 10.

[0058] An embodiment of the disclosed LAN telephone accessory power system is depicted in FIG. **7(a)** and FIG. **7(b)**. In FIG. **7(a)** is shown a source power system. The source power system of FIG. **7(a)** is used to provide power to the accessory. FIG. **7(b)** depicts an illustrative embodiment of the accessory internal power system. The accessory internal power system receives and converts the power from the source power system, which, for example, is contained within the LAN telephone. The source power is provided by the base unit **6** to the accessory unit via an accessory connector **104**, which is shown for purposes of illustration as a USB "A" connector. The connector **104** includes four wires. Two wires are used for power, specifically power pin **1 100** and ground pin **4 103**. Two other pins are used for data transfers, specifically pin **2 101** and pin **3 102**. Power is supplied on pin **1 100** of the connector **104** at either 5 VDC or at 48 VDC. In the illustrative embodiment of FIG. **7(a)**, the selection of supply voltage is made by the base unit microprocessor **74**. The microprocessor **74** sets an appropriate bit in the output latch **96** to select the proper power supply voltage. For example, the necessary power switch or switches may be implemented as a Double Pole Single Throw or a Double Pole Double Throw with MOSFET (Metal Oxide Semiconductor Field Effect Transistor).

[0059] During operation of the source power system shown in FIG. **7(a)**, default power setting is normally 5 VDC. When an accessory is connected, the accessory is queried by the base unit microprocessor **74**, via the USB interface **55**, to determine if the accessory uses 48 VDC. Such a query may, for example, be provided to the accessory over the data lines of the modified USB interface. A 48 VDC-capable accessory will respond to such a query in the affirmative. If the microprocessor **74** determines that the accessory uses 48 VDC, then the microprocessor **74** switches the voltage to 48 VDC. The 48 VDC is available from the station input power **86**. The 5 VDC power is available from the base unit's power converter **84**.

[0060] The base unit microprocessor **74** monitors the power usage by accessories connected to the base unit. It accomplishes this via a monitoring system. Low value, current sense resistors **98** are connected in series with the 48 VDC and the 5 VDC power lines. A voltage differential is formed across the resistors **98**, as current passes through. When an accessory is connected, a minimum current is passed, causing a small but measureable voltage to be present at the input of the HV and LV comparators **92** and **93**. The purpose of this circuit is to determine if the USB device is connected. In the illustrative embodiment of FIG. **7(a)**, the current threshold is 10 milli-amps. The output of the two comparators is connected to the input buffer **94**. The microprocessor **74** reads the input buffer **94** periodically, to determine if the accessory device is still connected. If the microprocessor **74** determines that the accessory device has been disconnected, then the microprocessor automatically resets the power switch **97** to 5 VDC operation. This action will prevent damage to a non-48 VDC capable USB device. Two comparators and two current sense resistors are required because the minimum currents will be different through each.

[0061] An illustrative embodiment of the disclosed accessory power system is shown in FIG. **7(b)**. The system of FIG. **7(b)** allows the accessory to automatically switch from the low-power to high-power modes. Power enters the accessory via a standard USB "B" connector **105**. The plus 5 VDC is present on pin **1 118**, and the Power ground return is on Pin **4 109**. The current limit **110** and voltage level **108** resistors are connected across the power **118** and ground **109** lines. The voltage developed across the voltage level resistor **108** is connected to the 48 VDC comparator **111**. If the comparator **111** senses that the voltage has exceeded the 5.5 VDC limit for USB, then it provides a control signal to the power select switch **113** and the 48 VDC to 5V DC DC-DC Converter **112**. Accessory Power is 3.3 VDC, normally provided by the 5 VDC to 3.3 VDC Power Converter **114**. The converter **114** can also be implemented as a shunt converter, if the power drain is low. This converter **114** derives its input power from either the input power bus **118** or the 48 VDC to 5 VDC converter **112**. The power select switch **113** may be implemented as a Double Pole Single Throw (DPST) switch, similar the power switch in the source power system **97**. If the voltage is 5 VDC, the 5 VDC to 3.3 VDC Converter **114** receives its power from the Input Power Bus **118**. If the power voltage is higher than 5 VDC, then the converter **114** receives its input power from the 48 VDC to 5 VDC Power Converter **112**. The accessory microprocessor **124** monitors the input buffer **119** to determine if 48 VDC is available. If 48 VDC is present, then the accessory microprocessor **124** can enable functions that

require higher power. Power is provided to the accessory downstream power circuit. The accessory downstream power circuit includes 48 VDC, if available or 5 VDC. The accessory downstream power circuit can then provide power to another accessory, "daisy-chained" from the first accessory.

**[0062]** An embodiment of the LAN Telephone Operator Console is illustrated in **FIG. 8**. The console of **FIG. 8** includes, for example, 100 small buttons and 100 LED indicators. The console of **FIG. 8** allows the user (usually an operator) to monitor the status of up to 100 extensions. A smaller, alternative accessory console embodiment may, for example, support up to 20 extensions. LEDs are individually associated with each button and each extension. An "on" LED indicates that the line is busy. The operator may transfer a call directly by pressing the button associated with the extension, while a current call is connected. The calling party will then be connected to the extension. The console accessory of **FIG. 8** is an example of a device that generally needs more power than 0.5 Watts.

**[0063]** **FIG. 8** shows an internal block diagram of an operator console accessory. The console of **FIG. 8** is controlled via a microprocessor **124**. The microprocessor **124** is connected to a data and address bus **134**, which is used to control and access all of the keys and switches. The microprocessor **124** connects with the USB Interfaces **123**. One of the USB Interfaces **123** is used for "Upstream" communications, to the base unit, and another one is used for "Downstream" communications, to additional accessories. Both USB interfaces have power conditioning circuits **122**, whose operation has been described above in connection with **FIG. 7(b)**. The circuits **122** allow the accessory to derive additional power over the USB interface, with no additional cables or connectors.

**[0064]** The microprocessor **124** also connects to output latches **128** and input latches **129** to enable the unit to read the status of all the buttons. The key switch matrix **130** is read by enabling rows of switches, via output latches **126**, and reading the rows with the input latches **129**. The indicators **131** are operated by setting the corresponding bits in the output latches **132**. For the operator console, there is one bit for each LED indicator. An optional text display **133** is also connected to the data and address Bus **134**. The text display **133** is used to present operator-specific messages to an operator. The design and architecture of the operator console **FIG. 8** is further illustrative of other possible accessory designs.

**[0065]** **FIG. 9** illustrates the disclosed LAN telephone's system for automatic registration with a LAN switch and a call agent. The disclosed system allows the LAN telephone to be moved from one LAN circuit cable or switch port to another, without changing the switch configuration. The disclosed system works by recognizing the specific LAN telephone's serial number, using that serial number to link to a database, and then "learning" the path to the LAN telephone. This process is performed in the call agent and in the LAN Telephone itself. In **FIG. 9(a)** is shown the set-up process to ready the LAN Telephone for regular use. The process shown in **FIG. 9(a)** may be initiated at any time by a "hard" reset of the device. This reset may be accomplished by pressing a partially concealed reset button on the bottom of the telephone base unit **6**. **FIG. 9(a)** shows a software

flowchart of the telephone configuration procedure. The telephone enters the procedure via a hard reset **140**. Upon receiving the reset **140**, the telephone executes an initialization and self-test program at step **141**. During the initialization and self-test program, all of the latches and interfaces of the device are reset and properly configured. Also, the microprocessor **74**, and memories **56**, **57** and **58** are tested, along with the DSP **75**. If the initialization and self-test performed at step **141** complete successfully, then the LAN telephone will display the current revision level of the control program, stored in flash memory **57**, along with an "OK" message, as shown in the power init display **143** of **FIG. 9(a)**. If the program executed at step **141** does not complete successfully, then the display will show "Fail" message, along with some indication as to the nature of the failure, as shown by the fail display **146** of **FIG. 9(a)**. A fail determination at step **145** will also cause the telephone to enter an idle state **144**.

**[0066]** If the initialization and self-test program executed at step **141** is successful, then at step **147** the telephone will prompt the user with a DHCP (Dynamic Host Configuration Protocol) query, as shown by the DHCP display **148** in **FIG. 9(a)**. DHCP is often used in LAN IP-based networks to ease the burden of IP number assignment. The administrator may then choose DHCP="Y" or "N". An input of "Y" will cause the telephone to prompt the user for DHCP information (not shown). An "N" response will cause the telephone to prompt the user to enter the assigned IP number for the LAN telephone at step **150**, and as illustrated in the instrument IP entry display **151**. When this process is complete, at step **152**, the telephone will prompt the user for the Server IP number, as illustrated by the server IP entry display **153**. This number is the IP address of the call agent server, to which the LAN telephone will direct and accept call requests. When the server IP number is entered, then the "Hard Initialization" phase is ended at step **154**.

**[0067]** **FIG. 9(b)** shows the series of steps, and associated displays, by which the disclosed LAN telephone identifies itself to a call agent. The process of **FIG. 9(b)** is entered either via the successful completion of a hard init **160**, or via a power-on reset **161**. In the case of a power-on reset **161**, the LAN telephone has just been connected to the LAN network, or the system power has just been restored, after a complete power failure. When a user moves a telephone from one location to another, the power-on reset **161** is activated. The first step is to complete an initialization and self-test at step **162**, which is essentially the same as performed at step **141** of **FIG. 9(a)** for the hard reset **140**. An initial display is provided at step **163**, as illustrated by init display **164**. This has the same result as before. If the LAN telephone does not fail initialization and self test, as determined at step **166**, then the network registration process begins. Otherwise, if the LAN telephone does fail initialization and self test, then an idle state **165** is entered.

**[0068]** The LAN telephone checks to see if it is configured for DHCP operation at step **168**. As it is generally known, DHCP (Dynamic Host Configuration Protocol) is a protocol that lets network administrators manage centrally and automate the assignment of Internet Protocol (IP) addresses in an organization's network. If the LAN telephone is configured for DHCP operation, then the telephone must access an IP address from the DHCP Server at step **167**, so that it can begin the logon process. If the telephone already has its IP

address assigned, then it proceeds directly to logon step 170. During the logon process performed at step 170, the telephone displays the state and success status of the process as illustrated by logon display 171. First, a logon message is sent to the call agent at step 170, at the call agent's assigned IP address. The telephone determines at step 174 whether a positive response is received from the call agent. If the telephone does not receive a positive response, then it waits a delay of random length at step 169, and returns to step 170. This process will repeat for a limited number of times, in this case, ten times. At step 173, the telephone determines whether the logon has been attempted the maximum number of times permitted before a failure is reported. If the logon attempt is unsuccessful then the telephone displays a logon failure display 175 and enters an idle state. If the logon attempt succeeds, then the telephone enters the "Ready" state at step 176, and displays the normal ready display 177, which typically contains the date and time. The telephone is now ready to make and receive calls.

[0069] The call agent program maintains a database, which contains a number of user records, each of which is keyed to the serial number of a LAN telephone. One of the user records in the database is keyed to the serial number of the illustrative LAN telephone whose operation is described in connection with the steps shown in FIG. 9(b). When the logon request is sent at step 170 of FIG. 9(b), the serial number of the LAN telephone is included in the request, and allows the call agent to determine a user name that is associated with the serial number in the database, accordingly identify the telephone user and call parameters. Such call parameters may, for example, include an associated telephone number, user name, Ethernet MAC (Media Access Control) address, serial number, and/or IP (Internet Protocol) address. By referencing the user name with the serial number, the disclosed system makes it possible to conduct a logon of a LAN phone from anywhere in the network, and as a result adapt the call agent to recognize the extension of that LAN telephone, regardless of where it is located physically.

[0070] In order to create the database, an entry field program automatically assists a system administrator in configuring the LAN telephone. To initialize a LAN telephone, the administrator runs an initialization program. Then, when a telephone is hard reset, as in step 140 of FIG. 9(a), the contents of an administrator record from the database, for that telephone, is displayed on the screen. An illustrative administrator record 180 is shown in FIG. 9(c). The contents of database fields for name and extension number can then be modified or reentered. Subsequently, the new or modified record, for that telephone instrument, is ready for use.

[0071] Other database records, which may be useful to an administrator, may also be provided in an embodiment of the disclosed system. For example, a specific LAN telephone's physical location may be traced, to the office and wall jack, via a location record, such as the illustrative location record 181 of FIG. 9(d). The Location Record 181 displays the location of every LAN telephone, within a network served by a call agent.

[0072] In an illustrative embodiment, the disclosed LAN Telephone may include the ability to accept a new control program. This capability is import to allow for future

upgrades to the telephone instrument's functions. The upgrade is accomplished by sending a new object program code image to each telephone instrument. Such a change in program code must be accomplished with a trusted procedure. Otherwise, the telephone could loose its ability to receive new code, and could further be rendered inoperable. The disclosed LAN telephone may accomplish such a code change by segregating the code into three pieces. For example, a first piece including modules referred to as Init and Com Load may be stored in the ROM 56. These modules are highly tested, designed to support the hardware initialization, and to reliably down load a new control program a call agent. During a code update, the actual control program for the LAN telephone may be temporarily stored, one segment at a time, within the RAM 58, as it is received. Each segment is then loaded into the Flash Memory 57. The control program is then entered, after the initialization sequence is completed, as described above in connection with FIG. 9(b). By storing the Init and Com Load modules in ROM 56, and placing only the control program in Flash Memory 57, no failure of the program load process can prevent the LAN Telephone from retrying the program load. In this way, no failure will permanently disable the LAN Telephone.

[0073] A flow chart of steps performed by an illustrative embodiment of the disclosed LAN Telephone during a control program update is illustrated in FIG. 10. The process of FIG. 10 is entered from a ready state 190. The process is initiated by receipt of an update command at step 191. The update command is sent by the call agent, which may reside on a network telephony server. The control program object code to be provided to the LAN telephone during the update may be stored on the network telephony server. When an operator desires to update the LAN telephones on the network, the operator initiates an update command from a network administration program. The call agent then sends an update command at step 191 to each LAN telephone within the network in turn. For example, the call agent may complete the update process for each individual LAN telephone before moving on to the next LAN telephone. In this way all of the LAN telephones in the network can be updated, automatically. The update process can be scheduled, so that the update is performed in an off hour.

[0074] The LAN Telephone then authenticates the update command at step 192. The LAN telephone may use an encrypted signature system to provide authentication of both the update command and subsequent data messages. Such authentication may be performed using a conventional authentication technique. Further in step 192, after authentication, the LAN Telephone send a response 192 indicating its readiness to receive the new code image. The call agent, in conjunction with the network administration program, then begins transmitting the update image, which is received at step 193. At this time, the entire load process is conducted under the control of control code located in the LAN telephone ROM 56. The load may be performed using IP TCP packet checking, and with a final, complete error check, using a standard CRC (Cyclic Redundancy Check) error checking system at step 195. If the new program image is received correctly, as determined at step 196, then the new control program will complete its load of the flash memory 57 at step 197. Otherwise, an update fail message is transmitted at step 194. In the case of a successful load, the LAN telephone returns an update acknowledge message at step

**198**, and returns to the ready state at step **200**. As the LAN telephone enters the Ready state at step **200**, it will be using the new control program. As the system administrator receives the acknowledgement that the new control program is ready, the system administrator logs the updated LAN Telephone as including its new control program revision, and then moves on to updating the next LAN Telephone scheduled for updating. If an error is detected during the final error check at step **195**, and the LAN Telephone send the update fail message at step **194**, the LAN telephone may then retry the update process. Successful completion of the update process will result in an "OK" revision message in the instrument display, as shown by the update OK display **199**. While the LAN Telephone is undergoing an update, the update program display **201** is displayed on the instrument's status display **3**.

**[0075]** The disclosed LAN Telephone is also capable of supporting a variety of audio accessories. Such accessories may be connected to the LAN Telephone base unit **6** via the enhanced USB system, as disclosed herein. One useful audio accessory is an external speakerphone. Many office telephones feature a "hands-free" built-in speakerphone. The disclosed LAN Telephone may include such a feature as well. However, because of the placement of the telephone on a user's desk, the effectiveness of built-in speakerphones may be limited. Often, a user's telephone is located behind, or to the side of their work surface. As a result, the ability of an internal speakerphone to pickup voices from the other side of the desk is limited. The external speakerphone described herein solves this problem.

**[0076]** An illustrative embodiment of the disclosed external speakerphone **210** is shown in **FIG. 11**. The speakerphone **210** is shown as a pod connected to the base unit **6** (**FIG. 1**), via an accessory cable **217**, through an accessory connector **4** (**FIG. 1**). As a result of the disclosed modifications to the USB interface described herein, the external speakerphone **210** can derive all of its power, audio, and control signals from the LAN Telephone base unit **6** (**FIG. 1**). Thus, the external speakerphone **210** may be placed on the main portion of a user's desk, even between the user and any visitors that may be sitting on the other side of the user's desk. Through its connection to the LAN Telephone, the external speakerphone **210** is able to operate in connection with any call that is active on the LAN Telephone.

**[0077]** The external speakerphone **210** includes two microphone arrays **211** and **214**, located on each side of the pod. The microphone arrays **211** and **214** are used to receive voice audio from the primary telephone user, as well as from visitors to the primary telephone user's office. The microphone arrays **211** and **214**, as well as the top microphones **212**, enable to the LAN Telephone to discriminate and reject voices and noise from other locations in the office. The external speakerphone **210** also includes a speaker **212**, which is used to output voice audio received from the distant party of the telephone connection. Also provided in the speakerphone **210** are a mute button **213**, mute indicator **215**, on-off button **218**, and on-off indicator **219**, which aid in operating the device.

**[0078]** An internal block diagram of an illustrative embodiment of the external speakerphone **210** is shown in **FIG. 12**. The system of **FIG. 12** is shown including a microprocessor **232**, which controls an address and data bus

**238**. Attached to the microprocessor **232**, via the bus **238**, are a number of serial "USB" interface circuits **223**. The circuit(s) **223** is used to communicate digital audio along with command and status information to the microprocessor **232**. In some embodiments of the disclosed speakerphone accessory, two or more USB interfaces may be employed, for the attachment of other accessories. The microprocessor **232** also makes use of ROM **224**, flash memory **225**, and RAM **226**. For example, initialization and update routines may be stored in ROM **224**, the control program for the microprocessor and DSP **231** may be stored in the flash memory **225**, and the variables and buffers may be stored in the RAM **226**. The microprocessor **232** also controls the indicators **230** via output latches **229**, and receives input from buttons **227** via the input latch **228**. Finally, the microprocessor **232** controls the DSP **231** via a dual-port RAM that is internal to the DSP **231**. In this way, the microprocessor **232** is able to load the DSP **231** prior to the beginning of operation. The DSP **231** provides the interface for the microphones **235**, **236**, and **238**, as well as to the speaker **237**. This interface is achieved through Analog to Digital (A to D) and Digital to Analog (D to A) converters **233**. The converters **233** provide the transition between the buffered analog signals and the digital samples of those signals needed by the DSP **231**. The signal conditioners **234** adapt the analog signals to and from the transducers **235**, **236** and **238**, in order to provide levels appropriate for the converters **233**.

**[0079]** The DSP **231** executes a program that performs acoustic echo cancellation, as needed by the telephone network. The DSP **231** supports audio input and output. The DSP **231** performs two mathematical functions. First, the DSP **231** performs a directional algorithm, referred to as "beam-steering", for noise reduction and isolation, which operates to suppress any "off-axis" acoustic signals. Second, the DSP **231** performs a subtraction of received audio. The received audio that is subtracted consists of the audio received by the accessory that is output of the speakers of the accessory. The received audio is subtracted from the input signal obtained from the microphones **235**, **236** and **238**. The object of this acoustic echo canceling algorithm is to eliminate acoustic coupling, coming through the air from the speaker, from the audio signal that is transmitted to the distant end.

**[0080]** A beam-steering technique is provided to suppress all acoustic wave fronts that are not coming directly from in front or behind the speakerphone **246** as shown in **FIG. 13**. **FIG. 13** illustrates the disclosed technique, which operates to accentuate audio within the audio signal received through the various microphones of the device that is received from predetermined "on-axis" sources. The disclosed technique for suppressing off-axis audio signals received from the microphones of the device further operates to assist in beam-nulling with respect to attenuating the audio signal output from the speaker of the device, based on the directionality of the output of the speaker.

**[0081]** The digital sample signals are processed by the DSP **231** such that the delays between the two paths to the microphone arrays are used to subtract out signals that originate from off-axis sources. This is the case with paths "a" and "b" from the off-axis person **240** in **FIG. 12**. Such a delay does not exist between paths "c" and "d" from the centered person **244**. The delays for paths "a" and "b" may,



for example, be in the range of fractions of milliseconds in length. Through this technique, the audio from off-axis person 240 can be effectively suppressed, relative to the audio from the centered person 244. The top microphone 242 can also be used to help center the “beam” of greatest microphone sensitivity, so that the height of the audio sources is also considered. In this way, the top microphone 242 can be used to suppress audio signals that are not centered around a predetermined source height. In this way, two zones of maximum sensitivity are centered on either side of the speakerphone accessory 246. As further shown in FIG. 13, off-axis voice signals may be detected by either of the front microphone array 241 or the rear microphone array 245. Audio components determined to be “on-axis” may further be added to the received audio signal in order to emphasize audio from on-axis sources. Also in FIG. 13, a speaker 243 is shown for outputting audio signals from the speakerphone 246.

[0082] The subtraction of the audio signal output through the speakers from the input audio signal received through the various microphones of the speakerphone accessory may be performed via an algorithm that includes an adaptation aspect which factors in the physical layout of the room or operating environment in which the speakerphone accessory located. Such an adaptation process may operate to output a known signal in order to determine all necessary parameters related to the physical characteristics of the room or other operating environment. This audio adaptation may, for example, include dividing up the received audio from the distant phone into frequency bands and then each octave is processed separately. The objective is to select a subtraction factor that minimizes the presence of known input audio in the transmitted signal. Conventional algorithms of this type are well known, for example making use of Fourier transforms to characterize the office and user acoustic environment.

[0083] While the illustrative embodiments of the disclosed speakerphone accessory shown in FIGS. 11 and 13 have two opposing sides at which users are expected to be positioned, the disclosed speakerphone accessory is not limited to such a configuration. Accordingly, those skilled in the art will recognize that the beam-nulling and beam-steering aspects of the disclosed system may be applied to one or more sides of a speakerphone accessory, and that the speakerphone accessory itself may be embodied in a variety of specific shapes.

[0084] Those skilled in the art should readily appreciate that various functions of the invention may be embodied using software or hardware components, or a combination of software or hardware components. Moreover, while the invention is described through the above exemplary embodiments, it will be understood by those of ordinary skill in the art that modifications to and variations of the illustrated embodiments may be made without departing from the inventive concepts herein disclosed. Accordingly, the inven-

tion should not be viewed as limited except by the scope and spirit of the appended claims.

What is claimed is:

1. A speakerphone accessory, comprising:

a first microphone array, said first microphone array including a left hand side microphone and a right hand side microphone;

a delay measurement subsystem, wherein said delay measurement subsystem is operable to determine a delay between a time at which an audio signal is received at said left hand side microphone and a time at which said audio signal is received at said right hand side microphone; and

an off-axis audio signal suppression subsystem, wherein said off-axis audio signal suppression subsystem is operable to suppress said audio signal in the event said delay is larger than a predetermined threshold.

2. The speakerphone accessory of claim 1, wherein said off-axis audio signal suppression subsystem is operable to suppress said audio signal by subtracting said audio signal from a received audio signal.

3. The speakerphone accessory of claim 1, further comprising:

a center microphone;

wherein said delay measurement subsystem is further operable to determine a second delay between said time at which said audio signal is received by said left microphone and a time at which said audio signal is received by said center microphone; and

wherein said off-axis audio suppression subsystem is further operable to suppress said audio signal in the event that said second delay is at least as large as a second predetermined threshold.

4. The speakerphone accessory of claim 3, further comprising:

wherein said delay measurement subsystem is further operable to determine a third delay between said time at which said audio signal is received by said right microphone and said time at which said audio signal is received by said center microphone; and

wherein said off-axis audio suppression subsystem is further operable to suppress said audio signal in the event that said third delay is at least as large as a third predetermined threshold.

5. The speakerphone accessory of claim 1, wherein said delay measurement subsystem comprises a digital signal processor.

6. The speakerphone accessory of claim 1, wherein said off-axis audio signal suppression subsystem comprises a digital signal processor.

\* \* \* \* \*