

SYSTEM AND METHOD FOR IMPLEMENTING PERSONAL EMERGENCY RESPONSE SYSTEM BASED ON UWB INTERFEROMETER

FIELD OF THE INVENTION

5 [0001] The present invention relates to the field of elderly monitoring using ultra-wide band interferometry, and more particularly, to human respiration feature extraction in personal emergency response system (PERS).

BACKGROUND OF THE INVENTION

10 [0002] Elderly people have a high risk of falling, for example, in residential environments. As most of elder people will need immediate help after such a fall, it is crucial that these falls are monitored and addressed in real time. Specifically, one fifth of falling elders are admitted to hospital after staying on the floor for over one hour following a fall. The late admission increases the risk of dehydration, pressure ulcers, hypothermia and pneumonia. Acute falls lead to high psychological effects of fear and negatively impact the quality of daily life.

15 [0003] Most of the existing personal emergency response systems (PERS), which take the form of fall detectors and alarm buttons, are wearable devices. These wearable devices have several disadvantages. First, they cannot recognize the human body positioning and posture.

[0004] Second, they suffer from limited acceptance and use due to: elders' perception and image issues, high rate of false alarms and miss-detects, elders neglect re-wearing when getting out of
20 bed or bath, and the fact that long term usage of wearable devices might lead to user skin irritations. Third, the wearable PERS are used mainly after experiencing a fall (very limited addressable market).

[0005] Therefore, there is a need for a paradigm shift toward automated and remote monitoring systems.

25

SUMMARY OF THE INVENTION

[0006] Some embodiments of the present invention provide a unique sensing system and a breakthrough for the supervision of the elderly during their stay in the house, in general, and detect falls, in particular. The system may include: a UWB-RF Interferometer, Vector
30 Quantization based Human states classifier, Cognitive situation analysis, communication unit and processing unit.

[0007] One aspect of the present invention provides a method comprising: (i) transmitting, via at least one transmitting antenna, ultra-wide band (UWB) radio frequency (RF) signals at an environment including at least one human, and receiving, via at least one receiving antenna, echo signals from the environment, (ii) processing the received echo signals to yield a range-bin-based slow signal that is spatially characterized over a plurality of spatial range bins, (iii) estimating at least one respiration feature of the at least one human by analyzing the slow signal, and classifying the respiration feature(s) to indicate respiration mode(s) of the human(s).

[0008] According to some embodiments of the present invention, the system may be installed in the house's ceiling, and covers a typical elder's apartment with a single sensor, using Ultra-Wideband RF technology. It is a machine learning based solution that learns the elder's unique characteristics (e.g., stature, gait and the like) and home primary locations (e.g., bedroom, restroom, bathroom, kitchen, entry, etc.), as well as the home external walls boundaries.

[0009] According to some embodiments of the present invention, the system may automatically detect and alert emergency situation that might be encountered by elders while being at home and identify the emergency situations.

[0010] According to some embodiments of the present invention, the system may detect falls of elderly people, but may also identify other emergencies situations, such as labored breathing, sleep apnea, as well as other abnormal cases, e.g., sedentary situation, repetitive non-acute falls that are not reported by the person. It is considered as a key element for the elderly connected smart home, and, by connecting the system to the network and cloud, it can also make use of data analytics to identify new patterns of emergencies and abnormal situations.

[0011] These, additional, and/or other aspects and/or advantages of the present invention are set forth in the detailed description which follows; possibly inferable from the detailed description; and/or learnable by practice of the present invention.

BRIEF DESCRIPTION OF THE DRAWINGS

[0012] The subject matter regarded as the invention is particularly pointed out and distinctly claimed in the concluding portion of the specification. The invention, however, both as to organization and method of operation, together with objects, features, and advantages thereof, may best be understood by reference to the following detailed description when read with the accompanying drawings in which:

[0013] **Figures 1A-1C** are block diagrams illustrating a non-limiting exemplary architecture of a system in accordance with embodiments of the present invention.

[0014] **Figure 2A** and **2B** are high level schematic illustrations of configurations of a linear baseline (SAAA), according to some embodiments of the invention.

[0015] **Figure 2C** illustrates a non-limiting example for image resolution data achieved under the parameters defined above, for the various human posture and ranges from the system,
5 according to some embodiments of the invention.

[0016] **Figure 2D** schematically illustrates the dependency of image resolution on the orientation of the object, according to some embodiments of the invention.

[0017] **Figures 2E-2G** are high level schematic diagrams illustrating conceptual 2D Synthetic Aperture Antennas arrays with virtual displacements, according to some embodiments of the
10 invention.

[0018] **Figures 2H-2J** are high level schematic illustrations of linear antennas arrays, according to some embodiments of the invention.

[0019] **Figures 2K** and **2L** are simulation results that present the field of view of the array designs, according to some embodiments of the invention.

[0020] **Figure 2M** shows simulation results that present the VSWR (Voltage Standing Wave Ratio) with and without metal beams, or walls, according to some embodiments of the invention.
15

[0021] **Figure 2N** and **2O** schematically illustrate an antenna array with tilted baselines, according to some embodiments of the invention.

[0022] **Figures 2P** is high level schematic illustrations of conceptual 2D Synthetic Aperture Antennas arrays providing unambiguous positioning, according to some embodiments of the
20 invention.

[0023] **Figures 2Q** and **2R** illustrate the coverage of the system's surroundings in the non-limiting case of four baselines, according to some embodiments of the invention.

[0024] **Figure 2S** is a high level schematic illustration of the system with two home cells as a
25 non-limiting example, according to some embodiments of the invention.

[0025] **Figure 3A** is a high level schematic block diagram of the system which schematically illustrates modules related to the posture extraction, in accordance with embodiments of the present invention.

[0026] **Figure 3B** is a high level schematic block diagram of the operations performed by a
30 preprocessing unit, in accordance with embodiments of the present invention.

[0027] **Figures 3C** and **3D** are illustrative examples for partially coherent images, according to some embodiments of the invention.

[0028] Figures 3E and 3F are illustrative examples for computed projections on the x, y and z axes of 3D images of a person standing and laying, respectively, in front of the sensor according to some embodiments of the invention.

5 [0029] Figure 3G illustrates schematically seven features on a schematic curve representing an arbitrary projection.

[0030] Figure 3H is an illustration of an exemplary spanning of the features' space by two of the features described above, according to some embodiments of the invention.

[0031] Figure 3I which is a schematic block diagram illustrating a training module in the posture classifier, according to some embodiments of the invention.

10 [0032] Figure 3J is a schematic block diagram of a classifying stage in the posture classifier, according to some embodiments of the invention.

[0033] Figure 4A is a high-level schematic flowchart illustration of exemplary motion feature extraction in feature extractor, according to some embodiments of the invention.

15 [0034] Figure 4B is a high-level schematic illustration of fast and slow signal mapping, according to some embodiments of the invention.

[0035] Figure 4C is a high-level schematic flowchart illustration of exemplary human body target detection, according to some embodiments of the invention.

[0036] Figure 4D is a high-level schematic flowchart illustration of an exemplary slow signal preprocessing unit, according to some embodiments of the invention.

20 [0037] Figure 4E is a high-level schematic flowchart illustration of exemplary Doppler preprocessing and segmentation, according to some embodiments of the invention.

[0038] Figure 4F is a high-level schematic flowchart illustration of an exemplary maximal Doppler frequency extraction, according to some embodiments of the invention.

25 [0039] Figure 4G is an exemplary illustration of a spectrogram of motion over a single range bin in the active area, according to some embodiments of the invention.

[0040] Figure 4H is a high-level schematic flowchart illustration of an exemplary motion energy features extractor, according to some embodiments of the invention.

30 [0041] Figure 4I is a high-level schematic flowchart illustration of an exemplary range-time preprocessing and segmentation flow as part of derivation of energy signature, according to some embodiments of the invention.

[0042] **Figure 4J** is a high-level schematic flowchart illustration of an exemplary over-range energy distribution analysis as part of derivation of energy signature, according to some embodiments of the invention.

5 [0043] **Figure 4K** is a high-level schematic flowchart illustration of an exemplary over-range activity distribution analysis, according to some embodiments of the invention.

[0044] **Figure 4L** is a high-level schematic flowchart illustration of an exemplary motion route energy estimation, according to some embodiments of the invention.

[0045] **Figure 4M**, being a schematic matrix illustration of DTW-based motion route estimation, according to some embodiments of the invention.

10 [0046] **Figure 4N** is a schematic illustration of the possibility to separate different types of motions based on the derived parameters, according to some embodiments of the invention.

[0047] **Figure 5A** is a high level schematic illustration of a human respiration features extraction system within the PERS system, according to some embodiments of the invention.

15 [0048] **Figure 5B** is a high level schematic illustration of a motion rejection filter within the human respiration features extraction system, according to some embodiments of the invention.

[0049] **Figure 5C** is a high level schematic illustration of a time to frequency converter within the human respiration features extraction system, according to some embodiments of the invention.

20 [0050] **Figure 5D** illustrates in a non-limiting manner the product of a pre-emphasis filter and the respiration spectrum, according to some embodiments of the invention.

[0051] **Figure 5E** is a high level schematic illustration of a target localization unit within the human respiration features extraction system, according to some embodiments of the invention.

[0052] **Figure 5F** is a high level schematic exemplary illustration of ROI selection, according to some embodiments of the invention.

25 [0053] **Figure 5G** is a high level schematic illustration of a range bins selector providing a range bin selection, within the human respiration features extraction system, according to some embodiments of the invention.

30 [0054] **Figure 5H** is a high level schematic illustration of a rake combiner with phase shifting within the human respiration features extraction system, according to some embodiments of the invention.

[0055] Figure 5I and 5J provide an exemplary illustration of pre-accumulation phase shifted time signals, and of a post-accumulation respiration echo signal, respectively, according to some embodiments of the invention.

5 [0056] Figure 5K is a high level schematic illustration of respiration features extraction from the time domain, within the human respiration features extraction system, according to some embodiments of the invention.

[0057] Figures 5L and 5M are high level schematic illustrations of a frame average power spectrum estimator and of a PCA-based past projection, respectively, which are used for respiration rate estimation, within the human respiration features extraction system, according to
10 some embodiments of the invention.

[0058] Figure 6A is a table illustrating an exemplary states definition in accordance with some embodiments of the present invention.

[0059] Figure 6B is a table illustrating an exemplary states matrix in accordance with some embodiments of the present invention.

15 [0060] Figure 6C is a table illustrating exemplary abnormal patterns in accordance with some embodiments of the present invention.

[0061] Figure 7 is a diagram illustrating a cloud-based architecture of the system in accordance with embodiments of the present invention.

[0062] Figure 8 is a floor plan diagram illustrating initial monitored person training as well as
20 the home environment and primary locations training in accordance with embodiments of the present invention.

[0063] Figure 9 is a diagram illustrating yet another aspect in accordance with some embodiments of the present invention.

[0064] Figure 10 is a high level schematic flowchart of a method, according to some
25 embodiments of the invention.

[0065] It will be appreciated that for simplicity and clarity of illustration, elements shown in the figures have not necessarily been drawn to scale. For example, the dimensions of some of the elements may be exaggerated relative to other elements for clarity. Further, where considered appropriate, reference numerals may be repeated among the figures to indicate corresponding or
30 analogous elements.

DETAILED DESCRIPTION OF THE INVENTION

[0066] Prior to the detailed description being set forth, it may be helpful to set forth definitions of certain terms that will be used hereinafter.

[0067] The term “slow signal” as used in this application refers to the signal derived from received echo (fast) signals and is spatio-temporally characterized over multiple range bins (as spatial units) and multiple sub-frames (as temporal units).

[0068] The term “motion” as used in this application refers to the motion of the body and/or of body parts without displacement of the whole body as a bulk, such as gestures, limb motions, posture changes such as sitting down or standing up, gait (separated from the displacement), motion suddenness (e.g., possible fall or collapse) etc.

[0069] The term “movement” as used in this application refers to the displacement of a person’s body as a whole, irrespective of the motion of body parts such as the limbs. In certain embodiments, the term “movement” may be used to refer only to radial displacements and radial components of displacement with respect to the antenna, whereas tangential displacement may be discarded. In certain embodiments, tangential components of the displacement may be taken into account as movements as well.

[0070] The terms “transmitting antenna” and “receiving antenna” as used in this application refer are non-limiting in the sense that the system may be configured to transmit signals via antennas denoted below as receiving antennas and receive echo signals via antennas denoted below as transmitting antennas. It is known in the art that the terms “transmitting antenna” and “receiving antenna” are interchangeable in the sense that the associated electronic circuitry may be configured to reverse their respective functions. System optimization may be carried out to determine which antennas are to be operated as transmitting antennas and which as receiving antennas. For the sake of simplicity alone, most of the following description related to transmitting antennas as single antennas and to receiving antennas as baselines (linear arrangements of antennas). It is explicitly noted that receiving antennas may be single antennas and transmitting antennas may be baselines, while maintaining the applicability and scope of the invention as described below.

[0071] In the following description, various aspects of the present invention are described. For purposes of explanation, specific configurations and details are set forth in order to provide a thorough understanding of the present invention. However, it will also be apparent to one skilled in the art that the present invention may be practiced without the specific details presented herein. Furthermore, well known features may have been omitted or simplified in order not to obscure the present invention. With specific reference to the drawings, it is stressed that the particulars shown are by way of example and for purposes of illustrative discussion of the present invention only, and are presented in the cause of providing what is believed to be the

most useful and readily understood description of the principles and conceptual aspects of the invention. In this regard, no attempt is made to show structural details of the invention in more detail than is necessary for a fundamental understanding of the invention, the description taken with the drawings making apparent to those skilled in the art how the several forms of the invention may be embodied in practice.

[0072] Before at least one embodiment of the invention is explained in detail, it is to be understood that the invention is not limited in its application to the details of construction and the arrangement of the components set forth in the following description or illustrated in the drawings. The invention is applicable to other embodiments that may be practiced or carried out in various ways as well as to combinations of the disclosed embodiments. Also, it is to be understood that the phraseology and terminology employed herein is for the purpose of description and should not be regarded as limiting.

[0073] Unless specifically stated otherwise, as apparent from the following discussions, it is appreciated that throughout the specification discussions utilizing terms such as "processing", "computing", "calculating", "determining", "enhancing" or the like, refer to the action and/or processes of a computer or computing system, or similar electronic computing device, that manipulates and/or transforms data represented as physical, such as electronic, quantities within the computing system's registers and/or memories into other data similarly represented as physical quantities within the computing system's memories, registers or other such information storage, transmission or display devices. Any of the disclosed modules or units may be at least partially implemented by a computer processor.

[0074] A sensing system is provided for the supervision and fall detection of the elderly during their stay in the house. The system combines an UWB-RF (ultra-wide band radio frequency) interferometer with a vector-quantization-based human states classifier implementing cognitive situation analysis. The UWB-RF interferometer may implement a synthetic aperture and the human states classifier may have two stages and employ abnormal states pattern recognition. The system may be installed in the house's ceiling, and cover the area of a typical elder's apartment (<100 sqm) with a single sensor, using ultra-wideband RF technology.

[0075] The system may use machine learning to learn the elder's unique characteristics (e.g., body features, stature, gait etc.) and the home environment, and uses a human state classifier to determine the instantaneous human state based on various extracted features such as human posture, motion, location at the environment as well as human respiration. The system may automatically detect, identify and alert concerning emergency situations (particularly falls) that might be encountered by elders while being at home and identifies the emergency situations. The system detects falls as well as identifies other emergency situations such as labor briefing,

sedentary situations and other abnormal cases. The decision process may be done based on the instantaneous human state (local decision) followed by abnormal states patterns recognition (global decision). The system global decision (emergency alert) is communicated to the operator through the communication system and two- ways communication is enabled between the monitored person and the remote operator.

[0076] The system may comprise a communication sub-system to communicate with the remote operator and centralized system for multiple users' data analysis. A centralized system (cloud) may receive data from distributed PERS systems to perform further analysis and upgrading the systems with updated database (codebooks).

[0077] Advantageously, the system may be used as a key element for the elderly connected smart home and by connecting the system to the network and cloud, it can also make a use of big data analytics to identify new patterns of emergencies and abnormal situations. The system overcomes the disadvantages of existing PERS such as wearable fall detectors and alarm buttons, as well as visual surveillance, by recognizing the human body positioning and posture and provides a significant enhancement in acceptability as it overcomes (i) elders' perception and image issues, (ii) high rate of false alarms and misdetections, (iii) elders' neglect of re-wearing when getting out of bed or bath, and (iv) user skin irritations by long term usage of wearable devices. Moreover, it may be used to prevent the first experience of fall (after which the use of wearable devices is first considered) and does not involve privacy issues that visual surveillance system arise.

[0078] **Figures 1A-1C** are block diagrams illustrating a non-limiting exemplary architecture of a system **100** in accordance with some embodiments of the present invention. As illustrated in **Figure 1A**, system **100** may include a radio frequency (RF) interferometer **120** configured to transmit signals via Tx antenna **101** and receive echo signals via array **110-1** to **110-N**. Tx antennas **101** and Rx antennas **110** are part of an antenna array **115**. It should be noted that transmit antennas and receive antennas may take different forms, and, according to a preferred embodiment, in each antenna array they may be a single transmit antenna and several receive antennas. An environmental clutter cancelation module may or may not be used to filter out static non-human related echo signals. System **100** may include a human state feature extractor **130** configured to extract from the filtered echo signals, a quantified representation of position postures, movements, motions and breathing of at least one human located within the specified area. A human state classifier may be configured to identify a most probable fit of human current state that represents an actual human instantaneous status. System **100** may include an abnormality situation pattern recognition module **140** configured to apply a pattern recognition based decision function to the identified states patterns and to determine whether an abnormal

physical event has occurred to the at least one human in the specified area. A communication system **150** for communicating with a remote server and end-user equipment for alerting (not shown here). Communication system **150** may further include two-way communication system between the caregiver and the monitored person for real-time assistance.

5 **[0079]** As illustrated in **Figure 1B**, system **100** comprises a system controller **105**, a UWB-RF interferometry unit **220**, a human state classifier **250**, a cognitive situation analysis module **260** and communication unit **150**, the operation of which is explained below (see **Figure 1C**). UWB-RF interferometry unit **220** comprises a UWB pulse generator **221**, a UWB RF transmission module **121**, UWB transmitting antennas **101** that deliver a UWB RF signal **91** to an
 10 environment **80**, e.g., one including at least one human **90**, UWB receiver antennas **110** that receive echo signals **99** from the scene and UWB RF interferometer **120** that processes the received echo signals and provide signals for extraction of multiple features, as explained below. Tx antennas **101** and Rx antennas **110** are part of antenna array **115**.

[0080] **Figure 1C** is another block diagram illustrating the architecture of system **100** in further
 15 details in accordance with some embodiments of the present invention as follows. UWB-RF interferometry unit **220** transmits an ultra-wideband signal (e.g., pulse) into the monitored environment and receives back the echo signals from multiple antenna arrays to provide a better spatial resolution by using the Synthetic Antenna Aperture approach. For example, UWB-RF interferometry unit **220** may comprise transmission path pulse generator **221**, UWB-RF front end
 20 **223** connected to transmitting antenna(s) **101** and receiving antennas **110-1...110-N**, e.g., arranged in arrays, and configured to transmit UWB RF signals generated by generator **221** to the environment and deliver echo pulses received therefrom to a reception path pro-processing module **222**, possible implementing clutter cancelation with respect to clutter originating from the environment and not from human(s) in the environment. In order to increase the received
 25 signal-to-noise (SNR), the transmitter sends multiple UWB pulses and receiver receives and integrates multiple echo signals (processing gain). The multiple received signals (one signal per each Rx Antenna) are sampled and digitally stored for further signal processing.

[0081] Environmental clutter cancelation **230** may be part of a processing unit **225** as illustrated and/or may be part of UWB-RF interferometry unit **220**, e.g., clutter cancelation may be at least
 30 partially carried out by a Rx path pre-processing unit **222**. The echo signals are pre-processed to reduce the environmental clutter (the unwanted reflected echo components that are arrived from the home walls, furniture, etc.). The output signal mostly contains only the echo components that reflected back from the monitored human body. Environmental clutter cancelation **230** is fed with the trained environmental parameters **232**. In addition, the clutter cancelation includes a

stationary environment detection (i.e., no human body at zone) to retrain the reference environmental clutter for doors or furniture movement cases.

[0082] The environmental clutter cancelation is required to remove unwanted echo components that are reflected from the apartment's static items, such as walls, doors, furniture, etc. The clutter cancelation is done by subtracting the unwanted environmental clutter from the received echo signals. The residual clutter represents the reflected echo signals from the monitored human body. According to some embodiments of the present invention, the clutter cancelation also includes stationary environment detection to detect if no person is at the environment, such as when the person is not at home, or is not at the estimated zone. Therefore, a periodic stationary clutter check is carried out, and new reference clutter fingerprint is captured when the environment is identified as stationary. The system according to some embodiments of the present invention re-estimates the environmental clutter to overcome the clutter changes due to doors or furniture movements.

[0083] Feature extractor **240** that processes the "cleaned" echo signals to extract the set of features that will be used to classify the instantaneous state of the monitored human person (e.g., posture, location, motion, movement, breathing, see more details below). The set of the extracted features constructs the feature vector that is the input for the classifier.

[0084] Human state classifier **250** – The features vector is entered to a Vector Quantization based classifier that classifies the instantaneous features vector by statistically finding the closest pre-trained state out of a set of N possible states, i.e., finding the closest code vector (centroid) out of all code vectors in a codebook **234**. The classifier output is the most probable states with its relative probability (local decision).

[0085] Cognitive Situation Analysis (CSA) module **260** – This unit recognizes whether the monitored person is in an emergency or abnormal situation. This unit is based on a pattern recognition engine (e.g., Hidden Markov Model- HMM, based). The instantaneous states with their probabilities are streamed in and the CSA search for states patterns that are tagged as emergency or abnormal patterns, such as a fall. These predefined patterns are stored in a patterns codebook **234**. In case that CSA recognizes such a pattern, it will send an alarm notification to the healthcare center or family care giver through the communication unit (e.g., Wi-Fi or cellular). Two-way voice/video communication unit **150** – this unit may be activated by the remote caregiver to communicate with the monitored person when necessary. UWB-RF interferometry unit **220** may include the following blocks: (i) Two-Dimensional UWB antenna array **110-1-110-N** to generate the synthetic aperture through all directions, followed by antenna selector. (ii) UWB pulse generator and Tx RF chain to transmit the pulse to the monitored environment UWB Rx chain to receive the echo signals from the antenna array followed by

analog to digital converter (ADC). The sampled signals (from each antenna) are stored in the memory, such as SRAM or DRAM.

[0086] In order to increase the received SNR, the RF interferometer may repeat the pulse transmission and echo signal reception per each antenna (of the antenna array) and coherently integrate the digital signal to improve the SNR.

Antenna array and interferometer

[0087] In order to successfully classify the human posture (based on the received echo signals) from any home location, an optimized 2-Dimensional (2D) switched antenna array with a very wide field of view (FOV) was designed to generate the 3-dimensional (3D) back-projection image with a small, or even with a minimal number of antennas. In order to cover the complete home environment, it may be split into several home cells, each with an installed system that detects and tracks the monitored person through the home environment. Coverage and infrastructure consideration may be used to determine the exact system configuration at different home environment. When the monitored person moves from one home cell to another, a pre-defined set of criteria may be used to determine whether to hand-over the human tracking from one cell to another. The width of the antenna array FOV may be configured to reduce the number of home cells while maintain the system's efficiency and reliability.

[0088] **Figure 2A** and **2B** are high level schematic illustrations of configurations of a linear baseline (SAAA) **110**, according to some embodiments of the invention. **Figure 2A** schematically illustrates an inline configuration with individual elements separated by $D/2$ and a staggered configuration with two lines of alternating elements separated by $D/2$ (on each line elements are separated by D). **Figure 2B** schematically illustrates some more details of linear baseline **110**. **Figure 2C** illustrates a non-limiting example for image resolution data achieved under the parameters defined above, for the various human posture and ranges from system **100**, according to some embodiments of the invention. **Figure 2D** schematically illustrates the dependency of image resolution on the orientation of the object, according to some embodiments of the invention.

[0089] The human posture may be determined by analyzing and classifying the 3-dimensional human image as reconstructed by the back-projection function based on the received echo signals (see above). The image resolution is determined by the interferometer's Down Range (the image resolution in the interferometer's radial direction - ΔR_{dr}) and Cross Range (the image resolution in the interferometer's angular direction - ΔR_{cr}), with ΔR_{dr} determined by the transmitted pulse width and ΔR_{cr} determined by the Antenna Aperture and the range from the interferometer. In order to increase the antenna aperture, a Synthetic Aperture Antenna Array

(SAAA) approach may be used by a switched antenna array. Every SAAA is termed herein a Baseline.

[0090] The resolutions for SAAA (Baseline) **110** is given by $\Delta R_{dr} = c/2B.W.$ and $\Delta R_{cr} = \lambda R/S.A.$ with c being the speed of light, $B.W.$ being the pulse bandwidth, λ being the wave length, R being the range from the system's antenna **110**, and $S.A.$ being the synthetic aperture. ΔR_{dr} and ΔR_{cr} are selected to ensure that classifier **250** can recognize the human posture. As a non-limiting example, the following parameter ranges may be used: $B.W.$ between 1 and 3 GHz (in a non-limiting example, $B.W.=1.5GHz$), λ between 0.03m and 0.1m (in a non-limiting example, $\lambda=0.06m$), f between 3 and 9 GHz (in a non-limiting example, $f=5GHz$), $S.A.$ between 0.1m and 0.7m (in a non-limiting example, $S.A.=0.33m$), $N_{antennas}$ between 3 and 21 antennas per baseline (in a non-limiting example, $N=12$), Antenna spacing between 0.03m and 0.1m (in a non-limiting example, 0.03m) with respect to scene parameters: Ceiling height=2.5m, sitting person height=1m, standing person height=1.5m. Terminated antennas are shown as elements that regulate the operation of the last receiver antennas **110-1** and **110-N** in the row.

[0091] **Figure 2C** presents image downrange and cross-range resolutions with respect to the floor (assuming system **100** is mounted on the ceiling) to a sitting person, a standing person and laying person on floor. The linear baseline may be considered as a switched antenna array in a constant spacing between each antenna element **110-1...110-N**. Specific antenna elements may be selected through a control channel **102** to perform the synthetic aperture.

[0092] **Figure 2D** schematically illustrates the dependency of image resolution on the orientation of the object, according to some embodiments of the invention. The resolution is illustrated schematically by the size of the rectangles in the figure. As seen in **Figure 2C**, the DownRange (DR) resolution is constant (depends on the bandwidth) while the CrossRange (CR) resolution depends on the antenna aperture and on the distance of the human from antenna array **110** of system **100**.

[0093] **Figures 2E-2G** are high level schematic diagrams illustrating conceptual 2D Synthetic Aperture Antennas arrays **115** with virtual displacements, according to some embodiments of the invention. In **Figure 2E**, antenna array system **115** may include several linear arrays of antennas **110A**, **110B**, **110C** and **110D**, as a non-limiting example. Each row (linear antenna **110A-D**) may have a plurality of receive antennas **110-1...110-N** as explained above; and/or additional transmitting and/or receiving antennas may be part of array **115**. As a non-limiting example, one or more Tx antennas **101**, **101A-D** are illustrated at the central region of array **115**. The solid line arrowed X marked **103** in **Figure 2E** illustrates the relative shifts of Tx antennas **101A-D** with respect to Tx antenna **101**.

[0094] In **Figure 2F**, 2D array structure **115** is shown with four baselines (linear arrays) **110A-D** located along sides of a square. Tx antenna(s) **101** may be at the central region of 2D array structure **115**. **Figure 2F** illustrates schematically the effect of using virtual-displacement Tx Antennas **101A-D** as virtual movements of Rx baselines **110A-D** in a same displacement vector (step and direction) as the moves from the respective virtual-displacement Tx Antenna **101A-D** to the original central Tx Antenna **101**. The virtual displacements marked are denoted by broken line arrowed X's marked **113**. Virtual displacement of Tx antenna **101** to **101A-D**, e.g., by toggling between original central Tx antenna **101** and any of virtual-displacement Tx Antennas **101A-D** introduces additional set of echo signals (Scatter) with different Radar Cross Section (RCS) from the target person with different signals' phases as a result of new roundtrip path from transmitting antenna, target, and receiving baselines (antennas arrays). The additional diverse scatter (four additional echo signals sets) improves the reconstructed image in both additional processing gain (target reflection intensity) as well as additional information due to the Tx antenna diversity.

[0095] It is emphasized that the indication of the transmitting antenna(s) as antenna elements **101** (and/or **101A-D**) and the indication of the receiving baseline(s) as antenna elements **110** (e.g., **110A-D**) may be reversed, i.e., antenna elements **101** (and/or **101A-D**) may be used as receiving antennas and antenna elements **110** (e.g., **110A-D**) may be used as transmitting antennas. System **100** may be configured with receiving antennas **101** and transmitting antennas **110**.

[0096] In **Figure 2G**, 2D array structure **115** is shown with four linear arrays **110A-D** located along sides of a square and Tx antenna **101** at the center of the square. Baseline arrays **110A-D** may be virtually displaced (marked schematically by the gray arrowed X's) to yield additional virtual baselines **113A-D** to improve the back-projection image (see above) by increasing the number of echo signals **99** with additional diversity. Virtual displacements of baseline arrays **110A-110D** (**Figure 2G**) may be combined with virtual displacements of Tx antenna **101** (**Figure 2F**) as well as with non-square positions (**Figure 2E**) in any practical configuration to optimize the antenna array configuration with respect to performance, size and cost.

[0097] UWB RF interferometer **120** may be to use multiple antennas to implement virtual displacement of the baselines – either multiple antennas **101** are receiving antennas and the virtual displaced baselines **110** are transmitting baselines, or multiple antennas **101** are transmitting antennas and the virtual displaced baselines **110** are receiving baselines.

[0098] **Figures 2H-2J** are high level schematic illustrations of linear antennas arrays **115**, according to some embodiments of the invention. **Figures 2K** and **2L** are simulation results that present the FOV of the array designs, according to some embodiments of the invention. The

simulations are electromagnetic simulations at the E-Plane. As shown above, the major requirement from the linear antenna array for home environment is having a large field of view, which becomes a real challenge for a UWB antenna array. An innovated approach of widening the antenna array field of view is presented herein. Exemplary implementations of UWB antenna element **110** illustrated in **Figures 2H-2J** provide Field Of View (FoV) performances that are described in **Figures 2K** (for the configuration of **Figures 2H, 2I**) and **Figure 2L** (for the configuration of **Figure 2J**) for a range of UWB frequencies. **Figure 2J** schematically illustrates the addition of (e.g., two) metal beams **114** added along array **110** that widen the FOV, as illustrated in the simulation results in **Figure 2L** (compare the wider FOV with respect to **Figure 2K**). **Figure 2M** shows simulation results that present the VSWR (Voltage Standing Wave Ratio) with and without metal beams **114** (=walls), according to some embodiments of the invention. **Figure 2M** illustrates that metal walls **114** improve the antenna's VSWR at the relevant operation UWB band (4-6GHz) with respect to an antenna lacking walls **114**.

[0099] In certain embodiments, a BALUN (Balance/Unbalance unit) may be located vertically below the antennas strip (e.g., one or more of baselines **110**).

[00100] **Figure 2N** and **2O** schematically illustrate antenna array **115** with tilted baselines **110A-D**, according to some embodiments of the invention. Baselines **110A-D** may be tilted from their common plane, e.g., by a tilt angle α **112** ranging e.g., between 10-60°, so that, when antenna array **115** is installed on a ceiling, baselines **110A-D** do not face directly downwards but somewhat sideways, by tilt angle α **112**. The provided tilt provides a larger field of view of antenna array **115** and hence system **100**. An optimization may be carried out involving as parameters e.g., the antenna array unit vertical dimension (enabling the tilt), the field of view of the baselines and the array, and the degree of overlap between different baselines.

[00101] **Figures 2P** is a high level schematic illustrations of conceptual 2D Synthetic Aperture Antennas arrays **115** providing unambiguous positioning, according to some embodiments of the invention. These embodiments of non-limiting exemplary configurations enable to validate a location of a real target **90A** by eliminating the possible images **95A** and **95B** after checking reflections **99** received at corresponding sub-arrays of antennas **110A** and **110D**, respectively. It is well understood that these configurations are non-limiting examples and other antennas configurations may be used effectively. Any combinations of embodiments of antenna arrays **115** illustrated herein are also considered part of the present invention. Two-dimensional array **115** guarantees that echo signals **99** are received from any direction around array **115** (assuming that each baseline **110A-D** has a field of you of at least **120** degrees), and as shown in the illustration, solves the direction ambiguity of each individual baseline.

[00102] Figures 2Q and 2R illustrate the coverage of the system's surroundings in the non-limiting case of four baselines 110A-D, according to some embodiments of the invention. In Figure 2Q, the coverage 117A-D of each baseline 110A-D is illustrated alongside uncovered angular ranges 116A-D. For the sake of clarity, single baseline 110 with coverage angular ranges 117 and uncovered angular ranges 116 is also illustrated. In this schematic non-limiting illustration, coverage angular ranges 117 are considered as being within the primary beam of the baseline (-3dB), between +60° and -60°. It is noted that wider or narrower definitions may be alternatively used with respect to the baseline and system performance and requirements.

[00103] Figure 2R exemplify possible angular ranges 117A-D in degrees (relating to 360° as the full circle coverage around array 115, i.e., $360^\circ/30^\circ$) which cover the whole range around array 115 with overlaps in baseline ranges covered by two baselines. The FoV is defined as the -3dB points and may be designed to cover 120° ($\pm 60^\circ$). Baselines 110 may be arranged to cover 360° with respect to array 115 with a certain overlap between baselines 110. Complementarily, baselines 110 may be arranged to solve the human target direction ambiguity by sufficient coverage and overlap requirements. Similar consideration may be taken with respect to either or both primary and secondary beams.

[00104] Figure 2S is a high level schematic illustration of system 100 with two home cells 108A and 108B as a non-limiting example, according to some embodiments of the invention. In some houses/apartments environments 80, PERS system 100 may comprise more than one sub-systems 100A, 100B and/or more than one antenna arrays 115A, 115B to cover whole environment 80 effectively and to monitor target person 90 everywhere in environment 80. For example, home environment 80 may be split into several home cells 80A, 80B, with respective sub-systems 100A, 100B and/or antenna arrays 115A, 115B that create respective sub-cells 108A, 108B. Sub-systems 100A, 100B, etc. may each comprise, e.g., a UWB RF interferometry unit, a human state feature extractor and a human state classifier. Control unit 105 of system 100 regulates (e.g., according to a pre-defined set of criteria) hand-overs between sub-systems 100A, 100B and/or between antenna arrays 115A, 115B as monitored person 90 moves between home cells 108A, 108B, while maintaining continuous detection and tracking. Examples for handing over criteria comprise: (i) $BPI_i > BPI_j$ with BPI being the back-projection (accumulated) intensity from the monitored person as received at PERS_i 100A and PERS_j 100B; and/or (ii) $PDR_i < PDR_j$ with PDR being the person down range distance from PERS_i 100A and PERS_j 100B as is estimated by each PERS unit. Abnormality situation pattern recognition module 140 of system 100 may be further configured to integrate input from all sub-systems 100A, 100B etc.

[00105] The multiple PERS sub-systems may hand-over person tracking among themselves by any of the following exemplary ways: (i) Hard hand-off: Once the handing over criteria are

fulfilled by the releasing PERS unit, the person's tracking is moved from the releasing PERS unit which stops the tracking to the receiving PERS unit that starts tracking (break before make); (ii) Soft Hand-off: Once the handing over criteria are fulfilled by the releasing PERS unit, the person's tracking is moved from the releasing PERS unit that keeps tracking the person and
 5 sends the information to the receiving PERS unit that starts tracking the person. The realizing PERS unit stops tracking when the receiving PERS acknowledges that it successfully tracks the person (make before break); and (iii) Co-tracking: Each PERS sub-system that sufficiently identifies the person performs the tracking as long as the received scatter signal doesn't decrease below a predefine threshold from the maximum received signal among all the active PERS units.
 10 In this mode, the system decision is based on majority based voting between all the PERS units.

Multiple Features extraction

[00106] Multiple features may be extracted y processing unit **225** from received echo signals by interferometer **120**. For example, processing unit **225** may be configured to process the
 15 received echo signals to derive a spatial distribution of echo sources in the environment using spatial parameters of transmitting and/or receiving antennas **101**, **110** respectively, with features extractor **240** being configured to estimate a posture of at least one human **10** by analyzing the spatial distribution with respect to echo intensity, as explained in detail below. For example, processing unit **225** may be configured to cancel environmental clutter by filtering out static non-
 20 human related echo signals, process the received echo signals by a back-projection algorithm, and analyze the spatial distribution using curve characteristics of at least two projections of an intensity of the received echo signals onto a vertical axis and at least one horizontal axis, as explained below.

[00107] The "cleaned" echo signal vectors may be used as the raw data for the features
 25 extraction unit. This unit extracts the features that mostly describe the instantaneous state of the monitored person. The following are examples for the set of the extracted features and the method it's extracted: Position – the position is extracted as the position (in case of 2D – angle/range, in case of 3D – x,y,z coordinates) metrics output of each array baseline. The actual person position at home will be determined as a "finger print" method, i.e., the most proximity to
 30 the pre-trained home position matrices (centroids) codebook. Posture – the person posture (sitting, standing, and laying) will be extracted by creating the person "image" by using, e.g., a back-projection algorithm. Both position and posture are extracted, for example, by operating, e.g., the Back-projection algorithm on received echo signals – as acquired from the multiple antennas array in SAR operational mode.

35

Human posture

[00108] One aspect of the present invention provides a unique human posture sensing and classification system and a breakthrough for the supervision of the elderly instantaneous status during their stay in the house, in general, and extracting features of the human position and posture in particular. The innovated system may be part of the Personal Emergency Response system (PERS) installed in the house's ceiling, and covers a typical elder's apartment (<100 sqm) with a single sensor. The innovated system helps detecting and alerting an emergency situation that might be encountered by elders while being at home. The innovated system may also enable the long term monitoring of elderly activities and other behavioral tendencies during the staying at home.

[00109] The following is an outline of the procedure used to find the human position and posture, comprising the following steps: Dividing the surveillance space into voxels (small cubes) in cross range, down range and height; Estimating the reflected EM signal from a specific voxel by the back projection algorithm; Estimating the human position by averaging the coordinates of the human reflecting voxels for each baseline (Synthetic Aperture Antenna Array); Triangulating all baselines' position to generate the human position in the environment; Estimating the human posture by mapping the human related high-power voxels into the form-factor vector; and Tracking the human movements in the environment (bedroom, restroom, etc.).

[00110] **Figure 3A** is a high level schematic block diagram of system **100** which schematically illustrates modules related to the posture extraction, in accordance with embodiments of the present invention. As explained in detail above, system **100** comprises UWB-RF interferometer **120** associated with antenna array **115** and delivering the received echo signals to home environment clutter cancellation **230**. The echo signals are then delivered to a pre-processor **302**, a human posture image back-projection reconstruction module **310**, possibly with floor enhancement **312** and projection on the x, y, z axes **315** and finally to posture features extractor **240A** (as part of feature extractor **240**) and consequently to posture classifier **250A** (as part of classifier **250**) which derived a classified posture **317**, possibly using codebook **234**.

[00111] Environmental clutter cancellation **230** may be configured to remove the unwanted echo components that are reflected from the apartment's static items as walls, door, furniture etc. The clutter cancellation may be carried out by subtracting the unwanted environmental clutter from the received echo signals. The residual clutter (scatter) represents the reflected echo signals from the monitored human body. System **100** may be configured to estimate (e.g., implementing a learning algorithm) the environmental clutter (to be cancelled) when there is no person at the environment, e.g., the person is not at home, or is not at the estimated zone, and use the estimated clutter for clutter cancellation **230**. Environmental clutter cancellation module **230** may

comprise a stationary environment detector that decided when the unit may re-estimate the environmental clutter, possibly with an addition manual control to perform the initial estimation during the system setup.

[00112] Figure 3B is a high level schematic block diagram of the operations performed by preprocessing unit 302, in accordance with embodiments of the present invention. Preprocessing unit 302 may be configured to perform the following blocks for each of the received echo (fast) signals: DC removal 302A by continuously estimating the DC signal (time varying DC). The estimated DC signal is subtracted from the original signal. Gain mismatch correction 302B may be performed to compensate for the path loss differences among each of the interferometer's antennas received fast signals. Phase mismatch correction 302C may be performed to compensate for the time delay among the fast signals. An out of band (O.O.B.) noise reduction filter 302D (matched filter) may be configured to filter out the out of pulse bandwidth noise and interferences.

[00113] Monitored the person's posture (e.g., sitting, standing, and laying) may be extracted (240A) by creating the person's low resolution "image", corresponding to a spatial distribution of echo sources, by using back-projection algorithm 310. For example, position and posture may be extracted by operating back-projection algorithm 310 on received echo signals as acquired from the multiple antennas array in Synthetic Aperture Antenna Array (SAAA) operational mode, illustrated in Figure 2E.

[00114] For example, 3D back-projection may be formulated as indicated in Equations 1, by defining the locations of a J- transmitting antenna elements as the transmitting array (e.g., either of antennas 101 or antennas 110) and a K-receiving antenna elements as the receiving array (e.g., the other one of antennas 101 or antennas 110), expressing the received fast signals denoted J · K and deriving the absolute image value I(V_m) using the confocal microwave imaging algorithm, applied to any selected voxel V_m in the region of interest.

J- transmitting antenna elements (transmitting array) located at - $\{x_{tj}, y_{tj}, z_{tj}\}_{j=1}^J$

K- receiving antenna elements (receiving array) located at - $\{x_{rk}, y_{rk}, z_{rk}\}_{k=1}^K$

J · K received fast signals are - $\left\{ \left\{ s_{j,k}(t) \right\}_{j=1}^J \right\}_{k=1}^K$ where $0 \leq t \leq T$.

Voxel V_m = (x_m, y_m, z_m)

$$I(V_m) = \left| \sum_{j=1}^J \sum_{k=1}^K s_{j,k} \left(t_{j,k}(V_m) \right) e^{j\varphi_{j,k}(V_m)} \right|$$

Equations 1

[00115] The summation is over all the received fast signals $s_{j,k} \left(t_{j,k}(V_m) \right)$, and it contains the reflections equivalent to the round-trip, which is the total distance $t_{j,k}(V_m)$ from each of the transmitting antennas to the specific voxel V_m and the distance from this specific voxel V_m to each of the receiving antennas, as calculated in **Equations 2** in terms of the coordinates of the transmitting and receiving arrays. The phase $\varphi_{j,k}(V_m)$ is also calculated as presented in **Equations 2**. c denotes the speed of light and f_c denotes the central frequency.

$$t_{j,k}(V_m) = \frac{l_{j,m}(V_m) + l_{m,k}(V_m)}{c}$$

$$l_{j,m}(V_m) = \sqrt{(x_{tj} - x_m)^2 + (y_{tj} - y_m)^2 + (z_{tj} - z_m)^2}$$

$$l_{m,k}(V_m) = \sqrt{(x_m - x_{rk})^2 + (y_m - y_{rk})^2 + (z_m - z_{rk})^2}$$

$$\varphi_{j,k}(V_m) = \frac{2\pi f_c}{c} (l_{j,m}(V_m) + l_{m,k}(V_m))$$

Equations 2

[00116] The image, expressing the spatial distribution of the echo sources, may be reconstructed from the absolute image values $I(V_m)$ by computing them for all the voxels in the region of interest Ω , i.e., $I(V_m) = I(x_m, y_m, z_m)$, $x_m \in \Omega_x$, $y_m \in \Omega_y$, $z_m \in \Omega_z$. This derived image is denoted in the following the “Coherent Image”, as it is a coherent accumulation of the fast signals’ intensity contributions from the Rx antennas. A “Partially Coherent Image”, which is a more sophisticatedly-derived spatial distribution of the echo sources, may be derived from several “2D Coherent Images” which are each reconstructed from a subset of fast signals, and are then multiplied by each other, as illustrated in **Equations 3**. **Equations 3** relate as a non-limiting example to a single transmitting antenna ($J=1$) and 32 receiving antennas ($K=32$) in four subsets (Baselines - BL_i). (e.g., corresponding to central transmitting antenna **101** and receiving baseline **110**).

“Partially Coherent Image”: $I(V_m) = \prod_{i=1}^4 I_i(V_m)$

“Coherent Images” (from subsets $1 \leq i \leq 4$): $I_i(V_m) = \left| \sum_{j=1}^i \sum_{k=1}^8 s_{j,k} \left(t_{j,k}(V_m) \right) e^{j\varphi_{j,k}(V_m)} \right|$

subset 1: $BL_1 = \{s_{1,1}(t), s_{1,2}(t), \dots, s_{1,8}(t)\}$

subset 2: $BL_2 = \{s_{1,9}(t), s_{1,10}(t), \dots, s_{1,16}(t)\}$

subset 3: $BL_3 = \{s_{1,17}(t), s_{1,18}(t), \dots, s_{1,24}(t)\}$

subset 4: $BL_4 = \{s_{1,25}(t), s_{1,26}(t), \dots, s_{1,32}(t)\}$

Equations 3

[00117] **Figures 3C** and **3D** are illustrative examples for partially coherent images, according to some embodiments of the invention. **Figures 3C** and **3D** are partially coherent images of a standing person and a laying person, respectively. As seen in **Figure 3C** and **3D**, the echo sources are detected as a spatial distribution with a spatial resolution depending on the sizes of the voxels. The echo sources may be characterized, e.g., in terms of human postures, according to the calculated and processed spatial distribution. High power voxels may be defined by a specified power threshold, and used, possibly enhanced, to derive the posture features.

[00118] Floor enhancement module **312** is configured to compute a floor enhancement 3D image, denoted $I(X, Y, Z)$, from the Back-Projection 3D image generated by module **310**. In the floor enhancement image the intensity is increased in the region of interest, e.g., the lower part of the 3D image that corresponds to the floor. In the process, the 3D image is divided into e.g., three levels: the lower cube level (floor region), the intermediate (transition) region, and the upper level. For example, floor enhancement may be implemented multiplying the voxel intensity of floor region voxels by a factor greater than one, not altering the upper level voxels, and multiplying the intermediate (transition) region voxels by a smoothing function, such as the function exemplified, in a non-limiting manner, in **Equation 4**, with *MaxWeight* being the multiplication factor for floor region voxels and z being the height above the floor.

$$FloorEnhancementFunction(z) = \begin{cases} MaxWeight, & z < 50[cm] \\ \frac{MaxWeight - 1}{100 - 50} z, & 50[cm] \leq z \leq 100[cm] \\ 1, & z > 100[cm] \end{cases}$$

Equation 4

[00119] Module **315** is configured to perform 3D image projection on the x , y , z axes, e.g., of the floor enhancement 3D image, by compressing the 3D image into three 1D signals for convenient processing. For this purpose, the projection of $I(X, Y, Z)$ on axes x , y and z , denoted P_x , P_y and P_z , may be computed according to **Equations 5**. It is noted that one or more projection axis may be used, e.g., a vertical axis and one or more horizontal axes.

$$\begin{aligned} P_x &\triangleq P(X = x) = \sum_y \sum_z I(X = x, Y = y, Z = z) \quad \forall x \in \Omega_x \\ P_y &\triangleq P(Y = y) = \sum_x \sum_z I(X = x, Y = y, Z = z) \quad \forall y \in \Omega_y \\ P_z &\triangleq P(Z = z) = \sum_x \sum_y I(X = x, Y = y, Z = z) \quad \forall z \in \Omega_z \end{aligned}$$

Equations 5

[00120] **Figures 3E and 3F** are illustrative examples for computed projections on the x, y and z axes of 3D images of a person standing and laying, respectively, in front of the sensor according to some embodiments of the invention. It is noted, e.g., that the z projection for the standing person image (**Figure 3E**) is typically different than the z projection for the laying person image (**Figure 3F**).

[00121] Various features may be computed for the three projections, P_i ($i=x, y \text{ or } z$), such as: Standard Deviation(P_i), Kurtosis(P_i), Skewness(P_i), Max(P_i), Argmax(P_i), Min(P_i), Argmin(P_i), RightPosition(P_i), LeftPosition(P_i), Width(P_i), and so forth. The first three features are statistical characteristics of the curves, namely their second, third and fourth standardized moments (centered moments) defined in **Equations 6**, with p_i denoting the projections, x_i denoting the respective axis points ($p_i = P_d(x_i)$ with $d \in \{X, Y, Z\}$ and $x_i \in \Omega_x$) and $\bar{p}$ denoting the average of p_i with N_d denoting the total samples per axis, i.e. N_x , N_y or N_z . **Figure 3G** illustrates schematically seven features on a schematic curve representing an arbitrary projection. The features relating to the right and left of the curve may be defined as being at an intensity below a specified threshold with respect to the maximum, e.g., the threshold being between 5%-15% of the maximal intensity. The shorthand “arg” refers to the respective argument (axis value) and the width is defined between the right and left positions.

$$\begin{aligned}\bar{p} &= \frac{1}{N_d} \sum_{i=1}^{N_d} p_i \\ Std(P_d) &= \sqrt{\frac{1}{N_d} \sum_{i=1}^{N_d} (p_i^2 - \bar{p})} \\ Skewness(P_d) &= \frac{\frac{1}{N_d} \sum_{i=1}^{N_d} (p_i - \bar{p})^3}{Std(P_d)^3} \\ Kurtosis(P_d) &= \frac{\frac{1}{N_d} \sum_{i=1}^{N_d} (p_i - \bar{p})^4}{Std(P_d)^4}\end{aligned}$$

Equations 6

[00122] **Figure 3H** is an illustration of an exemplary spanning of the features' space by two of the features described above, according to some embodiments of the invention. The features are seen to correlate with respect to different posture of the person, such as standing, sitting and laying.

[00123] Returning to **Figure 3A**, posture classifier **250A** receives the extracted features vector from posture features extractor **240A**, the posture features vector comprising the selected set of the features that were extracted from the projections P_x , P_y and P_z . Classifier **250A** is configured

to determine whether the person is in a standing, sitting or laying posture, for example according to the following example.

[00124] A set of all the possible postures is defined as $\tilde{C} = \{posture_1, posture_2, \dots, posture_c\}$ with c denoting the total number of postures, for example, $\tilde{C}$ may be a set of postures: {standing, sitting, laying}. $X_{posture_i}$ is defined as the set of template features vectors attributed to $posture_i$ and is used to train the classifier and creating the codebook, as illustrated in **Figure 3I** which is a schematic block diagram of a training module **251** in posture classifier **250A**, according to some embodiments of the invention. The training phase of classifier **250A** may comprise preprocessing **251A**, configured to scale each feature, e.g., to have the variance in each of the features as a known constant and then, using a training process **251B**, creating codebook **234** (used later for the actual classification) of code-vectors, which projects the complete set of the various features vectors into a smaller subset. Training process **251B** may be implemented by various methodologies, of which two are exemplified in the following in a non-limiting manner. One example is a 'Supervised Vector Quantization (VQ)', in which codebooks **234** are created according to the number of postures, e.g., for $C=3$ postures, K centroids (centroids are the centers of distributions according to a given measure, for example n -dimensional means) may be defined per posture, resulting in $3 \cdot K$ centroids denoted as $\left\{ \left\{ \mu_{k,c} \right\}_{k=1}^K \right\}_{c=1}^3$. Another example is a 'One Codebook VQ', in which one codebook is created for all the postures' feature vectors, without posture distinction. For example, K centroids may be defined for all the postures as $\{\mu_k\}_{k=1}^K$. Moreover, for each centroid the internal distribution for each posture, denoted as the conditional probability of a posture given the centroid - $P(posture_i | centroid_j)$, may be determined. The prior matrix, expressed in **Equation 7**, is defined as having rows that correspond to the centroids and columns that correspond to the probability of each posture given this centroid. The classifying phase (**250A**) depends on the selected training methodology and resulting codebook(s) **234**, as exemplified below.

$$PriorMatrix = \begin{bmatrix} P(posture_1 | centroid_1) & \cdots & P(posture_c | centroid_1) \\ \vdots & \ddots & \vdots \\ P(posture_1 | centroid_K) & \cdots & P(posture_c | centroid_K) \end{bmatrix}$$

Equation 7

[00125] **Figure 3J** is a schematic block diagram of a classifying stage **252** in posture classifier **250A**, according to some embodiments of the invention. In classifying phase **252**, new feature vectors are entered into a preprocessing unit **252A** and posture classifier **250A** computes the best posture fit out of all postures represented in codebook(s) **234**, e.g., by using a pre-defined cost function **252B**. For example, cost function **252B** of the 'Supervised VQ' methodology may be defined as the minimum distance across all the centroids. The classified posture is the posture

attributed to the minimum distance centroid. In the second example, cost function **252B** of the 'One Codebook VQ' methodology may be defined as in **Equation 8**, relating to the definitions of **Equation 7**, with x being the tested feature vector, $P(x|centroid_j)$ calculated using the normal distribution $N(x|\mu_j, \Sigma_j)$ and $P(centroid_j)$ estimated using the total vectors attributed to each of the centroids,

$$\begin{aligned}\hat{i} &= \operatorname{argmax}_i P(posture_i|x) = \operatorname{argmax}_i [\sum_j P(posture_i, centroid_j|x)] = \\ &\operatorname{argmax}_i [\sum_j P(posture_i|centroid_j, x) P(centroid_j|x)] \cong \\ &\operatorname{argmax}_i [\sum_j P(posture_i|centroid_j) P(centroid_j|x)] = \\ &\operatorname{argmax}_i [\sum_j P(posture_i|centroid_j) P(x|centroid_j) P(centroid_j)]\end{aligned}$$

Equation 8

[00126] Alternatively or complementarily, Support Vector Machine (SVM) classification may be implemented as posture classifier **250A**, in which the features vectors are represented as linear lines that are formulated as a set of cost functions. An unknown test vector is evaluated by these cost functions and the classification is determined according its results.

Human motion

[00127] Human motion – The monitored human body may create vibrations and other motions (such as gestures and gait). Therefore, it introduces frequency modulation on the returned echo signal. The modulation due to these motions is referred to as micro-Doppler (m-D) phenomena.

The human body's motion feature may be extracted by estimating the micro-Doppler frequency shift vector at the target distance from the system (down range). The following description and **Figures 4A-4N** elaborate on the aspect of human motion features extraction.

[00128] It is noted that the term "motion" refers to the motion of the body and/or of body parts without displacement of the whole body as a bulk, such as gestures, limb motions, posture changes such as sitting down or standing up, gait (separated from the displacement), motion suddenness (e.g., possible fall or collapse), etc. The term "movement" refers to the displacement of a person's body as a whole, irrespective of the motion of body parts such as the limbs (in case of movement detection by backpropagation algorithms, the movement may comprise only the radial components of displacement).

[00129] Non-wearable monitoring system **100** may comprise ultra-wide band (UWB) radio frequency (RF) interferometer **120** configured to transmit UWB RF signals at, and to receive echo signals from, an environment including at least one human, processing unit **225** configured to processing derive, e.g., at a slow signal derivation module **226**, a range-bin-based slow signal from the received echo signals, the slow signal being spatio-temporally characterized over a

plurality of spatial range bins and a plurality of temporal sub-frames, respectively, and feature extractor **240** configured to derive from the slow signal a Doppler signature and a range-time energy signature as motion characteristics of the at least one human.

[00130] The Doppler signature may be derived by comparing spectral signatures of sub-frames in the slow signals, which are related to identify human-related range bins and sub-frames. The energy signature may be derived by evaluating powers of the slow signal at identified human-related range bins and sub-frames. The Doppler signature and/or the energy signature may be derived with respect to different body parts of the at least one human.

[00131] Feature extractor **240** may be further configured to derive location data to yield movement characteristics of the at least one human. The location data may be derived by detecting displacements of the at least one human using back-projection and/or by identifying human-related range bins and sub-frames in the slow signal. The derivation of the location data may be carried out using a spatio-temporal histogram of the range-time energy signature, by identifying on the histogram range changes of at least body parts of the at least one human.

[00132] System **100** may further comprise human state classifier **250** configured to classify the motion and movement characteristics of the at least one human to indicate a state of the at least one human, and abnormality situation pattern recognition module **262**, e.g., as part of cognitive situation analysis module **260** configured to generate an alert once the indicated state is related to at least one specified emergency. The classification may be carried out by identification of a most probable fit of one of a plurality of predefined states to the motion and movement characteristics and wherein the alert generation is based on pattern recognition with respect to previously indicated states.

[00133] **Figure 4A** is a high-level schematic flowchart illustration of exemplary human motion features extraction **241** in feature extractor **240**, according to some embodiments of the invention. The Human Motion Features Extractor system receives a UWB echo signal **401** and processes it according to the following blocks. Detailed descriptions of modules in **Figure 4A** are presented in consecutive figures.

[00134] Echo (fast) signal preprocessing unit **405** receives the echo signals from antennas **110-1** to **110-N**. Each pulse transmission is represented by a vector that is referred to in the following as the 'fast time signal'. The transmission-reception cycle is performed repeatedly for a frame of, e.g., $T_{\text{frame}} = 2$ to 5 seconds at a rate of, e.g., $F_{\text{slow}} = 100\text{Hz}$ to **300Hz** as non-limiting values. The output of unit **405** is a matrix of the received echo signals, where each row is a fast time signal of a different transmission.

[00135] Range bin based slow signal constructor (Fast2Slow) **410** rearranges the downrange echo (fast) signals vectors (the matrix rows) to represent the cross-range (slow) signals **411** (the

matrix columns), as illustrated in **Figure 4B** below. The slow signal vector represents a single downrange distance (bin) with a sampling rate, e.g., $F_{\text{slow}} = 100\text{Hz}$ to **300Hz** as a non-limiting value. These vectors are referred as the 'slow time signals'.

[00136] Human body (target) detection is carried out by detecting its representation by a range bins window of e.g., $RW_{\text{target}} = 50$ to 200 range bins (assuming, in a non-limiting manner, that each range bin is approximately 1cm), in a non-limiting example. The target location may be determined by the range bins window with the highest motion power among all of the RW_{target} bins windows. The slow signal may be preprocessed for each range bin separately and may include DC removal, which is done by the subtraction of the estimated average DC signal from the original signal as well as other optional signal adjustments for example gain and phase mismatch correction between all the range bins slow signals and out-of-band noise reduction filtering.

[00137] Feature extraction **241** may be separated into two components – motion Doppler characteristics derivation **420A** (motion Doppler features) and motion change over range bins and time characteristics derivation **420B** (motion energy features). Motion features extraction **241** yields a motion features vector **440** which is then used for further processing and classification in classifiers **130** and/or **250**. The following demonstrates in a non-limiting manner possible embodiments of derivations **420A**, **420B**.

[00138] Motion characteristics detection **420** may comprise deriving from the slow signal a Doppler signature, e.g., by block **420A**, and a range-time energy signature, e.g., by block **420B**, as motion characteristics of the at least one human.

[00139] Motion characteristics detection **420** may comprise, concerning derivation of Doppler signature **420A**, Doppler preprocessing and segmentation **422** in which the slow signal frame is divided into $M_{\text{subframes}}$ sub-frames using **Equation 13** (see below). The spectrogram may be generated by fast Fourier transform (FFT) for each slow time signal sub-frame within the human target range. A maximal Doppler frequency extractor **424** may use the maximum Doppler frequency to identify the instantaneous moment and range that a rapid motion (such as falling) has occurred. This feature is extracted by scanning all the slow time signal sub-frames per each range bin and accumulating the related power spectrum with the highest motion (Doppler) frequency that is selected out of each range bin. The maximal Doppler feature is extracted from the accumulated range bins power spectrums. A Motion Energy Extractor **426** may estimate the motion energy features in the frequency domain. There are a few features that are extracted to better represent the overall motion energy.

[00140] Motion characteristics detection **420** may comprise, concerning derivation of energy signature **420B**, Range over Time preprocessing and segmentation **432** in which the signal is

preprocessed and segmentation of the data into histograms is performed. For example, at a first stage, a Dynamic Time Wrapping (DTW) process may be implemented to estimate the human motion path along the range bins window and at a second stage, e.g., three histograms, which contain information about the distribution of the motion activity and energy signature over range, are generated to represent: (i) Cumulated energy of all the range bins selected; (ii) The numbers of appearances of each range bin in the top 5 range bins; and (iii) The number of average energy for each range bin that appeared in the top 5 ranges bins list. For each histogram, a set of features may be extracted to represent the histogram form factor, for example: (i) Motion energy distribution analysis **434** which comprises the extraction of features that represent the distribution of the energy over the range bins, carried out e.g., by using the energy distribution histogram analysis over range bins; (ii) Motion over range distribution analysis **436** to represent the distribution of the active range bins during the motion period and helps determine if the motion is stationary in space or distributed among several range bins; and (iii) Motion route energy estimator **438** which extracts the motion route energy by accumulating the power over the motion path (the selected range bins power as a result of the DTW at the pre-processing unit).

[00141] **Figure 4B** is a high-level schematic illustration of fast and slow signal mapping **410**, **411**, according to some embodiments of the invention. The received preprocessed fast signals are mapped in a two dimensional matrix X (**Equation 9**). Each echo sample is an element on the matrix $[n][k]$; $n = 1 \dots N_{\text{Ranges}}$; $k = 1 \dots K_{\text{Samples}}$, where n is the downrange bin indicator of spatial range bin, and k is the cross-range (slow) time indicator of temporal bins. The number of total range bins is determined by the scanning window, while each range bin represents C/F_{fast} meters (F_{fast} is the echo signal sampling rate). The matrix is separated into its rows. Each row x_n is the echo signal from the same range from the interferometer (radar), sampled in $F_{\text{slow}}=250$ Hz. Those vectors are referred as the slow time signals.

$$X(x[n][k]) = \begin{bmatrix} x[1][1] & \dots & x[1][K] \\ \vdots & \ddots & \vdots \\ x[N][1] & \dots & x[N][K] \end{bmatrix} \quad \text{Equation 9}$$

[00142] **Figure 4C** is a high-level schematic flowchart illustration of exemplary human body target detection **452**, according to some embodiments of the invention. Human Body Target Detection unit **452** narrows the focus of the analysis to the relevant range bins with human presence. Unit **452** may operate with various inputs, according to the required features to be extracted. The process of the target detection given the slow time signals of all the N range bins is performed by the following blocks, as an exemplary embodiment. A range bin power calculator **452A** calculates the power of each slow time vector by **Equation 10**, where k and n are the time and range bin indicators respectively, to yield N power values.

$$p[n] = \sum_{k=1}^K x_n^2[k] \text{ for } n = 1 \dots N_{Ranges} \quad \text{Equation 10}$$

Following, the power sequence over a sliding window of RW_{target} range bins is calculated along the $(N_{Ranges} - RW_{target} + 1)$ windows (Eq. 2.2) and accumulated by accumulator **452B**, according to **Equation 11**.

$$s[n] = \sum_{j=0}^{M-1} p[j+n] \text{ for } n = 1 \dots (N_{Ranges} - RW_{target} + 1) \quad \text{Equation 11}$$

Finally, the human target location region is detected **452C** and indicated at the most powerful windowed power as expressed in **Equation 12**.

$$Windicator = \operatorname{argmax}_n(s[n]) \quad \text{Equation 12}$$

[00143] **Figure 4D** is a high-level schematic flowchart illustration of an exemplary slow signal preprocessing unit **454**, according to some embodiments of the invention. It is noted that **Figure 4D** is similar to **Figure 3B** presented above, and is repeated here to maintain the flow of explanation in the present context. The signal processing itself may be similar or differ in details with respect to posture features extraction. The slow time signal preprocessing may be carried out in a generic unit having its input determined by the extracted features (e.g., of features vector **440**) and optionally operating on each slow time signal separately. Preprocessing unit **454** may perform the following blocks: (i) Adaptive DC removal **454A** by continuously calculating the estimated DC signal (time varying DC) for each time bin by **Equation 13**, using the current slow signal vector $x[k]$,

$$s[k] = (1 - a)s[k - 1] + ax[k], k = 1 \dots K_{Samples} \quad \text{Equation 13}$$

where a , is the learning coefficient. The estimated DC signal is subtracted from the original signal, namely $y[k] = x[k] - s[k]$. Gain mismatch correction **454B** may optionally be performed to the selected range bins' slow signals to compensate the path losses differences among the selected range bins. The additional path loss of R_i versus R_{min} may be calculated as $\Delta P.L. [dB] = 20 \log\left(\frac{R_i}{R_{min}}\right)$, where R_i is the range bin i distance out of the selected set of range bins and R_{min} is the first (closest) range bin. A slow signal phase mismatch correction **454C** among the selected range bins may be carried out to compensate for the motion offset over the time/range bin. That is, the same motion profile may be preserved between neighbor range bins with a delayed version. The slow signal phase mismatch correction may estimate the phase error between $SlowSig_{Ri}$ and $SlowSig_{Rref}$, where $SlowSig_{Ri}$ is the slow signal of range bin R_i , and $SlowSig_{Rref}$ is the slow signal that is considered the reference range bin out of the selected range bins. Optionally, an out of band (O.O.B.) noise reduction filter **454D** may be enabled to filter out the irrelevant slow signal components or interferences that might influence the performance of the various energy based features extraction.

[00144] **Figure 4E** is a high-level schematic flowchart illustration of exemplary Doppler preprocessing and segmentation **422**, according to some embodiments of the invention. A spectrogram **422A** for each range bin may be generated and used for extraction of signal's spectral features, for every short time period, termed herein sub-frame (e.g., a plurality of specific fast signal times, i.e., a range of k values). The sub-frame period should be short enough to consider the motion as stationary). In order for a spectrogram to be created from a slow time signal vector of a specific range bin in the target region, slow time signal **411** of each range bin is first preprocessed by a preprocessing unit **422B**, and then a human motion target detection unit **422C** is being used to find the target range bin. Spectrogram **422A** of each range bin is generated by segmenting the original signal $x[k]$ to $M_{\text{subframes}}$ sub-vectors. For a given window size and number of overlaps, a new vectors group is constructed according to **Equation 14**.

$$\{v_m[i]\} = \{x[L_{\text{step}}m + i]\}; i = 1 \dots D; m = 1 \dots M_{\text{subframe}} \quad \text{Equation 14}$$

Each vector may have, as a non-limiting example, D_{WinSize} may be between 50 and 200 samples (equivalent a subframe length of between 0.15 and 2 seconds) with overlaps of $(D_{\text{WinSize}} - L_{\text{step}})$ samples from the previous vector in the sequence (L_{step} = is the samples step size between subframes). Then, a power spectrum V_m may be computed for each sub-frame by **Equation 15**, where h is a hamming window with length D .

$$\{V_m\} = FFT\{v_m \cdot h\}; m = 1 \dots M_{\text{subframes}} \quad \text{Equation 15}$$

This process is repeated for every range bin within the target region. RW_{target} spectrograms **422D** are gathered for further processing.

[00145] **Figure 4F** is a high-level schematic flowchart illustration of an exemplary maximal Doppler frequency extraction **424A**, according to some embodiments of the invention. Maximal Doppler frequency extractor **424** is configured to find the highest velocity of the motion, which is represented by the motion's Doppler frequency along the motion's down-range route. The timing of the human peak motion activity is not common for all range bins, due to the fact that the motions can cross range bins versus the time. Therefore, the maximal Doppler frequency feature is extracted by scanning all the slow time signal sub-frames per each range bin and accumulating the related power spectrum with the highest motion (Doppler) frequency that is selected out of each range bin. The max Doppler feature may be extracted from the accumulated range bins power spectrums. In order to extract the action power spectrum by extractor **424B** from each range bin spectrogram, the following process is performed: Noise level threshold estimation computation **424C** calculates the noise level threshold for the spectrogram energy by considering the spectrogram values below noise level are considered as not related to human motion. A threshold T_1 (measured in dB) may be determined by **Equation 16**, using the mean of

the upper four frequency bins of the spectrogram, while Q, P are respectively the numbers of frequency and time bins of the spectrogram matrix S .

$$T_1 = \frac{1}{4} \sum_{q=(Q-4)}^{q=Q} \frac{1}{P} \sum_{p=1}^{p=P} s[p, q], s \in S \quad \text{Equation 16}$$

The maximal motion frequency bin is defined and estimated in **424D**, as the first frequency bin to its power below the motion threshold when scanning the spectrum from $F_{\min}$ to $F_{\max}$ which is the motion (active) region for the p power spectrum as defined by **Equation 17**.

$$f_p = \operatorname{argmin}_q (s[q, p] < (T_1 + 1)) \text{ for } p = 1 \dots P \quad \text{Equation 17}$$

where f_p is the maximal frequency at the p power spectrum that its power is $< T_1 + 1$ dB. An example for that region from a full spectrogram can be seen in spectrogram **424E** of **Figure 4G**.

[00146] **Figure 4G** is an exemplary illustration of a spectrogram **424E** of motion over a single range bin in the active area, according to some embodiments of the invention. Action power spectrum extractor **424B** further carries out a selection **424F** of the power spectrum with the highest frequency – the selected power spectrum at time bin p is the one that has the highest value of f_p (referred as action power spectrum of range q). This power spectrum is extracted for farther analysis. The averaged action power spectrum P_{av} is created (**424G**) using action power spectrums **424E** from all range bins. Then, a new noise threshold T_2 is calculated from **Equation 18**, by using the average value of the upper four frequency bins of the averaged (accumulated) power spectrums, in a non-limiting example.

$$T_2 = \frac{1}{4} \sum_{q=(Q-4)}^{q=Q} P_{av}[q] \quad \text{Equation 18}$$

The maximal frequency feature is calculated by **Equation 19**:

$$f_{max} = \operatorname{argmin}_q (P_{av}[q] < (T_2 + 1)) \quad \text{Equation 19}$$

[00147] **Figure 4H** is a high-level schematic flowchart illustration of an exemplary motion energy features extractor **426**, according to some embodiments of the invention. The motion energy features may be estimated in the frequency domain. There are a few features that are extracted to better represent the overall motion energy. The motion energy might be affected by several conditions which are not related to the motion itself. For example, the relative distance from the interferometer as well as the motion duration. Unit **426** may create several spectrograms for all the target range bins to extract the various features that represent the energy signature.

The motion energy features may be extracted by the following exemplary process. Two spectrogram versions may be created for each target range bin. The first spectrogram may be created after a range gain mismatch correction (to compensate the path loss variations over the range bins). The other spectrogram may be created without the gain mismatch correction (**426A**). The gain mismatch may be implemented at preprocessing unit **422B**. Therefore, two spectrogram

sets are created for the complete range bins $\{S_{1n}\}$ and $\{S_{2n}\}$. For each set of spectrograms, an average spectrogram **426B** S_{1av} S_{2av} may be created by **Equation 20**.

$$S_{i,av}[q][m] = \frac{1}{RW} \sum_{n=1}^{RW} S_n[q][m]; \text{ for } i = 1, 2 \text{ } m = 1 \dots M_{subframes}, q = 1 \dots Q_{freqbins}$$

Equation 20

- 5 In order to emphasize the motion power in higher frequencies, each averaged spectrogram frequency bin $\vec{S}_{av}^q$ may be processed with a corresponding weight, into a new weight-averaged spectrogram **426C** by **Equation 21**.

$$\overline{SW}_{av}^q = \vec{S}_{av}^q * \sqrt{\frac{f[q]}{f_{max}}}; \text{ for } q = 1 \dots Q_{freqbins} \quad \text{Equation 21}$$

- where $f[q]$ is the frequency value of the q frequency bin, and f_{max} is the maximal frequency bin value. Two vectors of the power peaks may be created (**426D**) for each the two spectrograms, with and without power correction. A first vector $\vec{p}_1$ contains the maximal power of each sub-frame vector $\vec{S}_{av}^m$ (**Equation 22A**), and the second vector $\vec{p}_2$ contains the maximal values of each frequency bin vector $\vec{S}_{av}^q$ (**Equation 22B**).

$$p_1[m] = \max(\vec{S}_{av}^m); \text{ for } m = 1 \dots M_{subframes} \quad \text{Equation 22A}$$

$$15 \quad p_2[q] = \max(\vec{S}_{av}^q); \text{ for } q = 1 \dots Q_{freqbins} \quad \text{Equation 22B}$$

Each of the four (2x2) vectors - with the different procedures for gain processing and for maximal power values extraction, are accumulated into four energy features.

- [00148] **Figure 4I** is a high-level schematic flowchart illustration of an exemplary range-time preprocessing and segmentation flow **432** as part of derivation of energy signature **420B**, according to some embodiments of the invention. The motion features over range-time helps profiling the energy signature of each motion, not only by characterizing its power and velocity, but by also characterizing its distribution over space along the motion time. Module **432** may be configured to create three histograms that express the distribution of motion energy and activity over the range bins during motion period. The energy related histograms may be created by the following algorithms. After normalization of the slow time matrix X (defined in **Equation 9**) using the highest absolute value amplitude as $X = \frac{X}{\|X\|_{\infty}}$ (the notation X is maintained for simplicity), the target region is located by a target region detector unit **432A**. The two axis of the slow time matrix X correspond to the time of the sample (time bin) and the range of the sample (range bin). Each range bin vector, with $K_{Samples} = T_{frame} \cdot F_{slow}$ length as an example, may then segmented into 10 sub-frames as a non-limiting example and mapped in as new matrix X_n defined in **Equation 23**, with $K_{Samples}=800$ as a non-limiting example, with each row of the new matrix having $K_{Samples}/10$ samples with an overlap.

$$X_n = \begin{bmatrix} x_n[1] & \cdots & x_n[80] \\ \vdots & \ddots & \vdots \\ x_n[720] & \cdots & x_n[800] \end{bmatrix} \quad \text{Equation 23}$$

With E_n being the temporal energy vector of each range bin as calculated in **Equation 24**, j being the sub-frame number.

$$E_n[j] = \sum_{i=1}^{i=\frac{K}{10}} ||X_n[j, i]||^2 \text{ for } n = 1 \dots RW_{target} \quad \text{Equation 24}$$

- 5 A Matrix E defined by **Equation 25** is constructed by gathering all the temporal energy vectors from each range bin.

$$E = \begin{bmatrix} E_1 \\ \vdots \\ E_N \end{bmatrix} \quad \text{Equation 25}$$

- The columns of E are the energies of all the ranges along the new wider time bins, and the rows are the energy of a specific bin along time. From each column with indicator k , the five highest elements values may be extracted into $w_k(r)$, $r = 1 \dots 5$; together with their row indexes $g_k(r)$, as a non-limiting example. The three histograms **432B** are created from elements $w_k(r)$ as defined by **Equations 18A-C**.

An accumulated range histogram with elements calculated by **Equation 26A**:

$$h_{acc}(n) = \sum_{k=1}^{k=K} w_k(r) * I_{(g_k(r)=n)} \text{ for } n = 1 \dots RW_{target} \quad \text{Equation 26A}$$

- 15 The indicator function $I_{(\omega \in \Omega)}$ is equal to 1 if the condition in the brackets is true.

An activity in range over time histogram, with elements calculated by **Equation 26B**:

$$h_{app}(n) = \sum_{k=1}^{k=K} I_{(g_k(r)=n)} \text{ for } n = 1 \dots RW_{target} \quad \text{Equation 26B}$$

A normalized energy histogram, with elements calculated by **Equation 26C**:

$$h_{norm}(n) = \begin{cases} \frac{h_{acc}(n)}{h_{app}(n)}, & h_{app}(n) > 0 \\ 0, & h_{app}(n) = 0 \end{cases} \text{ for } n = 1 \dots RW_{target} \quad \text{Equation 26C}$$

- 20 **[00149] Figure 4J** is a high-level schematic flowchart illustration of an exemplary range energy distribution analysis **434** as part of derivation of energy signature **420B**, according to some embodiments of the invention. Range energy distribution analysis module **434** extracts features from the accumulated and normalized energy histograms, which relate to the amount and distribution of motion energy over the range bins. Range energy distribution analysis **434**
- 25 includes the extraction of the total and maximal (peak) energy over the range bins out of the histogram. In addition, the histogram form factor, defined as the percentage accumulated distribution points, is extracted (for example I20 – identifies the range bin point that covers 20% of the accumulated motion energy, I40 – identifies the range bin point that covers 40% of the accumulated motion energy, etc.).

[00150] **Figure 4K** is a high-level schematic flowchart illustration of an exemplary motion over range distribution analysis **436**, according to some embodiments of the invention. Motion over range distribution analysis unit **436** extracts features that relate to the distribution of active range bins over time, which is related to the motion's and varying over the down range. Unit **436** extracts the number of times that most of active region has been selected, the total number of active range bins and the mean number of repeated selection of the range bin as an active region.

[00151] **Figure 4L** is a high-level schematic flowchart illustration of an exemplary motion route energy estimation **438**, according to some embodiments of the invention. The motion route energy is defined as the accumulated power along the motion route in the range bins window during the motion period (time) relatively to the overall energy. This feature may be extracted in two major stages: (i) Estimating the motion route by using a dynamic Time Warping (DTW) approach **438A**, (ii) accumulating the estimated power along the selected range bin route, and normalizing by the overall power **438B** and calculating the motion route peak to average power ratio **438C**. The DTW may be performed by selecting the highest range bin power for every subframe, as illustrated in **Figure 4M**, being a schematic matrix illustration of DTW-based motion route estimation **438A**, according to some embodiments. The relative Motion Route Energy (MRE) may be calculated as expressed in **Equation 27**:

$$MRE = \frac{\sum_{m=1}^{M_{\text{subframes}}} MP[m]}{\sum_{m=1}^{M_{\text{subframes}}} \sum_{r=1}^R P[m,r]} \quad \text{Equation 27}$$

Where:

$P_{[m,r]} = \sum_{n=1}^N |x_{m,r[n]}|^2$ is the power of subframe m , and Range bin r ;

$x_{m,r[n]}$ – is the Slow signal at subframe m and range bin r ; and

$MP[m] = \max\{P_{[m,r]}\}, r \in \text{Window Range bins}$, is the Max Power at subframe m .

[00152] The motion route Peak to Average Power Ratio (PAR), measured by the ratio between maximal and average power of the motion route, may be calculated as in **Equation 28**:

$$PAR = \frac{\max_m(MP[m])}{\frac{1}{M_{\text{subframes}}} \sum_{m=1}^{M_{\text{subframes}}} MP[m]} \quad \text{Equation 28}$$

[00153] **Figure 4N** is a schematic illustration of the possibility to separate different types of motions based on the derived parameters, according to some embodiments of the invention.

[00154] The two illustrations in **Figure 4N** are of the same 3D graphics and are taken from different angles to illustrate the separation of the two types of motion in the 3D parameter space. **Figure 4N** clearly illustrates the ability of the analysis described above to separate motions that are categorized, in the non-limiting illustrated case, as fall motions and as regular motions. The results may be used independently to detect falls, or be provided to the classifier for verification

and augmentation with additional data and analysis results. Classification of the human state, as described in detail below, may relate to the derived motion characteristics as well as optionally to posture characteristics, respiration characteristics and position characteristics that may be derived from the received echo signals by implementing the disclosed methods, approaches and/or additional analysis of the received echo signals.

Human respiration

[00155] Human breathing – During the breathing (respiration) the chest wall moves by inhalation and exhalation. The average respiratory rate of a healthy adult is usually 12-20 breaths/min at rest (~ 0.3 Hz) and 35-45 breaths/min (~ 0.75 Hz) during labored breathing. The respiration features may be extracted from the slow-time signal (that is derived from the received echo signals at the target's distance (down range) from the system) using spatial time parameters thereof and the power spectrum as explained below. Specifically, in the following, the target may be selected as the chest of the one or more humans in the environment.

[00156] **Figure 5A** is a high level schematic illustration of a human respiration features extraction system **300** within system **100**, according to some embodiments of the invention. Human respiration features extraction system **300** is configured to extract respiration features from the received echo signals, and may comprise the following modules and operations. First, the echo signal may be rearranged by an echo (fast) signal preprocessing unit **405** configured to receive echo signals **401** (99) from receiving antenna **110** with respect to each pulse transmission 91, the received signals being represented by a vector termed the fast time signal. The transmission-reception cycle may performed repeatedly at any rate and duration, in an exemplary non-limiting manner, for a frame of $T_{\text{frame}} = 20$ seconds and at a rate of $F_{\text{slow}} = 16\text{Hz}$. The output of unit **405** may be a matrix of the received echo signals, where each row is a fast time signal of different transmission.

[00157] Fast to slow signal rearrangement and preprocessing (see also above) may comprise a range bin based slow signal constructor and a slow signal preprocessing unit. The range bin based slow signal constructor may be configured to rearrange the downrange echo (fast) signals vectors (the matrix rows) to represent the cross-range (slow) signals (the matrix columns) – see also **Figure 4B** above. The slow signal vector represents a single downrange distance (bin) with the sampling rate, e.g., $F_{\text{slow}} = 16$ Hz. These vectors are referred as the “slow time signals” and have a length of N_{samples} . The slow signal preprocessing unit may carry out the preprocessing for each range bin separately, comprising e.g., DC removal by subtraction of the estimated average DC signal from the original signal as well as other optional signal adjustments for

example gain and phase mismatch correction between all the echo (fast) signals and out-of-band noise reduction filtering.

[00158] Then, a motion rejection filter **320** may be applied to estimate the motion interference for each range bin, e.g., by evaluating the signal LPC (linear predictive coding) coefficients for each sub-frame, e.g., one second long sub-frames (see definitions above). Using the LPC coefficients, the motion related components may be removed from each of the slow time signals, to enhance the slow time signal components which characterize non-motion parameters such as respiration parameters.

[00159] A time-to-frequency constructor module **322** may be configured to convert the slow time signal of each range bin into the corresponding power spectrum, e.g., by applying an FFT (fast Fourier transform) with a hamming window, followed emphasizing higher respiration frequencies (see **Figures 5C** and **5D** below). Additionally, a target localization unit **324** may be configured to select the target range bins, e.g., as the range bins with the highest respiration power spectrum energy within a Region of Interest (ROI), e.g., relating to the chest of the respective humans. The ROI may be set by using the prior frames respiration energy over range bins, and the current frame bins region that have high respiration energy level (that can be related to the human general location), as illustrated e.g., in **Figures 5E** and **5F** below. In particular, the respective chest(s) of the human(s) may be identified by detecting cross-correlation in the respiration-related ROI as chest movements are correlated in their motions over the corresponding range bins. For example, at least two coordinates (e.g., a start point and an end point) of the chest may be identified as the chest ROI.

[00160] Following the human chest target localization, a rake receiver **330** may be configured to reconstruct the respiration signal, e.g., by implementing a range bins selector **332** to compute the correlation of each range bin with the target range bin by using multiple variations of phase shifts and selecting the N range bins that are most correlated with the target; and rake combiner **334** which shifts and combines the slow time signals of the selected range bins, by the range bins scanner, to reconstruct the respiration signal (see details in **Figures 5G-5J**).

[00161] The reconstructed respiration signal may be used to extract (**338**) respiration features **345** by calculating descriptive features of the respiration signal derivative. The features may focus on the respiration rate, asymmetry and other indicators of tidal volume changes. For example, a respiration rate **340** may be estimated by a frame average power spectrum estimator **336** that calculates the average power spectrum using the power spectrums of each selected range bin, received from range bins combiner **334**, PCA (principal component analysis) past projection module **326** that creates a PCA space based on the last, earlier-derived M frames and projects the average power spectrum over the first principle component subspace to determine the respiration

rate by the peak frequency of the projected average power spectrum. A respiration rate estimator **340** then extracts the respiration rate from the past projected power spectrum. These and related aspects of system **100** are presented below in detail.

[00162] Echo signal rearrangement unit **410**, may be configured to map the received preprocessed fast signals (from module **405**) in a two-dimensional matrix X which is defined in **Equation 29** (similar to **Equation 9** above).

$$\begin{bmatrix} x[1][1] & \cdots & x[1][N] \\ \vdots & \ddots & \vdots \\ x[M][1] & \cdots & x[M][N] \end{bmatrix} \quad \text{Equation 29}$$

[00163] Each matrix element represents an echo sample, $[m][n]$; $m = 1 \dots M_{\text{Ranges}}$; $n = 1 \dots N_{\text{Samples}}$, where n denotes the downrange bin indicator, and m denotes the cross-range (slow) time indicator. The number of total range bins is determined by the scanning window, while each range bin represents C/F_{fast} meters (F_{fast} is the echo signal sampling rate). The matrix is separated into its rows (see **Figure 4B**). Each row x_m is the echo signal from the same range from the radar, sampled e.g., in $F_{\text{slow}}=16$ Hz. Those vectors are referred as the slow time signals. The slow time signal preprocessing unit **405** may be configured to be generic in the sense that its input is determined by the extracted features and it may be operated on each slow time signal separately.

[00164] **Figure 5B** is a high level schematic illustration of motion rejection filter **320** within human respiration features extraction system **300**, according to some embodiments of the invention. Following the pre-processing of slow time signal **401**, motion rejection filter **320** is configured to remove motion related interferences, as described in the following. The slow time signal $x[n]$ of each range bin m is segmented (**452**) into sub frames $v_m[n]$ of $T_{SF}=1-2$ second duration, as expressed in **Equation 30**.

$$\{v_k^m[n]\} = \{x[D_k + n]\}; n = 1 \dots D; \forall m = 1 \dots M_{\text{ranges}}, k = 1 \dots N_{\text{Samples}}/D_{\text{subframesize}} \quad \text{Equation 30}$$

The motion interference model may then be estimated by an Auto-Regressive (AR) model **454**, under the assumption that from a frame with the length of 1-2 second, only the motion spectrum components are predicted, excluding the respiration frequency components. From each sub frame the first $K=2-4$ Linear Prediction Coefficients (LPC) of each sub frames are calculated. The estimated LPC coefficients of each sub-frame are then used to create a whitening filter and the correspondent filter of each sub frame is used to filter the motion interference **456**. The post filtered sub frames of each range bin may be re-combined into a filtered signal **451**.

[00165] **Figure 5C** is a high level schematic illustration of time to frequency converter **322** within human respiration features extraction system **300**, according to some embodiments of the

invention. Time to frequency converter **322** is configured to enable the frequency analysis of the human breathing (which may range between 0.2Hz and 0.75Hz), e.g., by using the slow time signal of each range bin to calculate the respiration power spectrum, as explained in the following. Each Slow time x_m signal **401** may be processed by FFT with hamming window h
 5 **457**, as expressed in **Equation 31**.

$$\{X_m\} = FFT\{x_m \cdot h\}; \forall m = 1 \dots M_{Ranges} \quad \text{Equation 31}$$

The respiration power spectrum for each range bin may be represented by the power spectrum in the frequencies bands of 0.2-1 Hz as expressed in **Equation 32**.

$$X_m[k], k = 1 \dots NF_{MAX} \quad \forall m = 1 \dots M_{Ranges} \quad \text{Equation 32}$$

10 **[00166]** A high respiration frequencies pre-emphasis **458** may be implemented by applying a corresponding filter **458** to overcome an expected attenuation of the signal amplitude at high respiration rates due to the natural limitation of the human maximal tidal volume when breathing at a high respiration rate (because the amount of air that is inhaled is not sufficient to fill the lungs). The high frequencies pre-emphasis **458** emphasizes the higher frequencies to balance the
 15 effect of the lower tidal volume on the power spectrum. An exemplary enhancement filter w is expressed in **Equation 33**, with the parameter α relating to the rate of maximal tidal volume that results from increasing the respiration rate.

$$w(f) = \begin{cases} 1 & , f < F_{MI} \\ 1 + (f - F_{MI}) \cdot \alpha & , f \geq F_{MI} \end{cases} \quad \text{Equation 33}$$

As a non-limiting example $\alpha=3$.

20 **[00167]** **Figure 5D** illustrates in a non-limiting manner the frequency response of the pre-emphasis filter **458**, according to some embodiments of the invention. The operation of enhancement filter **458** on the respiration signal is expressed in **Equation 34**, resulting in respiration frequencies **341**. $X_E[f]$ denotes the enhanced respiration spectrum that compensates the non-full inhale/exhale situations in hyperventilation cases. F_{MI} denotes the Maximum
 25 Respiration Frequency with a full inhale/exhale condition.

$$X_E(f) = X(f) \cdot w^2(f) \text{ for } f = 0 \dots F_{MaxResp} \quad \text{Equation 34}$$

[00168] **Figure 5E** is a high level schematic illustration of target localization unit **460** within human respiration features extraction system **300**, according to some embodiments of the invention. Target localization unit **460** may be configured to use the current and past distribution
 30 of respiration energy over range bins **461**, in order to determine the target's location range bins (e.g., of the chest of the human(s) in the scene). Although there may be more than a one range bin that includes the target, target localization unit **460** may be configured to identify or select a specific range bin that can be used as a reference, in order to locate other relevant range bins based on their similarity to the identified or selected range bin.

[00169] First, the search for the respiration target range bin may be limited to a Region of Interest (ROI), which is estimated by using past target regions, in order to reduce the chance of selecting a false range bin having high energy which does not relate to the respiration component. **Figure 5F** is a high level schematic exemplary illustration of ROI selection, according to some embodiments of the invention. The area with the highest respiration energy within the ROI may be selected as the center of the ROI for searching the reference target range bin, e.g., as explained below.

[00170] The respiration energy of each range bin may be estimated (462) by accumulation of the respiration power spectrums as expressed in **Equation 35**, which includes all the respiration frequencies bins - R_{bins} . $E[m]$ denotes the respiration energy at bin m , $X_m[k]$ denotes the power spectrum of range bin m and frequency bin k , and F_{bins} denotes the number of the frequency bins.

$$E[m] = \sum_{k=1}^{F_{bins}} X_m[k], \forall m = 1 \dots M_{Ranges} \quad \text{Equation 35}$$

[00171] Detecting ROI 465 may be carried out as follows (see also **Figure 5F**). The median value of all the range bins energies $E[m]$ may be calculated over the different values of m , and the initial ROI range bin may be determined by the first range bin (from the sensor) with respiration energy above the median value. Then, a weighted respiration energy may be calculated by accumulating past range bins energies, according to **Equation 36**, where $E_j[m]$ are the past average range bins energies ($j=1$ is the most recent while $j=K$ is the oldest).

$$E_{av}[m] = \frac{\sum_{j=1}^K E_j[m](K-j)}{K} \quad \text{Equation 36}$$

[00172] The range bin with highest past projected range bin may be selected to be the middle of the ROI. The total ROI area may be determined as explained below and exemplified in **Figure 5F** - The ROI Start may be selected as the first range bin with energy above median, the ROI Center may be determined as the estimated location by past frames, and the ROI End may be selected as the range bin that has a correlation with the ROI Center range bin which exceeds a pre-defined threshold. Finally, the target location may be determined as the range bin with the highest respiration power within the ROI 466 (**Figure 5E**). A range bins selector 468 may be configured to search for range bins that are highly correlated with the reference respiration target range bin slow signal, with a selection 469 of the range bins being performed as illustrated in **Figure 5G**.

[00173] **Figure 5G** is a high level schematic illustration of range bins selector 332 providing a range bin selection 469, within human respiration features extraction system 300, according to some embodiments of the invention. The tested range bins set, $x_m[n]$, may be cross-correlated

with the reference range bin R_{ref} slow-time signal $x_R[n]$ 471 after applying a delay tap t (472), e.g., $x_m^t[n] = x_m[n - t]$, $t = 1 \dots T_{shifts} \forall m = 1 \dots M_{Ranges}$. Using the sliding window, multiple cross-correlations (e.g., $T_{shifts}=32$) may be produced for each range bin slow time signal, from zero phase up to T_{shifts} taps, within e.g., two seconds time frame. Then, the range bins with the highest correlation may be selected 474, with the correspondent phase shift being expressed by Equation 37

$$CC[m, t] = \frac{\sum_{n=1}^N x_R[n] * x_m^t[n]}{\sqrt{\sum_{n=1}^N x_R[n]^2}} \quad \text{Equation 37}$$

[00174] Range bins selector 469 may be configured to select N_R range bins 476 with the maximal cross-correlation $C[m]$ out of all range-bins that are related to the target (e.g., human chest), and the correspondent phase shifts $PS[m]$ that achieve these values. That is, selected range bins 476 may be denoted as $m' \in m, m' = 1 \dots N_R$ that are selected according to Equations 38.

$$C[m] = \max_{t=1 \dots T_{shifts}} \{CC[m, t]\}; \quad PS[m] = \operatorname{argmax}_t \{CC[m, t]\}$$

Equations 38

[00175] Figure 5H is a high level schematic illustration of rake combiner 334 with phase shifting, within human respiration features extraction system 300, according to some embodiments of the invention. Each of slow time signals 401 may be zero padded from both sides, shifted by its correspondent phase, and all the shifted signals are accumulated (478) into one signal as expressed in Equations 39.

$$\hat{x}_{m'}^{PS[m']}[n] = \text{ZerosPadding}\{x_{m'}^{PS[m']}[n]\}$$

$$\hat{x}[n] = \sum_{m'=1}^R \hat{x}_{m'}^{PS[m']}[n]$$

Equations 39

[00176] After applying a rectangle window 479 to preserve the $N_{samples}$ frame size, the DC component of the combiner output signal may be estimated by an average estimator as the average signal $dc[n]$. The average signal may be then removed (480) from the combined output signal to produce the respiration signal $y[n]$ 482 by Equation 40.

$$y[n] = \hat{x}[n] - dc[n] \quad \text{Equation 40}$$

[00177] **Figure 5I** and **5J** provide an exemplary illustration of pre-accumulation phase shifted time signals (**476**), and of post-accumulation respiration echo signal **482**, respectively, according to some embodiments of the invention.

[00178] **Figure 5K** is a high level schematic illustration of respiration features extraction from time domain **338**, within human respiration features extraction system **300**, according to some embodiments of the invention. Respiration features **345** that are extracted from reconstructed respiration signal **482** may be selected to provide information on the physiological properties of the respiration process. These features are extracted from the time domain analysis of the slow time respiration signal as explained in the following. A derivative **484** of respiration signal **482** is calculated, and an absolute value **484A** and a sign **484B** of respiration signal derivative **484** are separated into two signals by **Equations 41**.

$$y'[n] = y[n] - y[n - 1], \forall n = 2 \dots N$$

$$y_1[n] = |y'[n]|$$

$$y_2[n] = \text{sign}(y'[n])$$

Equations 41

[00179] As a non-limiting example, six respiration features may be derived from the sign and absolute value of the respiration derivative, defined as F1-F6 in **Equations 42**, and used to construct respiration features vector **345**.

$$F1 = \frac{\sum_{n=1}^N 1_{y_1[n] > \text{Threshold}}}{\sum_{n=1}^N 1_{y_1[n] < \text{Threshold}}}; F2 = \frac{\sum_{n=1}^N 1_{y_2[n] = 1 \cap y_1[n] > \text{Threshold}}}{\sum_{n=1}^N 1_{y_2[n] = -1 \cap y_1[n] > \text{Threshold}}}; F3 = \text{med}_n(y')$$

$$F4 = \max\left(\frac{\sum_{n=1}^N y_1[n] \cdot 1_{y_2[n] = 1 \cap y_1[n] > \text{Threshold}}}{\sum_{n=1}^N 1_{y_2[n] = 1 \cap y_1[n] > \text{Threshold}}}, \frac{\sum_{n=1}^N y_1[n] \cdot 1_{y_2[n] = 1 \cap y_1[n] < \text{Threshold}}}{\sum_{n=1}^N 1_{y_2[n] = 1 \cap y_1[n] < \text{Threshold}}}\right)$$

$$F5 = \max\left(\sum_{n=1}^N y_1[n] \cdot 1_{y_2[n] = 1 \cap y_1[n] > \text{Threshold}}, \sum_{n=1}^N y_1[n] \cdot 1_{y_2[n] = 1 \cap y_1[n] < \text{Threshold}}\right)$$

$$F6 = \frac{1}{J} \sum_{j=1}^J \max_{n \in I_j} y_1[n]$$

Equations 42

[00180] In this example, F1 denotes the ratio between samples of the absolute derivative value that pass the pre-defined threshold versus the ones that do not pass that threshold. F1 may be used to provide information on the breath's duty cycle. F2 denotes the ratio between the inhalation and exhalation periods. F2 may be used to provide information on the respiration asymmetry, in terms of inhalation time versus exhalation time. F3 denotes the median value of the entire derivative signal. F3 may be used to provide information on the amount of chest

movements which indicate the amount energy related to the respiration action. F3 is expected to increase when the person is under stress. F4 denotes the maximum value of the average inhalation – exhalation and may be calculated by the average values of the derivative absolute value samples that pass the threshold and located at ascending or descending regions respectively. F4 may be used to provide information on the average chest velocity, which can be related to the average amount of air inhaled and exhaled. F5 denotes the maximum value of the total inhalation – exhalation, and may be calculated by the total values of the derivative absolute value samples that pass the threshold and are located as ascending or descending regions respectively. F5 may be used to provide information on the total chest activity, which can be related to the total amount of air inhaled and exhaled. F6 denotes the averaged inhalation/exhalation peaks within each frame segment, with J representing the number of segments, e.g., J may be in a range of 3 to 5 segments of 3-5 second each. F6 may be used to provide information about the maximum peak rate of inhalation-exhalation.

[00181] **Figures 5L and 5M** are high level schematic illustrations of frame average power spectrum estimator **336** and of Principle Component Analysis (PCA)-based respiration rate estimator **326**, respectively, that are used for respiration rate estimation **340**, within human respiration features extraction system **300**, according to some embodiments of the invention. The power of the range bins selected (**474**) by range bins scanner **332** may be combined to yield an average power spectrum **488** of the respiration process and each of the N_R range bins may be accumulated into a joint average spectrum of the respiration **490**, as expressed in **Equation 43**.

$$P_{av}[k] = \frac{1}{N_R} \sum_{r=1}^{N_R} P_{RB_r}[k] \quad \text{Equation 43,}$$

where:

$P_{RB_r}[k]$ denotes the power spectrum of slow time signal at range-bin RB_r , and

N_R denotes the number of the selected range bins to be averaged in the power spectrum.

[00182] Respiration rate estimation based on PCA (**326**) may be configured to reduce the effect of unwanted components such as the noise and the low motions interference signature, under the assumption that the respiration power spectrum usually fluctuates over the consecutive frames versus noise and quasi-static motion components. The PCA-based respiration rate estimation **326** may be configured to extract the first principle component **492** out of a current PCA space **494** that is generated from the L last frames' power spectra and the current frame power spectrum. The estimated respiration rate **340** may then be identified as the argument (frequency bin) **496** of the maximum value of the extracted first principle component vector.

[00183] The features vector relating, e.g., to posture, motion and respiration features and/or respiration modes, derived as described above, may prepared by quantizing the extracted features

with a final number of bits per field and adding the time stamp for the prepared vector. This vector may be used as the entry data for the human state classifier (for both training and classifying stages).

5 Human state classifier

[00184] The Human state classifier is a VQ (Vector Quantization) based classifier. This classifier consists of two main phases: (i) The training phase is carried out offline (supervised training) and online (unsupervised training), where a stream of features vectors reflecting various states are used as a preliminary database for vector quantization and finding the set of code-vectors (centroids) that sufficiently representing the instantaneous human states. The set of the calculated code-vectors are called codebook. Some embodiments of the training sessions are provided in more details hereinafter. (ii) The classifying phase is executed during the online operation while an unknown features vector is entered into the classifier and the classifier determines what the most probable state that it represents. The classifier output is the determined states and the set of the measured statistical distances (probabilities), i.e., the probability of State-i given the observation-O (the features vector). The aforementioned probability scheme may be formulated by: $P(S_i|O)$. The determined instantaneous state is called "Local Decision". The VQ states are defined as the set of instantaneous states at various locations at the monitored home environment. Therefore, any state is a two dimensional results which is mapped on the VQ state matrix. (iii) The State matrix consists of the state (row) and location (Column) followed by a time stamp. Typical elderly home environment consists of the specific locations (Primary zones) and others non-specified locations (Secondary zones). State is defined as the combination of posture/motion at a specific location (e.g., S21 will indicate sleeping at Bedroom).

[00185] Figure 6A is a table 134 illustrating an exemplary states definition in accordance with some embodiments of the present invention. Figure 6B is a table 135 illustrating an exemplary states matrix in accordance with some embodiments of the present invention.

Cognitive Situation Analysis (CSA)

[00186] The CSA's objective is to recognize the abnormal human patterns according to a trained model that contains the possible abnormal cases (e.g., fall). The core of the CSA, in this embodiment, may, in a non-limiting example a Hidden Markov Model (HMM) based pattern recognition. The CSA engine searches for states patterns that are tagged as an emergencies or abnormal patterns. These predefined patterns are stored in a patterns codebook. The output of the CSA is the Global recognized human situation.

[00187] **Figure 6C** is a table **136** illustrating exemplary abnormal patterns in accordance with some embodiments of the present invention. It can be seen that in the first abnormal case (Critical fall), it appears that the person was sleeping in the leaving room (S25), then was standing (S45) and immediately fell down (S65). He stayed on floor (S15) and start being in stress due to high respiration rate (S75). The CSA may contain additional codebook (irrelevant codebook) to identify irrelevant patterns that might mislead the system decision.

Communication unit

[00188] The communication unit creates the channel between the system and the remote caregiver (family member or operator center). It may be based on either wired (Ethernet) connectivity or wireless (e.g., cellular or WiFi communication or any other communication channel).

[00189] The communication unit provides the following functionalities: (i) This unit transmits any required ongoing situation of the monitored person and emergency alerts. (ii) It enables the two way voice/video communication with the monitored person when necessary. Such a communication is activated either automatically whenever the system recognizes an emergency situation or remotely by the caregiver. (iii) It enables the remote system upgrades for both software and updated codebooks (as will be in further detail below). (iv) It enables the communication to the centralized system (cloud) to share common information and for further big data analytics based on multiple deployments of such innovated system.

[00190] **Figure 7** is a diagram illustrating cloud-based architecture **700** of the system in accordance with embodiments of the present invention. Raw data history (e.g., states stream) is passed from each local system **100A-100E** to the central unit located on a cloud system **710** and performs various data analysis to find correlation of states patterns among the multiple users' data to identify new abnormal patterns that may be reflected just before the recognized abnormal pattern. New patterns code vectors will be included to the CSA codebook and cloud remotely updates the multiple local systems with the new code-book. The data will be used to analyze daily operation of local system **100A-100E**.

[00191] **Figure 8** is a diagram illustrating a floor plan **800** of an exemplary residential environment (e.g., an apartment) on which the process for the initial training is described herein.

The home environment is mapped into the primary zones (the major home places that the monitored person attends most of the time as bedroom **810**, restroom **820**, living room **830** and the like) and secondary zones (the rest of the barely used environments). The VQ based human state classifier (described above) is trained to know the various primary places at the home. This is done during the system setup while the installer **10A** (being the elderly person or another person) stands or walks at each primary place such as bedroom **810**, restroom **820**, and living

room **830** and let the system learn the “fingerprint” of the echo signals extracted features that mostly represents that place. These finger prints are stored in the VQ positions codebook. In addition, the system learns the home external walls boundaries. This is done during the system setup while the installer stands at various places along the external walls and lets the system tune its power and processing again (integration) towards each direction. For example, in bedroom **810**, installer **10A** may walk along walls in route **840** so that the borders of bedroom **810** are detected by tracking the changes in the RF signal reflections throughout the process of walking. A similar border identification process can be carried out in restroom **820**, and living room **830**. Finally, the system learns to identify the monitored person **10B**. This is done by capturing the fingerprint of the extracted features on several conditions, such as (1) while the person lays at the default bed **812** (where he or she is supposed to be during nighttime) to learn the overall body volume, (2) while the person is standing to learn the stature, and (3) while the person walks to learn the gait. All the captured cases are stored in the VQ unit and are used to weight the pre-trained codebooks and to generate the specific home/person codebooks. According to some embodiments, one or additional persons such as **20** can also be monitored simultaneously. The additional person can be another elderly person with specific fingerprint or it can be a care giver who needs not be monitored for abnormal postures.

[00192] **Figure 9** is a diagram illustrating yet another aspect in accordance with some embodiments of the present invention. System **900** is similar to the system described above but it is further enhanced by the ability to interface with at least one wearable medical sensor **910A** or **910B** coupled to the body of human **10** configured to sense vital signs of human **10**, and a home safety sensor **920** configured to sense ambient conditions at said specified area, and wherein data from said at least one sensor are used by said decision function for improving the decision whether an abnormal physical event has occurred to the at least one human in said specified area. The vital signs sensor may sense ECG, heart rate, blood pressure, respiratory system parameters and the like. Home safety sensors may include temperature sensors, smoke detector, open door detectors and the like. Data from all or some of these additional sensors may be used in order to improve the decision making process described above.

[00193] **Figure 10** is a high level schematic flowchart of a method **600** according to some embodiments of the invention. Method **600** may be at least partially implemented by at least one computer processor. Certain embodiments comprise computer program products comprising a computer readable storage medium having computer readable program embodied therewith and configured to carry out of the relevant stages of method **600**.

[00194] Method **600** may comprise transmitting UWB RF signals via transmitting antenna(s) at a specified area (such as an environment including at least one human) and receiving echo

signals via receiving antenna(s) (stage **500**). At least one of the UWB RF transmitting and receiving antennas comprises a Synthetic Aperture Antenna Array (SAAA) comprising a plurality of linear baseline antenna arrays ("baselines"). Method **600** may comprise configuring receiving antenna(s) and/or transmitting antennas(s) as a Synthetic Aperture Antenna Array (SAAA), such as baseline(s) (stage **510**), for example, method **600** may comprise configuring the UWB RF receiving SAAA as a plurality of linear baseline antenna arrays arranged in a rectangle as a non-limiting example, possibly parallel to edges thereof or at acute angles to edges thereof (stage **520**), e.g., as illustrated below in a non-limiting manner. Method **600** may comprise designing at least one of the linear baseline antenna arrays to comprise two (or more) parallel metal beams flanking the antenna elements of the baseline, to widen the baseline's field of view (stage **525**).

[00195] Method **600** may further comprise using multiple antennas to implement virtual displacement of the baselines (stage **530**), i.e., virtually displacing transmitting or receiving baselines to enhance performance (stage **535**). Method **600** may further comprise implementing phase-shifting-based integration (back-projection) to derive parameters relating to the human(s) (stage **540**), such as location, movement and/or posture features.

[00196] Method **600** may further comprise canceling environmental clutter (stage **605**), e.g., by filtering out static non-human related echo signals (stage **606**), extracting from the filtered echo signals, a quantified representation of position postures, movements, motions and breathing of at least one human located within the specified area (stage **610**), identifying a most probable fit of human current state that represents an actual human instantaneous status (stage **690**) and applying a pattern recognition based decision function to the identified states patterns and determine whether an abnormal physical event has occurred to the at least one human in the specified area (stage **693**) (see additional details below).

[00197] Method **600** may further comprise finding the best match to a codebook which represents the state being a set of human instantaneous condition/situation which is based on vector quantized extracted features (stage **691**).

[00198] Method **600** may further comprise ensuring, by the filtering out, that no human body is at the environment, using static clutter estimation and static clutter subtraction (stage **607**).

[00199] Method **600** may further comprise quantizing the known states features vectors and generating the states code-vectors (stage **692A**), measuring the distance between unknown tested features vectors and pre-defined known code-vectors (stage **692B**) and finding the best fit between unknown tested features vector and pre-determined code-vectors set, using the most probable state and the relative statistical distance to the tested features vector (stage **692C**).

[00200] Method **600** may further comprise generating the set of abnormal states patterns as a reference codebook, a set of states transition probabilities, and a states-patterns matching function to find and alert on a match between a tested states pattern and the pre-defined abnormal pattern of the codebook (stage **694**). Method **600** may further comprise communicating an alert
 5 upon determining of an abnormal physical event (stage **695**).

[00201] Method **600** may further comprise estimating the reflected clutter from a specific voxel to extract the human position and posture features (stage **612A**), extracting the human motions and breathing features using Doppler signatures (stage **612B**) and creating a quantized vectors of the extracted features (stage **612C**).

10 [00202] Method **600** may comprise, with respect to posture (and position) features extraction **612A**, processing the received echo signals to derive a spatial distribution of echo sources in the environment using spatial parameters of the transmitting and/or receiving antennas (stage **620**), carried out, e.g., by a back-projection algorithm, and estimating a posture of the at least one human by analyzing the spatial distribution with respect to echo intensity (stage **628**). Method
 15 **600** may comprise canceling environmental clutter by filtering out static non-human related echo signals (see stages **605**, **606**).

[00203] Processing **620** may be carried out with respect to multiple antenna baselines as the transmitting and/or receiving antennas, as explained above. Method **600** may further comprise enhancing echoes received from a lower level in the environment to enhance detection sensitivity
 20 to a laying posture of the at least one human (stage **622**).

[00204] Method **600** may further comprise detecting a position of the at least one human from the spatial distribution (stage **624**) and possibly tracking the detected position over time. Canceling environmental clutter **605** may be carried out by spatially characterizing the static non-human related echo signals during an absence of the at least one human from the
 25 environment, as detected by the tracking (stage **626**).

[00205] Posture estimation **628** may comprise analyzing the spatial distribution using curve characteristics of one or more projections of an intensity of the received echo signals onto at respective one or more axes (stage **630**), in particular with respect to one or more horizontal axis and a vertical axis. The spatial distribution may be defined using voxels and the posture may be
 30 estimated **628** using high-power voxels as defined by a specified power threshold (stage **632**).

[00206] Method **600** may further comprise classifying the posture characteristics of the at least one human to indicate a state of the at least one human (stage **634**), possibly by preparing at least one codebook during a training phase and using the at least one codebook to classify the detected postures (stage **636**), as explained above. As explained below,

Classification **634** may be carried out by identifying a most probable fit of one of a plurality of predefined states to the motion characteristics (stage **692C**), possibly followed by generating an alert once the indicated state is related to at least one specified emergency (stage **695**), the alert generation being possibly based on pattern recognition with respect to previously indicated states (stage **694**).

[00207] Method **600** may further comprise processing the received echo signals to yield a range-bin-based slow signal that is spatio-temporally characterized over a plurality of spatial range bins and a plurality of temporal sub-frames, respectively (stage **640**) and deriving from the slow signal a Doppler signature and a range-time energy signature as motion characteristics of the at least one human (stage **650**). Method **600** may comprise deriving the Doppler signature by comparing spectral signatures of sub-frames in the slow signals, which are related to identified human-related range bins and sub-frames (stage **642**) and deriving the energy signature by evaluating powers of the slow signal at identified human-related range bins and sub-frames (stage **644**). Method **600** may comprise deriving the Doppler signature and/or the energy signature with respect to different body parts of the at least one human (stage **646**).

[00208] Deriving **650** may further comprise deriving location data as movement characteristics of the at least one human (stage **652**). Deriving of the location data **652** may comprise detecting displacements of the at least one human using back-projection (stage **654**), using the received echo signals to derive, by back projection, 2D location data and 3D posture data about the at least one human (stage **655**), and/or identifying human-related range bins and sub-frames in the slow signals (stage **656**). Deriving of the location data **652** may be carried out using a spatio-temporal histogram of the range-time energy signature and by identifying on the histogram range changes of at least body parts (e.g., limbs) of the at least one human (stage **658**). The motion characteristics and/or movement characteristics may comprise gait parameters.

[00209] Method **600** may further comprise handing over detecting **654** among a plurality of interferometry units according to detected displacements (stage **660**), i.e., using different interferometry units for detection **654** according to displacement parameters, such as coverage region, signal intensity etc., as explained below. Method **600** may be carried out by a plurality of UWB RF receiving SAAAs positioned at a plurality of positions, and may further comprise integrating the received echo signals from the UWB RF receiving SAAAs (stage **662**).

[00210] Method **600** may comprise, after transmitting the UWB RF signals and receiving the echo signals (stage **500**) and after processing the received echo signals to yield the range-bin-based slow signal (stage **640**), estimating at least one respiration parameter of the at least one human by analyzing the slow signal (stage **665**).

[00211] Method **600** may further comprise removing motion related components from the slow signal (stage **667**) and deriving a range-bin power spectrum therefrom to identify a respiration-related ROI (stage **668**), possibly identifying chest(s) of the human(s) by detecting ROI cross-correlation as described above (stage **669**), deriving from the respiration-related ROI a respiration signal (stage **670**), and extracting at least one respiration feature from the respiration signal (stage **675**). Deriving **670** of the respiration signal may be carried out by combining, coherently, a plurality of differently phase-shifted slow signals (stage **672**) and/or with respect to a derivative of the respiration signal (stage **674**).

[00212] The respiration features may comprise any of: a respiration rate, respiration asymmetry, respiration tidal volume changes, breath duty cycle parameters, inhalation and/or exhalation durations, maximal inhalation and/or exhalation values, and chest movements and related energy, velocity and/or activity, as explained above.

[00213] Method **600** may further comprise applying a PCA (principal component analysis) on earlier-derived slow signals to estimate a respiration rate (stage **677**) and/or applying a FFT (fast Fourier transform) to the slow signal prior to range-bin power spectrum derivation **668**, and enhancing high frequencies of the spectrum (stage **680**), as demonstrated in detail above.

[00214] Method **600** may further comprise deriving a location of the at least one human (and/or the chest of the human) prior to the derivation of the respiration signal and possibly tracking the detected position over time (stage **682**). Other signal processing stages described above as well as classification stages described below may be applied with respect to the respiration signal(s) and feature(s). Various types of features (movement, motion, posture and/or respiration) may be correlated and/or used in combination for the classification and alert generation described below.

[00215] Method **600** may comprise classifying the position and/or posture and/or motion and/or movement and/or respiration characteristics of the at least one human to indicate a state of the at least one human (stage **688**). Classification **688**, e.g., by identifying the most probable fit **690**, may be carried out by identifying a most probable fit of one of a plurality of predefined states to the motion characteristics. Classification **688** may comprise classifying respiration parameters and feature to indicate respiration modes of the human(s), and may comprise using the respiration modes to indicate the state of the human(s).

[00216] Communicating the alert **695** may be carried out by generating the alert once the indicated state is related to at least one specified emergency. The alert generation may be based on pattern recognition with respect to previously indicated states.

[00217] Aspects of the present invention are described above with reference to flowchart illustrations and/or portion diagrams of methods, apparatus (systems) and computer program

products according to embodiments of the invention. It will be understood that each portion of the flowchart illustrations and/or portion diagrams, and combinations of portions in the flowchart illustrations and/or portion diagrams, can be implemented by computer program instructions. These computer program instructions may be provided to a processor of a general purpose computer, special purpose computer, or other programmable data processing apparatus to produce a machine, such that the instructions, which execute via the processor of the computer or other programmable data processing apparatus, create means for implementing the functions/acts specified in the flowchart and/or portion diagram portion or portions.

[00218] These computer program instructions may also be stored in a computer readable medium that can direct a computer, other programmable data processing apparatus, or other devices to function in a particular manner, such that the instructions stored in the computer readable medium produce an article of manufacture including instructions which implement the function/act specified in the flowchart and/or portion diagram portion or portions.

[00219] The computer program instructions may also be loaded onto a computer, other programmable data processing apparatus, or other devices to cause a series of operational steps to be performed on the computer, other programmable apparatus or other devices to produce a computer implemented process such that the instructions which execute on the computer or other programmable apparatus provide processes for implementing the functions/acts specified in the flowchart and/or portion diagram portion or portions.

[00220] The aforementioned flowchart and diagrams illustrate the architecture, functionality, and operation of possible implementations of systems, methods and computer program products according to various embodiments of the present invention. In this regard, each portion in the flowchart or portion diagrams may represent a module, segment, or portion of code, which comprises one or more executable instructions for implementing the specified logical function(s). It should also be noted that, in some alternative implementations, the functions noted in the portion may occur out of the order noted in the figures. For example, two portions shown in succession may, in fact, be executed substantially concurrently, or the portions may sometimes be executed in the reverse order, depending upon the functionality involved. It will also be noted that each portion of the portion diagrams and/or flowchart illustration, and combinations of portions in the portion diagrams and/or flowchart illustration, can be implemented by special purpose hardware-based systems that perform the specified functions or acts, or combinations of special purpose hardware and computer instructions.

[00221] In the above description, an embodiment is an example or implementation of the invention. The various appearances of "one embodiment", "an embodiment", "certain embodiments" or "some embodiments" do not necessarily all refer to the same embodiments.

Although various features of the invention may be described in the context of a single embodiment, the features may also be provided separately or in any suitable combination. Conversely, although the invention may be described herein in the context of separate embodiments for clarity, the invention may also be implemented in a single embodiment.

5 Certain embodiments of the invention may include features from different embodiments disclosed above, and certain embodiments may incorporate elements from other embodiments disclosed above. The disclosure of elements of the invention in the context of a specific embodiment is not to be taken as limiting their use in the specific embodiment alone. Furthermore, it is to be understood that the invention can be carried out or practiced in various
10 ways and that the invention can be implemented in certain embodiments other than the ones outlined in the description above.

[00222] The invention is not limited to those diagrams or to the corresponding descriptions. For example, flow need not move through each illustrated box or state, or in exactly the same order as illustrated and described. Meanings of technical and scientific terms used herein are to be
15 commonly understood as by one of ordinary skill in the art to which the invention belongs, unless otherwise defined. While the invention has been described with respect to a limited number of embodiments, these should not be construed as limitations on the scope of the invention, but rather as exemplifications of some of the preferred embodiments. Other possible variations, modifications, and applications are also within the scope of the invention.
20 Accordingly, the scope of the invention should not be limited by what has thus far been described, but by the appended claims and their legal equivalents.

CLAIMS

1. A non-wearable monitoring system comprising:

a radio frequency (RF) interferometer configured to transmit signals at a specified area
5 and receive echo signals via an antenna array;

an environmental clutter cancelation module configured to filter out static non-human
related echo signals;

a human state feature extractor configured to extract from the filtered echo signals, a
quantified representation of position postures, movements, motions and breathing of at least one
10 human located within the specified area;

a human state classifier configured to identify a most probable fit of human current state
that represents an actual human instantaneous status; and

an abnormality situation pattern recognition module configured to apply a pattern
recognition based decision function to the identified states patterns and determine whether an
15 abnormal physical event has occurred to the at least one human in the specified area.

2. The system according to claim 1, wherein the extracted features are vector quantized, and
wherein the classifier is configured to find the best match to a codebook which represents the
state being a set of human instantaneous condition/situation which is based on said quantized
20 features.

3. The system according to claim 1, wherein the RF interferometer is an ultra-wide band
(UWB) RF interferometer which includes: a multiple synthetic aperture antennas arrays; UWB
pulse generator, UWB transmitter and UWB receiver configured to capture echo signal from
25 every antenna and every array.



4. The system according to claim 1, wherein the environmental clutter cancelation module
comprises a static environment detector configured to ensure that no human body at the
environment, static clutter estimator and static clutter subtraction.

5. The system according to claim 1, wherein the human state features extractor comprises: a
back-projection unit configured to estimate the reflected clutter from a specific voxel to extract
the human position and posture features; a Doppler estimator configured to extract the human
motions and breathing features; and a features vector generator configured to create a quantized
35 vectors of the extracted features.

6. The system according to claim 1, wherein the human state classifier comprises a training unit configured to quantize the known states features vectors and generate the states code-vectors; a distance function configured to measure the distance between unknown tested features
5 vectors and pre-defined known code-vectors; and a classifier unit configured to find the best fit between unknown tested features vector and pre-determined code-vectors set, classifier output consisting of the most probable state and the relative statistical distance to the tested features vector.
- 10 7. The system according to claim 1, wherein the abnormality pattern recognition module comprises: a training unit configured to generate the set of abnormal states patterns as a reference codebook, and set of states transition probabilities, and states patterns matching function to find and alert on a match between a tested states pattern and the pre-defined abnormal pattern of the codebook.
- 15 8. The system according to claim 1, further comprising a communication sub-system configured to communicate an alert upon determining of an abnormal physical event.
- 20 9. The system according to claim 8, wherein the communication sub-system comprises: a signaling link configured to transmit the system alerts to far end, a two way voice and video communication to interact with the monitored person, and two-way data link to remotely upgrade the system.
- 25 10. The system according to claim 8, further comprising a remote centralized data analyzing unit comprising: a data collection unit to receive the monitoring and alerts units' data, data analyzer to find new abnormal patterns based on multiple users situations, abnormal patterns codebook generator to update the codebook with the new abnormal patterns.
- 30 11. The system according to claim 1, configured to operate with similar systems in a master-slave configuration in which the RF interferometer and set of antennas are configured to act as a repeater communicating between at least two systems.
- 35 12. The system according to claim 1, wherein parameters obtained in a training sequence are used to configure the human state classifier per a specific person.
13. The system according to claim 12, wherein the trained environmental parameters are calculated by monitoring a human in various locations and positions in a predefined order.

14. The system according to claim 7, wherein the abnormal patterns reference codebook is remotely updated with new abnormal patterns received from data analysis by multiple users.

5 15. The system according to claim 1, wherein the system further includes an interface with at least one of: a wearable medical sensor configured to sense vital signs of the human, and a home safety sensor configured to sense ambient conditions at said specified area, and wherein data from said at least one sensor are used by said decision function for improving the decision whether an abnormal physical event has occurred to the at least one human in said specified area.






Figure 1C




Figure 2C




Figure 2D




Figure 2E

Figure 2F




Figure 2G




Figure 2I




Figure 2H




Figure 2J




Figure 2K




Figure 2L









Figure 2M










Figure 2S




Figure 3A




Figure 3B




Figure 3C




Figure 3D




Figure 3E




Figure 3F




Figure 3G




Figure 3H




Figure 3I




Figure 3J




Figure 4A




Figure 4B




Figure 4C




Figure 4D




Figure 4E







Figure 4F

424E**Figure 4G**






Figure 4J






Figure 4K






Figure 4N




Figure 4N (cont. 1)




Figure 5A




Figure 5B




Figure 5C




Figure 5D




Figure 5E




Figure 5F




Figure 5G




Figure 5H




Figure 5I




Figure 5J




Figure 5K




Figure 5L




Figure 5M

134

VQ States Definition

State Number	State name	Location	Human Centroid Level from Floor	Posture	Movement Motions	Breathing [Resp/Min]	Time Limit [Minutes]
S10	On floor	NA	<0.5	Horizontal & all	No	Normal	5
S21	Sleeping	Bedroom	>0.5	Horizontal	No	Normal	Daylight-180 Night-480
S25	Sleeping	Livingroom	>0.5	Horizontal	No	Normal	Daylight-180 Night-480
S33	Sitting @ Toilet	Restroom	1	Zigzag	No	Normal	20
S36	Sitting	NA	1	Zigzag	No	Normal	180
S40	Standing	NA	>1.5	Vertical	No	Normal	60
S50	Walking	NA	>1.5	Vertical	Yes (Gait)	Normal	30
S60	Falling	NA	<0.5	NA	No	Abnormal	NA
S70	Stress	NA	NA	NA	NA	Very High	30
S80	Bath	Bathroom	>0.5 / >1/5	Zigzag/Vertical & all	No	Normal	30

Figure 6A

135

States Matrix						
State\Location	1-bedroom	2-Bathroom	3-Restroom	4-kitchen	5-Livingroom	6-other
1-On floor						
2-Sleeping	X					
3-Sitting						
4-Standing						
5-Walking						
6-"Falling" (Vertical motion)						
7. Stress						

Figure 6B

136

CSA States Patterns

Situation	State1	State2	State3	State4	State5	Pattern Repetitions
Critical Fall 1	S25	S45	S65	S15	S75	1
Critical Fall 2	S42	S62	S12	S72	X	1
Critical Fall 3	S51	S61	S11	X	X	1
Critical Fall 4	S35	S45	S65	S15	S75	1
High Restroom usage	S31	S51	S33	S51	S31	>5
Sedentary1	S35	X	X	X	X	>Time Thresh
Sedentary2	S35	S75	X	X	X	1

Figure 6C




Figure 7




Figure 8





Figure 9



600

605

Canceling environmental clutter

606

Filtering out static non-human related echo signals

607

Ensuring that no human body is at the environment, using static clutter estimation and static clutter subtraction

610

Extracting from the filtered echo signals, a quantified representation of position postures, movements, motions and breathing of human(s) located within the specified area

612A

Estimating the reflected clutter from a specific voxel to extract the human position and posture features

612B

Extracting the human motions and breathing features using Doppler signatures

612C

Creating a quantized vectors of the extracted features

Figure 10 (Cont. 1)

600

620

Processing received echo signals to derive a spatial distribution of echo sources in the environment using spatial parameters of transmitting and/or receiving antennas, e.g., using back propagation

622

Enhancing echoes received from a lower level in the environment to enhance detection sensitivity to a laying posture of human

624

Detecting and tracking a position of the human from the spatial distribution

626

Spatially characterizing the environment during an absence of the human

628

Estimating the posture of the human(s) by analyzing the spatial distribution with respect to echo intensity



Figure 10 (Cont. 2)

600

630

Analyzing the spatial distribution using curve characteristics of projection(s) of an intensity of the received echo signals onto vertical and horizontal axes

632

Defining the spatial distribution by voxels and using high power voxels to estimate the posture


634

Classifying the posture characteristics of the human to indicate a state thereof

636

Classifying by preparing codebook(s) during a training phase and using the codebook (s) to classify the detected postures

Figure 10 (Cont. 3)

**Figure 10 (Cont. 4)**


**Figure 10 (Cont. 5)**

**Figure 10 (Cont. 6)**




Figure 10 (Cont. 7)




Figure 10 (Cont. 8)

INTERNATIONAL SEARCH REPORT

International application No.

PCT/IL2016/050655

A. CLASSIFICATION OF SUBJECT MATTER IPC (2016.01) G08B 21/02, G08B 21/04, G01S 13/00, A61B 5/05 According to International Patent Classification (IPC) or to both national classification and IPC		
B. FIELDS SEARCHED Minimum documentation searched (classification system followed by classification symbols) IPC (2016.01) G08B 23/00, G01S 13/00, G01S 3/02, A61B 5/05, G08B 21/04 Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched Electronic data base consulted during the international search (name of data base and, where practicable, search terms used) Databases consulted: PATENTSCOPE, Esp@cenet, Google Patents, FamPat database Search terms used: radar, fall, home, health, monitor		
C. DOCUMENTS CONSIDERED TO BE RELEVANT		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 7567200 B1 Josef Osterweil 28 Jul 2009 (2009/07/28) Entire Document	1-15
A	US 2014362213 A1 TSENG VINCENT 11 Dec 2014 (2014/12/11) Entire Document	1-15
☐ Further documents are listed in the continuation of Box C. ☒ See patent family annex.		
* Special categories of cited documents: "A" document defining the general state of the art which is not considered to be of particular relevance "E" earlier application or patent but published on or after the international filing date "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified) "O" document referring to an oral disclosure, use, exhibition or other means "P" document published prior to the international filing date but later than the priority date claimed "T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art "&" document member of the same patent family		
Date of the actual completion of the international search 10 Oct 2016		Date of mailing of the international search report 13 Oct 2016
Name and mailing address of the ISA: Israel Patent Office Technology Park, Bldg.5, Malcha, Jerusalem, 9695101, Israel Facsimile No. 972-2-5651616		Authorized officer DRORI Avishag Telephone No. 972-2-5657821

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No.

PCT/IL2016/050655

Patent document cited search report	Publication date	Patent family member(s)	Publication Date
US 7567200 B1	28 Jul 2009	US 7567200 B1	28 Jul 2009
		CN 101657709 A	24 Feb 2010
		EP 2135051 A1	23 Dec 2009
		US 7377177 B1	27 May 2008
		US 7916066 B1	29 Mar 2011
		US 8068051 B1	29 Nov 2011
		WO 2008128015 A1	23 Oct 2008
US 2014362213 A1	11 Dec 2014	US 2014362213 A1	11 Dec 2014