




(86) Date de dépôt PCT/PCT Filing Date: 2005/02/14
(87) Date publication PCT/PCT Publication Date: 2005/08/25
(45) Date de délivrance/Issue Date: 2012/08/21
(85) Entrée phase nationale/National Entry: 2006/06/27
(86) N° demande PCT/PCT Application No.: KR 2005/000402
(87) N° publication PCT/PCT Publication No.: 2005/078964
(30) Priorités/Priorities: 2004/02/14 (KR10-2004-0009821);
2004/02/20 (KR10-2004-0011565);
2004/05/07 (KR10-2004-0032410);
2004/06/17 (KR10-2004-0045127);
2004/07/16 (KR10-2004-0055676);
2004/09/14 (KR10-2004-0073547);

(51) Cl.Int./Int.Cl. *H04B 7/26* (2006.01)
(72) Inventeurs/Inventors:
CHO, JOON-YOUNG, KR;
LEE, JU-HO, KR;
HEO, YOUN-HYOUNG, KR;
KWAK, YONG-JUN, KR;
KIM, YOUNG-BUM, KR
(73) Propriétaire/Owner:
SAMSUNG ELECTRONICS CO., LTD., KR
(74) Agent: MARKS & CLERK

(54) Titre : APPAREIL ET PROCEDE D'AFFECTATION DE CODES OVFS ET DE CANAUX I/Q POUR REDUIRE LE RAPPORT DE PUISSANCE CRETE/MOYENNE DANS LA TRANSMISSION DE DONNEES VIA DES CANAUX DEDIES DE LIAISON MONTANTE AMELIORES DANS DES SYSTEMES WCDMA
(54) Title: APPARATUS AND METHOD FOR ALLOCATING OVFS CODES AND I/Q CHANNELS FOR REDUCING PEAK-TO-AVERAGE POWER RATIO IN TRANSMITTING DATA VIA ENHANCED UP-LINK DEDICATED CHANNELS IN WCDMA SYSTEMS



(57) Abrégé/Abstract:

The present invention supposes a situation in which an Enhanced Uplink Dedicated transport Channel (EUDCH) is used in a Wideband Code Division Multiple Access (WCDMA) system. In a user equipment (UE), when physical channels for transmitting

(30) **Priorités(suite)/Priorities(continued)**: 2004/09/20 (KR10-2004-0075256); 2004/11/08 (KR10-2004-0090577); 2004/11/09 (KR10-2004-0091097); 2004/11/16 (KR10-2004-0093740)

(57) **Abrégé(suite)/Abstract(continued)**:

EUDCH data are transmitted in addition to existing physical channels, a Peak-to-Average Power Ratio (PAPR) of an uplink transport signal increases. The increase in PAPR depends upon Orthogonal Variable Spreading Factor (OVSF) codes allocated to the corresponding physical channels and in-phase/quadrature-phase (I/Q) channels. Therefore, the present invention proposes an apparatus and method for allocating optimum OVSF codes and I/Q channels to EUDCH-related physical channels in order to minimize an increase in PAPR due to EUDCH.

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property
Organization
International Bureau



(43) International Publication Date
25 August 2005 (25.08.2005)


PCT

(10) International Publication Number
WO 2005/078964 A1

- (51) International Patent Classification⁷: **H04B 7/26** 10-2004-0090577
8 November 2004 (08.11.2004) KR
- (21) International Application Number: 10-2004-0091097
PCT/KR2005/000402 9 November 2004 (09.11.2004) KR
10-2004-0093740 16 November 2004 (16.11.2004) KR
- (22) International Filing Date: 14 February 2005 (14.02.2005)
- (25) Filing Language: Korean
- (26) Publication Language: English
- (30) Priority Data:
10-2004-0009821 14 February 2004 (14.02.2004) KR
10-2004-0011565 20 February 2004 (20.02.2004) KR
10-2004-0032410 7 May 2004 (07.05.2004) KR
10-2004-0045127 17 June 2004 (17.06.2004) KR
10-2004-0055676 16 July 2004 (16.07.2004) KR
10-2004-0073547 14 September 2004 (14.09.2004) KR
10-2004-0075256 20 September 2004 (20.09.2004) KR
- (71) Applicant: **SAMSUNG ELECTRONICS CO., LTD.**
[KR/KR]; 416, Maetan-dong, Yeongtong-gu, Suwon-si,
Gyeonggi-do 442-742 (KR).
- (72) Inventors: **CHO, Joon-Young**; #124-802 Hwanggol-
maeul 1-danji APT., Yeongtong-dong, Yeongtong-gu,
Suwon-si, Gyeonggi-do 443-740 (KR). **LEE, Ju-Ho**;
#730-304 Salgugol Hyundai APT., Yeongtong-dong,
Yeongtong-gu, Suwon-si, Gyeonggi-do 443-736 (KR).
HEO, Youn-Hyoung; #303, 1003-14 Yeongtong-dong,
Yeongtong-gu, Suwon-si, Gyeonggi-do 443-813 (KR).
KWAK, Yong-Jun; #101-1601 Daejin 1-cha APT., Juk-
jeon 1-dong, Yongin-si, Gyeonggi-do 449-752 (KR). **KIM,**
Young-Bum; #302, Seongji Villa, 349-123 Sindang-dong,
Jung-gu, Seoul 100-450 (KR).
- (74) Agent: **LEE, Keon-Joo**; Mihwa Bldg. 110-2, Myon-
gyun-dong 4-ga, Chongro-gu, Seoul 110-524 (KR).

[Continued on next page]

(54) Title: APPARATUS AND METHOD FOR ALLOCATING OVFS CODES AND I/Q CHANNELS FOR REDUCING PEAK-TO-AVERAGE POWER RATIO IN TRANSMITTING DATA VIA ENHANCED UP-LINK DEDICATED CHANNELS IN WCDMA SYSTEMS



(57) Abstract: The present invention supposes a situation in which an Enhanced Uplink Dedicated transport Channel (EUDCH) is used in a Wideband Code Division Multiple Access (WCDMA) system. In a user equipment (UE), when physical channels for transmitting EUDCH data are transmitted in addition to existing physical channels, a Peak-to-Average Power Ratio (PAPR) of an uplink transport signal increases. The increase in PAPR depends upon Orthogonal Variable Spreading Factor (OVFS) codes allocated to the corresponding physical channels and in-phase/quadrature-phase (I/Q) channels. Therefore, the present invention proposes an apparatus and method for allocating optimum OVFS codes and I/Q channels to EUDCH-related physical channels in order to minimize an increase in PAPR due to EUDCH.

WO 2005/078964 A1

WO 2005/078964 A1

(81) **Designated States** (*unless otherwise indicated, for every kind of national protection available*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BW, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NA, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, UZ, VC, VN, YU, ZA, ZM, ZW.

(84) **Designated States** (*unless otherwise indicated, for every kind of regional protection available*): ARIPO (BW, GH, GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM),

European (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LT, LU, MC, NL, PL, PT, RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Published:

- *with international search report*
- *before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments*

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

- 1 -

**APPARATUS AND METHOD FOR ALLOCATING OVSF CODES AND
I/Q CHANNELS FOR REDUCING PEAK-TO-AVERAGE POWER RATIO
IN TRANSMITTING DATA VIA ENHANCED UP-LINK DEDICATED
CHANNELS IN WCDMA SYSTEMS**

5

BACKGROUND OF THE INVENTION

1. Field of the Invention

10 The present invention relates generally to an asynchronous Wideband Code Division Multiple Access (WCDMA) communication system, and in particular, to an apparatus and method for minimizing an increase in Peak-to-Average Power Ratio (PAPR) of a transmission signal during data transmission through an Enhanced Uplink Dedicated transport Channel (EUDCH).

15 That is, the present invention proposes an optimal Orthogonal Variable Spreading Factor (OVSF) code and in-phase/quadrature-phase (I/Q) channel allocation apparatus and method for uplink physical channels for EUDCH service.

2. Description of the Related Art

20 Currently, an uplink of a WCDMA system includes a Dedicated Physical Data Channel (DPDCH) and a Dedicated Physical Control Channel (DPCCH) as typical dedicated physical channels used to transmit user signals. The DPDCH is a data transport channel over which user data such as voice and image is transmitted, and the DPCCH is a control information transport channel on which
25 DPDCH frame format information and pilot information for DPDCH demodulation and power control are carried.

30 Recently, technology using a EUDCH which is an enhanced uplink data-only transport channel has been proposed to improve a rate and efficiency of packet data transmission in an uplink.

FIG. 1 is a diagram illustrating information exchanged between user equipments and a Node B to perform uplink transmission.

35 Referring to FIG. 1, UEs 110, 112, 114 and 116 transmit packet data with

- 2 -

different transmission power according to their distances from a Node B 100. The UE 110 which is located in the longest distance from the Node B 100 transmits packet data with the highest transmission power 120 for the uplink channel, while the UE 114 which is located in the shortest distance from the Node B transmits the packet data with the lowest transmission power 124 for the uplink channel. In order to improve performance of the mobile communication system, the Node B 100 can perform scheduling in such a manner that a level of the transmission power for the uplink channel should be in reverse proportion to the data rate. That is, the Node B allocates the lowest data rate to a UE having the highest transmission power for the uplink channel, and allocates the highest data rate to a UE having the lowest transmission power for the uplink channel.

FIG. 2 is a diagram illustrating information exchanged between a UE and a Node B to perform uplink transmission. That is, FIG. 2 illustrates a basic procedure required between a Node B 200 and a UE 202 for packet data transmission through a EUDCH.

Referring to FIG. 2, in step 210, a EUDCH is set up between the Node B 200 and the UE 202. Step 210 includes a process of transmitting/receiving messages through a dedicated transport channel. After step 210, the UE 202 transmits in step 212 information on a desired data rate and information indicating an uplink channel condition to the Node B 200. The information indicating an uplink channel condition includes transmission power of an uplink channel transmitted by the UE 202 and a transmission power margin of the UE 203.

The Node B 200 receiving the uplink channel transmission power can estimate a downlink channel condition by comparing the uplink channel transmission power with reception power. That is, the Node B 200 considers that an uplink channel condition is good if a difference between the uplink channel transmission power and the uplink channel reception power is small, and considers that the uplink channel condition is bad if the difference between the transmission power and the reception power is great. When the UE transmits transmission power margin to estimate an uplink channel condition, the Node B 200 can estimate the uplink transmission power by subtracting the transmission

- 3 -

power margin from the known possible maximum transmission power for the UE. The Node B 200 determines the possible maximum data rate for an uplink packet channel of the UE 202 using the estimated channel condition of the UE 202 and information on a data rate required by the UE 202.

5

The determined possible maximum data rate is notified to the UE 202 in step 214. The UE 202 determines a data rate for transmission packet data within a range of the notified possible maximum data rate, and transmits in step 216 the packet data to the Node B 200 at the determined data rate.

10

Herein, uplink physical channels supporting the EUDCH service include a Dedicated Physical Data Channel (DPDCH), a Dedicated Physical Control Channel (DPCCH), a High Speed Dedicated Physical Control Channel (HS-DPCCH) for HSDPA service, an Enhanced Dedicated Physical Data Channel (E-DPDCH) for the EUDCH service, and an Enhanced Dedicated Physical Control Channel (E-DPCCH) for the EUDCH service.

15

That is, in step 216, the UE 202 transmits an E-DPCCH which is a control channel to provide frame format and channel coding information of the E-DPDCH channel, and transmits packet data through the E-DPDCH. Herein, the E-DPCCH can also be used for transmission of an uplink data rate required by the UE 202 and transmission power margin, and transmission of pilot information required by the Node B 200 for demodulation of the E-DPDCH.

20

If the UE 202 additionally transmits separate physical channels in addition to the existing physical channels in order to transmit EUDCH packet data as described above, the number of physical channels transmitted in the uplink increases, causing an increase in a peak-to-average power ratio (PAPR) of an uplink transmission signal. It is general that the PAPR increases higher as the number of simultaneously transmitted physical channels increases higher.

25

30

Because the increase in the PAPR may increase distortion of transmission signals and an allowed Adjacent Channel Leakage power Ratio (ACLR), a radio frequency (RF) power amplifier in a UE requires power back-off which reduces amplifier's input power to prevent the foregoing problem. If the UE performs

35

- 4 -

power back-off, the power back-off results in a reduction in reception power at a receiver in a Node B, causing an increase in error rate of received data or a reduction in cell coverage.

Accordingly, in order to prevent the increase in PAPR, the UE intends to transmit the EUDCH over the existing physical channel such as a DPDCH on a time division basis, instead of transmitting the EUDCH on a separate physical channel. However, the process of transmitting the EUDCH over the existing physical channel on a time division basis causes an increase in implementation complexity.

Taking the problem into consideration, a WCDMA system has proposed a method for multiplying the physical channels by OVSF codes satisfying mutual orthogonality before transmission in the uplink. The physical channels multiplied by the OVSF codes can be distinguished in a Node B.

FIG. 3 is a diagram illustrating a tree structure for OVSF codes generally used in a WCDMA system.

Referring to FIG. 3, the OVSF codes can be simply generated in a calculation process of Equation (1) to Equation (3).

Equation (1)

$$C_{ch,1,0} = 1.$$

Equation (2)

$$\begin{bmatrix} C_{ch,2,0} \\ C_{ch,2,1} \end{bmatrix} = \begin{bmatrix} C_{ch,1,0} & C_{ch,1,0} \\ C_{ch,1,0} & -C_{ch,1,0} \end{bmatrix} = \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix}.$$

Equation (3)

- 5 -

$$\begin{bmatrix} C_{ch,2^{(n+1)},0} \\ C_{ch,2^{(n+1)},1} \\ C_{ch,2^{(n+1)},2} \\ C_{ch,2^{(n+1)},3} \\ \vdots \\ C_{ch,2^{(n+1)},2^{(n+1)}-2} \\ C_{ch,2^{(n+1)},2^{(n+1)}-1} \end{bmatrix} = \begin{bmatrix} C_{ch,2^n,0} & C_{ch,2^n,0} \\ C_{ch,2^n,0} & -C_{ch,2^n,0} \\ C_{ch,2^n,1} & C_{ch,2^n,1} \\ C_{ch,2^n,1} & -C_{ch,2^n,1} \\ \vdots & \vdots \\ C_{ch,2^n,2^{n-1}} & C_{ch,2^n,2^{n-1}} \\ C_{ch,2^n,2^{n-1}} & -C_{ch,2^n,2^{n-1}} \end{bmatrix}.$$

As illustrated in FIG. 3, the OVFS codes are characterized in that orthogonality is secured between codes having the same spreading factor (SF). In addition, for two codes having different SF values, if a code having a larger SF value cannot be generated from a code having a lower SF value using Equation (3), orthogonality is acquired between the two codes.

A description thereof will be made below by way of example.

10

For SF=4, $C_{ch,4,0}=(1,1,1,1)$ is orthogonal with $C_{ch,2,1}=(1,-1)$ but is not orthogonal with $C_{ch,2,0}=(1,1)$.

As another example, comparing SF=256 OVFS codes with the $C_{ch,2,1}=(1,1)$, because OVFS codes with SF=0~127 are generated from the $C_{ch,2,1}=(1,1)$, orthogonality is not secured therebetween. That is, as a higher data rate is required, an OVFS code with a lower SF value is used, and when a plurality of physical channels are simultaneously transmitted, the OVFS codes should be allocated such that orthogonality should necessarily be secured therebetween.

20

Even though two physical channels use the same OVFS code, if they are separately transmitted through an I channel and a Q channel of a transmitter, a receiver can separate the two physical channel signals without mutual interference and demodulate the separated physical channel signals, because the signals transmitted on the I channel and the Q channel are carried by carriers having a 90°-phase difference.

25

- 6 -

As described above, an increase in uplink PAPR depends on the number of physical channels simultaneously transmitted in the uplink, a power ratio between physical channels, an OVSF code used for each physical channel, and I/Q channel allocation for each physical channel.

5

In the WCDMA system to which the EUDCH technology is applied, if E-DPCCH and E-DPDCH channels for transmission of EUDCH packet data are simultaneously transmitted in addition to the uplink channels, the PAPR increases undesirably.

10

SUMMARY OF THE INVENTION

It is, therefore, an object of the present invention to provide a UE's transmission apparatus and method for efficiently transmitting packet data through an enhanced uplink in a mobile communication system.

15

It is another object of the present invention to provide an OVSF code and I/Q channel allocation apparatus and method for minimizing an increase in PAPR of an uplink transmission signal in a mobile communication system supporting an uplink.

20

It is further another object of the present invention to provide an apparatus and method for allocating I/Q channels and OVSF codes for E-DPDCHs and an E-DPCCH to minimize an increase in PAPR according to presence/absence of an HS-DPCCH and the number of codes for DPDCHs.

25

In accordance with one aspect of the present invention, to achieve the objects of the present invention, there is provided a method for transmitting packet data in a mobile communication system supporting transmission of enhanced uplink packet data, the method including the steps of: generating a dedicated physical control channel (DPCCH) using an Orthogonal Variable Spreading Factor (OVSF) code (256, 0) and a quadrature-phase (Q) channel; generating a dedicated physical data channel (DPDCH) using an OVSF code (SF_{DPDCH} , $SF_{DPDCH}/4$) and an in-phase (I) channel, where SF_{DPDCH} denotes a spreading factor of the DPDCH; generating an E-DPCCH using an OVSF code

30

35

- 7 -

($SF_{E-DPCCH}$, 1) and the I channel, where $SF_{E-DPCCH}$ denotes a spreading factor of an OVSF code to be allocated to an E-DPCCH for supporting transmission of enhanced uplink packet data; generating an E-DPDCH using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$) and the Q channel, where $SF_{E-DPDCH}$ denotes a spreading factor (SF) value of an OVSF code to be allocated to an E-DPDCH and the $SF_{E-DPDCH}$ is larger than 4; forming one complex symbol stream by summing up the generated I and Q channels and scrambling the complex symbol stream; and transmitting the scrambled complex symbol stream through an antenna.

10 In accordance with another aspect of the present invention, to achieve the objects of the present invention, there is provided a method for transmitting uplink packet data in a mobile communication system supporting transmission of enhanced uplink packet data, the method including the steps of: generating dedicated physical channels and a dedicated physical control channel for
15 supporting a high speed downlink packet service using Orthogonal Variable Spreading Factor (OVSF) codes; generating dedicated physical channels for transmission of enhanced uplink packet data using OVSF codes unused by the physical channels; forming one complex symbol stream by summing up an I channel and a Q channel of the generated channels and scrambling the complex
20 symbol stream; and transmitting the scrambled complex symbol stream through an antenna.

According to an aspect of the present invention, there is provided a method for transmitting enhanced packet data in a mobile communication system, the
25 method comprising the steps of:

generating a first enhanced dedicated physical data channel (E-DPDCH) through an in-phase (I) channel and a second E-DPDCH through a quadrature-phase (Q) channel if high speed downlink packet access (HSDPA) is set, and

- 7a -

generating the first E-DPDCH through the Q channel and the second E-DPDCH through the I channel if HSDPA is not set;

generating an enhanced dedicated physical control channel (E-DPCCH) using the I channel; and

5 summing up the E-DPDCHs and the E-DPCCH before transmission.

According to another aspect of the present invention, there is provided a method for transmitting enhanced packet data in a mobile communication system, the method comprising the steps of:

10 generating a dedicated physical control channel (DPCCH) using an Orthogonal Variable Spreading Factor (OVSF) code (256, 0) and a quadrature-phase (Q) channel;

generating a dedicated physical data channel (DPDCH) using an OVSF code (SF_{DPDCH} , $SF_{DPDCH}/4$) and an in-phase (I) channel, where SF_{DPDCH} denotes a spreading factor of the DPDCH;

generating an E-DPCCH using an OVSF code ($SF_{E-DPCCH}$, 1) and the I channel, where $SF_{E-DPCCH}$ denotes a spreading factor of an OVSF code to be allocated to an enhanced dedicated physical control channel (E-DPCCH) for supporting transmission of enhanced uplink packet data; and

20 generating an E-DPDCH using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$) and the Q channel, where $SF_{E-DPDCH}$ denotes a spreading factor of an OVSF code to be allocated to an enhanced dedicated physical data channel (E-DPDCH) for supporting transmission of the enhanced uplink packet data.

25 According to a further aspect of the present invention, there is provided an apparatus for supporting an enhanced packet data service in a mobile communication system, the apparatus comprising:

a controller for allocating a first enhanced dedicated physical data channel (E-DPDCH) to an in-phase (I) channel and a second E-DPDCH to a quadrature-

- 7b -

phase (Q) channel if high speed downlink packet access (HSDPA) is set, and allocating the first E-DPDCH to the Q channel and the second E-DPDCH to the I channel if HSDPA is not set, and an enhanced dedicated physical control channel (E-DPCCH) to the I channel;

5 a spreader for spreading the E-DPDCHs and the E-DPCCH according to a control signal from the controller;

a summer for summing up the spread E-DPDCHs and E-DPCCH; and
a transmitter for transmitting the summed signal.

10 According to a further aspect of the present invention, there is provided an apparatus for transmitting enhanced packet data in a mobile communication system, the apparatus comprising:

a controller for allocating an orthogonal variable spreading factor (OVSF) code (256, 0) and a quadrature-phase (Q) channel to a dedicated physical control channel (DPCCH), allocating an OVSF code (SF_{DPDCH} , $SF_{DPDCH}/4$) and an in-
15 phase (I) channel to a dedicated physical data channel (DPDCH), where SF_{DPDCH} denotes a spreading factor of the DPDCH, allocating an enhanced dedicated physical control channel (E-DPCCH) to an OVSF code ($SF_{E-DPCCH}$, 1) and the I channel, where $SF_{E-DPCCH}$ denotes a spreading factor of an OVSF code to be
20 allocated to the E-DPCCH for supporting transmission of enhanced uplink packet data, and allocating an enhanced dedicated physical data channel (E-DPDCH) to an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$) and the Q channel, where $SF_{E-DPDCH}$ denotes a spreading factor of an OVSF code to be allocated to the E-DPDCH for supporting transmission of the enhanced uplink packet data;

25 a spreader for spreading the E-DPDCH and the E-DPCCH according to a control signal from the controller;

a summer for summing up the spread E-DPDCH and E-DPCCH; and
a transmitter for transmitting the summed signal.

- 7c -

According to a further aspect of the present invention, there is provided a method for receiving enhanced packet data in a mobile communication system, the method comprising the steps of:

receiving information indicating a transport channel condition from a user
5 equipment (UE);

transmitting scheduling allocation information indicating data rate
information of an enhanced dedicated physical data channel (E-DPDCH) to the
UE; and

receiving a first enhanced dedicated physical data channel (E-DPDCH)
10 through an in-phase (I) channel and a second E-DPDCH through a quadrature-
phase (Q) channel if high speed downlink packet access (HSDPA) is set, and
receiving the first E-DPDCH through the Q channel and the second E-DPDCH
through the I channel if HSDPA is not set; and

receiving an enhanced dedicated physical control channel (E-DPCCH)
15 using the I channel.

According to a further aspect of the present invention, there is provided a method for receiving enhanced packet data in a mobile communication system, the method comprising the steps of:

20 receiving information indicating a transport channel condition from a user
equipment (UE);

transmitting scheduling allocation information indicating data rate
information of an enhanced dedicated physical data channel (E-DPDCH) to the
UE;

25 receiving a dedicated physical control channel (DPCCH) using an
orthogonal variable spreading factor (OVSF) code (256, 0) and a quadrature-phase
(Q) channel;

- 7d -

receiving a dedicated physical data channel (DPDCH) using an OVSF code (SF_{DPDCH} , $SF_{DPDCH}/4$) and an in-phase (I) channel, where SF_{DPDCH} denotes a spreading factor of the DPDCH;

receiving an enhanced dedicated physical control channel (E-DPCCH)
5 using an OVSF code ($SF_{E-DPCCH}$, 1) and the I channel, where $SF_{E-DPCCH}$ denotes a spreading factor of an OVSF code to be allocated to the E-DPDCH for supporting transmission of enhanced uplink packet data; and

receiving an E-DPDCH using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$) and the Q channel, where $SF_{E-DPDCH}$ denotes a spreading factor of an OVSF code to be
10 allocated to the E-DPDCH for supporting transmission of the enhanced uplink packet data.

According to a further aspect of the present invention, there is provided an apparatus for receiving enhanced packet data in a mobile communication system,
15 the apparatus comprising:

a receiver for receiving information indicating a transport channel condition from a user equipment (UE), and receiving a first enhanced dedicated physical data channel (E-DPDCH) through an in-phase (I) channel and a second E-DPDCH through a quadrature-phase (Q) channel if high speed downlink packet
20 access (HSDPA) is set, and receiving the first E-DPDCH through the Q channel and the second E-DPDCH through the I channel if HSDPA is not set, and an enhanced dedicated physical control channel (E-DPCCH) through the I channel; and

a transmitter for transmitting scheduling allocation information indicating
25 data rate information of an enhanced dedicated physical data channel (E-DPDCH) to the UE; and

a controller for controlling the transmitter and the receiver.

- 7e -

According to a further aspect of the present invention, there is provided an apparatus for receiving enhanced packet data in a mobile communication system, the apparatus comprising:

a receiver for receiving information indicating a transport channel condition from a user equipment (UE), receiving a dedicated physical control channel (DPCCH) using an orthogonal variable spreading factor (OVSF) code (256, 0) and a quadrature-phase (Q) channel, receiving a dedicated physical data channel (DPDCH) using an OVSF code (SF_{DPDCH} , $SF_{DPDCH}/4$) and an in-phase (I) channel, where SF_{DPDCH} denotes a spreading factor of the DPDCH, receiving an enhanced dedicated physical control channel (E-DPCCH) using an OVSF code ($SF_{E-DPCCH}$, 1) and the I channel, where $SF_{E-DPCCH}$ denotes a spreading factor of an OVSF code to be allocated to the E-DPCCH for supporting transmission of enhanced uplink packet data, and receiving an enhanced dedicated physical data channel (E-DPDCH) using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$) and the Q channel, where $SF_{E-DPDCH}$ denotes a spreading factor of an OVSF code to be allocated to the E-DPDCH for supporting transmission of the enhanced uplink packet data;

a transmitter for transmitting scheduling allocation information indicating data rate information of the E-DPDCH to the UE; and

a controller for controlling the receiver and the transmitter.

BRIEF DESCRIPTION OF THE DRAWINGS

The above and other objects, features and advantages of the present invention will become more apparent from the following detailed description when taken in conjunction with the accompanying drawings in which:

FIG. 1 is a diagram illustrating user equipments (UEs) performing uplink transmission and a Node B;

- 7f -

FIG. 2 is a diagram illustrating information exchanged between a UE and a Node B to perform uplink transmission;

FIG. 3 is a diagram illustrating a tree structure for general OVSF codes;

FIG. 4 is a diagram illustrating a transmitter structure of a UE according to
5 an embodiment of the present invention; and

FIG. 5 is a diagram illustrating a PAPR comparison result between

- 8-

physical channels according to an embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

5 Several preferred embodiments of the present invention will now be described in detail with reference to the annexed drawings. In the following description, a detailed description of known functions and configurations incorporated herein has been omitted for conciseness.

10 The present invention proposes an OVSF code and I/Q channel allocation method for minimizing an increase in PAPR of an uplink transmission signal in a WCDMA system supporting EUDCH data service. That is, the present invention proposes an OVSF code and I/Q channel allocation method optimized for the case
15 where an E-DPCCH which is a control channel and an E-DPDCH which is a data channel, for transmission of EUDCH packet data, are transmitted in addition to the existing physical channels. In order to increase a EUDCH data rate and minimize an increase in PAPR, the present invention proposes an OVSF code and I/Q channel allocation method for minimizing the PAPR increase while maintaining orthogonality between the existing DPCCH, DPDCH and HS-
20 DPCCH.

 In the existing Rel-5 WCDMA standard, OVSF code and I/Q channel allocation for an HS-DPCCH channel is achieved so as to reduce a PAPR considering the maximum number of transmittable DPDCHs, determined during
25 setup of a radio link between a UE and a Node B.

 Therefore, OVSF code and I/Q channel allocation for an E-DPDCH and an E-DPCCH, proposed in the present invention, is achieved considering the maximum number of DPDCHs transmittable in the radio link and
30 transmission/non-transmission of an HS-DPCCH, for the Rel-5 physical channels. In the EUDCH service, several E-DPDCH physical channels can be simultaneously transmitted because they support high-data rate transmission. However, it is generally sufficient that a single E-DPCCH, which is a physical control channel, is transmitted.

35

- 9 -

That is, in order to reduce a PAPR increase of an uplink transmission signal, the present invention supports a EUDCH considering backward compatibility with the existing WCDMA system. The reason is because serious problems may occur in initial call setup or handover processes when Node Bs are inconsistent with each other in terms of a version due to incompatibility for DPDCH and DPCCH standard.

In other words, the present invention proposes an OVSF code and I/Q channel allocation method optimized to minimize the PAPR increase for EUDCH-related physical channels while maintaining the existing Rel-5 WCDMA standard for the DPDCH and the DPCCH which are core uplink physical channels.

First, assuming that the existing uplink channels such as a DPCCH, a DPDCH and an HS-DPCCH undergo OVSF code and I/Q channel allocation as defined in the current standard in an OVSF code and I/Q channel allocation method by maintaining full compatibility with the existing Rel-5 WCDMA system, the present invention proposes an OVSF code and I/Q channel allocation method optimized for the case where an E-DPCCH and an E-DPDCH which are physical channels for transmission of EUDCH packet data are additionally transmitted on that assumption.

Second, the case where compatibility with the HS-DPCCH is partially lost while compatibility with the existing DPDCH and DPCCH is maintained will be taken into consideration. In the current Rel-5 WCDMA standard, if the maximum number of transmittable DPDCHs is one, the HS-DPCCH is transmitted on a Q channel using an OVSF code (256, 64). In this case, because an E-DPDCH cannot use an OVSF code (4, 1) on the Q channel, a maximum EUDCH data rate is limited accordingly. In order to solve the problem, the present invention proposes a code allocation rule for the HS-DPCCH, E-DPCCH and E-DPDCH so as to enable the E-DPDCH to use the OVSF code (4, 1) on the Q channel and reduce a PAPR of UE's transmission signal.

Third, in a Rel-6 standard, even a EUDCH stand-alone case in which no DPDCH is transmitted and only the E-DPDCH is transmitted in the uplink is

- 10 -

taken into consideration. Therefore, the present invention presents an OVSF code and I/Q channel allocation rule for the HS-DPCCH for the EUDCH stand-alone case.

5 In the foregoing methods, I/Q channel and OVSF code allocation for the HS-DPCCH depends on the maximum number of transmittable DPDCH channels, and the number of E-DPDCH channels does not affect the allocation rule for the HS-DPCCH. This is because the E-DPDCH is not always transmitted, but transmitted only when there is data in a EUDCH data buffer of a UE. Therefore,
10 in terms of a PAPR, it is preferable to define an OVSF code and I/Q channel allocation rule for the HS-DPCCH considering only the DPDCH according to the current standard.

15 FIG. 4 is a diagram illustrating a transmitter structure of a UE according to an embodiment of the present invention.

1. DPCCH

A DPCCH is allocated an OVSF code (256, 0) on a Q channel according to the existing Rel-99 and Rel-5 channel allocation rules. The (256, 0) is equal to
20 an OVSF code $C_{ch,256,0}$ illustrated in FIG. 3. That is, in FIG. 4, the DPCCH is multiplied by the OVSF code $C_{ch,256,0}$ for spreading after being BPSK-modulated, and then multiplied by a transmission gain β_c . The β_c is set by a network according to a rate or a required quality-of-service level of data transmitted by a UE.

25

The DPCCH signal is added to other channel signals transmitted through a Q channel, multiplied by a scrambling code $S_{dpch,n}$, and then transmitted via an antenna through a transmission pulse forming filter and an RF stage.

2. DPDCH

30 According to the channel allocation rule defined in the existing standard, if an SF value of a DPDCH is denoted by SF_{DPDCH} , the DPDCH is spread by an OVSF code $(SF_{DPDCH}, SF_{DPDCH}/4)$ on an I channel. In FIG. 4, c_d denotes an OVSF code for a DPDCH. In the present invention, it is assumed that when physical
35 channels related to the EUDCH service are transmitted together with the DPDCH,

- 11 -

only a maximum of one DPDCH channel is transmitted.

3. HS-DPCCH

Also, this follows the existing Rel-5 standard and is transmitted only
5 when HSDPA service is achieved in a downlink. As can be seen in FIG. 4, when only one DPDCH is transmitted in the uplink, an HS-DPCCH is spread by an OVSF code (256, 64) on a Q channel.

4. E-DPCCH

10 An E-DPCCH, a physical control channel for EUDCH service, transmits a buffer state of a UE, or transmits uplink transmission power, uplink transmission power margin, and channel state information (CSI), which are needed by a Node B to estimate an uplink channel condition. The E-DPCCH transmits a Transport Format and Resource Indicator (E-TFRI) for EUDCH
15 service transmitted over the E-DPDCH.

If an SF value of an E-DPCCH is denoted by $SF_{E-DPCCH}$, the E-DPCCH is spread by an OVSF code ($SF_{E-DPCCH}$, 1) on an I channel. Herein, OVSF codes and
20 I/Q channels are allocated to the E-DPCCH in a free way.

In an alternative method, the E-DPCCH uses an OVSF code ($SF_{E-DPCCH}$, 1) on a Q channel, unlike the DPCCH transmitted using an OVSF code (256, 1) on an I channel.

25 In another alternative method, the E-DPCCH is allocated to a Q channel when no DPDCH is set up and an HS-DPCCH is set up. In this case, an OVSF code ($SF_{E-DPCCH}$, 1) or ($SF_{E-DPCCH}$, $SF_{E-DPCCH}/8$) is suitable for the E-DPCCH.

In further another alternative method, when no DPDCH is set up, the E-
30 DPCCH can be allocated to the Q channel regardless of setup/non-setup of the HS-DPCCH. In this case, an OVSF code ($SF_{E-DPCCH}$, 1) or ($SF_{E-DPCCH}$, $SF_{E-DPCCH}/8$) is suitable for the E-DPCCH.

Such a rule is always available regardless of transmission/non-
35 transmission of the HS-DPCCH and the number of E-DPDCH channels. In this

- 12 -

case, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPCCH}$, and an $SF_{E-DPCCH}$ value to be actually used is determined considering the amount of information to be transmitted over the E-DPCCH.

5 In the case where no DPDCH is set up and an HS-DPCCH is set up for an I channel (256, 1), even if $SF_{E-DPCCH}=256$, the E-DPCCH cannot be allocated ($SF_{E-DPCCH}$, 1). Therefore, the E-DPCCH cannot be allocated for I channels ($SF_{E-DPCCH}$, 2) to ($SF_{E-DPCCH}$, $SF_{E-DPCCH}/8$). That is, allocating the E-DPCCH for the I channels ($SF_{E-DPCCH}$, 2) to ($SF_{E-DPCCH}$, $SF_{E-DPCCH}/8$) is most efficient in achieving a
10 low PAR value. Herein, 32, 64, 128 and 256 are available for the $SF_{E-DPCCH}$.

Referring to FIG. 4, a EUDCH transmission controller 402 transmits control information through the E-DPCCH, which is needed by a Node B to receive an E-DPDCH. In FIG. 4, $c_{ch,SF,I}$ denotes an OVVSF code for the E-DPCCH,
15 and is multiplied by a transmission symbol so that the corresponding channel should be orthogonal with other physical channels. In addition, a transmission gain $\beta_{E-DPCCH}$ of the E-DPCCH, like those of other physical channels, is set according to a rate or a required quality-of-service level of data transmitted by a UE.

20

5. E-DPDCH

An E-DPDCH, a dedicated physical data channel for the EUDCH service, transmits EUDCH packet data using a data rate determined based on scheduling information provided from the Node B. The E-DPDCH supports not only BPSK
25 but also QPSK and 8PSK in order to increase a data rate while maintaining the number of simultaneously transmitted spreading codes.

Referring back to FIG. 4, the E-DPDCH simultaneously transmits two channels of an E-DPDCH1 and an E-DPDCH2, by way of example. Herein, it is
30 obvious that the number of E-DPDCH physical channels in use depends on a transfer rate of EUDCH packet data. In addition, the EUDCH transmission controller 402 determines the number of simultaneously transmitted E-DPDCH channels and an SF value.

35 In other words, when a data rate is low, an E-DPDCH is spread with an

- 13 -

OVSF code having a relatively large SF value so that it can be transmitted with one E-DPDCH. However, when a data rate is high, an $SF_{E-DPDCH}$ value is set to 4 or 2 so that EUDCH packet data is transmitted through one or two E-DPDCH channels.

5

That is, a EUDCH packet transmitter 404 transmits EUDCH transmission data through an E-DPDCH1 under the control of the EUDCH transmission controller 402. Alternatively, even the E-DPDCH2 is allocated for the transmission when necessary. A EUDCH data buffer 400 is a buffer for storing EUDCH data to be transmitted. The EUDCH data to be transmitted through the E-DPDCH channels is delivered to the EUDCH packet transmitter 404 under the control of the EUDCH transmission controller 402.

10

A description will now be made of methods for allocating OVSF codes and I/Q channels for E-DPDCHs according to several embodiments of the present invention.

15

First Embodiment

20

A first embodiment proposes methods for allocating OVSF codes and I/Q channels for the E-DPDCHs without considering DPDCHs. The proposed methods can reduce a PAPR by appropriately adjusting the minimum spreading gain value for E-DPDCHs and the number of transmission channels according to a EUDCH data rate. Herein, for convenience of description, the methods will be divided into Method A, Method B and Method C considering an $SF_{E-DPDCH}$ set based on a data rate.

25

Method A corresponds to a case where an $SF_{E-DPDCH}$ for E-DPDCHs is set to 4 or larger.

30

1. One E-DPDCH Channel Transmitted

35

An E-DPDCH1 transmits EUDCH transmission symbols through a Q channel using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$). Herein, 4, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPDCH}$. In FIG. 4, c_{ed1} denotes an OVSF code used for the E-DPDCH1. The E-DPDCH1 allocated an OVSF code in this way satisfies orthogonality with other physical channels. That is, compared with a

- 14-

DPDCH transmitted on an I channel, the E-DPDCH1 can reduce its PAPR as it is transmitted on the Q channel.

2. Two E-DPDCH Channels Transmitted

5 When an $SF_{E-DPDCH}$ for an E-DPDCH1 and an E-DPDCH2 is 4, the E-DPDCH1 and the E-DPDCH2 are spread with an OVSF code (4, 2) and then simultaneously transmitted through a Q channel and an I channel, respectively. That is, the E-DPDCH1 is allocated to the Q channel, and the E-DPDCH2 is allocated to the I channel. Herein, the EUDCH packet data is transmitted with a modulation scheme having a 4th order or higher, such as QPSK, 8PSK and 16QAM.

15 For example, when QPSK modulation is used, symbols transmitted through the E-DPDCH1 and the E-DPDCH2 are transmitted in four possible combinations of $(\pm 1, \pm 1)$, and when 8PSK is used, symbols transmitted through the E-DPDCH1 and the E-DPDCH2 are transmitted in eight possible combinations of $(\pm \sqrt{2}, 0)$, $(0, \pm \sqrt{2})$ and $(\pm 1, \pm 1)$.

20 If a desired EUDCH data rate cannot be achieved even though the two channels of the E-DPDCH1 and the E-DPDCH 2 are simultaneously transmitted using the $SF_{E-DPDCH}=4$, it is possible to enable transmission at a higher data rate by setting the $SF_{E-DPDCH}$ to 2. That is, if an $SF_{E-DPDCH}$ for the E-DPDCH1 and the E-DPDCH2 is 2, the E-DPDCH1 and the E-DPDCH2 are spread with an OVSF code (2, 1) and then simultaneously transmitted on a Q channel and an I channel, respectively.

30 When it is necessary to transmit several E-DPDCH physical channels in this way, it is possible to remarkably reduce a PAPR by halving the number of E-DPDCH channels being transmitted, as compared with the case where the minimum spreading gain is 4.

35 Method B is similar to Method A described above, but allocates OVSF codes such that when only an E-DPDCH1 is transmitted, $SF_{E-DPDCH}$ is set to a minimum of 2.

- 15 -

1. One E-DPDCH Channel Transmitted

When only the E-DPDCH1 is transmitted, 2, 4, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPDCH}$. The E-DPDCH1 is allocated to a Q channel using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$)

5

2. Two E-DPDCH Channels Transmitted

The E-DPDCH1 and the E-DPDCH2 are spread with an OVSF code (2, 1) and then simultaneously transmitted on a Q channel and an I channel, respectively. In this case, EUDCH packet data is transmitted with a modulation scheme having a 4th order or higher, such as QPSK, 8PSK and 16QAM.

10

Method C is similar to Method A described above, but allocates OVSF codes such that $SF_{E-DPDCH}$ for the E-DPDCH1 is set to 2 and $SF_{E-DPDCH}$ for the E-DPDCH2 is set to 4, if a desired EUDCH data rate cannot be achieved even though the two channels of the E-DPDCH1 and the E-DPDCH 2 are simultaneously transmitted using the $SF_{E-DPDCH}=4$.

15

1. One E-DPDCH Channel Transmitted

When an $SF_{E-DPDCH}$ for E-DPDCHs is 4 or larger, EUDCH transmission symbols are transmitted through a Q channel using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$). Herein, 4, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPDCH}$.

20

2. Two E-DPDCH Channels Transmitted

When an $SF_{E-DPDCH}$ for the E-DPDCH1 and the E-DPDCH2 is 4, the E-DPDCH1 and the E-DPDCH2 are spread with an OVSF code (4, 2) and then simultaneously transmitted through a Q channel and an I channel, respectively. If a desired EUDCH data rate cannot be achieved even though the two channels of the E-DPDCH1 and the E-DPDCH 2 are simultaneously transmitted, an $SF_{E-DPDCH}$ for the E-DPDCH1 and an $SF_{E-DPDCH}$ for the E-DPDCH2 are set to different values.

25

30

That is, as an $SF_{E-DPDCH}$ for the E-DPDCH1 is set to 2 and an $SF_{E-DPDCH}$ for the E-DPDCH2 is set to 4, data carried on the respective channels independently undergoes BPSK modulation before being transmitted. Therefore, symbols transmitted on the E-DPDCH1 and the E-DPDCH2 are spread with

35

- 16-

OVSF codes (2, 1) and (4, 2) on a Q channel and an I channel, respectively, before being transmitted.

5 In addition, when a data rate cannot be achieved in the foregoing manner, the $SF_{E-DPDCH}$ for the E-DPDCH1 is set to 2 and the $SF_{E-DPDCH}$ for the E-DPDCH2 is set to 2 for transmission. That is, the E-DPDCH2 and the E-DPDCH1 are spread with an OVSF code (2, 1) and then simultaneously transmitted on the I channel and the Q channel, respectively. In this case, the EUDCH packet data can be transmitted with a modulation scheme having a 4th order or higher, such as
10 QPSK, 8PSK and 16QAM.

Method D is a method for allocating an OVSF code (4, 1) to an additional E-DPDCH to increase a EUDCH packet data rate when a DPDCH and an HS-DPCCH are not transmitted or when an OVSF code generated from an OVSF
15 code (4, 0) is used even though the HS-DPCCH is transmitted. This is because the HS-DPCCH is transmitted only for the HSDPA service. In addition, this is because when there is no data to be transmitted over a DPDCH, the DPDCH is occasionally used only for transmission of signaling information and may not be transmitted for the other time. In the post-Rel-5 WCDMA standard, there is a
20 possible case where the DPDCH is not set up and only the E-DPDCH is set up.

1. Two or Less E-DPDCH Channels Transmitted

The foregoing Method A, Method B, or Method C can be used.

25 2. Three E-DPDCH Channels Transmitted

When an HS-DPCCH is not transmitted, an E-DPDCH3 channel is transmitted through a Q channel using an OVSF code (4, 1).

Alternatively, when the HS-DPCCH is transmitted and the DPDCH is not
30 transmitted, the E-DPDCH3 channel is transmitted through an I channel using the OVSF code (4, 1).

3. Four or More E-DPDCH Channels Transmitted

The I channel and the Q channel both use the OVSF code (4, 1) for
35 transmission. This is applied when the OVSF code (4, 1) is not used by the

- 17 -

DPDCH and the HS-DPCCH.

In other words, when both of the HS-DPCCH and the DPDCH are not transmitted, third and fourth E-DPDCH channels are transmitted through the I channel and the Q channel using the OVSF code (4, 1), respectively. Even when the DPDCH is not set up and the HS-DPCCH is transmitted using an OVSF code generated from the OVSF code (4, 0), the OVSF code (4, 1) is never used in the I and Q channels. Therefore, it is possible to transmit the third and fourth E-DPDCH channels on the I/Q channels using the OVSF code (4, 1).

Second Embodiment

A second embodiment proposes methods for applying an OVSF code and I/Q channel allocation rule for the E-DPDCH in a different way considering setup/non-setup of an HS-DPCCH.

The second embodiment provides a method for first allocating an E-DPDCH to an I channel when the HS-DPCCH is set for an OVSF code (256, 64) in a Q channel, thereby reducing a PAPR. The second embodiment is advantageous in that it can remarkably reduce a PAPR when an HS-DPCCH has higher power than that of a DPDCH as a UE is located in the vicinity of a cell boundary.

When the HS-DPCCH is not set up, OVSF codes are allocated in the following method.

1. One E-DPDCH Transmitted

An E-DPDCH transmits EUDCH transmission symbols on a Q channel using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/4$). Herein, 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$.

If a EUDCH data rate cannot be fully achieved even though the $SF_{E-DPDCH}=4$ is used, the E-DPDCH uses on the Q channel an OVSF code (2, 1) with $SF_{E-DPDCH}=2$ instead of its OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/4$).

2. Two E-DPDCHs Transmitted

- 18 -

When an $SF_{E-DPDCH}$ for E-DPDCHs is set to 2, an E-DPDCH1 is transmitted on a Q channel using an OVSF code (2, 1), and an E-DPDCH2 is transmitted on an I channel using an OVSF code (2, 1).

Alternatively, the E-DPDCH1 is transmitted on the Q channel using an OVSF code (2, 1), and the E-DPDCH2 is transmitted on the I channel using an OVSF code (4, 2). In this case, if a desired EUDCH data rate cannot be achieved, an $SF_{E-DPDCH}$ for the E-DPDCH2 is set to 2 and an OVSF code (2, 1) is used instead of the OVSF code (4, 2) for transmission of the E-DPDCH2.

3. Three E-DPDCHs Transmitted

When an E-DPDCH1 is transmitted on a Q channel using an OVSF code (2, 1) and an E-DPDCH2 is transmitted on an I channel using an OVSF code (2, 1), an E-DPDCH3 is transmitted on the Q channel using an OVSF code (4, 1).

4. Fourth E-DPDCHs Transmitted

An E-DPDCH4 is transmitted on an I channel using an OVSF code (4, 1).

Herein, the case where an OVSF code (4, 1) can be used on both the I channel and the Q channel corresponds to the case where the OVSF code (4, 1) is unused by a DPDCH and an HS-DPCCH. That is, in the case where no DPDCH is set up, or in the case where a DPDCH is equal to an E-DPDCH in radio frame length even though the DPDCH is set up, an E-DPDCH4 is transmitted on an I channel using an OVSF code (4, 1) in addition to the E-DPDCH1, E-DPDCH2, and E-DPDCH3 in a transmission time interval (TTI) for which the DPDCH is not transmitted.

However, when an HS-DPCCH is set for (Q, 256, 64), an OVSF code allocation method is as follows.

1. One E-DPDCH Transmitted

An E-DPDCH1 transmits EUDCH transmission symbols on an I channel using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$). Herein, 2, 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$.

- 19 -

2. Two E-DPDCHs Transmitted

An E-DPDCH1 is transmitted on an I channel using an OVSF code (2, 1), and an E-DPDCH2 is also transmitted on a Q channel using an OVSF code (2, 1).

5 Third Embodiment

A third embodiment uses the same OVSF code allocation method as that of the second embodiment when an HS-DPCCH is not set up. However, the third embodiment is characterized in that it first allocates an E-DPDCH to a Q channel instead of an I channel on which the HS-DPCCH is set for (Q, 256, 64).

10

When the HS-DPCCH is not set up, the third embodiment uses the same OVSF code allocation method as that of the second embodiment.

15

However, when the HS-DPCCH is set for (Q, 256, 64), the following OVSF code allocation method is used.

1. One E-DPDCH Transmitted

An E-DPDCH1 uses ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$) on a Q channel, and 2, 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$.

20

2. Two E-DPDCHs Transmitted

When an $SF_{E-DPDCH}$ for E-DPDCHs is set to 2, an E-DPDCH1 is transmitted on a Q channel using an OVSF code (2, 1), and an E-DPDCH2 is transmitted on an I channel using an OVSF code (2, 1).

25

Alternatively, the E-DPDCH1 is transmitted on the Q channel using an OVSF code (2, 1), and the E-DPDCH2 is transmitted on the I channel using an OVSF code (4, 2). In this case, if a desired EUDCH data rate cannot be achieved, an $SF_{E-DPDCH}$ for the E-DPDCH2 is set to 2 and an OVSF code (2, 1) is used instead of the OVSF code (4, 2) for transmission of the E-DPDCH2.

30

3. Three E-DPDCHs Transmitted

In the case where no DPDCH is set up, or in the case where a DPDCH is equal to an E-DPDCH in radio frame length even though the DPDCH is set up, an E-DPDCH3 is transmitted on a Q channel using an OVSF code (4, 1) in addition

35

- 20 -

to the E-DPDCH1 and E-DPDCH2 transmitted on I and Q channels using an OVSF code (2, 1), in a TTI for which the DPDCH is not transmitted on the I channel.

5 Fourth Embodiment

 A fourth embodiment proposes a method for reducing a PAPR and efficiently using OVSF codes for the case where no DPDCH is set up or the case where an E-DPDCH is equal to a DPDCH, even if it is set up, in radio frame length, in the case where an HS-DPCCH is set for an OVSF code (256, 64) on a
10 Q channel. An I/Q channel and OVSF code allocation method used for E-DPDCHs varies according to presence/absence of DPDCHs transmitted in the current TTI.

1. One E-DPDCH Transmitted

15 When DPDCHs are transmitted in the current TTI, an E-DPDCH1 uses ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$) on a Q channel, and 2, 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$.

 However, when no DPDCH is transmitted in the current TTI, an OVSF
20 code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/4$) is used on an I channel, and 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$. In this case, in order to further increase a EUDCH data rate, the E-DPDCH is transmitted using an OVSF code (2, 1) instead of the OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/4$).

25 2. Two E-DPDCHs Transmitted

 When an $SF_{E-DPDCH}$ for E-DPDCHs is set to 2, an E-DPDCH1 is transmitted on a Q channel using an OVSF code (2, 1), and an E-DPDCH2 is transmitted on an I channel using an OVSF code (2, 1).

30 Alternatively, the E-DPDCH1 is transmitted on the Q channel using an OVSF code (2, 1), and the E-DPDCH2 is transmitted on the I channel using an OVSF code (4, 2). In this case, if a desired EUDCH data rate cannot be achieved, an $SF_{E-DPDCH}$ for the E-DPDCH2 is set to 2 and an OVSF code (2, 1) is used instead of the OVSF code (4, 2) for transmission of the E-DPDCH2.

35

- 21 -

3. Three E-DPDCHs Transmitted

In addition to the E-DPDCH1 and the E-DPDCH2 transmitted on the Q and I channels using the OVSF code (2, 1), an E-DPDCH is transmitted on the I channel using an OVSF code (4, 1) when no DPDCH is transmitted in the current
5 TTI.

Fifth Embodiment

A fifth embodiment proposes a method for allocating E-DPDCHs when no DPDCH is set up. For the E-DPDCHs, the fifth embodiment has a basic
10 concept of allocating an E-DPDCH1 to opposite I/Q channels of the I/Q channels on which an HS-DPDCH is transmitted, and can reduce a PAPR when a channel gain factor for the HS-DPCCH is high.

When the HS-DPCCH is not set up, an E-DPDCH allocation method is as
15 follows.

1. One E-DPDCH Transmitted

An E-DPDCH1 transmits EUDCH transmission symbols on an I channel using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/4$). Herein, 4, 8, 16, 32, 64, 128, 256
20 and 512 are available for the $SF_{E-DPDCH}$. In this case, if a EUDCH data rate cannot be fully achieved even though the $SF_{E-DPDCH}$ is set to 4, the $SF_{E-DPDCH}$ is set to 2 and the EUDCH transmission symbols are transmitted on the I channel using an OVSF code (2, 1) instead of the OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/4$).

2. Two E-DPDCHs Transmitted

An E-DPDCH1 is transmitted on an I channel using an OVSF code (2, 1),
25 and an E-DPDCH2 is transmitted on a Q channel using an OVSF code (2, 1).

3. Three or More E-DPDCHs Transmitted

In addition to the E-DPDCH1 and the E-DPDCH2, an E-DPDCH3 and an E-DPDCH4 transmit EUDCH transmission symbols on I and Q channels using an
30 OVSF code (4, 1).

However, when the DPDCH is not set up and an HS-DPCCH is set up,
35 the HS-DPCCH is likely allocated for the I channel.

- 22 -

1. One E-DPDCH Transmitted

An E-DPDCH transmits EUDCH transmission symbols on a Q channel using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/4$). Herein, 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$. If a EUDCH data rate cannot be fully achieved even though the $SF_{E-DPDCH}=4$ is used, the SF is set to 2 and the Q channel uses an OVSF code (2, 1).

2. Two E-DPDCHs Transmitted

An E-DPDCH1 is transmitted on a Q channel using an OVSF code (2, 1), and an E-DPDCH2 is transmitted on an I channel using an OVSF code (2, 1).

3. Three or More E-DPDCHs Transmitted

In addition to the E-DPDCH1 and the E-DPDCH2 transmitted on the Q and I channels using an OVSF code (2, 1), an E-DPDCH3 and an E-DPDCH4 additionally transmit EUDCH transmission symbols on both the I and Q channels using an OVSF code (4, 1).

Referring back to FIG. 4, the EUDCH transmission controller 402 transmits UE's data buffer state and CSI, required for Node B's scheduling control, to the Node B through the E-DPCCH. The EUDCH transmission controller 402 determines an E-TFRI and transmits the determined E-TFRI to the Node B through the E-DPCCH. The E-TFRI is determined using a possible maximum data rate.

The EUDCH packet transmitter 404 receives packet data determined based on the E-TFRI from the EUDCH data buffer 400. The received packet data undergoes channel coding and modulation using the E-TFRI, and then transmitted to the Node B through the E-DPDCH1 and E-DPDCH2 channels according to an embodiment of the present invention.

Data on the DPDCH is spread at a chip rate using an OVSF code c_d in a multiplier 422, and multiplied by a channel gain β_d in a multiplier 424. The DPDCH data multiplied by the channel gain β_d is input to a summer 426.

Control information on an E-DPCCH is spread in a multiplier 406 at a

- 23 -

chip rate using an OVSF code $c_{ch,SF,1}$, i.e., $(SF_{E-DPCCH}, 1)$, to maintain orthogonality with other physical channels. Thereafter, the output of the multiplier 406 is multiplied by a channel gain β_{ec} in a multiplier 408. The E-DPCCH control information multiplied by the channel gain β_{sc} is input to the summer 426.

Packet data provided from the EUDCH packet transmitter 404 is converted into a complex symbol stream $I+jQ$, and then delivered to a multiplier 446 and a multiplier 416 as I and Q channel components, respectively. The multiplier 446 spreads the packet data into an I channel component of a modulation symbol with an OVSF code C_{ed2} at a chip rate. The output of the multiplier 446 is multiplied by a channel gain β_{ed2} in a multiplier 448. The summer 426 forms an I channel by summing up the DPDCH data, the E-DPCCH control information, and the E-DPDCH2 data.

Control information on the DPCCH is spread in a multiplier 428 at a chip rate using an OVSF code $(256, 0)$, i.e., $c_{ch,256,0}$, and then multiplied by a channel gain β_c in a multiplier 430. The DPCCH control information multiplied by the channel gain β_c is input to a summer 436.

Control information on the HS-DPCCH is spread in a multiplier 432 using an OVSF code $(256, 64)$, i.e., $c_{ch,256,64}$, at a chip rate, and then multiplied by a channel gain β_{hs} in a multiplier 434.

A Q channel component of a EUDCH packet data modulation symbol provided from the EUDCH packet transmitter 404 is spread in a multiplier 416 with an OVSF code C_{ed1} at a chip rate. The output of the multiplier 416 is multiplied by a channel gain β_{ed1} in a multiplier 418. The summer 436 forms a Q channel by summing up the DPCCH control information, the HS-DPCCH control information, and the E-DPDCH1 data. The output of the summer 436 is multiplied by an imaginary number in a multiplier 438, and then delivered to a summer 440.

The summer 440 forms one complex symbol stream by summing up the output of the summer 426 and the output of the multiplier 438, and delivers the

- 24 -

complex symbol stream to a multiplier 450. The multiplier 450 scrambles the complex symbol stream using a scrambling code $S_{dpch,1}$. The scrambled complex symbol stream is converted into a pulse signal by a pulse shaping filter 452, and then delivered to the Node B via an antenna 456 through an RF module 454.

5

FIG. 5 is a diagram illustrating a comparison between physical channels in terms of a PAPR reduction effect by FIG. 4.

In FIG. 5, reference numeral 40 represents the case where a method proposed by the present invention is used, and reference numerals 41 and 42 represent the cases where different OVSF codes or different I/Q channels are allocated for an E-DPCCH. Herein, the PAPR result has been obtained through simulation using the transmission pulse shaping filter 452 and the scrambling code, specified in the Rel-5 WCDMA standard, and the channel gain β is generally set under discussion of the EUDCH technique.

15

Referring to FIG. 5, the case 40 proposed by the present invention is superior to the case 41 in terms of a PAPR reduction effect by about 0.7 dB. In addition, the case 40 proposed by the present invention is superior to the case 42 in terms of a PAPR reduction effect by about 0.12 dB. That is, the proposed OVSF code and I/Q channel allocation method for the E-DPCCH and the E-DPDCH can achieve a relatively low PAPR.

20

A description will now be made of an OVSF code and I/Q channel allocation method for an E-DPCCH and an E-DPDCH considering transmission/non-transmission of an HS-DPCCH when compatibility with the existing Rel-5 standard is maintained and at least one DPDCH is transmitted, according to sixth to ninth embodiments.

25

30

Sixth Embodiment

1. One or More DPDCHs being Transmittable and HS-DPCCH being not Transmitted

A method of allocating I/Q channels and OVSF codes for a DPCCH and a DPDCH according to the current standard are illustrated in Table 1.

35

- 25 -

Table 1

Channel	Allocation
DPCCH	(Q, 256, 0)
DPDCH	(I, SF, SF/4)

That is, a DPCCH channel is transmitted on a Q channel using an OVSF code (256, 0), and a DPDCH can be allocated to an I channel with an OVSF code (SF_{DPDCH}, SF_{DPDCH}/4). Here, 4, 8, 16, 32, 64, 128, 256 and 512 are available for the SF_{DPDCH}.

A method of allocating I/Q channels and OVSF codes for an E-DPCCH and E-DPDCHs in the present invention considering compatibility with the current standard of Table 1 is illustrated in Table 2.

Table 2

Channel	Allocation
E-DPCCH	(I, SF _{E-DPCCH} , 1)
E-DPDCH1, E-DPDCH2, E-DPDCH3, E-DPDCH4, E-DPDCH5	(Q, SF, SF/4), (I, 4, 3) (Q, 4, 3), (I, 4, 2) (Q, 4, 2)

Here, 8, 16, 32, 64, 128 and 256 are available for the SF_{E-DPCCH} for the E-DPCCH, and 4, 8, 16, 32, 64, 128, 256 and 512 are available for the SF_{E-DPDCH} for the E-DPDCHs.

As illustrated in Table 2, if a maximum of 5 E-DPDCH channels can be transmitted and SF=4 is applied to an E-DPDCH1, the E-DPDCH1 is transmitted on a Q channel using an OVSF code (4, 1), and an E-DPDCH2 is transmitted on an I channel with an OVSF code (4, 3). In addition, an E-DPDCH3 is transmitted on a Q channel using an OVSF code (4, 3), and an E-DPDCH4 is transmitted on the I channel using an OVSF code (4, 2). Finally, an E-DPDCH5 is transmitted on the Q channel using an OVSF code (4, 2).

2. One or More DPDCHs being Transmittable and HS-DPCCH being

Transmitted

A method of allocating I/Q channels and OVSF codes for a DPCCH, a DPDCH, and an HS-DPCCH according to the current standard are illustrated in Table 3.

5

Table 3

Channel	Allocation
DPCCH	(Q, 256, 0)
DPDCH	(I, SF, SF/4)
HS-DPCCH	(Q, 256, 64)

A method of allocating I/Q channels and OVSF codes for an E-DPCCH and E-DPDCHs in the present invention considering compatibility with the current standard of Table 3 is illustrated in Table 4.

10

Table 4

Channel	Allocation
E-DPCCH	(I, $SF_{E-DPCCH}$, 1)
E-DPDCH1, E-DPDCH2, E-DPDCH3, E-DPDCH4	(Q, SF, $SF/4+SF/2$), (I, 4, 3) (Q, 4, 2), (I, 4, 2)

Here, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPCCH}$ for the E-DPCCH, and 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$ for the E-DPDCHs.

15

In this case, if a maximum of 4 E-DPDCH channels can be transmitted and $SF_{E-DPDCH}=4$ is used, an E-DPDCH1 and an E-DPDCH2 are allocated (Q, 4, 3) and (I, 4, 3), respectively. An E-DPDCH3 is transmitted on a Q channel using an OVSF code (4, 2), and an E-DPDCH4 is transmitted on an I channel using an OVSF code (4, 2).

20

3. A Maximum of 2 DPDCHs being Transmittable and HS-DPCCH being not Transmitted

25

A method of allocating I/Q channels and OVSF codes for a DPCCH and

- 27 -

DPDCHs according to the current standard is illustrated in Table 5.

Table 5

Channel	Allocation
DPCCH	(Q, 256, 0)
DPDCH1, DPDCH2	(I, SF, SF/4), (Q, 4, 1)

- 5 A method of allocating I/Q channels and OVSF codes for an E-DPCCH and E-DPDCHs in the present invention considering compatibility with the current standard of Table 5 is illustrated in Table 6.

Table 6

Channel	Allocation
E-DPCCH	(I, $SF_{E-DPCCH}$, 1)
E-DPDCH1, E-DPDCH2, E-DPDCH3, E-DPDCH4	(Q, SF, $SF/4+SF/2$), (I, 4, 3) (Q, 4, 2), (I, 4, 2)

10

Here, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPCCH}$ for the E-DPCCH, and 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$ for the E-DPDCHs.

- 15 In this case, if a maximum of 4 E-DPDCH channels can be transmitted and $SF_{E-DPDCH}=4$ is used, an E-DPDCH1 and an E-DPDCH2 are transmitted using (Q, 4, 3) and (I, 4, 3), respectively. An E-DPDCH3 is transmitted on a Q channel using an OVSF code (4, 2), and an E-DPDCH4 is transmitted on an I channel using an OVSF code (4, 2).

20

4. A Maximum of 2 DPDCHs being Transmittable and HS-DPCCH being Transmitted

- 25 A method of allocating I/Q channels and OVSF codes for a DPCCH, a DPDCH and an HS-DPCCH according to the current standard is illustrated in Table 7.

Table 7

- 28 -

Channel	Allocation
DPCCH	(Q, 256, 0)
DPDCH	(I, SF, SF/4)
HS-DPCCH	(Q, 256, 64)

A method of allocating I/Q channels and OVSF codes for an E-DPCCH and E-DPDCHs in the present invention considering compatibility with the current standard of Table 7 is illustrated in Table 8.

5

Table 8

Channel	Allocation
E-DPCCH	(Q, $SF_{E-DPCCH}$, $SF_{E-DPCCH}/8$)
E-DPDCH1, E-DPDCH2, E-DPDCH3, E-DPDCH4	(I, SF, $SF/4+SF/2$), (Q, 4, 8) (I, 4, 2), (Q, 4, 2)

Here, 64, 128 and 256 are available for the $SF_{E-DPCCH}$ for the E-DPCCH, and 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$ for the E-DPDCHs.

10

In this case, if a maximum of 4 E-DPDCH channels can be transmitted and $SF=4$ is used, an E-DPDCH1 and an E-DPDCH2 are allocated (I, 4, 3) and (Q, 4, 3), respectively. An E-DPDCH3 is transmitted on an I channel using an OVSF code (4, 2), and an E-DPDCH4 is transmitted on a Q channel using an OVSF code (4, 2).

15

5. A Maximum of 3 DPDCHs being Transmittable and HS-DPCCH being not Transmitted

20

A method of allocating I/Q channels and OVSF codes for a DPCCH and DPDCHs according to the current standard is illustrated in Table 9.

Table 9

Channel	Allocation
DPCCH	(Q, 256, 0)
DPDCH1, DPDCH2,	(I, SF, SF/4), (Q, 4, 1)

- 29 -

DPDCH3	(I, 4, 3)
--------	-----------

A method of allocating I/Q channels and OVSF codes for an E-DPCCH and E-DPDCHs in the present invention considering compatibility with the current standard of Table 9 is illustrated in Table 10.

5

Table 10

Channel	Allocation
E-DPCCH	(I, $SF_{E-DPCCH}$, 1)
E-DPDCH1, E-DPDCH2, E-DPDCH3	(Q, SF, $SF/4+SF/2$), (I, 4, 2) (Q, 4, 2)

Here, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPCCH}$ for the E-DPCCH, and 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$ for the E-DPDCHs.

10

In this case, if a maximum of 3 E-DPDCH channels can be transmitted and $SF=4$ is used, an E-DPDCH1 is transmitted on a Q channel using an OVSF code (4, 3). An E-DPDCH2 is transmitted on an I channel using an OVSF code (4, 2), and an E-DPDCH3 is transmitted on the Q channel using an OVSF code (4, 2).

15

6. A Maximum of 3 DPDCHs being Transmittable and HS-DPCCH being Transmitted

A method of allocating I/Q channels and OVSF codes for a DPCCH, DPDCHs and an HS-DPCCH according to the current standard is illustrated in Table 11.

20

Table 11

Channel	Allocation
DPCCH	(Q, 256, 0)
DPDCH1, DPDCH2, DPDCH3	(I, SF, $SF/4$), (Q, 4, 1) (I, 4, 3)
HS-DPCCH	(Q, 256, 32)

- 30 -

A method of allocating I/Q channels and OVSF codes for an E-DPCCH and E-DPDCHs in the present invention considering compatibility with the current standard of Table 11 is illustrated in Table 12.

5

Table 12

Channel	Allocation
E-DPCCH	(I, $SF_{E-DPCCH}$, 1)
E-DPDCH1, E-DPDCH2, E-DPDCH3	(Q, SF, $SF/4+SF/2$), (I, 4, 2) (Q, 4, 2)

Here, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPCCH}$ for the E-DPCCH, and 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$ for the E-DPDCHs.

10

In this case, if a maximum of 3 E-DPDCH channels can be transmitted and $SF=4$ is used, an E-DPDCH1 is transmitted on a Q channel using an OVSF code (4, 3). An E-DPDCH2 is transmitted on an I channel using an OVSF code (4, 2), and an E-DPDCH3 is transmitted on the Q channel using an OVSF code (4, 2).

15

7. A Maximum of 4 DPDCHs being Transmittable and HS-DPCCH being not Transmitted

A method of allocating I/Q channels and OVSF codes for a DPCCH and DPDCHs according to the current standard is illustrated in Table 13.

20

Table 13

Channel	Allocation
DPCCH	(Q, 256, 0)
DPDCH1, DPDCH2, DPDCH3, DPDCH4	(I, SF, $SF/4$), (Q, 4, 1) (I, 4, 3), (Q, 4, 3)

A method of allocating I/Q channels and OVSF codes for an E-DPCCH and E-DPDCHs in the present invention considering compatibility with the current standard of Table 13 is illustrated in Table 14.

25

]

- 31 -

Table 14

Channel	Allocation
E-DPCCH	(I, $SF_{E-DPCCH}$, 1)
E-DPDCH1, E-DPDCH2	(I, SF, SF/2), (Q, 4, 2)

Here, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPCCH}$ for the E-DPCCH, and 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$ for the E-DPDCHs.

In this case, if a maximum of 2 E-DPDCH channels can be transmitted and $SF=4$ is used, an E-DPDCH1 is transmitted on an I channel using an OVSF code (4, 2) and an E-DPDCH2 is transmitted on a Q channel using an OVSF code (4, 2).

8. A Maximum of 4 DPDCHs being Transmittable and HS-DPCCH being Transmitted

A method of allocating I/Q channels and OVSF codes for a DPCCH and DPDCHs according to the current standard is illustrated in Table 15.

Table 15

Channel	Allocation
DPCCH	(Q, 256, 0)
DPDCH1, DPDCH2, DPDCH3, DPDCH4	(I, SF, SF/4), (Q, 4, 1) (I, 4, 3), (Q, 4, 3)
HS-DPCCH	(I, 256, 1)

A method of allocating I/Q channels and OVSF codes for an E-DPCCH and E-DPDCHs in the present invention considering compatibility with the current standard of Table 15 is illustrated in Table 16.

Table 16

Channel	Allocation
E-DPCCH	(Q, $SF_{E-DPCCH}$, $SF_{E-DPCCH}/8$)
E-DPDCH1, E-DPDCH2	(I, SF, SF/2), (Q, 4, 2)

- 32 -

Here, 64, 128 and 256 are available for the $SF_{E-DPCCH}$ for the E-DPCCH, and 4, 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$ for the E-DPDCHs.

5 In this case, if a maximum of 2 E-DPDCH channels can be transmitted and $SF=4$ is used, an E-DPDCH1 is transmitted on an I channel using an OVSF code (4, 2) and an E-DPDCH2 is transmitted on a Q channel using an OVSF code (4, 2).

10 9. A Maximum of 5 DPDCHs being Transmittable and HS-DPCCH being not Transmitted

A method of allocating I/Q channels and OVSF codes for a DPCCH and DPDCHs according to the current standard is illustrated in Table 17.

15 Table 17

Channel	Allocation
DPCCH	(Q, 256, 0)
DPDCH1, DPDCH2, DPDCH3, DPDCH4, DPDCH5	(I, SF, SF/4), (Q, 4, 1) (I, 4, 3), (Q, 4, 3) (I, 4, 2)

A method of allocating I/Q channels and OVSF codes for an E-DPCCH and E-DPDCHs in the present invention considering compatibility with the current standard of Table 17 is illustrated in Table 18.

20

Table 18

Channel	Allocation
E-DPCCH	(I, $SF_{E-DPCCH}$, 1)
E-DPDCH1	(Q, SF, SF/2)

25 Here, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPCCH}$ for the E-DPCCH, and 8, 16, 32, 64, 128, 256 and 512 are available for the $SF_{E-DPDCH}$ for the E-DPDCHs. A maximum of only one E-DPDCH can be transmitted. An E-DPDCH1 is transmitted on a Q channel using an OVSF code (4, 2).

- 33 -

10. A Maximum of 5 DPDCHs being Transmittable and HS-DPCCH being Transmitted

A method of allocating I/Q channels and OVSF codes for a DPCCH and DPDCHs according to the current standard is illustrated in Table 19.

5

Table 19

Channel	Allocation
DPCCH	(Q, 256, 0)
DPDCH1, DPDCH2, DPDCH3, DPDCH4, DPDCH5	(I, SF, SF/4), (Q, 4, 1) (I, 4, 3), (Q, 4, 3) (I, 4, 2)
HS-DPCCH	(Q, 256, 32)

A method of allocating I/Q channels and OVSF codes for an E-DPCCH and E-DPDCHs in the present invention considering compatibility with the current standard of Table 19 is illustrated in Table 20.

10

Table 20

Channel	Allocation
E-DPCCH	(I, $SF_{E-DPCCH}$, 1)
E-DPDCH1, E-DPDCH2	(Q, SF, SF/2)

Here, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPCCH}$ for the E-DPCCH, and a maximum of only one E-DPDCH can be transmitted. An E-DPDCH1 is transmitted on a Q channel using an OVSF code (4, 2).

15

Seventh Embodiment

Compared with the sixth embodiment, a seventh embodiment presents an allocation rule which is similar in packet back-off required in an RF power amplifier but simpler in implementation. A method of allocating I/Q channels and OVSF codes for an E-DPCCH and E-DPDCHs is determined based on the maximum number of transmittable DPDCHs and transmission/non-transmission of an HS-DPCCH, and a basic rule thereof is as follows:

20

E-DPCCH: If the maximum number of transmittable DPDCHs is 2 or 4

25

- 34 -

and an HS-DPCCH is allocated (I, 256, 1), it uses (Q, $SF_{E-DPCCH}$, $SF_{E-DPCCH}/8$) and in other cases, it uses (I, $SF_{E-DPCCH}$, 1).

5 E-DPDCH: When several DPDCH channels are transmitted, the DPDCHs use OVSF codes in order of (I, 4, 1), (Q, 4, 1), (I, 4, 3), (Q, 4, 3), (I, 4, 2) and (Q, 4, 2) according to a data rate. Therefore, the E-DPDCHs additionally use the remaining codes except the codes set for DPDCH transmission among the six codes in the arranged order according to a EUDCH packet data rate.

10 In a stand-alone case where only EUDCH is transmitted, HSDPA uses an OVSF code (256, 1) on an I channel, and in a case where a DPDCH is set up, HSDPA follows the Rel-5 standard.

It is most preferable to allocate I/Q channels and OVSF codes for the E-DPCCH and E-DPDCHs in the foregoing manner in terms of a PAPR.

15

1. HS-DPCCH being not Set Up and EUDCH Stand-Alone

An E-DPCCH always uses (I, $SF_{E-DPCCH}$, 1). Here, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPCCH}$.

20 As illustrated in Table 21, the E-DPDCHs are allocated I/Q channels and OVSF codes according to the maximum number of transmittable DPDCHs.

Table 21

Max No of Transmittable DPDCHs	Max No of Transmittable E-DPDCHs	E-DPDCH Allocation Order
0	6	(I, SF , $SF/4$), (Q, 4, 1), (I, 4, 3), (Q, 4, 3), (I, 4, 2), (Q, 4, 2)
1	5	(Q, SF , $SF/4$), (I, 4, 3), (Q, 4, 3), (I, 4, 2), (Q, 4, 2)
2	4	(I, SF , $SF/2+SF/4$), (Q, 4, 3), (I, 4, 2), (Q, 4, 2)
3	3	(Q, SF , $SF/2+SF/4$), (I, 4, 2), (Q, 4, 2)
4	2	(I, SF , $SF/2$), (Q, 4, 2)

- 35 -

5	1	(Q, SF, SF/2)
---	---	---------------

In Table 21, 4, 8, 16, 32, 64, 128, 256 and 512 are available for the SF. In Table 21, if the maximum number of transmittable DPDCHs is 0, E-DPDCHs transmitting EUDCH data can use a maximum of 6 codes.

5

For example, when all of the six channels are used according to the EUDCH data rate, an E-DPDCH1 is transmitted on an I channel using an OVSF code (4, 1), and an E-DPDCH2 is transmitted on a Q channel using an OVSF code (4, 1). An E-DPDCH3 is transmitted on the I channel using an OVSF code (4, 3), and an E-DPDCH4 is transmitted on the Q channel using an OVSF code (4, 3). An E-DPDCH5 is transmitted on the I channel using an OVSF code (4, 2), and an E-DPDCH6 is transmitted on the Q channel using an OVSF code (4, 2).

10

As another example, if the maximum number of transmittable DPDCHs is 4 in Table 21, E-DPDCHs for transmitting EUDCH data can use a maximum of 2 codes. For the E-DPDCHs, an E-DPDCH1 is transmitted on an I channel using an OVSF code (SF, SF/2), and an additionally allocated E-DPDCH2 is transmitted on a Q channel using an OVSF code (4, 2).

15

20 2. A Maximum of 1 DPDCH being Transmittable and HS-DPCCH being Allocated (Q, 256, 64)

An E-DPCCH always uses (I, $SF_{E-DPCCH}$, 1). Here, 8, 16, 32, 64, 128 and 256 are available for the $SF_{E-DPCCH}$.

25

The E-DPDCHs are sequentially allocated four OVSF codes (I, SF, $SF/2+SF/4$), (Q, 4, 3), (I, 4, 2) and (Q, 4, 2) according to a EUDCH data rate. Here, 4, 8, 16, 32, 64, 128, 256 and 512 are available for the SF. Because the HS-DPCCH is allocated (Q, 256, 64) on the Q channel, the OVSF code (4, 1) can be hardly used for an E-DPDCH.

30

3. A Maximum of 2 DPDCHs being Transmittable and HS-DPCCH being Set Up

As illustrated in Table 22, an E-DPCCH is allocated I/Q channels and OVSF codes according to the maximum number of transmittable DPDCHs.

- 36 -

Table 22

Max No of Transmittable DPDCHs	E-DPCCH Allocation
1, 3, 5	(I, $SF_{E-DPCCH}$, 1)
2, 4	(Q, $SF_{E-DPCCH}$, $SF_{E-DPCCH}/8$)

In this case, if the maximum number of transmittable DPDCHs is 2 or 4 and an HS-DPCCH is allocated (I, 256, 1), an E-DPCCH uses (Q, $SF_{E-DPCCH}$, $SF_{E-DPCCH}/8$). Here, 64, 128 and 256 are available for the $SF_{E-DPCCH}$.

However, the E-DPDCHs are allocated I/Q channels and OVSF codes as illustrated in Table 21 according to the maximum number of transmittable DPDCHs.

Eighth Embodiment

An eighth embodiment has a basic principle of first allocating an E-DPDCH to a Q channel for an OVSF code having the same index, and additionally allocating an E-DPDCH to an I channel. In this case, codes for the E-DPDCHs are determined according to the maximum number of transmittable DPDCHs and transmission/non-transmission of an HS-DPCCH.

That is, according to the eighth embodiment, DPDCHs are first allocated to an I channel and E-DPDCHs are first allocated to a Q channel, so that the numbers of DPDCHs and E-DPDCHs transmitted on the I/Q channels can be equal to each other. In other words, when an HS-DPCCH is transmitted on the Q channel using an OVSF code (256, 64) or the number of the DPDCHs is smaller than the maximum number of transmittable DPDCHs, the eighth embodiment can prevent an excessive increase in PAPR due to the preponderance of DPDCHs and E-DPDCHs over the I channel.

However, when the foregoing OVSF code and I/Q channel allocation rule for E-DPDCHs is used, compared with a DPCCH using an OVSF code (256, 0) on a Q channel, an E-DPDCH is transmitted on an I channel using (SF, 1), thereby minimizing an increase in PAPR. Here, 4, 8, 16, 32, 64 and 128 are available for the SF. In a stand-alone case, HSDPA uses an OVSF code (256, 1) on an I channel, and in a case where a DPDCH is set up, HSDPA follows the Rel-

- 37 -

5 standard. It is most preferable to allocate OVSF codes in the foregoing manner in terms of a PAPR.

1. HS-DPCCH being not Set Up and EUDCH Stand-Alone

5 E-DPDCHs are allocated I/Q channels and OVSF codes as illustrated in Table 23 according to the maximum number of transmittable DPDCHs.

Table 23

Max No of Transmittable DPDCHs	Max No of Transmittable E-DPDCHs	E-DPDCH Allocation Order
0	6	(Q, SF, SF/4), (I, 4, 1), (Q, 4, 3), (I, 4, 3), (Q, 4, 2), (I, 4, 2)
1	5	(Q, SF, SF/4), (Q, 4, 3), (I, 4, 3), (Q, 4, 2), (I, 4, 2)
2	4	(Q, SF, SF/2+SF/4), (I, 4, 3), (Q, 4, 2), (I, 4, 2)
3	3	(Q, SF, SF/2+SF/4), (Q, 4, 2), (I, 4, 2)
4	2	(Q, SF, SF/2), (I, 4, 2)
5	1	(I, SF, SF/2)

10 In Table 23, 4, 8, 16, 32, 64, 128, 256 and 512 are available for the SF. In Table 23, if the maximum number of transmittable DPDCHs is 0, a maximum of 6 E-DPDCH channels can be transmitted. In this case, OVSF codes are used in order of (Q, SF, SF/4), (I, 4, 1), (Q, 4, 3), (I, 4, 3), (Q, 4, 2) and (I, 4, 2) according to the number of E-DPDCH channels being transmitted.

15

However, if the maximum number of transmittable DPDCHs is 1, a maximum of 5 codes can be used for E-DPDCH channels transmitting EUDCH data, so that a maximum of 5 E-DPDCH channels can be transmitted. In this case, OVSF codes are used in order of (Q, SF, SF/4), (Q, 4, 3), (I, 4, 3), (Q, 4, 2) and (I, 4, 2) according to the number of E-DPDCH channels being transmitted.

20

As another example, if the maximum number of transmittable DPDCHs

]

- 38 -

is 4 in Table 23, a maximum of 2 codes can be used for E-DPDCHs. In this case, when only one E-DPDCH is transmitted, the E-DPDCH is transmitted on a Q channel using an OVSF code (SF, SF/2), and an E-DPDCH additionally allocated when necessary is transmitted on an I channel using an OVSF code (4, 2).

5

2. A Maximum of 1 DPDCH being Transmittable and HS-DPCCH being Allocated (Q, 256, 64)

E-DPDCHs are sequentially allocated four OVSF codes (Q, SF, SF/2+SF/4), (I, 4, 3), (Q, 4, 2) and (I, 4, 2) according to a EUDCH data rate. Here, 4, 8, 16, 32, 64, 128, 256 and 512 are available for the SF.

10

For example, when only one E-DPDCH is transmitted, the E-DPDCH is transmitted on a Q channel using an OVSF code (SF, SF/2+SF/4). This is to prevent an excessive increase in PAPR due to the preponderance of physical data channels over one of the I and Q channels. Therefore, DPDCHs are transmitted on the I channel and E-DPDCHs are transmitted on the Q channel, so that the number of physical data channels transmitted on the I channel is equal to the number of physical data channels transmitted on the Q channel, thereby preventing an increase in PAPR.

15

20

3. A Maximum of 2 DPDCHs being Transmittable and HS-DPCCH being Set Up

The same code allocation rule as that illustrated in Table 23 is used.

25

Ninth Embodiment

When several E-DPDCH physical channels are transmitted, SF=2 OVSF codes are used for E-DPDCHs exceptionally only in the following case in order to further reduce a PAPR.

30

For example, when (I, 4, 3) and (I, 4, 2) are simultaneously allocated to E-DPDCHs for multicode transmission on the E-DPDCHs, the E-DPDCHs are transmitted using (I, 2, 1) instead of the foregoing two codes. That is, for the case where E-DPDCHs are transmitted on the I channel using both of the OVSF codes (4, 3) and (4, 2), the E-DPDCHs are transmitted on the I channel using the OVSF code (2, 1).

35

- 39 -

Likewise, for the case where OVSF codes (4, 3) and (4, 2) are simultaneously allocated to E-DPDCHs on a Q channel, the E-DPDCHs are transmitted on the Q channel using an OVSF code (2, 1). That is, the E-DPDCHs are transmitted using (Q, 2, 1).

5

The following tenth embodiment proposes a method of additionally using possible codes generated from an OVSF code (4, 1), including a Q channel OVSF code (256, 64) used by an HS-DPCCH channel, for E-DPDCHs. In addition, the tenth embodiment proposes a method of additionally using codes allocated to
10 DPDCHs, for E-DPDCHs.

Tenth Embodiment

An OVSF code (Q, 256, 64) used for an HS-DPCCH is used for an additional E-DPDCH. That is, the tenth embodiment allows an HS-DPCCH to use
15 an OVSF code (256, 32) on a Q channel, thereby guaranteeing a EUDCH data rate. In this embodiment, OVSF code and I/Q channel allocation methods for E-DPDCHs are summarized as follows.

1. Two or Less E-DPDCH Channels being Transmitted

20 The methods proposed in the first to fifth embodiments are used.

2. Three E-DPDCH Channels being Transmitted

An E-DPDCH1 and an E-DPDCH2 are allocated to I and Q channels, respectively, using an OVSF code (2, 1).

25

An E-DPDCH3 is allocated to the Q channel using an OVSF code (4, 1). In this case, data transmitted over the E-DPDCH3 undergoes QPSK modulation.

In addition, methods of using OVSF codes allocated to DPDCHs, for E-DPDCHs, are as follows.
30

1. Three or Less E-DPDCH Channels being Transmitted

The methods proposed in the sixth to ninth embodiments are used.

35

2. Four or Less E-DPDCH Channels being Transmitted

- 40 -

When no DPDCH is transmitted, a fourth E-DPDCH is transmitted on an I channel using an OVSF code (4, 1).

5 As described above, the present invention proposes an OVSF code and I/Q channel allocation method optimized for E-DPDCHs and an E-DPCCH for EUDCH service, while maintaining backward compatibility with DPDCHs and a DPCCH which are uplink physical channels, in a method for allocating OVSF codes and I/Q channels to uplink physical channels. In addition, the present invention proposes an HS-DPCCH channel and an OVSF code which are
10 different from those defined in the existing Rel-5 standard in order to increase a maximum EUDCH data rate, and an OVSF code and I/Q channel allocation method optimized for E-DPDCHs and an E-DPCCH for the EUDCH service for the foregoing case.

15 Therefore, the present invention can minimize a PARP increase during packet data transmission for the EUDCH service and minimize a transmission error of EUDCH packet data, thereby contributing to an increase in EUDCH service capacity.

20 While the invention has been shown and described with reference to a certain preferred embodiment thereof, it will be understood by those skilled in the art that various changes in form and details may be made therein without departing from the spirit and scope of the invention as defined by the appended claims.

25

- 41 -

The embodiments of the invention in which an exclusive property or privilege is claimed are defined as follows:

1. A method for transmitting enhanced packet data in a mobile communication system, the method comprising the steps of:

generating a first enhanced dedicated physical data channel (E-DPDCH) through an in-phase (I) channel and a second E-DPDCH through a quadrature-phase (Q) channel if high speed downlink packet access (HSDPA) is set, and generating the first E-DPDCH through the Q channel and the second E-DPDCH through the I channel if HSDPA is not set;

generating an enhanced dedicated physical control channel (E-DPCCH) using the I channel; and

summing up the E-DPDCHs and the E-DPCCH before transmission.

2. The method of claim 1, wherein the E-DPCCH is spread with an orthogonal variable spreading factor (OVSF) code (256, 0) on the I channel before being transmitted.

3. The method of claim 1, wherein if one Dedicated Physical Data Channel (DPDCH) is set up, a High Speed Dedicated Physical Control Channel (HS-DPCCH) is spread with an OVSF code (256, 64) on the Q channel before being transmitted.

4. The method of claim 1, wherein if a spreading factor of the E-DPDCH is denoted by $SF_{E-DPDCH}$, an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$) is allocated.

5. The method of claim 4, further comprising the step of, if $SF_{E-DPDCH}$ is 2 and two E-DPDCHs are simultaneously transmitted, generating the first E-DPDCH and the second E-DPDCH which are spread with an OVSF code (2, 1) on the I channel and the Q channel, respectively.

- 42 -

6. The method of claim 4, further comprising the step of, if the DPDCH is not transmitted, generating third and fourth E-DPDCHs using an OVSF code (4, 1) on the I channel and the Q channel, respectively.

7. An apparatus for supporting an enhanced packet data service in a mobile communication system, the apparatus comprising:

a controller for allocating a first enhanced dedicated physical data channel (E-DPDCH) to an in-phase (I) channel and a second E-DPDCH to a quadrature-phase (Q) channel if high speed downlink packet access (HSDPA) is set, and allocating the first E-DPDCH to the Q channel and the second E-DPDCH to the I channel if HSDPA is not set, and an enhanced dedicated physical control channel (E-DPCCH) to the I channel;

a spreader for spreading the E-DPDCHs and the E-DPCCH according to a control signal from the controller;

a summer for summing up the spread E-DPDCHs and E-DPCCH; and

a transmitter for transmitting the summed signal.

8. The apparatus of claim 7, wherein the controller allocates the E-DPCCH to an orthogonal variable spreading factor (OVSF) code (256, 1) on the I channel.

9. The apparatus of claim 7, wherein if one DPDCH is set up, the controller allocates a high speed downlink physical control channel (HS-DPCCH) to an OVSF code (256, 64) on the Q channel.

10. The apparatus of claim 7, wherein if one dedicated physical data channel (DPDCH) is set up, the controller allocates the E-DPDCH to an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$), where $SF_{E-DPDCH}$ denotes a spreading factor of the E-DPDCH.

- 43 -

11. The apparatus of claim 10, wherein if $SF_{E-DPDCH}$ is 2 and two E-DPDCHs are simultaneously transmitted, the controller allocates the first E-DPDCH and the second E-DPDCH to an OVSF code (2, 1) on the I channel and the Q channel, respectively.

12. The apparatus of claim 10, wherein if the DPDCH is not transmitted, the controller allocates third and fourth E-DPDCHs to an OVSF code (4, 1) on the I channel and the Q channel, respectively.

13. A method for receiving enhanced packet data in a mobile communication system, the method comprising the steps of:

receiving information indicating a transport channel condition from a user equipment (UE);

transmitting scheduling allocation information indicating data rate information of an enhanced dedicated physical data channel (E-DPDCH) to the UE; and

receiving a first enhanced dedicated physical data channel (E-DPDCH) through an in-phase (I) channel and a second E-DPDCH through a quadrature-phase (Q) channel if high speed downlink packet access (HSDPA) is set, and receiving the first E-DPDCH through the Q channel and the second E-DPDCH through the I channel if HSDPA is not set; and

receiving an enhanced dedicated physical control channel (E-DPCCH) using the I channel.

14. The method of claim 13, wherein the E-DPCCH is received using an orthogonal variable spreading factor (OVSF) code (256, 1) on the I channel.

15. The method of claim 13, wherein if one dedicated physical data channel (DPDCH) is set up, a high-speed downlink physical control channel (HS-DPCCH) is received using an OVSF code (256, 64) on the Q channel.

- 44 -

16. The method of claim 13, wherein if one dedicated physical data channel (DPDCH) is set up, the E-DPDCH is received using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$), where $SF_{E-DPDCH}$ denotes a spreading factor of the E-DPDCH.

17. The method of claim 16, wherein if $SF_{E-DPDCH}$ is 2 and two E-DPDCHs are simultaneously transmitted, the first E-DPDCH and the second E-DPDCH are received using an OVSF code (2, 1) on the I channel and the Q channel, respectively.

18. The method of claim 16, wherein if the DPDCH is not transmitted, third and fourth E-DPDCHs are received using an OVSF code (4, 1) on the I channel and the Q channel, respectively.

19. An apparatus for receiving enhanced packet data in a mobile communication system, the apparatus comprising:

a receiver for receiving information indicating a transport channel condition from a user equipment (UE), and receiving a first enhanced dedicated physical data channel (E-DPDCH) through an in-phase (I) channel and a second E-DPDCH through a quadrature-phase (Q) channel if high speed downlink packet access (HSDPA) is set, and receiving the first E-DPDCH through the Q channel and the second E-DPDCH through the I channel if HSDPA is not set, and an enhanced dedicated physical control channel (E-DPCCH) through the I channel; and

a transmitter for transmitting scheduling allocation information indicating data rate information of an enhanced dedicated physical data channel (E-DPDCH) to the UE; and

a controller for controlling the transmitter and the receiver.

20. The apparatus of claim 19, wherein the receiver receives the E-DPCCH

- 45 -

using an orthogonal variable spreading factor (OVSF) code (256, 1) on the I channel.

21. The apparatus of claim 19, wherein if one dedicated physical data channel (DPDCH) is set up, the receiver receives a high speed-downlink physical channel (HS-DPCCH) using an OVSF code (256, 64) on the Q channel.

22. The apparatus of claim 19, wherein if one dedicated physical data channel (DPDCH) is set up, the receiver receives the E-DPDCH using an OVSF code ($SF_{E-DPDCH}$, $SF_{E-DPDCH}/2$), where $SF_{E-DPDCH}$ denotes a spreading factor of the E-DPDCH.

23. The apparatus of claim 19, wherein if $SF_{E-DPDCH}$ is 2 and two E-DPDCHs are simultaneously transmitted, the receiver receives the first E-DPDCH and the second E-DPDCH using an OVSF code (2, 1) on the I channel and the Q channel, respectively.

24. The apparatus of claim 19, wherein if a dedicated physical data channel (DPDCH) is not transmitted, the receiver receives third and fourth E-DPDCHs using an OVSF code (4, 1) on the I channel and the Q channel, respectively.




FIG.1




FIG.2





FIG.3



Case #	99.9% PAPR [dB]	I CHANNEL			Q CHANNEL		
		PHYSICAL CHANNEL	OVSF CODE	β	PHYSICAL CHANNEL	OVSF CODE	β
40 (PROPOSED METHOD)	5.49	E-DPCCH	64, 1	30	DPCCH	256, 0	15
		DPDCH	64, 16	15	HS-DPCCH	256, 64	30
		E-DPDCH1	4, 2	34	E-DPDCH2	4, 2	34
					DPCCH	256, 0	15
41	6.19				E-DPCCH	64, 1	30
					HS-DPCCH	256, 64	30
		DPDCH	64, 16	15			
		E-DPDCH1	4, 2	34	E-DPDCH2	4, 2	34
42	5.61	E-DPCCH	64, 8	30	DPCCH	256, 0	15
		DPDCH	64, 16	15	HS-DPCCH	256, 64	30
		E-DPDCH1	4, 2	34	E-DPDCH2	4, 2	34

FIG.5

