




(86) **Date de dépôt PCT/PCT Filing Date:** 2015/02/26
(87) **Date publication PCT/PCT Publication Date:** 2015/09/03
(85) **Entrée phase nationale/National Entry:** 2016/08/22
(86) **N° demande PCT/PCT Application No.:** SE 2015/050216
(87) **N° publication PCT/PCT Publication No.:** 2015/130210
(30) **Priorité/Priority:** 2014/02/27 (US61/945,403)

(51) **Cl.Int./Int.Cl.** *H03M 7/30* (2006.01),
G10L 19/038 (2013.01), *H04N 19/124* (2014.01)
(71) **Demandeur/Applicant:**
TELEFONAKTIEBOLAGET LM ERICSSON (PUBL), SE
(72) **Inventeur/Inventor:**
SVEDBERG, JONAS, SE
(74) **Agent:** ERICSSON CANADA PATENT GROUP

(54) **Titre : PROCEDE ET APPAREIL POUR INDEXATION ET DESINDEXATION DE QUANTIFICATION VECTORIELLE PYRAMIDE
DE VECTEURS D'ECHANTILLON AUDIO/VIDEO**
(54) **Title: METHOD AND APPARATUS FOR PYRAMID VECTOR QUANTIZATION INDEXING AND DE-INDEXING OF AUDIO/VIDEO
SAMPLE VECTORS**



(57) **Abrégé/Abstract:**

A method for pyramid vector quantization indexing of audio/video signals comprises obtaining (402) of an integer input vector representing the audio/video signal samples. A leading sign is extracted (404) from the integer input vector. The leading sign is a sign of a terminal non-zero coefficient in the integer input vector. The terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in the integer input vector. The integer input vector is indexed (406) with a pyramid vector quantization enumeration scheme into an output index representing the audio/video signal samples. The pyramid vector quantization enumeration scheme is designed for neglecting the sign of the terminal non-zero coefficient. The output index and the leading sign are outputted (408). A corresponding method for de-indexing, an encoder, a decoder, and computer programs therefore are also disclosed.

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property
Organization
International Bureau



WIPO | PCT



(10) International Publication Number

WO 2015/130210 A1

(43) International Publication Date
3 September 2015 (03.09.2015)

(51) International Patent Classification:
H03M 7/30 (2006.01)

(21) International Application Number:
PCT/SE2015/050216

(22) International Filing Date:
26 February 2015 (26.02.2015)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
61/945,403 27 February 2014 (27.02.2014) US

(71) Applicant: TELEFONAKTIEBOLAGET L M ERICSSON (PUBL) [SE/SE]; SE-164 83 Stockholm (SE).

(72) Inventor: SVEDBERG, Jonas; Lingonstigen 75, S-973 33 Luleå (SE).

(74) Agent: EGRELIUS, Fredrik; Ericsson AB, Patent Unit Kista DSM, SE-16480 Stockholm (SE).

(81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM,


DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

(84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, KM, ML, MR, NE, SN, TD, TG).

Published:

- with international search report (Art. 21(3))
- before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments (Rule 48.2(h))

(54) Title: METHOD AND APPARATUS FOR PYRAMID VECTOR QUANTIZATION INDEXING AND DE-INDEXING OF AUDIO/VIDEO SAMPLE VECTORS



(57) Abstract: A method for pyramid vector quantization indexing of audio/video signals comprises obtaining (402) of an integer input vector representing the audio/video signal samples. A leading sign is extracted (404) from the integer input vector. The leading sign is a sign of a terminal non-zero coefficient in the integer input vector. The terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in the integer input vector. The integer input vector is indexed (406) with a pyramid vector quantization enumeration scheme into an output index representing the audio/video signal samples. The pyramid vector quantization enumeration scheme is designed for neglecting the sign of the terminal non-zero coefficient. The output index and the leading sign are outputted (408). A corresponding method for de-indexing, an encoder, a decoder, and computer programs therefore are also disclosed.

WO 2015/130210 A1

METHOD AND APPARATUS FOR PYRAMID VECTOR QUANTIZATION INDEXING AND DE-INDEXING OF AUDIO/VIDEO SAMPLE VECTORS

5

TECHNICAL FIELD

The proposed technology generally relates to encoding/decoding of audio/video signals and in particular to methods and apparatuses for pyramid vector quantization indexing and de-indexing of audio/video
10 sample vectors.

BACKGROUND

When audio or video signals are to be transmitted or stored, the signals are
15 typically encoded. In an encoder, vectors representing audio/video signal samples are encoded to be represented by a number of coefficients or parameters. These coefficients or parameters can then efficiently be transmitted or stored. When the coefficients or parameters are received or retrieved, a decoding of the coefficients or parameters into audio/video
20 signal samples is performed to retrieve the original audio/video signal. Many different kinds of encoding techniques have been used for audio/video signals.

One approach is based on vector quantization (VQ). It is known that
25 unconstrained vector quantization (VQ) is the optimal quantization method for grouped samples (vectors) of a certain length. However, the memory and search complexity constraints have led to the development of structured vector quantizers. Different structures gives different trade-offs in terms of search complexity and memory requirements. One such method is the gain-
30 shape vector quantization, where the target vector x is represented using a shape vector vec and a gain G :

$$vec = \frac{x}{G}$$

The concept is, instead of quantizing directly the target vector, to quantize pairs of {vec, G}. Gain and shape components are then encoded using a shape quantizer which is tuned for the normalized shape input and a gain quantizer which handles the dynamics of the signal. This structure is well used in e.g. audio coding since the division into dynamics and shape (or fine structure) fits well with the perceptual auditory model.

A valid entry in the selected structured vector quantizer, is first searched using the knowledge of the structure (e.g. L1(absolute amplitude)-normalization or L2(energy)-normalization). After a valid vector has been found one needs to efficiently create an index (or codeword) that represents that specific vector and then transmit that index to the receiver. The index creation (also known as indexing or enumeration) will use the properties of the selected structure and create a unique index (codeword) for the found vector in the structured VQ.

On the receiving side the decoder needs to efficiently decompose the index into the same vector that was determined on the encoder side. This decomposition can be made very low complex in terms of operations by using a large table lookup, but then at the cost of huge stored Read-Only Memory (ROM) tables. Alternatively one can design the decomposition (also known as de-indexing) so that it uses knowledge of the selected structure and potentially also the available target hardware numerical operations to algorithmically decompose the index into the unique vector, in an efficient way.

A well designed structured VQ, has a good balance between encoder search complexity, encoder indexing complexity and decoder de-indexing complexity in terms of Million Operations Per Second (MOPS) and in terms of Program ROM and dynamic Random Access Memory (RAM) required, and in terms of Table ROM.

Many audio codecs such as CELT, IETF/Opus-Audio and ITU-T G.719 use an envelope and shape VQ and an envelope mixed gain-shape VQ to encode the spectral coefficients of the target audio signal (in the Modified Discrete Cosine Transform (MDCT) domain). CELT/IETF OPUS-Audio use a PVQ-Vector Quantizer, while G.719 uses and slightly extended RE8 Algebraic Vector Quantizer for R=1 bit/dimension coding and a very low complexity D8 Lattice quantizer for VQ rates higher than 1 bit/dimension. PVQ stands for Pyramid Vector Quantizer, it is a VQ that uses the L1-norm($\sum \text{abs}(\text{vector})$) to enable a fast search. It has also been found that PVQ may provide quite efficient indexing. The PVQ has been around for some time, but was initially developed in 1983-86 by Fischer.

PVQ-quantizers have also been used for encoding of time domain and Linear Prediction (LP) residual domain samples in speech coders, and for encoding of frequency domain Discrete Cosine Transform (DCT) coefficients. An advantage with the PVQ compared to other structured VQs is that it naturally can handle any vector dimension, while other structured VQs often are limited to the dimension being multiples, e.g. multiples of 4 or multiples of 8.

The IETF/OPUS Codec in Audio mode is employing a recursive PVQ-indexing and de-index scheme that has a maximum size of the PVQ-indices/(short) codewords set to 32 bits. If the target vector to be quantized requires more than 32 bits, the original target vector is recursively split in halves into lower dimensions, until all sub-vectors fit into the 32 bit short codeword indexing domain. In the course of the recursive binary dimension splitting there is an added cost of adding a codeword for encoding the energy relation (the relative energies, which can be represented by a quantized angle) between the two split sub target vectors. In OPUS-Audio the structured PVQ-search is made on the resulting split smaller dimension target sub-vectors.

The original CELT codec (developed by Valin, Terriberry and Maxwell in 2009), is employing a similar PVQ-indexing/deindexing scheme, (with a 32 bit codeword limit) but the binary dimension split in CELT is made in the indexing domain after searching and after establishing the initial PVQ-
 5 structured vector. The integer PVQ-vector to index is then recursively reduced to smaller than or equal to 32 bit PVQ-vector sub-units in the integer domain. This is again achieved by adding an additional codeword for the split, this time for the integer relation between the ‘left’ integer sub-vector and the ‘right’ integer sub-vector, so that one can know the L1-norm
 10 of each of the sub PVQ-vectors in the decoder. The CELT post-search integer indexing split approach leads to a variable rate (variable total size index), which can be a disadvantage if the media-transport requires fixed rate encoding.

15 In 1997 and 1998 Hung, Tsern and Meng, investigated the error robustness of a few PVQ-indexing variations, they summarized the PVQ-enumeration (indexing) problem this way (l is the vector dimension and k is the number of unit pulses):

*“Enumeration assigns a unique index to all possible vectors in the PVQ-
 20 codebook, $P(l, k)$, imparting a sorting order to the PVQ-codebook vectors.”*

“Systematic sorting for enumeration is done through counting formulas for the number of vectors in the pyramid; this is a common concept to all pyramid enumeration techniques.”

*“The number of vectors in the pyramid codebook $P(l, k)$ is denoted $N(l, k)$. This
 25 is related to a binary codeword index length which is $\text{ceil}(\log_2(N(l, k)))$ bits. $N(l, k)$ can be viewed as the number of ways l integer values in a vector can have an absolute sum of k .”*

Hung et al, studied the bit error robustness of the PVQ-codewords for a
 30 couple of variations of PVQ-indexing/enumeration schemes, but they did not focus the study on making the implementation of PVQ-enumeration efficient and of sufficiently low complex for an actual hardware implementation. The CELT and the IETF/OPUS-Audio PVQ-implementations

of PVQ-indexing are strongly focused on providing an as low complex enumeration as possible (both encoding and decoding), given a 32 bit unsigned integer based hardware, but disregarding the PVQ- sensitivity to bit errors. Also in 1999 Ashley proposed a way to reduce the complexity for
 5 implementing the product code PVQ-enumeration by the use of a low complexity deterministic approximation of the Binomial combinatorial function used for size calculation and offset calculation, Ashley et al call this technique Factorial Pulse Coding (FPC), and it has been employed in the ITU-G.718 speech codec standard.

10

In CELT and IETF/OPUS-Audio, the PVQ-codeword is not limited by the granularity of a single bit. The two codecs use a higher granularity scheme, using eighth ($1/8$) bits resolution. This is achieved by using an arithmetic encoder/decoder as an intermediate step in the interface to the transport bit
 15 stream, (CELT/OPUS-Audio uses an implementation of a range encoder/decoder as the arithmetic encoder/decoder) where the number of bits used by the PVQ-codeword can be made into fractional bits. With a bit resolution $\text{BITRES} = 8$ (eighths), the fractional PVQ codeword length becomes $\text{ceil}(\log_2(N(l, k) * \text{BITRES})) / \text{BITRES}$. For instance, if $l=64$, $k=5$ and
 20 $\text{BITRES}=8$, this leads to that $\text{NPVQ}=N(l,k)=286680704$, $\log_2(\text{NPVQ})=28.0948696$, and $\text{ceil}(\log_2(\text{NPVQ})*\text{BITRES})/\text{BITRES} = 28.125$ bits. By using fractional bits there will be much less truncation loss for many of the $N(l, k)$ PVQ codeword sizes, and especially when a codec is using many calls/instances of a PVQ-quantizer, this will increase the
 25 codec's efficiency.

One general issue with structured vector quantization is to find a suitable overall compromise including the methods for efficient search, efficient codeword indexing and efficient codeword de-indexing.

30

Long index codewords (e.g. a 400 bit integer codeword) gives larger complexity overhead in indexing and deindexing calculations (and special

software routines will be needed for multiplying and dividing these large integers in the long codeword composition and decomposition).

Short index code words can use efficient hardware operators (e.g. Single
5 Instruction Multiple Data (SIMD) instructions in a 32 bit Digital Signal
Processor (DSP)), however at the cost of requiring pre-splitting of the target
VQ-vectors (like in IETF/OPUS-Audio), or post-search-splitting the integer
PVQ-search result-vector (like in original-CELT). These dimension splitting
methods adds a transmission cost for the splitting information codeword
10 (splitting overhead), and the shorter the possible index-codewords are, the
higher number of splits are required and the result is an increased overhead
for the long index codeword splitting. E.g. 16 bit short PVQ-codewords will
result in many more splits than 32 bit short codewords, and thus a higher
overhead for the splitting.

15

The PVQ (Pyramid Vector Quantizer) readily allows for a very efficient
search, through L1-normalization. Typically the absolute sum normalized
target vector is created, followed by vector value truncation (or rounding)
and then a limited set of corrective iterations are run to reach the target L1-
20 norm (k) for the PVQ-vector (PVQ-vec).

The problem of the previously mentioned CELT/OPUS prior art short
codeword indexing schemes is that they are limited to a 32-bit integer range
(unsigned 32-bit integers), and further they cannot be efficiently
25 implemented in a DSP-architecture that only supports fast instructions for
signed 32-bit integers.

SUMMARY

30 It is an object of the here presented technology to expand the size of the
vectors indexed by PVQ that can be processed in a hardware having an
optimum operation bit size.

This and other objects are met by embodiments of the proposed technology.

According to a first aspect, there is provided a method for pyramid vector quantization indexing of audio/video signals. The method comprises
5 obtaining of an integer input vector, which integer input vector representing audio/video signal samples, which integer input vector having a number of integer-valued coefficients, extracting of a leading sign from said integer input vector, which leading sign is a sign of a terminal non-zero coefficient in the integer input vector, which terminal non-zero coefficient is one of a first non-
10 zero coefficient and a last non-zero coefficient in the integer input vector, indexing the integer input vector with a pyramid vector quantization enumeration scheme into an output index, which output index together with the leading sign representing the audio/video signal samples, wherein the pyramid vector quantization enumeration scheme is designed for neglecting
15 the sign of the terminal non-zero coefficient, and outputting of the output index as a first codeword and the leading sign as a second codeword into an outgoing bit stream.

In one embodiment, the extracting takes place before the enumerating. In
20 another embodiment, extracting takes place concurrently and in cooperation with the enumerating. In one embodiment, an offset parameter, in this disclosure denoted as $U(n,k)$, is defined as the number of integer vectors of dimension n and $L1$ -norm of k , that does not have a leading zero, and does not have the leading value k , has a leading positive value, and has a positive
25 next leading sign. The offset parameter U is in that embodiment used for calculation of the indexing scheme used in the enumeration. In another embodiment, the index calculation is dependent on both the U parameter and an offset parameter, in this disclosure denoted as $A(n,k)$, being defined as the number of integer vectors of dimension n and $L1$ -norm of k , that has
30 a positive leading value and that does not have a leading zero. In yet another embodiment, index calculation in the enumeration is dependent partly on the enumeration procedures based on U or a combination of U and A . In other words, the enumeration may employ an initial MPVQ-leading sign

enumeration stage followed by any other efficient PVQ-enumeration scheme, for the remainder of the vector.

According to a second aspect, there is provided a method for pyramid vector
5 quantization deindexing of audio/video signals. The method comprises
receiving, from an ingoing bit stream, of a leading sign as a first codeword
and an input index as a second codeword, the leading sign and the input
index representing audio/video signal samples, which leading sign is a sign
of a terminal non-zero coefficient in an integer output vector to be created,
10 representing the audio/video signal samples, which integer output vector
having a number of integer-valued coefficients, which terminal non-zero
coefficient is one of a first non-zero coefficient and a last non-zero coefficient
in the integer output vector, deindexing of the input index into the integer
output vector according to a pyramid vector quantization de-enumeration
15 scheme, wherein the input index being created by an enumeration scheme is
designed for neglecting the sign of the terminal non-zero coefficient,
assigning of a sign of the terminal non-zero coefficient in the integer output
vector according to the received leading sign, and outputting of the integer
output vector.

20

According to a third aspect, there is provided a method for communication of
audio/video signals. The method comprises encoding the audio/video
samples, in an encoder of a transmitter, according to a method according to
the first aspect, transmission of the output index and the leading sign from
25 the transmitter to a receiver, where it is received as an input index and a
leading sign, and decoding, in a decoder in the receiver, said input index
and said leading sign according to a method according to the second aspect.

According to a fourth aspect, there is provided an encoder for indexing of
30 audio/video signals by pyramid vector quantization. The encoder is operative
to obtain an integer input vector, which integer input vector representing
the audio/video signal samples, which integer input vector having a number
of integer-valued coefficients, extract a leading sign from the integer input

vector, which leading sign is a sign of a terminal non-zero coefficient in the integer input vector, which terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in the integer input vector, index the integer input vector with a pyramid vector quantization
5 enumeration scheme into an output index, which output index together with the leading sign representing the audio/video signal samples, wherein the pyramid vector quantization enumeration scheme is designed for neglecting the sign of the terminal non-zero coefficient, and to output the leading sign as a first codeword and the output index as a second codeword into an
10 outgoing bit stream.

According to a fifth aspect, there is provided a decoder for deindexing of audio/video signals by pyramid vector quantization. The decoder is operative to receive, from an ingoing bit stream, a leading sign as a first codeword and
15 an input index as a second codeword, the leading sign and the input index representing audio/video signal samples, which leading sign is a sign of a terminal non-zero coefficient in an integer output vector to be created, representing the audio/video signal samples, which integer output vector having a number of integer-valued coefficients, which terminal non-zero
20 coefficient is one of a first non-zero coefficient and a last non-zero coefficient in the integer output vector, deindex the input index into a the integer output vector according to a pyramid vector quantization de-enumeration scheme, wherein the input index being created by an enumeration scheme is designed for neglecting the sign of the terminal non-zero coefficient, assign a
25 sign of the terminating non-zero coefficient according to the received leading sign, and to output the integer output vector.

According to a sixth aspect, there is provided an encoder for pyramid vector quantization indexing of audio/video signal samples. The encoder comprises
30 an input module for obtaining an integer input vector, which integer input vector representing the audio/video signal samples, which integer input vector having a number of integer-valued coefficients. The encoder further comprises an extracting module for extracting a leading sign from the

integer input vector. The leading sign is a sign of a terminal non-zero coefficient in the integer input vector. The terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in the integer input vector. The encoder further comprises an indexing module for indexing
5 the integer input vector with a pyramid vector quantization enumeration scheme into an output index, which output index together with the leading sign representing the audio/video signal samples, wherein the pyramid vector quantization enumeration scheme is designed for neglecting the sign of the terminal non-zero coefficient. The encoder further comprises an
10 output module for outputting the leading sign as a first codeword and the output index as a second codeword into an outgoing bit stream.

According to a seventh aspect, there is provided a decoder for decoding of audio/video signal samples. The decoder comprises a receiver for receiving a
15 leading sign as a first codeword and an input index as a second codeword from an ingoing bit stream. The leading sign and the input index representing audio/video signal samples. The leading sign is a sign of a terminal non-zero coefficient in an integer output vector to be created, representing the audio/video signal samples. The integer output vector has a
20 number of integer-valued coefficients. The terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in the integer output vector. The decoder further comprises a deindexing module for deindexing the input index into the integer output vector according to a pyramid vector quantization de-enumeration scheme, wherein the input
25 index being created by an enumeration scheme is designed for neglecting the sign of the terminal non-zero coefficient. The decoder further comprises an assigning module for assigning a sign of the terminal non-zero coefficient in the integer output vector according to the received leading sign. The decoder further comprises an output module for outputting the integer output
30 vector.

According to an eighth aspect, there is provided a network node comprising an encoder according to the fourth or sixth aspect and/or a decoder according to the fifth or seventh aspect.

- 5 According to a ninth aspect, there is provided a user equipment comprising an encoder according to the fourth or sixth aspect and/or a decoder according to the fifth or seventh aspect.

According to a tenth aspect, there is provided a computer program for
10 encoding of audio/video signal samples, which computer program comprises instructions, which when executed by at least one processor, cause the processor(s) to obtain an integer input vector, which integer input vector represents the audio/video signal samples. The integer input vector has a number of integer-valued coefficients. The computer program comprises
15 further instructions, which when executed by the processor(s), cause the processor(s) to extract a leading sign from the integer input vector. The leading sign is a sign of a terminal non-zero coefficient in the integer input vector. The terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in the integer input vector. The computer program
20 comprises further instructions, which when executed by the processor(s), cause the processor(s) to index the integer input vector with a pyramid vector quantization enumeration scheme into an output index, which output index together with said leading sign representing the audio/video signal samples. The pyramid vector quantization enumeration scheme is designed for
25 neglecting the sign of said terminal non-zero coefficient. The computer program comprises further instructions, which when executed by the processor(s), cause the processor(s) to output the leading sign as a first codeword and the output index as a second codeword into an outgoing bit stream.

30

According to an eleventh aspect, there is provided a computer program for decoding of audio/video signals, which computer program comprises instructions, which when executed by at least one processor, cause the

processor(s) to receive a leading sign as a first codeword and an input index as a second codeword from an ingoing bit stream. The leading sign and the input index representing audio/video signal samples. The leading sign is a sign of a terminal non-zero coefficient in an integer output vector to be created, 5 representing the audio/video signal samples. The integer output vector has a number of integer-valued coefficients. The terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in said integer output vector. The computer program comprises further instructions, which when executed by the processor(s), cause the processor(s) to deindex the input 10 index into the integer output vector with a pyramid vector quantization deenumeration scheme. The input index being created by an enumeration scheme is designed for neglecting the sign of the terminal non-zero coefficient. The computer program comprises further instructions, which when executed by the processor(s), cause the processor(s) to assign a sign of the terminating 15 non-zero coefficient according to the received leading sign. The computer program comprises further instructions, which when executed by the processor(s), cause the processor(s) to output the integer output vector.

According to a twelfth aspect, there is provided a carrier comprising the 20 computer program of at least one of the tenth and eleventh aspect. The carrier is one of an electronic signal, an optical signal, an electromagnetic signal, a magnetic signal, an electric signal, a radio signal, a microwave signal, or a computer-readable storage medium.

25 One advantage with the here presented techniques is that it reduces the dynamic range necessary for the required indexing offsets, thereby reducing the demands on the accepted bit size of the used hardware.

The indexing algorithm preferably iteratively decomposes the PVQ-structure 30 and indices into leading sign sections. The decomposition is made in such a way that independently of the number of non-zero elements in the found PVQ-vector to index, always one leading sign is extracted. This low complex

sign extraction further enables the creation of a reduced dynamic range for runtime calculated PVQ indexing offsets.

As one particular example, the improved indexing and de-indexing algorithms will enable the use of 33 bit PVQ- indices in 32-bit DSP Hardware, with marginal additional cost in terms of overall MOPS, RAM, ROM and Program Read-Only Memory (P-ROM). Further the algorithm will enable the use of 32-bit PVQ-indices in a DSP Hardware only supporting signed 32 bit arithmetic.

10

Other advantages will be appreciated when reading the detailed description.

BRIEF DESCRIPTION OF THE DRAWINGS

15

The embodiments, together with further objects and advantages thereof, may best be understood by making reference to the following description taken together with the accompanying drawings, in which:

- 20 FIG. 1 is a schematic illustration of an example audio coding system;
FIG. 2 is a schematic block diagram of an embodiment of an encoder;
FIG. 3 is a schematic block diagram of an embodiment of a decoder;
FIG. 4 is a tabled structure view of an embodiment of an offset and its relation to the total number of vectors in the structure;
25 FIG. 5 is a flow diagram of steps of an embodiment of a method for pyramid vector quantization indexing of audio/video samples;
FIG. 6 is a flow diagram of steps of an embodiment of a MPVQ indexing on a general level;
FIG. 7A-B is a flow diagram of steps of an embodiment of a method for
30 MPVQ-index composition;
FIG. 8 is a tabled high level structure view of an embodiment of a basic MPVQ iteration;

FIG. 9 is a flow diagram of steps of a combination of three embodiments of a MPVQ-A/U offset recursion for increasing dimension;

FIG. 10 illustrates a flow diagram of steps of an embodiment of a method for pyramid vector quantization deindexing of audio/video samples;

5 FIG. 11 is a flow diagram of steps of an embodiment of MPVQ deindexing;

FIG. 12 is a flow diagram of steps of an embodiment of procedures to find size and offsets;

FIG. 13 is a flow diagram of steps of an embodiment of MPVQ index decomposition;

10 FIG. 14 is a flow diagram of steps of an embodiment for finding an amplitude of a next coefficient;

FIG. 15 is a flow diagram of steps of an embodiment of a procedure for finding the next leading sign and removing the extracted sign information;

FIG. 16 is a flow diagram of steps of an embodiment of a procedure for offset
15 updating for one dimension less;

FIG. 17A is a diagram presenting an overview of PVQ-codewords for some common hardware bit limits;

FIG. 17B is a diagram presenting an overview of the related R values in bits/sample for optimal PVQ-codeword quantizers with different BIT limits;

20 FIG. 17C is a diagram showing a corresponding achievable pulse density, which is directly correlated to the resulting shape matching capability of the PVQ;

FIG. 17D is a diagram illustrating a worst case MOPS Instruction trade-off in indexing/deindexing for a sample prior art scheme PVQ and for the new
25 scheme MPVQ;

FIG. 18 is a flow diagram of steps of an embodiment of a MPVQ-index composition using pre-extracted leading signs;

FIG. 19 is a flow diagram of steps of an embodiment of a sign extraction function;

30 FIG. 20 illustrates schematically an embodiment of an encoder;

FIG. 21 illustrates schematically an embodiment of a decoder;

FIG. 22 illustrates schematically an embodiment of an encoder; and

FIG. 23 illustrates schematically an embodiment of a decoder.

DETAILED DESCRIPTION

The embodiments, together with further objects and advantages thereof,
5 may best be understood by making reference to the following description
taken together with the accompanying drawings.

Throughout the drawings, the same reference designations are used for
similar or corresponding elements.

10

The indexing algorithm iteratively decomposes the PVQ-structure and
indices into leading sign sections. The decomposition is made in such a way
that independently of the number of non-zero elements in the found PVQ-
vector to index, always one leading sign is extracted. This low complex sign
15 extraction further enables the creation of a reduced dynamic range for
runtime calculated PVQ indexing offsets.

The PVQ indexing offsets are used in PVQ-index composition and in the
PVQ-index decomposition. As the structured PVQ-quantizer intrinsically can
20 handle a large variation in dimension (l) and unit pulses (k), and thus in bit
rate, the offsets are usually only calculated for the current dimension to be
encoded and the current number of unit pulses. The bit rate corresponds to
 $\log_2(N_{PVQ}(l,k))$, resulting in a huge amount of possible PVQ offsets. The
offsets are stored in a dynamic RAM. However, an l,k -limited PVQ quantizer
25 implementation may use table lookup to store the indexing/de-indexing
offsets.

For a better understanding of the proposed technology, it may be useful to
refer to extracts of IETF/OPUS search/indexing/de-indexing prior art
30 description, collected in Appendix A.

In Fig. 1, an example audio coding system using the scheme presented in
the present description is illustrated. This is an example audio codec system

with an encoder 10 and a decoder 60 using MPVQ indexing and de-indexing. The first part corresponds to the parts comprised in an encoder 10 and the second part of the figure corresponds to the parts comprised in a decoder 60. An input sample 1 is provided to the encoder 10. The encoder 10 provides a bit stream 2 representing the input vector as at least a MPVQ index and a leading sign. A bit stream 2', preferably essentially equal to the bit stream 2 from the encoder 10, is provided to the decoder 60, where the decoder decodes the MPVQ index and the leading sign to a reconstructed sample 3. Typically, the MPVQ index and the leading sign are provided as separate codewords.

An embodiment of an encoder 10 is illustrated in more detail in Fig. 2. The input sample 1, representing an audio/video sample x is received. In a norm calculator 12, a norm factor g is computed. A norm quantizer 14 creates norm quantization bits NORMQ-bits representing the norm of the input vector. These bits are typically provided to be included in the Bit stream. The input vector is normalized by the norm factor into a normalized vector 4. The norm quantizer 14 also optionally provided the norm factor, e.g. as NORMQ-bits, to a bit allocation section 16, which calculates, or retrieves from look-up tables, suitable values of N and K , i.e. the dimension of the integer vector and the total number of unit pulses. These values may optionally be provided in the outgoing bit-stream or be derived at the receiving side from preceding parameters in the bit stream. A PVQ shape search section 18 converts the normalized vector 4 into an integer input vector 5 for PVQ. The integer input vector 5 is provided to a MPVQ-indexing section 20, where the actual MPVQ indexing takes place. This will be discussed more in detail further below. A leading sign 15, as a first codeword, and an output index, as a second codeword, an MPVQ index 25, typically accompanied by the MPVQ size are output from the MPVQ-indexing section 20 to a bit stream multiplexor, MUX, 30. There, the different information quantities are merged into a single bit stream 2, being output from the bit stream MUX 30.

An embodiment of a decoder 60 is illustrated in more detail in Fig. 3. An incoming bit stream 2' is provided to a bit stream DEMUX 80. Here the different parts of the information is divided into parts. Information supporting the bit allocation, such as N and K values or NORMQ-bits, is provided to a bit allocation section 62, outputting relevant values of N and K to a size/offsets calculation section 64 and a MPVQ-deindexing section 70. The size/offsets calculation section 64 calculates offsets 8, based on the N and K values as well as the MPVQ size obtained from the information 25' of reconstructed MPVQ index 25', typically accompanied by the MPVQ size, and provided to the MPVQ deindexing section 70. The reconstructed MPVQ index 25', as a second codeword, and the reconstructed leading sign 15', as a first codeword, are also provided to the MPVQ deindexing section 70, where the actual MPVQ deindexing takes place. This will be discussed more in detail further below. An integer output vector 6', being a reconstruction of the integer input vector in the encoder, is output to a unit energy normalization section 68 in which the normalization is secured. A norm dequantizer 66 uses the NORMQ-bits to provide a norm factor $\hat{g}$. The norm factor is then used to form the final output vector $\hat{x}$ being a reconstructed sample 3 of the original audio/video sample.

20

It should be noted that the MPVQ-scheme is not limited to the particular system in the figures 2 and 3, but can also be employed for indexing of any PVQ-based quantization system, e.g. time domain signals in a Linear Predictive (LP) Vocoder or transform domain coefficients in a video codec.

25

For instance, in Figures 2 and 3 the "BITSTREAM MUX" and "BITSTREAM DEMUX" blocks may optionally employ an arithmetic encoder and decoder respectively, to limit the PVQ-index truncation loss as explained elsewhere in the present disclosure. The "MUX" and "DEMUX" blocks need to know the integer size (MPVQ-size) of each short PVQ-codeword, to be able to extract the right number of bits for the MPVQ(n,k) codeword. Without an arithmetic encoder/decoder the MUX/DEMUX will use $\text{ceil}(\log_2(\text{MPVQ-size}))$ whole non-fractional bits when parsing the bit-stream for the MPVQ(n, k) short

30

codeword. With an arithmetic encoder/decoder pair, the bit resolution and distribution function(s) employed by the arithmetic encoder/decoder pair will decide the fractional bits used by the “MUX” and “DEMUX blocks”. The arithmetic encoder/decoder pair will also need the integer MPVQ-size to
 5 determine how it should parse bits (now fractional) decoded from the bit-stream.

Such operations are well known by anyone skilled in the art and are in the remaining description assumed to be a natural part of a PVQ system.

10

In Fig. 2, in the encoder the MPVQ-size is calculated as a part of the MPVQ-indexing loop and then provided to the MUX. In Fig. 3, the decoder, a function calculating MPVQ-offsets and MPVQ-size is called first, then the codeword is extracted from the MUX using this integer size information. The
 15 extracted index (second codeword) and the initial offsets are then provided to the MPVQ-deindexing block.

The encoder part and/or the decoder part of Figs. 2 and 3 may in some applications be comprised in a node of a communication network, or a User
 20 Equipment. The node of the communication network may e.g. be a radio network node, e.g. a base station. The communication between the encoder part and the decoder part can be performed by wired and/or wireless transmission. The encoder part and the decoder part may also operate separately. For instance, the encoder part could be a part of a recording
 25 equipment, and the resulting bitstream could be stored for a future use. Likewise, the decoder part could be a part of a playing equipment, which for instance retrieves a bitstream from a storage and decode it into audio/video signals.

30 One embodiment of an MPVQ enumeration method is using an inventive combined magnitude and single leading sign bit based enumeration, $N_{PVQ}(l,k) = 2 * N_{MPVQ}(l,k)$, where the MPVQ scheme preferably is using an iterative additive magnitude enumeration, further preferably based on an

established leading sign of the first non-zero element in the remaining vector.

The prior art, IETF/OPUS-codec is using an optimized version of the original
5 Fischer enumeration, with improved row-by-row, direct row offset
calculation recursions, fast exact-integer division through wrapping
multiplication, and also direct non-recursive equation offset and size
calculations (if dimension l and the number of unit pulses k , are low enough
to allow for such direct calculations). See Appendix A for RFC-text
10 description extracts of the IETF/OPUS-Audio PVQ-implementation and
OPUS-c-code references. To reduce the implementation complexity in OPUS,
the maximum index values for a PVQ codeword is restricted to $2^{32}-1$ (an
index value that can be represented in unsigned 32 bit integer arithmetic,
which is a typical format for many desktop computers).

15

In a first part of the presently presented technology a leading sign Modular
PVQ (MPVQ) enumeration using a leading sign approach is described. This
new improved MPVQ enumeration is using the same general techniques (e.g.
row-by-row, direct row offset calculation recursions, exact integer division,
20 and direct non-recursive equation offset and size calculations), but by
employing another recursion scheme. The dynamics of the offset, and size
calculation are reduced, enabling an efficient implementation of short PVQ-
codeword indexing, with double the size (1 bit more) of the number of entries
in a codeword that can be indexed and de-indexed efficiently.

25

This indexing/de-indexing improvement seeks in a particular example to
enable a low complexity assignment procedure for 33 bit indices, extending
the largest possible PVQ that can be used by 1 bit (or alternatively keep it at
1+31 bits, by modifying the enumeration so that one can use signed
30 arithmetic for a 32 bit spanning PVQ).

Define an offset parameter $U(n,k)$ as the number of integer vectors of
dimension n and L1-norm of k , that does not have a leading zero, and does

not have the leading value k , has a leading positive value, and has a positive leading sign. The leading sign is the first sign encountered after the current value in the direction of the recursion.

- 5 Define an offset parameter $A(n,k)$, as the number of integer vectors of dimension n and L1-norm of k , that has a positive leading value and that does not have a leading zero.

It then follows that $A(n,k) = 1 + 2*U(n,k)$. The “1” comes from the single
 10 initial-“ k ” valued vector, and the factor “2” is due to positive and negative sign possibility of the next leading sign. $A(n, k)$ is also equal to the $(N_{PVQ}(n,k-1) + N_{PVQ}(n-1,k-1))/2$, a sum which have been used as an indexing offset in prior art.

- 15 See figure 4 for a tabled structured view of $U(n,k)$ and its relation to the total number of vectors in the $MPVQ(n, k)$ structure with $N_{MPVQ}(n, k)$ vectors. The figure illustrates a high level schematic view of an embodiment of a basic MPVQ-iteration including the preferred Least Significant Bit (LSB) leading sign enumeration variation, using LSB first “interleaving” of the next leading
 20 sign information. In a preferred solution the leading sign interleaving is performed for each $pos[0]$ unique amplitude k_delta , e.g. $k_delta=k-1$ or $k-2$ block. For $pos[0]$ value = “ k ”, all unit pulses are consumed in $pos[0]$ and the iteration can stop. For $pos[0]$ value being non-zero, positive or negative next leading sign, the first encountered non-zero position sign requires 1 bit of
 25 information. This is stored as the LSB bit in the always even sized “ $2*U(n-k)$ ” subsection. For $pos[0]$ value = “ k ”, iteration is extended to $pos[0]$ without any new leading sign info.

The basic indexing/enumeration approach of this first part is described in
 30 the following. The PVQ vector to index/enumerate is known to be in the range $[0...2^{B+1}-1]$ and fits into $B+1$ bits. Here, $B= 32$ bits is typical for current DSP hardware. For instance if one has $PVQ(N,K)$, i.e. dimension N , K unit pulses, the number of indices $N_{PVQ} \leq (2^{B+1}-1)$.

Fig. 5 illustrates a flow diagram of steps of an embodiment of a method for pyramid vector quantization indexing of audio/video samples. The method starts in step 400. In step 402, an integer input vector representing the 5 audio/video signal samples is obtained. The integer input vector has a number of integer-valued coefficients. In step 404, a leading sign is extracted from the integer input vector. The leading sign is a sign of a terminal non-zero coefficient in the integer input vector. The terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in the integer 10 input vector. In step 406, the integer input vector is indexed with a pyramid vector quantization enumeration scheme into an output index, which output index together with the leading sign representing the audio/video signal samples. The pyramid vector quantization enumeration scheme is designed to neglect the sign of said terminal non-zero coefficient. In alternative 15 embodiments, step 406 can be performed concurrently as, in combination with or before step 404. In step 408, the leading sign and the output index are outputted as a first codeword and a second codeword, respectively, into an outgoing bit stream. The procedure ends in step 449.

20 In a particular embodiment, the step of indexing 406 is performed by an iterative enumeration procedure. In a further particular embodiment, the iterative enumeration procedure comprises repetition of an iteration step, in which one current coefficient of the integer input vector is selected for consideration. The iteration step in turn comprises finding of an offset 25 parameter that is associated with all coefficients of said integer input vector processed prior to the current coefficient of the integer input vector and increasing of an accumulated index in dependence of the offset parameter. The repetition is continued with coefficients of the integer input vector being selected one after the other as the current coefficient at least until all 30 coefficients in the integer input vector has been considered. The iterative enumeration procedure comprises a terminating step in which the output index is set equal to the accumulated index after all iteration steps have been ended.

Fig. 6 illustrates an embodiment of a MPVQ indexing on a general level. Detailed block diagrams implementing the sending side aspects of MPVQ-indexing are following below. The MPVQ indexing process starts in step 200, in step 210, the VQ dimension N and number of unit pulses K is achieved from the codec bit allocation loop. In step 220, the PVQ vector "PVQ-vec" is achieved from the PVQ search. In step 230, the MPVQ index is composed by finding the leading sign bit and MPVQ size. The leading sign is in step 240 sent to the bit stream and the index is in step 245 sent to the bit stream. The procedure is exited in step 249.

In comparison with the flow diagram of Fig. 5, steps 210 and 220 can be considered as being comprised in the step 402. Steps 404 and 406 are similarly considered to be comprised in step 230. Finally, the steps 240 and 250 are considered to be comprised in step 408.

Fig. 7A-B illustrate an embodiment of MPVQ-index composition, and is e.g. provided as step 230 of Fig. 6. In Fig. 7A-B, the composition of the MPVQ index and the finding of the leading sign and MPVQ size starts in step 300. This embodiment is based on a solution with a next sign of the vector in a LSB position. In step 302, the process is initialized by a known offset iteration base case. In step 304, the current position parameter is set. The indexing is in this embodiment run from the end of the vector towards the beginning. The indexing is run in reverse position order compared to deindexing, see further below. This means that when increasing the accumulated index in each iteration step as caused by a leading sign, the accumulated index is given a least significant bit in dependence of a previous leading sign in the integer input vector.

In alternative embodiments, the vector position order can be changed between the indexing and de-indexing.

In step 306, an accumulated index is initiated to zero. The parameter k_acc denotes the accumulated unit pulses that are analyzed, and is initiated to zero. The flag got_sign_flag , indicating whether or not a sign is extracted, and is initially also set to zero. In step 308, a current coefficient “ $vec(pos)$ ”
5 from the vector is considered as a parameter “ val ”. In step 310, if a first sign has been found and the current coefficient is not equal to zero, the process continues to step 312, otherwise, the process continues directly to step 314. In step 312, a saved leading sign information from a previous step is put in a LSB. A negative sign in a previous step corresponds to the value
10 $next_sign_ind=1$ and a positive sign corresponds to the value $next_sign_ind=0$. In step 314, the search for the present sign begins. If the value is equal to zero, no new sign is present and the last sign should be forwarded, which means that the process continues directly to step 324 (of Fig. 7B). If the current coefficient is not zero, first the flag that a sign has
15 been found is set in step 316. This is really only necessary for the first sign, but in the present embodiment, to simplify the flow, the flag is set every time a non-zero value is found. In step 318, the $next_sign_ind$, i.e. the indicator of the next sign is set to indicate a positive sign. In step 320, it is checked whether the value of the current coefficient really is positive. If it is found to
20 be like that, the flow continues to step 324, otherwise, the $next_sign_ind$, i.e. the indicator of the next sign is changed to indicate a negative sign.

In step 324, the accumulated index is increased in accordance with an offset value based on the present dimension n and the accumulated unit pulses
25 that are analyzed. In other words, the accumulated index is counted up a number that corresponds to the number of integer vectors of dimension n and L1-norm of k_acc , that has a positive leading value and that does not have a leading zero. In the present embodiment, the A offset is used for modification of the accumulated index. As will be discussed further below,
30 in other embodiments, the U offset can be used instead, or a combination of A and U offsets can be used. In step 326, the k_acc parameter is then updated by adding the value of current coefficient. If not all positions in the vector has been considered, i.e. the parameter “ pos ” is larger than zero, and

a next repetition is prepared. In step 330, the dimension is increased, and the offsets are updated, as will be discussed more in detail further below. In step 332, the position of the current coefficient is reduced one step. The process then returns to step 308 (Fig. 7A) for another repetition with a new
5 current coefficient from the integer input vector to be considered.

If all positions in the vector has been considered, the flow continues to step 334, where the leading sign is set equal to the current next sign indication. In other words, the very first sign in the vector has not been included in the
10 accumulated index and is extracted as a separate parameter which do not influence the rest of the indexing. This means that the pyramid vector quantization enumeration scheme that is used neglects the sign of the first non-zero coefficient. Instead, this sign is “pushed” out from the indexing process and is denoted as the “leading sign” or “lead_sign”. The other signs
15 are typically also extracted during the iteration but will also influence the index accumulation. Finally in step 336, the MPVQ size is calculated, which in the present embodiment can be performed in two different ways. The accumulated index is exiting this procedure as the output index of the MPVQ pyramid vector quantization enumeration scheme. The procedure ends in step
20 349.

The above structure operates to shift all the signs of the non-zero vector values to be coded one step, to the next, in a selected direction, non-zero coefficient. If there is no next position, i.e. the process is outside the original
25 vector, store that sign as the remaining lead_sign. This sign shifting can be done as a separate preprocessing step, as can be seen further below, or in a preferred embodiment inside the overall dimension iteration loop, as above. The lead_sign (+1 or -1) can now be transmitted as a separate bit in the bit stream, as lead_sign_ind (0 or 1).

30

The remaining shifted signs and the amplitudes of the original vector are encoded with a modified indexing/enumeration scheme that use the fact that always exactly one sign has been extracted/shifted out from the

original PVQ-vector. This extraction is independent of the number of non-zero elements in the original PVQ-target vector PVQ-vec.

Three examples are described here below, in order to support the understanding of the structure of Figs. 7A and 7B. The examples are of an extremely low complexity in order to keep the description limited and to make the total example perceivable. However, in typical real examples, the dimensions and the number of unit pulses are far higher. The principles are however the same.

10

In a first example, having a dimension $N=3$ and number of unit pulses $K=5$, consider an integer input vector of $[2, 2, -1]$. The initializing is performed and “pos” is set to “2”, index, k_acc to “0”, dimension $n=1$, and the got_sign_flag is unset ($=0$). The first value “val” is selected as coefficient 2 of the vector, i.e. -1. (The coefficients of the vector are numbered: 0, 1, and 2.) Since no non-zero value has been evaluated yet, no sign has been extracted, and the flow skips the adjustment of the index based on detected signs. The flow thereby passes directly to the evaluation of the value “val”, which is not identical to zero. This trigs the sign flag to be set. A first sign has been detected, and next_sign_ind is set according to the detected sign, in this case next_sign_ind=1, i.e. a negative value (-1). The accumulated index is then counted up by an offset $A(1,0)$, which corresponds to the number of integer vectors of dimension 1 and L1-norm of 0, that has a positive leading value and that does not have a leading zero. $A(1,0)$ is equal to 0. The accumulated index is now index=0. The accumulated k-parameter k_acc is then updated by the absolute value of “val”, i.e. by 1 unit, i.e. k_acc=1.

A next repetition is prepared by increasing the number n by 1, i.e. $n=2$, and decreasing the position indicator “pos” by 1, e.g. pos=1. The flow returns to step 308 and a new value of position 1 is selected, i.e. val=vec(1)=2 in our example. The sign flag “got_sign_flag” indicates that a sign is detected and since the present value “val” is not equal to zero, the “next_sign_ind” is added to the accumulated index “index” as a LSB, giving an accumulated

30

index of 1 ($=2*0+1$). The flow continues to the evaluation of the value “val”, which is again not identical to zero. The next_sign_ind is set according to the detected sign, in this case next_sign_ind=0, i.e. a positive value (2). The accumulated index is then counted up by an offset $A(2,1)$, which
 5 corresponds to the number of integer vectors of dimension 2 and L1-norm of 1, that has a positive leading value and that does not have a leading zero. $A(2,1)$ is equal to 1. The accumulated index is now index=2. The accumulated k-parameter k_acc is then updated by the absolute value of vec(1), i.e. by 2 units, i.e. k_acc=3.

10

A next repetition is prepared by increasing the number n by 1, i.e. n=3, and decreasing the position indicator “pos” by 1, e.g. pos=0. The flow returns to step 308 and a new value of position 0 is selected, i.e. val=vec(0)=2 in our example. The sign flag “got_sign_flag” indicates that a sign is detected and
 15 since the present value “val” is not equal to zero, the “next_sign_ind” is added to the accumulated index “index” as a LSB, giving an accumulated index of 4 ($=2*2+0$). The flow continues to the evaluation of the value “val”, which is again not identical to zero. The next_sign_ind is set according to the detected sign, in this case next_sign_ind=0, i.e. a positive value (2). The
 20 accumulated index is then counted up by an offset $A(3,3)$, which corresponds to the number of integer vectors of dimension 3 and L1-norm of 3, that has a positive leading value and that does not have a leading zero. $A(3,3)$ is equal to 13. The accumulated index is now index=17. The accumulated k-parameter k_acc is then updated by the absolute value of
 25 “val”, i.e. by 2 units, i.e. k_acc=5.

The accumulated k_acc is now equal to the maximum $K=5$, and all positions of the vector are considered. The output index is therefore equal to the present accumulated index, i.e. output index 17. The last identified sign is
 30 still not included in the accumulated index and is instead extracted as a separate parameter, i.e. leading sign = “+1” (next_sign_ind=0).

In a second example, having a dimension $N=3$ and number of unit pulses $K=5$, consider an integer input vector of $[-4,0,-1]$. The initializing is performed and “pos” is set to “2”, index, k_acc to “0”, dimension $n=1$, and the `got_sign_flag` is unset ($=0$). The first value “val” is selected as coefficient
 5 2 of the vector, i.e. -1. Since no non-zero value has been evaluated yet, no sign has been extracted, and the flow skips the adjustment of the index based on detected signs. The flow thereby passes directly to the evaluation of the value “val”, which is not identical to zero. This trigs the sign flag to be set. A first sign has been detected, and `next_sign_ind` is set according to the
 10 detected sign, in this case `next_sign_ind=1`, i.e. a negative value (-1). The accumulated index is then counted up by an offset $A(1,0)$, which corresponds to the number of integer vectors of dimension 1 and L1-norm of 0, that has a positive leading value and that does not have a leading zero. $A(1,0)$ is equal to 0. The accumulated index is now $index=0$. The
 15 accumulated k -parameter k_acc is then updated by the absolute value of “val”, i.e. by 1 unit, i.e. $k_acc=1$.

A next repetition is prepared by increasing the number n by 1, i.e. $n=2$, and decreasing the position indicator “pos” by 1, e.g. $pos=1$. The flow returns to
 20 step 308 and a new value of position 1 is selected, i.e. $val=vec(1)=0$ in our example. The sign flag “`got_sign_flag`” indicates that a sign is detected but since the present value “val” is equal to zero, the “`next_sign_ind`” is saved for the next repetition. The flow continues to the evaluation of the value “val”, which is identical to zero. The `next_sign_ind` is therefore not changed. The
 25 accumulated index is then counted up by an offset $A(2,1)$, which corresponds to the number of integer vectors of dimension 2 and L1-norm of 1, that has a positive leading value and that does not have a leading zero. $A(2,1)$ is equal to 1. The accumulated index is now $index=1$. The accumulated k -parameter k_acc is then updated by the absolute value of
 30 “val”, i.e. by 0 units, i.e. still $k_acc=1$.

A next repetition is prepared by increasing the number n by 1, i.e. $n=3$, and decreasing the position indicator “pos” by 1, e.g. $pos=0$. The flow returns to

step 308 and a new value of position 0 is selected, i.e. $val = vec(0) = -4$ in our example. The sign flag “got_sign_flag” indicates that a sign is detected and since the present value “val” is not equal to zero, the “next_sign_ind”, emanating from vector position 2, is added to the accumulated index “index”
 5 as a LSB, giving an accumulated index of 3 ($=2*1+1$). The flow continues to the evaluation of the value “val”, which is not identical to zero. The next_sign_ind is set according to the detected sign, in this case next_sign_ind=1, i.e. a negative value (-4). The accumulated index is then counted up by an offset $A(3,1)$, which corresponds to the number of integer
 10 vectors of dimension 3 and L1-norm of 1, that has a positive leading value and that does not have a leading zero. $A(3,1)$ is equal to 1. The accumulated index is now index=4. The accumulated k-parameter k_acc is then updated by the absolute value of “val”, i.e. by 4 units, i.e. k_acc=5.

15 The accumulated k_acc is now equal to the maximum $K=5$, and all positions of the vector are considered. The output index is therefore equal to the present accumulated index, i.e. output index 4. The last identified sign is still not included in the accumulated index and is instead extracted as a separate parameter, i.e. leading sign = “-1” (next_sign_ind=1).

20

In a third example, having a dimension $N=3$ and number of unit pulses $K=5$, consider an integer input vector of $[0,5,0]$. The initializing is performed and “pos” is set to “2”, index, k_acc to “0”, dimension $n=1$, and the got_sign_flag is unset ($=0$). The first value “val” is selected as coefficient 2 of the vector,
 25 i.e. 0. Since no non-zero value has been evaluated yet, no sign has been extracted, and the flow skips the adjustment of the index based on detected signs. The flow thereby passes directly to the evaluation of the value “val”, which is identical to zero. This skips the triggering of the sign flag. A first sign has thus yet not been detected. The accumulated index is then counted up
 30 by an offset $A(1,0)$, which corresponds to the number of integer vectors of dimension 1 and L1-norm of 0, that has a positive leading value and that does not have a leading zero. $A(1,0)$ is equal to 0. The accumulated index is

now $\text{index}=0$. The accumulated k-parameter k_{acc} is then updated by the absolute value of “val”, i.e. by 0 units, i.e. still $k_{\text{acc}}=0$.

A next repetition is prepared by increasing the number n by 1, i.e. $n=2$, and
 5 decreasing the position indicator “pos” by 1, e.g. $\text{pos}=1$. The flow returns to step 308 and a new value of position 1 is selected, i.e. $\text{val}=\text{vec}(1)=5$ in our example. The sign flag “got_sign_flag” indicates that a sign is not yet detected. The flow thereby passes directly to the evaluation of the value “val”, which is not identical to zero. This trigs the sign flag to be set. A first
 10 sign has now been detected, and next_sign_ind is set according to the detected sign, in this case $\text{next_sign_ind}=0$, i.e. a positive value (5). The accumulated index is then counted up by an offset $A(2,0)$, which corresponds to the number of integer vectors of dimension 2 and L1-norm of 0, that has a positive leading value and that does not have a leading zero.
 15 $A(2,0)$ is equal to 0. The accumulated index is now still $\text{index}=0$. The accumulated k-parameter k_{acc} is then updated by the absolute value of “val”, i.e. by 5 units, i.e. $k_{\text{acc}}=5$.

A next repetition is prepared by increasing the number n by 1, i.e. $n=3$, and
 20 decreasing the position indicator “pos” by 1, e.g. $\text{pos}=0$. The flow returns to step 308 and a new value of position 0 is selected, i.e. $\text{val}=\text{vec}(0)=0$ in our example. The sign flag “got_sign_flag” indicates that a sign is detected but since the present value “val” is equal to zero, the “next_sign_ind” is saved for the next repetition, or in this example the final step. The flow continues to
 25 the evaluation of the value “val”, which is identical to zero. The next_sign_ind is therefore unchanged. The accumulated index is then counted up by an offset $A(3,5)$, which corresponds to the number of integer vectors of dimension 3 and L1-norm of 5, that has a positive leading value and that does not have a leading zero. $A(3,5)$ is equal to 41. The
 30 accumulated index is now $\text{index}=41$. The accumulated k-parameter k_{acc} is then updated by the absolute value of “val”, i.e. by 0 units, i.e. still $k_{\text{acc}}=5$.

The accumulated k_acc is now equal to the maximum $K=5$, and all positions of the vector have been considered. The output index is therefore equal to the present accumulated index, i.e. output index 41. The last identified sign is still not included in the accumulated index and is instead extracted as a
 5 separate parameter, i.e. leading sign = "+1" (next_sign_ind=0).

In Fig. 8, a high level schematic view of an embodiment of a basic MPVQ iteration instead using a sectioned leading sign encoding is illustrated. The figure illustrates a high level schematic view of an embodiment of a basic
 10 MPVQ-iteration using sectioned partitioning of the leading sign information. In a preferred solution, the two sign sections are implemented for each unique $pos[0]$ amplitude k_delta , e.g. $k_delta = [k-1, k-2, \dots, 1]$. For $pos[0]$ value = "k", all unit pulses are consumed in $pos[0]$ and the iteration can stop. For $pos[0]$ value being non-zero, positive next leading sign, the first
 15 encountered non-zero position sign requires 1 bit of information. For $pos[0]$ value being non-zero, negative next leading sign, the first encountered non-zero position sign requires 1 bit of information. For $pos[0]$ value = "0", iteration is extended to $pos[0]$ without requiring any new leading sign info.

20 From the iteration definition above, one can establish that:

$$M(n,k) = 1 + U(n,k) + U(n,k) + M(n-1,k) = 1 + 2 * U(n,k) + M(n-1,k)$$

$$M(n,k) - M(n-1,k) = 1 + 2 * U(n,k)$$

25 By applying Fischer's PVQ recursion, one obtains:

$$M(n,k) - M(n-1,k) = M(n-1,k-1) + M(n,k-1)$$

$$1 + 2 * U(n,k) = M(n-1,k-1) + M(n,k-1) - M(n-1,k-1) + M(n-1,k-1)$$

$$1 + 2 * U(n,k) = 1 + 2 * U(n,k-1) + 2 * M(n-1,k-1)$$

$$30 \quad U(n,k) = U(n,k-1) + M(n-1,k-1)$$

$$M(n-1,k-1) = U(n,k) - U(n,k-1)$$

leading to

$$M(n-1,k)=[U(n,k+1)-U(n,k)]$$

From the recursion definition is known:

5

$$M(n,k)=1+2*U(n,k)+[U(n,k+1)-U(n,k)] = 1 + U(n,k)+U(n,k+1)$$

MPVQ-size can now be determined recursively as:

10
$$N_{MPVQ}(n,k) = M(n,k) = 1 + U(n, k) + U(n,k+1).$$

See further Appendix B for the derivation of the employed MPVQ recursion formula.

15
$$N_{MPVQ}(n,k) = 1 + 2*U(n, k) + N_{MPVQ}(n-1,k)$$

In the enumeration/indexing use any of the below defined properties (a-g) that:

- a) $N_{PVQ}(n, k) = 2*N_{MPVQ}(n, k)$,
 20 (recursively applied for efficient indexing);
- b) $U(n,k) = 1 + U(n, k-1) + U(n-1, k-1) + U(n-1, k)$,
 with initial conditions $U(0,*) = 0$, $U(*,0) = 0$, $U(1,*) = 0$, $U(*,1) = 0$,
 and $U(a, b) = U(b, a)$, and further for efficiency one can use
 $U(2,k) = k-1$, and $U(n,2)=n-1$, and $U(3,k) = k*(k-1)$, and $U(n,3)=n(n-1)$;
- 25 c) $N_{MPVQ}(n,k) = 1 + U(n, k) + U(n, k+1)$,
 (final MPVQ-size calculation)
- d) $N_{MPVQ}(n,k) = 1 + \text{floor}((A(n,k))/2) + U(n, k+1)$,
 (alternative final size calculation)
- e) $N_{MPVQ}(n,k) - N_{MPVQ}(n-1,k) = 1 + 2*U(n, k) = A(n, k)$,
 30 (can be used for iterative amplitude index addition determination)
- f) $A(n,k) = A(n, k-1) + A(n-1, k-1) + A(n-1, k)$,
 (this recursion, also used in e.g. CELT/OPUS-audio, can also be used
 here for low complexity amplitude indexing offset updates)

g) Iteratively update the PVQ-offsets = $U(n, k=0 \dots K+1)$ or preferably iteratively update: $A(n, k=0 \dots K)$ and $U(n, K+1)$. $A(n, k)$ recursion is slightly faster than $U(n, k)$ recursion and the last element $U(n, K+1)$ has lower dynamic range than $A(n, K+1)$.

5

Here the c) and d) are used to calculate the size the final MPVQ(n, k) codeword, which is needed to obtain the index from the bit-stream, or which is provided to the bitstream or the arithmetic encoder/decoder which is interfacing the bit stream.

10

Fig. 9 illustrates a combination of three embodiments of a MPVQ-A/U offset recursion for increasing dimension.

The procedure for updating offsets starts in step 350. The input parameters are the dimension n and the $k_{\max}+1$ value. This procedure provides indexing offsets of a row $n-1$ to indexing offsets of row n , including updating of offsets for k 's of $0 \dots (k_{\max}+1)$. In step 352, it is decided whether or not only A offsets are to be used. If that is the case, in the step 354, $A(n, k)$ is calculated as:

$$A(n, k) = A(n-1, k) + A(n-1, k-1) + A(n, k-1).$$

This particular recursion is utilized also in prior art, but together with less efficient PVQ indexing processes. The $A(n, k)$ is returned in step 397. In step 356, it is decided whether or not only U offsets are to be used. If that is the case, in step 358, $U(n, k)$ is calculated as:

$$U(n, k) = 1 + U(n-1, k-1) + U(n-1, k) + U(n, k-1).$$

The $U(n, k)$ is returned in step 398. In step 360, a combination of A and U offsets are to be used. In step 362, recursions for $k=0 \dots (k_{\max})$ are performed according to:

$$A(n, k) = A(n-1, k) + A(n-1, k-1) + A(n, k-1).$$

This particular recursion is utilized also in prior art, but together with less efficient PVQ indexing processes. For the highest dynamics offset ($k_{\max}+1$), recursions are performed in step 364. In one particular embodiment, a pure U recursion is used according to:

$$U(n, k_{\max}+1) = 1 + U(n-1, k_{\max}) + U(n-1, k_{\max}+1) + U(n, k_{\max}).$$

In another particular embodiment, a mixed A/U recursion is used according to:

$$U(n, k_{\max}+1) = 1 + (A(n-1, k_{\max}) \gg 1) + (A(n, k_{\max}) \gg 1) + U(n-1, k_{\max}+1),$$

where $(y \gg 1)$ signifies $y = \text{floor}(y/2)$. The $A(n, k)$ and $U(n, k_{\max}+1)$ are returned in step 399.

At the receiver side, an opposite procedure has to be performed, in which a leading sign and an index is transformed into an integer output vector. Fig. 10 illustrates a flow diagram of steps of an embodiment of a method for pyramid vector quantization deindexing of audio/video samples. The method starts in step 450. In step 452, a leading sign as a first codeword and an input index as a second codeword are received from an ingoing bit stream. The leading sign and the input index represent audio/video signal samples. The leading sign is a sign of a terminal non-zero coefficient in an integer output vector to be created, representing the audio/video signal samples. The integer output vector has a number of integer-valued coefficients. The terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in said integer output vector. In step 454, the input index is deindexed into the integer output vector with a pyramid vector quantization de-enumeration scheme. The input index being created by an enumeration scheme is neglecting the sign of the terminal non-zero coefficient. In step 456, a sign of the terminal non-zero coefficient in the integer output vector is assigned according to the received leading sign. In alternative embodiments, step 456 can be performed concurrently as, in combination with or before step 454. In step 458, the integer output vector is output. The process ends in step 499.

In a particular embodiment, the step of deindexing 454 is performed by an iterative de-enumeration procedure. In a further particular embodiment, the iterative de-enumeration procedure comprises an initializing step, in which a remaining index is set equal to the input index, and a repetition of an iteration

step, in which one current coefficient of the integer output vector is selected for consideration. The iteration step in turn comprises finding of an offset parameter being compatible with a position of the current coefficient within the integer output vector and with the remaining index, reducing of the
5 remaining index in dependence of the offset parameter, and setting of an amplitude of the current coefficient of the integer input vector to be equal to an amplitude associated with the offset parameter. The repetition is continued with coefficients of the integer input vector being selected one after the other as the current coefficient at least until the remaining index becomes equal to
10 zero.

Some receiver side aspects of MPVQ-deindexing are illustrated in the following using detailed block diagrams implementing embodiments of the processes. An overview of an embodiment of MPVQ deindexing is illustrated
15 in Fig. 11. The MPVQ deindexing starts in step 250. In step 260, VQ dimensions N and the number of unit pulses K are achieved from the codec bit allocation loop. In step 270, a size and offsets are found. In step 280, a leading sign is extracted from the incoming bit stream and in step 285, the MPVQ index is obtained from the incoming bit stream. These quantities are
20 utilized in step 290, where the MPVQ index is decomposed. The process ends in step 299.

In comparison with the flow diagram of Fig. 10, steps 260, 270, 280 and 285 can be considered as being comprised in the step 452. Steps 454 and 456
25 are similarly considered to be comprised in step 290.

An embodiment of the procedures to find size and offsets, e.g. corresponding to step 270 of Fig. 11 is illustrated in Fig. 12. The $A(n,k)$ offset in deindexing is typically an amplitude offset, but it also accounts for the remaining signs.
30 The $U(n,k)$ offset is similar. It is also an amplitude offset. However, it does not include the first leading sign (the “2”), but all the rest of the remaining leading signs are included. The offsets in general indicate the section sizes for the remaining possible combinations of amplitudes and leading signs.

Sometimes this is performed with the current leading sign ($A(n,k)$) and sometimes without the next leading sign, but all the rest ($U(n,k)$ case). The procedure to find the MPVQ size $N_{MPVQ}(N,K)$ and the indexing offsets A , U for dimension N from $k=0$ to $k=K+1$ starts in step 500. Note that direct equations of $A(n,k)$, $A(n,k)$ row-only recursion and A basic recursion is known as such in prior art. In step 502, it is checked whether or not size and offsets are stored in ROM tables. If so, which may be realistic if both N , and K are low, the procedure continues directly with step 519. In step 504, it is checked whether or not an efficient direct calculation is possible. If so, which may be realistic for low N , the process continues to step 506, in which direct equations are used for MPVQ size (N,K) and amplitude offsets $A(N,K)$. The procedure then continues to step 519. In step 508, it is checked whether or not an efficient row recursion is possible. If so, which may be realistic for some K 's, the process continues to step 510, in which recursive row-only equations are used for row N to calculate $A(N, k=0...K)$ and $U(N,K+1)$. The procedure then continues to step 514. If it in step 508 is found that row-only recursion is not feasible, the procedure continues to step 512, in which an offset update process is used for a basic column and row offset recursion equation for row 0 to row N to calculate offsets as $A(N, k=0...K)$ and $U(N,K+1)$. This is possible for all N and K . One example of such an update offset routine can be found in e.g. Fig. 9. In step 514, the MPVQ size can be calculated as $MPVQ\text{-size}=1+(A(N,K)>>1)+U(N,K+1)$ or alternatively as $MPVQ\text{-size}=1+U(N,K)+U(N,K+1)$. In step 519, the procedure is ended by returning offsets (A , U) and MPVQ size.

25

Fig. 13 illustrates an embodiment of MPVQ index decomposition. The procedure for decomposing an MPVQ index starts in step 520. The parameters N , K , the input index and leading sign as well as offset values are provided. A remaining index is set equal to the input index. In step 522, the output vector "vec" is initialized with zeros. In step 524, the local maximum k , k_max_local is set equal to K , the position in the vector starts from 0 and n is set to N . In step 526, it is investigated if all positions in the vector are considered. If so, the vector is returned as the output vector in

30

step 548, i.e. an exit after the last position is treated. In step 528, it is investigated if the remaining index is zero. If so, no more vector positions are to be filled with non-zero values. The procedure continues to step 530, in which the leading sign is incorporated into and the vector is returned as the
5 output vector in step 549, i.e. a fast early exit before the last position has been treated. If the remaining index is larger than zero, the procedure continues to step 532, in which a k_delta , i.e. an absolute amplitude of the vector position under investigation, and an amplitude offset “amp_offset” is found. This will be described more in detail further below. In step 534, the
10 remaining index is reduced by the amplitude offset. If the amplitude of the vector position is not zero, as investigated in step 536, the procedure continues to step 538, where the vector position is given a value equal to the amplitude multiplied with the leading sign. For the first non-zero coefficient, the leading sign is the leading sign extracted from the bit stream. In step
15 540, a next leading sign for a future position is deduced. This is described more in detail further below. In step 542, the local maximum k value is reduced with the current k value “ k_delta ”. A next repetition is then prepared in step 544 by increasing the dimension n , by updating the offsets and by increasing the position in the vector by one step. The procedure then
20 returns to step 526.

As indicated in Fig. 13, from the received index, the amplitude ‘ k_delta ’ of the current position is determined. This is preferably performed by using available $A(n,k)$ offsets and/or $U(n,k)$ offsets. The amplitude information
25 offset is also deduced and the remaining index is reduced by this amplitude information offset ‘amp_offset’. One embodiment of such a procedure is illustrated in Fig. 14.

An embodiment of a procedure for finding the amplitude k_delta and the
30 amplitude offset amp_offset starts in step 550. In other words, this procedure is supposed to find the amplitude of the current position and the corresponding index offset. Linear or tree searches using offsets of $A(n,k)$ are, as such, available in prior art. The ingoing parameters are the local

maximum k “k_max_local”, the index and the offsets $H(n,k)=A(n,k)$. In step 552, a tree or linear search is selected. For the linear search option, step 554 sets an accumulated k value, k_acc, equal to the local maximum k and an amplitude offset is set equal to an offset for the present n and the accumulated k value. In step 556, it is checked whether or not the offset is larger than the index. If this is the case, in step 558 the k_acc value is reduced by one unit, a new amplitude offset is derived. The procedure then returns to step 556. This is repeated until the largest amplitude offset value less than or equal to the remaining index is found. The procedure then continues to step 560, in which the k_delta, i.e. the amplitude of the current position is calculated as the local maximum k value reduced by the k_acc value.

If a tree procedure is selected, in step 562, a high and a low parameter are defined and an amplitude offset for n and the high parameter is deduced. The k region to search is divided into two parts in step 564 with a k_test parameter and an amplitude offset for n and the high parameter is deduced. Depending on if the amplitude offset is larger or smaller than the index, as decided in step 566, The high parameter is changed, in step 568, or the low parameter is changed, in step 572. This is repeated until either the difference between the amplitude offset and the index becomes zero or the k_test point becomes equal to the high parameter, as checked in steps 570 and 574, respectively. In step 576, the k_delta, i.e. the amplitude of the current position is calculated as the local maximum k value reduced by the k_test value. The amplitude k_delta, k_acc and amp_offset, where $k_acc=k_max_local-k_delta$ is used for sectioned sign coding, are returned in step 579.

In Fig. 13, in step 536, if the magnitude is non-zero and less than the maximum remaining K unit pulses value, the previously extracted (stored) leading sign is applied in step 538, to the current position amplitude. Subsequently the next leading sign is to be extracted from the decomposed received MPVQ-index. One embodiment of a procedure for finding the next

leading sign and removing the extracted sign information (bit or sign_offset) from the index is illustrated in Fig. 15.

The procedure for getting a next leading sign starts in step 580. The input parameters are the remaining index, the offsets and the accumulated k value k_acc. In step 582, the sign positioning method is selected. If the LSB approach is selected, which presently is believed to be the preferred embodiment, the leading sign is initially set to be positive (+1) in step 584. In step 586 the least significant bit in index is determined, using a bitwise 'and' operation. If the bit is a "1", this signifies a negative sign and the leading sign is consequently changed to "-1" in step 588. In step 590, the index is shifted one position, i.e. shifting out the sign bit.

If a sectioned leading sign decoding is selected, which is a little bit more complex, the leading sign is initially set to be positive (1) in step 592. In step 594, the size of the k_delta segment is divided by 2. If the index is larger than or equal to this sign offset, the sign is negative and the leading sign is consequently changed in step 597. In step 598, the index is also reduced by the found sign offset. The leading sign and modified index are returned in step 599.

Returning again to Fig. 13, if the current position has zero amplitude, the leading sign is kept, i.e. remembered for potential use in the next position after the current position.

25

If the magnitude equals the maximum remaining K unit pulses value, the stored leading sign is applied. Optionally a fast iteration exit can be used for this last non-zero entry, and exit early with a series of trailing zeroes. This is optional as sometimes in DSP-HW the cost of conditionally exiting an optimized constant length loop is higher than staying in the loop.

30

The offsets $A(n,k)$ (or $U(n,k)$) can be updated recursively for the remaining vector, with one dimension less to de-index and 'k_delta' less unit pulses to

de-index. One embodiment of a procedure for offset updating for one dimension less is illustrated in Fig. 16. The procedure is similar to the one presented in Fig. 9, but here, the dimension is reduced instead of increased.

5 The procedure for updating offsets starts in step 600. The input parameters are the dimension n and the k_max value. This procedure provides indexing offsets of a row $n+1$ to indexing offsets of row n , including updating of offsets for k 's of $0 \dots k_max$. In step 602, it is decided whether or not only A offsets are to be used. If that is the case, in the step 604, $A(n,k)$ is calculated
10 as:

$$A(n,k)=A(n+1,k)-A(n,k-1)-A(n+1,k-1).$$

This particular recursion is utilized also in prior art, but together with less efficient PVQ indexing processes. The $A(n,k)$ is returned in step 617. In step 606, it is decided whether or not only U offsets are to be used. If that is the
15 case, in step 608, $U(n,k)$ is calculated as:

$$U(n,k)=U(n+1,k)-U(n,k-1)-U(n+1,k-1)-1.$$

The $U(n,k)$ is returned in step 618. In step 610, a combination of A and U offsets are to be used. In step 612, recursions for $k=0 \dots (k_max-1)$ are performed according to:

20
$$A(n,k)=A(n+1,k)-A(n,k-1)-A(n+1,k-1).$$

This particular recursion is utilized also in prior art, but together with less efficient PVQ indexing processes. For the highest dynamics offset k_max , where $k_max=K+1$, recursions are performed in step 614. In one particular embodiment, a pure U recursion is used according to:

25
$$U(n,k_max)=U(n+1,k_max)-U(n,k_max-1)-U(n+1,k_max-1)-1.$$

In another particular embodiment, a mixed A/U recursion is used according to:

$$U(n,k_max)=U(n+1,k_max)-(A(n,k_max-1)>>1)-(A(n+1,k_max-1)>>1)-1,$$

where $(y>>1)$ signifies $y=\text{floor}(y/2)$. The $A(n,k)$ and $U(n,k_max)$ are returned
30 in step 619.

Three examples are described here below, in order to support the understanding of the structure of Fig 13. The examples are of an extremely

low complexity in order to keep the description limited and to make the total example perceivable. However, in typical real examples, the dimensions and the number of unit pulses are far higher. The principles are however the same.

5

In a first example, having a dimension $N=3$ and number of unit pulses $K=5$, consider an input index of 17 and a leading sign "+1", i.e. positive. The initializing is performed and "pos" is set to "0", i.e. the de-indexing starts from the first coefficient in the vector, k_max_local to "5", and dimension
 10 $n=3$. The input index is "renamed" into a remaining index. The position is lower than 3 and the remaining index is non-zero. An amplitude k_delta and offset amp_offset is searched (e.g. according to Fig. 14). If e.g. the A offsets are used, the group of offsets $A(3,0...5)$ are investigated and the largest A offset that still is smaller than or equal to the remaining index is $A(3,3)=13$.
 15 k_acc therefore becomes 3, k_delta becomes 2 and amp_offset equals 13. The remaining index is reduced by the amp_offset and becomes now equal to 4. Since k_delta is not equal to zero, there is a sign to be applied. The vector position is therefore set to the absolute value (k_delta) times the received and stored leading sign, which was positive. The output vector is
 20 now $[2,0,0]$. A determination of a next leading sign is then performed, e.g. according to Fig. 15. If assuming an LSB sign positioning, the LSB of the remaining index (4) is zero, which corresponds to a positive sign. The lead_sign is therefore set to "+1". The remaining index is also reduced by shifting the index one step, i.e. equal to an integer division by 2. The
 25 remaining index is now equal to 2. Finally, the remaining pulse units k_max_local are updated and is now 3.

A next repetition is prepared by reducing the number n by 1, i.e. $n=2$, and increasing the position indicator "pos" by 1, e.g. $pos=1$. The available offsets
 30 are also updated according to the new n . The flow returns to step 526 and a new amplitude and offset is to be found (e.g. according to Fig. 14). If e.g. the A offsets are used, the group of offsets $A(2,0...3)$ are investigated and the largest A offset that still is smaller than or equal to the remaining index is

A(2,1)=1. k_{acc} therefore becomes 1, k_{delta} becomes 2 and amp_{offset} equals 1. The remaining index is reduced by the amp_{offset} and becomes now equal to 1. Since k_{delta} is not equal to zero, there is a sign to be applied. The vector position is therefore set to the absolute value (k_{delta}) times the recently extracted leading sign, which was positive. The output vector is now [2,2,0]. A determination of a next leading sign is then performed, e.g. according to Fig. 15. If assuming an LSB sign positioning, the LSB of the remaining index (1) is 1, which corresponds to a negative sign. The $lead_sign$ is therefore set to -1. The remaining index is also reduced by shifting the index one step, i.e. equal to an integer division by 2. The remaining index is now equal to 0. Finally, the remaining pulse units k_{max_local} are updated and is now 1.

A next repetition is prepared by reducing the number n by 1, i.e. $n=1$, and increasing the position indicator “pos” by 1, e.g. $pos=2$. The available offsets are also updated according to the new n . The flow returns to step 526. Since the remaining index is zero, the step 530 is performed to give the last vector coefficient. $lead_sign$ is equal to -1 and k_{max_local} is equal to 1, which gives an output vector of [2,2,-1].

20

In a second example, having a dimension $N=3$ and number of unit pulses $K=5$, consider an input index of 4 and a negative leading sign. The initializing is performed and “pos” is set to “0”, i.e. the de-indexing starts from the first coefficient in the vector, k_{max_local} to “5”, and dimension $n=3$. The input index is “renamed” into a remaining index. The position is lower than 3 and the remaining index is non-zero. An amplitude k_{delta} and offset amp_{offset} is searched (e.g. according to Fig. 14). If e.g. the A offsets are used, the group of offsets A(3,0...5) are investigated and the largest A offset that still is smaller than or equal to the remaining index is A(3,1)=1. k_{acc} therefore becomes 1, k_{delta} becomes 4 and amp_{offset} equals 1. The remaining index is reduced by the amp_{offset} and becomes now equal to 3. Since k_{delta} is not equal to zero, there is a sign to be applied. The vector position is therefore set to the absolute value (k_{delta}) times the received

30

leading sign, which was negative. The output vector is now $[-4,0,0]$. A determination of a next leading sign is then performed, e.g. according to Fig. 15. If assuming an LSB sign positioning, the LSB of the remaining index (3) is 1, which corresponds to a negative sign. The lead_sign is therefore set to -
 5 1. The remaining index is also reduced by shifting the index one step, i.e. equal to an integer division by 2. The remaining index is now equal to 2. Finally, the remaining pulse units k_max_local are updated and is now 1.

A next repetition is prepared by reducing the number n by 1, i.e. $n=2$, and
 10 increasing the position indicator "pos" by 1, e.g. $pos=1$. The available offsets are also updated according to the new n . The flow returns to step 526 and a new amplitude and offset is to be found (e.g. according to Fig. 14). If e.g. the A offsets are used, the group of offsets $A(2,0...1)$ are investigated and the largest A offset that still is smaller than the remaining index is $A(2,1)=1$.
 15 k_acc therefore becomes 1, k_delta becomes 0 and amp_offset equals 1. The remaining index is reduced by the amp_offset and becomes now equal to 1. Since k_delta is equal to zero, the last extracted sign is saved for a next repetition. The output vector is still $[-4,0,0]$.

20 A next repetition is prepared by reducing the number n by 1, i.e. $n=1$, and increasing the position indicator "pos" by 1, e.g. $pos=2$. The available offsets are also updated according to the new n . The flow returns to step 526 and a new amplitude and offset is to be found (e.g. according to Fig. 14). If e.g. the A offsets are used, the group of offsets $A(1,0...1)$ are investigated and the
 25 largest A offset that still is smaller than or equal to the remaining index is $A(1,1)=1$. k_acc therefore becomes 1, k_delta becomes 0 and amp_offset equals 1. The remaining index is reduced by the amp_offset and becomes now equal to 0. Since k_delta is not equal to zero, there is a sign to be applied. The vector position is therefore set to the absolute value (k_delta)
 30 times the previously extracted leading sign, which was negative. The final output vector is now $[-4,0,-1]$.

In a third example, having a dimension $N=3$ and number of unit pulses $K=5$, consider an input index of 41 and a positive leading sign. The initializing is performed and “pos” is set to “0”, i.e. the de-indexing starts from the first coefficient in the vector, k_max_local to “5”, and dimension $n=3$. The input index is “renamed” into a remaining index. The position is lower than 3 and the remaining index is non-zero. An amplitude k_delta and offset amp_offset is searched (e.g. according to Fig. 14). If e.g. the A offsets are used, the group of offsets $A(3,0...5)$ are investigated and the largest A offset that still is smaller than or equal to the remaining index is $A(3,5)=41$. k_acc therefore becomes 5, k_delta becomes 0 and amp_offset equals 41. The remaining index is reduced by the amp_offset and becomes now equal to 0. Since k_delta is equal to zero, the sign is saved for a later iteration. The output vector is still [0,0,0].

A next repetition is prepared by reducing the number n by 1, i.e. $n=2$, and increasing the position indicator “pos” by 1, e.g. $pos=1$. The available offsets are also updated according to the new n . The flow returns to step 526 and a new amplitude and offset is to be found (e.g. according to Fig. 14). If e.g. the A offsets are used, the group of offsets $A(2,0...5)$ are investigated and the largest A offset that still is smaller than or equal to the remaining index is $A(2,0)=0$. k_acc therefore becomes 0, k_delta becomes 5 and amp_offset equals 0. The remaining index is reduced by the amp_offset and becomes now equal to 0. Since k_delta is not equal to zero, there is a sign to be applied. The vector position is therefore set to the absolute value (k_delta) times the received and stored leading sign, which was positive. The output vector is now [0,5,0].

A next repetition is prepared by reducing the number n by 1, i.e. $n=1$, and increasing the position indicator “pos” by 1, e.g. $pos=2$. The flow returns to step 526. In step 528, it is found that the index is zero and the fast exit via steps 530 and 549 is used.

This new indexing approach, presented in the present disclosure, is an improved low complex short codeword scheme. In design it is a solution based on the optimized pure magnitude indexing schemes (Fischer/Hung/Opus/CELT) but in addition it makes efficient use of the fact
 5 that the size of any PVQ structure always is an even number of vectors.

There will still be a need to handle very large PVQ-vectors (larger than $1+B$) bits in an efficient way. This can be performed e.g. by target vector dimension splitting, PVQ-vector dimension splitting or costly higher
 10 dynamic range integer calculations, for instance $n \cdot 16$ or $n \cdot 32$ virtual, software defined large integers.

The gain of going from B to $B+1$ bits (e.g. 32 to 33 bits) can be quantified as the extended $R = \text{bits}/\text{coefficient}$ range capability where dimension splitting is
 15 not needed for a given dimension. E.g. for dimension $N=8$, one goes from $R = 32/8 = 4$ bits/coefficient (or sample) to $R = 33/8 = 4.125$ bits per coefficient or sample. Typically $R=7$ shape bits/coefficient (or sample) is required for a high quality frequency domain audio PVQ-scheme.

20 Fig. 17A presents an overview of the PVQ-codewords for some common hardware bit limits. Curve 900 denotes PVQ(n,k) bitlimit 33, curve 901 denotes PVQ(n,k) bitlimit 32, curve 902 denotes PVQ(n,k) bitlimit 31, curve 903 denotes PVQ(n,k) bitlimit 17, curve 904 denotes PVQ(n,k) bitlimit 16, and curve 905 denotes PVQ(n,k) bitlimit 15. 33 bits are possible to use with
 25 new scheme and unsigned 32-bit integers, 32 bits corresponds to unsigned 32-bit integer, 31 bits corresponds to signed 32-bit integers, 17 bits are possible to use with new scheme and unsigned 16-bit integers, 16 bits correspond to unsigned 16-bit integers, 15 bits correspond to signed 16-bit integer.

30

Fig. 17B presents an overview of the related R values in bits/sample for optimal PVQ-codeword quantizers with different BIT limits. Curve 910 denotes PVQ(n,k) bitlimit 33, curve 911 denotes PVQ(n,k) bitlimit 32, curve

912 denotes PVQ(n,k) bitlimit 31, curve 913 denotes PVQ(n,k) bitlimit 17, curve 914 denotes PVQ(n,k) bitlimit 16, and curve 915 denotes PVQ(n,k) bitlimit 15. With higher R values, higher coding quality can be achieved.

5 Fig. 17C shows the corresponding achievable pulse density, which is directly correlated to the resulting shape matching capability of a gain-shape PVQ. Curve 920 denotes PVQ(n,k) bitlimit 33, curve 921 denotes PVQ(n,k) bitlimit 32, curve 922 denotes PVQ(n,k) bitlimit 31, curve 923 denotes PVQ(n,k) bitlimit 17, curve 924 denotes PVQ(n,k) bitlimit 16, and curve 925 denotes
10 PVQ(n,k) bitlimit 15. With higher R values, higher coding quality can be achieved. The possible pulse density for optimal PVQ-codeword quantizers are shown with different BIT-limits. With higher pulse densities higher coding quality, e.g. higher VQ SNR, can be achieved.

15 Fig. 17D illustrates a worst case MOPS Instruction trade-off in indexing/deindexing for a sample prior art scheme PVQ and for the new scheme MPVQ, both using PVQ-codewords of maximum size 32 for a fair comparison. Curve 930 denotes total complexity for MPVQ, curve 931 denotes total complexity for PVQ, curve 932 denotes deindexing complexity
20 for MPVQ, curve 933 denotes deindexing complexity for PVQ, curve 934 denotes indexing complexity for MPVQ, and curve 935 denotes indexing complexity for PVQ. MPVQ above can be implemented on a signed 32-bit architecture, while prior art PVQ requires an unsigned 32-bit architecture.

25 In a second part of the presently presented technology a low dynamic MPVQ runtime calculation of offsets is described. In Appendix A, the high level text description from the OPUS RFC is repeated as background. In the IETF-OPUS c-code (cwrs.c) the dynamically runtime calculated indexing offset $A(n,k)$ is used for both sign and amplitude indexing. Note however, that a
30 different offset variable name is used in OPUS c-code. The number $A(n, k)$ represents the number of vectors PVQ(n,k) that starts with a positive non-zero value in the first position. It has been found in prior art that

$$A(n, k) = (N_{PVQ}(n, k-1) + N_{PVQ}(n-1, k-1))/2,$$

In words, the number A is a weighted sum of a row n element and a previous row n-1 element in the PVQ-size matrix N(n, k).

5

Table 1, for A(n,k), shows an example where the prior art (CELT/OPUS) PVQ offset data scheme used, where for memory efficiency only one row e.g. n=3 is stored in RAM memory, for a given point in the forward recursion, and then n=4 is calculated based on row n=3, and so on.

10

Note that in a real world PVQ implementation for speech and audio coding the dimension n can be around 256 and number of unit pulses k can be around 512, depending on the target DSP capacity. So storing n*k offsets is often not feasible.

15

n/k	0	1	2	3	4	5	k=6
0	1						
1		1	1	1	1	1	1
2		1	3	5	7	9	11
3		1	5	13	25	41	61
4		1	7	25	63	129	231
5		1	9	41	129	321	681
6		1	11	61	231	681	1683

Table 1 Prior art A (n, k) offsets needed for PVQ(n=6, k=5) calculated for PVQ decoding/encoding in e.g. a IETF-OPUS-Audio like indexing scheme

20

The dynamic indexing offset calculations can, however, be improved. The here proposed novel recursion is

$$U(n, k) = U(n, k-1) + U(n-1, k-1) + U(n-1, k) + 1,$$

25

It can be found that it relates to the previously employed, OPUS/CELT prior art offsets $A(n,k)$ as:

$$A(n,k) = 2*U(n,k) + 1.$$

5

The integer range dynamics of $U(n, k)$ is now always at least half of the $A(n,k)$ range. This means that 1 bit extra can be made available for fast indexing, e.g. inside a 32 bit word. Also $U(2,k)$ and $U(3,k)$ can be directly computed faster than for $A(2,k)$ and $A(3,k)$, as $U(2,k)=k-1$, $U(3,k)=k*(k-1)$,
10 and $U(a,b)=U(b,a)$ symmetrically.

n/k	0	1	2	3	4	5	k=6
0							
1							
2			1	2	3	4	5
3			2	6	12	20	30
4			3	12	31	64	115
5			4	20	64	160	340
6			5	30	115	340	841

Table 2 New Low dynamic range $U(n,k)$ indexing offsets,
calculated for MPVQ($n=6,k=5$)

15

In the Tables 1 and 2 above one can see that $A(n=6,k=6)=1683$ cannot fit within 10 bits. 10 bits corresponds to 1024 entries, e.g. values 0-1023. However, the new offset $U(n=6, k=6)$ will fit within 10 bits. As the indexing offsets needs to be exactly calculated for successful exact indexing/de-
20 indexing, offset $A(6,6)$ cannot be allowed to saturate to 1023, or be wrapped to an incorrect low value.

The previous (IETF/OPUS-Audio PVQ-prior art) recursion is

25

$$A(n,k) = A(n,k-1) + A(n-1,k-1) + A(n-1,k).$$

It has three addition terms, making it a slightly faster to calculate, especially for high n or high k compared to the new $U(n,k)$ recursion which has addition of 4 terms.

5

To keep recursion efficiency and maintain a low dynamic range when it is needed one can in another embodiment define a preferred mixed recursion where $U(n, KMAX)$ is a function of previous $A(n, \text{lower } k)$ offset values, and only used for dynamic recursion data that is close to the range limit of a B-
10 bit word. This is typically true for the last column $KMAX$ in a N -row-based recursion. In Table 3 it is seen that the offsets still stays within 10 bits, compared to Table 1, which last entry exceeds 10 bits.

n/k	0(A)	1(A)	2(A)	3(A)	4(A)	5(A)	k=6(U) KMAX
0	1						
1		1	1	1	1	1	0
2		1	3	5	7	9	5
3		1	5	13	25	41	30
4		1	7	25	63	129	115
5		1	9	41	129	321	340
6 NMAX		1	11	61	231	681	841

15 Table 3 mixed $A(n,k)$ and last k column $U(n,6=KMAX)$
offsets calculated for efficient and range safe indexing
recursion.

Note that typically it is the last n -row $NMAX$ (6 in this case) and highest
20 ($k=6$ in this case) that causes dynamic range troubles. However, in some cases also the second last row ($NMAX-1$) may cause range problems, e.g. in row-only recursion calculations, when the numerator in a division is close to the hardware bit limit.

The derivation of the above recursive relations for the MPVQ scheme can be found in Appendix B.

5 An example of a prior art PVQ indexing scheme is presented in Table 4. Here, the maximum index value, $A(n, k) + A(k+1) - 1$, needs to be less than e.g. 232. The scheme in Table 4 with switched signs [{+, 0 } / -] is used in prior art OPUS/CELT. Comments: a) vector [-2,-1,1]; b) Here for indices 25-40, de-indexing a zero in position p0 may eventually become a positive value
10 or a negative value or a zero in p1; c) p0 positive decision limit.

A prior art PVQ-indexing with [{+, 0 } / -] PVQ recursive deindexing scheme PVQ($n=3, k=4$), NPVQ= 66, [{-, 0 } / +] prior art indexing (blue, white) cells pX = position in the 3-dimensional vector [p0 , p1, p2] , $k=4$ unit pulses can
15 be encoded, e.g. decoded index 7 -> vector [-2, -1, 1], offsets $A(n, k)$ are used to determined signs, and the relation $NPVQ(n=3, k=4) = A(n, k) + A(n, k+1)$ is used to determine the size from these offsets.

ind		p0					p1		p2	Com.
0		-4				$A(n, k-3)$	0		0	
1		-3			$A(n, k-2)$		1		0	
2		-3					0		-1	
3		-3					0		1	
4		-3					1		0	
5		-2					-2		0	
6		-2		$A(n, k-1)$			-1		-1	
7		-2					-1		1	a
8		-2					0		-2	
9		-2					0		2	
10		-2					2		0	
11		-2					1		-1	
12		-2	$A(n, k)$				1		1	
13		-1					-3		0	

14	A(n,k+1)	-1					-2		-1	
15		-1					-2		1	
16		-1					-1		-2	
17		-1					-1		2	
18		-1					0		-3	
19		-1					0		3	
20		-1					3		0	
21		-1					2		-1	
22		-1					2		1	
23		-1					1		-2	
24		-1					1		2	
25		A(n,k-1)					0			
26	0		-3		-1					
27	0		-3		1					
28	0		-2		-2					
29	0		-2		2					
30	0		-1		-3					
31	0		-1		3					
32	0		0		-4					
33	0		0		4					
34	0		4		0					
35	0		3		-1					
36	0		3		1					
37	0		2		-2					
38	0		2		2					
39	0		1		-3					
40	0		1		3					
41		4	A(n, k-2)	A(n,k-3)		0		0	c	
42	3				-1		0			
43	3				0		-1			
44	3				0		1			
45	3				1		0			
46	2				-2		0			

47	A(n,k)	2	A(n, k-1)				-1		-1	
48		2					-1		1	
49		2					0		-2	
50		2					0		2	
51		2					2		0	
52		2					1		-1	
53		2					1		1	
54		1	A(n, k-2)				-3		0	
55		1					-2		-1	
56		1					-2		1	
57	1	-1						-2		
58	1	-1						2		
59	1	0						-3		
60	1	0						3		
61	1	3						0		
62	1	2						-1		
63	1	2						1		
64	1	1					-2			
65	1	1					2			

Table 4 Example prior art PVQ indexing scheme.

The A and U relations can be graphically seen in Table 5 for the MPVQ(3,5) example, using a leading sign recursive solution. $N_{PVQ}(n=3,k=5) = 2 \cdot N_{MPVQ}(3,5) = 2 \cdot 51 = 102$, where the “2” corresponds to a now pre-extracted leading sign bit. The vector PVQ-vec=[p0,p1,p2], e.g. decoded index 8 is [3, -1, 1], $\text{sum}(\text{abs}(\text{PVQ-vec})) = 5$, In the Table 5 below the now pre-extracted initial sign is positive (+), i.e. the value p0 below is always larger than or equal to 0. In the example the next leading sign is stored in the LSB- bit of the $2 \cdot U(n, k)$ sections.

ind	Size (A(n,k))	Size (U(n,k))	Val. p0	Size new K	lead sign	Val. p1	lead sign	Val. p2
0	A(n,K)= A(3,5)	1	5	1, new K=5	none	0	none	0
1		2*U(n,K)	4	new K= K-4=1	+	1	none	0
2			4		-	-1	none	0
3			4		+	0	kept	1
4			4		-	0	kept	-1
5			3	new K= K-3=2	+	2		0
6			3		-	-2		0
7			3		+	1	+	1
8			3		-	-1	+	1
9			3		+	1	-	-1
10			3		-	-1	-	-1
11			3		+	0	+	2
12			3		-	0	-	-2
13			2	new K= K-2=3	+	3		0
14			2		-	-3		0
15			2		+	2	+	1
16			2		-	-2	+	1
17			2		+	2	-	-1
18			2		-	-2	-	-1
19			2		+	1	+	2
20			2		-	-1	+	2
21			2		+	1	-	-2
22			2		-	-1	-	-2
23			2		+	0	kept	3
24			2		-	0	kept	-3
25			1	new K= K-1=4	+	4	none	0
26			1		-	-4	none	0
27			1		+	3	+	1
28			1		-	-3	+	1
29			1		+	3	-	-1
30			1		-	-3	-	-1

31			1		+	2	+	2
32			1		-	-2	+	2
33			1		+	2	-	-2
34			1		-	-2	-	-2
35			1		+	1	+	3
36			1		-	-1	+	3
37			1		+	1	-	-3
38			1		-	-1	-	-3
39			1		+	0	kept	4
40			1		-	0	kept	-4
41	$(A(n,K+1)-A(n,K))/2$	$U(n,K+1)-U(n,K)$	0	size= 1+ $U(n-1,K)+U(n-1,K+1)$ new K K=5	kept (+)	5	none	0
42			0			4	+	1
43			0			4	-	-1
44			0			3	+	2
45			0			3	-	-2
46			0			2	+	3
47			0			2	-	-3
48			0			1	+	4
49			0			1	-	-4
50			0			0	kept	5

Table 5 Example MPVQ(3,5) LSB based leading sign enumeration.

5 Table 6 illustrates index construction examples according to Table 5.

index	Value p0	lead sign	Value p1	lead sign	Value p2	Index construction examples
0	5	none	0	none	0	$A(3,0) = 0$
1	4	+	1	none	0	$A(3,1)+2*(A(2,0)) +0 = 1$
2	4	-	-1	none	0	$A(3,1)+2*(A(2,0)) +1 = 2$
3	4	+	0	kept	1	$A(3,1)+2*(A(2,1)) +0 = 3$
4	4	-	0	kept	-1	$A(3,1)+2*(A(2,1)) +1 = 4$
5	3	+	2		0	$A(3,2)+2*(A(2,0)) +0 = 5$
6	3	-	-2		0	$A(3,2)+2*(A(2,0)) +1 = 6$
7	3	+	1	+	1	$A(3,2)+2*(A(2,1)) +0 = 7$
8	3	-	-1	+	1	$A(3,2)+2*(A(2,1)) +1 = 8$
9	3	+	1	-	-1	$A(3,2)+2*(A(2,1)+1) +0 = 9$
10	3	-	-1	-	-1	$A(3,2)+2*(A(2,1)+1) +1 = 10$
11	3	+	0	+	2	
12	3	-	0	-	-2	
13	2	+	3		0	$A(3,3)+2*0 +0 = 13$
14	2	-	-3		0	$A(3,3)+2*0 +1 = 14$
15	2	+	2	+	1	$A(3,3)+2*(A(2,1)+0) +0 = 15$
16	2	-	-2	+	1	$A(3,3)+2*(A(2,1)+0) +1 = 16$
17	2	+	2	-	-1	$A(3,3)+2*(A(2,1)+0) +1 = 17$
18	2	-	-2	-	-1	$A(3,3)+2*(A(2,1)+1) +1 = 18$
19	2	+	1	+	2	
20	2	-	-1	+	2	
21	2	+	1	-	-2	
22	2	-	-1	-	-2	
23	2	+	0	kept	3	
24	2	-	0	kept	-3	
25	1	+	4	none	0	$A(3,4)+2*(A(2,0)) +0 = 24$
26	1	-	-4	none	0	$A(3,4)+2*(A(2,0)) +1 = 25$
27	1	+	3	+	1	
28	1	-	-3	+	1	
29	1	+	3	-	-1	
30	1	-	-3	-	-1	

31	1	+	2	+	2	
32	1	-	-2	+	2	
33	1	+	2	-	-2	
34	1	-	-2	-	-2	
35	1	+	1	+	3	
36	1	-	-1	+	3	
37	1	+	1	-	-3	$A(3,4)+2*(A(2,3)) +0 = 37$
38	1	-	-1	-	-3	$A(3,4)+2*(A(2,3)) +1 = 38$
39	1	+	0	kept	4	$A(3,4)+2*(A(2,3)) +0 = 39$
40	1	-	0	kept	-4	$A(3,4)+2*(A(2,4)) +1 = 40$
41	0	kept (+)	5	none	0	$A(3,5) = 41$
42	0		4	+	1	$A(3,5)+A(2,1)+0=42$
43	0		4	-	-1	$A(3,5)+A(2,1)+1=43$
44	0		3	+	2	$A(3,5)+A(2,2)+0=44$
45	0		3	-	-2	$A(3,5)+A(2,2)+1=45$
46	0		2	+	3	$A(3,5)+A(2,3)+0=46$
47	0		2	-	-3	$A(3,5)+A(2,3)+1=47$
48	0		1	+	4	$A(3,5)+A(2,4)+0=48$
49	0		1	-	-4	$A(3,5)+A(2,4)+1=49$
50	0		0	kept	5	$A(3,5)+A(2,5)=50$

Table 6 Example MPVQ(3,5) LSB based leading sign enumeration, index construction examples.

5 Note that the PVQ-size in Table 5 now has to be computed using $N_{MPVQ} = 1+U(n,k)+U(n,K+1)$, as $A(n,k+1)$, cannot be computed safely within the $2*N_{MPVQ}(n,k)$ bit-limit (e.g. 32bits) for all n, k. Prior art uses PVQ-size = $A(n,K+1) + A(n,K)$, or a summation over non-zero elements using MOPS costly combinatorial functions or a ROM costly table lookup of stored 10 values.

$A(n,k)$ can also be found as $1+2*U(n,k)$ in the basic recursion schematics of Fig. 5 (Sectioned positioning of the leading sign(s)) and in Fig. 2 (LSB positioning of the leading sign(s)).

5 In another part of the presently presented technology an optimized MPVQ-indexing through pre-extraction of sign encoding positions is described. It is also possible to optimize the encoder side MPVQ index composition inner loop by pre-extracting the MPVQ leading signs into a vector of sign encoding positions `encode_sign [0 ... N-1]`, and the actual sign to encode at that
10 position, and the remaining initial leading sign. However, this requires running a pre-processing sign shifting function which may be costly in the case of few pulses. However, in some cases it can be the preferred way to implement the MPVQ-indexing as the inner loop of the index-composition becomes even more straightforward, and can be strongly optimized e.g. for
15 DSP-pipelining.

The example below of sign pre-shifting utilizes $N=8$ and $K=13$.

```
% Example of pre-shifting the leading signs, (N=8,K=13)
20 % pos      =    0    1    2    3    4    5    6    7
% PVQ-vec    =   -1    0    0    0    +5    0   -6   -1
% becomes:
%
% PVQ-vec    =   -1    0    0    0    +5    0   -6   -1
25 % encode_sign = +1    0    0    0   -1    0   -1    0
% and:
lead_sign = -1 (negative, (the sign from PVQ-vec(0)))
```

In the example above, the encoding is done right to left, i.e. position $(N-1)$ to
30 position 0.

The pre-shifting function shifts the first sign to the variable 'lead_sign' and the rest of the signs in PVQ-vec are shifted to the next (to the left) non-zero

position. The last non-zero position in PVQ-vec will always get a 0 value in the encode_sign vector.

Fig. 18 illustrates an embodiment of a MPVQ-index composition using pre-
 5 extracted leading signs. There, embodiments of detailed block diagrams for this MPVQ-index composition implementation are shown. The procedure to compose MPVQ index with pre-extracted leading signs and MPVQ size starts in step 700. This embodiment is based on a solution with next sign in LSB position. Input parameters are N, K and the PVQ-vector as "vec". Step 702 is
 10 an initializing step, with known offset recursion base case, and set $n=1$. In step 704, the position parameter is set to $N-1$, i.e. the vector is analyzed from the end towards the beginning starting with the last position. The accumulated index and the accumulated pulses are set to 0 in step 706. First, in step 708, the signs are analyzed, which will be described more in
 15 detail further below. The leading sign is thereby determined, and a sign vector is available. In step 710, a value is set equal to the current input vector coefficient. In steps 712-720, the accumulated index is adapted for the sign of the coefficient, if the coefficient is non-zero, in this embodiment by adding a LSB. In step 722, the accumulated index is modified according
 20 to the offset associated with the remaining unit pulses and the present dimension. If the present position is non-zero, as checked in step 724, i.e. the search has not reached the front of the input vector, a new repetition is prepared in steps 726 and 728 and the procedure returns to step 710. If the entire vector is searched, the MPVQ-SIZE is calculated in step 730 and the
 25 outgoing index, leading sign and MPVQ size are provided in step 739.

Fig. 19 illustrates an embodiment of a sign extraction function. The procedure starts in step 740. In step 742, initializing is performed, giving an encoded sign vector 0-coefficients, assuming a positive leading sign, giving a
 30 temporary position of initial non-zero coefficient as -1 and starts with position number 0. In step 744, it is checked if the position is less than the maximum and still no leading sign is found. If so, in step 746, it is checked if the vector coefficient of the current position is zero. If so, the present

position is stepped one step forward in step 754 and the process is iterated. If the present vector coefficient is non-zero, the procedure continues to step 748, where a negative coefficient results in a negative lead_sign in step 750. The position of the first non-zero coefficient is recorded as initial_pos in step 5 752 before the procedure continues to step 754. If it in step 744 is found that the leading sign is found, the procedure continues to step 756, in which the sign vector encode_sign procedure is initialized. Steps 758-766 continue to search through the input vector for non-zero coefficients, and corresponding positions in the sign vector are given the sign of the following 10 non-zero coefficient. When all positions are investigated, the leading sign and the sign vector are returned in step 769.

A benefit with this approach is that the pre-shifting or pre-localization of the leading sign encoding positions makes it possible to avoid leading sign 15 shuffling in the indexing inner iteration loop. This can be a benefit when one wants to optimize the encoding inner loop in certain hardware where branches (IFs/ELSEs) are costly to implement.

Table 7 illustrates an MPVQ Sectioned leading sign iteration example. 20 $N_{PVQ}(n=3, k=5) = 2 * N_{MPVQ}(3, 5) = 2 * 51 = 102$, where the “2” corresponds to a now pre-extracted leading sign bit. The vector PVQ-vec=[p0, p1, p2], e.g. decoded index 8 is [3, 0, 2], $\text{sum}(\text{abs}(\text{PVQ-vec})) = 5$. In the Table 7 the now pre-extracted initial sign is positive, in the example the next leading sign derived from the low/high sections of the $2 * U(n, k)$ initial amplitude sections.

25

ind	Size (A(n,k))	Size (U(n,k))	Val. p0	Size new K	lead sign	Val. p1	lead sign	Val. p2
0		1	5	1, new K=5	+	0	none	0
1			4	new K= K-4=1	+	1	none	0
2			4		-	0	kept	1
3			4		-	1	none	0
4			4		+	0	kept	1
5			3		+	2	none	0

6	A(n,K)= A(3,5)	2*U(n,K)	3	new K= K-3=2	+	1	+	1
7			3		+	1	-	-1
8			3		-	0	kept	2
9			3		-	-2	none	0
10			3		-	-1	+	1
11			3		-	-1	-	-1
12			3		+	0	kept	-2
13			2	new K= K-2=3	+	3	none	0
14			2		+	2	+	1
15			2		+	2	-	-1
16			2		+	1	+	2
17			2		+	1	-	-2
18			2		-	0	kept	3
19			2		-	-3	none	0
20			2		-	-2	+	1
21			2		-	-2	-	-1
22			2		-	-1	+	2
23			2		-	-1	-	-2
24			2		+	0	kept	-3
25			1	new K= K-1=4	+	4	none	0
26			1		+	3	+	1
27			1		+	3	-	-1
28			1		+	2	+	2
29			1		+	2	-	-2
30			1		+	1	+	3
31			1		+	1	-	-3
32			1		-	0	kept	4
33			1		-	-4	none	0
34			1		-	-3	+	1
35			1		-	-3	-	-1
36			1		-	-2	+	2
37			1		-	-2	-	-2
38			1		-	-1	+	3

39			1		-	-1	-	-3
40			1			0	kept	-4
41	(A(n,K+1)- A(n,K))/2	U(n,K+1)- U(n,K)	0	size= 1+ U(n-1,K)+ U(n-1,K+1) new K K=5	kept (+)	5	none	0
42			0			4	+	1
43			0			4	-	-1
44			0			3	+	2
45			0			3	-	-2
46			0			2	+	3
47			0			2	-	-3
48			0			1	+	4
49			0			1	-	-4
50			0			0	kept	5

Table 7 Example MPVQ(3,5) Sectioned leading sign enumeration.

5 Table 8 illustrates index construction examples according to Table 7.

In a further part of the presently presented technology a mixed low dynamic row-only recursion is described. If the k value is low enough, it is possible to calculate the offset needed for a given row n in the offset matrix A(n, k) using the new row-only recursion formula presented further below. Detailed derivation of the new recursion formulas are given in Appendix B. The generic recursive equation for a given row n for the PVQ difference offset A(n,k), is used in the 2012 prior art IETF/OPUS-Audio code:

15 $A(n,k) = A(n,k-2) + ((2*n-1)*A(n,k-1) - A(n,k-2)) / (k-1).$

index	Value p0	lead sign	Value p1	lead sign	Value p2	Index construction examples
0	5	+	0	none	0	$A(3,0) = 0$
1	4	+	1	none	0	
2	4	-	0	kept	1	
3	4	-	1	none	0	
4	4	+	0	kept	1	
5	3	+	2	none	0	
6	3	+	1	+	1	
7	3	+	1	-	-1	
8	3	-	0	kept	2	
9	3	-	-2	none	0	
10	3	-	-1	+	1	
11	3	-	-1	-	-1	
12	3	+	0	kept	-2	
13	2	+	3	none	0	$A(3,3) + 0*(A(3,4)-(A3,3))/2 = 13$
14	2	+	2	+	1	
15	2	+	2	-	-1	
16	2	+	1	+	2	
17	2	+	1	-	-2	
18	2	-	0	kept	3	
19	2	-	-3	none	0	$A(3,3) + (A(3,4)-(A3,3))/2 = 19$
20	2	-	-2	+	1	
21	2	-	-2	-	-1	
22	2	-	-1	+	2	
23	2	-	-1	-	-2	
24	2	+	0	kept	-3	
25	1	+	4	none	0	$A(3,4) + 0*(A(3,5)-(A3,4))/2 = 25$
26	1	+	3	+	1	

27	1	+	3	-	-1	
28	1	+	2	+	2	
29	1	+	2	-	-2	
30	1	+	1	+	3	
31	1	+	1	-	-3	
32	1	-	0	kept	4	
33	1	-	-4	none	0	$A(3,4) + (A(3,5)-(A3,4))/2 = 33$
34	1	-	-3	+	1	
35	1	-	-3	-	-1	
36	1	-	-2	+	2	
37	1	-	-2	-	-2	
38	1	-	-1	+	3	
39	1	-	-1	-	-3	
40	1		0	kept	-4	
41	0	kept (+)	5	none	0	$A(3,5) = 41$
42	0		4	+	1	$A(3,5)+A(2,1)+0=42$
43	0		4	-	-1	$A(3,5)+A(2,1)+1=43$
44	0		3	+	2	$A(3,5)+A(2,2)+0=44$
45	0		3	-	-2	$A(3,5)+A(2,2)+1=45$
46	0		2	+	3	$A(3,5)+A(2,3)+0=46$
47	0		2	-	-3	$A(3,5)+A(2,3)+1=47$
48	0		1	+	4	$A(3,5)+A(2,4)+0=48$
49	0		1	-	-4	$A(3,5)+A(2,4)+1=49$
50	0		0	kept	5	$A(3,5)+A(2,5) = 50$

Table 8 Example MPVQ(3,5) Sectioned leading sign enumeration, index construction examples.

5 By massaging and manipulation the equation above and using the new relation that

$$U(n,k)= (A(n,k)-1)/2,$$

one can obtain a new preferred lower dynamic range mixed recursion formula:

$$U(n,k) = U(n,k-2) + (n \cdot A(n,k-1) - N_{MPVQ}(n,k-2)) / (k-1),$$

5

where $N_{MPVQ}(n,k) = 1 + U(n,k) + U(n,k+1)$, (the MPVQ(n,k) size).

The new numerator term $n \cdot A(n, k-1)$ is here of much lower dynamic range than the corresponding prior art numerator term $(2 \cdot n - 1) \cdot A(n, k-1)$.

10

In a preferred solution this row-only recursion can be further massaged to only use past $A(n,k)$ values for row n , by using the fact that $A(n, k)$ is odd for $k > 0$. We obtain a new very efficient mixed recursion formula:

$$15 \quad U(n,k) = A(n,k-2) \gg 1 + (n \cdot A(n,k-1) - (1 + A(n,k-1) \gg 1 + A(n,k-2) \gg 1)) / (k-1),$$

where “ $\gg$ ” is integer division by 2, a low cost right shift in most hardware.

This enables the use of fast row-only recursions with limited precision, e.g. within 64 or 32 or 33 bits, for higher n and higher k values than the prior art row-only recursion. In other words, the new $n \cdot A(n,k-1)$ term overflows/wraps later than the old term $2 \cdot n \cdot A(n,k-1)$ as one increases the range of n 's or k 's, for the row recursion.

25 The dynamic benefit of optimized row-only recursion can also be seen indirectly in the reduced dynamic offset Table 2, and also in the mixed recursion offset Table 3, as the $U(n,k)$ resulting offsets have lower dynamics than the previously used $A(n, k)$.

30 In a further part of the presently presented technology a Mixed MPVQ leading sign iteration and any legacy PVQ iteration is described. Another possible enumeration alternative is to employ an initial MPVQ-leading sign enumeration stage followed by any other efficient PVQ-enumeration scheme,

for the remainder of the vector. In other words, whenever the second leading sign is to be enumerated, the PVQ-enumeration method in use can be switched to a legacy scheme. The initial leading sign MPVQ stages will make it possible to use one bit more than the legacy short codeword scheme, and the initial MPVQ stage will reduce the dynamics of the offsets (A,U) to at least 1 bit less, after the first MPVQ stage.

Table 99 shows an example deindexing structure and results for MPVQH, a hybrid combination a first MPVQ stage followed by a second OPUS/IETF-
10 Audio magnitude and (Size PVQ(n,k) = A(n,k)+A(n, k+1)) based enumeration stage.

ind	Size	Val p0	Size				Val p1		Size			Val p2	Size	
0	1	-5	1	1	1	1	0	1	1	1	1	0	1	
1	U(3,k) + U(3,k+1) = 20+30= 50 (This sum has to be below the target indexing numerical	-4				2*	-1	3				0	1	
2		-4				U(3, k-3 =2*2	0					2		
3		-4					0							
4		-4				2*	1	1				0	1	
5		+				-3	U(3, k-2) =2*6	-2				5	0	1
6		U(3,k+1)				-3		-1					-1	2
7		=				-3	-1	1						
8		20+30=				-3	0	-2					2	
9		50				-3	0	2						
10		(This				-3	2*	2				3	0	1
11		sum has				-3		1					-1	2
12		to be				-3	2* U(3,k) = 2*20	1				7	1	
13		below				-2		-3					0	1
14		the				-2		-2					-1	2
15		target				-2		-2					1	
16		indexing				-2		-1					-2	2
17	numerical	-2	-1	2										
18		-2				0						-3	2	

19	dyna- mics e.g. < 2 ³² or <2 ³¹)	-2						0		[p1,p2] section where the sub- index is encoded as PVQ(2,remaining k) sub pyramid using any other PVQ scheme, like the IETF/OPUS- Audio magnitude scheme.			3						
20		-2						3					5		0	1			
21		-2						2							-1	2			
22		-2						2							1	2			
23		-2						1							-2				
24		-2						1	2										
25		-1							-4				9	0	1				
26		-1							-3					-1	2				
27		-1							-3					1	2				
28		-1							-2					-2					
29		-1							-2					2					
30		-1							-1					-3	2				
31		-1							-1					3	2				
32		-1							0					-4					
33		-1							0					4					
34		-1							4				7	0	1				
35		-1							3					-1	2				
36		-1							3					1	2				
37		-1							2					-2					
38		-1							2					2					
39		-1							1					-3	2				
40		-1							1					3					
41		0							M(2,k) = 1+ U(2, k+1) + U(2,k) =10				-5	1	1	1	0	1	
42		0											-4	2* U(2,k)	2* U(2, k-1)	2* U(2, k-2)	2*U(2 ,k-3)	-1	2
43		0											-4					1	
44		0											-3			2			-2
45		0						-3					2						
46		0						-2					-3		2				
47		0						-2					3						
48		0						-1					-4			2			
49		0						-1					4						
50		0						0					M(1,k)						-5

Table 9 Example MPVQH(3,5) hybrid single leading sign enumeration.

MPVQ-variation for $(n=3, k=5)$. This hybrid version uses single leading sign
 5 iterative indexing stage followed by a prior art IETF/OPUS like $[-, 0] / +$ magnitude based PVQ-indexing stage cells, $N_{PVQ}=2*N_{MPVQH}=2*51=102$, where the “2” corresponds to a single initial single extracted leading sign bit.

The drawback with a hybrid scheme (like the above exemplified MPVQH)
 10 using a first MPVQ(n, k) stage and then another pyramid based PVQ-enumeration stage (above a IETF/OPUS-like magnitude stage) when a second sign is to be added, is that the PROM code size will be quite much larger, and that the switch of indexing method inside the iteration loop will require further decision logic requiring further DSP cycles inside the critical
 15 iteration loops. Also several offsets memories may have to be maintained. However a hybrid MPVQ single leading sign stage followed by stages of a subsequent regular PVQ scheme can also provide the benefit of extending the total short codeword size by 1 bit, e.g. from 32 to 33 bits.

20 In the above described embodiments, the leading sign has been selected as the sign of the first non-zero coefficient in the vector. However, in other embodiments, the leading sign can also be selected as the last non-zero coefficient in the vector. The leading sign is thus a sign of a terminal non-zero coefficient in the integer input vector or the integer output vector. The
 25 terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in the integer input vector or the integer output vector. The use of extracting the leading sign is that the remaining indexing can be simplified. One prominent reason is that the indexing scheme can be reduced by a factor 2. Before the indexing, it is not known how many non-zero coefficients
 30 there are in the vector to be treated. However, there is always a terminal non-zero coefficient.

In the above described embodiments, it has also been assumed that the indexing of the integer input vector starts from the last coefficient and ends with the first coefficient, and that the de-indexing starts with the first coefficient of the integer output vector and ends with the last. In alternative
5 embodiments, the indexing may instead start with the first vector coefficient and end with the last, whereas the de-indexing starts with the last coefficient and ends with the first. This can be combined with any of the alternative of the terminal non-zero coefficients. In further embodiments, the indexing may pick the coefficients of the integer input vector in any
10 predetermined order, and the corresponding de-indexing then goes through the coefficients of the integer output vector in the opposite direction. The pyramid vector quantization enumeration scheme and the pyramid vector quantization de-enumeration scheme may then be adapted accordingly. In one particular embodiment, the “position” in the integer input/output vector can
15 be a position in the assumed treatment order and do not have to correspond to the actual position within the vector itself.

The proposed technology may in particular embodiments be applied to a user terminal or user equipment, which may be a wired or wireless device.

20

As used herein, the non-limiting terms “User Equipment” (UE) and “wireless device” may refer to a mobile phone, a cellular phone, a Personal Digital Assistant, PDA, equipped with radio communication capabilities, a smart phone, a laptop or Personal Computer (PC) equipped with an internal or
25 external mobile broadband modem, a tablet PC with radio communication capabilities, a target device, a device to device UE, a machine type UE or UE capable of machine to machine communication, iPad, Customer Premises Equipment (CPE), Laptop Embedded Equipment (LEE), Laptop Mounted Equipment (LME), Universal Serial Bus (USB) dongle, a portable electronic
30 radio communication device, a sensor device equipped with radio communication capabilities or the like. In particular, the term “UE” and the term “wireless device” should be interpreted as non-limiting terms comprising any type of wireless device communicating with a radio network

node in a cellular or mobile communication system or any device equipped with radio circuitry for wireless communication according to any relevant standard for communication within a cellular or mobile communication system.

5

As used herein, the term “wired device” may refer to any device configured or prepared for wired connection to a network. In particular, the wired device may be at least some of the above devices, with or without radio communication capability, when configured for wired connection.

10

The proposed technology may in particular embodiments be applied to a network node, which may be a wired or wireless device.

The network node can in particular embodiments be a radio network node.

15 As used herein, the non-limiting term “radio network node” may refer to base stations, network control nodes such as network controllers, radio network controllers, base station controllers, and the like. In particular, the term “base station” may encompass different types of radio base stations including standardized base stations such as Node Bs, or evolved Node Bs,
20 eNBs, and also macro/micro/pico radio base stations, home base stations, also known as femto base stations, relay nodes, repeaters, radio access points, base transceiver stations, BTSs, and even radio control nodes controlling one or more Remote Radio Units, RRUs, or the like.

25 The network node can in particular embodiments be a network node in a wired communication system.

The UE or network node may also include radio circuitry for communication with one or more other nodes, including transmitting and/or receiving
30 information.

It will be appreciated that the methods and devices described herein can be combined and re-arranged in a variety of ways.

For example, embodiments may be implemented in hardware, or in software for execution by suitable processing circuitry, or a combination thereof.

- 5 The steps, functions, procedures, modules and/or blocks described herein may be implemented in hardware using any conventional technology, such as discrete circuit or integrated circuit technology, including both general-purpose electronic circuitry and application-specific circuitry.
- 10 Particular examples include one or more suitably configured digital signal processors and other known electronic circuits, e.g. discrete logic gates interconnected to perform a specialized function, or Application Specific Integrated Circuits (ASICs).
- 15 Alternatively, at least some of the steps, functions, procedures, modules and/or blocks described herein may be implemented in software such as a computer program for execution by suitable processing circuitry such as one or more processors or processing units.
- 20 The flow diagram or diagrams presented herein may therefore be regarded as a computer flow diagram or diagrams, when performed by one or more processors. A corresponding apparatus may be defined as a group of function modules, where each step performed by the processor corresponds to a function module. In this case, the function modules are implemented as
- 25 a computer program running on the processor.

Examples of processing circuitry includes, but is not limited to, one or more microprocessors, one or more Digital Signal Processors, DSPs, one or more Central Processing Units, CPUs, video acceleration hardware, and/or any

30 suitable programmable logic circuitry such as one or more Field Programmable Gate Arrays, FPGAs, or one or more Programmable Logic Controllers, PLCs.

It should also be understood that it may be possible to re-use the general processing capabilities of any conventional device or unit in which the proposed technology is implemented. It may also be possible to re-use existing software, e.g. by reprogramming of the existing software or by
5 adding new software components.

The proposed technology provides an encoder configured to encode audio/video signals, wherein the encoder is configured to obtain an integer input vector representing audio/video signal samples, which integer input
10 vector has a number of integer-valued coefficients, extract a leading sign from said integer input vector, said leading sign being a sign of a terminal non-zero coefficient in the input vector, said terminal non-zero coefficient being one of a first non-zero coefficient and a last non-zero coefficient in the integer input vector, index said integer input vector with a pyramid vector quantization
15 enumeration scheme into an output index, which output index together with said leading sign representing audio/video signal samples, wherein the pyramid vector quantization enumeration scheme is designed for neglecting the sign of the terminal non-zero coefficient, and to output the leading sign as a first codeword and the output index as a second codeword into an
20 outgoing bit stream.

In a particular example, the encoder comprises a processor and a memory. The memory comprising instructions executable by the processor, whereby the encoder/processor is operative to obtain an integer input vector
25 representing audio/video signal samples, which integer input vector has a number of integer-valued coefficients, extract a leading sign from said integer input vector, said leading sign being a sign of a terminal non-zero coefficient in the input vector, said terminal non-zero coefficient being one of a first non-zero coefficient and a last non-zero coefficient in the integer input vector,
30 index said integer input vector with a pyramid vector quantization enumeration scheme into an output index, which output index together with the leading sign representing audio/video signal samples, wherein the pyramid vector quantization enumeration scheme is designed for neglecting

the sign of the terminal non-zero coefficient, and to output the leading sign as a first codeword and the output index as a second codeword into an outgoing bit stream.

5 The proposed technology also provides a decoder configured deindex into audio/video samples by pyramid vector quantization, wherein the decoder is configured to receive a leading sign as a first codeword and an input index as a second codeword from an ingoing bit stream, the leading sign and the input index representing audio/video signal samples, which leading sign is a
10 sign of a terminal non-zero coefficient in an integer output vector to be created, representing the audio/video signal samples, which integer output vector has a number of integer-valued coefficients, which terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in the integer output vector, deindex the input index into the integer output
15 vector with a pyramid vector quantization de-enumeration scheme, wherein the input index being created by an enumeration scheme is designed for neglecting the sign of the terminal non-zero coefficient, assign a sign of the terminating non-zero coefficient according to the received leading sign, and to output the vector.

20

In a particular example, the decoder comprises a processor and a memory. The memory comprising instructions executable by the processor, whereby the decoder/processor is operative to receive a leading sign as a first codeword and an input index as a second codeword from an ingoing bit
25 stream, the leading sign and the input index representing audio/video signal samples, which leading sign is a sign of a terminal non-zero coefficient in an integer output vector to be created, representing the audio/video signal samples, which integer output vector has a number of integer-valued coefficients, which terminal non-zero coefficient is one of a first non-zero
30 coefficient and a last non-zero coefficient in the integer output vector, deindex the input index into the integer output vector with a pyramid vector quantization de-enumeration scheme, wherein the input index being created by an enumeration scheme is designed for neglecting the sign of the

terminal non-zero coefficient, assign a sign of the terminating non-zero coefficient according to the received leading sign, and to output the vector

In the following, an example of a computer implementation will be described
5 with reference to Fig. 20. The encoder 10 comprises processing circuitry such as one or more processors 800 and a memory 810. In this particular example, at least some of the steps, functions, procedures, modules and/or blocks described herein are implemented in a computer program 820-826, which is loaded into the memory for execution by the processing circuitry. The
10 processing circuitry and memory are interconnected to each other to enable normal software execution. An optional input/output 804-808 device may also be interconnected to the processing circuitry and/or the memory to enable input and/or output of relevant data such as input parameter(s) and/or resulting output parameter(s).

15

In the following, another example of a computer implementation will be described with reference to Fig. 21. The decoder 60 comprises processing circuitry such as one or more processors 850 and a memory 860. In this particular example, at least some of the steps, functions, procedures,
20 modules and/or blocks described herein are implemented in a computer program 870-876, which is loaded into the memory for execution by the processing circuitry. The processing circuitry and memory are interconnected to each other to enable normal software execution. An optional input/output device 854-858 may also be interconnected to the
25 processing circuitry and/or the memory to enable input and/or output of relevant data such as input parameter(s) and/or resulting output parameter(s).

The term 'computer' should be interpreted in a general sense as any system
30 or device capable of executing program code or computer program instructions to perform a particular processing, determining or computing task.

In a particular embodiment, the computer program comprises instructions, which when executed by at least one processor, cause the processor(s) to obtain an integer input vector representing said audio/video signal samples, which integer input vector has a number of integer-valued coefficients, to
5 extract a leading sign from the integer input vector, which leading sign is a sign of a terminal non-zero coefficient in the integer input vector, which terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in the integer input vector, to index the integer input vector with a pyramid vector quantization enumeration scheme into an output
10 index, which output index together with the leading sign representing the audio/video signal samples, which pyramid vector quantization enumeration scheme neglecting the sign of the terminal non-zero coefficient, and to output the leading sign as a first codeword and the output index as a second codeword into an outgoing bit stream.

15

In a particular embodiment, the computer program comprises instructions, which when executed by at least one processor, cause the processor(s) to receive a leading sign as a first codeword and an input index as a second codeword from an ingoing bit stream, where the leading sign and the input
20 index represent audio/video signal samples, which leading sign is a sign of a terminal non-zero coefficient in an integer output vector to be created, representing the audio/video signal samples, which integer output vector has a number of integer-valued coefficients, which terminal non-zero coefficient is one of a first non-zero coefficient and a last non-zero coefficient in the integer
25 output vector, to deindex the input index into the integer output vector with a pyramid vector quantization de-enumeration scheme, which input index is created by an enumeration scheme neglecting the sign of said terminal non-zero coefficient, to assigning a sign of the terminating non-zero coefficient according to the received leading sign, and to output the integer output vector.

30

The proposed technology also provides a carrier comprising the computer program, wherein the carrier is one of an electronic signal, an optical signal,

an electromagnetic signal, a magnetic signal, an electric signal, a radio signal, a microwave signal, or a computer-readable storage medium.

The software or computer program may thus be realized as a computer
5 program product, which is normally carried or stored on a computer-readable medium. The computer-readable medium may include one or more removable or non-removable memory devices including, but not limited to a Read-Only Memory, ROM, a Random Access Memory, RAM, a Compact Disc, CD, a Digital Versatile Disc, DVD, a Blu-ray disc, a Universal Serial Bus, USB,
10 memory, a Hard Disk Drive, HDD storage device, a flash memory, a magnetic tape, or any other conventional memory device. The computer program may thus be loaded into the operating memory of a computer or equivalent processing device for execution by the processing circuitry thereof.

15 As indicated herein, the encoder may alternatively be defined as a group of function modules, where the function modules are implemented as a computer program running on at least one processor.

Figure 22 is a schematic block diagram illustrating an example of an
20 encoder 10 comprising a group of function modules 830-836.

The computer program residing in memory 810 may thus be organized as appropriate function modules 830-836 configured to perform, when executed by the processor 800, at least part of the steps and/or tasks
25 described herein. An example of such function modules 830-836 is illustrated in Figure 22.

As indicated herein, the decoder may alternatively be defined as a group of function modules, where the function modules are implemented as a
30 computer program running on at least one processor.

Figure 23 is a schematic block diagram illustrating an example of a decoder
60 comprising a group of function modules 880-886.

The computer program residing in memory 860 may thus be organized as appropriate function modules 880-886 configured to perform, when executed by the processor 850, at least part of the steps and/or tasks 5 described herein. An example of such function modules 880-886 is illustrated in Figure 23.

The proposed approaches improves the performance of a short codeword based pyramid vector quantization schemes. The scheme reduces the 10 dynamic range of the required indexing offsets. The desired side effect of the reduced dynamic range is that 1-bit larger 'short' PVQ-codewords can be used, without any significant penalty, for a given HW.

This makes it possible to use B+1 bit PVQ-codeword scheme on DSP 15 hardware supporting B bit unsigned arithmetic, and this makes it possible to implement a B bit PVQ-codeword scheme on a DSP hardware which only supports signed B-bit integer arithmetic (with a B-1 bit magnitude).

Further, the overhead required for transmitting splitting side information 20 will be reduced due to the capability of efficiently encoding 1-bit larger codewords. As an example is used, PVQ-encoding of k evenly distributed pulses in dimension N=128, where 5 bits is used to encode the relation for each binary dimension split and 71 bits were allocated to the PVQ over dimension N=128 by the audio codec bit-allocation algorithm.

25 Optimal unrestricted PVQ gives:

$$\log_2(N_{PVQ}(N=128, k=12)) = 67.2 \text{ bits,}$$

$$\log_2(N_{MPVQ}(N=128, k=12+1)) = 71.5 \text{ bits.}$$

30 $67.2 < 71 < 71.5$, i.e. 12 unit pulses are possible using an optimal unlimited PVQ over N=128, resulting in a pulse density of 12/128.

Legacy B=32 bit scheme requires 2 splits, into nearly equal dimensions [N1=43, N2=43, N3=42]]:

$$2*\log_2(N_{PVQ}(43,4)) + \log_2(N_{PVQ}(42,4)) + 2*5 = 63.25 + 2*5 = 73.25 \text{ bits}$$

5

73.25 is over the bit budget 71. By trying to reduce number of pulses by 1 to 11, one obtains:

$$2*\log_2(N_{PVQ}(43,4)) + \log_2(N_{PVQ}(42,3)) + 2*5 = 58.84 + 2*5 = 68.84 < 71.$$

10

Resulting pulse density becomes 11/128.

Legacy B=32 bit scheme requires 2 splits, into non-uniform split dimensions [N1=64, N2=32, N3=32]]:

15

$$\log_2(N_{PVQ}(64,6)) + 2*\log_2(N_{PVQ}(32,3)) + 2*5 = 53.34 + 2*5 = 63.34 \text{ bits}$$

73.25 is over the bit budget 71. By trying to reduce number of pulses by 1 to 11, one obtains:

20

$$2*\log_2(N_{PVQ}(32,3)) + \log_2(N_{PVQ}(64,5)) + 2*5 = 58.92 + 2*5 = 68.9 < 71.$$

Resulting pulse density becomes 11/128.

25 New (B+1)=33-bit MPVQ scheme requires one split into [N1=64 ,N2=64]]:

$$2* \log_2(2*N_{MPVQ}(64,6)) + 5 = 2*32.51 + 5 = 70.02 \text{ bits} < 71,$$

where

30

$$2*N_{MPVQ}(64,6) = N_{PVQ}(64,6) = 32.51 > B.$$

Resulting pulse density becomes 12/128. In other words, given 71 bits allocated to dimension $N=128$ vector, the old 32 bit codeword scheme can only provide 11 pulses, while the new 33-bit codeword scheme can provide 12 pulses.

5

Due to its 1-bit larger encoding range of 33-bits, the new scheme is better suited to allocate bits according the audio codec's original bit allocation instructions, as the overhead for additional vectors splitting (often) may be reduced.

10

An example audio codec bit allocation scheme can be found in the ITU-T G.719 specification, section 7.5.2 or OPUUS RFC6716, section 4.3.4.1.

The embodiments described above are merely given as examples, and it should be understood that the proposed technology is not limited thereto. It will be understood by those skilled in the art that various modifications, combinations and changes may be made to the embodiments without departing from the present scope as defined by the appended claims. In particular, different part solutions in the different embodiments can be combined in other configurations, where technically possible.

Abbreviations

VQ	Vector Quantizer/Quantization
PVQ	Pyramid VQ
25 PVQ(n,k)	The PVQ structure with dimension n and k unit pulses, the PVQ(n,k) is pyramid structure with an L1-norm equaling k.
MPVQ	leading sign Modular PVQ
MPVQ(n,k)	The MPVQ structure with dimension n and k unit pulses, the MPVQ(n,k) structure is a sliced PVQ(n,k) pyramid structure, the
30	L1-norm of MPVQ(n,k) is k.
$N_{PVQ}(N,K)$	Size of PVQ (dimension N, K unit pulses)
$N_{MPVQ}(N,K)$	Size of MPVQ (dimension N, K unit pulses)
SIMD	Single Instruction Multiple Data (a DSP instruction category)

DSP	Digital Signal Processor
HW	HardWare
SW	SoftWare
N,dim	Dimension
5 n, l	current dimension
k, K	number of unit pulses in PVQ(n, k) and in MPVQ(n,k)
KMAX	maximum K-value
B	bit-limit in the target hardware system for efficient operations, typically (16), 32 or 64 bits in today's processors.
10 R	bits per sample, or bits per coefficient,
x	target vector
r, vec	shape vector (also sometimes called residual)
G	gain (scalar or vector) for scaling target vector
RAM	Random Access Memory
15 OPS	Operations Per Second
MOPS	Million Operations Per Second
P-ROM	Program ROM
ROM	Read-Only Memory (typically pre-stored data)
LSB	Least Significant Bit
20 MSB	Most Significant Bit
LP	Linear Prediction

APPENDIX A

In this appendix, relevant extracts from the IETF/OPUS audio PVQ-sections are included to establish the prior art status. The refined and optimized
 5 OPUS-Audio PVQ indexing/de-indexing algorithm involve several optimizations which are not described in the text description of RFC 6716 but is provided as a c-code file (cwrs.c) in an attachment IETF/OPUS-Audio RFC6716 PVQ-deindexing

10 “PVQ Decoding

Decoding of PVQ vectors is implemented in `decode_pulses()` (cwrs.c). The unique codeword index is decoded as a uniformly distributed integer value between 0 and $V(N,K)-1$, where $V(N,K)$ is the number of possible
 15 combinations of K pulses in N samples. The index is then converted to a vector in the same way specified in [PVQ]. The indexing is based on the calculation of $V(N,K)$ (denoted $N(L,K)$ in [PVQ]).

The number of combinations can be computed recursively as $V(N,K) = V(N-1,K) + V(N,K-1) + V(N-1,K-1)$, with $V(N,0) = 1$ and $V(0,K) = 0, K \neq 0$. There are many different ways to compute $V(N,K)$, including precomputed tables and direct use of the recursive formulation. The reference implementation applies the recursive formulation one line (or column) at a time to save on
 25 memory use, along with an alternate, univariate recurrence to initialize an arbitrary line, and direct polynomial solutions for small N . All of these methods are equivalent, and have different trade-offs in speed, memory usage, and code size. Implementations MAY use any methods they like, as long as they are equivalent to the mathematical definition.

30 The decoded vector X is recovered as follows. Let i be the index decoded with the procedure in Section 4.1.5 with $ft = V(N,K)$, so that $0 \leq i < V(N,K)$. Let $k = K$. Then, for $j = 0$ to $(N - 1)$, inclusive,
 do:

1. Let $p = (V(N-j-1,k) + V(N-j,k))/2$.
2. If $i < p$, then let $sgn = 1$, else let $sgn = -1$ and set $i = i - p$.
- 5 3. Let $k_0 = k$ and set $p = p - V(N-j-1,k)$.
4. While $p > i$, set $k = k - 1$ and $p = p - V(N-j-1,k)$.
- 10 5. Set $X[j] = sgn*(k_0 - k)$ and $i = i - p$.

The decoded vector X is then normalized such that its L2-norm equals one.”

IETF/OPUS-audio PVQ codeword limit and splitting

15

“Split Decoding

To avoid the need for multi-precision calculations when decoding PVQ codevectors, the maximum size allowed for codebooks is 32 bits. When
 20 larger codebooks are needed, the vector is instead split in two sub-vectors of size $N/2$. A quantized gain parameter with precision derived from the current allocation is entropy coded to represent the relative gains of each side of the split, and the entire decoding process is recursively applied. Multiple levels of splitting may be applied up to a limit of $LM+1$ splits. The
 25 same recursive mechanism is applied for the joint coding of stereo audio.”

IETF/OPUS Audio RFC-6716 PVQ search

“Spherical Vector Quantization

30

CELT uses a Pyramid Vector Quantizer (PVQ) [PVQ] for quantizing the details of the spectrum in each band that have not been predicted by the pitch predictor. The PVQ codebook consists of all sums of K signed pulses in

a vector of N samples, where two pulses at the same position are required to have the same sign. Thus, the codebook includes all integer codevectors y of N dimensions that satisfy $\text{sum}(\text{abs}(y(j))) = K$.

5 In bands where there are sufficient bits allocated, PVQ is used to encode the unit vector that results from the normalization in Section 5.3.2 directly. Given a PVQ codevector y , the unit vector X is obtained as $X = y / ||y||$, where $||\cdot||$ denotes the L2 norm.”

10 “PVQ Search

The search for the best codevector y is performed by `alg_quant()` (`vq.c`). There are several possible approaches to the search, with a trade-off between quality and complexity. The method used in the reference implementation
15 computes an initial codeword y_1 by projecting the normalized spectrum X onto the codebook pyramid of $K-1$ pulses:

$$y_0 = \text{truncate_towards_zero}((K-1) * X / \text{sum}(\text{abs}(X)))$$

20 Depending on N , K and the input data, the initial codeword y_0 may contain from 0 to $K-1$ non-zero values. All the remaining pulses, with the exception of the last one, are found iteratively with a greedy search that minimizes the normalized correlation between y and X :

25

$$T$$

$$J = -X * y / ||y||$$

The search described above is considered to be a good trade-off between
30 quality and computational cost. However, there are other possible ways to search the PVQ codebook and the implementers MAY use any other search methods. See `alg_quant()` in `celt/vq.c`. ”

IETF/OPUS Audio RFC-6716 PVQ-indexing

“PVQ Encoding

5 The vector to encode, X , is converted into an index i such that $0 \leq i < V(N,K)$ as follows. Let $i = 0$ and $k = 0$. Then, for $j = (N - 1)$ down to 0 , inclusive, do:

1. If $k > 0$, set $i = i + (V(N-j-1,k-1) + V(N-j,k-1))/2$.

10

2. Set $k = k + \text{abs}(X[j])$.

3. If $X[j] < 0$, set $i = i + (V(N-j-1,k) + V(N-j,k))/2$.

15 The index i is then encoded using the procedure in Section 5.1.4 with $ft = V(N,K)$.“

APPENDIX B**Derivation of the MPVQ related recursion equations**

5 Derivation of the $U(n,k)$ and $M(n, k)=N_{MPVQ}(n, k)$ size relation using Fischer's formula:

Use $N(n,k)$ as a short notation for $N_{PVQ}(n,k)$, the number of PVQ-vectors for dimension n with k unit pulses.

10 Fischer's original PVQ recursion from 1986:

$$N(n, k) = N(n-1, k) + N(n-1, k-1) + N(n-1, k) \quad (1)$$

Define $M(n, k) = N(n, k)/2$; (2)

$M(n,k)$ is used below as short notation for $N_{MPVQ}(n,k)$

// $M(n,k)$ number of PVQ-vectors with an positive
15 initial
// sign, is half the number of entries in a full PVQ-
// pyramid $N(n,k)$

Define $U(n, k)$ as $\text{sum}(j=1, j=k-1, M(n-1, j))$ (3)
// the number of vectors with a remaining leading
20 // +(positive) sign, excluding the vectors with an
// initial position value of 'k' and excluding the
// vectors an initial position value of '0'

$$M(n, k) = 1 + 2*U(n, k) + M(n-1, k); \quad (4)$$

25 // 1 for $k=KMAX$, only one such leading vector possible
// $2*U(n,k)$ for the number of vectors with a new/next leading
// sign, ("2" due to positive or negative new/next leading
// sign) (the " $U(n,k)$ " vectors have initial positive
// amplitudes [$KMAX-1, KMAX-2 \dots 1$]) $M(n-1, k)$ for remaining
30 // with vectors a leading zero value

(Equivalently with $M(n, k) = N_{MPVQ}(n, k)$)

$$N_{MPVQ}(n, k) = 1 + 2*U(n, k) + N_{MPVQ}(n-1, k); \quad (4b)$$

$$M(n, k) - M(n-1, k) = 1 + 2*U(n, k) = A(n, k) \quad (5)$$

Combine (1) (2) (5)

$$5 \quad M(n-1, k) = U(n, k+1) - U(n, k) \quad (6)$$

Combine (4) (6)

$$M(n, k) = 1 + U(n, k) + U(n, k+1) \quad (7)$$

(7) can now be used for size calculation, as both $U(n, k)$ and $U(n, k+1) < M(n, k)$ (5) the difference (5), $A(n, k)$, can still
 10 be used for amplitude offset iterations, if only used for offsets up to $A(n, KMAX)$, as $A(n, KMAX+1)$, may exceed $M(n, KMAX)$, and thus causing numeric problems in precision limited hardware

15 **Derivation of direct row calculation recursion for $U(n, k)$**

$$U(n, k) = (A(n, k) - 1) / 2 \quad (\text{from eq (5)})$$

Generic equation for a PVQ difference row $A(n, k)$, used in
 20 CELT/OPUS-Audio

$$A(n, k) = A(n, k-2) + ((2*n-1)*A(n, k-1) - A(n, k-2)) / (k-1) \quad (8)$$

Combine (5) (8)

$$25 \quad U(n, k) = ((2*n - 1) * (U(n, k-1) + (k-2) * U(n, k-2) + n - 1) / (k-1) \quad (9)$$

Or allow a mixed recursion

$$U(n, k) = (A(n, k-2) - 1) / 2 + ((2*n-1) * A(n, k-1) - A(n, k-2)) / (2 * (k-1)) \quad (10)$$

Due to the high dynamic range of the numerator of (8 and 9, 10), special care has to be taken when evaluating this direct function, esp. in a limited precision arithmetic system (e.g. a 32 bit system).

5 (8) is used in IETF/OPUS , and original-CELT

(10) can be used in the MPVQ system calculation of $U(n, KMAX+1)$, as it is known apriori that all previous $A(n, k < KMAX+1)$ have low enough values.

(10) can be simplified even further (as $A(n, k)$ is always
10 odd for $k > 1$)

$$U(n, k) = \text{floor}(A(n, k-2)/2) + (n * A(n, k-1) - (\text{floor}(A(n, k-1)/2) + \text{floor}(A(n, k-2)/2 + 1))) / (k-1) \quad (11)$$

or $U(n, k) = U(n, k-2) + (n * A(n, k-1) - N_{MPVQ}(n, k-2)) / (k-1)$
15 (11.b)

MPVQ n,k- matrix recursion relations

From Fischer relation (1) $N(n, k) = N(n-1, k) + N(n-1, k-1) +$
20 $N(n-1, k)$

Combine (7) and (5) one can find these recursive relations:

$$U(n, k+1) = 1 + U(n-1, k) + U(n-1, k+1) + U(n, k) \quad (12),$$

with initial conditions

$$U(0, *) = 0, \quad U(1, *) = 0, \quad \text{and} \quad U(a, b) = U(b, a)$$

25

$$A(n, k+1) = A(n-1, k) + A(n-1, k+1) + A(n, k) \quad (13)$$

with initial conditions $A(0, 0) = 1, \quad A(0, 1+) = 0,$
 $A(1, *) = 1, \quad \text{and} \quad A(a, b) = A(b, a)$

(13) can now be used to iteratively calculate row n , $k=0:KMAX$ from previous vector row $n-1, k=0:KMAX$ for $A(n, k)$, and (12) be used to iteratively calculate row n , $k=0:KMAX+1$ from previous vector row $n-1, k=0:KMAX+1$ for $U(n, k)$.

5 (13) is used in IETF-OPUS-Audio

Using (12) and the fact that $A(n, k)$ is odd, we obtain a new efficient mixed recursion formula :

$$U(n, k+1) = 1 + A(n-1, k) \gg 1 + U(n-1, k+1) + A(n, k) \gg 1$$

10 (14)

, where " $\gg$ " is integer division by 2 (a right shift), as $A(\text{large } n, k+1)$ may saturate, Equation 14 is used to stay within the given dynamic range e.g (32 bits, for the last $(k+1)$ offset column.

15

The vector radius relation, enumeration by products and vector length recursion relations

Hung, Tsern, Meng 1998 also summarizes some relevant additional relations for a PVQ($l=n, k$) pyramid the size is $N(l, k) = N_{PVQ}(l, k)$, The vector radius recursive relation "(43)" below is a basic row-only size relation for row $l=n$.

The enumeration formula by products "(44)" below is a number of non-zero elements based product relation for the PVQ size.

$$(l-1)N(l, k) = 2kN(l-1, k) + (l-1)N(l-2, k)$$

Vector length recursion (42)

$$kN(l, k) = 2lN(l, k-1) + (k-2)N(l, k-2)$$

Vector radius recursion (43)

$$N(l, k) = \sum_s 2^s \binom{l}{s} \binom{k-1}{s-1}$$

Enumeration formula by products (44)

CLAIMS

1. A method for pyramid vector quantization indexing of audio/video samples, wherein said method comprises the steps of:

obtaining (402) an integer input vector;

said integer input vector representing said audio/video signal samples;

said integer input vector having a number of integer-valued coefficients;

extracting (404) a leading sign from said integer input vector;

said leading sign being a sign of a last non-zero coefficient in said integer input vector in a direction of coding;

indexing (406) said integer input vector with a modified pyramid vector quantization enumeration scheme into an output index, which output index together with said leading sign representing said audio/video signal samples;

said modified pyramid vector quantization enumeration scheme neglecting said leading sign by shifting a sign of each non-zero coefficient such that said shifted sign is coded in association with next non-zero coefficient in the direction of coding; and

outputting (408) said leading sign as a first codeword and said output index as a second codeword into an outgoing bit stream.

2. The method according to claim 1, wherein said step of indexing (406) is performed by an iterative enumeration procedure;

wherein said iterative enumeration procedure comprises repetition of an iteration step, in which one current coefficient of said integer input vector is selected for consideration;

said iteration step in turn comprising:

finding an offset parameter being associated with all coefficients of said integer input vector processed prior to said current coefficient of said integer input vector; and

increasing an accumulated index in dependence of said offset parameter;

wherein said repetition is continued with coefficients of said integer input vector being selected one after the other as said current coefficient at least until all coefficients in said integer input vector has been considered;

said iterative enumeration procedure comprising a terminating step in which said output index is set equal to said accumulated index after all iteration steps have been ended.

3. The method according to claim 2, wherein said increasing of said accumulated index in each iteration step is given a least significant bit in dependence of a sign of a previous non zero coefficient in said integer input vector.

4. The method according to claim 2 or 3, wherein said increasing of said accumulated index is based at least partly on a first offset parameter $U(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said first offset parameter $U(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k , that does not have a leading zero, and does not have the leading value k , has a leading positive value, and has a positive next leading sign.

5. The method according to claim 4, wherein said first offset parameter $U(n,k)$ being recursively defined as:

$$U(n,k) = 1 + U(n,k-1) + U(n-1,k-1) + U(n-1,k).$$

6. The method according to any of the claims 2 to 5, wherein said increasing of said index is based at least partly on a second offset parameter $A(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said second offset parameter $A(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k , that has a positive leading value and that does not have a leading zero.

7. The method according to claim 6, wherein said second offset parameter $A(n,k)$ being recursively defined as:

$$A(n,k) = A(n,k-1) + A(n-1,k-1) + A(n-1,k).$$

8. The method according to any of the claims 2 to 7, wherein said increasing of index value is based on both a first offset parameter $U(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said first offset parameter $U(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k , that does not have a leading zero, and does not have the leading value k , has a leading positive value, and has a positive next leading sign and on a second offset parameter $A(n,k)$, said second offset parameter $A(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k , that has a positive leading value and that does not have a leading zero.

9. The method according to claim 8, wherein a recursion of U is performed according to:

$$U(n,k+1) = 1 + A(n-1,k) \gg 1 + U(n-1,k+1) + A(n,k) \gg 1.$$

10. A method for pyramid vector quantization deindexing of audio/video samples, wherein said method comprises the steps of:

receiving (452) a leading sign as a first codeword and an input index as a second codeword from an ingoing bit stream;

said leading sign and said input index representing audio/video signal samples;

said leading sign being a sign of a terminal non-zero coefficient in an integer output vector to be created, representing said audio/video signal samples;

said integer output vector having a number of integer-valued coefficients;

said terminal non-zero coefficient being a first non-zero coefficient in said integer output vector;

deindexing (454) said input index into said integer output vector with a modified pyramid vector quantization de-enumeration scheme;

said input index being created by an enumeration scheme neglecting said sign of said terminal non-zero coefficient;

assigning (456) a sign of said terminal non-zero coefficient in said integer output vector according to said received leading sign;

outputting (458) said integer output vector.

11. The method according to claim 10, wherein said step of deindexing (454) is performed by an iterative de-enumeration procedure;

wherein said iterative de-enumeration procedure comprises an initializing step, in which a remaining index is set equal to said input index, and a repetition of an iteration step, in which one current coefficient of said integer output vector is selected for consideration;

said iteration step in turn comprises

finding an offset parameter being compatible with a position of said current coefficient within said integer output vector and with said remaining index;

reducing said remaining index in dependence of said offset parameter; and

setting an amplitude of said current coefficient of said integer input vector to be equal to an amplitude associated with said offset parameter;

wherein said repetition is continued with coefficients of said integer input vector being selected one after the other as said current coefficient at least until said remaining index becomes equal to zero.

12. The method according to claim 11, wherein a sign of a next non zero coefficient in said integer input vector is deduced in dependence of a least significant bit in said remaining index.

13. The method according to claim 11 or 12, wherein said reduction of said remaining index is based at least partly on a first offset parameter $U(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said first offset parameter $U(n,k)$ being defined as the number of integer vectors of dimension n and $L1$ -norm of k , that does not have a

leading zero, and does not have the leading value k, has a leading positive value, and has a positive next leading sign.

14. The method according to claim 13, wherein said first offset parameter $U(n,k)$ being recursively defined as:

$$U(n,k) = 1 + U(n,k-1) + U(n-1,k-1) + U(n-1,k).$$

15. The method according to any of the claims 11 to 14, wherein said reduction of said remaining index is based at least partly on a second offset parameter $A(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said second offset parameter $A(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k, that has a positive leading value and that does not have a leading zero.

16. The method according to claim 15, wherein said second offset parameter $A(n,k)$ being recursively defined as:

$$A(n,k) = A(n,k-1) + A(n-1,k-1) + A(n-1,k).$$

17. The method according to any of the claims 11 to 16, wherein said reduction of said remaining index is based on both a first offset parameter $U(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said first offset parameter $U(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k, that does not have a leading zero, and does not have the leading value k, has a leading positive value, and has a positive next leading sign, and on a second offset parameter $A(n,k)$, said second offset parameter $A(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k, that has a positive leading value and that does not have a leading zero.

18. The method according to claim 17, wherein a row-only recursion of U for a last matrix column ($k=K+1$) is performed according to:

$$U(n,k) = A(n,k-2) >> 1 + (n * A(n,k-1) - (1 + A(n,k-1) >> 1 + A(n,k-2) >> 1)) / (k-1).$$

Printed: 13/01/2016

CLMSPAMD

PCT/SE 2015/050 21-12-2015
SE2015050216

19. A method for communication of audio/video signals, comprising:
- encoding audio/video samples, in an encoder of a transmitter, according to a method for modified pyramid vector quantization indexing of audio/video samples according to any of the claims 1 to 9 into said output index and said leading sign;
 - transmitting of said output index and the leading sign from the transmitter to a receiver, where it is received as an input index and a leading sign; and
 - decoding, in a decoder in the receiver, said input index and said leading sign according to a method for modified pyramid vector quantization deindexing of audio/video samples according to any of the claims 10 to 18.
20. An encoder (10) configured to index audio/video samples by pyramid vector quantization,
- wherein said encoder (10) is configured to obtain an integer input vector;
 - said integer input vector (5) representing said audio/video signal samples,
 - said integer input vector having a number of integer-valued coefficients;
 - wherein said encoder (10) is configured to extract a leading sign (15) from said integer input vector (5);
 - said leading sign (15) being a sign of a last non-zero coefficient in said integer input vector (5) in a direction of coding;
 - wherein said encoder (10) is configured to index said integer input vector (5) with a modified pyramid vector quantization enumeration scheme into an output index (25), which output index together with said leading sign representing said audio/video signal samples;
 - said modified pyramid vector quantization enumeration scheme neglecting said leading sign by shifting a sign of each non-zero coefficient such that said shifted sign is coded in association with next non-zero coefficient in the direction of coding; and

wherein said encoder (10) is configured to output said leading sign (15) as a first codeword and said output index (25) as a second codeword into an outgoing bit stream (2).

21. The encoder according to claim 20, wherein the encoder (10) comprises a processor (800) and a memory (810), said memory (810) comprising instructions executable by the processor (810), whereby the processor (810) is operative to extract said leading sign (15) from said integer input vector (5) and to index said integer input vector (5) with said modified pyramid vector quantization enumeration scheme, neglecting said leading sign, into said output index (25) representing said audio/video signal samples.

22. The encoder according to claim 20 or 21, wherein the encoder (10) comprises communication circuitry (804, 806, 808) configured to obtain said integer input vector (5) representing said audio/video signal samples and to output said leading sign (15) and said output index (25) into said outgoing bit stream (2).

23. The encoder according to any of the claims 20 to 22, wherein said encoder (10) is configured to perform said indexing by an iterative enumeration procedure;

wherein said iterative enumeration procedure comprises repetition of an iteration step, in which one current coefficient of said integer input vector (5) is selected for consideration;

said iteration step in turn comprising:

finding an offset parameter being associated with all coefficients of said integer input vector processed prior to said current coefficient of said integer input vector (5); and

increasing an accumulated index in dependence of said offset parameter;

wherein said repetition is continued with coefficients of said integer input vector (5) being selected one after the other as said current coefficient at least until all coefficients in said integer input vector (5) has been considered;

said iterative enumeration procedure comprising a terminating step in which said output index (25) is set equal to said accumulated index after all iteration steps have been ended.

24. The encoder according to claim 23, wherein said increasing of said accumulated index in each iteration step is given a least significant bit in dependence of a sign of a previous non zero coefficient in said integer input vector (5).

25. The encoder according to claim 23 or 24, wherein said increasing of said accumulated index is based at least partly on a first offset parameter $U(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said first offset parameter $U(n,k)$ being defined as the number of integer vectors of dimension n and $L1$ -norm of k , that does not have a leading zero, and does not have the leading value k , has a leading positive value, and has a positive next leading sign.

26. The encoder according to claim 25, wherein said first offset parameter $U(n,k)$ being recursively defined as:

$$U(n,k) = 1 + U(n,k-1) + U(n-1,k-1) + U(n-1,k).$$

27. The encoder according to any of the claims 23 to 26, wherein said increasing of said index is based at least partly on a second offset parameter $A(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said second offset parameter $A(n,k)$ being defined as the number of integer vectors of dimension n and $L1$ -norm of k , that has a positive leading value and that does not have a leading zero.

28. The encoder according to claim 27, wherein said second offset parameter $A(n,k)$ being recursively defined as:

$$A(n,k) = A(n,k-1) + A(n-1,k-1) + A(n-1,k).$$

Printed: 13/01/2016

CLMSPAMD

PCT/SE 2015/050 216 22-12-2015
SE2015050216

29. The encoder according to any of the claims 23 to 28, wherein said increasing of index value is based on both a first offset parameter $U(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said first offset parameter $U(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k , that does not have a leading zero, and does not have the leading value k , has a leading positive value, and has a positive next leading sign and on a second offset parameter $A(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said second offset parameter $A(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k , that has a positive leading value and that does not have a leading zero.

30. The encoder according to claim 29, wherein a recursion of U is performed according to:

$$U(n,k+1) = 1 + A(n-1,k) \gg 1 + U(n-1,k+1) + A(n,k) \gg 1.$$

31. A decoder (60) configured to deindex into audio/video samples by pyramid vector quantization,

wherein said decoder (60) is configured to receive a leading sign (15') as a first codeword and an input index (25') as a second codeword from an ingoing bit stream (2');

said leading sign (15') and said input index (25') representing audio/video signal samples

said leading sign (15') being a sign of a terminal non-zero coefficient in an integer output vector (6') to be created, representing said audio/video signal samples;

said integer output vector having a number of integer-valued coefficients;

said terminal non-zero coefficient being a first non-zero coefficient in said integer output vector;

wherein said decoder (60) is configured to deindex said input index (25') into said integer output vector (6') with a modified pyramid vector quantization de-enumeration scheme;

said input index being created by an enumeration scheme neglecting said sign of said terminal non-zero coefficient;

wherein said decoder (60) is configured to assign a sign of said terminating non-zero coefficient according to said received leading sign (15'); and

wherein said decoder (60) is configured to output said integer output vector (6').

32. The decoder according to claim 31, wherein the decoder (60) comprises a processor (850) and a memory (860), said memory (860) comprising instructions executable by the processor (860), whereby the processor (860) is operative to deindex said input index (25') into said integer output vector (6') with said modified pyramid vector quantization de-enumeration scheme, neglecting said leading sign and to assign a sign of said terminating non-zero coefficient according to said received leading sign (15').

33. The decoder according to claim 31 or 32, wherein said decoder (60) comprises communication circuitry (854, 856, 858) configured to receive a leading sign (15') and an input index (25') representing audio/video signal samples from an ingoing bit stream (2'), and to output said integer output vector.

34. The decoder according to any of the claims 31 to 33, wherein said decoder (60) is configured to perform said deindexing by an iterative de-enumeration procedure;

wherein said iterative de-enumeration procedure comprises an initializing step, in which a remaining index is set equal to said input index (25'), and a repetition of an iteration step, in which one current coefficient of said integer output vector is selected for consideration;

said iteration step in turn comprises

finding an offset parameter being compatible with a position of said current coefficient within said integer output vector and with said remaining index;

reducing said remaining index in dependence of said offset parameter; and

setting an amplitude of said current coefficient of said integer input vector to be equal to an amplitude associated with said offset parameter;

wherein said repetition is continued with coefficients of said integer input vector being selected one after the other as said current coefficient at least until said remaining index becomes equal to zero.

35. The decoder according to claim 34, wherein a sign of a next non zero coefficient in said integer input vector is deduced in dependence of a least significant bit in said remaining index.

36. The decoder according to claim 34 or 35, wherein said reduction of said remaining index is based at least partly on a first offset parameter $U(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said first offset parameter $U(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k , that does not have a leading zero, and does not have the leading value k , has a leading positive value, and has a positive next leading sign.

37. The decoder according to claim 36, wherein said first offset parameter $U(n,k)$ being recursively defined as:

$$U(n,k) = 1 + U(n,k-1) + U(n-1,k-1) + U(n-1,k).$$

38. The decoder according to any of the claims 34 to 37, wherein said reduction of said remaining index is based at least partly on a second offset parameter $A(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said second offset parameter $A(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k , that has a positive leading value and that does not have a leading zero.

39. The decoder according to claim 38, wherein said second offset parameter $A(n,k)$ being recursively defined as:

$$A(n,k) = A(n,k-1) + A(n-1,k-1) + A(n-1,k).$$

40. The decoder according to any of the claims 34 to 39, wherein said reduction of said remaining index is based on both a first offset parameter $U(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said first offset parameter $U(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k , that does not have a leading zero, and does not have the leading value k , has a leading positive value, and has a positive next leading sign and on a second offset parameter $A(n,k)$, where n is the dimension of the integer input vector and k is the number of unit pulses, said second offset parameter $A(n,k)$ being defined as the number of integer vectors of dimension n and L1-norm of k , that has a positive leading value and that does not have a leading zero.

41. The decoder according to claim 40, wherein a row recursion of U for a last matrix column ($k=K+1$) is performed according to:

$$U(n,k) = A(n,k-2) \gg 1 + (n * A(n,k-1) - (1 + A(n,k-1) \gg 1 + A(n,k-2) \gg 1)) / (k-1).$$

42. A computer program (820, 822, 824, 836) comprising instructions, which when executed by at least one processor (800), cause the at least one processor (800) to obtain an integer input vector (5), said integer input vector representing said audio/video signal samples, said integer input vector having a number of integer-valued coefficients, to extract a leading sign (15) from said integer input vector (5), said leading sign (5) being a sign of a last non-zero coefficient in said integer input vector in a direction of coding, to index said integer input vector with a modified pyramid vector quantization enumeration scheme into an output index (25), which output index together with said leading sign representing said audio/video signal samples, said modified pyramid vector quantization enumeration scheme neglecting said leading sign by shifting a sign of each non-zero coefficient such that said shifted sign is coded in association with next non-zero coefficient in the direction of coding,

and to output said leading sign (15) as a first codeword and said output index (25) as a second codeword into an outgoing bit stream (2).

43. A computer program (870, 872, 874, 876) comprising instructions, which when executed by at least one processor (850), cause the at least one processor (850) to receive a leading sign (15') as a first codeword and an input index (25') as a second codeword from an ingoing bit stream (2'), said leading sign and said input index representing audio/video signal samples, said leading sign (15') being a sign of a terminal non-zero coefficient in an integer output vector (6') to be created, representing said audio/video signal samples, said integer output vector having a number of integer-valued coefficients, said terminal non-zero coefficient being a first non-zero coefficient in said integer output vector, to deindex said input index (25') into said integer output vector (6') with a modified pyramid vector quantization de-enumeration scheme, said input index being created by an enumeration scheme neglecting said sign of said terminal non-zero coefficient, to assigning a sign of said terminating non-zero coefficient according to said received leading sign (15'), and to output said integer output vector (6').

44. A carrier comprising the computer program of at least one of claim 42 and claim 43, wherein the carrier is one of an electronic signal, an optical signal, an electromagnetic signal, a magnetic signal, an electric signal, a radio signal, a microwave signal, or a computer-readable storage medium.

45. An encoder (10) for pyramid vector quantization indexing of audio/video samples, wherein said coder comprises:

- an input module (830) for obtaining an integer input vector (5);
- said integer input vector representing said audio/video signal samples;
- said integer input vector having a number of integer-valued coefficients;
- an extracting module (832) for extracting a leading sign (15) from said integer input vector (5);
- said leading sign (15) being a sign of a last non-zero coefficient in said integer input vector (5) in a direction of coding;

an indexing module (834) for indexing said integer input vector (5) with a modified pyramid vector quantization enumeration scheme into an output index (25), which output index together with said leading sign representing said audio/video signal samples;

said modified pyramid vector quantization enumeration scheme neglecting said leading sign by shifting a sign of each non-zero coefficient such that said shifted sign is coded in association with next non-zero coefficient in the direction of coding; and

an output module (836) for outputting said leading sign (15) as a first codeword and said output index (25) as a second codeword into an outgoing bit stream (2).

46. A decoder (60) for pyramid vector quantization deindexing of audio/video samples, wherein said decoder comprises:

a receiver (880) for receiving a leading sign (15) as a first codeword and an input index (25) as a second codeword from an ingoing bit stream (2);

said leading sign and said input index representing audio/video signal samples;

said leading sign (15) being a sign of a terminal non-zero coefficient in an integer output vector (6) to be created, representing said audio/video signal samples;

said integer output vector having a number of integer-valued coefficients;

said terminal non-zero coefficient being a first non-zero coefficient in said integer output vector (6);

a deindexing module (882) for deindexing said input index into said integer output vector (6) with a modified pyramid vector quantization de-enumeration scheme;

said input index being created by an enumeration scheme neglecting said sign of said terminal non-zero coefficient;

an assigning module (884) for assigning a sign of said terminal non-zero coefficient in said integer output vector (6) according to said received leading sign (15); and

Printed: 13/01/2016

CLMSPAMD

PCT/SE 2015/050 21
SE2015050216

an output module (886) for outputting said integer output vector (6').

47. A network node comprising an encoder according to any of the claims 20 to 30 or 45 and/or a decoder according to any of the claims 31 to 41 or 46.

48. A user equipment comprising an encoder according to any of the claims 20 to 30 or 45 and/or a decoder according to any of the claims 31 to 41 or 46.




Fig. 1




Fig. 6




Fig. 2




Fig. 3

4/24

N _{MPVQ} (n,k)=M(n,k)		
pos[0] value	NUMBER OF ENTRIES	
"k"	1	
NON-ZERO POSITIVE OR NEGATIVE NEXT LEAD_SIGN	2*U(n,k)	
"0"	M(n-1,k)	
MPVQ-SIZE IS: N _{MPVQ} (n,k)=M(n,k)=1+2*U(n,k)+M(n-1,k)		

Fig. 4

LSB BIT IN "2*U(n,k)" section		
0	NEXT LEADING SIGN AFTER pos[0] IS POSITIVE	
1	NEXT LEADING SIGN AFTER pos [0] IS NEGATIVE	
0	NEXT LEADING SIGN AFTER pos [0] IS POSITIVE	
1	NEXT LEADING SIGN AFTER pos [0] IS NEGATIVE	
	⋮	
1	NEXT LEADING SIGN AFTER pos [0] IS NEGATIVE	
0	NEXT LEADING SIGN AFTER pos [0] IS POSITIVE	
1	NEXT LEADING SIGN AFTER pos [0] IS NEGATIVE	

5/24





FIG 5



7/24

TO STEP 308

FROM STEP 314, 320 OR 322





Fig. 7B

8/24

NMPVQ(n,k)=M(n,k)			
pos[0] value	NUMBER OF ENTRIES		
"k"	1		
NON-ZERO POSITIVE NEXT LEAD_SIGN	U(n,k)		
NON-ZERO NEGATIVE NEXT LEAD_SIGN	U(n,k)		
"0"		M(n-1,k)	
MPVQ-SIZE IS: NMPVQ(n,k)=M(n,k)=1+2*U(n,k)+M(n-1,k)			

Fig. 8



10/24





FIG 10



12/24

Fig. 12




Fig. 13





Fig. 14







Fig. 15



17/24

MAXIMUM BITS




Fig. 17A

R-MAX (bits/coeff)




Fig. 17B

18/24




Fig. 17C

ESTIMATED WORST CASE COMPLEXITY (MOPS)






Fig. 17D

Fig. 18



20/24



21/24




Fig. 20

22/24




Fig. 21

23/24




Fig. 22

24/24




Fig. 23




FIG 5