



(12) **DEMANDE DE BREVET CANADIEN**
CANADIAN PATENT APPLICATION
(13) **A1**

(86) Date de dépôt PCT/PCT Filing Date: 2015/11/06 (87) Date publication PCT/PCT Publication Date: 2017/03/30 (85) Entrée phase nationale/National Entry: 2018/03/22 (86) N° demande PCT/PCT Application No.: CN 2015/094029 (87) N° publication PCT/PCT Publication No.: 2017/049744 (30) Priorité/Priority: 2015/09/25 (CN PCT/CN2015/090750)	(51) Cl.Int./Int.Cl. <i>H04W 52/10</i> (2009.01) (71) Demandeur/Applicant: HUAWEI TECHNOLOGIES CO., LTD., CN (72) Inventeurs/Inventors: YAN, ZHIYU, CN; LYU, YONGXIA, CN; GUAN, LEI, CN; MA, SHA, CN (74) Agent: GOWLING WLG (CANADA) LLP
--	---

(54) Titre : PROCÉDE ET APPAREIL DE REGULATION DE PUISSANCE POUR CANAL DE COMMANDE DE LIAISON MONTANTE
(54) Title: POWER CONTROL METHOD AND APPARATUS FOR UPLINK CONTROL CHANNEL




FIG. 1

(57) **Abrégé/Abstract:**

Embodiments of the present invention provide a power control method and apparatus for an uplink control channel. The method comprises: a user equipment determines to send first uplink control information on a first PUCCH on a time point of a subframe i ; the user equipment determines to send a transmit power of the first uplink control information on the first PUCCH on the time point of the subframe i ; and the user equipment sends the first uplink control information on the first PUCCH by using a power not greater than the transmit power. In the embodiments of the present invention, a transmit power is determined according to a sum of a basic power adjustment value and any one of a first power adjustment value determined by the number of bits of the first uplink control information, a second power adjustment value determined by the number of bits of the first uplink control information and the number of resources of the first PUCCH, a third power adjustment value determined by a ratio of the number of bits of the first uplink control information to the number of resources of the first PUCCH, a fourth power adjustment value and a fifth power adjustment value, and accordingly a method for determining the transmit power is provided.

ABSTRACT

Embodiments of the present invention provide a power control method and apparatus for an uplink control channel. The method includes: determining, by user equipment, to send first uplink control information on a first PUCCH and in a subframe i ;
5 determining transmit power for sending the first uplink control information on the first PUCCH and in the subframe i ; and sending the first uplink control information on the first PUCCH by using power that is not greater than the transmit power. In the embodiments of the present invention, the transmit power is determined by using a sum of a base power adjustment value and any one of a first power adjustment value determined according to a
10 quantity of bits of the first uplink control information, a second power adjustment value determined according to the quantity of the bits of the first uplink control information and a quantity of resources of the first PUCCH, or a third power adjustment value, a fourth power adjustment value, or a fifth power adjustment value that is determined according to a ratio of the quantity of the bits of the first uplink control information to the quantity of the resources
15 of the first PUCCH. Therefore, a method for determining the transmit power is provided.

POWER CONTROL METHOD AND APPARATUS FOR UPLINK CONTROL CHANNEL

TECHNICAL FIELD

[0001] Embodiments of the present invention relate to the field of communications technologies, and in particular, to a power control method and apparatus for an uplink control channel.

BACKGROUND

[0002] In a Long Term Evolution (Long Term Evolution, LTE for short) system, service transmission is based on scheduling by a network device. A basic time unit for scheduling is one subframe. One subframe includes multiple time-domain symbols. A specific scheduling process is: The network device configures multiple carriers for user equipment, where each carrier includes at least one physical uplink shared channel (Physical Uplink Shared Channel, PUSCH for short); the network device sends control information to the user equipment; the user equipment sends, according to the control information and on a PUSCH indicated by the network device, uplink data, uplink control information, or both uplink data and uplink control information; in addition, one of the multiple carriers includes a physical uplink control channel (Physical Uplink Control Channel, PUCCH for short), and the user equipment sends uplink control information on the PUCCH.

[0003] In the prior art, transmit power $P_{\text{PUCCH}}(i)$ for sending, by user equipment, uplink control information on a PUCCH and in a subframe i is determined according to a formula (1):

$$P_{\text{PUCCH}}(i) = \min \left\{ P_{\text{CMAX,c}}(i), P_{0\_ \text{PUCCH}} + PL_c + h(n_{\text{CQI}}, n_{\text{HARQ}}, n_{\text{SR}}) + \Delta_{\text{F\_PUCCH}}(F) + \Delta_{\text{TXD}}(F') + g(i) \right\} \quad (1),$$

where

$P_{\text{CMAX},c}(i)$ is maximum transmit power of the user equipment; $P_{\text{O\_PUCCH}}$ is a value configured for the user equipment by a network device by using higher layer signaling, and is used to describe target receive power of a PUCCH; PL_c is a path loss that is estimated by the user equipment and that is of a downlink of a cell c in which the PUCCH is located; n_{CQI} ,
 5 n_{HARQ} , and n_{SR} are respectively quantities of bits of a CQI, a HARQ-ACK, and an SR that are to be fed back by the user equipment, where a total of the quantities of bits of the CQI, the HARQ-ACK, and the SR that are to be fed back by the user equipment is not greater than 22 bits; $\Delta_{\text{F\_PUCCH}}(F)$ is one of power offset values that are configured for the user equipment by the network device and that are of a format of a current PUCCH relative to a second PUCCH
 10 format; $\Delta_{\text{TxD}}(F')$ is a power adjustment value that is configured for the user equipment by the network device and that is used when the PUCCH in a first PUCCH format uses multi-antenna transmit diversity; and $g(i)$ is a power adjustment value that is in the subframe i and that is configured for the user equipment by the network device by using physical layer signaling.

15 **[0004]** In the prior art, transmit power $P_{\text{PUSCH},c}(i)$ for sending, by the user equipment, information on a PUSCH of a cell c and in the subframe i is determined according to a formula (2) and a formula (3):

when the user equipment sends information simultaneously on the PUSCH and the PUCCH:

20
$$P_{\text{PUSCH},c}(i) = \min \left\{ P_{\text{CMAX},c}(i), 10 \log_{10}(M_{\text{PUSCH},c}(i)) + P_{\text{O\_PUSCH},c}(j) + \alpha_c(j) \cdot PL_c + \Delta_{\text{TF},c}(i) + f_c(i) \right\} \quad (2); \text{ or}$$

when the user equipment sends information not simultaneously on the PUSCH and the PUCCH:

$$P_{\text{PUSCH},c}(i) = \min \left\{ 10 \log_{10}(P_{\text{CMAX},c}(i) - P_{\text{PUCCH}}(i)), 10 \log_{10}(M_{\text{PUSCH},c}(i)) + P_{\text{O\_PUSCH},c}(j) + \alpha_c(j) \cdot PL_c + \Delta_{\text{TF},c}(i) + f_c(i) \right\} \quad (3).$$

[0005] The current channel format of the PUCCH is any one of a PUCCH format 1, 1a,
 25 1b, 2, 2a, 2b, or 3. Herein, it is defined that the first PUCCH format is different from any one

of the PUCCH format 1, 1a, 1b, 2, 2a, 2b, or 3, the second PUCCH format is the PUCCH format 1a, and a third PUCCH format is different from the first PUCCH format and different from any one of the PUCCH format 1, 1a, 1b, 2, 2a, 2b, or 3. For a PUCCH in the first PUCCH format or the third PUCCH format, the user equipment is incapable of determining, according to transmit power used for sending information on an existing PUSCH or PUCCH, transmit power for sending information on the PUCCH in the first PUCCH format or the third PUCCH format.

SUMMARY

[0006] Embodiments of the present invention provide a power control method and apparatus for an uplink control channel, so as to determine transmit power for sending information on a PUCCH in a first PUCCH format.

[0007] A first aspect provides a power control method for an uplink control channel, including:

determining, by user equipment, to send first uplink control information on a first PUCCH and in a subframe i , where the first uplink control information includes at least one of channel state information CSI, a hybrid automatic repeat request-acknowledgment HARQ-ACK, or a scheduling request SR;

determining, by the user equipment, transmit power for sending the first uplink control information on the first PUCCH and in the subframe i , where the transmit power is a sum of a base power adjustment value and any one of a first power adjustment value, a second power adjustment value, a third power adjustment value, a fourth power adjustment value, or a fifth power adjustment value; and

sending, by the user equipment, the first uplink control information on the first PUCCH by using power that is not greater than the transmit power, where

the first power adjustment value is a power adjustment value determined by the user equipment according to a quantity of bits of the first uplink control information, the second power adjustment value is a power adjustment value determined by the user

equipment according to the quantity of the bits of the first uplink control information and a quantity of resources of the first PUCCH, the third power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, the fourth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH, and the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to a quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to the quantity of the resources of the first PUCCH, where the second uplink control information is a subset of the first uplink control information; and

the base power adjustment value includes a sum of P_{O_PUCCH} and PL_c , or the base power adjustment value includes a sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, where

P_{O_PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling;

PL_c is a path loss that is determined by the user equipment and that is of a downlink of a cell c in which the first PUCCH is located; and

α_c is a path loss factor that is configured for the user equipment by the network device and that is of the cell c in which the first PUCCH is located.

[0008] With reference to the first aspect, in a first possible implementation of the first aspect, the quantity of the bits of the first uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the first uplink control information, and the quantity of the bits of the second uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the second uplink control information.

[0009] With reference to the first aspect or the first possible implementation of the first aspect, in a second possible implementation of the first aspect, the first PUCCH is in a first physical uplink control channel PUCCH format, and the PUCCH in the first PUCCH format is characterized in that:

- 5 the PUCCH occupies at least one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or two time-domain symbols in each timeslot bear a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal; or
- 10 the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or
- a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

- [0010] With reference to any one of the first aspect to the second possible implementation of the first aspect, in a third possible implementation of the first aspect, if a quantity of RBs
- 15 occupied by the first PUCCH is not greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the first power adjustment value and the base power adjustment value, or the transmit power is a sum of the second power adjustment value and the base power adjustment value; or
- 20 value; or

if a quantity of RBs occupied by the first PUCCH is greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the third power adjustment value and the base power adjustment value, where

- 25 N_u is 1, 2, 3, or 4.

[0011] With reference to any one of the first aspect to the third possible implementation of the first aspect, in a fourth possible implementation of the first aspect, the quantity of the resources of the first PUCCH is K_{RE} , a quantity of modulation symbols occupied by the first

PUCCH; or

the quantity of the resources of the first PUCCH is Q' , a quantity of bits corresponding to modulation symbols occupied by the first PUCCH, where $Q' = K_{RE} * Q_m$, and Q_m is a modulation order used by the user equipment for sending the first uplink control information on the first PUCCH; or

the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, a quantity of RBs included in the first PUCCH; and

the quantity of the resources occupied on the first PUCCH by the second uplink control information is M_{RE} , a quantity of modulation symbols occupied on the first PUCCH by the second uplink control information; or

the quantity of the resources occupied on the first PUCCH by the second uplink control information is Q'' , a quantity of bits corresponding to modulation symbols occupied on the first PUCCH by the second uplink control information, where $Q'' = M_{RE} * Q'_m$, and Q'_m is a modulation order used by the user equipment for sending the second uplink control information on the first PUCCH.

[0012] With reference to any one of the first aspect to the fourth possible implementation of the first aspect, in a fifth possible implementation of the first aspect, the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $h'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ where } 0.05 \leq K_1 \leq 0.08, \text{ and } 5 \leq K_2 \leq 7.$$

[0013] With reference to any one of the first aspect to the fourth possible implementation of the first aspect, in a sixth possible implementation of the first aspect, the second power adjustment value determined according to the quantity of the bits of the first uplink control

5 information and the quantity of the resources of the first PUCCH is $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$,

where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

[0014] With reference to the sixth possible implementation of the first aspect, in a seventh possible implementation of the first aspect,

10 $h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n_{bit}(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$,

15 and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,

and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$;

20 if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$,

and $6.8 \leq P_2 \leq 10$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,

and $8 \leq P_3 \leq 12.6$;

if $n_{bit}(i)$ is greater than 128 and $n_{bit}(i)$ is not greater than 256, $h'(n_{bit}(i)) = P_4$,

and $10.6 \leq P_4 \leq 17.7$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

5 [0015] With reference to any one of the first aspect to the fourth possible implementation of the first aspect, in an eighth possible implementation of the first aspect, the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n'_{bit}(i)$ indicates a quantity of bits obtained by subtracting the quantity of the bits of the cyclic redundancy code CRC corresponding to the second uplink control information from the quantity of the bits of the second uplink control information, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value of $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n'_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

15 [0016] With reference to the eighth possible implementation of the first aspect, in a ninth possible implementation of the first aspect, $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$,

and $-1.6 \leq K_2 \leq -0.7$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.03 \leq K_1 \leq 0.05$,

20 and $-0.3 \leq K_2 \leq 0.5$.

[0017] With reference to the eighth possible implementation of the first aspect, in a tenth possible implementation of the first aspect,

$h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, where when $M_{RB}^{PUCCH}(i) = 1$,

$h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where $0.05 \leq K_1 \leq 0.075$, and $-2.2 \leq K_2 \leq -1.1$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where $0.03 \leq K_1 \leq 0.08$, and $-0.6 \leq K_2 \leq 0.1$.

[0018] With reference to any one of the first aspect to the fourth possible implementation of the first aspect, in an eleventh possible implementation of the first aspect, the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $k(m(i), M_{RB}^{PUCCH}(i))$, where $m(i)$ indicates the ratio of the quantity of the bits of the first uplink control information sent by the user equipment on the first PUCCH to the quantity of the resources of the first PUCCH, and a value of $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$.

[0019] With reference to the eleventh possible implementation of the first aspect, in a twelfth possible implementation of the first aspect, when the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, the quantity of the RBs included in the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$;

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$q'(m(i)) = K_1 \cdot m(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$;

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and

$$6.8 \leq P_2 \leq 10;$$

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $8 \leq P_3 \leq 12.6$;

if $m(i)$ is greater than 128 and $m(i)$ is not greater than 256, $q'(m(i)) = P_4$, and $10.6 \leq P_4 \leq 17.7$; or

$$q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ where } 0.02 \leq K_1 \leq 0.04, \text{ and } 5.5 \leq K_2 \leq 7.5.$$

[0020] With reference to the eleventh possible implementation of the first aspect, in a thirteenth possible implementation of the first aspect, when the quantity of the resources of the first PUCCH is K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $8 \leq K_1 \leq 11$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $8.5 \leq K_1 \leq 10.5$, and $6 \leq K_2 \leq 8$.

[0021] With reference to any one of the first aspect to the fourth possible implementation of the first aspect, in a fourteenth possible implementation of the first aspect, the determining the third power adjustment value according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH includes:

determining the third power adjustment value according to a ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, where the third power adjustment value is $10 \log_{10}(M_{RB}^{PUCCH}(i)) + 10 \log_{10}((2^{K_S \cdot BP_{RE}} - 1) \cdot \beta_{offset}^{PUCCH})$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, BP_{RE} is the ratio of the quantity of the bits of the

first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_s is a value configured for the user equipment by the network device by using higher layer signaling.

5 [0022] With reference to any one of the fourteenth possible implementation of the first aspect, in a fifteenth possible implementation of the first aspect, β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following:

- 10 a channel quality indicator CQI and/or a precoding matrix indicator PMI;
a hybrid automatic repeat request HARQ-ACK; or
a rank indication RI; and

if the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

[0023] With reference to any one of the first aspect to the fourth possible implementation of the first aspect, in a sixteenth possible implementation of the first aspect, the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH is
20 $10 \log_{10}(M_{RB}^{PUCCH}(i))$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH.

[0024] With reference to any one of the first aspect to the fourth possible implementation of the first aspect, in a seventeenth possible implementation of the first aspect, the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink
25

control information to the quantity of the resources of the first PUCCH is $R(r(i), M_{RB}^{PUCCH}(i))$,
 where $r(i)$ indicates the ratio of the quantity of the bits of the second uplink control
 information to the quantity of the resources occupied on the first PUCCH by the second
 uplink control information or the ratio of the quantity of the bits of the second uplink control
 5 information to the quantity of the resources of the first PUCCH, and a value of
 $R(r(i), M_{RB}^{PUCCH}(i))$ is determined by $r(i)$ and $M_{RB}^{PUCCH}(i)$.

[0025] With reference to the first aspect or the first possible implementation of the first
 aspect, in an eighteenth possible implementation of the first aspect, the first PUCCH is in a
 third physical uplink control channel PUCCH format, and the PUCCH in the third PUCCH
 10 format is characterized in that:

the PUCCH occupies one RB, and in a case of a normal cyclic prefix, only one
 time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a
 demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain
 symbol in each timeslot bears a demodulation reference signal, where uplink control
 15 information of at least two user equipments is capable of being sent on the PUCCH by means
 of code division; or

the PUCCH is capable of encoding the first uplink control information according
 to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that
 20 the PUCCH is capable of bearing is greater than 22.

[0026] With reference to any one of the first aspect or the first or the eighteenth possible
 implementation of the first aspect, in a nineteenth possible implementation of the first aspect,
 the first power adjustment value determined according to the quantity of the bits of the first
 uplink control information is $k'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of
 25 the first uplink control information sent on the first PUCCH; and

$$k'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ where } 0.08 \leq K_1 \leq 0.12, \text{ and } -3.7 \leq K_2 \leq -2.7.$$

[0027] With reference to any one of the first aspect or the first or the eighteenth possible
 implementation of the first aspect, in a twentieth possible implementation of the first aspect,

the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $10 \log_{10} \left(\left(2^{K_S \cdot BPRE} - 1 \right) \cdot \beta_{offset}^{PUCCH} \right)$, where $BPRE$ is a ratio of the quantity of the bits of the first uplink control information to K_{RE} , a quantity of modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

[0028] With reference to the twentieth possible implementation of the first aspect, in a twenty-first possible implementation of the first aspect, β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following:

- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
 - a hybrid automatic repeat request HARQ-ACK; or
 - a rank indication RI; and
- if the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

[0029] A second aspect provides a power control method for an uplink control channel, including:

- determining, by a network device, that user equipment is to send first uplink control information on a first PUCCH and in a subframe i , where the first uplink control information includes at least one of channel state information CSI, a hybrid automatic repeat request-acknowledgment HARQ-ACK, or a scheduling request SR;
- determining, by the network device, transmit power for sending, by the user

equipment, the first uplink control information on the first PUCCH and in the subframe i , where the transmit power is a sum of a base power adjustment value and any one of a first power adjustment value, a second power adjustment value, a third power adjustment value, a fourth power adjustment value, or a fifth power adjustment value; and

5 receiving, by the network device, the first uplink control information that is sent by the user equipment on the first PUCCH by using power that is not greater than the transmit power, where

the first power adjustment value is a power adjustment value determined by the user equipment according to a quantity of bits of the first uplink control information, the
 10 second power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the bits of the first uplink control information and a quantity of resources of the first PUCCH, the third power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of the quantity of the bits of the first uplink control
 15 information to the quantity of the resources of the first PUCCH, the fourth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH, and the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to a
 20 quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to the quantity of the resources of the first PUCCH, where the second uplink control information is a subset of the first uplink
 25 control information; and

the base power adjustment value includes a sum of P_{O_PUCCH} and PL_c , or the base power adjustment value includes a sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, where

P_{O_PUCCH} is a value configured for the user equipment by the network device by

using higher layer signaling;

PL_c is a path loss that is determined by the user equipment and that is of a downlink of a cell c in which the first PUCCH is located; and

α_c is a path loss factor that is configured for the user equipment by the network device and that is of the cell c in which the first PUCCH is located.

[0030] With reference to the second aspect, in a first possible implementation of the second aspect, the quantity of the bits of the first uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the first uplink control information, and the quantity of the bits of the second uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the second uplink control information.

[0031] With reference to the second aspect or the first possible implementation of the second aspect, in a second possible implementation of the second aspect, the first PUCCH is in a first physical uplink control channel PUCCH format, and the PUCCH in the first PUCCH format is characterized in that:

the PUCCH occupies at least one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or two time-domain symbols in each timeslot bear a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

[0032] With reference to any one of the second aspect to the second possible implementation of the second aspect, in a third possible implementation of the second aspect, if a quantity of RBs occupied by the first PUCCH is not greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH

and in the subframe i is a sum of the first power adjustment value and the base power adjustment value, or the transmit power is a sum of the second power adjustment value and the base power adjustment value; or

if a quantity of RBs occupied by the first PUCCH is greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the third power adjustment value and the base power adjustment value, where

N_u is 1, 2, 3, or 4.

[0033] With reference to any one of the second aspect to the third possible implementation of the second aspect, in a fourth possible implementation of the second aspect, the quantity of the resources of the first PUCCH is K_{RE} , a quantity of modulation symbols occupied by the first PUCCH; or

the quantity of the resources of the first PUCCH is Q' , a quantity of bits corresponding to modulation symbols occupied by the first PUCCH, where $Q' = K_{RE} * Q_m$, and Q_m is a modulation order used by the user equipment for sending the first uplink control information on the first PUCCH; or

the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, a quantity of RBs included in the first PUCCH; and

the quantity of the resources occupied on the first PUCCH by the second uplink control information is M_{RE} , a quantity of modulation symbols occupied on the first PUCCH by the second uplink control information; or

the quantity of the resources occupied on the first PUCCH by the second uplink control information is Q'' , a quantity of bits corresponding to modulation symbols occupied on the first PUCCH by the second uplink control information, where $Q'' = M_{RE} * Q'_m$, and Q'_m is a modulation order used by the user equipment for sending the second uplink control

information on the first PUCCH.

[0034] With reference to any one of the second aspect to the fourth possible implementation of the second aspect, in a fifth possible implementation of the second aspect, the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $h'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$,

and $8.2 \leq P_2 \leq 12.12$;

10 if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,

and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

[0035] With reference to any one of the second aspect to the fourth possible implementation of the second aspect, in a sixth possible implementation of the second aspect,

15 the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is

$h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink

control information sent on the first PUCCH, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included

in the first PUCCH, and a value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n_{bit}(i)$ and

20 $M_{RB}^{PUCCH}(i)$.

[0036] With reference to the sixth possible implementation of the second aspect, in a seventh possible implementation of the second aspect,

$h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n_{bit}(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$;

25 if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$,
and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,
and $11.4 \leq P_3 \leq 17.24$; or

5 $h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$,
and $6.8 \leq P_2 \leq 10$;

10 if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,
and $8 \leq P_3 \leq 12.6$;

if $n_{bit}(i)$ is greater than 128 and $n_{bit}(i)$ is not greater than 256, $h'(n_{bit}(i)) = P_4$,
and $10.6 \leq P_4 \leq 17.7$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

15 [0037] With reference to any one of the second aspect to the fourth possible
implementation of the second aspect, in an eighth possible implementation of the second
aspect, the second power adjustment value determined according to the quantity of the bits of
the first uplink control information and the quantity of the resources of the first PUCCH is
20 $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n'_{bit}(i)$ indicates a quantity of bits obtained by subtracting the
quantity of the bits of the cyclic redundancy code CRC corresponding to the second uplink
control information from the quantity of the bits of the second uplink control information,
 $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value of
 $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n'_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

[0038] With reference to the eighth possible implementation of the second aspect, in a

ninth possible implementation of the second aspect,

$$h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i)), \text{ where}$$

$$\text{when } M_{RB}^{PUCCH}(i) = 1, \quad h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2, \quad \text{where } 0.05 \leq K_1 \leq 0.08,$$

and $-1.6 \leq K_2 \leq -0.7$; or

$$5 \quad \text{when } M_{RB}^{PUCCH}(i) = 2, \quad h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2, \quad \text{where } 0.03 \leq K_1 \leq 0.05,$$

and $-0.3 \leq K_2 \leq 0.5$.

[0039] With reference to the eighth possible implementation of the second aspect, in a

tenth possible implementation of the second aspect,

$$h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i)), \quad \text{where when } M_{RB}^{PUCCH}(i) = 1,$$

$$10 \quad h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2, \quad \text{where } 0.05 \leq K_1 \leq 0.075, \quad \text{and } -2.2 \leq K_2 \leq -1.1; \text{ or}$$

$$\text{when } M_{RB}^{PUCCH}(i) = 2, \quad h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2, \quad \text{where}$$

$$0.03 \leq K_1 \leq 0.08, \quad \text{and } -0.6 \leq K_2 \leq 0.1.$$

[0040] With reference to any one of the second aspect to the fourth possible

implementation of the second aspect, in an eleventh possible implementation of the second

15 aspect, the third power adjustment value determined according to the quantity of the resources

of the first PUCCH and the ratio of the quantity of the bits of the first uplink control

information to the quantity of the resources of the first PUCCH is $k(m(i), M_{RB}^{PUCCH}(i))$, where

$m(i)$ indicates the ratio of the quantity of the bits of the first uplink control information sent

by the user equipment on the first PUCCH to the quantity of the resources of the first PUCCH,

20 and a value of $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$.

[0041] With reference to the eleventh possible implementation of the second aspect, in a

twelfth possible implementation of the second aspect, when the quantity of the resources of

the first PUCCH is $M_{RB}^{PUCCH}(i)$, the quantity of the RBs included in the first PUCCH,

$$k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i)), \quad \text{where}$$

$$25 \quad \text{when } M_{RB}^{PUCCH}(i) = 1;$$

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and
 5 $11.4 \leq P_3 \leq 17.24$; or

$q'(m(i)) = K_1 \cdot m(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$;

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and
 10 $6.8 \leq P_2 \leq 10$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and
 $8 \leq P_3 \leq 12.6$;

if $m(i)$ is greater than 128 and $m(i)$ is not greater than 256, $q'(m(i)) = P_4$, and
 $10.6 \leq P_4 \leq 17.7$; or

15 $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

[0042] With reference to the eleventh possible implementation of the second aspect, in a thirteenth possible implementation of the second aspect, when the quantity of the resources of the first PUCCH is K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$, where

20 when $M_{RB}^{PUCCH}(i) = 1$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $8 \leq K_1 \leq 11$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $8.5 \leq K_1 \leq 10.5$, and $6 \leq K_2 \leq 8$.

[0043] With reference to any one of the second aspect to the fourth possible implementation of the second aspect, in a fourteenth possible implementation of the second aspect, the determining the third power adjustment value according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH includes:

determining the third power adjustment value according to a ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, where the third power adjustment value is $10\log_{10}(M_{RB}^{PUCCH}(i)) + 10\log_{10}\left((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH}\right)$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, $BPRE$ is the ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

[0044] With reference to any one of the fourteenth possible implementation of the second aspect, in a fifteenth possible implementation of the second aspect, β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following:

- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
- a hybrid automatic repeat request HARQ-ACK; or
- a rank indication RI; and

if the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

[0045] With reference to any one of the second aspect to the fourth possible

implementation of the second aspect, in a sixteenth possible implementation of the second aspect, the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH is $10\log_{10}(M_{RB}^{PUCCH}(i))$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH.

5 [0046] With reference to any one of the second aspect to the fourth possible implementation of the second aspect, in a seventeenth possible implementation of the second aspect, the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second
10 uplink control information or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH is $R(r(i), M_{RB}^{PUCCH}(i))$, where $r(i)$ indicates the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by
15 the second uplink control information or the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH, and a value of $R(r(i), M_{RB}^{PUCCH}(i))$ is determined by $r(i)$ and $M_{RB}^{PUCCH}(i)$.

[0047] With reference to the second aspect or the first possible implementation of the second aspect, in an eighteenth possible implementation of the second aspect, the first
20 PUCCH is in a third physical uplink control channel PUCCH format, and the PUCCH in the third PUCCH format is characterized in that:

the PUCCH occupies one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain
25 symbol in each timeslot bears a demodulation reference signal, where uplink control information of at least two user equipments is capable of being sent on the PUCCH by means of code division; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

[0048] With reference to any one of the second aspect or the first or the eighteenth possible implementation of the second aspect, in a nineteenth possible implementation of the second aspect, the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $k'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

$$k'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ where } 0.08 \leq K_1 \leq 0.12, \text{ and } -3.7 \leq K_2 \leq -2.7.$$

[0049] With reference to any one of the second aspect or the first or the eighteenth possible implementation of the second aspect, in a twentieth possible implementation of the second aspect, the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $10\log_{10}((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH})$, where $BPRE$ is a ratio of the quantity of the bits of the first uplink control information to K_{RE} , a quantity of modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

[0050] With reference to the twentieth possible implementation of the second aspect, in a twenty-first possible implementation of the second aspect, β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following:

- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
 - a hybrid automatic repeat request HARQ-ACK; or
 - a rank indication RI; and
- if the first uplink control information includes the HARQ-ACK or the RI, the

first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

[0051] A third aspect provides user equipment, including:

- 5 a first processing unit, configured to: determine that first uplink control information is to be sent on a first PUCCH and in a subframe i , where the first uplink control information includes at least one of channel state information CSI, a hybrid automatic repeat request-acknowledgment HARQ-ACK, or a scheduling request SR; determine transmit power for sending the first uplink control information on the first PUCCH and in the
- 10 subframe i , where the transmit power is a sum of a base power adjustment value and any one of a first power adjustment value, a second power adjustment value, a third power adjustment value, a fourth power adjustment value, or a fifth power adjustment value; and
- a sending unit, configured to send the first uplink control information on the first PUCCH by using power that is not greater than the transmit power, where
- 15 the first power adjustment value is a power adjustment value determined by the user equipment according to a quantity of bits of the first uplink control information, the second power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the bits of the first uplink control information and a quantity of resources of the first PUCCH, the third power adjustment value is a power
- 20 adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, the fourth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH, and the fifth power adjustment value is a power
- 25 adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to a quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a

quantity of bits of second uplink control information to the quantity of the resources of the first PUCCH, where the second uplink control information is a subset of the first uplink control information; and

the base power adjustment value includes a sum of P_{O_PUCCH} and PL_c , or the
 5 base power adjustment value includes a sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, where

P_{O_PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling;

PL_c is a path loss that is determined by the user equipment and that is of a downlink of a cell c in which the first PUCCH is located; and

10 α_c is a path loss factor that is configured for the user equipment by the network device and that is of the cell c in which the first PUCCH is located.

[0052] With reference to the third aspect, in a first possible implementation of the third aspect, the quantity of the bits of the first uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the first uplink control information,
 15 and the quantity of the bits of the second uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the second uplink control information.

[0053] With reference to the third aspect or the first possible implementation of the third aspect, in a second possible implementation of the third aspect, the first PUCCH is in a first physical uplink control channel PUCCH format, and the PUCCH in the first PUCCH format
 20 is characterized in that:

the PUCCH occupies at least one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or two time-domain symbols in each timeslot bear a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain
 25 symbol in each timeslot bears a demodulation reference signal; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that

the PUCCH is capable of bearing is greater than 22.

[0054] With reference to any one of the third aspect to the second possible implementation of the third aspect, in a third possible implementation of the third aspect, if a quantity of RBs occupied by the first PUCCH is not greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the first power adjustment value and the base power adjustment value, or the transmit power is a sum of the second power adjustment value and the base power adjustment value; or

if a quantity of RBs occupied by the first PUCCH is greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the third power adjustment value and the base power adjustment value, where

N_u is 1, 2, 3, or 4.

[0055] With reference to any one of the third aspect to the third possible implementation of the third aspect, in a fourth possible implementation of the third aspect, the quantity of the resources of the first PUCCH is K_{RE} , a quantity of modulation symbols occupied by the first PUCCH; or

the quantity of the resources of the first PUCCH is Q' , a quantity of bits corresponding to modulation symbols occupied by the first PUCCH, where $Q' = K_{RE} * Q_m$, and Q_m is a modulation order used by the user equipment for sending the first uplink control information on the first PUCCH; or

the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, a quantity of RBs included in the first PUCCH; and

the quantity of the resources occupied on the first PUCCH by the second uplink control information is M_{RE} , a quantity of modulation symbols occupied on the first PUCCH by the second uplink control information; or

the quantity of the resources occupied on the first PUCCH by the second uplink control information is Q'' , a quantity of bits corresponding to modulation symbols occupied on the first PUCCH by the second uplink control information, where $Q'' = M_{RE} * Q_m'$, and Q_m' is a modulation order used by the user equipment for sending the second uplink control information on the first PUCCH.

[0056] With reference to any one of the third aspect to the fourth possible implementation of the third aspect, in a fifth possible implementation of the third aspect, the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $h'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

[0057] With reference to any one of the third aspect to the fourth possible implementation of the third aspect, in a sixth possible implementation of the third aspect, the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

[0058] With reference to the sixth possible implementation of the third aspect, in a seventh possible implementation of the third aspect,

$$h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n_{bit}(i)), \text{ where}$$

$$\text{when } M_{RB}^{PUCCH}(i) = 1;$$

$$\text{if } n_{bit}(i) \text{ is not greater than } 22, h'(n_{bit}(i)) = P_1, \text{ and } 6.1 \leq P_1 \leq 8.76;$$

$$\text{if } n_{bit}(i) \text{ is greater than } 22 \text{ and } n_{bit}(i) \text{ is not greater than } 64, h'(n_{bit}(i)) = P_2,$$

$$\text{and } 8.2 \leq P_2 \leq 12.12;$$

$$\text{if } n_{bit}(i) \text{ is greater than } 64 \text{ and } n_{bit}(i) \text{ is not greater than } 128, h'(n_{bit}(i)) = P_3,$$

$$\text{and } 11.4 \leq P_3 \leq 17.24; \text{ or}$$

$$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ where } 0.05 \leq K_1 \leq 0.08, \text{ and } 5 \leq K_2 \leq 7; \text{ or}$$

$$\text{when } M_{RB}^{PUCCH}(i) = 2;$$

$$\text{if } n_{bit}(i) \text{ is not greater than } 22, h'(n_{bit}(i)) = P_1, \text{ and } 5.9 \leq P_1 \leq 8.4;$$

$$\text{if } n_{bit}(i) \text{ is greater than } 22 \text{ and } n_{bit}(i) \text{ is not greater than } 64, h'(n_{bit}(i)) = P_2,$$

$$\text{and } 6.8 \leq P_2 \leq 10;$$

$$\text{if } n_{bit}(i) \text{ is greater than } 64 \text{ and } n_{bit}(i) \text{ is not greater than } 128, h'(n_{bit}(i)) = P_3,$$

$$\text{and } 8 \leq P_3 \leq 12.6;$$

$$\text{if } n_{bit}(i) \text{ is greater than } 128 \text{ and } n_{bit}(i) \text{ is not greater than } 256, h'(n_{bit}(i)) = P_4,$$

$$\text{and } 10.6 \leq P_4 \leq 17.7; \text{ or}$$

$$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ where } 0.02 \leq K_1 \leq 0.04, \text{ and } 5.5 \leq K_2 \leq 7.5.$$

[0059] With reference to any one of the third aspect to the fourth possible implementation of the third aspect, in an eighth possible implementation of the third aspect, the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n'_{bit}(i)$ indicates a quantity of bits obtained by subtracting the quantity of the bits of the cyclic redundancy code CRC corresponding to the second uplink control information from

the quantity of the bits of the second uplink control information, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value of $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n'_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

[0060] With reference to the eighth possible implementation of the third aspect, in a ninth possible implementation of the third aspect,

$$h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i)), \text{ where}$$

when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $-1.6 \leq K_2 \leq -0.7$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.03 \leq K_1 \leq 0.05$, and $-0.3 \leq K_2 \leq 0.5$.

[0061] With reference to the eighth possible implementation of the third aspect, in a tenth possible implementation of the third aspect,

$$h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i)), \text{ where when } M_{RB}^{PUCCH}(i) = 1,$$

$h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where $0.05 \leq K_1 \leq 0.075$, and $-2.2 \leq K_2 \leq -1.1$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where $0.03 \leq K_1 \leq 0.08$, and $-0.6 \leq K_2 \leq 0.1$.

[0062] With reference to any one of the third aspect to the fourth possible implementation of the third aspect, in an eleventh possible implementation of the third aspect, the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $k(m(i), M_{RB}^{PUCCH}(i))$, where $m(i)$ indicates the ratio of the quantity of the bits of the first uplink control information sent by the user equipment on the first PUCCH to the quantity of the resources of the first PUCCH, and a value of $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$.

[0063] With reference to the eleventh possible implementation of the third aspect, in a

twelfth possible implementation of the third aspect, when the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, the quantity of the RBs included in the first PUCCH,

$$k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i)), \text{ where}$$

when $M_{RB}^{PUCCH}(i) = 1$:

5 if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

10 $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$:

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $6.8 \leq P_2 \leq 10$;

15 if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $8 \leq P_3 \leq 12.6$;

if $m(i)$ is greater than 128 and $m(i)$ is not greater than 256, $q'(m(i)) = P_4$, and $10.6 \leq P_4 \leq 17.7$; or

$$q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ where } 0.02 \leq K_1 \leq 0.04, \text{ and } 5.5 \leq K_2 \leq 7.5.$$

20 **[0064]** With reference to the eleventh possible implementation of the third aspect, in a thirteenth possible implementation of the third aspect, when the quantity of the resources of the first PUCCH is K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $8 \leq K_1 \leq 11$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $8.5 \leq K_1 \leq 10.5$, and $6 \leq K_2 \leq 8$.

5 [0065] With reference to any one of the third aspect to the fourth possible implementation of the third aspect, in a fourteenth possible implementation of the third aspect, the determining the third power adjustment value according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH includes:

10 determining the third power adjustment value according to a ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, where the third power adjustment value is $10\log_{10}(M_{RB}^{PUCCH}(i)) + 10\log_{10}\left((2^{K_S \cdot BP_{RE}} - 1) \cdot \beta_{offset}^{PUCCH}\right)$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, BP_{RE} is the ratio of the quantity of the bits of the

15 first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

[0066] With reference to any one of the third aspect to the fourteenth possible

20 implementation of the third aspect, in a fifteenth possible implementation of the third aspect, β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following:

a channel quality indicator CQI and/or a precoding matrix indicator PMI;

25 a hybrid automatic repeat request HARQ-ACK; or

a rank indication RI; and

if the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

5 [0067] With reference to any one of the third aspect to the fourth possible implementation of the third aspect, in a sixteenth possible implementation of the third aspect, the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH is $10\log_{10}(M_{RB}^{PUCCH}(i))$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH.

10 [0068] With reference to any one of the third aspect to the fourth possible implementation of the third aspect, in a seventeenth possible implementation of the third aspect, the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control
15 information or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH is $R(r(i), M_{RB}^{PUCCH}(i))$, where $r(i)$ indicates the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second
20 uplink control information or the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH, and a value of $R(r(i), M_{RB}^{PUCCH}(i))$ is determined by $r(i)$ and $M_{RB}^{PUCCH}(i)$.

[0069] With reference to the third aspect or the first possible implementation of the third aspect, in an eighteenth possible implementation of the third aspect, the first PUCCH is in a
25 third physical uplink control channel PUCCH format, and the PUCCH in the third PUCCH format is characterized in that:

the PUCCH occupies one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a

demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal, where uplink control information of at least two user equipments is capable of being sent on the PUCCH by means of code division; or

- 5 the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

- [0070] With reference to any one of the third aspect or the first or the eighteenth possible
10 implementation of the third aspect, in a nineteenth possible implementation of the third aspect, the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $k'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

$$k'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ where } 0.08 \leq K_1 \leq 0.12, \text{ and } -3.7 \leq K_2 \leq -2.7.$$

- 15 [0071] With reference to any one of the third aspect or the first or the eighteenth possible implementation of the third aspect, in a twentieth possible implementation of the third aspect, the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $10 \log_{10} \left((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH} \right)$, where
20 $BPRE$ is a ratio of the quantity of the bits of the first uplink control information to K_{RE} , a quantity of modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

- 25 [0072] With reference to the twentieth possible implementation of the third aspect, in a twenty-first possible implementation of the third aspect, β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when

first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following:

a channel quality indicator CQI and/or a precoding matrix indicator PMI;

a hybrid automatic repeat request HARQ-ACK; or

5 a rank indication RI; and

if the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

10 **[0073]** A fourth aspect provides a network device, including:

a second processing unit, configured to: determine that user equipment is to send first uplink control information on a first PUCCH and in a subframe i , where the first uplink control information includes at least one of channel state information CSI, a hybrid automatic repeat request-acknowledgment HARQ-ACK, or a scheduling request SR; determine transmit power for sending the first uplink control information on the first PUCCH and in the subframe i , where the transmit power is a sum of a base power adjustment value and any one of a first power adjustment value, a second power adjustment value, a third power adjustment value, a fourth power adjustment value, or a fifth power adjustment value; and

20 a receiving unit, configured to receive the first uplink control information that is sent by the user equipment on the first PUCCH by using power that is not greater than the transmit power, where

the first power adjustment value is a power adjustment value determined by the user equipment according to a quantity of bits of the first uplink control information, the second power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the bits of the first uplink control information and a quantity of resources of the first PUCCH, the third power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, the fourth power adjustment

value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH, and the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to a quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to the quantity of the resources of the first PUCCH, where the second uplink control information is a subset of the first uplink control information; and

the base power adjustment value includes a sum of P_{O_PUCCH} and PL_c , or the base power adjustment value includes a sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, where

P_{O_PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling;

PL_c is a path loss that is determined by the user equipment and that is of a downlink of a cell c in which the first PUCCH is located; and

α_c is a path loss factor that is configured for the user equipment by the network device and that is of the cell c in which the first PUCCH is located.

[0074] With reference to the fourth aspect, in a first possible implementation of the fourth aspect, the quantity of the bits of the first uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the first uplink control information, and the quantity of the bits of the second uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the second uplink control information.

[0075] With reference to the fourth aspect or the first possible implementation of the fourth aspect, in a second possible implementation of the fourth aspect, the first PUCCH is in a first physical uplink control channel PUCCH format, and the PUCCH in the first PUCCH format is characterized in that:

the PUCCH occupies at least one RB, and in a case of a normal cyclic prefix, only

one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or two time-domain symbols in each timeslot bear a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal; or

5 the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

[0076] With reference to any one of the fourth aspect to the second possible
10 implementation of the fourth aspect, in a third possible implementation of the fourth aspect, if a quantity of RBs occupied by the first PUCCH is not greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the first power adjustment value and the base power adjustment value, or the transmit power is a sum of the second power adjustment value and
15 the base power adjustment value; or

if a quantity of RBs occupied by the first PUCCH is greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the third power adjustment value and the base power adjustment value, where

20 N_u is 1, 2, 3, or 4.

[0077] With reference to any one of the fourth aspect to the third possible implementation of the fourth aspect, in a fourth possible implementation of the fourth aspect, the quantity of the resources of the first PUCCH is K_{RE} , a quantity of modulation symbols occupied by the first PUCCH; or

25 the quantity of the resources of the first PUCCH is Q' , a quantity of bits corresponding to modulation symbols occupied by the first PUCCH, where $Q' = K_{RE} * Q_m$, and Q_m is a modulation order used by the user equipment for sending the first uplink control

information on the first PUCCH; or

the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, a quantity of RBs included in the first PUCCH; and

the quantity of the resources occupied on the first PUCCH by the second uplink control information is M_{RE} , a quantity of modulation symbols occupied on the first PUCCH by the second uplink control information; or

the quantity of the resources occupied on the first PUCCH by the second uplink control information is Q'' , a quantity of bits corresponding to modulation symbols occupied on the first PUCCH by the second uplink control information, where $Q'' = M_{RE} * Q'_m$, and Q'_m is a modulation order used by the user equipment for sending the second uplink control information on the first PUCCH.

[0078] With reference to any one of the fourth aspect to the fourth possible implementation of the fourth aspect, in a fifth possible implementation of the fourth aspect, the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $h'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

[0079] With reference to any one of the fourth aspect to the fourth possible implementation of the fourth aspect, in a sixth possible implementation of the fourth aspect, the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is

$h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

5 [0080] With reference to the sixth possible implementation of the fourth aspect, in a seventh possible implementation of the fourth aspect, $h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n_{bit}(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

10 if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$,
and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,

and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

15 when $M_{RB}^{PUCCH}(i) = 2$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$,

and $6.8 \leq P_2 \leq 10$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,

20 and $8 \leq P_3 \leq 12.6$;

if $n_{bit}(i)$ is greater than 128 and $n_{bit}(i)$ is not greater than 256, $h'(n_{bit}(i)) = P_4$,

and $10.6 \leq P_4 \leq 17.7$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

[0081] With reference to any one of the fourth aspect to the fourth possible implementation of the fourth aspect, in an eighth possible implementation of the fourth aspect, the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is

5 $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n'_{bit}(i)$ indicates a quantity of bits obtained by subtracting the quantity of the bits of the cyclic redundancy code CRC corresponding to the second uplink control information from the quantity of the bits of the second uplink control information, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value of $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n'_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

10 [0082] With reference to the eighth possible implementation of the fourth aspect, in a ninth possible implementation of the fourth aspect, $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $-1.6 \leq K_2 \leq -0.7$; or

15 when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.03 \leq K_1 \leq 0.05$, and $-0.3 \leq K_2 \leq 0.5$.

[0083] With reference to the eighth possible implementation of the fourth aspect, in a tenth possible implementation of the fourth aspect, $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, where when $M_{RB}^{PUCCH}(i) = 1$,

20 $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where $0.05 \leq K_1 \leq 0.075$, and $-2.2 \leq K_2 \leq -1.1$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where $0.03 \leq K_1 \leq 0.08$, and $-0.6 \leq K_2 \leq 0.1$.

[0084] With reference to any one of the fourth aspect to the fourth possible implementation of the fourth aspect, in an eleventh possible implementation of the fourth aspect, the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control

25

information to the quantity of the resources of the first PUCCH is $k(m(i), M_{RB}^{PUCCH}(i))$, where $m(i)$ indicates the ratio of the quantity of the bits of the first uplink control information sent by the user equipment on the first PUCCH to the quantity of the resources of the first PUCCH, and a value of $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$.

- 5 [0085] With reference to the eleventh possible implementation of the fourth aspect, in a twelfth possible implementation of the fourth aspect, when the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, the quantity of the RBs included in the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$;

- 10 if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

- 15 $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$;

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $6.8 \leq P_2 \leq 10$;

- 20 if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $8 \leq P_3 \leq 12.6$;

if $m(i)$ is greater than 128 and $m(i)$ is not greater than 256, $q'(m(i)) = P_4$, and $10.6 \leq P_4 \leq 17.7$; or

$$q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ where } 0.02 \leq K_1 \leq 0.04, \text{ and } 5.5 \leq K_2 \leq 7.5.$$

[0086] With reference to the eleventh possible implementation of the fourth aspect, in a thirteenth possible implementation of the fourth aspect, when the quantity of the resources of the first PUCCH is K_{RE} , the quantity of the modulation symbols occupied by the first

5 PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $8 \leq K_1 \leq 11$, and

$5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $8.5 \leq K_1 \leq 10.5$, and

$6 \leq K_2 \leq 8$.

10 [0087] With reference to any one of the first aspect to the fourth possible implementation of the fourth aspect, in a fourteenth possible implementation of the fourth aspect, the determining the third power adjustment value according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH includes:

15 determining the third power adjustment value according to a ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, where the third power adjustment value is $10 \log_{10}(M_{RB}^{PUCCH}(i)) + 10 \log_{10}((2^{K_S \cdot BP_{RE}} - 1) \cdot \beta_{offset}^{PUCCH})$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, BP_{RE} is the ratio of the quantity of the bits of the

20 first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

[0088] With reference to any one of the fourth aspect to the fourteenth possible implementation of the fourth aspect, in a fifteenth possible implementation of the fourth

25

aspect, β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following:

- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
 - 5 a hybrid automatic repeat request HARQ-ACK; or
 - a rank indication RI; and
- if the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control
- 10 information is the CQI and/or the PMI.

[0089] With reference to any one of the fourth aspect to the fourth possible implementation of the fourth aspect, in a sixteenth possible implementation of the fourth aspect, the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH is $10\log_{10}(M_{RB}^{PUCCH}(i))$, where $M_{RB}^{PUCCH}(i)$ is the quantity of

15 the RBs included in the first PUCCH.

[0090] With reference to any one of the fourth aspect to the fourth possible implementation of the fourth aspect, in a seventeenth possible implementation of the fourth aspect, the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control

20 information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH is

$R(r(i), M_{RB}^{PUCCH}(i))$, where $r(i)$ indicates the ratio of the quantity of the bits of the second

25 uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH, and a value of

$R(r(i), M_{RB}^{PUCCH}(i))$ is determined by $r(i)$ and $M_{RB}^{PUCCH}(i)$.

[0091] With reference to the fourth aspect or the first possible implementation of the fourth aspect, in an eighteenth possible implementation of the fourth aspect, the first PUCCH is in a third physical uplink control channel PUCCH format, and the PUCCH in the third PUCCH format is characterized in that:

5 the PUCCH occupies one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal, where uplink control information of at least two user equipments is capable of being sent on the PUCCH by means
10 of code division; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

15 [0092] With reference to any one of the fourth aspect or the first or the eighteenth possible implementation of the fourth aspect, in a nineteenth possible implementation of the fourth aspect, the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $k'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

20 $k'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.08 \leq K_1 \leq 0.12$, and $-3.7 \leq K_2 \leq -2.7$.

[0093] With reference to any one of the fourth aspect or the first or the eighteenth possible implementation of the fourth aspect, in a twentieth possible implementation of the fourth aspect, the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control
25 information to the quantity of the resources of the first PUCCH is $10 \log_{10} \left((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH} \right)$, where $BPRE$ is a ratio of the quantity of the bits of the first uplink control information to K_{RE} , a quantity of modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by

using higher layer signaling, and K_s is a value configured for the user equipment by the network device by using higher layer signaling.

[0094] With reference to the twentieth possible implementation of the fourth aspect, in a twenty-first possible implementation of the fourth aspect, β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following:

a channel quality indicator CQI and/or a precoding matrix indicator PMI;

a hybrid automatic repeat request HARQ-ACK; or

10 a rank indication RI; and

if the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

15 [0095] According to the power control method and apparatus for an uplink control channel that are provided in the embodiments of the present invention, the transmit power for sending the first uplink control information on the first PUCCH and in the subframe i is determined by the user equipment by using the sum of the base power adjustment value and any one of the first power adjustment value determined according to the quantity of the bits of the first uplink control information that is to be sent on the first PUCCH, the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH, the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH, the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment

value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH. Therefore, a method for determining the transmit power for sending the first uplink control information on the first PUCCH is provided.

5

BRIEF DESCRIPTION OF DRAWINGS

[0096] To describe the technical solutions in the embodiments of the present invention or in the prior art more clearly, the following briefly describes the accompanying drawings required for describing the embodiments or the prior art. Apparently, the accompanying drawings in the following description show some embodiments of the present invention, and
10 persons of ordinary skill in the art may still derive other drawings from these accompanying drawings without creative efforts.

[0097] FIG. 1 is a flowchart of a power control method for an uplink control channel according to an embodiment of the present invention;

[0098] FIG. 2 is a flowchart of a power control method for an uplink control channel
15 according to another embodiment of the present invention;

[0099] FIG. 3 is a structural diagram of user equipment according to an embodiment of the present invention;

[0100] FIG. 4 is a structural diagram of a network device according to an embodiment of the present invention; and

20 [0101] FIG. 5 is a structural diagram of a power control system for an uplink control channel according to an embodiment of the present invention.

DESCRIPTION OF EMBODIMENTS

[0102] To make the objectives, technical solutions, and advantages of the embodiments of the present invention clearer, the following clearly and completely describes the technical
25 solutions in the embodiments of the present invention with reference to the accompanying drawings in the embodiments of the present invention. Apparently, the described embodiments are some but not all of the embodiments of the present invention. All other

embodiments obtained by persons of ordinary skill in the art based on the embodiments of the present invention without creative efforts shall fall within the protection scope of the present invention.

[0103] FIG. 1 is a flowchart of a power control method for an uplink control channel according to an embodiment of the present invention. In this embodiment of the present invention, it is defined that a first physical uplink control channel PUCCH format, that is, a first PUCCH format, is different from any one of a PUCCH format 1, 1a, 1b, 2, 2a, 2b, or 3 in the prior art, a second physical uplink control channel PUCCH format, that is, a second PUCCH format, is the PUCCH format 1a, and a third physical uplink control channel PUCCH format, that is, a third PUCCH format, is different from the first PUCCH format and different from any one of the PUCCH format 1, 1a, 1b, 2, 2a, 2b, or 3 in the prior art. For a problem that user equipment cannot determine, according to transmit power used for sending information on an existing PUSCH or PUCCH, transmit power for sending information on a PUCCH in the first PUCCH format or the third PUCCH format, the power control method for an uplink control channel is provided. Specific steps of the method are as follows.

[0104] Step S101: User equipment determines to send first uplink control information on a first PUCCH and in a subframe i , where the first uplink control information includes at least one of channel state information CSI, a hybrid automatic repeat request-acknowledgment HARQ-ACK, or a scheduling request SR.

[0105] In the prior art, formats of a PUCCH include the format 1, the format 1a, the format 1b, the format 2, the format 2a, the format 2b, and the format 3. In this embodiment of the present invention, a format of the first PUCCH is the first physical uplink control channel PUCCH format, or a format of the first PUCCH is the third physical uplink control channel PUCCH format, and both the first PUCCH format and the third PUCCH format are different from any PUCCH format in the prior art.

[0106] A network device configures multiple PUCCHs for the user equipment. The user equipment determines the first PUCCH from the multiple PUCCHs, and sends the first uplink control information in the subframe i by using the first PUCCH. Alternatively, a network device instructs, by using physical layer signaling, the user equipment to send the first uplink

control information in the subframe i by using the first PUCCH. This embodiment of the present invention does not limit a method for determining the first PUCCH in the subframe i by the user equipment. The first uplink control information includes at least one of channel state information CSI, a hybrid automatic repeat request-acknowledgment HARQ-ACK, or a scheduling request SR. That is, the first uplink control information generated by the current user equipment may include one of the channel state information CSI, the hybrid automatic repeat request-acknowledgment HARQ-ACK, or the scheduling request SR; may include any two of the channel state information CSI, the hybrid automatic repeat request-acknowledgment HARQ-ACK, or the scheduling request SR; or may include all of the channel state information CSI, the hybrid automatic repeat request-acknowledgment HARQ-ACK, and the scheduling request SR.

[0107] Step S102: The user equipment determines transmit power for sending the first uplink control information on the first PUCCH and in the subframe i , where the transmit power is a sum of a base power adjustment value and any one of a first power adjustment value, a second power adjustment value, a third power adjustment value, a fourth power adjustment value, or a fifth power adjustment value.

[0108] The first power adjustment value is a power adjustment value determined by the user equipment according to a quantity of bits of the first uplink control information. The second power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the bits of the first uplink control information and a quantity of resources of the first PUCCH. The third power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH. The fourth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH. The fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to a quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth

power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to the quantity of the resources of the first PUCCH, where the second uplink control information is a subset of the first uplink control information.

5 [0109] The base power adjustment value includes a sum of P_{O_PUCCH} and PL_c , or the base power adjustment value includes a sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, where P_{O_PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, PL_c is a path loss that is determined by the user equipment and that is of a downlink of a cell c in which the first PUCCH is located, and α_c is a path loss factor that is configured for the user equipment by the network device and that is of the cell c in which the first PUCCH is located.

[0110] In this embodiment of the present invention, when the base power adjustment value includes the sum of P_{O_PUCCH} and PL_c , the base power adjustment value further includes at least one of $\Delta_{TxD}(F')$, $g(i)$, or $\Delta_{F\_PUCCH}(F)$. $\Delta_{TxD}(F')$ is a power adjustment value that is configured for the user equipment by the network device and that is used when the PUCCH in the first PUCCH format uses multi-antenna transmit diversity. Optionally, a value of $\Delta_{TxD}(F')$ is -2 dB or 0 dB. $g(i)$ is determined by using a sixth power adjustment value that is in the subframe i and that is configured for the user equipment by the network device by using physical control information. $\Delta_{F\_PUCCH}(F)$ is a power offset value that is configured for the user equipment by the network device and that is of a PUCCH in the first PUCCH format relative to a PUCCH in the second PUCCH format. Optionally, a value of $\Delta_{F\_PUCCH}(F)$ is one of -2 dB, 0 dB, 1 dB, or 2 dB. Preferably, the base power adjustment value in this embodiment of the present invention includes a sum of P_{O_PUCCH} , PL_c , $\Delta_{TxD}(F')$, $g(i)$, and $\Delta_{F\_PUCCH}(F)$, that is, the base power adjustment value is

25 $P_{O\_PUCCH} + PL_c + \Delta_{TxD}(F') + g(i) + \Delta_{F\_PUCCH}(F)$. Alternatively, preferably, the base power

adjustment value in this embodiment of the present invention includes a sum of P_{O_PUCCH} , PL_c , $g(i)$, and $\Delta_{F\_PUCCH}(F)$, that is, the base power adjustment value is $P_{O\_PUCCH} + PL_c + g(i) + \Delta_{F\_PUCCH}(F)$. Alternatively, preferably, the base power adjustment value in this embodiment of the present invention includes a sum of P_{O_PUCCH} , PL_c , and $g(i)$, that is, the base power adjustment value is $P_{O\_PUCCH} + PL_c + g(i)$.

[0111] When the base power adjustment value includes the sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, the base power adjustment value further includes $\Delta_{TF,c}(i)$ and/or $f_c(i)$. When $K_S = 0$, $\Delta_{TF,c}(i) = 0$; or when $K_S = 1.25$, $\Delta_{TF,c}(i) = 10 \log_{10} \left((2^{BP_{RE} \cdot K_S} - 1) \cdot \beta_{offset}^{PUCCH} \right)$. K_S is a parameter that is configured for the user equipment by the network device by using higher layer signaling and that is of the cell c in which the first PUCCH is located. β_{offset}^{PUCCH} is a parameter configured for the user equipment by the network device by using higher layer signaling, or β_{offset}^{PUCCH} is equal to 1. $BP_{RE} = O / N_{RE}$, where O is a quantity of bits of third uplink control information sent by the user equipment on the first PUCCH, the quantity of the bits of the third uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the third uplink control information, and N_{RE} is a quantity of modulation symbols occupied by the first PUCCH. The third uplink control information is a subset of the first uplink control information. $f_c(i)$ is a seventh power adjustment value that is in the subframe i and that is configured for the user equipment by the network device by using physical control information. Preferably, the base power adjustment value in this embodiment of the present invention includes a sum of P_{O_PUCCH} , $\alpha_c \cdot PL_c$, $\Delta_{TF,c}(i)$, and $f_c(i)$, that is, the base power adjustment value may be $P_{O\_PUCCH} + \alpha_c \cdot PL_c + \Delta_{TF,c}(i) + f_c(i)$. Alternatively, preferably, the base power adjustment value in this embodiment of the present invention includes a sum of P_{O_PUCCH} , $\alpha_c \cdot PL_c$, and $f_c(i)$, that is, the base power adjustment value may be $P_{O\_PUCCH} + \alpha_c \cdot PL_c + f_c(i)$.

[0112] In addition, in this embodiment of the present invention, $P_{O\_PUCCH} = P_{O\_PUSCH} + \Delta P$, where P_{O_PUSCH} and ΔP are values configured for the user equipment by the network device by using higher layer signaling, and α_c may be equal to 1.

[0113] Step S103: The user equipment sends the first uplink control information on the first PUCCH by using power that is not greater than the transmit power.

[0114] If the transmit power determined in the foregoing step is greater than a maximum transmit power of the user equipment, the user equipment sends the first uplink control information on the first PUCCH by using the maximum transmit power. If the transmit power determined in the foregoing step is not greater than a maximum transmit power of the user equipment, the user equipment sends the first uplink control information on the first PUCCH by using the transmit power.

[0115] In this embodiment of the present invention, the transmit power for sending the first uplink control information on the first PUCCH and in the subframe i is determined by the user equipment by using the sum of the base power adjustment value and any one of the first power adjustment value determined according to the quantity of the bits of the first uplink control information that is to be sent on the first PUCCH, the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH, the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH, the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH. Therefore, a method for determining the transmit power for sending the first

uplink control information on the first PUCCH is provided.

[0116] Based on the foregoing embodiment, the quantity of the bits of the first uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the first uplink control information, and the quantity of the bits of the second uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the second uplink control information.

[0117] The first PUCCH is in the first physical uplink control channel PUCCH format. The PUCCH in the first PUCCH format is characterized in that: the PUCCH occupies at least one RB, and in a case of a normal cyclic prefix (Normal Cyclic Prefix, normal CP for short), only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or two time-domain symbols in each timeslot bear a demodulation reference signal, or in a case of an extended cyclic prefix (Extended Cyclic Prefix, extended CP for short), the third time-domain symbol in each timeslot bears a demodulation reference signal; or the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

[0118] The quantity of the resources of the first PUCCH is K_{RE} , a quantity of modulation symbols occupied by the first PUCCH. Alternatively, the quantity of the resources of the first PUCCH is Q' , a quantity of bits corresponding to modulation symbols occupied by the first PUCCH, where $Q' = K_{RE} * Q_m$, and Q_m is a modulation order used by the user equipment for sending the first uplink control information on the first PUCCH. Alternatively, the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, a quantity of RBs included in the first PUCCH.

[0119] The quantity of the resources occupied on the first PUCCH by the second uplink control information is M_{RE} , a quantity of modulation symbols occupied on the first PUCCH by the second uplink control information. Alternatively, the quantity of the resources occupied on the first PUCCH by the second uplink control information is Q'' , a quantity of bits

corresponding to modulation symbols occupied on the first PUCCH by the second uplink control information, where $Q'' = M_{RE} * Q_m'$, and Q_m' is a modulation order used by the user equipment for sending the second uplink control information on the first PUCCH.

[0120] Specifically, $K_{RE} = M_{sc}^{PUCCH} \cdot N_{\text{syb}}^{PUCCH}$, where M_{sc}^{PUCCH} is a quantity of subcarriers
 5 of the first PUCCH, and N_{syb}^{PUCCH} is a quantity of OFDM symbols of the first PUCCH. For QPSK, $Q_m = 2$. For 16QAM, $Q_m = 4$.

[0121] This embodiment of the present invention specifically defines characteristics of the PUCCH in the first PUCCH format, to distinguish between the PUCCH in the first PUCCH format and a PUCCH in an existing PUCCH format, and also specifically defines a method
 10 for determining the quantity of the resources of the first PUCCH and the quantity of the resources occupied on the first PUCCH by the second uplink control information.

[0122] Based on the foregoing embodiment, a specific method for determining the transmit power includes the following five cases. Optionally, if a quantity of RBs occupied by the first PUCCH is not greater than N_u , the transmit power for sending, by the user
 15 equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the first power adjustment value and the base power adjustment value, or the transmit power is a sum of the second power adjustment value and the base power adjustment value. If a quantity of RBs occupied by the first PUCCH is greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first
 20 PUCCH and in the subframe i is a sum of the third power adjustment value and the base power adjustment value. N_u is 1, 2, 3, or 4.

[0123] First case: The first power adjustment value determined according to the quantity of the bits of the first uplink control information is $h'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH.

25 [0124] In the first case, the transmit power is a sum of the first power adjustment value $h'(n_{bit}(i))$ and the base power adjustment value

$P_{O\_PUCCH} + PL_c + \Delta_{TxD}(F') + g(i) + \Delta_{F\_PUCCH}(F)$. The transmit power is

$P_{PUCCH}(i) = P_{O\_PUCCH} + PL_c + h'(n_{bit}(i)) + \Delta_{F\_PUCCH}(F) + \Delta_{TxD}(F') + g(i)$. A value of $h'(n_{bit}(i))$

is determined by $n_{bit}(i)$. A specific determining relationship is as follows:

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$,

5 if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$,

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,

and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

10 [0125] Preferably, $K_1 = 0.07$, and $K_2 = 5.6$. Alternatively, preferably, $K_1 = 0.06$, and $K_2 = 6.2$.

[0126] $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent

on the first PUCCH. For example, $n_{bit}(i)$ may be specifically expressed as

$n_{bit}(i) = n_{CSI} + n_{HARQ} + n_{SR}$, where n_{CSI} is a quantity of bits of the channel state information

15 CSI, n_{HARQ} is a quantity of bits of the hybrid automatic repeat request-acknowledgment

HARQ-ACK, n_{SR} is a quantity of bits of the scheduling request SR, and any one of n_{CSI} ,

n_{HARQ} , or n_{SR} may be 0.

[0127] Second case: The second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of

20 the first PUCCH is $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of

the first uplink control information sent on the first PUCCH, $M_{RB}^{PUCCH}(i)$ is the quantity of

the RBs included in the first PUCCH, and a value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by

$n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

[0128] In the second case, the transmit power is a sum of the second power adjustment

value $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ and the base power adjustment value

$P_{O\_PUCCH} + PL_c + \Delta_{TxD}(F') + g(i) + \Delta_{F\_PUCCH}(F)$. The transmit power is

$P_{PUCCH}(i) = P_{O\_PUCCH} + PL_c + h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) + \Delta_{F\_PUCCH}(F) + \Delta_{TxD}(F') + g(i)$, where

5 $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ indicates the second power adjustment value, $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH, and a

value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$. A specific determining relationship is as follows:

$$h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n_{bit}(i)).$$

10 [0129] When $M_{RB}^{PUCCH}(i) = 1$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,

15 and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

[0130] Preferably, $K_1 = 0.07$, and $K_2 = 5.6$. Alternatively, preferably, $K_1 = 0.06$, and $K_2 = 6.2$.

[0131] When $M_{RB}^{PUCCH}(i) = 2$;

20 if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $6.8 \leq P_2 \leq 10$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,

and $8 \leq P_3 \leq 12.6$;

if $n_{bit}(i)$ is greater than 128 and $n_{bit}(i)$ is not greater than 256, $h'(n_{bit}(i)) = P_4$,

and $10.6 \leq P_4 \leq 17.7$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

5 [0132] Preferably, $K_1 = 0.03$, and $K_2 = 6.7$.

[0133] Alternatively, in the second case, the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n'_{bit}(i)$ indicates a quantity of bits obtained by subtracting the quantity of the bits of the cyclic redundancy code
10 CRC corresponding to the second uplink control information from the quantity of the bits of the second uplink control information, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value of $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n'_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

[0134] Preferably, $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, where when
15 $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $-1.6 \leq K_2 \leq -0.7$; or when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.03 \leq K_1 \leq 0.05$, and $-0.3 \leq K_2 \leq 0.5$.

[0135] Alternatively, preferably, $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$,
where when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where $0.05 \leq K_1 \leq 0.075$,
20 and $-2.2 \leq K_2 \leq -1.1$; or when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where $0.03 \leq K_1 \leq 0.08$, and $-0.6 \leq K_2 \leq 0.1$.

[0136] When the second power adjustment value is $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, the transmit
power is $P_{PUCCH}(i) = P_{0\_PUCCH} + PL_c + h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) + \Delta_{F\_PUCCH}(F) + \Delta_{TxD}(F) + g(i)$

or $P_{\text{PUCCH}}(i) = P_{0\_ \text{PUCCH}} + \alpha_c \cdot PL_c + h'(n'_{\text{bit}}(i), M_{\text{RB}}^{\text{PUCCH}}(i)) + \Delta_{F\_ \text{PUCCH}}(F) + \Delta_{\text{TxD}}(F') + f_c(i)$.

[0137] When the first PUCCH is in the first physical uplink control channel PUCCH format, and the PUCCH in the first physical uplink control channel PUCCH format does not support a transmit diversity solution, the transmit power is

5 $P_{\text{PUCCH}}(i) = P_{0\_ \text{PUCCH}} + PL_c + h'(n'_{\text{bit}}(i), M_{\text{RB}}^{\text{PUCCH}}(i)) + \Delta_{F\_ \text{PUCCH}}(F) + g(i)$ or

$P_{\text{PUCCH}}(i) = P_{0\_ \text{PUCCH}} + \alpha_c \cdot PL_c + h'(n'_{\text{bit}}(i), M_{\text{RB}}^{\text{PUCCH}}(i)) + \Delta_{F\_ \text{PUCCH}}(F) + f_c(i)$, where $P_{0\_ \text{PUCCH}}$

is a value configured for the user equipment by the network device by using higher layer signaling, and is used to determine the transmit power of the first PUCCH in the first physical

uplink control channel. $P_{0\_ \text{PUCCH}}$ is determined by a cell-level parameter $P_{0\_ \text{NOMINAL\_ PUCCH\_2}}$

10 and a user-level parameter $P_{0\_ \text{UE\_ PUCCH\_2}}$ that are configured for the user equipment by the network device. In the prior art, a network device configures a cell-level parameter

$P_{0\_ \text{NOMINAL\_ PUCCH\_1}}$ and a user-level parameter $P_{0\_ \text{UE\_ PUCCH\_1}}$ for the user equipment by using

higher layer signaling. A value of $P_{0\_ \text{NOMINAL\_ PUCCH\_1}}$ ranges from -127 dBm to -96 dBm. A

value of $P_{0\_ \text{UE\_ PUCCH\_1}}$ ranges from -8 dB to 7 dB. A sum $P_{0\_ \text{PUCCH\_1}}$ of values of the two

15 parameters is configured for the user equipment by the network device and is used to adjust

transmit power for performing, by the user equipment, sending on a PUCCH in an existing

PUCCH format (including the PUCCH format 1, the PUCCH format 1a, the PUCCH format

1b, the PUCCH format 2, the PUCCH format 2a, the PUCCH format 2b, and the PUCCH

format 3). In the prior art, the network device further configures a cell-level parameter

20 $P_{0\_ \text{NOMINAL\_ PUSCH}}$ and a user-level parameter $P_{0\_ \text{UE\_ PUSCH}}$ for the user equipment by using

higher layer signaling. A value of $P_{0\_ \text{NOMINAL\_ PUSCH}}$ ranges from -126 dBm to 24 dBm. A

value of $P_{0\_ \text{UE\_ PUSCH}}$ ranges from -8 dB to 7 dB. A sum $P_{0\_ \text{PUSCH}}$ of values of the two

parameters is configured for the user equipment by the network device and is used to adjust

transmit power for performing, by the user equipment, sending on a PUSCH. $P_{0\_ \text{PUCCH}}$ is

25 determined by the cell-level parameter $P_{0\_ \text{NOMINAL\_ PUCCH\_2}}$ and the user-level parameter

$P_{O\_UE\_PUCCH\_2}$ that are configured for the user equipment by the network device. $P_{O\_NOMINAL\_PUCCH\_2}$ may be any one of the cell-level parameter $P_{O\_NOMINAL\_PUCCH\_1}$ or $P_{O\_NOMINAL\_PUSCH}$ that is configured for an existing PUCCH format by the network device, or may be determined by another parameter configured by the network device. $P_{O\_UE\_PUCCH\_2}$ may be any one of the user-level parameter $P_{O\_UE\_PUCCH\_1}$ or $P_{O\_UE\_PUSCH}$ that is configured for an existing PUCCH format by the network device, or may be determined by another parameter configured by the network device. If $P_{O\_NOMINAL\_PUCCH\_2}$ is determined by the another parameter configured by the network device, a value of the parameter ranges from -126 dBm to 24 dBm. If $P_{O\_UE\_PUCCH\_2}$ is determined by the another parameter configured by the network device, a value of the parameter ranges from -8 dB to 7 dB.

[0138] $\Delta_{F\_PUCCH}(F)$ is the power offset value that is configured for the user equipment by the network device and that is of the PUCCH in the first PUCCH format relative to the PUCCH in the second PUCCH format.

[0139] $g(i)$ and $f_c(i)$ indicate power adjustment values that are sent to the user equipment by the network device by using a physical downlink control channel.

[0140] Third case: The third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $k(m(i), M_{RB}^{PUCCH}(i))$, where $m(i)$ indicates the ratio of the quantity of the bits of the first uplink control information sent by the user equipment on the first PUCCH to the quantity of the resources of the first PUCCH, and a value of $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$. In this case, the transmit power is the sum of the third power adjustment value $k(m(i), M_{RB}^{PUCCH}(i))$ and the base power adjustment value $P_{O\_PUCCH} + PL_c + \Delta_{TXD}(F') + g(i) + \Delta_{F\_PUCCH}(F)$. The transmit power is $P_{PUCCH}(i) = P_{O\_PUCCH} + PL_c + k(m(i), M_{RB}^{PUCCH}(i)) + \Delta_{F\_PUCCH}(F) + \Delta_{TXD}(F') + g(i)$, where

$k(m(i), M_{RB}^{PUCCH}(i))$ indicates the third power adjustment value, $m(i)$ indicates the ratio of the quantity of the bits of the first uplink control information sent by the user equipment on the first PUCCH to the quantity of the resources of the first PUCCH, and a value of $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$. A specific determining relationship is as follows.

[0141] When the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, the quantity of the RBs included in the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$.

[0142] When $M_{RB}^{PUCCH}(i) = 1$:

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

10 if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$q'(m(i)) = K_1 \cdot m(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

15 [0143] Preferably, $K_1 = 0.07$, and $K_2 = 5.6$. Alternatively, preferably, $K_1 = 0.06$, and $K_2 = 6.2$.

[0144] When $M_{RB}^{PUCCH}(i) = 2$:

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and

20 $6.8 \leq P_2 \leq 10$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $8 \leq P_3 \leq 12.6$;

if $m(i)$ is greater than 128 and $m(i)$ is not greater than 256, $q'(m(i)) = P_4$, and

$10.6 \leq P_4 \leq 17.7$; or

$$q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ where } 0.02 \leq K_1 \leq 0.04, \text{ and } 5.5 \leq K_2 \leq 7.5.$$

[0145] Preferably, $K_1 = 0.03$, and $K_2 = 6.7$.

[0146] When the quantity of the resources of the first PUCCH is K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH,
 $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$.

[0147] When $M_{RB}^{PUCCH}(i) = 1$:

$$q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ where } 8 \leq K_1 \leq 11, \text{ and } 5 \leq K_2 \leq 7.$$

[0148] Preferably, $K_1 = 8.4$, and $K_2 = 6.3$.

10 [0149] When $M_{RB}^{PUCCH}(i) = 2$:

$$q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ where } 8.5 \leq K_1 \leq 10.5, \text{ and } 6 \leq K_2 \leq 8.$$

[0150] Preferably, $K_1 = 9.5$, and $K_2 = 6.7$.

[0151] Alternatively, the determining the third power adjustment value according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH includes:

determining the third power adjustment value according to a ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, where the third power adjustment value is $10 \log_{10}(M_{RB}^{PUCCH}(i)) + 10 \log_{10}((2^{K_S \cdot BP_{RE}} - 1) \cdot \beta_{offset}^{PUCCH})$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, BP_{RE} is the ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

[0152] Preferably, $K_s = 1.25$. In this case, the transmit power is the sum of the third power adjustment value $10 \log_{10}(M_{RB}^{PUCCH}(i)) + 10 \log_{10}((2^{1.25 BPRE} - 1) \cdot \beta_{offset}^{PUCCH})$ and the base power adjustment value $P_{O\_PUCCH} + PL_c + g(i)$, that is, the transmit power of the PUCCH is $P_{PUCCH}(i) = P_{O\_PUCCH} + PL_c + 10 \log_{10}(M_{RB}^{PUCCH}(i)) + 10 \log_{10}((2^{1.25 BPRE} - 1) \cdot \beta_{offset}^{PUCCH}) + g(i)$.

5 [0153] Alternatively, the transmit power is the sum of the third power adjustment value $10 \log_{10}(M_{RB}^{PUCCH}(i)) + 10 \log_{10}((2^{1.25 BPRE} - 1) \cdot \beta_{offset}^{PUCCH})$ and the base power adjustment value $P_{O\_PUCCH} + \alpha_c \cdot PL_c + f_c(i)$, that is, the transmit power of the PUCCH is $P_{PUCCH}(i) = P_{O\_PUCCH} + \alpha_c \cdot PL_c + 10 \log_{10}(M_{RB}^{PUCCH}(i)) + 10 \log_{10}((2^{1.25 BPRE} - 1) \cdot \beta_{offset}^{PUCCH}) + f_c(i)$, where P_{O_PUCCH} is the same as P_{O_PUCCH} in the second case, PL_c is the path loss that is

10 determined by the user equipment and that is of the downlink of the cell c in which the first PUCCH is located, α_c is the path loss factor that is configured for the user equipment by the network device and that is of the cell c in which the first PUCCH is located, $g(i)$ is the same as $g(i)$ in the second case, and $f_c(i)$ is the same as $f_c(i)$ in the second case.

[0154] β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following: a channel quality indicator CQI and/or a precoding matrix indicator PMI, a hybrid automatic repeat request HARQ-ACK, or a rank indication RI. If the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the

20 RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

[0155] In the prior art, the network device configures parameters "betaOffset-ACK-Index", "betaOffset-RI-Index", and "betaOffset-CQI-Index" for the user equipment by using higher layer signaling. The parameters are respectively used to determine parameters $\beta_{offset}^{HARQ-ACK}$,

25 β_{offset}^{RI} , and β_{offset}^{CQI} that are required when the user equipment determines a quantity of PUSCH

modulation symbols occupied for sending HARQ-ACK, rank indication RI (Rank Indication), and channel quality indicator CQI (Channel Quality Indicator)/precoding matrix indicator PMI (Precoding Matrix Indicator) information on a single-codeword PUSCH. Values of the parameters are integers within $[0,15]$. The network device configures parameters

5 "betaOffset-ACK-Index-MC-r10", "betaOffset-RI-Index-MC-r10", and "betaOffset-CQI-Index-MC-r10" for the user equipment by using higher layer signaling. The parameters are respectively used to determine the parameters $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , and β_{offset}^{CQI} that are required when the user equipment determines a quantity of PUSCH modulation symbols occupied for sending the HARQ-ACK, RI, and CQI/PMI information on a

10 multi-codeword PUSCH. Optionally, the user equipment determines that the quantity of the PUSCH modulation symbols occupied for sending the HARQ-ACK, RI, and CQI/PMI information on the multi-codeword PUSCH are a product of $\beta_{offset}^{HARQ-ACK}$ and a first ratio, a product of β_{offset}^{RI} and the first ratio, and a product of β_{offset}^{CQI} and the first ratio respectively.

The first ratio is $\frac{O \cdot M_{RE}}{R}$, where O is a quantity of bits of the HARQ-ACK, the RI, or the

15 CQI/PMI (if CRC parity bits are added before channel encoding when the HARQ-ACK, RI, or CQI/PMI information is transmitted on the PUSCH, the quantity of the bits includes a bit quantity of CRC parity bits corresponding to the HARQ-ACK, RI, or CQI/PMI information), M_{RE} is a quantity of modulation symbols of the PUSCH, and R is a quantity of bits of uplink data sent on the PUSCH.

20 [0156] Optionally, $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , and β_{offset}^{CQI} are ratios of a first quantity of modulation symbols to a second quantity of modulation symbols. The first quantity of modulation symbols is a quantity of modulation symbols of the PUSCH that are occupied when first encoded modulation symbols obtained by encoding and modulating uplink control information of the HARQ-ACK, RI, or CQI/PMI are sent on the PUSCH. The second quantity

25 of modulation symbols is a quantity of modulation symbols of the PUSCH that are occupied when second encoded modulation symbols obtained by encoding and modulating uplink data are sent on the PUSCH. A quantity of the first encoded modulation symbols is equal to a

quantity of the second encoded modulation symbols.

- [0157] β_{offset}^{PUCCH} in the third power adjustment value may be one of the parameter $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , or β_{offset}^{CQI} that is corresponding to a parameter configured for the UE by the network device.
- 5 [0158] β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be $\beta_{offset}^{HARQ-ACK}$ corresponding to the parameter "betaOffset-ACK-Index" or "betaOffset-ACK-Index-MC-r10" that is configured for the UE by the network device. $\beta_{offset}^{HARQ-ACK}$ corresponding to the parameter "betaOffset-ACK-Index" is preferred.
- 10 [0159] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be β_{offset}^{RI} corresponding to the parameter "betaOffset-RI-Index" or "betaOffset-RI-Index-MC-r10" that is configured for the UE by the network device. β_{offset}^{RI} corresponding to the parameter "betaOffset-RI-Index" is preferred.
- 15 [0160] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" or "betaOffset-CQI-Index-MC-r10" that is configured for the UE by the network device. β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" is preferred.
- 20 [0161] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" or "betaOffset-CQI-Index-MC-r10" that is configured for the UE by the network device. β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" is preferred.

[0162] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be one of $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , or β_{offset}^{CQI} that is corresponding to a parameter configured for the UE by the network device. Specifically, if the first uplink control information includes the HARQ-ACK or the RI, β_{offset}^{PUCCH} in the third power adjustment value may be $\beta_{offset}^{HARQ-ACK}$ or β_{offset}^{RI} that is corresponding to a parameter configured for the UE by the network device; if the first uplink control information does not include the HARQ-ACK and the RI, β_{offset}^{PUCCH} in the third power adjustment value may be β_{offset}^{CQI} that is corresponding to a parameter configured for the UE by the network device.

[0163] It should be noted that if the quantity of the resources of the PUCCH in the first PUCCH format is fixedly one RB, the third power adjustment value is a power adjustment value determined by the user equipment according to the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, and impact of the quantity of the resources of the first PUCCH on the third power adjustment value may not be considered.

[0164] Fourth case: The fourth power adjustment value determined according to the quantity of the resources of the first PUCCH is $10\log_{10}(M_{RB}^{PUCCH}(i))$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH.

[0165] In the fourth case, the transmit power is a sum of the fourth power adjustment value $10\log_{10}(M_{RB}^{PUCCH}(i))$ and the base power adjustment value $P_{O\_PUCCH} + \alpha_c \cdot PL_c + \Delta_{TF,c}(i) + f_c(i)$. The transmit power is $P_{PUCCH}(i) = 10\log_{10}(M_{RB}^{PUCCH}(i)) + P_{O\_PUCCH} + \alpha_c \cdot PL_c + \Delta_{TF,c}(i) + f_c(i)$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH.

[0166] Fifth case: The fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by

the second uplink control information or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH is $R(r(i), M_{RB}^{PUCCH}(i))$, where $r(i)$ indicates the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH, and a value of $R(r(i), M_{RB}^{PUCCH}(i))$ is determined by $r(i)$ and $M_{RB}^{PUCCH}(i)$.

[0167] In the fifth case, the transmit power is a sum of the fifth power adjustment value and the base power adjustment value. The second uplink control information is a subset of the first uplink control information, and the second uplink control information is at least one type of uplink control information with a highest priority in the first uplink control information. A priority sequence includes at least one of the following cases: a priority of the HARQ-ACK is higher than a priority of the CSI, a priority of the SR is equal to or higher than a priority of the HARQ-ACK, a priority of an RI/PTI in the CSI is higher than a priority of a CQI/PMI in the CSI, or a priority of an RI/PTI in the CSI is equal to a priority of the HARQ-ACK. Alternatively, the second uplink control information is at least one type of uplink control information that is in the first uplink control information and that is used to determine a benchmark of a quantity of resources occupied on the first PUCCH by each piece of control information in the first uplink control information. For example, a quantity of resources occupied on the first PUCCH by other control information may be determined according to a preset ratio or difference between the quantity of the resources occupied on the first PUCCH by the other control information and a quantity of resources occupied on the first PUCCH by the at least one type of uplink control information.

[0168] It should be noted that if the quantity of the resources of the PUCCH in the first PUCCH format is fixedly one RB, the fifth power adjustment value is a power adjustment value determined by the user equipment according to the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or a power adjustment value determined by

the user equipment according to the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH, and impact of the quantity of the resources of the first PUCCH on the fifth power adjustment value may not be considered.

5 [0169] In addition, the first PUCCH may be in the third physical uplink control channel PUCCH format. The PUCCH in the third PUCCH format is characterized in that: the PUCCH occupies one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears
10 a demodulation reference signal, where uplink control information of at least two user equipments is capable of being sent on the PUCCH by means of code division; or the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

15 [0170] When the first PUCCH is in the third physical uplink control channel PUCCH format, the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $k'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

$$k'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ where } 0.08 \leq K_1 \leq 0.12, \text{ and } -3.7 \leq K_2 \leq -2.7.$$

20 [0171] In this case, the transmit power is the sum of the first power adjustment value $k'(n_{bit}(i))$ and the base power adjustment value $P_{O\_PUCCH} + PL_c + g(i) + \Delta_{F\_PUCCH}(F)$, that is, the transmit power is $P_{PUCCH}(i) = P_{O\_PUCCH} + PL_c + k'(n_{bit}(i)) + \Delta_{F\_PUCCH}(F) + g(i)$.

[0172] When the first PUCCH is in the third physical uplink control channel PUCCH format, the third power adjustment value determined according to the quantity of the RBs
25 included in the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH is $10 \log_{10}((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH})$, where $BPRE$ is the ratio of the quantity of the bits of the

first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

5 [0173] Preferably, $K_S = 1.25$. In this case, the transmit power is the sum of the third power adjustment value $10 \log_{10} \left(\left(2^{1.25 BP_{RE}} - 1 \right) \cdot \beta_{offset}^{PUCCH} \right)$ and the base power adjustment value $P_{O\_PUCCH} + PL_c + g(i)$, that is, the transmit power is $P_{PUCCH}(i) = P_{O\_PUCCH} + PL_c + 10 \log_{10} \left(\left(2^{1.25 BP_{RE}} - 1 \right) \cdot \beta_{offset}^{PUCCH} \right) + g(i)$.

[0174] β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following: a channel quality indicator CQI and/or a precoding matrix indicator PMI, a hybrid automatic repeat request HARQ-ACK, or a rank indication RI. If the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

[0175] β_{offset}^{PUCCH} in the third power adjustment value may be one of the parameter $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , or β_{offset}^{CQI} that is corresponding to a parameter configured for the UE by the network device.

20 [0176] β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be $\beta_{offset}^{HARQ-ACK}$ corresponding to the parameter "betaOffset-ACK-Index" or "betaOffset-ACK-Index-MC-r10" that is configured for the UE by the network device. $\beta_{offset}^{HARQ-ACK}$ corresponding to the parameter "betaOffset-ACK-Index" is preferred.

25 [0177] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the

user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be β_{offset}^{RI} corresponding to the parameter "betaOffset-RI-Index" or "betaOffset-RI-Index-MC-r10" that is configured for the UE by the network device. β_{offset}^{RI} corresponding to the parameter "betaOffset-RI-Index" is preferred.

5 [0178] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" or "betaOffset-CQI-Index-MC-r10" that is configured for the UE by the network device. β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" is preferred.

10 [0179] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" or "betaOffset-CQI-Index-MC-r10" that is configured for the UE by the network device. β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" is preferred.

15 [0180] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be one of $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , or β_{offset}^{CQI} that is corresponding to a parameter configured for the UE by the network device. Specifically, if the first uplink control information includes the HARQ-ACK or the RI, β_{offset}^{PUCCH} in the third power adjustment value may be $\beta_{offset}^{HARQ-ACK}$ or β_{offset}^{RI} that is corresponding to a parameter configured for the UE by the network device; if the first uplink control information does not include the HARQ-ACK and the RI, β_{offset}^{PUCCH} in the third power adjustment value may be β_{offset}^{CQI} that is corresponding to a parameter configured for the UE by the network device.

[0181] This embodiment of the present invention specifically provides an expression for

calculating the transmit power according to the sum of the base power adjustment value and any one of the first power adjustment value, the second power adjustment value, the third power adjustment value, the fourth power adjustment value, or the fifth power adjustment value, and provides a method for calculating the transmit power for sending the first uplink control information on the first PUCCH.

[0182] FIG. 2 is a flowchart of a power control method for an uplink control channel according to another embodiment of the present invention. In this embodiment of the present invention, it is defined that a first physical uplink control channel PUCCH format, that is, a first PUCCH format, is different from any one of a PUCCH format 1, 1a, 1b, 2, 2a, 2b, or 3 in the prior art, a second physical uplink control channel PUCCH format, that is, a second PUCCH format, is the PUCCH format 1a, and a third physical uplink control channel PUCCH format, that is, a third PUCCH format, is different from the first PUCCH format and different from any one of the PUCCH format 1, 1a, 1b, 2, 2a, 2b, or 3 in the prior art. For a problem that user equipment cannot determine, according to transmit power used for sending information on an existing PUSCH or PUCCH, transmit power for sending information on a PUCCH in the first PUCCH format or the third PUCCH format, the power control method for an uplink control channel is provided. Specific steps of the method are as follows.

[0183] Step S201: A network device determines that user equipment is to send first uplink control information on a first PUCCH and in a subframe i , where the first uplink control information includes at least one of channel state information CSI, a hybrid automatic repeat request-acknowledgment HARQ-ACK, or a scheduling request SR.

[0184] In the prior art, formats of a PUCCH include the format 1, the format 1a, the format 1b, the format 2, the format 2a, the format 2b, and the format 3. In this embodiment of the present invention, a format of the first PUCCH is the first physical uplink control channel PUCCH format, or a format of the first PUCCH is the third physical uplink control channel PUCCH format, and both the first PUCCH format and the third PUCCH format are different from any PUCCH format in the prior art.

[0185] A network device configures multiple PUCCHs for the user equipment. The user equipment determines the first PUCCH from the multiple PUCCHs, and sends the first uplink control information in the subframe i by using the first PUCCH. Alternatively, a network

device instructs, by using physical layer signaling, the user equipment to send the first uplink control information in the subframe i by using the first PUCCH. This embodiment of the present invention does not limit a method for determining the first PUCCH in the subframe i by the user equipment. The first uplink control information includes at least one of channel state information CSI, a hybrid automatic repeat request-acknowledgment HARQ-ACK, or a scheduling request SR. That is, the first uplink control information generated by the current user equipment may include one of the channel state information CSI, the hybrid automatic repeat request-acknowledgment HARQ-ACK, or the scheduling request SR; may include any two of the channel state information CSI, the hybrid automatic repeat request-acknowledgment HARQ-ACK, or the scheduling request SR; or may include all of the channel state information CSI, the hybrid automatic repeat request-acknowledgment HARQ-ACK, and the scheduling request SR.

[0186] Step S202: The network device determines transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i , where the transmit power is a sum of a base power adjustment value and any one of a first power adjustment value, a second power adjustment value, a third power adjustment value, a fourth power adjustment value, or a fifth power adjustment value.

[0187] The first power adjustment value is a power adjustment value determined by the user equipment according to a quantity of bits of the first uplink control information. The second power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the bits of the first uplink control information and a quantity of resources of the first PUCCH. The third power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH. The fourth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH. The fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to a quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth

power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to the quantity of the resources of the first PUCCH, where the second uplink control information is a subset of the first uplink control information.

5 [0188] The base power adjustment value includes a sum of P_{O_PUCCH} and PL_c , or the base power adjustment value includes a sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, where P_{O_PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, PL_c is a path loss that is determined by the user equipment and that is of a downlink of a cell
10 c in which the first PUCCH is located, and α_c is a path loss factor that is configured for the user equipment by the network device and that is of the cell c in which the first PUCCH is located.

[0189] In this embodiment of the present invention, when the base power adjustment value includes the sum of P_{O_PUCCH} and PL_c , the base power adjustment value further includes at least one of $\Delta_{TxD}(F')$, $g(i)$, or $\Delta_{F\_PUCCH}(F)$. $\Delta_{TxD}(F')$ is a power adjustment
15 value that is configured for the user equipment by the network device and that is used when the PUCCH in the first PUCCH format uses multi-antenna transmit diversity. Optionally, a value of $\Delta_{TxD}(F')$ is -2 dB or 0 dB. $g(i)$ is determined by using a sixth power adjustment value that is in the subframe i and that is configured for the user equipment by the network device by using physical control information. $\Delta_{F\_PUCCH}(F)$ is a power offset value that is
20 configured for the user equipment by the network device and that is of a PUCCH in the first PUCCH format relative to a PUCCH in the second PUCCH format. Optionally, a value of $\Delta_{F\_PUCCH}(F)$ is one of -2 dB, 0 dB, 1 dB, or 2 dB. Preferably, the base power adjustment value in this embodiment of the present invention includes a sum of P_{O_PUCCH} , PL_c , $\Delta_{TxD}(F')$, $g(i)$, and $\Delta_{F\_PUCCH}(F)$, that is, the base power adjustment value is
25 $P_{O\_PUCCH} + PL_c + \Delta_{TxD}(F') + g(i) + \Delta_{F\_PUCCH}(F)$. Alternatively, preferably, the base power

adjustment value in this embodiment of the present invention includes a sum of P_{O_PUCCH} , PL_c , $g(i)$, and $\Delta_{F\_PUCCH}(F)$, that is, the base power adjustment value is $P_{O\_PUCCH} + PL_c + g(i) + \Delta_{F\_PUCCH}(F)$. Alternatively, preferably, the base power adjustment value in this embodiment of the present invention includes a sum of P_{O_PUCCH} , PL_c , and $g(i)$, that is, the base power adjustment value is $P_{O\_PUCCH} + PL_c + g(i)$.

[0190] When the base power adjustment value includes the sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, the base power adjustment value further includes $\Delta_{TF,c}(i)$ and/or $f_c(i)$. When $K_S = 0$, $\Delta_{TF,c}(i) = 0$; or when $K_S = 1.25$, $\Delta_{TF,c}(i) = 10 \log_{10} \left((2^{BP_{RE} \cdot K_S} - 1) \cdot \beta_{offset}^{PUCCH} \right)$. K_S is a parameter that is configured for the user equipment by the network device by using higher layer signaling and that is of the cell c in which the first PUCCH is located. β_{offset}^{PUCCH} is a parameter configured for the user equipment by the network device by using higher layer signaling, or β_{offset}^{PUCCH} is equal to 1. $BP_{RE} = O / N_{RE}$, where O is a quantity of bits of third uplink control information sent by the user equipment on the first PUCCH, the quantity of the bits of the third uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the third uplink control information, and N_{RE} is a quantity of modulation symbols occupied by the first PUCCH. The third uplink control information is a subset of the first uplink control information. $f_c(i)$ is a seventh power adjustment value that is in the subframe i and that is configured for the user equipment by the network device by using physical control information. Preferably, the base power adjustment value in this embodiment of the present invention includes a sum of P_{O_PUCCH} , $\alpha_c \cdot PL_c$, $\Delta_{TF,c}(i)$, and $f_c(i)$, that is, the base power adjustment value may be $P_{O\_PUCCH} + \alpha_c \cdot PL_c + \Delta_{TF,c}(i) + f_c(i)$. Alternatively, preferably, the base power adjustment value in this embodiment of the present invention includes a sum of P_{O_PUCCH} , $\alpha_c \cdot PL_c$, and $f_c(i)$, that is, the base power adjustment value may be $P_{O\_PUCCH} + \alpha_c \cdot PL_c + f_c(i)$.

[0191] In addition, in this embodiment of the present invention, $P_{O\_PUCCH} = P_{O\_PUSCH} + \Delta P$, where P_{O_PUSCH} and ΔP are values configured for the user equipment by the network device by using higher layer signaling, and α_c may be equal to 1.

[0192] Step S203: The network device receives the first uplink control information that is sent by the user equipment on the first PUCCH by using power that is not greater than the transmit power.

[0193] The network device receives the first uplink control information that is sent by the user equipment on the first PUCCH. In a sending process, if the transmit power determined in the foregoing step is greater than a maximum transmit power of the user equipment, the user equipment sends the first uplink control information on the first PUCCH by using the maximum transmit power; or if the transmit power determined in the foregoing step is not greater than a maximum transmit power of the user equipment, the user equipment sends the first uplink control information on the first PUCCH by using the transmit power.

[0194] In this embodiment of the present invention, the transmit power for sending the first uplink control information on the first PUCCH and in the subframe i is determined by the user equipment by using the sum of the base power adjustment value and any one of the first power adjustment value determined according to the quantity of the bits of the first uplink control information that is to be sent on the first PUCCH, the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH, the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH, the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of

the first PUCCH. Therefore, a method for determining the transmit power for sending the first uplink control information on the first PUCCH is provided.

[0195] Based on the foregoing embodiment, the quantity of the bits of the first uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the first uplink control information, and the quantity of the bits of the second uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the second uplink control information.

[0196] The first PUCCH is in the first physical uplink control channel PUCCH format. The PUCCH in the first PUCCH format is characterized in that: the PUCCH occupies at least one RB, and in a case of a normal cyclic prefix (Normal Cyclic Prefix, normal CP for short), only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or two time-domain symbols in each timeslot bear a demodulation reference signal, or in a case of an extended cyclic prefix (Extended Cyclic Prefix, extended CP for short), the third time-domain symbol in each timeslot bears a demodulation reference signal; or the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

[0197] The quantity of the resources of the first PUCCH is K_{RE} , a quantity of modulation symbols occupied by the first PUCCH. Alternatively, the quantity of the resources of the first PUCCH is Q' , a quantity of bits corresponding to modulation symbols occupied by the first PUCCH, where $Q' = K_{RE} * Q_m$, and Q_m is a modulation order used by the user equipment for sending the first uplink control information on the first PUCCH. Alternatively, the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, a quantity of RBs included in the first PUCCH.

[0198] The quantity of the resources occupied on the first PUCCH by the second uplink control information is M_{RE} , a quantity of modulation symbols occupied on the first PUCCH by the second uplink control information. Alternatively, the quantity of the resources occupied

on the first PUCCH by the second uplink control information is Q'' , a quantity of bits corresponding to modulation symbols occupied on the first PUCCH by the second uplink control information, where $Q'' = M_{RE} * Q_m'$, and Q_m' is a modulation order used by the user equipment for sending the second uplink control information on the first PUCCH.

5 [0199] Specifically, $K_{RE} = M_{sc}^{PUCCH} \cdot N_{\text{sybm}}^{PUCCH}$, where M_{sc}^{PUCCH} is a quantity of subcarriers of the first PUCCH, and N_{sybm}^{PUCCH} is a quantity of OFDM symbols of the first PUCCH. For QPSK, $Q_m = 2$. For 16QAM, $Q_m = 4$.

[0200] This embodiment of the present invention specifically defines characteristics of the PUCCH in the first PUCCH format, to distinguish between the PUCCH in the first PUCCH
10 format and a PUCCH in an existing PUCCH format, and also specifically defines a method for determining the quantity of the resources of the first PUCCH and the quantity of the resources occupied on the first PUCCH by the second uplink control information.

[0201] Based on the foregoing embodiment, a specific method for determining the transmit power includes the following five cases. Optionally, if a quantity of RBs occupied by
15 the first PUCCH is not greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the first power adjustment value and the base power adjustment value, or the transmit power is a sum of the second power adjustment value and the base power adjustment value. If a quantity of RBs occupied by the first PUCCH is greater than N_u , the transmit
20 power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the third power adjustment value and the base power adjustment value. N_u is 1, 2, 3, or 4.

[0202] First case: The first power adjustment value determined according to the quantity of the bits of the first uplink control information is $h'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the
25 quantity of the bits of the first uplink control information sent on the first PUCCH.

[0203] In the first case, the transmit power is a sum of the first power adjustment value

$h'(n_{bit}(i))$ and the base power adjustment value

$P_{O\_PUCCH} + PL_c + \Delta_{TxD}(F') + g(i) + \Delta_{F\_PUCCH}(F)$. The transmit power is

$P_{PUCCH}(i) = P_{O\_PUCCH} + PL_c + h'(n_{bit}(i)) + \Delta_{F\_PUCCH}(F) + \Delta_{TxD}(F') + g(i)$. A value of $h'(n_{bit}(i))$

is determined by $n_{bit}(i)$. A specific determining relationship is as follows:

5 if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;
if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and
 $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,
and $11.4 \leq P_3 \leq 17.24$; or

10 $h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

[0204] Preferably, $K_1 = 0.07$, and $K_2 = 5.6$. Alternatively, preferably, $K_1 = 0.06$, and
 $K_2 = 6.2$.

[0205] $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent
on the first PUCCH. For example, $n_{bit}(i)$ may be specifically expressed as
15 $n_{bit}(i) = n_{CSI} + n_{HARQ} + n_{SR}$, where n_{CSI} is a quantity of bits of the channel state information CSI,
 n_{HARQ} is a quantity of bits of the hybrid automatic repeat request-acknowledgment
HARQ-ACK, n_{SR} is a quantity of bits of the scheduling request SR, and any one of n_{CSI} ,
 n_{HARQ} , or n_{SR} may be 0.

[0206] Second case: The second power adjustment value determined according to the
20 quantity of the bits of the first uplink control information and the quantity of the resources of
the first PUCCH is $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of
the first uplink control information sent on the first PUCCH, $M_{RB}^{PUCCH}(i)$ is the quantity of
the RBs included in the first PUCCH, and a value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by

$n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

[0207] In the second case, the transmit power is a sum of the second power adjustment

value $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ and the base power adjustment value

$P_{O\_PUCCH} + PL_c + \Delta_{TxD}(F') + g(i) + \Delta_{F\_PUCCH}(F)$. The transmit power is

5 $P_{PUCCH}(i) = P_{O\_PUCCH} + PL_c + h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) + \Delta_{F\_PUCCH}(F) + \Delta_{TxD}(F') + g(i)$, where

$h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ indicates the second power adjustment value, $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH, and a

value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$. A specific determining relationship is as follows:

10 $h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n_{bit}(i))$.

[0208] When $M_{RB}^{PUCCH}(i) = 1$:

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$,

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$,

and $8.2 \leq P_2 \leq 12.12$,

15 if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,

and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$ $0.05 \leq K_1 \leq 0.08$, where $0.05 \leq K_1 \leq 0.08$, and

$5 \leq K_2 \leq 7$.

[0209] Preferably, $K_1 = 0.07$, and $K_2 = 5.6$. Alternatively, preferably, $K_1 = 0.06$, and

20 $K_2 = 6.2$.

[0210] When $M_{RB}^{PUCCH}(i) = 2$:

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$,

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$,

and $6.8 \leq P_2 \leq 10$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,

and $8 \leq P_3 \leq 12.6$;

if $n_{bit}(i)$ is greater than 128 and $n_{bit}(i)$ is not greater than 256, $h'(n_{bit}(i)) = P_4$,

5 and $10.6 \leq P_4 \leq 17.7$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

[0211] Preferably, $K_1 = 0.03$, and $K_2 = 6.7$.

[0212] Alternatively, in the second case, the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n'_{bit}(i)$ indicates a quantity of bits obtained by subtracting the quantity of the bits of the cyclic redundancy code CRC corresponding to the second uplink control information from the quantity of the bits of the second uplink control information, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value of $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n'_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

[0213] Preferably, $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, where when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $-1.6 \leq K_2 \leq -0.7$; or when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.03 \leq K_1 \leq 0.05$, and $-0.3 \leq K_2 \leq 0.5$.

20 [0214] Alternatively, preferably, $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, where when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where $0.05 \leq K_1 \leq 0.075$, and $-2.2 \leq K_2 \leq -1.1$; or when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where $0.03 \leq K_1 \leq 0.08$, and $-0.6 \leq K_2 \leq 0.1$.

[0215] When the second power adjustment value is $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, the transmit power is $P_{PUCCH}(i) = P_{0\_PUCCH} + PL_c + h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) + \Delta_{F\_PUCCH}(F) + \Delta_{TxD}(F') + g(i)$ or $P_{PUCCH}(i) = P_{0\_PUCCH} + \alpha_c \cdot PL_c + h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) + \Delta_{F\_PUCCH}(F) + \Delta_{TxD}(F') + f_c(i)$.

[0216] When the first PUCCH is in the first physical uplink control channel PUCCH format, and the PUCCH in the first physical uplink control channel PUCCH format does not support a transmit diversity solution, the transmit power is $P_{PUCCH}(i) = P_{0\_PUCCH} + PL_c + h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) + \Delta_{F\_PUCCH}(F) + g(i)$ or $P_{PUCCH}(i) = P_{0\_PUCCH} + \alpha_c \cdot PL_c + h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) + \Delta_{F\_PUCCH}(F) + f_c(i)$, where P_{0_PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and is used to determine the transmit power of the first PUCCH in the first physical uplink control channel. P_{0_PUCCH} is determined by a cell-level parameter $P_{O\_NOMINAL\_PUCCH\_2}$ and a user-level parameter $P_{O\_UE\_PUCCH\_2}$ that are configured for the user equipment by the network device. In the prior art, a network device configures a cell-level parameter $P_{O\_NOMINAL\_PUCCH\_1}$ and a user-level parameter $P_{O\_UE\_PUCCH\_1}$ for the user equipment by using higher layer signaling. A value of $P_{O\_NOMINAL\_PUCCH\_1}$ ranges from -127 dBm to -96 dBm. A value of $P_{O\_UE\_PUCCH\_1}$ ranges from -8 dB to 7 dB. A sum $P_{O\_PUCCH\_1}$ of values of the two parameters is configured for the user equipment by the network device and is used to adjust transmit power for performing, by the user equipment, sending on a PUCCH in an existing PUCCH format (including the PUCCH format 1, the PUCCH format 1a, the PUCCH format 1b, the PUCCH format 2, the PUCCH format 2a, the PUCCH format 2b, and the PUCCH format 3). In the prior art, the network device further configures a cell-level parameter $P_{O\_NOMINAL\_PUSCH}$ and a user-level parameter $P_{O\_UE\_PUSCH}$ for the user equipment by using higher layer signaling. A value of $P_{O\_NOMINAL\_PUSCH}$ ranges from -126 dBm to 24 dBm. A value of $P_{O\_UE\_PUSCH}$ ranges from -8 dB to 7 dB. A sum P_{O_PUSCH} of values of the two parameters is configured for the user equipment by the network device and is used to adjust

transmit power for performing, by the user equipment, sending on a PUSCH. P_{O_PUCCH} is determined by the cell-level parameter $P_{O\_NOMINAL\_PUCCH\_2}$ and the user-level parameter $P_{O\_UE\_PUCCH\_2}$ that are configured for the user equipment by the network device. $P_{O\_NOMINAL\_PUCCH\_2}$ may be any one of the cell-level parameter $P_{O\_NOMINAL\_PUCCH\_1}$ or $P_{O\_NOMINAL\_PUSCH}$ that is configured for an existing PUCCH format by the network device, or may be determined by another parameter configured by the network device. $P_{O\_UE\_PUCCH\_2}$ may be any one of the user-level parameter $P_{O\_UE\_PUCCH\_1}$ or $P_{O\_UE\_PUSCH}$ that is configured for an existing PUCCH format by the network device, or may be determined by another parameter configured by the network device. If $P_{O\_NOMINAL\_PUCCH\_2}$ is determined by the another parameter configured by the network device, a value of the parameter ranges from -126 dBm to 24 dBm. If $P_{O\_UE\_PUCCH\_2}$ is determined by the another parameter configured by the network device, a value of the parameter ranges from -8 dB to 7 dB.

[0217] $\Delta_{F\_PUCCH}(F)$ is the power offset value that is configured for the user equipment by the network device and that is of the PUCCH in the first PUCCH format relative to the PUCCH in the second PUCCH format.

[0218] $g(i)$ and $f_c(i)$ indicate power adjustment values that are sent to the user equipment by the network device by using a physical downlink control channel.

[0219] Third case: The third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $k(m(i), M_{RB}^{PUCCH}(i))$, where $m(i)$ indicates the ratio of the quantity of the bits of the first uplink control information sent by the user equipment on the first PUCCH to the quantity of the resources of the first PUCCH, and a value of $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$. In this case, the transmit power is the sum of the third power adjustment value $k(m(i), M_{RB}^{PUCCH}(i))$ and the base power adjustment value

$P_{O\_PUCCH} + PL_c + \Delta_{TXD}(F') + g(i) + \Delta_{F\_PUCCH}(F)$. The transmit power is

$P_{PUCCH}(i) = P_{O\_PUCCH} + PL_c + k(m(i), M_{RB}^{PUCCH}(i)) + \Delta_{F\_PUCCH}(F) + \Delta_{TXD}(F') + g(i)$, where

$k(m(i), M_{RB}^{PUCCH}(i))$ indicates the third power adjustment value, $m(i)$ indicates the ratio of the

quantity of the bits of the first uplink control information sent by the user equipment on the

5 first PUCCH to the quantity of the resources of the first PUCCH, and a value of

$k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$. A specific determining

relationship is as follows.

[0220] When the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, the quantity

of the RBs included in the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$.

10 [0221] When $M_{RB}^{PUCCH}(i) = 1$:

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and

$8.2 \leq P_2 \leq 12.12$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and

15 $11.4 \leq P_3 \leq 17.24$; or

$q'(m(i)) = K_1 \cdot m(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

[0222] Preferably, $K_1 = 0.07$, and $K_2 = 5.6$. Alternatively, preferably, $K_1 = 0.06$, and

$K_2 = 6.2$.

[0223] When $M_{RB}^{PUCCH}(i) = 2$:

20 if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and

$6.8 \leq P_2 \leq 10$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and

$$8 \leq P_3 \leq 12.6 ;$$

if $m(i)$ is greater than 128 and $m(i)$ is not greater than 256, $q'(m(i)) = P_4$, and $10.6 \leq P_4 \leq 17.7$; or

$$q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ where } 0.02 \leq K_1 \leq 0.04, \text{ and } 5.5 \leq K_2 \leq 7.5.$$

5 [0224] Preferably, $K_1 = 0.03$, and $K_2 = 6.7$.

[0225] When the quantity of the resources of the first PUCCH is K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$.

[0226] When $M_{RB}^{PUCCH}(i) = 1$:

10 $q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ where } 8 \leq K_1 \leq 11, \text{ and } 5 \leq K_2 \leq 7.$

[0227] Preferably, $K_1 = 8.4$, and $K_2 = 6.3$.

[0228] When $M_{RB}^{PUCCH}(i) = 2$:

$$q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ where } 8.5 \leq K_1 \leq 10.5, \text{ and } 6 \leq K_2 \leq 8.$$

[0229] Preferably, $K_1 = 9.5$, and $K_2 = 6.7$.

15 [0230] Alternatively, the determining the third power adjustment value according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH includes:

determining the third power adjustment value according to a ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, where the third power adjustment value is $10 \log_{10}(M_{RB}^{PUCCH}(i)) + 10 \log_{10}((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH})$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, $BPRE$ is the ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by

20

using higher layer signaling, and K_s is a value configured for the user equipment by the network device by using higher layer signaling.

[0231] Preferably, $K_s = 1.25$. In this case, the transmit power is the sum of the third power adjustment value $10\log_{10}(M_{RB}^{PUCCH}(i)) + 10\log_{10}((2^{1.25BP_{PRE}} - 1) \cdot \beta_{offset}^{PUCCH})$ and the base

5 power adjustment value $P_{O\_PUCCH} + PL_c + g(i)$, that is, the transmit power of the PUCCH is $P_{PUCCH}(i) = P_{O\_PUCCH} + PL_c + 10\log_{10}(M_{RB}^{PUCCH}(i)) + 10\log_{10}((2^{1.25BP_{PRE}} - 1) \cdot \beta_{offset}^{PUCCH}) + g(i)$.

[0232] Alternatively, the transmit power is the sum of the third power adjustment value $10\log_{10}(M_{RB}^{PUCCH}(i)) + 10\log_{10}((2^{1.25BP_{PRE}} - 1) \cdot \beta_{offset}^{PUCCH})$ and the base power adjustment value

10 $P_{O\_PUCCH} + \alpha_c \cdot PL_c + f_c(i)$, that is, the transmit power of the PUCCH is $P_{PUCCH}(i) = P_{O\_PUCCH} + \alpha_c \cdot PL_c + 10\log_{10}(M_{RB}^{PUCCH}(i)) + 10\log_{10}((2^{1.25BP_{PRE}} - 1) \cdot \beta_{offset}^{PUCCH}) + f_c(i)$,

where P_{O_PUCCH} is the same as P_{O_PUCCH} in the second case, PL_c is the path loss that is determined by the user equipment and that is of the downlink of the cell c in which the first PUCCH is located, α_c is the path loss factor that is configured for the user equipment by the network device and that is of the cell c in which the first PUCCH is located, $g(i)$ is the same as $g(i)$ in the second case, and $f_c(i)$ is the same as $f_c(i)$ in the second case.

[0233] β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following: a channel quality indicator CQI and/or a precoding matrix indicator PMI, a hybrid automatic repeat request HARQ-ACK, or a rank indication RI. If the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

[0234] In the prior art, the network device configures parameters "betaOffset-ACK-Index", "betaOffset-RI-Index", and "betaOffset-CQI-Index" for the user equipment by using higher

layer signaling. The parameters are respectively used to determine parameters $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , and β_{offset}^{CQI} that are required when the user equipment determines a quantity of PUSCH modulation symbols occupied for sending HARQ-ACK, rank indication RI (Rank Indication), and channel quality indicator CQI (Channel Quality Indicator)/precoding matrix indicator PMI (Precoding Matrix Indicator) information on a single-codeword PUSCH. Values of the parameters are integers within [0,15]. The network device configures parameters "betaOffset-ACK-Index-MC-r10", "betaOffset-RI-Index-MC-r10", and "betaOffset-CQI-Index-MC-r10" for the user equipment by using higher layer signaling. The parameters are respectively used to determine the parameters $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , and β_{offset}^{CQI} that are required when the user equipment determines a quantity of PUSCH modulation symbols occupied for sending the HARQ-ACK, RI, and CQI/PMI information on a multi-codeword PUSCH. Optionally, the user equipment determines that the quantity of the PUSCH modulation symbols occupied for sending the HARQ-ACK, RI, and CQI/PMI information on the multi-codeword PUSCH are a product of $\beta_{offset}^{HARQ-ACK}$ and a first ratio, a product of β_{offset}^{RI} and the first ratio, and a product of β_{offset}^{CQI} and the first ratio respectively.

The first ratio is $\frac{O \cdot M_{RE}}{R}$, where O is a quantity of bits of the HARQ-ACK, the RI, or the CQI/PMI (if CRC parity bits are added before channel encoding when the HARQ-ACK, RI, or CQI/PMI information is transmitted on the PUSCH, the quantity of the bits includes a bit quantity of CRC parity bits corresponding to the HARQ-ACK, RI, or CQI/PMI information), M_{RE} is a quantity of modulation symbols of the PUSCH, and R is a quantity of bits of uplink data sent on the PUSCH.

[0235] Optionally, $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , and β_{offset}^{CQI} are ratios of a first quantity of modulation symbols to a second quantity of modulation symbols. The first quantity of modulation symbols is a quantity of modulation symbols of the PUSCH that are occupied when first encoded modulation symbols obtained by encoding and modulating uplink control information of the HARQ-ACK, RI, or CQI/PMI are sent on the PUSCH. The second quantity

of modulation symbols is a quantity of modulation symbols of the PUSCH that are occupied when second encoded modulation symbols obtained by encoding and modulating uplink data are sent on the PUSCH. A quantity of the first encoded modulation symbols is equal to a quantity of the second encoded modulation symbols.

5 [0236] β_{offset}^{PUCCH} in the third power adjustment value may be one of the parameter $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , or β_{offset}^{CQI} that is corresponding to a parameter configured for the UE by the network device.

[0237] β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be $\beta_{offset}^{HARQ-ACK}$ corresponding to the parameter "betaOffset-ACK-Index" or "betaOffset-ACK-Index-MC-r10" that is configured for the UE by the network device. $\beta_{offset}^{HARQ-ACK}$ corresponding to the parameter "betaOffset-ACK-Index" is preferred.

[0238] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be β_{offset}^{RI} corresponding to the parameter "betaOffset-RI-Index" or "betaOffset-RI-Index-MC-r10" that is configured for the UE by the network device. β_{offset}^{RI} corresponding to the parameter "betaOffset-RI-Index" is preferred.

[0239] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" or "betaOffset-CQI-Index-MC-r10" that is configured for the UE by the network device. β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" is preferred.

[0240] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be

β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" or "betaOffset-CQI-Index-MC-r10" that is configured for the UE by the network device. β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" is preferred.

[0241] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be one of $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , or β_{offset}^{CQI} that is corresponding to a parameter configured for the UE by the network device. Specifically, if the first uplink control information includes the HARQ-ACK or the RI, β_{offset}^{PUCCH} in the third power adjustment value may be $\beta_{offset}^{HARQ-ACK}$ or β_{offset}^{RI} that is corresponding to a parameter configured for the UE by the network device; if the first uplink control information does not include the HARQ-ACK and the RI, β_{offset}^{PUCCH} in the third power adjustment value may be β_{offset}^{CQI} that is corresponding to a parameter configured for the UE by the network device.

[0242] It should be noted that if the quantity of the resources of the PUCCH in the first PUCCH format is fixedly one RB, the third power adjustment value is a power adjustment value determined by the user equipment according to the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, and impact of the quantity of the resources of the first PUCCH on the third power adjustment value may not be considered.

[0243] Fourth case: The fourth power adjustment value determined according to the quantity of the resources of the first PUCCH is $10\log_{10}(M_{RB}^{PUCCH}(i))$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH.

[0244] In the fourth case, the transmit power is a sum of the fourth power adjustment value $10\log_{10}(M_{RB}^{PUCCH}(i))$ and the base power adjustment value $P_{O\_PUCCH} + \alpha_c \cdot PL_c + \Delta_{TF,c}(i) + f_c(i)$. The transmit power is $P_{PUCCH}(i) = 10\log_{10}(M_{RB}^{PUCCH}(i)) + P_{O\_PUCCH} + \alpha_c \cdot PL_c + \Delta_{TF,c}(i) + f_c(i)$, where $M_{RB}^{PUCCH}(i)$ is

the quantity of the RBs included in the first PUCCH.

[0245] Fifth case: The fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH is $R(r(i), M_{RB}^{PUCCH}(i))$, where $r(i)$ indicates the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH, and a value of $R(r(i), M_{RB}^{PUCCH}(i))$ is determined by $r(i)$ and $M_{RB}^{PUCCH}(i)$.

[0246] In the fifth case, the transmit power is a sum of the fifth power adjustment value and the base power adjustment value. The second uplink control information is a subset of the first uplink control information, and the second uplink control information is at least one type of uplink control information with a highest priority in the first uplink control information. A priority sequence includes at least one of the following cases: a priority of the HARQ-ACK is higher than a priority of the CSI, a priority of the SR is equal to or higher than a priority of the HARQ-ACK, a priority of an RI/PTI in the CSI is higher than a priority of a CQI/PMI in the CSI, or a priority of an RI/PTI in the CSI is equal to a priority of the HARQ-ACK. Alternatively, the second uplink control information is at least one type of uplink control information that is in the first uplink control information and that is used to determine a benchmark of a quantity of resources occupied on the first PUCCH by each piece of control information in the first uplink control information. For example, a quantity of resources occupied on the first PUCCH by other control information may be determined according to a preset ratio or difference between the quantity of the resources occupied on the first PUCCH by the other control information and a quantity of resources occupied on the first PUCCH by the at least one type of uplink control information.

[0247] It should be noted that if the quantity of the resources of the PUCCH in the first

PUCCH format is fixedly one RB, the fifth power adjustment value is a power adjustment value determined by the user equipment according to the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or a power adjustment value determined by the user equipment according to the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH, and impact of the quantity of the resources of the first PUCCH on the fifth power adjustment value may not be considered.

[0248] In addition, the first PUCCH may be in the third physical uplink control channel PUCCH format. The PUCCH in the third PUCCH format is characterized in that: the PUCCH occupies one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal, where uplink control information of at least two user equipments is capable of being sent on the PUCCH by means of code division; or the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

[0249] When the first PUCCH is in the third physical uplink control channel PUCCH format, the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $k'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

$$k'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ where } 0.08 \leq K_1 \leq 0.12, \text{ and } -3.7 \leq K_2 \leq -2.7.$$

[0250] In this case, the transmit power is the sum of the first power adjustment value $k'(n_{bit}(i))$ and the base power adjustment value $P_{O\_PUCCH} + PL_c + g(i) + \Delta_{F\_PUCCH}(F)$, that is, the transmit power is $P_{PUCCH}(i) = P_{O\_PUCCH} + PL_c + k'(n_{bit}(i)) + \Delta_{F\_PUCCH}(F) + g(i)$.

[0251] When the first PUCCH is in the third physical uplink control channel PUCCH format, the third power adjustment value determined according to the quantity of the RBs

included in the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH is $10\log_{10}\left(\left(2^{K_S \cdot BPRE} - 1\right) \cdot \beta_{offset}^{PUCCH}\right)$, where $BPRE$ is the ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

[0252] Preferably, $K_S = 1.25$. In this case, the transmit power is the sum of the third power adjustment value $10\log_{10}\left(\left(2^{1.25BPRE} - 1\right) \cdot \beta_{offset}^{PUCCH}\right)$ and the base power adjustment value $P_{O\_PUCCH} + PL_c + g(i)$, that is, the transmit power is $P_{PUCCH}(i) = P_{O\_PUCCH} + PL_c + 10\log_{10}\left(\left(2^{1.25BPRE} - 1\right) \cdot \beta_{offset}^{PUCCH}\right) + g(i)$.

[0253] β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following: a channel quality indicator CQI and/or a precoding matrix indicator PMI, a hybrid automatic repeat request HARQ-ACK, or a rank indication RI. If the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

[0254] β_{offset}^{PUCCH} in the third power adjustment value may be one of the parameter $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , or β_{offset}^{CQI} that is corresponding to a parameter configured for the UE by the network device.

[0255] β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be $\beta_{offset}^{HARQ-ACK}$ corresponding to the parameter "betaOffset-ACK-Index" or "betaOffset-ACK-Index-MC-r10"

that is configured for the UE by the network device. $\beta_{offset}^{HARQ-ACK}$ corresponding to the parameter "betaOffset-ACK-Index" is preferred.

[0256] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be
 5 β_{offset}^{RI} corresponding to the parameter "betaOffset-RI-Index" or "betaOffset-RI-Index-MC-r10" that is configured for the UE by the network device. β_{offset}^{RI} corresponding to the parameter "betaOffset-RI-Index" is preferred.

[0257] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be
 10 β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" or "betaOffset-CQI-Index-MC-r10" that is configured for the UE by the network device. β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" is preferred.

[0258] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be
 15 β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" or "betaOffset-CQI-Index-MC-r10" that is configured for the UE by the network device. β_{offset}^{CQI} corresponding to the parameter "betaOffset-CQI-Index" is preferred.

[0259] Alternatively, β_{offset}^{PUCCH} in the third power adjustment value is configured for the user equipment by the network device by using the higher layer signaling. β_{offset}^{PUCCH} may be
 20 one of $\beta_{offset}^{HARQ-ACK}$, β_{offset}^{RI} , or β_{offset}^{CQI} that is corresponding to a parameter configured for the UE by the network device. Specifically, if the first uplink control information includes the HARQ-ACK or the RI, β_{offset}^{PUCCH} in the third power adjustment value may be $\beta_{offset}^{HARQ-ACK}$ or β_{offset}^{RI} that is corresponding to a parameter configured for the UE by the network device; if

the first uplink control information does not include the HARQ-ACK and the RI, β_{offset}^{PUCCH} in the third power adjustment value may be β_{offset}^{CQI} that is corresponding to a parameter configured for the UE by the network device.

- [0260] This embodiment of the present invention specifically provides an expression for calculating the transmit power according to the sum of the base power adjustment value and any one of the first power adjustment value, the second power adjustment value, the third power adjustment value, the fourth power adjustment value, or the fifth power adjustment value, and provides a method for calculating the transmit power for sending the first uplink control information on the first PUCCH.
- 10 [0261] FIG. 3 is a structural diagram of user equipment according to an embodiment of the present invention. The user equipment provided in this embodiment of the present invention can execute a processing procedure provided in the embodiments of the power control method for an uplink control channel. As shown in FIG. 3, the user equipment 30 includes a first processing unit 31 and a sending unit 32. The first power adjustment value is a power adjustment value determined by the user equipment according to a quantity of bits of the first uplink control information. The second power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the bits of the first uplink control information and a quantity of resources of the first PUCCH. The third power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH. The fourth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH. The fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to a quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to the quantity

of the resources of the first PUCCH, where the second uplink control information is a subset of the first uplink control information.

[0262] The base power adjustment value includes a sum of P_{O_PUCCH} and PL_c , or the base power adjustment value includes a sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, where

5 P_{O_PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling;

PL_c is a path loss that is determined by the user equipment and that is of a downlink of a cell c in which the first PUCCH is located; and

10 α_c is a path loss factor that is configured for the user equipment by the network device and that is of the cell c in which the first PUCCH is located.

[0263] The first processing unit 31 in this embodiment of the present invention may be implemented by a processor.

[0264] In this embodiment of the present invention, the transmit power for sending the first uplink control information on the first PUCCH and in the subframe i is determined by
 15 the user equipment by using the sum of the base power adjustment value and any one of the first power adjustment value determined according to the quantity of the bits of the first uplink control information that is to be sent on the first PUCCH, the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH, the third power adjustment value
 20 determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH, the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the
 25 second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of

the first PUCCH. Therefore, a method for determining the transmit power for sending the first uplink control information on the first PUCCH is provided.

[0265] Based on the foregoing embodiment, the quantity of the bits of the first uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the first uplink control information, and the quantity of the bits of the second uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the second uplink control information.

[0266] The first PUCCH is in a first physical uplink control channel PUCCH format. The PUCCH in the first PUCCH format is characterized in that:

10 the PUCCH occupies at least one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or two time-domain symbols in each timeslot bear a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal; or

15 the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

[0267] If a quantity of RBs occupied by the first PUCCH is not greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the first power adjustment value and the base power adjustment value, or the transmit power is a sum of the second power adjustment value and the base power adjustment value; or

25 if a quantity of RBs occupied by the first PUCCH is greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the third power adjustment value and the base power adjustment value, where

N_u is 1, 2, 3, or 4.

[0268] The quantity of the resources of the first PUCCH is K_{RE} , a quantity of modulation symbols occupied by the first PUCCH.

[0269] Alternatively, the quantity of the resources of the first PUCCH is Q' , a quantity of bits corresponding to modulation symbols occupied by the first PUCCH, where $Q' = K_{RE} * Q_m$,

5 and Q_m is a modulation order used by the user equipment for sending the first uplink control information on the first PUCCH.

[0270] Alternatively, the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, a quantity of RBs included in the first PUCCH.

[0271] The quantity of the resources occupied on the first PUCCH by the second uplink control information is M_{RE} , a quantity of modulation symbols occupied on the first PUCCH by the second uplink control information.

[0272] Alternatively, the quantity of the resources occupied on the first PUCCH by the second uplink control information is Q'' , a quantity of bits corresponding to modulation symbols occupied on the first PUCCH by the second uplink control information, where
15 $Q'' = M_{RE} * Q'_m$, and Q'_m is a modulation order used by the user equipment for sending the second uplink control information on the first PUCCH.

[0273] The first power adjustment value determined according to the quantity of the bits of the first uplink control information is $h'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH.

20 [0274] If $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;
if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,
and $11.4 \leq P_3 \leq 17.24$; or

25 $h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

[0275] The second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

[0276] $h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n_{bit}(i))$, where
 when $M_{RB}^{PUCCH}(i) = 1$;
 if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;
 10 if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,
 and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or
 15 when $M_{RB}^{PUCCH}(i) = 2$;
 if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;
 if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $6.8 \leq P_2 \leq 10$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,
 20 and $8 \leq P_3 \leq 12.6$;

if $n_{bit}(i)$ is greater than 128 and $n_{bit}(i)$ is not greater than 256, $h'(n_{bit}(i)) = P_4$,
 and $10.6 \leq P_4 \leq 17.7$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

[0277] The second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n'_{bit}(i)$ indicates a quantity of bits obtained by subtracting the quantity of the bits of the cyclic redundancy code CRC corresponding to the second uplink control information from the quantity of the bits of the second uplink control information, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value of $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n'_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

[0278] $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, where
when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and
10 $-1.6 \leq K_2 \leq -0.7$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.03 \leq K_1 \leq 0.05$,
and $-0.3 \leq K_2 \leq 0.5$.

[0279] $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, where
when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where
15 $0.05 \leq K_1 \leq 0.075$, and $-2.2 \leq K_2 \leq -1.1$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where
 $0.03 \leq K_1 \leq 0.08$, and $-0.6 \leq K_2 \leq 0.1$.

[0280] The third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $k(m(i), M_{RB}^{PUCCH}(i))$, where
20 $m(i)$ indicates the ratio of the quantity of the bits of the first uplink control information sent by the user equipment on the first PUCCH to the quantity of the resources of the first PUCCH, and a value of $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$.

[0281] When the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, the quantity

of the RBs included in the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$,
where

when $M_{RB}^{PUCCH}(i) = 1$;

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

5 if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and
 $8.2 \leq P_2 \leq 12.12$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and
 $11.4 \leq P_3 \leq 17.24$; or

$q'(m(i)) = K_1 \cdot m(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

10 when $M_{RB}^{PUCCH}(i) = 2$;

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and
 $6.8 \leq P_2 \leq 10$;

15 if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and
 $8 \leq P_3 \leq 12.6$;

if $m(i)$ is greater than 128 and $m(i)$ is not greater than 256, $q'(m(i)) = P_4$, and
 $10.6 \leq P_4 \leq 17.7$; or

$q'(m(i)) = K_1 \cdot m(i) + K_2$, where $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

[0282] When the quantity of the resources of the first PUCCH is K_{RE} , the quantity of the
20 modulation symbols occupied by the first PUCCH,

$k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $8 \leq K_1 \leq 11$, and
 $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $8.5 \leq K_1 \leq 10.5$, and $6 \leq K_2 \leq 8$.

[0283] The determining the third power adjustment value according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH includes:

determining the third power adjustment value according to a ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, where the third power adjustment value is $10\log_{10}(M_{RB}^{PUCCH}(i)) + 10\log_{10}((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH})$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, $BPRE$ is the ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

[0284] β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following:

- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
- a hybrid automatic repeat request HARQ-ACK; or
- a rank indication RI.

[0285] If the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

[0286] The fourth power adjustment value determined according to the quantity of the resources of the first PUCCH is $10\log_{10}(M_{RB}^{PUCCH}(i))$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH.

[0287] The fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH is $R(r(i), M_{RB}^{PUCCH}(i))$, where $r(i)$ indicates the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH, and a value of $R(r(i), M_{RB}^{PUCCH}(i))$ is determined by $r(i)$ and $M_{RB}^{PUCCH}(i)$.

[0288] The first PUCCH is in a third physical uplink control channel PUCCH format. The PUCCH in the third PUCCH format is characterized in that:

the PUCCH occupies one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal, where uplink control information of at least two user equipments is capable of being sent on the PUCCH by means of code division; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

[0289] The first power adjustment value determined according to the quantity of the bits of the first uplink control information is $k'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

$$k'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ where } 0.08 \leq K_1 \leq 0.12, \text{ and } -3.7 \leq K_2 \leq -2.7.$$

[0290] The third power adjustment value determined according to the quantity of the

resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $10\log_{10}\left(\left(2^{K_S \cdot BPRE} - 1\right) \cdot \beta_{offset}^{PUCCH}\right)$, where $BPRE$ is a ratio of the quantity of the bits of the first uplink control information to K_{RE} , a quantity of modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

[0291] β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following:

- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
- a hybrid automatic repeat request HARQ-ACK; or
- a rank indication RI.

[0292] If the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

[0293] The user equipment provided in this embodiment of the present invention may be specifically configured to execute the method embodiment provided in FIG. 1. Detailed functions are not described herein again.

[0294] This embodiment of the present invention specifically defines characteristics of the PUCCH in the first PUCCH format, to distinguish between the PUCCH in the first PUCCH format and a PUCCH in an existing PUCCH format, and also specifically defines a method for determining the quantity of the resources of the first PUCCH and the quantity of the resources occupied on the first PUCCH by the second uplink control information. This embodiment of the present invention specifically provides an expression for calculating the transmit power according to the sum of the base power adjustment value and any one of the first power adjustment value, the second power adjustment value, the third power adjustment

value, the fourth power adjustment value, or the fifth power adjustment value, and provides a method for calculating the transmit power for sending the first uplink control information on the first PUCCH.

[0295] FIG. 4 is a structural diagram of a network device according to an embodiment of the present invention. The network device provided in this embodiment of the present invention can execute a processing procedure provided in the embodiments of the power control method for an uplink control channel. As shown in FIG. 4, the network device 40 includes a second processing unit 41 and a receiving unit 42. The first power adjustment value is a power adjustment value determined by the user equipment according to a quantity of bits of the first uplink control information. The second power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the bits of the first uplink control information and a quantity of resources of the first PUCCH. The third power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH. The fourth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH. The fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to a quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to the quantity of the resources of the first PUCCH, where the second uplink control information is a subset of the first uplink control information.

[0296] The base power adjustment value includes a sum of P_{O_PUCCH} and PL_c , or the base power adjustment value includes a sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, where

P_{O_PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling;

PL_c is a path loss that is determined by the user equipment and that is of a downlink of a cell c in which the first PUCCH is located; and

α_c is a path loss factor that is configured for the user equipment by the network device and that is of the cell c in which the first PUCCH is located.

5 [0297] The second processing unit 41 in this embodiment of the present invention may be implemented by a processor.

[0298] In this embodiment of the present invention, the transmit power for sending the first uplink control information on the first PUCCH and in the subframe i is determined by the user equipment by using the sum of the base power adjustment value and any one of the
 10 first power adjustment value determined according to the quantity of the bits of the first uplink control information that is to be sent on the first PUCCH, the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH, the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the
 15 quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH, the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first
 20 PUCCH by the second uplink control information, or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH. Therefore, a method for determining the transmit power for sending the first uplink control information on the first PUCCH is provided.

25 [0299] Based on the foregoing embodiment, the quantity of the bits of the first uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the first uplink control information, and the quantity of the bits of the second uplink control information includes a quantity of bits of a cyclic redundancy code CRC corresponding to the second uplink control information.

[0300] The first PUCCH is in a first physical uplink control channel PUCCH format. The PUCCH in the first PUCCH format is characterized in that:

the PUCCH occupies at least one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or two time-domain symbols in each timeslot bear a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

10 a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

[0301] If a quantity of RBs occupied by the first PUCCH is not greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the first power adjustment value and the base power adjustment value, or the transmit power is a sum of the second power adjustment value and the base power adjustment value; or

if a quantity of RBs occupied by the first PUCCH is greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the third power adjustment value and the base power adjustment value, where

20

N_u is 1, 2, 3, or 4.

[0302] The quantity of the resources of the first PUCCH is K_{RE} , a quantity of modulation symbols occupied by the first PUCCH.

[0303] Alternatively, the quantity of the resources of the first PUCCH is Q' , a quantity of bits corresponding to modulation symbols occupied by the first PUCCH, where $Q' = K_{RE} * Q_m$, and Q_m is a modulation order used by the user equipment for sending the first uplink control information on the first PUCCH.

25

[0304] Alternatively, the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, a quantity of RBs included in the first PUCCH.

[0305] The quantity of the resources occupied on the first PUCCH by the second uplink control information is M_{RE} , a quantity of modulation symbols occupied on the first PUCCH by the second uplink control information.

[0306] Alternatively, the quantity of the resources occupied on the first PUCCH by the second uplink control information is Q'' , a quantity of bits corresponding to modulation symbols occupied on the first PUCCH by the second uplink control information, where $Q'' = M_{RE} * Q'$, and Q' is a modulation order used by the user equipment for sending the second uplink control information on the first PUCCH.

[0307] The first power adjustment value determined according to the quantity of the bits of the first uplink control information is $h'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

15 if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

20 [0308] The second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

[0309] $h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n_{bit}(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

5 if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,
and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$;

10 if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and
 $6.8 \leq P_2 \leq 10$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$,
and $8 \leq P_3 \leq 12.6$;

15 if $n_{bit}(i)$ is greater than 128 and $n_{bit}(i)$ is not greater than 256, $h'(n_{bit}(i)) = P_4$,
and $10.6 \leq P_4 \leq 17.7$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, where $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

[0310] The second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first

20 PUCCH is $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, where $n'_{bit}(i)$ indicates a quantity of bits obtained by subtracting the quantity of the bits of the cyclic redundancy code CRC corresponding to the second uplink control information from the quantity of the bits of the second uplink control information, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH, and a value

of $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n'_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

[0311] $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.05 \leq K_1 \leq 0.08$, and $-1.6 \leq K_2 \leq -0.7$; or

5 when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, where $0.03 \leq K_1 \leq 0.05$, and $-0.3 \leq K_2 \leq 0.5$.

[0312] $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where $0.05 \leq K_1 \leq 0.075$, and $-2.2 \leq K_2 \leq -1.1$; or

10 when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, where $0.03 \leq K_1 \leq 0.08$, and $-0.6 \leq K_2 \leq 0.1$.

[0313] The third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $k(m(i), M_{RB}^{PUCCH}(i))$, where
 15 $m(i)$ indicates the ratio of the quantity of the bits of the first uplink control information sent by the user equipment on the first PUCCH to the quantity of the resources of the first PUCCH, and a value of $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$.

[0314] When the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, the quantity
 of the RBs included in the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$,
 20 where

when $M_{RB}^{PUCCH}(i) = 1$;

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and

$$8.2 \leq P_2 \leq 12.12;$$

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$$q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ where } 0.05 \leq K_1 \leq 0.08, \text{ and } 5 \leq K_2 \leq 7; \text{ or}$$

5 when $M_{RB}^{PUCCH}(i) = 2$:

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $6.8 \leq P_2 \leq 10$;

10 if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $8 \leq P_3 \leq 12.6$;

if $m(i)$ is greater than 128 and $m(i)$ is not greater than 256, $q'(m(i)) = P_4$, and $10.6 \leq P_4 \leq 17.7$; or

$$q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ where } 0.02 \leq K_1 \leq 0.04, \text{ and } 5.5 \leq K_2 \leq 7.5.$$

[0315] When the quantity of the resources of the first PUCCH is K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$, where

when $M_{RB}^{PUCCH}(i) = 1$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $8 \leq K_1 \leq 11$, and $5 \leq K_2 \leq 7$; or

20 when $M_{RB}^{PUCCH}(i) = 2$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, where $8.5 \leq K_1 \leq 10.5$, and $6 \leq K_2 \leq 8$.

[0316] The determining the third power adjustment value according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH includes:

- determining the third power adjustment value according to a ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, where the third power adjustment value is $10\log_{10}(M_{RB}^{PUCCH}(i)) + 10\log_{10}((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH})$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the
- 5 RBs included in the first PUCCH, $BPRE$ is the ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.
- 10 [0317] β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following:
- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
 - a hybrid automatic repeat request HARQ-ACK; or
 - 15 a rank indication RI.
- [0318] If the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.
- 20 [0319] The fourth power adjustment value determined according to the quantity of the resources of the first PUCCH is $10\log_{10}(M_{RB}^{PUCCH}(i))$, where $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs included in the first PUCCH.
- [0320] The fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the
- 25 second uplink control information or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of

the second uplink control information to the quantity of the resources of the first PUCCH is $R(r(i), M_{RB}^{PUCCH}(i))$, where $r(i)$ indicates the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH, and a value of $R(r(i), M_{RB}^{PUCCH}(i))$ is determined by $r(i)$ and $M_{RB}^{PUCCH}(i)$.

[0321] The first PUCCH is in a third physical uplink control channel PUCCH format. The PUCCH in the third PUCCH format is characterized in that:

the PUCCH occupies one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal, where uplink control information of at least two user equipments is capable of being sent on the PUCCH by means of code division; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

[0322] The first power adjustment value determined according to the quantity of the bits of the first uplink control information is $k'(n_{bit}(i))$, where $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

$$k'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ where } 0.08 \leq K_1 \leq 0.12, \text{ and } -3.7 \leq K_2 \leq -2.7.$$

[0323] The third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $10\log_{10}\left(\left(2^{K_S \cdot BPRE} - 1\right) \cdot \beta_{offset}^{PUCCH}\right)$, where $BPRE$ is a ratio of the quantity of the bits of the first uplink control information to K_{RE} , a quantity of modulation symbols occupied by the first

PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_s is a value configured for the user equipment by the network device by using higher layer signaling.

- [0324] β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, where the first-type uplink control information is any one of the following:
- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
 - a hybrid automatic repeat request HARQ-ACK; or
 - a rank indication RI.
- 10 [0325] If the first uplink control information includes the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not include the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

- [0326] The network device provided in this embodiment of the present invention may be specifically configured to execute the method embodiment provided in FIG. 2. Detailed functions are not described herein again.

- [0327] This embodiment of the present invention specifically defines characteristics of the PUCCH in the first PUCCH format, to distinguish between the PUCCH in the first PUCCH format and a PUCCH in an existing PUCCH format, and also specifically defines a method for determining the quantity of the resources of the first PUCCH and the quantity of the resources occupied on the first PUCCH by the second uplink control information. This embodiment of the present invention specifically provides an expression for calculating the transmit power according to the sum of the base power adjustment value and any one of the first power adjustment value, the second power adjustment value, the third power adjustment value, the fourth power adjustment value, or the fifth power adjustment value, and provides a method for calculating the transmit power for sending the first uplink control information on the first PUCCH.

[0328] FIG. 5 is a structural diagram of a power control system for an uplink control channel according to an embodiment of the present invention. The power control system for

an uplink control channel that is provided in this embodiment of the present invention can execute a processing procedure provided in the embodiments of the power control method for an uplink control channel. As shown in FIG. 5, the power control system 50 for an uplink control channel includes the user equipment 30 and the network device 40 that are described
 5 in the foregoing embodiments.

[0329] The power control system for an uplink control channel that is provided in this embodiment of the present invention can execute the processing procedure provided in the embodiments of the power control method for an uplink control channel.

[0330] To sum up, in this embodiment of the present invention, transmit power for
 10 sending first uplink control information on a first PUCCH and in a subframe i is determined by the user equipment by using a sum of a base power adjustment value and any one of a first power adjustment value determined according to a quantity of bits of the first uplink control information that is to be sent on the first PUCCH, a second power adjustment value determined according to the quantity of the bits of the first uplink control information and a
 15 quantity of resources of the first PUCCH, a third power adjustment value determined according to the quantity of the resources of the first PUCCH and a ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, a fourth power adjustment value determined according to the quantity of the resources of the first PUCCH, a fifth power adjustment value determined according to the quantity of the
 20 resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to a quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to the quantity of the resources of the first PUCCH. Therefore, a method for
 25 determining the transmit power for sending the first uplink control information on the first PUCCH is provided. This embodiment of the present invention specifically defines characteristics of a PUCCH in a first PUCCH format, to distinguish between the PUCCH in the first PUCCH format and a PUCCH in an existing PUCCH format, and also specifically defines a method for determining the quantity of the resources of the first PUCCH and the

quantity of the resources occupied on the first PUCCH by the second uplink control information. This embodiment of the present invention specifically provides an expression for calculating the transmit power according to the sum of the base power adjustment value and any one of the first power adjustment value, the second power adjustment value, the third
 5 power adjustment value, the fourth power adjustment value, or the fifth power adjustment value, and provides a method for calculating the transmit power for sending the first uplink control information on the first PUCCH.

[0331] In the several embodiments provided in the present invention, it should be understood that the disclosed apparatus and method may be implemented in other manners.
 10 For example, the described apparatus embodiments are merely examples. For example, the unit division is merely logical function division and may be other division in an actual implementation. For example, a plurality of units or components may be combined or integrated into another system, or some features may be ignored or not performed. In addition, the shown or discussed mutual couplings or direct couplings or communication connections
 15 may be indirect couplings or communication connections implemented by using some interfaces, apparatuses or units, and may be implemented in electrical, mechanical, or other forms.

[0332] The units described as separate parts may or may not be physically separated. Parts shown as units may or may not be physical units, and may be located in one position or
 20 distributed on a plurality of network units. Some or all of the units may be selected according to actual requirements to achieve the objectives of the solutions of the embodiments.

[0333] In addition, functional units in the embodiments of the present invention may be integrated into one processing unit, or each of the units may exist alone physically, or two or more units are integrated into one unit. The integrated unit may be implemented in a form of
 25 hardware, or may be implemented in a form of hardware in addition to a software functional unit.

[0334] When the foregoing integrated unit is implemented in a form of a software functional unit, the integrated unit may be stored in a computer-readable storage medium. The software functional unit is stored in a storage medium and includes several instructions for
 30 instructing a computer device (which may be a personal computer, a server, a network device,

or the like) or a processor (processor) to perform some of the steps of the methods described in the embodiments of the present invention. The foregoing storage medium includes: any medium that can store program code, such as a USB flash drive, a removable hard disk, a read-only memory (Read-Only Memory, ROM), a random access memory (Random Access
5 Memory, RAM), a magnetic disk, or an optical disc.

[0335] It may be clearly understood by persons skilled in the art that, for the purpose of convenient and brief description, division of the foregoing functional modules is used as an example for illustration. In actual application, the foregoing functions can be allocated to different functional modules and implemented according to a requirement, that is, an inner
10 structure of an apparatus is divided into different functional modules to implement all or some of the functions described above. For a detailed working process of the foregoing apparatus, reference may be made to a corresponding process in the foregoing method embodiments, and details are not described herein again.

[0336] Finally, it should be noted that the foregoing embodiments are merely intended for
15 describing the technical solutions of the present invention, but not for limiting the present invention. Although the present invention is described in detail with reference to the foregoing embodiments, persons of ordinary skill in the art should understand that they may still make modifications to the technical solutions described in the foregoing embodiments or make equivalent replacements to some or all technical features thereof, without departing from the
20 scope of the technical solutions of the embodiments of the present invention.

CLAIMS

What is claimed is:

1. A power control method for an uplink control channel, comprising:

determining, by user equipment, to send first uplink control information on a first PUCCH and in a subframe i , wherein the first uplink control information comprises at least one of channel state information CSI, a hybrid automatic repeat request-acknowledgment HARQ-ACK, or a scheduling request SR;

determining, by the user equipment, transmit power for sending the first uplink control information on the first PUCCH and in the subframe i , wherein the transmit power is a sum of a base power adjustment value and any one of a first power adjustment value, a second power adjustment value, a third power adjustment value, a fourth power adjustment value, or a fifth power adjustment value; and

sending, by the user equipment, the first uplink control information on the first PUCCH by using power that is not greater than the transmit power, wherein

the first power adjustment value is a power adjustment value determined by the user equipment according to a quantity of bits of the first uplink control information, the second power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the bits of the first uplink control information and a quantity of resources of the first PUCCH, the third power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, the fourth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH, and the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to a quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value is a power adjustment value determined by the user equipment

according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to the quantity of the resources of the first PUCCH, wherein the second uplink control information is a subset of the first uplink control information; and

- 5 the base power adjustment value comprises a sum of P_{O_PUCCH} and PL_c , or the base power adjustment value comprises a sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, wherein

P_{O_PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling;

- PL_c is a path loss that is determined by the user equipment and that is of a downlink of a
10 cell c in which the first PUCCH is located; and

α_c is a path loss factor that is configured for the user equipment by the network device and that is of the cell c in which the first PUCCH is located.

2. The method according to claim 1, wherein the quantity of the bits of the first uplink control information comprises a quantity of bits of a cyclic redundancy code CRC
15 corresponding to the first uplink control information, and the quantity of the bits of the second uplink control information comprises a quantity of bits of a cyclic redundancy code CRC corresponding to the second uplink control information.

3. The method according to claim 1 or 2, wherein the first PUCCH is in a first physical uplink control channel PUCCH format, and the PUCCH in the first PUCCH format is
20 characterized in that:

- the PUCCH occupies at least one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or two time-domain symbols in each timeslot bear a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain
25 symbol in each timeslot bears a demodulation reference signal; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the

PUCCH is capable of bearing is greater than 22.

4. The method according to any one of claims 1 to 3, wherein if a quantity of RBs occupied by the first PUCCH is not greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe
5 i is a sum of the first power adjustment value and the base power adjustment value, or the transmit power is a sum of the second power adjustment value and the base power adjustment value; or

if a quantity of RBs occupied by the first PUCCH is greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH
10 and in the subframe i is a sum of the third power adjustment value and the base power adjustment value, wherein

N_u is 1, 2, 3, or 4.

5. The method according to any one of claims 1 to 4, wherein the quantity of the resources of the first PUCCH is K_{RE} , a quantity of modulation symbols occupied by the first
15 PUCCH; or

the quantity of the resources of the first PUCCH is Q' , a quantity of bits corresponding to modulation symbols occupied by the first PUCCH, wherein $Q' = K_{RE} * Q_m$, and Q_m is a modulation order used by the user equipment for sending the first uplink control information on the first PUCCH; or

20 the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, a quantity of RBs comprised in the first PUCCH; and

the quantity of the resources occupied on the first PUCCH by the second uplink control information is M_{RE} , a quantity of modulation symbols occupied on the first PUCCH by the second uplink control information; or

25 the quantity of the resources occupied on the first PUCCH by the second uplink control information is Q'' , a quantity of bits corresponding to modulation symbols occupied on the

first PUCCH by the second uplink control information, wherein $Q'' = M_{RE} * Q_m'$, and Q_m' is a modulation order used by the user equipment for sending the second uplink control information on the first PUCCH.

6. The method according to any one of claims 1 to 5, wherein the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $h'(n_{bit}(i))$, wherein $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, wherein $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

7. The method according to any one of claims 1 to 5, wherein the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$, wherein $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH, and a value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

8. The method according to claim 7, wherein $h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n_{bit}(i))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and

$$8.2 \leq P_2 \leq 12.12;$$

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ wherein } 0.05 \leq K_1 \leq 0.08, \text{ and } 5 \leq K_2 \leq 7; \text{ or}$$

5 when $M_{RB}^{PUCCH}(i) = 2$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $6.8 \leq P_2 \leq 10$;

10 if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $8 \leq P_3 \leq 12.6$;

if $n_{bit}(i)$ is greater than 128 and $n_{bit}(i)$ is not greater than 256, $h'(n_{bit}(i)) = P_4$, and $10.6 \leq P_4 \leq 17.7$; or

$$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ wherein } 0.02 \leq K_1 \leq 0.04, \text{ and } 5.5 \leq K_2 \leq 7.5.$$

9. The method according to any one of claims 1 to 5, wherein the second power
15 adjustment value determined according to the quantity of the bits of the first uplink control
information and the quantity of the resources of the first PUCCH is $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$,
wherein $n'_{bit}(i)$ indicates a quantity of bits obtained by subtracting the quantity of the bits of
the cyclic redundancy code CRC corresponding to the second uplink control information from
the quantity of the bits of the second uplink control information, $M_{RB}^{PUCCH}(i)$ is the quantity
20 of the RBs comprised in the first PUCCH, and a value of $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$ is
determined by $n'_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

10. The method according to claim 9, wherein
 $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, wherein $0.05 \leq K_1 \leq 0.08$, and $-1.6 \leq K_2 \leq -0.7$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, wherein $0.03 \leq K_1 \leq 0.05$, and $-0.3 \leq K_2 \leq 0.5$.

5 11. The method according to claim 9, wherein $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i) + h'(n'_{bit}(i)))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, wherein $0.05 \leq K_1 \leq 0.075$, and $-2.2 \leq K_2 \leq -1.1$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, wherein $0.03 \leq K_1 \leq 0.08$,
10 and $-0.6 \leq K_2 \leq 0.1$.

12. The method according to any one of claims 1 to 5, wherein the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $k(m(i), M_{RB}^{PUCCH}(i))$, wherein $m(i)$ indicates the ratio of
15 the quantity of the bits of the first uplink control information sent by the user equipment on the first PUCCH to the quantity of the resources of the first PUCCH, and a value of $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$.

13. The method according to claim 12, wherein when the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, the quantity of the RBs comprised in the first PUCCH,
20 $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i) + q'(m(i)))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$;

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$;

5 if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $6.8 \leq P_2 \leq 10$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $8 \leq P_3 \leq 12.6$;

10 if $m(i)$ is greater than 128 and $m(i)$ is not greater than 256, $q'(m(i)) = P_4$, and $10.6 \leq P_4 \leq 17.7$; or

$q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

14. The method according to claim 12, wherein when the quantity of the resources of the first PUCCH is K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH,

15 $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i) + q'(m(i)))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $8 \leq K_1 \leq 11$, and $5 \leq K_2 \leq 7$;

or

when $M_{RB}^{PUCCH}(i) = 2$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $8.5 \leq K_1 \leq 10.5$, and

$6 \leq K_2 \leq 8$.

20 15. The method according to any one of claims 1 to 5, wherein the determining the third power adjustment value according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH comprises:

determining the third power adjustment value according to a ratio of the quantity of the

bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, wherein the third power adjustment value is $10\log_{10}(M_{RB}^{PUCCH}(i)) + 10\log_{10}((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH})$, wherein $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH, $BPRE$ is the ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

16. The method according to claim 15, wherein β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, wherein the first-type uplink control information is any one of the following:

- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
- a hybrid automatic repeat request HARQ-ACK; or
- a rank indication RI; and

if the first uplink control information comprises the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not comprise the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

17. The method according to any one of claims 1 to 5, wherein the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH is $10\log_{10}(M_{RB}^{PUCCH}(i))$, wherein $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH.

18. The method according to any one of claims 1 to 5, wherein the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control

information or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH is $R(r(i), M_{RB}^{PUCCH}(i))$, wherein $r(i)$ indicates the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH, and a value of $R(r(i), M_{RB}^{PUCCH}(i))$ is determined by $r(i)$ and $M_{RB}^{PUCCH}(i)$.

19. The method according to claim 1 or 2, wherein the first PUCCH is in a third physical uplink control channel PUCCH format, and the PUCCH in the third PUCCH format is characterized in that:

the PUCCH occupies one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal, wherein uplink control information of at least two user equipments is capable of being sent on the PUCCH by means of code division; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

20. The method according to any one of claim 1, 2, or 19, wherein the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $k'(n_{bit}(i))$, wherein $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

$$k'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ wherein } 0.08 \leq K_1 \leq 0.12, \text{ and } -3.7 \leq K_2 \leq -2.7.$$

21. The method according to any one of claim 1, 2, or 19, wherein the third power adjustment value determined according to the quantity of the resources of the first PUCCH

and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $10\log_{10}\left(\left(2^{K_S \cdot BPRE} - 1\right) \cdot \beta_{offset}^{PUCCH}\right)$, wherein $BPRE$ is a ratio of the quantity of the bits of the first uplink control information to K_{RE} , a quantity of modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

22. The method according to claim 21, wherein β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, wherein the first-type uplink control information is any one of the following:

- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
- a hybrid automatic repeat request HARQ-ACK; or
- a rank indication RI; and

if the first uplink control information comprises the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not comprise the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

23. A power control method for an uplink control channel, comprising:

determining, by a network device, that user equipment is to send first uplink control information on a first PUCCH and in a subframe i , wherein the first uplink control information comprises at least one of channel state information CSI, a hybrid automatic repeat request-acknowledgment HARQ-ACK, or a scheduling request SR;

determining, by the network device, transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i , wherein the transmit power is a sum of a base power adjustment value and any one of a first power adjustment value, a second power adjustment value, a third power adjustment value, a fourth power adjustment value, or a fifth power adjustment value; and

receiving, by the network device, the first uplink control information that is sent by the user equipment on the first PUCCH by using power that is not greater than the transmit power, wherein

the first power adjustment value is a power adjustment value determined by the user equipment according to a quantity of bits of the first uplink control information, the second power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the bits of the first uplink control information and a quantity of resources of the first PUCCH, the third power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, the fourth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH, and the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to a quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to the quantity of the resources of the first PUCCH, wherein the second uplink control information is a subset of the first uplink control information; and

the base power adjustment value comprises a sum of P_{O_PUCCH} and PL_c , or the base power adjustment value comprises a sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, wherein

P_{O_PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling;

PL_c is a path loss that is determined by the user equipment and that is of a downlink of a cell c in which the first PUCCH is located; and

α_c is a path loss factor that is configured for the user equipment by the network device

and that is of the cell c in which the first PUCCH is located.

24. The method according to claim 23, wherein the quantity of the bits of the first uplink control information comprises a quantity of bits of a cyclic redundancy code CRC corresponding to the first uplink control information, and the quantity of the bits of the second
5 uplink control information comprises a quantity of bits of a cyclic redundancy code CRC corresponding to the second uplink control information.

25. The method according to claim 23 or 24, wherein the first PUCCH is in a first physical uplink control channel PUCCH format, and the PUCCH in the first PUCCH format is characterized in that:

10 the PUCCH occupies at least one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or two time-domain symbols in each timeslot bear a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal; or

15 the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

26. The method according to any one of claims 23 to 25, wherein if a quantity of RBs
20 occupied by the first PUCCH is not greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the first power adjustment value and the base power adjustment value, or the transmit power is a sum of the second power adjustment value and the base power adjustment value; or

25 if a quantity of RBs occupied by the first PUCCH is greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the third power adjustment value and the base power adjustment value, wherein

N_u is 1, 2, 3, or 4.

27. The method according to any one of claims 23 to 26, wherein the quantity of the resources of the first PUCCH is K_{RE} , a quantity of modulation symbols occupied by the first PUCCH; or

5 the quantity of the resources of the first PUCCH is Q' , a quantity of bits corresponding to modulation symbols occupied by the first PUCCH, wherein $Q' = K_{RE} * Q_m$, and Q_m is a modulation order used by the user equipment for sending the first uplink control information on the first PUCCH; or

the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, a quantity of RBs
10 comprised in the first PUCCH; and

the quantity of the resources occupied on the first PUCCH by the second uplink control information is M_{RE} , a quantity of modulation symbols occupied on the first PUCCH by the second uplink control information; or

the quantity of the resources occupied on the first PUCCH by the second uplink control
15 information is Q'' , a quantity of bits corresponding to modulation symbols occupied on the first PUCCH by the second uplink control information, wherein $Q'' = M_{RE} * Q'_m$, and Q'_m is a modulation order used by the user equipment for sending the second uplink control information on the first PUCCH.

28. The method according to any one of claims 23 to 27, wherein the first power
20 adjustment value determined according to the quantity of the bits of the first uplink control information is $h'(n_{bit}(i))$, wherein $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and
25 $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ wherein } 0.05 \leq K_1 \leq 0.08, \text{ and } 5 \leq K_2 \leq 7.$$

29. The method according to any one of claims 23 to 27, wherein the second power
5 adjustment value determined according to the quantity of the bits of the first uplink control
information and the quantity of the resources of the first PUCCH is $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$,
wherein $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent
on the first PUCCH, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH,
and a value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

10 30. The method according to claim 29, wherein
 $h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n_{bit}(i))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

15 if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and
 $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and
 $11.4 \leq P_3 \leq 17.24$; or

$$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ wherein } 0.05 \leq K_1 \leq 0.08, \text{ and } 5 \leq K_2 \leq 7; \text{ or}$$

when $M_{RB}^{PUCCH}(i) = 2$;

20 if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and
 $6.8 \leq P_2 \leq 10$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and

$$8 \leq P_3 \leq 12.6 ;$$

if $n_{bit}(i)$ is greater than 128 and $n_{bit}(i)$ is not greater than 256, $h'(n_{bit}(i)) = P_4$, and $10.6 \leq P_4 \leq 17.7$; or

$$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ wherein } 0.02 \leq K_1 \leq 0.04, \text{ and } 5.5 \leq K_2 \leq 7.5.$$

5 31. The method according to any one of claims 23 to 27, wherein the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, wherein $n'_{bit}(i)$ indicates a quantity of bits obtained by subtracting the quantity of the bits of the cyclic redundancy code CRC corresponding to the second uplink control information from
10 the quantity of the bits of the second uplink control information, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH, and a value of $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n'_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

32. The method according to claim 31, wherein $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, wherein

15 when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, wherein $0.05 \leq K_1 \leq 0.08$, and $-1.6 \leq K_2 \leq -0.7$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, wherein $0.03 \leq K_1 \leq 0.05$, and $-0.3 \leq K_2 \leq 0.5$.

33. The method according to claim 31, wherein $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, wherein
20

when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, wherein $0.05 \leq K_1 \leq 0.075$, and $-2.2 \leq K_2 \leq -1.1$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, wherein $0.03 \leq K_1 \leq 0.08$,

and $-0.6 \leq K_2 \leq 0.1$.

34. The method according to any one of claims 23 to 27, wherein the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $k(m(i), M_{RB}^{PUCCH}(i))$, wherein $m(i)$ indicates the ratio of the quantity of the bits of the first uplink control information sent by the user equipment on the first PUCCH to the quantity of the resources of the first PUCCH, and a value of $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$.

35. The method according to claim 34, wherein when the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, the quantity of the RBs comprised in the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i) + q'(m(i)))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$;

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$;

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $6.8 \leq P_2 \leq 10$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $8 \leq P_3 \leq 12.6$;

if $m(i)$ is greater than 128 and $m(i)$ is not greater than 256, $q'(m(i)) = P_4$, and $10.6 \leq P_4 \leq 17.7$; or

$$q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ wherein } 0.02 \leq K_1 \leq 0.04, \text{ and } 5.5 \leq K_2 \leq 7.5.$$

36. The method according to claim 34, wherein when the quantity of the resources of the first PUCCH is K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH,

$$k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i)), \text{ wherein}$$

$$\text{when } M_{RB}^{PUCCH}(i) = 1, \quad q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ wherein } 8 \leq K_1 \leq 11, \text{ and } 5 \leq K_2 \leq 7;$$

or

$$\text{when } M_{RB}^{PUCCH}(i) = 2, \quad q'(m(i)) = K_1 \cdot m(i) + K_2, \text{ wherein } 8.5 \leq K_1 \leq 10.5, \text{ and}$$

$$6 \leq K_2 \leq 8.$$

37. The method according to any one of claims 23 to 27, wherein the determining the third power adjustment value according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH comprises:

15 determining the third power adjustment value according to a ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, wherein the third power adjustment value is $10 \log_{10}(M_{RB}^{PUCCH}(i)) + 10 \log_{10}((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH})$, wherein $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH, $BPRE$ is the ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

38. The method according to claim 37, wherein β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when

first-type uplink control information is sent on a PUSCH, wherein the first-type uplink control information is any one of the following:

a channel quality indicator CQI and/or a precoding matrix indicator PMI;

a hybrid automatic repeat request HARQ-ACK; or

5 a rank indication RI; and

if the first uplink control information comprises the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not comprise the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

10 39. The method according to any one of claims 23 to 27, wherein the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH is $10\log_{10}(M_{RB}^{PUCCH}(i))$, wherein $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH.

15 40. The method according to any one of claims 23 to 27, wherein the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH is $R(r(i), M_{RB}^{PUCCH}(i))$,
 20 wherein $r(i)$ indicates the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH, and a value of $R(r(i), M_{RB}^{PUCCH}(i))$ is determined by $r(i)$ and $M_{RB}^{PUCCH}(i)$.
 25

41. The method according to claim 23 or 24, wherein the first PUCCH is in a third physical uplink control channel PUCCH format, and the PUCCH in the third PUCCH format is characterized in that:

the PUCCH occupies one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal, wherein uplink control
 5 information of at least two user equipments is capable of being sent on the PUCCH by means of code division; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the
 10 PUCCH is capable of bearing is greater than 22.

42. The method according to any one of claim 23, 24, or 41, wherein the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $k'(n_{bit}(i))$, wherein $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

15 $k'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, wherein $0.08 \leq K_1 \leq 0.12$, and $-3.7 \leq K_2 \leq -2.7$.

43. The method according to any one of claim 23, 24, or 41, wherein the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $10 \log_{10} \left((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH} \right)$, wherein $BPRE$ is a
 20 ratio of the quantity of the bits of the first uplink control information to K_{RE} , a quantity of modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

44. The method according to claim 43, wherein β_{offset}^{PUCCH} is a parameter used to
 25 determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, wherein the first-type uplink control information is any one of the following:

a channel quality indicator CQI and/or a precoding matrix indicator PMI;

a hybrid automatic repeat request HARQ-ACK; or

a rank indication RI; and

if the first uplink control information comprises the HARQ-ACK or the RI, the first-type
 5 uplink control information is the HARQ-ACK or the RI; or if the first uplink control
 information does not comprise the HARQ-ACK and the RI, the first-type uplink control
 information is the CQI and/or the PMI.

45. User equipment, comprising:

a first processing unit, configured to: determine that first uplink control information is to
 10 be sent on a first PUCCH and in a subframe i , wherein the first uplink control information
 comprises at least one of channel state information CSI, a hybrid automatic repeat
 request-acknowledgment HARQ-ACK, or a scheduling request SR; determine transmit power
 for sending the first uplink control information on the first PUCCH and in the subframe i ,
 wherein the transmit power is a sum of a base power adjustment value and any one of a first
 15 power adjustment value, a second power adjustment value, a third power adjustment value, a
 fourth power adjustment value, or a fifth power adjustment value; and

a sending unit, configured to send the first uplink control information on the first
 PUCCH by using power that is not greater than the transmit power, wherein

the first power adjustment value is a power adjustment value determined by the user
 20 equipment according to a quantity of bits of the first uplink control information, the second
 power adjustment value is a power adjustment value determined by the user equipment
 according to the quantity of the bits of the first uplink control information and a quantity of
 resources of the first PUCCH, the third power adjustment value is a power adjustment value
 determined by the user equipment according to the quantity of the resources of the first
 25 PUCCH and a ratio of the quantity of the bits of the first uplink control information to the
 quantity of the resources of the first PUCCH, the fourth power adjustment value is a power
 adjustment value determined by the user equipment according to the quantity of the resources
 of the first PUCCH, and the fifth power adjustment value is a power adjustment value
 determined by the user equipment according to the quantity of the resources of the first

PUCCH and a ratio of a quantity of bits of second uplink control information to a quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits
 5 of second uplink control information to the quantity of the resources of the first PUCCH, wherein the second uplink control information is a subset of the first uplink control information; and

the base power adjustment value comprises a sum of P_{O_PUCCH} and PL_c , or the base power adjustment value comprises a sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, wherein

10 P_{O_PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling;

PL_c is a path loss that is determined by the user equipment and that is of a downlink of a cell c in which the first PUCCH is located; and

α_c is a path loss factor that is configured for the user equipment by the network device
 15 and that is of the cell c in which the first PUCCH is located.

46. The user equipment according to claim 45, wherein the quantity of the bits of the first uplink control information comprises a quantity of bits of a cyclic redundancy code CRC corresponding to the first uplink control information, and the quantity of the bits of the second uplink control information comprises a quantity of bits of a cyclic redundancy code CRC
 20 corresponding to the second uplink control information.

47. The user equipment according to claim 45 or 46, wherein the first PUCCH is in a first physical uplink control channel PUCCH format, and the PUCCH in the first PUCCH format is characterized in that:

the PUCCH occupies at least one RB, and in a case of a normal cyclic prefix, only one
 25 time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or two time-domain symbols in each timeslot bear a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

5 48. The user equipment according to any one of claims 45 to 47, wherein if a quantity of RBs occupied by the first PUCCH is not greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the first power adjustment value and the base power adjustment value, or the transmit power is a sum of the second power adjustment value and the base power adjustment value; or

if a quantity of RBs occupied by the first PUCCH is greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the third power adjustment value and the base power adjustment value, wherein

15 N_u is 1, 2, 3, or 4.

49. The user equipment according to any one of claims 45 to 48, wherein the quantity of the resources of the first PUCCH is K_{RE} , a quantity of modulation symbols occupied by the first PUCCH; or

the quantity of the resources of the first PUCCH is Q' , a quantity of bits corresponding to modulation symbols occupied by the first PUCCH, wherein $Q' = K_{RE} * Q_m$, and Q_m is a modulation order used by the user equipment for sending the first uplink control information on the first PUCCH; or

the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, a quantity of RBs comprised in the first PUCCH; and

25 the quantity of the resources occupied on the first PUCCH by the second uplink control information is M_{RE} , a quantity of modulation symbols occupied on the first PUCCH by the

second uplink control information; or

the quantity of the resources occupied on the first PUCCH by the second uplink control information is Q'' , a quantity of bits corresponding to modulation symbols occupied on the first PUCCH by the second uplink control information, wherein $Q'' = M_{RE} * Q_m'$, and Q_m' is a modulation order used by the user equipment for sending the second uplink control information on the first PUCCH.

50. The user equipment according to any one of claims 45 to 49, wherein the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $h'(n_{bit}(i))$, wherein $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, wherein $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

51. The user equipment according to any one of claims 45 to 49, wherein the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$, wherein $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH, and a value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

52. The user equipment according to claim 51, wherein $h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n_{bit}(i))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

5 if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, wherein $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

10 if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $6.8 \leq P_2 \leq 10$;

if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $8 \leq P_3 \leq 12.6$;

15 if $n_{bit}(i)$ is greater than 128 and $n_{bit}(i)$ is not greater than 256, $h'(n_{bit}(i)) = P_4$, and $10.6 \leq P_4 \leq 17.7$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, wherein $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

53. The user equipment according to any one of claims 45 to 49, wherein the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is

20 $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, wherein $n'_{bit}(i)$ indicates a quantity of bits obtained by subtracting the quantity of the bits of the cyclic redundancy code CRC corresponding to the second uplink control information from the quantity of the bits of the second uplink control information, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH, and a

value of $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n'_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

54. The user equipment according to claim 53, wherein

$$h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i)), \text{ wherein}$$

$$\text{when } M_{RB}^{PUCCH}(i) = 1, \quad h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2, \text{ wherein } 0.05 \leq K_1 \leq 0.08, \text{ and}$$

$$-1.6 \leq K_2 \leq -0.7; \text{ or}$$

$$\text{when } M_{RB}^{PUCCH}(i) = 2, \quad h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2, \text{ wherein } 0.03 \leq K_1 \leq 0.05, \text{ and}$$

$$-0.3 \leq K_2 \leq 0.5.$$

55. The user equipment according to claim 53, wherein

$$h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i)), \text{ wherein}$$

$$\text{when } M_{RB}^{PUCCH}(i) = 1, \quad h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2, \text{ wherein } 0.05 \leq K_1 \leq 0.075,$$

$$\text{and } -2.2 \leq K_2 \leq -1.1; \text{ or}$$

$$\text{when } M_{RB}^{PUCCH}(i) = 2, \quad h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2, \text{ wherein } 0.03 \leq K_1 \leq 0.08,$$

$$\text{and } -0.6 \leq K_2 \leq 0.1.$$

56. The user equipment according to any one of claims 45 to 49, wherein the third power
adjustment value determined according to the quantity of the resources of the first PUCCH
and the ratio of the quantity of the bits of the first uplink control information to the quantity of
the resources of the first PUCCH is $k(m(i), M_{RB}^{PUCCH}(i))$, wherein $m(i)$ indicates the ratio of
the quantity of the bits of the first uplink control information sent by the user equipment on
the first PUCCH to the quantity of the resources of the first PUCCH, and a value of
 $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$.

57. The user equipment according to claim 56, wherein when the quantity of the
resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, the quantity of the RBs comprised in the first
PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$, wherein

$$\text{when } M_{RB}^{PUCCH}(i) = 1;$$

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and
5 $11.4 \leq P_3 \leq 17.24$; or

$q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$;

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and
10 $6.8 \leq P_2 \leq 10$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and
 $8 \leq P_3 \leq 12.6$;

if $m(i)$ is greater than 128 and $m(i)$ is not greater than 256, $q'(m(i)) = P_4$, and
 $10.6 \leq P_4 \leq 17.7$; or

15 $q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

58. The user equipment according to claim 56, wherein when the quantity of the resources of the first PUCCH is K_{RE} , the quantity of the modulation symbols occupied by the

first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i) + q'(m(i)))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $8 \leq K_1 \leq 11$, and $5 \leq K_2 \leq 7$;

20 or

when $M_{RB}^{PUCCH}(i) = 2$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $8.5 \leq K_1 \leq 10.5$, and
 $6 \leq K_2 \leq 8$.

59. The user equipment according to any one of claims 45 to 49, wherein the determining

the third power adjustment value according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH comprises:

determining the third power adjustment value according to a ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, wherein the third power adjustment value is $10\log_{10}(M_{RB}^{PUCCH}(i)) + 10\log_{10}((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH})$, wherein $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH, $BPRE$ is the ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

60. The user equipment according to claim 59, wherein β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, wherein the first-type uplink control information is any one of the following:

- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
- a hybrid automatic repeat request HARQ-ACK; or
- a rank indication RI; and

if the first uplink control information comprises the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not comprise the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

61. The user equipment according to any one of claims 45 to 49, wherein the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH is $10\log_{10}(M_{RB}^{PUCCH}(i))$, wherein $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH.

62. The user equipment according to any one of claims 45 to 49, wherein the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH is $R(r(i), M_{RB}^{PUCCH}(i))$, wherein $r(i)$ indicates the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH, and a value of $R(r(i), M_{RB}^{PUCCH}(i))$ is determined by $r(i)$ and $M_{RB}^{PUCCH}(i)$.

63. The user equipment according to claim 45 or 46, wherein the first PUCCH is in a third physical uplink control channel PUCCH format, and the PUCCH in the third PUCCH format is characterized in that:

the PUCCH occupies one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal, wherein uplink control information of at least two user equipments is capable of being sent on the PUCCH by means of code division; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

64. The user equipment according to any one of claim 45, 46, or 63, wherein the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $k'(n_{bit}(i))$, wherein $n_{bit}(i)$ indicates the quantity of the bits of the

first uplink control information sent on the first PUCCH; and

$$k'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2, \text{ wherein } 0.08 \leq K_1 \leq 0.12, \text{ and } -3.7 \leq K_2 \leq -2.7.$$

65. The user equipment according to any one of claim 45, 46, or 63, wherein the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $10 \log_{10} \left((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH} \right)$, wherein $BPRE$ is a ratio of the quantity of the bits of the first uplink control information to K_{RE} , a quantity of modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a value configured for the user equipment by the network device by using higher layer signaling.

66. The user equipment according to claim 65, wherein β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, wherein the first-type uplink control information is any one of the following:

- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
- a hybrid automatic repeat request HARQ-ACK; or
- a rank indication RI; and

if the first uplink control information comprises the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not comprise the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

67. A network device, comprising:

a second processing unit, configured to: determine that user equipment is to send first uplink control information on a first PUCCH and in a subframe i , wherein the first uplink control information comprises at least one of channel state information CSI, a hybrid automatic repeat request-acknowledgment HARQ-ACK, or a scheduling request SR;

determine transmit power for sending the first uplink control information on the first PUCCH and in the subframe i , wherein the transmit power is a sum of a base power adjustment value and any one of a first power adjustment value, a second power adjustment value, a third power adjustment value, a fourth power adjustment value, or a fifth power adjustment value;

5 and

a receiving unit, configured to receive the first uplink control information that is sent by the user equipment on the first PUCCH by using power that is not greater than the transmit power, wherein

the first power adjustment value is a power adjustment value determined by the user
 10 equipment according to a quantity of bits of the first uplink control information, the second power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the bits of the first uplink control information and a quantity of resources of the first PUCCH, the third power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first
 15 PUCCH and a ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH, the fourth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH, and the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first
 20 PUCCH and a ratio of a quantity of bits of second uplink control information to a quantity of resources occupied on the first PUCCH by the second uplink control information, or the fifth power adjustment value is a power adjustment value determined by the user equipment according to the quantity of the resources of the first PUCCH and a ratio of a quantity of bits of second uplink control information to the quantity of the resources of the first PUCCH,
 25 wherein the second uplink control information is a subset of the first uplink control information; and

the base power adjustment value comprises a sum of P_{O_PUCCH} and PL_c , or the base power adjustment value comprises a sum of P_{O_PUCCH} and $\alpha_c \cdot PL_c$, wherein

P_{O_PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling;

PL_c is a path loss that is determined by the user equipment and that is of a downlink of a cell c in which the first PUCCH is located; and

5 α_c is a path loss factor that is configured for the user equipment by the network device and that is of the cell c in which the first PUCCH is located.

68. The network device according to claim 67, wherein the quantity of the bits of the first uplink control information comprises a quantity of bits of a cyclic redundancy code CRC corresponding to the first uplink control information, and the quantity of the bits of the second
10 uplink control information comprises a quantity of bits of a cyclic redundancy code CRC corresponding to the second uplink control information.

69. The network device according to claim 67 or 68, wherein the first PUCCH is in a first physical uplink control channel PUCCH format, and the PUCCH in the first PUCCH format is characterized in that:

15 the PUCCH occupies at least one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or two time-domain symbols in each timeslot bear a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal; or

20 the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the PUCCH is capable of bearing is greater than 22.

70. The network device according to any one of claims 67 to 69, wherein if a quantity of
25 RBs occupied by the first PUCCH is not greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the first power adjustment value and the base power adjustment value, or the transmit power is a sum of the second power adjustment value and the base

power adjustment value; or

if a quantity of RBs occupied by the first PUCCH is greater than N_u , the transmit power for sending, by the user equipment, the first uplink control information on the first PUCCH and in the subframe i is a sum of the third power adjustment value and the base power adjustment value, wherein

N_u is 1, 2, 3, or 4.

71. The network device according to any one of claims 67 to 70, wherein the quantity of the resources of the first PUCCH is K_{RE} , a quantity of modulation symbols occupied by the first PUCCH; or

the quantity of the resources of the first PUCCH is Q' , a quantity of bits corresponding to modulation symbols occupied by the first PUCCH, wherein $Q' = K_{RE} * Q_m$, and Q_m is a modulation order used by the user equipment for sending the first uplink control information on the first PUCCH; or

the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, a quantity of RBs comprised in the first PUCCH; and

the quantity of the resources occupied on the first PUCCH by the second uplink control information is M_{RE} , a quantity of modulation symbols occupied on the first PUCCH by the second uplink control information; or

the quantity of the resources occupied on the first PUCCH by the second uplink control information is Q'' , a quantity of bits corresponding to modulation symbols occupied on the first PUCCH by the second uplink control information, wherein $Q'' = M_{RE} * Q'_m$, and Q'_m is a modulation order used by the user equipment for sending the second uplink control information on the first PUCCH.

72. The network device according to any one of claims 67 to 71, wherein the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $h'(n_{bit}(i))$, wherein $n_{bit}(i)$ indicates the quantity of the bits of the first uplink

control information sent on the first PUCCH; and

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

5 if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, wherein $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$.

73. The network device according to any one of claims 67 to 71, wherein the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$, wherein $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH, and a value of $h'(n_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

15 74. The network device according to claim 73, wherein $h'(n_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n_{bit}(i))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

20 if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, wherein $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$;

if $n_{bit}(i)$ is not greater than 22, $h'(n_{bit}(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $n_{bit}(i)$ is greater than 22 and $n_{bit}(i)$ is not greater than 64, $h'(n_{bit}(i)) = P_2$, and $6.8 \leq P_2 \leq 10$;

5 if $n_{bit}(i)$ is greater than 64 and $n_{bit}(i)$ is not greater than 128, $h'(n_{bit}(i)) = P_3$, and $8 \leq P_3 \leq 12.6$;

if $n_{bit}(i)$ is greater than 128 and $n_{bit}(i)$ is not greater than 256, $h'(n_{bit}(i)) = P_4$, and $10.6 \leq P_4 \leq 17.7$; or

$h'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, wherein $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

10 75. The network device according to any one of claims 67 to 71, wherein the second power adjustment value determined according to the quantity of the bits of the first uplink control information and the quantity of the resources of the first PUCCH is $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$, wherein $n'_{bit}(i)$ indicates a quantity of bits obtained by subtracting the quantity of the bits of the cyclic redundancy code CRC corresponding to the second
15 uplink control information from the quantity of the bits of the second uplink control information, $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH, and a value of $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i))$ is determined by $n'_{bit}(i)$ and $M_{RB}^{PUCCH}(i)$.

76. The network device according to claim 75, wherein $h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, wherein

20 when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, wherein $0.05 \leq K_1 \leq 0.08$, and $-1.6 \leq K_2 \leq -0.7$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times n'_{bit}(i) + K_2$, wherein $0.03 \leq K_1 \leq 0.05$, and $-0.3 \leq K_2 \leq 0.5$.

77. The network device according to claim 75, wherein

$h'(n'_{bit}(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + h'(n'_{bit}(i))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, wherein $0.05 \leq K_1 \leq 0.075$,

and $-2.2 \leq K_2 \leq -1.1$; or

when $M_{RB}^{PUCCH}(i) = 2$, $h'(n'_{bit}(i)) = K_1 \times (n'_{bit}(i) + 8) + K_2$, wherein $0.03 \leq K_1 \leq 0.08$,

5 and $-0.6 \leq K_2 \leq 0.1$.

78. The network device according to any one of claims 67 to 71, wherein the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $k(m(i), M_{RB}^{PUCCH}(i))$, wherein $m(i)$ indicates the ratio of the quantity of the bits of the first uplink control information sent by the user equipment on the first PUCCH to the quantity of the resources of the first PUCCH, and a value of $k(m(i), M_{RB}^{PUCCH}(i))$ is determined by $m(i)$ and $M_{RB}^{PUCCH}(i)$.

79. The network device according to claim 78, wherein when the quantity of the resources of the first PUCCH is $M_{RB}^{PUCCH}(i)$, the quantity of the RBs comprised in the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$:

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $6.1 \leq P_1 \leq 8.76$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $8.2 \leq P_2 \leq 12.12$;

20 if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $11.4 \leq P_3 \leq 17.24$; or

$q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $0.05 \leq K_1 \leq 0.08$, and $5 \leq K_2 \leq 7$; or

when $M_{RB}^{PUCCH}(i) = 2$:

if $m(i)$ is not greater than 22, $q'(m(i)) = P_1$, and $5.9 \leq P_1 \leq 8.4$;

if $m(i)$ is greater than 22 and $m(i)$ is not greater than 64, $q'(m(i)) = P_2$, and $6.8 \leq P_2 \leq 10$;

if $m(i)$ is greater than 64 and $m(i)$ is not greater than 128, $q'(m(i)) = P_3$, and $8 \leq P_3 \leq 12.6$;

5 if $m(i)$ is greater than 128 and $m(i)$ is not greater than 256, $q'(m(i)) = P_4$, and $10.6 \leq P_4 \leq 17.7$; or

$q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $0.02 \leq K_1 \leq 0.04$, and $5.5 \leq K_2 \leq 7.5$.

80. The network device according to claim 78, wherein when the quantity of the resources of the first PUCCH is K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, $k(m(i), M_{RB}^{PUCCH}(i)) = 10 \log_{10}(M_{RB}^{PUCCH}(i)) + q'(m(i))$, wherein

when $M_{RB}^{PUCCH}(i) = 1$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $8 \leq K_1 \leq 11$, and $5 \leq K_2 \leq 7$;

or

when $M_{RB}^{PUCCH}(i) = 2$, $q'(m(i)) = K_1 \cdot m(i) + K_2$, wherein $8.5 \leq K_1 \leq 10.5$, and $6 \leq K_2 \leq 8$.

15 81. The network device according to any one of claims 67 to 71, wherein the determining the third power adjustment value according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH comprises:

determining the third power adjustment value according to a ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by the first PUCCH, wherein the third power adjustment value is $10 \log_{10}(M_{RB}^{PUCCH}(i)) + 10 \log_{10}((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH})$, wherein $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH, $BPRE$ is the ratio of the quantity of the bits of the first uplink control information to K_{RE} , the quantity of the modulation symbols occupied by

the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_s is a value configured for the user equipment by the network device by using higher layer signaling.

82. The network device according to claim 81, wherein β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, wherein the first-type uplink control information is any one of the following:

- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
- a hybrid automatic repeat request HARQ-ACK; or
- a rank indication RI; and

if the first uplink control information comprises the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not comprise the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

83. The network device according to any one of claims 67 to 71, wherein the fourth power adjustment value determined according to the quantity of the resources of the first PUCCH is $10\log_{10}(M_{RB}^{PUCCH}(i))$, wherein $M_{RB}^{PUCCH}(i)$ is the quantity of the RBs comprised in the first PUCCH.

84. The network device according to any one of claims 67 to 71, wherein the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the fifth power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources of the first PUCCH is $R(r(i), M_{RB}^{PUCCH}(i))$, wherein $r(i)$ indicates the ratio of the quantity of the bits of the second uplink control information to the quantity of the resources occupied on the first PUCCH by the second uplink control information or the ratio of the quantity of the bits of the second uplink control

information to the quantity of the resources of the first PUCCH, and a value of $R(r(i), M_{RB}^{PUCCH}(i))$ is determined by $r(i)$ and $M_{RB}^{PUCCH}(i)$.

85. The network device according to claim 67 or 68, wherein the first PUCCH is in a third physical uplink control channel PUCCH format, and the PUCCH in the third PUCCH
5 format is characterized in that:

the PUCCH occupies one RB, and in a case of a normal cyclic prefix, only one time-domain symbol in the middle of each timeslot corresponding to the PUCCH bears a demodulation reference signal, or in a case of an extended cyclic prefix, the third time-domain symbol in each timeslot bears a demodulation reference signal, wherein uplink control
10 information of at least two user equipments is capable of being sent on the PUCCH by means of code division; or

the PUCCH is capable of encoding the first uplink control information according to a convolutional code encoding manner; or

a maximum quantity of bits that are of the first uplink control information and that the
15 PUCCH is capable of bearing is greater than 22.

86. The network device according to any one of claim 67, 68, or 85, wherein the first power adjustment value determined according to the quantity of the bits of the first uplink control information is $k'(n_{bit}(i))$, wherein $n_{bit}(i)$ indicates the quantity of the bits of the first uplink control information sent on the first PUCCH; and

20 $k'(n_{bit}(i)) = K_1 \cdot n_{bit}(i) + K_2$, wherein $0.08 \leq K_1 \leq 0.12$, and $-3.7 \leq K_2 \leq -2.7$.

87. The network device according to any one of claim 67, 68, or 85, wherein the third power adjustment value determined according to the quantity of the resources of the first PUCCH and the ratio of the quantity of the bits of the first uplink control information to the quantity of the resources of the first PUCCH is $10 \log_{10}((2^{K_S \cdot BPRE} - 1) \cdot \beta_{offset}^{PUCCH})$, wherein
25 $BPRE$ is a ratio of the quantity of the bits of the first uplink control information to K_{RE} , a quantity of modulation symbols occupied by the first PUCCH, β_{offset}^{PUCCH} is a value configured for the user equipment by the network device by using higher layer signaling, and K_S is a

value configured for the user equipment by the network device by using higher layer signaling.

88. The network device according to claim 87, wherein β_{offset}^{PUCCH} is a parameter used to determine a quantity of modulation symbols in a PUSCH resource that are occupied when first-type uplink control information is sent on a PUSCH, wherein the first-type uplink control information is any one of the following:
- a channel quality indicator CQI and/or a precoding matrix indicator PMI;
 - a hybrid automatic repeat request HARQ-ACK; or
 - a rank indication RI; and
- if the first uplink control information comprises the HARQ-ACK or the RI, the first-type uplink control information is the HARQ-ACK or the RI; or if the first uplink control information does not comprise the HARQ-ACK and the RI, the first-type uplink control information is the CQI and/or the PMI.

1/3




FIG. 1

2/3




FIG. 2

3/3




FIG. 3




FIG. 4




FIG. 5

