

(51) International Patent Classification:
H04R 3/00 (2006.01)(21) International Application Number:
PCT/US2016/039888(22) International Filing Date:
28 June 2016 (28.06.2016)

(25) Filing Language: English

(26) Publication Language: English

(71) Applicant: **CIRRUS LOGIC, INC.** [US/US]; 800 W. 6th Street, Austin, TX 78701 (US).

(72) Inventors; and


(71) Applicants: **MILLER, Antonio, John** [US/US]; 7337 Covered Bridge Drive, Austin, TX 78736 (US). **SU, Jie** [US/US]; 1513 Acacia Bud Dr, Austin, TX 78733 (US).(74) Agent: **SMITH, Darren** et al.; Norton Rose Fulbright US LLP, 98 San Jacinto Boulevard, Suite 1100, Austin, TX 78701-4255 (US).(81) Designated States (*unless otherwise indicated, for every kind of national protection available*): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC, SD, SE,

SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

(84) Designated States (*unless otherwise indicated, for every kind of regional protection available*): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, KM, ML, MR, NE, SN, TD, TG).

Published:

— with international search report (Art. 21(3))

(54) Title: **SPEAKER IMPEDANCE MONITORING**

(57) **Abstract:** A speaker impedance may be determined by monitoring a voltage and/or current of the speaker. The calculated impedance may be used to determine whether the mobile device containing the speaker is on- or off-ear. The impedance determination may be assisted by applying a test tone low level signal to the speaker. The test tone may be inaudible to the user, but used to determine an impedance of the speaker at the frequency of the test tone. The impedance at that test tone may be used to determine whether a resonance frequency of the speaker is at a frequency corresponding to an on- or off-ear condition. The measured speaker impedance may be provided as feedback to an adaptive noise cancellation (ANC) algorithm to adjust the output at the speaker. For example, when the mobile device is removed from the user's ear, the ANC algorithm may be disabled.



SPEAKER IMPEDANCE MONITORING

FIELD OF THE DISCLOSURE

[0001] The instant disclosure relates to mobile devices. More specifically, this disclosure relates to audio output of mobile devices.

BACKGROUND

[0002] Mobile devices are carried by a user throughout most or all of a day. During the day, the user may encounter many different environments, each with a different background noise characteristic and other acoustic effects. Mobile devices employ noise cancelling to take into account the environmental changes and improve the user's experience while using the mobile device. However, the performance of noise cancelling systems vary with how closely a speaker of the mobile device is placed against the user's ear, because the coupling between the user's ear and the speaker varies with distance.

SUMMARY

[0003] An impedance of a speaker of a mobile device varies due to objects interfering with the speaker's acoustic radiation field. For example, when a user places the mobile device closer to the user's ear, the speaker impedance increases. The impedance may be calculated from voltage and/or current measurements obtained from the speaker using a test tone signal and/or using the playback of audio through the speaker. From the calculated impedance, a proximity of the speaker to other devices may be determined. For example, a mobile device may be determined to be on- or off-ear from the calculated impedance.

[0004] The mobile device may be controlled based on the determined impedance of the speaker and/or the detection of on- or off-ear condition. In one embodiment, adaptive noise cancellation (ANC) may be adjusted based on the impedance of the speaker and/or

determination of an on- or off-ear condition. For example, when the phone is off-ear, the ANC may be disabled. In another example, the impedance of the speaker may be calculated by the mobile device to determine a pressure applied by the user between the mobile device and the user's ear. The impedance may be applied to an adaptive noise cancellation (ANC) circuit to adjust processing of an audio signal for playback through the speaker. The changes in impedance vary proportionally to the pressure applied by the user to place the mobile device against his ear and thus vary proportionally to a distance between the speaker and the user's ear canal. In one example, the impedance of a speaker may range from 5 ohms to 11 ohms depending on the pressure applied between the speaker and the user's ear.

[0005] According to one embodiment, a method may include calculating an impedance of a speaker of a mobile device. The method may also include determining a force applied by a user of the mobile device that causes contact between the mobile device and the user based, at least in part, on the calculated impedance. In certain embodiments, the impedance is an acoustic radiation impedance.

[0006] The method may also include applying a voltage to the speaker, and measuring a current through the speaker, in which the step of calculating the impedance comprises calculating the impedance based at least in part on the applied voltage and the measured current; adjusting an adaptive noise cancellation (ANC) algorithm based, at least in part, on the determined force; receiving an audio signal from an error microphone, in which the step of adjusting the ANC algorithm comprises adjusting the ANC algorithm based, at least in part, on the error microphone audio signal; and/or linearizing an output of the speaker based, at least in part, on the calculated impedance.

[0007] According to another embodiment, an apparatus may include a speaker. The apparatus may also include an amplifier coupled to the speaker. The apparatus may further include a processor coupled to the amplifier. The processor may be configured to execute the

steps comprising calculating an impedance of the speaker and determining an environmental load of the speaker based, at least in part, on the calculated impedance.

[0008] In certain embodiments, the apparatus may be a mobile device; the environmental load may be proportional to a force, applied by a user of the mobile device, that causes contact between the mobile device and the user; the amplifier may be configured to apply a voltage to the speaker and measure a current through the speaker, and the processor may be configured to calculate the impedance based, at least in part, on the applied voltage and the measured current; the processor may be a digital signal processor (DSP) and the digital signal processor may be configured to adjust an adaptive noise cancellation (ANC) algorithm based, at least in part, on the determined force; and/or the processor may be further configured to linearize an output of the speaker based, at least in part, on the calculated impedance.

[0009] The apparatus may also include an error microphone coupled to the digital signal processor, in which the digital signal processor is further configured to adjust the ANC algorithm based, at least in part, on an audio signal received from the error microphone

[0010] According to yet another embodiment, a computer program product includes a non-transitory computer readable medium comprising code to execute the steps comprising calculating an impedance of a speaker and determining an environmental load of the speaker based, at least in part, on the calculated impedance. In certain embodiments, the environmental load may be proportional to a force, applied by a user of the mobile device that causes contact between the mobile device and the user.

[0011] The medium may also include code to detect, based at least in part on the determined force, when the mobile device is removed from an ear of the user; code to adjust an adaptive noise cancellation (ANC) algorithm based, at least in part, on the determined force; and/or code to linearize an output of the speaker based, at least in part, on the calculated impedance.

[0012] According to one embodiment, a method may include receiving, at a processor, a voltage measurement and a current measurement from a speaker during output of audio by the speaker; calculating an impedance of the speaker based, at least in part, on the received voltage measurement and the received current measurement; and/or detecting, based at least in part on the calculated impedance, when the speaker is removed from an ear of the user.

[0013] In some embodiments, the method may also include outputting, by the processor, a test tone to the speaker at a first frequency before receiving the voltage measurement and the current measurement, wherein the step of calculating the impedance includes calculating the impedance of the speaker at the first frequency; the step of detecting when the speaker is removed from the ear of the user includes determining if the calculated impedance at the first frequency is above a threshold impedance; the step of calculating the impedance of the speaker may include applying a bandpass filter to the voltage measurement and the current measurement, wherein the bandpass filter is centered at the first frequency of the test tone; the step of calculating the impedance of the speaker may include applying a low pass filter to the result of bandpass filtering the voltage measurement and the current measurement; the step of calculating the impedance of the speaker may include dividing the result of the low pass filtering of the bandpass filtered voltage measurement by the result of the low pass filtering of the bandpass filtered current measurement; the step of detecting when the speaker is removed from the ear of the user comprises determining a change in an impedance curve of the speaker based, at least in part, on the received voltage measurement and the received current measurement; and/or the method may also include adjusting an adaptive noise cancellation (ANC) algorithm based, at least in part, on the calculated impedance, such as by disabling the adaptive noise cancellation (ANC) algorithm when the speaker is detected as removed from the ear of the user.

[0014] According to another embodiment, an apparatus may include a speaker, an amplifier coupled to the speaker, and a processor coupled to the amplifier, in which the processor is configured to perform steps including receiving, at a processor, a voltage measurement and a current measurement from a speaker during output of audio by the speaker; calculating an

impedance of the speaker based, at least in part, on the received voltage measurement and the received current measurement; and/or detecting, based at least in part on the calculated impedance, when the speaker is removed from an ear of the user. In some embodiments of this apparatus, the processor may be configured to perform other steps described in this patent application.

[0015] According to a further embodiment, a computer program product may include a non-transitory computer readable medium comprising code to perform steps including receiving, at a processor, a voltage measurement and a current measurement from a speaker during output of audio by the speaker; calculating an impedance of the speaker based, at least in part, on the received voltage measurement and the received current measurement; and/or detecting, based at least in part on the calculated impedance, when the speaker is removed from an ear of the user. In some embodiments of this computer program product, the medium may include code to perform other steps described in this patent application.

[0016] The foregoing has outlined rather broadly certain features and technical advantages of embodiments of the present invention in order that the detailed description that follows may be better understood. Additional features and advantages will be described hereinafter that form the subject of the claims of the invention. It should be appreciated by those having ordinary skill in the art that the conception and specific embodiment disclosed may be readily utilized as a basis for modifying or designing other structures for carrying out the same or similar purposes. It should also be realized by those having ordinary skill in the art that such equivalent constructions do not depart from the spirit and scope of the invention as set forth in the appended claims. Additional features will be better understood from the following description when considered in connection with the accompanying figures. It is to be expressly understood, however, that each of the figures is provided for the purpose of illustration and description only and is not intended to limit the present invention.

BRIEF DESCRIPTION OF THE DRAWINGS

[0017] For a more complete understanding of the disclosed system and methods, reference is now made to the following descriptions taken in conjunction with the accompanying drawings.

[0018] FIGURE 1 is a cross-section illustrating a mobile device with speaker impedance monitoring according to one embodiment of the disclosure.

[0019] FIGURE 2 is a block diagram illustrating speaker impedance monitoring according to one embodiment of the disclosure.

[0020] FIGURE 3 is a graph illustrating speaker impedance over time based on various user placements of the mobile device according to one embodiment of the disclosure.

[0021] FIGURE 4 is a block diagram illustrating a noise canceling system according to one embodiment of the disclosure.

[0022] FIGURE 5 is a flow chart illustrating a method for adaptive noise cancellation (ANC) in a mobile device according to one embodiment of the disclosure.

[0023] FIGURE 6 is a block diagram of an adaptive noise cancellation (ANC) circuit according to one embodiment of the disclosure.

[0024] FIGURE 7 is a graph of a response against pressure applied between the mobile device and the user's ear according to one embodiment of the disclosure.

[0025] FIGURE 8 is a graph of a response as a function of frequency for different levels of ear pressure according to one embodiment of the disclosure.

[0026] FIGURE 9 is a flow chart illustrating a method for adapting adaptive noise cancellation algorithms based on ear pressure according to one embodiment of the disclosure.

[0027] FIGURE 10 is a flow chart illustrating an example method for detecting on- or off-ear condition based on a measured voltage and/or current value of the speaker according to one embodiment of the disclosure.

[0028] FIGURE 11 is a graph illustrating an example impedance curve for a speaker in on- and off-ear conditions according to one embodiment of the disclosure.

DETAILED DESCRIPTION

[0029] FIGURE 1 is a cross-section illustrating a mobile device with speaker impedance monitoring according to one embodiment of the disclosure. A mobile device 102 may be placed near a user's ear 160. The mobile device 102 may be, for example, a mobile phone, a tablet computer, a laptop computer, or a wireless earpiece. The mobile device 102 may include a speaker 104, such as a transducer, driven by an amplifier 122 of a circuit 120. The speaker 104 may generate an acoustic sound field 150 near the mobile device 102. The user's ear 160 translates the acoustic sound field 150 into recognizable sounds for the user. For example, the acoustic sound field 150 may include speech conversations occurring during a phone call, playback of a voice mail message, playback of ring tones, and/or playback of audio or video files. The amplifier 122 may receive audio signals from a processor 124 of the circuit 120, such as a digital signal processor (DSP).

[0030] The mobile device 102 may also include a near-speech microphone 136, an error microphone 134, and a reference microphone 132. Each of the microphones 132, 134, and 136 receive audible sounds fields and translate the acoustic sound fields into electrical signals for processing by the circuit 120. For example, the near-speech microphone 136 may receive speech during a conversation occurring during a phone call. In another example, the error microphone 134 may receive the acoustic sound field 150 generated by the speaker 104. In a further example, the reference microphone 132 may be positioned away from a typical position of a user's mouth and may measure an ambient acoustic environment.

[0031] One apparatus for measuring a speaker impedance includes a resistor for measuring current. FIGURE 2 is a block diagram illustrating speaker impedance monitoring according to one embodiment of the disclosure. The speaker 104 may be coupled to a voltage source 202 of the amplifier 122. The speaker 104 may have an impedance 206 proportional to loading of the acoustic sound field 150. A resistor 204 may be coupled in series with the speaker 104, such that a current passing through the resistor 204 is proportional to a current passing through the speaker 104. A voltmeter 208 may be coupled in parallel with the resistor 204 to measure a voltage across the resistor 204. The current passing through the resistor 204, and thus the speaker 104, may be calculated by multiplying the resistance value of the resistor 204 with the measured voltage at the voltmeter 208. The current may be calculated by a processor, such as the processor 124. The impedance 206 of the speaker 104 may be calculated, by the processor 124, from the voltage value at the voltage source 202, the resistance value of the resistor 204, and the voltage across the resistor 204 measured by the voltmeter 208.

[0032] The voltage at the speaker 104, V_T , may be calculated by dividing the voltage of the voltage source 202, V_S , across the resistor 204 and the speaker 104 according to a voltage ladder. For example, the impedance 206, Z_L , may be calculated from the current, I , through the resistor 204, and the value of the resistor 204, R .

[0033] Speaker impedance, Z_L , varies with the pressure applied by the user to place the mobile device against the user's ear. FIGURE 3 is a graph illustrating speaker impedance over time based on various user placements of the mobile device according to one embodiment of the disclosure. A graph 300 plots current on a y-axis 306 against time on an x-axis 304. The x-axis 304 is divided into time periods 312, 314, 316, and 318 illustrating different events determined by the speaker impedance. A current line 302 illustrates a baseline pressure applied during the time period 312. During the time period 314, the current line 302, and thus speaker impedance, increases proportional to increasing pressure applied by the user to place the mobile device against the user's ear. During time period 316, the user removes the mobile device from his/her ear resulting in a decrease in the current line 302, and thus speaker

impedance. During a time period 318, the user places the mobile device on the user's cheek resulting in an increase in current, and thus speaker impedance.

[0034] A speaker impedance may be provided to an adaptive noise cancellation (ANC) system for adapting the noise control system. FIGURE 4 is a block diagram illustrating a noise canceling system according to one embodiment of the disclosure. A circuit 420 may receive input from the microphones 132, 134, and 136. Analog values from the microphones 132, 134, and 136 may be converted by analog-to-digital converters (ADCs) 421A, 421B, and 421C. The ADCs 421A, 421B, and 421C may be part of the noise control system or may be built into the microphones 132, 134, and 136, respectively. In one embodiment, the microphones 132, 134, and 136 are digital microphones, and no ADCs are placed between the digital microphones and the circuit 420.

[0035] The circuit 420 may also receive input from the speaker 104, such as an impedance value of the speaker 104. The impedance value may be calculated by the amplifier 122 and output to an analog-to-digital converter 421D, which converts the impedance value to a digital value for ANC circuit 430. In one embodiment, the speaker impedance output by the amplifier 122 is a digital value, and no analog-to-digital converter is present.

[0036] The ANC circuit 430 may generate an anti-noise signal, which is provided to a combiner 426. The anti-noise signal may be adjusted according to a force, or distance, between the user's ear and the speaker 104. For example, the anti-noise signal may be disabled when the user removes the phone from the user's ear. The removal of the phone from the user's ear may be detected when the speaker impedance falls below a threshold value.

[0037] The combiner 426 combines the anti-noise signal from the ANC circuit 430 with sound from the near speech microphone 136, internal audio 426, and audio signals received wirelessly through an antenna 428 and processed by a radio frequency (RF) circuit 422. The internal audio 426 may be, for example, ringtones, audio files, and/or audio portions of

video files. Audio signals received through the antenna 428 may be, for example, streamed analog or digital audio signals and/or telephone conversations. The combiner 426 provides a single signal to a digital-to-analog converter (DAC) 423. The DAC 423 converts the digital signal of the combiner 423 to an analog audio signal for amplification by the amplifier 122 and output at the speaker 104.

[0038] FIGURE 5 is a flow chart illustrating a method for adaptive noise cancellation in a mobile device according to one embodiment of the disclosure. A method 500 begins at block 502 with calculating an impedance of a speaker. The speaker impedance may be calculated by monitoring a current through the speaker and calculating an impedance of the speaker based on a known voltage value driving the speaker. The current monitoring may be performed in real-time during playback of an audio signal, such as during a voice conversation or during playback of audio files.

[0039] At block 504, a force applied by the user between the mobile device and the user's ear may be determined from the calculated impedance. The impedance of the speaker is proportional to a loading of the speaker. Higher force applied by the user between the mobile device and the user's ear increases the load on the speaker, which appears as an increase in impedance of the speaker. The force applied by the user may be proportional to the distance between the speaker and the user's ear canal.

[0040] At block 506, an adaptive noise cancellation algorithm is adjusted based, at least in part, on the determined force at block 504. For example, a control oversight algorithm may determine from the determined force that the user has removed the mobile device from the user's ear. When the off-ear condition is detected, the adaptive noise cancellation algorithm may be disabled. In another example, feedback regarding the speaker impedance may be provided to an adaptive noise cancellation algorithm to adjust the output of a speaker to compensate for the user's ear position. For example, output to the speaker may be adjusted to obtain linearization of the speaker audio output at high sound pressure levels (SPLs).

[0041] Additional details regarding the adaptive noise cancellation circuit are illustrated in FIGURE 6. FIGURE 6 is a block diagram of an adaptive noise cancellation circuit according to one embodiment of the disclosure. An adaptive filter 630 may be formed from a fixed filter 632A, having a response $W_{\text{FIXED}}(z)$, and an adaptive portion 632B, having a response $W_{\text{ADAPT}}(z)$ with outputs summed by a combiner 636B. The adaptive filter 630 may receive the reference microphone signal *ref* and may adapt a transfer function $W(z) = W_{\text{FIXED}}(z) + W_{\text{ADAPT}}(z)$ to generate an anti-noise signal, which is provided to the combiner 426 that combines the anti-noise signal with the audio to be reproduced by the speaker. The response $W(z)$ adapts to estimate a ratio $P(z)/S(z)$, where $S(z)$ is the response for an electro-acoustic path and $P(z)$ is the response for an acoustic path. A controllable amplifier circuit 611 mutes or attenuates the anti-noise signal under certain non-ideal conditions, such as when the anti-noise signal is expected to be ineffective or erroneous due to lack of a seal between the user's ear and mobile device.

[0042] The coefficients of adaptive filter 632B may be controlled by a W coefficient control block 631, which may use a correlation of two signals to determine the response of the adaptive filter 632B to reduce the energy of the error, such as calculated by a least-mean square function, between the components of the reference microphone signal *ref* that are present in the error microphone signal *err*. The signals compared by the W coefficient control block 631 may be the reference microphone signal *ref* as shaped by a copy of an estimate $SE_{\text{COPY}}(z)$ of the response of path $S(z)$ provided by filter 634B and an error signal $e(n)$ formed by subtracting a modified portion of a downlink audio signal *ds* from the error microphone signal *err*. By transforming the reference microphone signal *ref* with a copy of the estimate of the response of path $S(z)$, $SE_{\text{COPY}}(z)$, and adapting the adaptive filter 632B to reduce the correlation between the resultant signal and the error microphone signal *err*, the adaptive filter 632B adapts to the desired response of $P(z)/S(z) - W_{\text{FIXED}}(z)$. Thus, response $W(z)$ adapts to $P(z)/S(z)$, resulting in a noise-cancelling error, which may be for example white noise.

[0043] The signal compared to the output of the filter 634B by the W coefficient control block 631 adds to the error microphone signal *err* an inverted amount of the downlink audio signal *ds* that is processed by the filter response 634A, $SE(z)$, of which response $SE_{COPY}(z)$ is a copy. By injecting an inverted amount of the downlink audio signal *ds*, the adaptive filter 632B may be prevented from adapting to the relatively large amount of downlink audio present in the error microphone signal *err* and by transforming that inverted copy of the downlink audio signal *ds* with the estimate of the response of path $S(z)$. The downlink audio that is removed from the error microphone signal *err* before comparison may match the expected version of the downlink audio signal *ds* reproduced at the error microphone signal *err*, because the electrical and acoustical path of $S(z)$ may be the path taken by the downlink audio signal *ds* to arrive at an error microphone. The filter 634B may have an adjustable response tuned to match the response of the adaptive filter 634A, such that the response of the filter 634B tracks the adapting of the adaptive filter 634A.

[0044] The adaptive filter 634A may include coefficients controlled by SE coefficient control block 633, which compares the downlink audio signal *ds* and the error microphone signal *err* after removal of the above-described filtered downlink audio signal *ds* that has been filtered by the adaptive filter 634A to represent the expected downlink audio delivered to an error microphone, and which has been removed from the output of the adaptive filter 634A by a combiner 636A. The SE coefficient control block 633 correlates the downlink speech signal *ds* with the components of downlink audio signal *ds* that are present in the error microphone signal *err*. The adaptive filter 634A is adapted to generate a signal from the downlink audio signal *ds*, and optionally the anti-noise signal combined by the combiner 636B during muting conditions, that when subtracted from the error microphone signal *err*, contains the content of error microphone signal *err* that is not due to the downlink audio signal *ds*. The overall energy of the error signal normalized to the overall energy of the response $SE(z)$ is related to the pressure between the user's ear and mobile device, which may be determined by calculating the speaker impedance described above with reference to FIGURE 5.

[0045] In one embodiment, an ear pressure indicator 637 may determine the ratio between $|Ele(N)|$, which is the energy of the error signal generated by the combiner 636A and an overall magnitude of the response of $SE(z)$: $\sum |SE_n(z)|$. Ear pressure indication $|Ele(n)| / \sum |SE_n(z)|$ may be only one example function of $e(n)$ and $SE_n(z)$ that may be used to yield a measure of ear pressure. For example, $\sum |SE_n(z)|$ or $\sum SE_n(z)^2$, which are a function of only $SE(z)$ may be alternatively used, because the response $SE(z)$ changes with ear pressure.

[0046] In another embodiment, the ear pressure indicator 637 may receive the speaker impedance measurement and calculate an ear pressure based, at least in part, on the speaker impedance. As described above with reference to FIGURE 3, the speaker impedance may be used to determine a force applied by the user between the mobile device and the user's ear. That force may be entered into an algorithm to determine ear pressure. The ear pressure indicator 637 may implement calculation of ear pressure based on the speaker impedance, the error signal, and/or $SE(z)$.

[0047] The ear pressure indicator 637 may output a value, either digital or analog, proportional to the force applied by the user between the mobile device and the user's ear. A comparator 642 compares the output of the ear pressure indicator 637 with a first, low pressure, threshold $V_{th,L}$. If the output is below the threshold, indicating that ear pressure is below the normal operating range, such as when the mobile device is off the user's ear, then the ear pressure response logic 638 may be signaled to take action to prevent generation of undesirable anti-noise at the user's ear. Similarly, a comparator 644 compares the output of the ear pressure indicator 637 with a second, high pressure, threshold $V_{th,H}$, and if $|Ele(n)| / \sum |SE_n(z)|$ is above the threshold, indicating that ear pressure is above the normal operating range, such as when the mobile device is pressed hard onto the user's ear, then the ear pressure response logic 638 may be signaled to take action to prevent generation of undesirable anti-noise at the user's ear.

[0048] FIGURE 7 is a graph of a response against force between the mobile device and the user's ear according to one embodiment of the disclosure. As pressure increases

between a mobile device and the user's ear, the response $SE(z)$ increases in magnitude, which indicates an improved electro-acoustic path $S(z)$, which is a measure of a degree of coupling between the speaker and the error microphone. A higher degree of coupling between the user's ear and the speaker is indicated when response $SE(z)$ increases in magnitude, and conversely, a lower degree of coupling between the user's ear and the speaker is indicated when response $SE(z)$ decreases in magnitude. Because the adaptive filter 632B of FIGURE 6 adapts to the desired response of $P(z)/S(z)$, as ear pressure is increased and response $SE(z)$ increases in energy, less anti-noise is generated. Conversely, as the pressure between the ear and mobile device decreases, the anti-noise signal may increase in energy, because the user's ear is no longer highly coupled to the speaker and/or the error microphone.

[0049] FIGURE 8 is a graph of response $SE(z)$ as a function of frequency for different levels of ear pressure according to one embodiment of the disclosure. As illustrated in FIGURE 7, as the pressure is increased between the mobile device and the user's ear, the response $SE(z)$ increases in magnitude in the middle frequency ranges of the graph, which correspond to frequencies at which most of the energy for speech is located. The graphs shown in FIGURES 7 and 8 may be determined for individual mobile device designs using either a computer model, or a mock-up of a simulated user's head that allows adjustment of contact pressure between the user's ear and mobile device, which may also have a measurement microphone in simulated ear canal.

[0050] In general, ANC operates properly when the user's ear is coupled to the speaker. Because the speaker may be able to only generate a certain output level, such as 80 dB sound pressure level (SPL) in a closed cavity, once the mobile device is no longer in contact with the user's ear, the anti-noise signal may be ineffective and muted. At high coupling between the user's ear and the mobile device, such as when a large force is applied between the mobile device and the user's ear, the higher-frequency energy, such as between 2 kHz and 5 kHz, may be attenuated, which may cause noise boost due to response $W(z)$ not adapting to the attenuated condition of the higher frequencies. When the ear pressure is increased, the anti-noise signal

may not be adapted to cancel energies at the higher frequencies. The response $W_{\text{ADAPT}}(z)$ may then be reset to a predetermined value, and adaptation of response $W_{\text{ADAPT}}(z)$ may be frozen, such as by holding the coefficients of response $W_{\text{ADAPT}}(z)$ at constant predetermined values. Alternatively, the overall level of the anti-noise signal may be attenuated, or a leakage of response $W_{\text{ADAPT}}(z)$ of the adaptive filter 632B may be increased. Leakage of response $W_{\text{ADAPT}}(z)$ of the adaptive filter 632B may be provided by having the coefficients of response $W_{\text{ADAPT}}(z)$ return to a flat frequency response or a fixed frequency response.

[0051] Referring back to FIGURE 6, when the comparator 642 indicates that the degree of coupling between the user's ear and mobile device has been reduced below a first, low pressure, threshold, the ear pressure response logic 638 may stop adaptation of the W coefficient control 631, and the amplifier 611 may be disabled to mute the anti-noise signal. When the comparator 644 indicates that the coupling between the user's ear and the mobile device has increased above a second, high pressure, threshold, the ear pressure logic 638 may increase leakage of the W coefficient control 631 or reset response $W_{\text{ADAPT}}(z)$ and freeze adaptation of response $W_{\text{ADAPT}}(z)$.

[0052] Alternatively, the ear pressure indicator 637 may be a multi-valued or continuous indication of different ear pressure levels, and the actions above may be replaced by applying an attenuation factor to the anti-noise signal in conformity with the level of ear pressure, so that when the ear pressure passes out of the normal operating range, between the first threshold and the second threshold, the anti-noise signal level is also attenuated by lowering the gain of the amplifier 611.

[0053] In one embodiment, the response $W_{\text{FIXED}}(z)$ of the fixed filter 632A may be trained for high ear pressure. Then, the adaptive response of the adaptive filter 632B, response $W_{\text{ADAPT}}(z)$, may be allowed to vary with ear pressure changes, up to the point that contact with the ear is minimal, at which point the adapting of response $W(z)$ may be halted and the anti-noise signal may be muted, or the pressure on the ear is over a high threshold, at which

time response $W_{\text{ADAPT}}(z)$ may be reset and adaptation of response $W_{\text{ADAPT}}(z)$ may be frozen, or the leakage may be increased. Additional details regarding ANC operation are disclosed in U.S. Patent Application No. 13/310,380 entitled “Ear-Coupling Detection and Adjustment of Adaptive Response in Noise-Canceling in Personal Audio Devices,” which is hereby incorporated by reference.

[0054] FIGURE 9 is a flow chart illustrating a method for adapting adaptive noise cancellation algorithms based on ear pressure according to one embodiment of the disclosure. A method 900 begins at block 970 with computing an ear pressure indication from at least one of the error microphone signal, the $SE(z)$ coefficients, and/or the speaker impedance. At block 972, it is determined if the ear pressure is lower than a first threshold. If so, an off-ear event is detected, and the method 900 continues to block 974 to stop adapting response $W(z)$ and/or mute the anti-noise signal. If not, the method 900 continues to block 976.

[0055] At block 976, it is determined whether the ear pressure is above a second threshold, higher than the first threshold. If so a hard-pressure event is detected, and the method 900 continues to block 978 to increase leakage of the response $W(z)$ and/or reset and freeze the adaptive portion of response $W(z)$. If not, then normal operation is continued at block 980, during which response $W(z)$ adapts to the ambient audio environment and the anti-noise signal is output to the speaker.

[0056] At block 982, it is determined whether the ANC is terminated or the mobile device is shut down. If not, then the method 900 repeats, such as by returning to block 970 and repeating blocks 972 and/or 976. If the determination is yes at block 982, then the method 900 terminates.

[0057] As described above, a speaker impedance may be monitored to determine information regarding objects in proximity to a speaker, such as information regarding a mobile device containing the speaker. With regard to FIGURE 1 and FIGURE 2, the speaker 104 is

described as having an impedance 206 proportional to loading of the acoustic sound field 150. The loading of the acoustic sound field 150 may increase or decrease relative to objects in proximity to the speaker 104 that alter the acoustic sound field 150, such as by increasing the impedance 206. For example, when a user places a mobile device containing the speaker 104 near the user's ear, the impedance 206 may increase, and the impedance 206 may decrease as the mobile device is removed from the user's ear. This change in impedance is illustrated with reference to FIGURE 3. During the time period 314, the current line 302, and thus speaker impedance, increases proportional to increasing pressure applied by the user to place the mobile device against the user's ear. During time period 316, the user removes the mobile device from his/her ear resulting in a decrease in the current line 302, and thus speaker impedance.

[0058] An impedance of a speaker in a mobile device may be monitored, such as by using the apparatus of FIGURE 2, to determine when a mobile phone is on-ear or off-ear. Such a determination may be useful in that the speaker, a necessary component of a mobile device, particularly a mobile phone, may be used for proximity detection. The speaker may thus be used in combination with, or as a replacement for, a conventional optical proximity detector of a mobile device. Removing the optical proximity detector may reduce costs of manufacturing the mobile device and allow for smaller, thinner construction of the mobile device. One method of detecting mobile device proximity is described with reference to FIGURE 10.

[0059] FIGURE 10 is a flow chart illustrating an example method for detecting on-ear and off-ear conditions of a mobile device according to one embodiment of the disclosure. A method 1000 may begin at block 1002 with receiving, at a processor, a voltage measurement and/or a current measurement for a speaker. In some embodiments, the measurements may be performed during output of audio by the speaker. In some embodiments, the measurements may be performed while outputting an inaudible test tone signal to the speaker, which may be output to the speaker during the output of audio. Then, at block 1004, the method 1000 may continue with calculating an impedance of the speaker based, at least in part, on the received voltage measurement and the received current measurement. Next, at block 1006, the method 1000 may

continue with detecting, based at least in part on the calculated impedance of block 1004, when the speaker is removed from an ear of the user.

[0060] One example impedance curve for a speaker, such as a speaker in a mobile device, is shown in FIGURE 11. A line 1102 shows impedance as a function of frequency for a speaker that is not in proximity to another object, such as when the mobile device is off-ear. A line 1104 shows an impedance as a function of frequency for a speaker that is in proximity to another object, such as when the mobile device is on-ear. The impedance of the speaker at frequency $f_0(\text{ONear})$ 1114 when the speaker is on ear may be impedance level 1124; the impedance of the speaker at frequency $f_0(\text{ONear})$ 1114 when the speaker is off-ear may be impedance level 1122. The frequencies 1112 and 1114 correspond to resonance frequencies for the speaker at off-ear and on-ear conditions. The impedance at a test tone frequency may be used to determine whether a resonance frequency of the speaker is at a frequency corresponding to an on- or off-ear condition. Thus, the proximity of the mobile device to another object, such as the user's ear, may be detected by measuring a voltage and/or a current of the speaker and calculating an impedance at one or more frequencies. In one embodiment, the calculated impedance from the voltage and/or current measurements may be used to determine a resonance frequency of the speaker, and a change in the resonance frequency detected to determine an on- or off-ear condition.

[0061] To assist in determining the on- or off-ear condition, a small level test tone signal may be injected at frequency $f_0(\text{ONear})$ 1114. The test tone signal may be inaudible, such as being at an amplitude and/or frequency generally undetectable to the human ear. A difference in impedance at frequency $f_0(\text{ONear})$ 1114 may be measured and used to determine the on/off ear condition. For example, as described with reference to block 1002 of FIGURE 10, a small level test tone signal may be output to the speaker at frequency $f_0(\text{ONear})$ 1114. The small level signal may be, for example, a test tone injected into the speaker at a level between approximately -30 decibels full scale (dBFS) and -40 decibels full scale (dBFS). The current and/or voltage

measurements at block 1002 of FIGURE 10 may be performed while outputting this test signal simultaneously with or separate from audio playback through the speaker.

[0062] The current and/or voltage measurements may be used to calculate an impedance at block 1004 of FIGURE 10. The impedance may be calculated from Ohm's law as:

$$Impedance = \frac{V_{meas}}{I_{meas}},$$

where V_{meas} and I_{meas} are a measured voltage and a measured current, respectively, of the speaker. In some embodiments, the impedance may be calculated using filters. For example, the voltage and current values may be applied to a bandpass filter and/or a lowpass filter as part of the impedance calculation. According to one embodiment, the impedance may be calculated using filters as:

$$Impedance = \frac{|LPF(BPF(V_{mon}))|}{|LPF(BPF(I_{mon}))|},$$

where V_{mon} is a monitored voltage of a speaker, I_{mon} is a monitored current of a speaker, BPF represents a bandpass filter (BPF) centered at the frequency of the test tone signal, such as frequency $f_0(\text{ONear})$ 1114, and where LPF represents a lowpass filter (LPF) to average the monitored voltage V_{mon} and current I_{mon} . Although impedance calculations at the frequency $f_0(\text{ONear})$ 1114 are described above, other frequencies may be used for calculating impedance in a similar manner, such as the frequency $f_0(\text{OFFear})$ 1112. The frequencies 1112 and 1114 are thus both examples of a first frequency that may be applied to a speaker as part of a test tone for determining an impedance of the speaker.

[0063] The calculated impedance, which may be calculated according to one of the equations above or another equation, may be used to determine when the mobile device is on- or off-ear. For example, block 1006 of FIGURE 10 may include detecting the on- or off-ear condition by determining whether the calculated impedance of block 1004 is closer to level 1124

or closer to level 1122. An impedance that is closer to level 1122 than level 1124 may indicate an off-ear condition, whereas an impedance that is closer to level 1124 than level 1122 may indicate an on-ear condition. Determining whether the impedance is closer to level 1122 or level 1124 may be performed by comparing the impedance with a threshold impedance level. The threshold impedance level may be selected, for example, as a level halfway between the impedance level 1124 and the impedance level 1122. The calculated impedance of block 1004 may be compared with the threshold level to determine whether the calculated impedance exceeds the threshold level. If the threshold level is exceeded by the calculated impedance, then the mobile device may be determined to be on-ear, whereas if the threshold level is not exceeded by the calculated impedance, then the mobile device may be determined to be off-ear. In some embodiments, the threshold level may be at a different level than the midway point between the levels 1122 and 1124.

[0064] Detection of the on- or off-ear condition may trigger an event to occur on the mobile device. For example, adaptive noise cancellation (ANC) may be turned on and off with the on- and off-ear conditions. As another example, a display screen of the mobile device may be turned off when the on-ear condition is detected. In some embodiments, the action taken when the on- and off-ear condition is determined may depend in part on other conditions. For example, when the on-ear condition is detected, the display screen may be turned off only if an active telephone call is in progress.

[0065] If implemented in firmware and/or software, the functions described above may be stored as one or more instructions or code on a computer-readable medium. Examples include non-transitory computer-readable media encoded with a data structure and computer-readable media encoded with a computer program. Computer-readable media includes physical computer storage media. A storage medium may be any available medium that can be accessed by a computer. By way of example, and not limitation, such computer-readable media can comprise RAM, ROM, EEPROM, CD-ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other medium that can be used to store desired program

code in the form of instructions or data structures and that can be accessed by a computer. Disk and disc includes compact discs (CD), laser discs, optical discs, digital versatile discs (DVD), floppy disks and blu-ray discs. Generally, disks reproduce data magnetically, and discs reproduce data optically. Combinations of the above should also be included within the scope of computer-readable media.

[0066] In addition to storage on computer readable medium, instructions and/or data may be provided as signals on transmission media included in a communication apparatus. For example, a communication apparatus may include a transceiver having signals indicative of instructions and data. The instructions and data are configured to cause one or more processors to implement the functions outlined in the claims.

[0067] Although the present disclosure and certain representative advantages have been described in detail, it should be understood that various changes, substitutions and alterations can be made herein without departing from the spirit and scope of the disclosure as defined by the appended claims. Moreover, the scope of the present application is not intended to be limited to the particular embodiments of the process, machine, manufacture, composition of matter, means, methods and steps described in the specification. As one of ordinary skill in the art will readily appreciate from the present disclosure, processes, machines, manufacture, compositions of matter, means, methods, or steps, presently existing or later to be developed that perform substantially the same function or achieve substantially the same result as the corresponding embodiments described herein may be utilized. Accordingly, the appended claims are intended to include within their scope such processes, machines, manufacture, compositions of matter, means, methods, or steps.

CLAIMS

What is claimed is:

1. A method, comprising:
 - outputting, by the processor, a test tone to the speaker at a first frequency;
 - receiving, by the processor, at least one of a voltage measurement and a current measurement for a speaker after outputting the test tone;
 - calculating, by the processor, an impedance of the speaker based, at least in part, on the received at least one of a voltage measurement and a current measurement; and
 - detecting, by the processor based at least in part on the calculated impedance, when the speaker is removed from an ear of the user.
2. The method of claim 1, wherein the step of calculating the impedance comprises calculating the impedance of the speaker at the first frequency.
3. The method of claim 2, wherein the step of detecting when the speaker is removed from the ear of the user comprises determining if the calculated impedance at the first frequency is above a threshold impedance level.

4. The method of claim 1, wherein the received at least one of a voltage measurement and a current measurement comprises both a voltage measurement and a current measurement, and wherein the step of calculating the impedance of the speaker comprises:
 - applying a bandpass filter to the voltage measurement and the current measurement, wherein the bandpass filter is centered at the first frequency of the test tone;
 - applying a low pass filter to the result of bandpass filtering the voltage measurement and the current measurement; and
 - dividing the result of the low pass filtering of the bandpass filtered voltage measurement by the result of the low pass filtering of the bandpass filtered current measurement.
5. The method of claim 1, wherein the step of detecting when the speaker is removed from the ear of the user comprises determining a change in an impedance curve of the speaker based, at least in part, on the received at least one of a voltage measurement and a current measurement.
6. The method of claim 1, further comprising adjusting an adaptive noise cancellation (ANC) algorithm based, at least in part, on the calculated impedance.
7. The method of claim 6, wherein the step of adjusting the adaptive noise cancellation (ANC) algorithm comprises disabling the adaptive noise cancellation (ANC) algorithm when the speaker is detected as removed from the ear of the user.

8. An apparatus, comprising:
 - a speaker;
 - an amplifier coupled to the speaker;
 - a processor coupled to the amplifier, in which the processor is configured to execute steps comprising:
 - outputting a test tone to the speaker at a first frequency;
 - receiving at least one of a voltage measurement and a current measurement for the speaker during output of audio by the speaker;
 - calculating an impedance of the speaker based, at least in part, on the received at least one of a voltage measurement and a current measurement; and
 - detecting, based at least in part on the calculated impedance, when the speaker is removed from an ear of the user.
9. The apparatus of claim 8, wherein the step of calculating the impedance comprises calculating the impedance of the speaker at the first frequency.
10. The apparatus of claim 9, wherein the step of detecting when the speaker is removed from the ear of the user comprises determining if the calculated impedance at the first frequency is above a threshold impedance level.

11. The apparatus of claim 8, wherein the received at least one of a voltage measurement and a current measurement comprises both a voltage measurement and a current measurement, and wherein the step of calculating the impedance of the speaker comprises:
 - applying a bandpass filter to the voltage measurement and the current measurement, wherein the bandpass filter is centered at the first frequency of the test tone;
 - applying a low pass filter to the result of bandpass filtering the voltage measurement and the current measurement; and
 - dividing the result of the low pass filtering of the bandpass filtered voltage measurement by the result of the low pass filtering of the bandpass filtered current measurement.
12. The apparatus of claim 8, wherein the step of detecting when the speaker is removed from the ear of the user comprises determining a change in an impedance curve of the speaker based, at least in part, on the received at least one of a voltage measurement and a current measurement.
13. The apparatus of claim 8, wherein the processor is further configured to perform the step of adjusting an adaptive noise cancellation (ANC) algorithm based, at least in part, on the calculated impedance.
14. The apparatus of claim 13, wherein the step of adjusting the adaptive noise cancellation (ANC) algorithm comprises disabling the adaptive noise cancellation (ANC) algorithm when the speaker is detected as removed from the ear of the user.
15. The apparatus of claim 8, in which the apparatus is a mobile device.

16. A computer program product, comprising:
 - a non-transitory computer readable medium comprising code to execute the steps comprising:
 - outputting a test tone to the speaker at a first frequency;
 - receiving at least one of a voltage measurement and a current measurement from a speaker during output of audio by the speaker;
 - calculating an impedance of the speaker based, at least in part, on the received at least one of a voltage measurement and a current measurement; and
 - detecting, based at least in part on the calculated impedance, when the speaker is removed from an ear of the user.
17. The computer program product of claim 16, wherein the step of calculating the impedance comprises calculating the impedance of the speaker at the first frequency.
18. The computer program product of claim 17, wherein the step of detecting when the speaker is removed from the ear of the user comprises determining if the calculated impedance at the first frequency is above a threshold impedance level.

19. The computer program product of claim 16, wherein the step of calculating the impedance of the speaker comprises:
- applying a bandpass filter to the received at least one of a voltage measurement and a current measurement, wherein the bandpass filter is centered at the first frequency of the test tone;
 - applying a low pass filter to the result of bandpass filtering the voltage measurement and the current measurement; and
 - dividing the result of the low pass filtering of the bandpass filtered voltage measurement by the result of the low pass filtering of the bandpass filtered current measurement.
20. The computer program product of claim 16, wherein the step of detecting when the speaker is removed from the ear of the user comprises determining a change in an impedance curve of the speaker based, at least in part, on the received at least one of a voltage measurement and a current measurement.

1/8




FIG. 1




FIG. 2

2/8




FIG. 3




FIG. 4

3/8




FIG. 5

4/8




FIG. 6




FIG. 7

6/8




FIG. 8

7/8




FIG. 9

8/8




FIG. 10




FIG. 11

INTERNATIONAL SEARCH REPORT

International application No
PCT/US2016/039888

A. CLASSIFICATION OF SUBJECT MATTER
INV. H04R3/00
ADD.

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
H04R G01R G10K

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

EPO-Internal, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 2014/270208 A1 (MILLER ANTONIO JOHN [US] ET AL) 18 September 2014 (2014-09-18) figures 1-3 paragraphs [0003] - [0010] paragraph [0024] paragraph [0029] paragraph [0026]	1-20
A	----- EP 2 890 160 A1 (NXP BV [NL]) 1 July 2015 (2015-07-01) figure 3 paragraph [0011] paragraph [0013] paragraph [0040] paragraph [0041] ----- -/-	2,4,9, 11,17,19



Further documents are listed in the continuation of Box C.



See patent family annex.

* Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier application or patent but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

14 February 2017

Date of mailing of the international search report

08/03/2017

Name and mailing address of the ISA/

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040,
Fax: (+31-70) 340-3016

Authorized officer

Mendoza Lopez, Jorge

INTERNATIONAL SEARCH REPORT

International application No

PCT/US2016/039888

C(Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	EP 2 712 209 A1 (DIALOG SEMICONDUCTOR GMBH [DE]) 26 March 2014 (2014-03-26) paragraph [0020] - paragraph [0023] -----	4,11,19
A	WO 2008/000304 A1 (SONY ERICSSON MOBILE COMM AB [SE]; HANSSON MAGNUS [SE]) 3 January 2008 (2008-01-03) page 1, line 4 - line 7 -----	1-20

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/US2016/039888

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
US 2014270208	A1	18-09-2014	NONE	

EP 2890160	A1	01-07-2015	CN 104735600 A	24-06-2015
			EP 2890160 A1	01-07-2015
			US 2015181318 A1	25-06-2015

EP 2712209	A1	26-03-2014	EP 2712209 A1	26-03-2014
			US 2014086418 A1	27-03-2014

WO 2008000304	A1	03-01-2008	US 2007297634 A1	27-12-2007
			WO 2008000304 A1	03-01-2008
