




## INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification <sup>6</sup> :  H03M 13/00		A1	(11) International Publication Number: <b>WO 98/44638</b>
			(43) International Publication Date: 8 October 1998 (08.10.98)
(21) International Application Number: PCT/US98/05844			(81) Designated States: AL, AM, AT, AT (Utility model), AU, AZ, BA, BB, BG, BR, BY, CA, CH, CN, CU, CZ, CZ (Utility model), DE, DE (Utility model), DK, DK (Utility model), EE, EE (Utility model), ES, FI, FI (Utility model), GB, GE, HU, ID, IL, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SK (Utility model), TJ, TM, TR, TT, UA, UG, UZ, VN, YU, ZW, ARIPO patent (GH, GM, KE, LS, MW, SD, SZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, ML, MR, NE, SN, TD, TG).
(22) International Filing Date: 25 March 1998 (25.03.98)			
(30) Priority Data: 08/826,484 27 March 1997 (27.03.97) US			
(71) Applicant: ERICSSON INC. [US/US]; Patent Dept., 7001 Development Drive, P.O. Box 13969, Research Triangle Park, NC 27709 (US).			
(72) Inventor: STARK, Wayne, E.; 1609 Fordham Boulevard, Chapel Hill, NC 27414 (US).			
(74) Agents: BIGEL, Mitchell, S. et al.; Myers, Bigel, Sibley & Sajovec, P.A., P.O. Box 37428, Raleigh, NC 27627 (US).			
		Published	<i>With international search report.</i> <i>Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.</i>

(54) Title: COMMUNICATIONS SYSTEMS AND METHODS EMPLOYING CODE RATE PARTITIONING WITH NONORTHOGONAL MODULATION



(57) Abstract

Information is processed to produce a plurality of information symbols. The plurality of information symbols are encoded according to a concatenation of an error correction code and a nonorthogonal modulation code to produce a modulated communications signal. The modulated communications signal is communicated over a communication medium, and communications signal processing means process the communicated modulated communications signal to produce information. Preferably, the information symbols are encoded according to an error correction code, preferably a convolutional code, to produce a plurality of coded symbols. The plurality of coded symbols are preferably interleaved to produce a plurality of interleaved coded symbols. The interleaved coded symbols are then modulated according to a nonorthogonal code to produce the modulated communications signal. Preferably, the coded symbols are modulated according to a proper subset of one of a Nordstrom-Robinson code, a Reed-Muller code, or a Kerdock code, the proper subset being operable to produce a modulated communications signal from a signal set such that the communications signal noncoherently demodulates to produce a unique output for each signal in the signal set, and the communications signal processing means includes noncoherent demodulating means for noncoherently demodulating the communicated modulated communications signal.

**FOR THE PURPOSES OF INFORMATION ONLY**

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakhstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		

## COMMUNICATIONS SYSTEMS AND METHODS EMPLOYING CODE RATE PARTITIONING WITH NONORTHOGONAL MODULATION

### Field of the Invention

The present invention relates to communications systems and methods, in particular, to coding systems and methods in communications systems.

5

### Background of the Invention

In many communications systems, for example, wireless communications systems such as mobile satellite radiotelephone systems, it is generally desirable to use as little signal power as necessary to 10 communicate signals. Toward this end, many communications systems utilize error correction coding to improve signal-to-noise ratio without requiring an increase in signal power. As illustrated in Figure 1, in a typical wireless communications system, information represented by information symbols 105 is first encoded according to an error control code, for example, in a 15 convolutional encoder 110. The coded symbols 115 output from the convolutional coder 110 are then typically interleaved in an interleaver 120, which reorders the coded symbols 115 to produce a plurality of interleaved coded symbols 125. The interleaved coded symbols 125 are then typically orthogonally modulated by an orthogonal modulator 130 to produce a 20 communications signal 135 which is then communicated over a communications medium 140. An orthogonal modulator 130 is typically employed because the orthogonally modulated communications signal 135 can be demodulated in a noncoherent fashion at a receiver.

The convolutional encoder 110 and the orthogonal demodulator 130 25 produce an overall code rate and minimum distance for the communications signal 135. The convolutional encoder 110 typically employs a rate  $k/n$  convolutional code, i.e., a code which produces  $n$  coded symbols 115 for each  $k$  information symbols 105 input into the encoder 110, and generally has a minimum Hamming distance  $d_{1,\min}$  associated therewith. The orthogonal

modulator 130 typically employs a set of  $p$  orthogonal block modulation vectors of length  $l$  for input vectors of length  $m$ , producing a code rate of  $m/l$  and a minimum distance of  $d_{2,\min}$ . When combined as illustrated in Figure 1, the convolutional encoder 110 and the orthogonal modulator 130 produce an overall code rate of  $k/n * m/l$  and a minimum distance of  $d_{1,\min} * d_{2,\min}$ .

5 Although techniques exist for improving the error-correcting performance of a conventional combination of a convolutional encoder and an orthogonal modulator, for example, lowering the rate of the convolutional encoder 110 or the orthogonal modulator 130 to provide greater redundancy, 10 these techniques can result in lower efficiency and greater complexity in receiver design. Due to bandwidth and power constraints, there is an ever present need to provide improved signal-to-noise performance without requiring undue additional complexity in receiver design, increased signal power, decreased rate and the like.

#### Summary of the Invention

In light of the foregoing, it is an object of the present invention to provide error correction coding and modulation systems and methods which provide improved signal-to-noise performance.

20 It is another object of the present invention to provide error correction coding and modulation systems and methods which may be utilized with noncoherent demodulation techniques.

25 These and other objects, features and advantages are provided according to the present invention by communications systems and methods in which information symbols are encoded according to a concatenation of a error correcting code, preferably a convolutional code, and a nonorthogonal modulation code to produce a modulated communications signal representing the information symbols. The nonorthogonal modulation code preferably corresponds to one of a Nordstrom-Robinson, a Reed-Muller and a Kerdock 30 code, representing a union of selected translations of an orthogonal code set. More preferably, the nonorthogonal modulation code represents a signal set such that when the communications signal is noncoherently demodulated, a unique output is produced for each code in the set. In this manner, less

complex demodulation techniques can be employed.

The present invention stems from the recognition that a coding scheme having improved distance characteristics over a conventional concatenation of an error correcting code and an orthogonal modulation can be achieved by 5 replacing the orthogonal modulation code with a selected nonorthogonal modulation code which represents an expansion of an orthogonal code which can be demodulated without undue complexity using modified noncoherent orthogonal demodulation techniques. By utilizing nonorthogonal modulation vectors, the present invention allows a decreased code rate to be utilized for 10 the error correcting code while maintaining a desired overall code rate and increasing overall minimum distance.

In particular, in a communications system according to the present invention, information processing means process information to produce a plurality of information symbols. Means are provided to encode the plurality 15 of information symbols according to a concatenation of an error correction code and a nonorthogonal modulation code to produce a modulated communications signal. Communications signal communicating means communicate the modulated communications signal over a communications medium, and communications signal processing means process the 20 communicated modulated communications signal to produce information. Preferably, the convolutional code is punctured to thereby provide a desired overall coding rate. More optimal partitioning between error correction encoding and modulation may thereby be provided.

Preferably, the means for encoding comprises error correction 25 encoding means for encoding the plurality of information symbols according to an error correction code to produce a plurality of coded symbols, and nonorthogonal modulating means for modulating the plurality of coded symbols according to a nonorthogonal modulation code to produce a modulated communications signal. The coded symbols produced by the error 30 correction encoding means preferably are interleaved before modulation in the nonorthogonal modulating means. According to a preferred embodiment, the nonorthogonal modulating means modulate the plurality of coded symbols according to a nonorthogonal modulation code representing a union of

-4-

translations of a set of orthogonal code vectors according to a predetermined translation which produces one of a Nordstrom-Robinson code, a Reed-Muller code, and a Kerdock code, the predetermined translation including a plurality of vectors which map the orthogonal code to the nonorthogonal code.

5 Preferably, the nonorthogonal modulating means modulates the coded symbols according to a proper subset of a nonorthogonal modulation code, the proper subset being operable to produce a modulated communications signal from a signal set such that the communications signal noncoherently demodulates to produce a unique output for each signal in the signal set.

10 The communications signal processing means preferably includes noncoherent demodulating means for noncoherently demodulating the communicated modulated communications signal.

The noncoherent demodulating means preferably includes means for processing the communicated modulated communications signal to produce a plurality of received communications symbols, and means for translating the plurality of received communications symbols according to the translation vectors which produce the nonorthogonal modulation code to produce a plurality of groups of communications symbols, a respective group corresponding to a respective one of the translation vectors of the 15 nonorthogonal code. Means are also preferably provided for correlating each group of communications symbols with the set of orthogonal code vectors to produce decision information for each group, and for combining the decision information for the groups of communications symbols to produce a second plurality of information symbols. Efficient demodulation of the 20 nonorthogonally modulated communications signal is thereby provided.

25

#### Brief Description of the Drawings

Some of the objects and advantages of the present invention having been stated, others will be more fully understood from the detailed description 30 that follows and by reference to the accompanying drawings in which:

Figure 1 is a schematic diagram illustrating a communications system according to the prior art;

Figure 2 is a schematic diagram illustrating a communications system

-5-

according to the present invention;

Figure 3 is a schematic diagram illustrating a preferred embodiment of a communications system according to the present invention;

5 Figure 4 is a schematic diagram illustrating a preferred embodiment for processing a modulated communications signal according to the present invention; and

Figure 5 is a flowchart illustration of operations for communicating information according to the present invention.

## 10 Detailed Description of Preferred Embodiments

The present invention now will be described more fully hereinafter with reference to the accompanying drawings, in which embodiments of the invention are shown. This invention may, however, be embodied in many different forms and should not be construed as limited to the embodiments 15 set forth herein; rather, these embodiments are provided so that this disclosure will be thorough and complete, and will fully convey the scope of the invention to those skilled in the art. In the drawings, like numbers refer to like elements throughout.

## 20 Overview

As will be appreciated by those skilled in the art, in a typical conventional communication scheme such as the one illustrated in Figure 1, information may be protected by an error control code, e.g., a convolutional code. For an input information sequence of binary symbols  $b_i \in \{+1, -1\}$ , the 25 convolutional code produces a coded symbol sequence  $\{c_j\}$  including symbols which are a function of the input sequence  $b_i$ . For a rate 1/2 convolutional code, for example, the coded bits  $c_{2i}$  and  $c_{2i+1}$  are some function of  $b_1, \dots, b_{i-M+1}$  where  $M$  is the memory of the code, i.e., the rate 1/2 code produces two coded symbols for each input information symbol.

30 Those skilled in the art will also understand that in addition to the rate of the code, an important measure of the performance of a code is the minimum Hamming and Euclidean distance of the code, representing a measure of the separation between two possible codewords in the code. For

-6-

example, consider a typical orthogonal modulation scheme, in which a sequence of symbols input into a modulator are mapped onto a signal set including  $p$  vectors of length  $p$  that are orthogonal, each component of the vectors being commonly known as a "chip." If  $s_i = (s_{i,1}, \dots, s_{i,p})$  for  $i = 1, \dots, p$  are these vectors, with  $s_{j,i} \in \{\pm 1\}$ , then

$$\sum_{i=1}^p s_{l,i} s_{m,i} = \begin{cases} p, & l=m \\ 0, & l \neq m \end{cases}.$$

For example, if  $p=16$ , these vectors are:

$s_1 = \{+1, +1, +1, +1, +1, +1, +1, +1, +1, +1, +1, +1, +1, +1, +1, +1\};$   
10     $s_2 = \{+1, -1, +1, -1, +1, -1, +1, -1, +1, -1, +1, -1, +1, -1, +1, -1\};$   
 $s_3 = \{+1, +1, -1, -1, +1, +1, -1, -1, +1, +1, -1, -1, +1, +1, -1, -1\};$   
 $s_4 = \{+1, -1, -1, +1, +1, -1, -1, +1, +1, -1, -1, +1, +1, -1, -1, +1\};$   
 $s_5 = \{+1, +1, +1, +1, -1, -1, -1, +1, +1, +1, +1, -1, -1, -1, -1\};$   
 $s_6 = \{+1, -1, +1, -1, -1, +1, -1, +1, +1, -1, +1, -1, -1, +1, -1, +1\};$   
15     $s_7 = \{+1, +1, -1, -1, -1, +1, +1, +1, +1, -1, -1, -1, -1, +1, +1, +1\};$   
 $s_8 = \{+1, -1, -1, +1, -1, +1, +1, -1, +1, -1, -1, +1, -1, +1, +1, -1\};$   
 $s_9 = \{+1, +1, +1, +1, +1, +1, +1, +1, -1, -1, -1, -1, -1, -1, -1, -1\};$   
 $s_{10} = \{+1, -1, +1, -1, +1, -1, -1, +1, -1, +1, -1, +1, -1, +1, -1, +1\};$   
 $s_{11} = \{+1, +1, -1, -1, +1, +1, -1, -1, -1, +1, +1, -1, -1, +1, +1, +1\};$   
20     $s_{12} = \{+1, -1, -1, +1, +1, -1, -1, +1, +1, -1, +1, -1, -1, +1, +1, -1\};$   
 $s_{13} = \{+1, +1, +1, +1, -1, -1, -1, -1, -1, -1, +1, +1, +1, +1, +1\};$   
 $s_{14} = \{+1, -1, +1, -1, -1, +1, -1, +1, -1, +1, +1, +1, -1, +1, -1\};$   
 $s_{15} = \{+1, +1, -1, -1, -1, +1, +1, -1, -1, +1, +1, +1, +1, -1, -1\};$  and  
 $s_{16} = \{+1, -1, -1, +1, -1, +1, +1, -1, -1, +1, +1, -1, +1, -1, -1, +1\}.$

25

The squared Euclidean distance between two distinct codewords is defined as:

$$d_{l,m}^2 = \sum_{j=1}^p (s_{l,j} - s_{m,j})^2$$

For orthogonal modulation vectors:

$$d_{l,m}^2 = 2p, \text{ for } l \neq m.$$

For the above example in which  $p=16$ , the minimum squared Euclidean distance is thus 32.

5 As is well-known by those skilled in the art, an orthogonal modulation code is conventionally used in communications systems, as an orthogonally modulated signal may be demodulated in a noncoherent fashion, i.e., decision statistics for received symbols can be derived without knowing the phase of the received signal. For example, when a convolutional code with minimum  
10 Hamming distance  $d_{\min}$  is followed by a long interleaver and then orthogonally modulated according to an orthogonal modulation code as described above with distance  $2p$  and rate  $1/4$ , the overall squared Euclidean distance is  $2pd_{\min}$ . The rate of the concatenation of the convolutional code and the  
15 orthogonal modulation code in bits/chip is  $1/4 * 1/n$  where  $1/n$  is the rate of the convolutional code, e.g., for a rate  $1/2$  convolutional code, the overall rate becomes  $1/8$ .

Increasing the size of the modulation signal set is generally desirable because using a larger modulation code set can increase the rate of communication without substantially increasing the likelihood of a decoder  
20 error or substantially degrading reliability, thus enabling the use of lower rate convolutional codes. Thus, performance of a coding scheme can be adjusted by varying the size of the signal set used for modulation and varying the rate of the convolutional code such that the overall rate of communications is the same as that provided by a conventional combination of a convolutional  
25 encoder and an orthogonal modulator. However, although a larger modulation signal set can be created including complementary codes, i.e., codes which are negatives of one another, these codes produce signals representing 180 degree phase shifts from one another, and thus produce signals which are not amenable to noncoherent demodulation. For this  
30 reason, it generally is preferable to use a proper subset of modulation vectors such that none of the modulation vectors has a complement within the

subset.

According to the present invention, the original orthogonal code set is expanded by adding selected translates of the original orthogonal vectors to the modulation code set. For the example given above, the orthogonal signal set for 16 vectors can be expanded to 128 vectors by using the following 5 translation vectors which produce a subcode of the length 16 Nordstrom-Robinson code:

$$b_1 = \{+1, +1, +1, +1, +1, +1, +1, +1, +1, +1, +1, +1, +1, +1, +1\};$$

$$b_2 = \{+1, +1, +1, -1, +1, +1, +1, -1, +1, +1, -1, +1, -1, +1, -1\};$$

$$b_3 = \{+1, +1, +1, +1, +1, -1, -1, +1, +1, +1, -1, -1, +1, -1, +1, -1\};$$

$$b_4 = \{+1, +1, +1, -1, +1, +1, -1, +1, +1, +1, -1, +1, +1, -1, -1, -1\};$$

$$b_5 = \{+1, +1, +1, +1, +1, +1, -1, -1, +1, -1, +1, -1, -1, +1, +1, -1\};$$

$$b_6 = \{+1, +1, +1, -1, +1, -1, -1, +1, -1, -1, -1, -1, -1, +1\};$$

$$b_7 = \{+1, +1, +1, +1, +1, -1, +1, -1, +1, -1, +1, +1, +1, -1, -1\}; \text{ and}$$

$$b_8 = \{+1, +1, +1, -1, +1, -1, +1, +1, +1, +1, +1, -1, +1, -1, -1\}.$$

The new code includes all vectors of the form:

$$(s_{l,1}b_{m,1}, s_{l,2}b_{m,2}, \dots, s_{l,16}b_{m,16})$$

for  $l=1, \dots, 16$  and  $m=1, \dots, 8$ , i.e.,  $16*8=128$  code words. Those skilled in the

20 art will appreciate that this construction is not unique, and that there may be other possible vectors  $b_1, \dots, b_8$  that will give an equivalent or identical code.

To allow for noncoherent demodulation, a subset (or subcode) is preferably selected for use in nonorthogonal modulation such that no two vectors of the nonorthogonal modulation code produce antipodal signals. The 25 number of vectors can be further expanded from 128 to 1024, producing a new code which is a subset of the linear Reed-Muller code of length 16 and rate 11/16. Removing complements, a subset of this code is produced having a rate of 10/16. The Nordstrom-Robinson code of length 16 can also be generalized to lengths that are even powers of two (e.g. 64, 256) to 30 produce codes known as Kerdock codes.

Relationships between the orthogonal codes and these expanded nonorthogonal codes can be summarized as follows:

-9-

BO(5,16)  $\subset$  NR(8,16)  $\subset$  RM(11,16)  $\subset$  RM(15,16)

and

O(4,16)  $\subset$  NR\*(7,16)  $\subset$  RM\*(10,16)  $\subset$  RM\*(14,16).

5 BO(5,16) represents a biorthogonal code, i.e. an orthogonal code including complementary code words, having a code of length 16 and including  $2^5$  codewords, found by taking the 16 vectors  $s_1-s_{16}$  listed above and adding the negatives of each vector to produce 32 vectors. NR(8,16) code represents the standard Nordstrom-Robinson code of length 16, which

10 includes  $2^8$  vectors and produced by taking the 32 vectors from the biorthogonal code BO(5,16) and adding translates corresponding to the eight translation vectors listed above. RM(11,16) represents the Reed-Muller code of length 16 with  $2^{11}$  codewords. The RM(15,16) code is the Reed-Muller code of length 16 with  $2^{15}$  codewords. As the number of codewords in the

15 code increases, the code distance decreases, i.e., code BO(5,16) has distance 8, code NR(8,16) has distance 6, code RM(11,16) has distance 4, and code RM(15,16) code has distance 2.

Because noncoherent demodulation is preferred, however, subsets of these various codes are preferably used. Half of the codewords are removed

20 from the sets such that no two codewords produce antipodal signals. This reduces the number of codes in the sets and reduces the rate of transmission, but does not change the minimum distance between codewords. Thus, the orthogonal code O(4,16) represents half of the biorthogonal code B(5,16), i.e., the 16 vectors  $s_1-s_{16}$  listed above. Similarly,

25 the code NR\*(7,16) is a subset of the Nordstrom-Robinson code NR(8,16), the RM\*(10,16) is a subset of the RM(11,16) code, and the RM\*(14,16) code is a subset of the RM(15,16) code.

According to the present invention, the use of a selectively expanded modulation signal set allows the use of a lower rate convolutional code, thus

30 providing greater error protection. For example, replacing the original combination of an orthogonal code set O(4,16) having the rate 1/4 and a rate 1/2 convolutional code, with the nonorthogonal Nordstrom-Robinson code set NR\*(7,16) having a rate 7/16 and a lower rate convolutional code with rate

-10-

2/7, can be used to produce the same overall code rate of  $(2/7) * (7/16) = 1/8$ .

The squared Euclidean distance associated with the Nordstrom-Robinson

code NR\*(7,16) is  $6*4=24$ , compared to the squared Euclidean distance

$8*4=32$  of the original orthogonal code O(4,16). The punctured convolutional

5 code with rate 2/7 and memory 4 has distance 13 compared to the original rate 1/2 code with distance 7. Thus, assuming sufficient interleaving, the new combination of codes has distance  $24*13=312$ , compared to the old scheme with distance  $32*7=224$ , corresponding to a 1.44dB gain in additive white Gaussian noise at high signal-to-noise ratio.

10 Tables 1 and 2 illustrate the effect of expanding the modulation code set and modifying the convolutional code as described above for codes of length 16 and 64, respectively:

Table 1

Modulation Code			Convolutional Code			Overall		
Length	Rate	Distance/4	Memory	Rate	Distance	Overall Rate	Overall Distance	
15	16	4/16	8	4	1/2	7	1/8	56
	16	7/16	6	4	2/7	13	1/8	78
	16	10/16	4	4	1/5	20	1/8	80
	16	14/16	2	4	1/7	28	1/8	56
20	16	4/16	8	5	1/2	8	1/8	64
	16	7/16	6	5	2/7	16	1/8	96
	16	10/16	4	5	1/5	22	1/8	88
	16	14/16	2	5	1/7	32	1/8	64
25	16	4/16	8	6	1/2	10	1/8	80
	16	7/16	6	6	2/7	16	1/8	96
	16	10/16	4	6	1/5	25	1/8	100
	16	14/16	2	6	1/7	36	1/8	72
30	16	4/16	8	7	1/2	10	1/8	80
	16	7/16	6	7	2/7	19	1/8	114
	16	10/16	4	7	1/5	28	1/8	112
	16	14/16	2	7	1/7	40	1/8	80

Table 2

Modulation Code			Convolutional Code			Overall		
Length	Rate	Distance/4	Memory	Rate	Distance	Overall Rate	Overall Distance	
5	64	6/64	32	4	1/3	12	1/32	384
	64	11/64	28	4	2/11	21	1/32	588
	64	6/64	32	5	1/3	13	1/32	416
	64	11/64	28	5	2/11	24	1/32	672
10	64	6/64	32	6	1/3	15	1/32	480
	64	11/64	28	6	2/11	28	1/32	784
	64	6/64	32	7	1/3	16	1/32	512
	64	11/64	28	7	2/11	31	1/32	868

For the length 16 modulation vectors shown in Table 1, assuming additive white Gaussian noise, a rate 2/7 convolutional code of memory 7 combined with a (7,16) Nordstrom-Robinson code produces a coding gain of 1.54dB over orthogonal modulation with a rate 1/2 convolutional code. For the length 64 modulation vectors shown in Table 2, a rate 2/11 convolutional code of memory 7 combined with a (11, 64) Kerdock code produces a performance gain estimated at  $10 \log_{10} (4*868/4*512) = 2.3$ dB over orthogonal modulation with a rate 1/3 convolutional code.

A demodulator for demodulating the nonorthogonally modulated communications signal can be implemented by augmentation of a receiver used for orthogonally modulated signals. Assuming the preferred noncoherent demodulation, the demodulator processes the received signal by first applying a noncoherent matched filter to each chip of the modulation, and then performing a fast Haddamard transform to obtain decision statistics for the orthogonal vector subset, e.g.,  $s_1-s_{16}$ , of the nonorthogonal modulation code. Decision statistics for the other vectors in the modulation code may be obtained by translating the received vector and then performing a fast Haddamard transform to produce decision statistics corresponding to each vector translation. Decision information about a symbol can then be obtained by comparing the decision statistics from each subset.

**Implementation**

Referring now to Figure 2, in a communications system 200 according to the present invention, information 205 is processed by information processing means 210 to produce a plurality of information symbols 215.

- 5      Error correction encoding means 220 encode the plurality of information symbols 215 according to an error correction code to produce a plurality of error-correction encoded symbols 225. Nonorthogonal modulating means 240 modulate error correction encoded symbols, preferably interleaved error correction encodes symbols 235 interleaved by interleaving means 230,
- 10     according to a nonorthogonal modulation code to produce a modulated communications signal 245. The modulated communications signal 245 is communicated over a communications medium by communications signal communicating means 250. The communicated modulated communications signal 250 is processed by communications signal processing means 260 to
- 15     produce information 265.

As illustrated in Figure 3, the error correction encoding means 220 preferably includes a convolutional encoder 222 which encodes the plurality of information symbols 215 according to a convolutional code, which may in turn may be followed by puncturing means 224, e.g., a puncture table or the like, which punctures the output of the convolutional encoder 222 to produce a desired rate for the error-correction encoding means 220. Those skilled in the art will appreciate, however, that other error correcting codes, such as block codes, may be used with the present invention.

- 20     Interleaved error correction encoded symbols 235 produced by interleaving means 230 are modulated in a nonorthogonal modulating means 240, preferably using a nonorthogonal modulation code or signal set 242 which is a proper subset of one of a Nordstrom-Robinson code, a Reed Muller code and a Kerdock code, more preferably a subset which includes only one of each complementary pair of vectors, i.e., vectors which produce antipodal signals. The modulated communications signal 245 thereby produced is then communicated over a communications medium by communications signal communicating means 250. Communications signal processing means 260 preferably includes a noncoherent demodulating
- 25
- 30

means 262 for noncoherently demodulating the communicated modulated communications signal 255 to produce demodulated communications symbols 261. The demodulated communications symbols 261 may then deinterleaved by deinterleaving means 264 and convolutionally decoded in a convolutional decoder 266, for example, a Viterbi algorithm, to produce information symbols 263 which may be further processed to recover information 265.

Those skilled in the art will appreciate that the elements described above may include various communications system components. It will be understood that the information processing means 210, error-correction 10 encoding means 220, interleaving means 230 and nonorthogonal modulating means 240 may include special purpose hardware, software running on general purpose computers or other data processing hardware, or combinations thereof. These elements may be implemented using, for example, commonly-used communications hardware such as amplifiers, 15 multiplexers, gate arrays or other application-specific integrated circuits (ASICs), microprocessors, digital signal processor (DSP) chips and the like, the operation of which is well-known to those skilled in the art and need not be described in greater detail herein. It will also be understood that communications signal communicating means 250 may be implemented using 20 special-purpose hardware, software running on data processors, or combinations thereof, and may include commonly used communications components such as multiplexers, mixers, amplifiers, antennas, receivers, and the like, the operation of which is well-known to those skilled in the art and need not be discussed in greater detail herein. Similarly, communications 25 signal processing means 260 may include special-purpose hardware, software running on data processors or combinations thereof, and may include such commonly-used components as amplifiers, filters, analog-to-digital converters (A/D's), ASICs, DSP chips and the like, the operation of which is well-known to those skilled in the art and need not be discussed in 30 greater detail herein.

Figure 4 illustrates means 262 for noncoherently demodulating a communications signal 255 which is modulated according to the nonorthogonal modulation scheme described above to produce information

-14-

symbols 445 corresponding to the coded symbols 235 input into the nonorthogonal modulating means 240 of Figures 2 and 3. A noncoherent matched filter 410 is applied to the communications signal 255, and the complex output of the matched filter sampled by sampling means 420 to 5 produce a plurality of received communications symbols 425. The received communications symbols 425 are then correlated in correlating means 430 against the vectors of the nonorthogonal modulation code by which the communications signal 255 was modulated, to produce decision information 435a-m representing the degree of correlation of received communications 10 symbols with the code vectors of the nonorthogonal code. The decision information 435a-m is then input into a decision means 440 to produce information symbols 445, representing an estimate of the coded information symbols 235 before modulation in the nonorthogonal modulating means 240 of Figures 2 and 3. In this manner, decoding of the communications signal 15 255 is provided.

The correlating means 430 preferably includes a plurality of code vector translators 420a-m which translate the received communications symbols 435 according to the translation vectors used to produce the nonorthogonal modulation code employed in the nonorthogonal modulating 20 means 240 of Figures 2 and 3, as described above. Those skilled in the art will appreciate that because these translation vectors map an orthogonal code to the nonorthogonal code such that the orthogonal code is a subset of the nonorthogonal code, one of the translators 420a-m corresponds to a unity translation and therefore in practice does not require an actual translation. 25 Orthogonal vector correlators 434a-m correlate the translated received communications symbols with the orthogonal subset of the nonorthogonal modulation code to produce the decision information 435a-m, for example, by computing fast Haddamard transforms for each of the translated vector outputs 433a-m using what is commonly referred to as a "Green machine" 30 algorithm, as described in *The Theory of Error-Correcting Codes*, by F.J. MacWilliams et al., North-Holland Publishing Co., 1978, pp. 419-426.

Figure 5 illustrates operations for communicating information over a communications medium according to the present invention (Block 500).

-15-

Information is processed to produce a plurality of information symbols (Block 510). The plurality of information symbols are encoded according to an error-correction code, preferably a convolutional code, to produce a plurality of coded symbols (Block 520). The plurality of symbols is then preferably interleaved to produce a plurality of interleaved coded symbols (Block 530). The plurality of interleaved coded symbols are then modulated according to a nonorthogonal modulation code, preferably a proper subset of one of a Nordstrom-Robinson code, a Reed-Muller code or a Kerdock code from which complementary code vectors have been eliminated to allow noncoherent demodulation, to produce a modulated communications signal (Block 540). The modulated communications signal is then communicated over the communications medium (Block 550). The communicated modulated communications signal is then processed, preferably by noncoherent demodulation techniques, to produce information (Block 560), e.g. coded symbol likelihoods. These likelihoods may be deinterleaved and further decoded.

Those skilled in the art will appreciate that variations to the above operations may be performed according to the present invention. For example, it will be understood that although convolutional encoding is preferred for the error correction encoding operation (Block 520), other types of error correction coding, for example, block coding, may be used in lieu of convolutional coding. It will also be understood that although the interleaving operation (Block 530) is preferred, the present invention may be performed without interleaving. Similarly, although using a proper subset of one of the aforementioned nonorthogonal codes in which complementary code vectors have been eliminated is preferred in order to enable less complex noncoherent demodulation techniques. It is not required to obtain the benefits of the present invention.

In the drawings and specification, there have been disclosed typical embodiments of the invention and, although specific terms are employed, they are used in a generic and descriptive sense only and not for purposes of limitation, the scope of the invention being set forth in the following claims.

## THAT WHICH IS CLAIMED IS:

1. A method of communicating information over a communications medium, the method comprising the steps of:

processing information to produce a plurality of information symbols;  
encoding the plurality of information symbols according to a

5 concatenation of an error correction code and a nonorthogonal modulation code to produce a modulated communications signal;

communicating the modulated communications signal over the communications medium; and

10 processing the communicated modulated communications signal to produce information.

2. A method according to Claim 1, wherein said step of encoding comprises the steps of :

encoding the plurality of information symbols according to the error correction code to produce a plurality of coded symbols; and

5 modulating the plurality of coded symbols according to a nonorthogonal modulation code to produce a modulated communications signal.

3. A method according to Claim 2, wherein said step of modulating comprises the step of modulating the plurality of coded symbols according to a nonorthogonal modulation code representing a union of translations of a set of orthogonal code vectors according to a predetermined translation which

5 produces one of a Nordstrom-Robinson code, a Reed-Muller code, or a Kerdock code.

4. A method according to Claim 2, wherein said step of modulating comprises the step of modulating the plurality of coded symbols according to one of a Nordstrom-Robinson code, a Reed-Muller code or a Kerdock code.

5. A method according to Claim 2:

-17-

wherein said step of modulating comprises the step of modulating the plurality of coded symbols according to a proper subset of a nonorthogonal modulation code, the proper subset being operable to produce a modulated 5 communications signal from a signal set such that the communications signal noncoherently demodulates to produce a unique output for each signal in the signal set; and

wherein said step of processing the communicated modulated 10 communications signal comprises the step of noncoherently demodulating the communicated modulated communications signal.

6. A method according to Claim 5:

wherein said step of modulating comprises the step of modulating the plurality of coded symbols according to a nonorthogonal modulation code representing a union of translations of a set of orthogonal code vectors 5 according to a predetermined set of translation vectors which produces one of a Nordstrom-Robinson code, a Reed-Muller code, or a Kerdock code, the translation including a plurality of translation vectors; and

wherein said step of noncoherently demodulating comprises the steps of:

10 processing the communicated modulated communications signal to produce a plurality of received communications symbols;

translating the plurality of received communications symbols according to the translation vectors to produce a plurality of groups of communications symbols, a respective group corresponding to a 15 respective one of the translation vectors;

correlating each group of communications symbols with the set of orthogonal code vectors to produce decision information for each group; and

20 combining the decision information for the groups of communications symbols to produce a plurality of information symbols.

7. A method according to Claim 1, wherein said step of encoding comprises the step of encoding the plurality of information symbols according

-18-

to a concatenation of a convolutional code and a nonorthogonal modulation code to produce the modulated communications signal.

8. A method according to Claim 7, wherein said step of encoding comprises the step of encoding the plurality of information symbols according to a concatenation of a punctured convolutional code and a nonorthogonal code to produce the modulated communications signal.

9. A method according to Claim 2, wherein said step of modulating is preceded by the step of interleaving the plurality of coded symbols to produce a plurality of interleaved coded symbols, and wherein said step of modulating comprises the step of modulating the plurality of interleaved coded symbols to produce a modulated communications signal.

10. A method of producing a communications signal representing a plurality of information symbols, the method comprising the steps of:  
encoding the plurality of information symbols according to a concatenation of an error correction code and a nonorthogonal modulation code to produce a modulated communications signal.

11. A method according to Claim 10, wherein said step of encoding comprises the steps of:  
encoding the plurality of information symbols according to the error correction code to produce a plurality of coded symbols; and  
modulating the plurality of coded symbols according to a nonorthogonal modulation code to produce a modulated communications signal.

12. A method according to Claim 11, wherein said step of modulating comprises the step of modulating the plurality of coded symbols according to a nonorthogonal modulation code representing a translation of a set of orthogonal code vectors according to a predetermined translation which produces one of a Nordstrom-Robinson code, a Reed-Muller code, or a

Kerdock code.

13. A method according to Claim 11, wherein said step of modulating comprises the step of modulating the plurality of coded symbols according to one of a Nordstrom-Robinson code, a Reed-Muller code, or a Kerdock code.

14. A method according to Claim 11, wherein said step of modulating comprises the step of modulating the plurality of coded symbols according to a proper subset of a nonorthogonal modulation code, the proper subset being operable to produce a modulated communications signal from a signal set such that the communications signal noncoherently demodulates to produce a unique output for each signal in the signal set.

15. A method according to Claim 10, wherein said step of encoding comprises the step of encoding the plurality of information symbols according to a concatenation of a convolutional code and a nonorthogonal modulation code to produce the modulated communications signal.

16. A method according to Claim 15, wherein said step of encoding comprises the step of encoding the plurality of information symbols according to a concatenation of a punctured convolutional code and a nonorthogonal modulation code to produce the modulated communications signal.

17. A method according to Claim 11, wherein said step of modulating is preceded by the step of interleaving the plurality of coded symbols to produce a plurality of interleaved coded symbols, and wherein said step of modulating comprises the step of modulating the plurality of interleaved coded symbols to produce a modulated communications signal.

18. A system for communicating information over a communications medium, the system comprising:

information processing means for processing information to produce a

plurality of information symbols;

5 means, responsive to said information processing means, for encoding the plurality of information symbols according to a concatenation of an error correction code and a nonorthogonal modulation code to produce a modulated communications signal;

communications signal communicating means, responsive to said 10 means for encoding the plurality of information symbols according to a concatenation of an error correction code and a nonorthogonal modulation code, for communicating the modulated communications signal over the communications medium; and

communications signal processing means, responsive to said 15 communications signal communicating means, for processing the communicated modulated communications signal to produce information.

19. A system according to Claim 18, wherein said means for encoding the plurality of information symbols according to a concatenation of an error correction code and a nonorthogonal modulation code comprises:

error correction encoding means, responsive to said information 5 processing means, for encoding the plurality of information symbols according to the error correction code to produce a plurality of coded symbols; and

nonorthogonal modulating means, responsive to said error correction encoding means, for modulating the plurality of coded symbols according to a nonorthogonal modulation code to produce a modulated communications 10 signal.

20. A system according to Claim 19, wherein said nonorthogonal modulating means comprises means for modulating the plurality of coded symbols according to a nonorthogonal modulation code representing a translation of a set of orthogonal code vectors according to a predetermined 5 translation which produces one of a Nordstrom-Robinson code, a Reed-Muller code, or a Kerdock code.

21. A system according to Claim 19, wherein said nonorthogonal

-21-

modulating means comprises means for modulating the plurality of coded symbols according to one of a Nordstrom-Robinson code, a Reed-Muller code, or a Kerdock code.

22. A system according to Claim 19:

wherein said nonorthogonal modulating means comprises means for modulating the plurality of coded symbols according to a proper subset of a nonorthogonal modulation code, the proper subset being operable to produce a modulated communications signal from a signal set such that the communications signal noncoherently demodulates to produce a unique output for each signal in the signal set; and

wherein said communications signal processing means comprises noncoherent demodulating means for noncoherently demodulating the communicated modulated communications signal.

23. A system according to Claim 22:

wherein said nonorthogonal modulating means comprises means for modulating the plurality of coded symbols according to a nonorthogonal modulation code representing a union of translations of a set of orthogonal code vectors according to a predetermined set of translation vectors which produces one of a Nordstrom-Robinson code, a Reed-Muller code, or a Kerdock code, the translation including a plurality of translation vectors; and

wherein said noncoherent demodulating means comprises:

means for processing the communicated modulated

communications signal to produce a plurality of received communications symbols;

means, responsive to said means for processing the communicated modulated communications signal to produce a plurality of received communications symbols, for translating the plurality of received communications symbols according the translation vectors to produce a plurality of groups of communications symbols, a respective group corresponding to a respective one of the translation vectors; and

means, responsive to said means for translating, for correlating

-22-

each group of communications symbols with the set of orthogonal code  
20 vectors to produce decision information for each group; and  
means, responsive to said means for correlating, for combining  
the decision information for the groups of communications symbols to  
produce a plurality of information symbols.

24. A system according to Claim 18, wherein said means for  
encoding the plurality of information symbols according to a concatenation of  
an error correction code and a nonorthogonal modulation code comprises  
means for encoding the plurality of information symbols according to a  
5 concatenation of a convolutional code and a nonorthogonal modulation code  
to produce the modulated communications signal.

25. A system according to Claim 24, wherein said means for  
encoding the plurality of information symbols according to a concatenation of  
an error correction code and a nonorthogonal modulation code comprises  
means for encoding the plurality of information symbols according to a  
5 concatenation of a punctured convolutional code and a nonorthogonal  
modulation code to produce the modulated communications signal.

26. A system according to Claim 19, further comprising interleaving  
means, responsive to said error correction encoding means, for interleaving  
the plurality of coded symbols to produce a plurality of interleaved coded  
symbols, and wherein said nonorthogonal modulating means comprises  
5 means for modulating the plurality of interleaved coded symbols to produce a  
modulated communications signal.

27. An apparatus for producing a communications signal  
representing a plurality of information symbols, the apparatus comprising:  
means for encoding the plurality of information symbols according to a  
concatenation of an error correction code and a nonorthogonal modulation  
5 code to produce a modulated communications signal.

-23-

28. An apparatus according to Claim 27, wherein said means for encoding the plurality of information symbols according to a concatenation of an error correction code and a nonorthogonal modulation code comprises:

error correction encoding means, responsive to said information  
5 processing means, for encoding the plurality of information symbols according to the error correction code to produce a plurality of coded symbols; and  
nonorthogonal modulating means, responsive to said error correction encoding means, for modulating the plurality of coded symbols according to a nonorthogonal modulation code to produce a modulated communications  
10 signal.

29. An apparatus according to Claim 28, wherein said nonorthogonal modulating means comprises means for modulating the plurality of coded symbols according to a nonorthogonal modulation code representing a translation of a set of orthogonal code vectors according to a  
5 predetermined translation which produces one of a Nordstrom-Robinson code, a Reed-Muller code, or a Kerdock code.

30. An apparatus according to Claim 28, wherein said nonorthogonal modulating means comprises means for modulating the plurality of coded symbols according to one of a Nordstrom-Robinson code, a Reed-Muller code, or a Kerdock code.

31. An apparatus according to Claim 28, wherein said nonorthogonal modulating means comprises means for modulating the plurality of coded symbols according to a proper subset of a nonorthogonal modulation code, the proper subset being operable to produce a modulated  
5 communications signal from a signal set such that the communications signal noncoherently demodulates to produce a unique output for each signal in the signal set.

32. An apparatus according to Claim 27, wherein said means for encoding the plurality of information symbols according to a concatenation of

-24-

an error correction code and a nonorthogonal modulation code comprises means for encoding the plurality of information symbols according to a concatenation of a convolutional code and a nonorthogonal modulation code to produce the modulated communications signal.

5 33. An apparatus according to Claim 32, wherein said means for encoding the plurality of information symbols according to a concatenation of a convolutional code and a nonorthogonal modulation code comprises means for encoding the plurality of information symbols according to a concatenation of a punctured convolutional code and a nonorthogonal modulation code to produce the modulated communications signal.

5 34. A system according to Claim 28, further comprising interleaving means, responsive to said error correction encoding means, for interleaving the plurality of coded symbols to produce a plurality of interleaved coded symbols, and wherein said nonorthogonal modulating means comprises means for modulating the plurality of interleaved coded symbols to produce a modulated communications signal.

FIG. 1  
PRIOR ART






FIG. 2








FIG. 4

5/5




FIG. 5

# INTERNATIONAL SEARCH REPORT

International Application No

PCT/US 98/05844

**A. CLASSIFICATION OF SUBJECT MATTER**  
IPC 6 H03M13/00

According to International Patent Classification (IPC) or to both national classification and IPC

**B. FIELDS SEARCHED**

Minimum documentation searched (classification system followed by classification symbols)  
IPC 6 H03M

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

**C. DOCUMENTS CONSIDERED TO BE RELEVANT**

Category <sup>o</sup>	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	WO 95 22859 A (MICRILOR INC) 24 August 1995  see page 9, line 21 - page 11, line 28 see page 13, line 26 - page 16, line 31 see page 23, line 30 - page 29, line 21; figures 8,9  ---  A EP 0 663 775 A (GEN INSTRUMENT CORP) 19 July 1995  see the whole document  ---  A WO 96 05668 A (ERICSSON GE MOBILE INC) 22 February 1996  ---  -/-	1,2,10, 11,18, 19,27,28  7-9, 15-17, 24-26, 32-34

Further documents are listed in the continuation of box C.

Patent family members are listed in annex.

<sup>o</sup> Special categories of cited documents :

- "A" document defining the general state of the art which is not considered to be of particular relevance
- "E" earlier document but published on or after the international filing date
- "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- "O" document referring to an oral disclosure, use, exhibition or other means
- "P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

"&" document member of the same patent family

Date of the actual completion of the international search

13 August 1998

Date of mailing of the international search report

24/08/1998

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2  
NL - 2280 HV Rijswijk  
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,  
Fax: (+31-70) 340-3016

Authorized officer

Devergranne, C

**INTERNATIONAL SEARCH REPORT**

International Application No

PCT/US 98/05844

**C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT**

Category	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	HENKEL W: "PHASE-INVARIANT CODED PHASE SHIFT KEYING USING REED-MULLER CODES" ARCHIV FUR ELEKTRONIK UND UBERTRAGUNGSTECHNIK, vol. 46, no. 3, 1 May 1992, pages 125-130, XP000304721 -----	

# INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/US 98/05844

Patent document cited in search report	Publication date	Patent family member(s)			Publication date
WO 9522859	A 24-08-1995	AU	684905	B	08-01-1998
		AU	1699795	A	04-09-1995
		CA	2176401	A	24-08-1995
		CN	1141103	A	22-01-1997
		EP	0745290	A	04-12-1996
		JP	9509294	T	16-09-1997
		ZA	9501282	A	23-10-1995
EP 0663775	A 19-07-1995	US	5511096	A	23-04-1996
		AU	679591	B	03-07-1997
		AU	1026895	A	27-07-1995
		CA	2140484	A	19-07-1995
		JP	7288556	A	31-10-1995
		NO	950190	A	19-07-1995
WO 9605668	A 22-02-1996	US	5550809	A	27-08-1996
		AU	3322095	A	07-03-1996
		BR	9508876	A	30-12-1997
		CA	2197640	A	22-02-1996
		CN	1159872	A	17-09-1997
		EP	0776555	A	04-06-1997
		FI	970637	A	11-04-1997
		JP	10507322	T	14-07-1998
		NO	970667	A	16-04-1997
		US	5742678	A	21-04-1998
		US	5771288	A	23-06-1998