

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property Organization  
International Bureau



(43) International Publication Date  
18 January 2007 (18.01.2007)

PCT

(10) International Publication Number  
WO 2007/008000 A2

(51) International Patent Classification:

G10L 19/00 (2006.01)

(74) Agents: BAHNG, Hae Cheol et al.; 15th Floor Yo Sam Building, 648-23, Yeoksam-dong, Kangnam-gu, Seoul, 135-080 (KR).

(21) International Application Number:

PCT/KR2006/002678

(22) International Filing Date:

10 July 2006 (10.07.2006)

(25) Filing Language:

English

(26) Publication Language:

English

(30) Priority Data:

60/697,551	11 July 2005 (11.07.2005)	US
PCT/KR2005/002290	16 July 2005 (16.07.2005)	KR
PCT/KR2005/002291	16 July 2005 (16.07.2005)	KR
PCT/KR2005/002292	16 July 2005 (16.07.2005)	KR
PCT/KR2005/002306	18 July 2005 (18.07.2005)	KR
PCT/KR2005/002307	18 July 2005 (18.07.2005)	KR
PCT/KR2005/002308	18 July 2005 (18.07.2005)	KR
60/700,570	19 July 2005 (19.07.2005)	US

(71) Applicant (for all designated States except US): LG ELECTRONICS INC. [KR/KR]; 20, Yoido-dong, Youngdungpo-gu, Seoul, 150-721 (KR).

(72) Inventor; and

(75) Inventor/Applicant (for US only): LIEBCHEN, Tilman [DE/DE]; Lefevrestr., 17, D-12161, Berlin (DE).

(81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BW, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, HN, HR, HU, ID, IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LT, LU, LV, LY, MA, MD, MG, MK, MN, MW, MX, MZ, NA, NG, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RS, RU, SC, SD, SE, SG, SK, SL, SM, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.


(84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LT, LU, LV, MC, NL, PL, PT, RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Published:

— without international search report and to be republished upon receipt of that report

[Continued on next page]

(54) Title: APPARATUS AND METHOD OF ENCODING AND DECODING AUDIO SIGNAL



(57) Abstract: In one embodiment, at least first and second channels in a frame of the audio signal are independently subdivided into blocks if the first and second channels are not correlated with each other. At least two of the blocks have different block lengths. Furthermore, the first and second channels are correspondingly subdivided into blocks such that the lengths of the blocks into which the second channel is subdivided correspond to the lengths of the blocks into which the first channel is subdivided if the first and second channels are correlated with each other. At least two of the blocks have different block lengths.

WO 2007/008000 A2



*For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.*

## [DESCRIPTION]

## APPARATUS AND METHOD OF ENCODING AND DECODING AUDIO SIGNAL

## BACKGROUND OF THE INVENTION

5 The present invention relates to a method for processing audio signal, and more particularly to a method and apparatus of encoding and decoding audio signal.

The storage and replaying of audio signals has been accomplished in different ways in the past. For example, 10 music and speech have been recorded and preserved by phonographic technology (e.g., record players), magnetic technology (e.g., cassette tapes), and digital technology (e.g., compact discs). As audio storage technology progresses, many challenges need to be overcome to optimize the quality 15 and storability of audio signals.

For the archiving and broadband transmission of music signals, lossless reconstruction is becoming a more important feature than high efficiency in compression by means of perceptual coding as defined in MPEG standards such as MP3 or AAC. 20 Although DVD audio and Super CD Audio include proprietary lossless compression schemes, there is a demand for an open and general compression scheme among content-holders and broadcasters. In response to this demand, a new lossless coding scheme has been considered as an extension to the MPEG-25 4 Audio standard. Lossless audio coding permits the

compression of digital audio data without any loss in quality due to a perfect reconstruction of the original signal.

#### SUMMARY OF THE INVENTION

5 The present invention relates to processing an audio signal. In one embodiment, at least first and second channels in a frame of the audio signal are independently subdivided into blocks if the first and second channels are not correlated with each other. At least two of the blocks have different 10 block lengths. Furthermore, the first and second channels are correspondingly subdivided into blocks such that the lengths of the blocks into which the second channel is subdivided correspond to the lengths of the blocks into which the first channel is subdivided if the first and second channels are 15 correlated with each other. At least two of the blocks have different block lengths.

In one embodiment, the subdivided blocks of the first and second channels are interleaved if the first and second channels are correspondingly subdivided.

20 In another embodiment, the subdivided blocks of the first and second channels are not interleaved if the first and second channels are not correlated with each other.

According to one embodiment, the first and second channels are subdivided independently and correspondingly according to a 25 subdivision hierarchy. The subdivision hierarchy has more than

one level, and each level is associated with a different block length. For example, a superordinate level of the subdivision hierarchy is associated with a block length double a block length associated with a subordinate level.

5 In one embodiment, if a channel has a length of  $N$ , then the channel is subdivided into the plurality of blocks such that each block has a length of one of  $N/2$ ,  $N/4$ ,  $N/8$ ,  $N/16$  and  $N/32$ . In one embodiment, information is generated such that a length of the information depends on a number of levels in the 10 subdivision hierarchy. For example, the information may be generated such that the information includes a number of information bits, and the information bits indicate the subdivision of a channel into the blocks. More specifically, each information bit may be associated with a level in the 15 subdivision hierarchy and may be associated with a block at the associated level, and each information bit indicates whether the associated block was subdivided.

In one embodiment, the method further includes predicting current data samples in the channel based on previous data 20 samples. The number of the previous data samples used in the predicting is referred to as the prediction order. A residual of the current data samples is obtained based on the predicted data samples.

25 In one embodiment, the prediction is performed by progressively increasing the prediction order to a desired

prediction order as previous data samples become available.

For example, this progressive prediction process may be performed for random access frames, which are frames to be encoded such that previous frames are not necessary to decode

5 the frame.

In another embodiment, the desired prediction order for each block is determined based on a maximum permitted prediction order and a length of the block.

In another embodiment of the method of processing an audio

10 signal, lengths of blocks into which each of a plurality of channels in an audio data frame is divided are independently switched if the plurality of channels are not correlated with each other. Furthermore, the lengths of blocks into which the plurality of channels in the frame are divided are switched

15 such that the block lengths of each channel are switched to a same length at a same time if the plurality of channels are correlated with each other. Accordingly, the channels are each divided into a plurality of blocks, and at least two of the blocks in each channel have different block lengths.

20 The present invention further relates to methods and apparatuses for encoding an audio signal, and to methods and apparatuses for decoding an audio signal.

#### BRIEF DESCRIPTION OF THE DRAWINGS

25 The accompanying drawings, which are included to provide a

further understanding of the invention and are incorporated in and constitute a part of this application, illustrate embodiment(s) of the invention and together with the description serve to explain the principle of the invention.

5 In the drawings:

FIG. 1 is an example illustration of an encoder according to an embodiment of the present invention.

FIG. 2 is an example illustration of a decoder according to an embodiment of the present invention.

10 FIG. 3 is an example illustration of a bitstream structure of a compressed  $M$ -channel file according to an embodiment of the present invention.

FIG. 4 is an example illustration of a conceptual view of a hierarchical block switching method according to an embodiment 15 of the present invention.

FIG. 5 is an example illustration of a block switching examples and corresponding block switching information codes.

FIG. 6 is an example illustration of block switching methods for a plurality of channel according to embodiments of the 20 present invention.

#### DETAILED DESCRIPTION OF EXAMPLE EMBODIMENTS

Reference will now be made in detail to the preferred 25 embodiments of the present invention, examples of which are

illustrated in the accompanying drawings. Wherever possible, the same reference numbers will be used throughout the drawings to refer to the same or like parts.

Prior to describing the present invention, it should be noted

5 that most terms disclosed in the present invention correspond to general terms well known in the art, but some terms have been selected by the applicant as necessary and will hereinafter be disclosed in the following description of the present invention. Therefore, it is preferable that the terms  
10 defined by the applicant be understood on the basis of their meanings in the present invention.

In a lossless audio coding method, since the encoding process has to be perfectly reversible without loss of information, several parts of both encoder and decoder have to be  
15 implemented in a deterministic way.

#### Codec Structure

FIG. 1 is an example illustration of an encoder 1 according to the present invention.

20 A partitioning part 100 partitions the input audio data into frames. Within one frame, each channel may be further subdivided into blocks of audio samples for further processing. A buffer 110 stores block and/or frame samples partitioned by the partitioning part 100.

25 A coefficient estimating part 120 estimates an optimum set of

coefficient values for each block. The number of coefficients, i.e., the order of the predictor, can be adaptively chosen as well. The coefficient estimating part 120 calculates a set of parcor values for the block of digital audio data. The parcor 5 value indicates parcor representation of the predictor coefficient. A quantizing part 130 quantizes the set of parcor values.

A first entropy coding part 140 calculates parcor residual values by subtracting an offset value from the parcor value, 10 and encodes the parcor residual values using entropy codes defined by entropy parameters, wherein the offset value and the entropy parameters are chosen from an optimal table. The optimal table is selected from a plurality of tables based on a sampling rate of the block of digital audio data. The 15 plurality of tables are predefined for a plurality of sampling rate ranges, respectively, for optimal compression of the digital audio data for transmission.

A coefficient converting part 150 converts the quantized parcor values into linear predictive coding (LPC) coefficients. 20 A predictor 160 estimates current prediction values from the previous original samples stored in the buffer 110 using the linear predictive coding coefficients. A subtracter 170 calculates a prediction residual of the block of digital audio data using an original value of digital audio data stored in 25 the buffer 110 and a prediction value estimated in the

predictor 160.

A second entropy coding part 180 codes the prediction residual using different entropy codes and generates code indices. The indices of the chosen codes will be transmitted as auxiliary

5 information. The second entropy coding part 180 may code the prediction residual using one of two alternative coding techniques having different complexities. One coding

technique is the well-known Golomb-Rice coding (herein after simply "Rice code") method and the other is the well-known

10 Block Gilbert-Moore Codes (herein after simply "BGMC") method.

Rice codes have low complexity yet are efficient. The BGMC arithmetic coding scheme offers even better compression at the expense of a slightly increased complexity compared to Rice codes.

15 Finally, a multiplexing part 190 multiplexes coded prediction residual, code indices, coded parcor residual values, and other additional information to form a compressed bitstream.

The encoder 1 also provides a cyclic redundancy check (CRC) checksum, which is supplied mainly for the decoder to verify

20 the decoded data. On the encoder side, the CRC can be used to ensure that the compressed data are losslessly decodable.

Additional encoding options include flexible block switching scheme, random access and joint channel coding. The encoder 1 may use these options to offer several compression levels with 25 different complexities. The joint channel coding is used to

exploit dependencies between channels of stereo or multi-channel signals. This can be achieved by coding the difference between two channels in the segments where this difference can be coded more efficiently than one of the 5 original channels. These encoding options will be described in more detail below after a description of an example decoder according to the present invention.

FIG. 2 is an example illustration of a decoder 2 according to the present invention. More specially, FIG. 2 shows the 10 lossless audio signal decoder which is significantly less complex than the encoder, since no adaptation has to be carried out.

A demultiplexing part 200 receives an audio signal and demultiplexes a coded prediction residual of a block of 15 digital audio data, code indices, coded parcor residual values and other additional information. A first entropy decoding part 210 decodes the parcor residual values using entropy codes defined by entropy parameters and calculates a set of parcor values by adding offset values to the decoded parcor 20 residual values; wherein the offset value and the entropy parameters are chosen from a table selected by the decoder from a plurality of tables based on a sampling rate of the block of digital audio data. A second entropy decoding part 220 decodes the demultiplexed coded prediction residual using 25 the code indices. A coefficient converting part 230 converts

the entropy decoded parcor value into LPC coefficients. A predictor 240 estimates a prediction residual of the block of digital audio data using the LPC coefficients. An adder 250 adds the decoded prediction residual to the estimated prediction residual to obtain the original block of digital audio data. An assembling part 260 assembles the decoded block data into frame data.

Therefore, the decoder 2 decodes the coded prediction residual and the parcor residual values, converts the parcor residual

values into LPC coefficients, and applies the inverse prediction filter to calculate the lossless reconstruction signal. The computational effort of the decoder 2 depends on the prediction orders chosen by the encoder 1. In most cases, real-time decoding is possible even on low-end systems.

15 FIG. 3 is an example illustration of a bitstream structure of a compressed audio signal including a plurality of channels (e.g., M channels) according to the present invention.

The bitstream consists of at least one audio frame including a plurality of channels (e.g., M channels). The "channels"

20 field in the bitstream configuration syntax (see Table 6 below) indicates the number of channels. Each channel is sub-divided into a plurality of blocks using the block switching scheme according to present invention, which will be described in detail later. Each sub-divided block has a different size  
25 and includes coding data according to the encoding of FIG.1.

For example, the coding data within a subdivided block contains the code indices, the prediction order  $K$ , the predictor coefficients, and the coded residual values. If joint coding between channel pairs is used, the block 5 partition is identical for both channels, and blocks are stored in an interleaved fashion. A "js\_stereo" field in the bitstream configuration syntax (Table 6) indicates whether joint stereo (channel difference) is on or off, and a "js\_switch" field in the frame\_data syntax (See Table 7 below) 10 indicates whether joint stereo (channel difference) is selected. Otherwise, the block partition for each channel is independent.

Hereinafter, the block switching, random access, prediction, and entropy coding options previously mentioned will now be 15 described in detail with reference to the accompanying drawings and syntaxes that follow.

### **Block Switching**

An aspect of the present invention relates to subdividing each 20 channel into a plurality of blocks prior to using the actual coding scheme. Hereinafter, the block partitioning (or subdividing) method according to the present invention will be referred to as a "block switching method".

### **25 Hierarchical Block Switching**

FIG. 4 is an example illustration of a conceptual view of a hierarchical block switching method according to the present invention. For example, FIG. 4 illustrates a method of hierarchically subdividing one channel into 32 blocks. When a plurality of channels is provided in a single frame, each channel may be subdivided (or partitioned) to up to 32 blocks, and the subdivided blocks for each channel configure a frame. Accordingly, the block switching method according to the present invention is performed by the partitioning part 100 shown in FIG. 1. Furthermore, as described above, the prediction and entropy coding are performed on the subdivided block units.

In general, conventional Audio Lossless Coding (ALS) includes a relatively simple block switching mechanism. Each channel of  $N$  samples is either encoded using one full length block ( $N_B = N$ ) or four blocks of length  $N_B = N/4$  (e.g., 1:4 switching), where the same block partition applies to all channels. Under some circumstances, this scheme may have some limitations. For example, while only 1:1 or 1:4 switching may be possible, different switching (e.g., 1:2, 1:8, and combinations thereof) may be more efficient in some cases. Also in conventional ALS, switching is performed identically for all channels, although different channels may benefit from different switching (which is especially true if the channels are not correlated).

Therefore, the block switching method according to embodiments of the present invention provide relatively flexible block switching schemes, where each channel of a frame may be hierarchically subdivided into a plurality of blocks. For example, FIG. 4 illustrates a channel which can be hierarchically subdivided to up to 32 blocks. Arbitrary combinations of blocks with  $N_B = N, N/2, N/4, N/8, N/16$ , and  $N/32$  may be possible within a channel according to the presented embodiments, as long as each block results from a subdivision of a superordinate block of double length. For example, as illustrated in the example shown in FIG. 4, a partition into  $N/4 + N/4 + N/2$  may be possible, while a partition into  $N/4 + N/2 + N/4$  may not be possible (e.g., block switching examples shown in FIGs. 5(e) and 5 described below). Stated another way, the channel is divided into the plurality of blocks such that each block has a length equal to one of,

$$N/(m^i) \quad \text{for } i = 1, 2, \dots p,$$

20

where  $N$  is the length of the channel,  $m$  is an integer greater than or equal to 2, and  $p$  represents a number of the levels in the subdivision hierarchy.

Accordingly, in embodiments of the present invention, a bitstream includes information indicating block switching

levels and information indicating block switching results.

Herein, the information related to block switching is included in the syntax, which is used in the decoding process, described in detail below.

5 For example, settings are made so that a minimum block size generated after the block switching process is  $N_B = N/32$ . However, this setting is only an example for simplifying the description of the present invention. Therefore, settings according to the present invention are not limited to this  
10 setting.

More specifically, when the minimum block size is  $N_B = N/32$ , this indicates that the block switching process has been hierarchically performed 5 times, which is referred to as a level 5 block switching. Alternatively, when the minimum  
15 block size is  $N_B = N/16$ , this indicates that the block switching process has been hierarchically performed 4 times, which is referred to as a level 4 block switching. Similarly, when the minimum block size is  $N_B = N/8$ , the block switching process has been hierarchically performed 3 times, which is  
20 referred to as a level 3 block switching. And, when the minimum block size is  $N_B = N/4$ , the block switching process has been hierarchically performed 2 times, which is referred to as a level 2 block switching. When the minimum block size is  $N_B = N/2$ , the block switching process has been hierarchically

performed 1 time, which is referred to as a level 1 block switching. Finally, when the minimum block size is  $N_B = N$ , the hierarchical block switching process has not been performed, which is referred to as a level 0 block switching.

5 In embodiments of the present invention, the information indicating the block switching level will be referred to as a first block switching information. For example, the first block switching information may be represented by a 2-bit "block\_switching" field within the syntax shown in Table 6, 10 which will be described in a later process. More specifically, "block\_switching = 00" signifies level 0, "block\_switching = 01" signifies any one of level 1 to level 3, "block\_switching = 10" signifies level 4, and "block\_switching = 11" signifies level 5.

15 Additionally, information indicating the results of the block switching performed for each hierarchical level in accordance with the above-described block switching levels is referred to in the embodiments as second block switching information. Herein, the second block switching information may be 20 represented by a "bs\_info" field which is expressed by any one of 8 bits, 16 bits, and 32 bits within the syntax shown in Table 7. More specifically, if "block\_switching = 01" (signifying any one of level 1 to level 3), "bs\_info" is expressed as 8 bits. If "block\_switching = 10" (signifying level 4), "bs\_info" is expressed as 16 bits. In other words,

up to 4 levels of block switching results may be indicated by using 16 bits. Furthermore, if "block\_switching = 11" (signifying level 5, "bs\_info" is expressed as 32 bits. In other words, up to 5 levels of block switching results may be 5 indicated by using 32 bits. Finally, if "block\_switching = 00" (signifying that the block switching has not been performed), "bs\_info" is not transmitted. This signifies that one channel configures one block.

The total number of bits being allocated for the second block 10 switching information is decided based upon the level value of the first block switching information. This may result in reducing the final bit rate. The relation between the first block switching information and the second block switching information is briefly described in Table 1 below.

15

Table 1: Block switching levels.

Maximum #levels	Minimum $N_B$	#Bytes for "bs_info"
0 ("block_switching =00")	N	0
1 ("block_switching =01")	N/2	1 (=8bits)
2 ("block_switching =01")	N/4	1 (=8bits)
3 ("block_switching =01")	N/8	1 (=8bits)
4 ("block_switching =10")	N/16	2 (=16bits)

5 ("block_switching =11")	N/32	4 (=32bits)
---------------------------------	------	-------------

Hereinafter, an embodiment of a method of configuring (or mapping) each bit within the second block switching information (bs\_info) will now be described in detail.

5 The bs\_info field may include up to 4 bytes in accordance with the above-described embodiments. The mapping of bits with respect to levels 1 to 5 may be [(0)1223333 44444444 55555555 55555555]. The first bit may be reserved for indicating independent or synchronous block switching, which is described

10 in more detail below in the Independent/Synchronous Block Switching section. FIGS. 5(a)-5(f) illustrate different block switching examples for a channel where level 3 block switching may take place. Therefore, in these examples, the minimum block length is  $N_B = N/8$ , and the bs\_info consists of one byte.

15 Starting from the maximum block length  $N_B = N$ , the bits of bs\_info are set if a block is further subdivided. For example, in FIG. 5(a), there is no subdivision at all, thus "bs\_info" is (0)000 0000. In FIG. 5(b), the frame is subdivided ((0)1...) and the second block of length  $N/2$  is further split ((0)101...) into two blocks of length  $N/4$ ; thus "bs\_info" is (0)1010 0000.

20 In FIG. 5(c), the frame is subdivided ((0)1...), and only the first block of length  $N/2$  is further split ((0)110...) into two blocks of length  $N/4$ ; thus "bs\_info" is (0)1100 0000. In FIG.

5 (d), the frame is subdivided ((0)1...), the first and second blocks of length  $N/2$  is further split ((0)111...) into two blocks of length  $N/4$ , and only the second block of length  $N/4$  is further split ((0)11101...) into two blocks of length  $N/8$ ;  
5 thus "bs\_info" is (0)111 0100.

As discussed above, the examples in FIGs. 5(e) and 5(f) represent cases of block switching that are not permitted because the  $N/2$  block in FIG. 5(e) and the first  $N/4$  block in FIG. 5(f) could not have been obtained by subdividing a block  
10 of the previous level.

#### Independent / Synchronous Block Switching

FIGs. 6(a) - 6(c) are example illustrations of block switching according to embodiments of the present invention.

15 More specifically, FIG. 6(a) illustrates an example where block switching has not been performed for channels 1, 2, and 3. FIG. 6(b) illustrates an example in which two channels (channels 1 and 2) configure one channel pair, and block switching is performed synchronously in channels 1 and 2.  
20 Interleaving is also applied in this example. FIG. 6(c) illustrates an example in which two channels (channels 1 and 2) configure one channel pair, and the block switching of channels 1 and 2 is performed independently. Herein, the channel pair refers to two arbitrary audio channels. The  
25 decision on which channels are grouped into channel pairs can

be made automatically by the encoder or manually by the user.

(e.g., L and R channels, Ls and Rs channels).

In independent block switching, while the length of each channel may be identical for all channels, the block switching can be performed individually for each channel. Namely, as shown in FIG. 6(c), the channels may be divided into blocks differently. If the two channels of a channel pair are correlated with each other and difference coding is used, both channels of a channel pair may be block switched synchronously.

10 In synchronous block switching, the channels are block switched (i.e., divided into blocks) in the same manner. FIG. 6(b) illustrates an example of this, and further illustrates that the blocks may be interleaved. If the two channels of a channel pair are not correlated with each other, difference 15 coding may not provide a benefit, and thus there will be no need to block switch the channels synchronously. Instead, it may be more appropriate to switch the channels independently.

Furthermore, according to another embodiment of the present invention, the described method of independent or synchronous

20 block switching may be applied to a multi-channel group having a number of channels equal to or more than 3 channels. For example, if all channels of a multi-channel group are correlated with each other, all channels of a multi-channel group may be switched synchronously. On the other hand, if all 25 channels of a multi-channel group are not correlated with each

other, each channel of the multi-channel group may be switched independently.

Moreover, the "bs\_info" field is used as the information for indicating the block switching result. Additionally, the

5 "bs\_info" field is also used as the information for indicating whether block switching has been performed independently or performed synchronously for each channel configuring the channel pair. In this case, as described above, a particular bit (e.g., first bit) within the "bs\_info" field may be used.

10 If, for example, the two channels of the channel pair are independent from one another, the first bit of the "bs\_info" field is set to "1". On the other hand, if the two channels of the channel pair are synchronous to one another, the first bit of the "bs\_info" field is set as "0".

15 Hereinafter, FIGs. 6(a), 6(b), and 6(c) will now be described in detail.

Referring to FIG. 6(a), since none of the channels perform block switching, the related "bs\_info" is not generated.

Referring to FIG. 6(b), channels 1 and 2 configure a channel 20 pair, wherein the two channels are synchronous to one another, and wherein block switching is performed synchronously. For example, in FIG. 6(b), both channels 1 and 2 are split into blocks of length N/4, both having the same bs\_info "bs\_info = (0)101 0000". Therefore, one "bs\_info" may be transmitted for 25 each channel pair, which results in reducing the bit rate.

Furthermore, if the channel pair is synchronous, each block within the channel pair may be required to be interleaved with one another. The interleaving may be beneficial (or advantageous). For example, a block of one channel (e.g., 5 block 1.2 in FIG. 6(b)) within a channel pair may depend on previous blocks from both channels (e.g., blocks 1.1 and 2.1 in FIG. 6(b)), and so these previous blocks should be available prior to the current one.

Referring to FIG. 6(c), channels 1 and 2 configure a channel 10 pair. However, in this example, block switching is performed independently. More specifically, channel 1 is split into blocks of a size (or length) of up to  $N/4$  and has a `bs_info` of "bs\_info = (1)101 0000". Channel 2 is split into blocks of a size of up to  $N/2$  and has a `bs_info` of "bs\_info = (1)100 0000". 15 In the example shown in FIG. 6(c), block switching is performed independently among each channel, and therefore, the interleaving process between the blocks is not performed. In other words, for the channel having the blocks switched independently, channel data may be arranged separately.

20

#### **Joint Channel Coding**

Joint channel coding, also called joint stereo, can be used to 25 exploit dependencies between two channels of a stereo signal, or between any two channels of a multi-channel signal. While it is straightforward to process two channels  $x_1(n)$  and  $x_2(n)$

independently, a simple method of exploiting dependencies between the channels is to encode the difference signal:

$$d(n) = x_2(n) - x_1(n)$$

5

instead of  $x_1(n)$  or  $x_2(n)$ . Switching between  $x_1(n)$ ,  $x_2(n)$  and  $d(n)$  in each block may be carried out by comparison of the individual signals, depending on which two signals can be coded most efficiently. Such prediction with switched difference coding is advantageous in cases where two channels are very similar to one another. In case of multi-channel material, the channels can be rearranged by the encoder in order to assign suitable channel pairs.

10

Besides simple difference coding, lossless audio codec also supports a more complex scheme for exploiting inter-channel redundancy between arbitrary channels of multi-channel signals.

#### **Random Access**

The present invention relates to audio lossless coding and is able to support random access. Random access stands for fast access to any part of the encoded audio signal without costly decoding of previous parts. It is an important feature for applications that employ seeking, editing, or streaming of the compressed data. In order to enable random access, within a

random access unit, the encoder needs to insert a frame that can be decoded without decoding previous frames. The inserted frame is referred to as a "random access frame". In such a random access frame, no samples from previous frames may be 5 used for prediction.

Hereinafter, the information for random access according to the present invention will be described in detail. Referring to the configuration syntax (shown in Table 6), information related with random access are transmitted as configuration 10 information. For example, a "random\_access" field is used as information for indicating whether random access is allowed, which may be represented by using 8 bits. Furthermore, if random access is allowed, the 8-bit "random\_access" field designates the number of frames configuring a random access 15 unit. For example, when "random\_access = 0000 0000", the random access is not supported. In other words, when "random\_access > 0", random access is supported. More specifically, when "random\_access = 0000 0001", this indicates that the number of frames configuring the random access unit 20 is 1. This signifies that random access is allowed in all frame units. Furthermore, when "random\_access = 1111 1111", this indicates that the number of frames configuring the random access unit is 255. Accordingly, the "random\_access" information corresponds to a distance between a random access 25 frame within the current random access unit and a random

access frame within the next random access unit. Herein, the distance is expressed by the number of frames.

A 32-bit "ra\_unit\_size" field is included in the bitstream and transmitted. Herein, the "ra\_unit\_size" field indicates the

5 size from the current random access frame to the next random access frame in byte units. Accordingly, the "ra\_unit\_size" field is either included in the configuration syntax (Table 6)

or included in the frame-data syntax (Table 7). The configuration syntax (Table 6) may further include information

10 indicating a location where the "ra\_unit\_size" information is stored within the bitstream. This information is represented

as a 2-bit "ra\_flag" field. More specifically, for example, when "ra\_flag = 00", this indicates that the "ra\_unit\_size"

information is not stored in the bitstream. When the "ra\_flag = 01", this indicated that the "ra\_unit\_size" information is

15 stored in the frame-data syntax (Table 7) within the bitstream.

Furthermore, when the "ra\_flag = 10", the "ra\_unit\_size" information is stored in the configuration syntax (Table 6)

information is stored in the configuration syntax (Table 6) within the bitstream. If the "ra\_unit\_size" information is

20 included in the configuration syntax, this indicates that the "ra\_unit\_size" information is transmitted on the bitstream

only one time and is applied equally to all random access units. Alternatively, if the "ra\_unit\_size" information is

included in the frame-data syntax, this indicates the distance

25 between the random access frame within the current random

access unit and the random access frame within the next random access unit. Therefore, the "ra\_unit\_size" information is transmitted for each random access unit within the bitstream. Accordingly, the "random\_access" field within the configuration syntax (Table 6) may also be referred to as first general information. And, the "ra\_flag" field may also be referred to as second general information. In this aspect of the present invention, an audio signal includes configuration information and a plurality of random access units, each random access unit containing one or more audio data frames, one of which is a random access frame, wherein the configuration information includes first general information indicating a distance between two adjacent random access frames in frames, and second general information indicating where random access unit size information for each random access unit is stored. The random access unit size information indicating a distance between two adjacent random access frames in bytes.

Alternatively, in this aspect of the present invention, a method of decoding an audio signal includes receiving the audio signal having configuration information and a plurality of random access units, each random access unit containing one or more audio data frames, one of which is a random access frame, reading first general information from the configuration information, the first general information

indicating a distance between two adjacent random access frames in frames, and reading second general information from the configuration information, the second general information indicating where random access size information for each 5 random access unit is stored, and the random access unit size information indicating a distance between two adjacent random access frames in bytes.

#### Channel configuration

10 As shown in FIG. 3, an audio signal includes multi-channels information according to the present invention. For example, each channel may be mapped at a one-to-one correspondence with a location of an audio speaker. The configuration syntax (Table 6 below) includes channel configuration information, 15 which is indicated as a 16-bit "chan\_config\_info" field and a 16-bit "channels" field. The "chan\_config\_info" field includes information for mapping the channels to the loudspeaker locations and the 16-bit "channels" field includes information indicating the total number of channels. For example, when the 20 "channels" field is equal to "0", this indicates that the channel corresponds to a mono channel. When the "channels" field is equal to "1", this indicates that the channel corresponds to one of stereo channels. And, when the "channels" field is equal to or more than "2", this indicates 25 that the channel corresponds to one of multi-channels.

Table 2 below shows examples of each bit configuring the "chan\_config\_info" field and each respective channel corresponding thereto. More specifically, when a corresponding channel exists within the transmitted bitstream, 5 the corresponding bit within the "chan\_config\_info" field is set to "1". Alternatively, when a corresponding channel does not exist within the transmitted bitstream, the corresponding bit within the "chan\_config\_info" field is set to "0". The present invention also includes information indicating whether 10 the "chan\_config\_info" field exists within the configuration syntax (Table 6). This information is represented as a 1-bit "chan\_config" flag. More specifically, "chan\_config = 0" indicates that the "chan\_config\_info" field does not exist. And, "chan\_config = 1" indicates that the "chan\_config\_info" 15 field exists. Therefore, when "chan\_config = 0", this indicates that the "chan\_config\_info" field is not newly defined within the configuration syntax (Table 6).

**Table 2: Channel configuration.**

Speaker location	Abbreviation	Bit position in chan_config_info
Left	L	1
Right	R	2
Left Rear	Lr	3
Right Rear	Rr	4
Left Side	Ls	5
Right Side	Rs	6

Center	C	7
Center Rear / Surround	S	8
Low Frequency Effects	LFE	9
Left Downmix	L0	10
Right Downmix	R0	11
Mono Downmix	M	12
(reserved)		13-16

### Frame length

As shown in FIG. 3, an audio signal includes multiple or 5 multi-channels according to the present invention. Therefore, when performing encoding, information on the number of multi-channels configuring one frame and information on the number of samples for each channel are inserted in the bitstream and transmitted. Referring to the configuration syntax (Table 6), 10 a 32-bit "samples" field is used as information indicating the total number of audio data samples configuring each channel. Further, a 16-bit "frame\_length" field is used as information indicating the number of samples for each channel within the corresponding frame. 15 Furthermore, a 16-bit value of the "frame\_length" field is determined by a value used by the encoder, and is referred to as a user-defined value. In other words, instead of being a fixed value, the user-defined value is arbitrarily determined upon the encoding process.

Therefore, during the decoding process, when the bitstream is received through the demultiplexing part 200 of shown in FIG. 2, the frame number of each channel should first be obtained. This value is obtained according to the algorithm shown below.

5

```
frames = samples / frame_length;  
  
rest = samples % frame_length;  
  
if (rest)  
{  
  
10    frames++;  
  
     frlen_last = rest;  
  
}  
  
else  
  
15    frlen_last = frame_length;
```

15

More specifically, the total number of frames for each channel is calculated by dividing the total number of samples for each channel, which is decided by the "samples" field transmitted through the bitstream, by the number of samples within a frame 20 of each channel, which is decided by the "frame\_length" field. For example, when the total number of samples decided by the "samples" field is an exact multiple of the number of samples within each frame, which is decided by the "frame\_length" field, the multiple value becomes the total number of frames. 25 However, if the total number of samples decided by the

"samples" field is not an exact multiple of the number of samples decided by the "frame\_length" field, and a remainder (or rest) exist, the total number of frames increases by "1" more than the multiple value. Furthermore, the number of 5 samples of the last frame (frlen\_last) is decided as the remainder (or rest). This indicates that only the number of samples of the last frame is different from its previous frame. By defining a standardized rule between the encoder and the decoder, as described above, the encoder may freely decide and 10 transmit the total number of samples ("samples" field) for each channel and the number of samples("frame\_length" field) within a frame of each channel. Furthermore, the decoder may accurately decide, by using the above-described algorithm on the transmitted information, the number of frames for each 15 channel that is to be used for decoding.

#### Linear Prediction

In the present invention, linear prediction is applied for the lossless audio coding. The predictor 160 shown in FIG. 1 20 includes at least one or more filter coefficients so as to predict a current sample value from a previous sample value. Then, the second entropy coding part 180 performs entropy coding on a residual value corresponding to the difference between the predicted value and the original value. 25 Additionally, the predictor coefficient values for each block

that are applied to the predictor 160 are selected as optimum values from the coefficient estimating part 120. Further, the predictor coefficient values are entropy coded by the first entropy coding part 140. The data coded by the first entropy coding part 180 are inserted as part of the bitstream by the multiplexing part 190 and then transmitted.

Hereinafter, the method of performing linear prediction according to the present invention will now be described in detail.

#### Prediction with FIR Filters

Linear prediction is used in many applications for speech and audio signal processing. Hereinafter, an exemplary operation of the predictor 160 will be described based on Finite Impulse Response (FIR) filters. However, it is apparent that this example will not limit the scope of the present invention.

The current sample of a time-discrete signal  $x(n)$  can be approximately predicted from previous samples  $x(n-k)$ . The prediction is given by the following equation.

$$\hat{x}(n) = \sum_{k=1}^K h_k * x(n-k),$$

wherein  $K$  is the order of the predictor. If the

predicted samples are close to the original samples, the residual shown below:

$$e(n) = x(n) - \hat{x}(n)$$

5

has a smaller variance than  $x(n)$  itself, hence  $e(n)$  can be encoded more efficiently.

The procedure of estimating the predictor coefficients from a segment of input samples, prior to filtering that segment is 10 referred to as forward adaptation. In this case, the coefficients should be transmitted. On the other hand, if the coefficients are estimated from previously processed segments or samples, e.g., from the residual, reference is made to backward adaptation. The backward adaptation procedure has 15 the advantage that no transmission of the coefficients is needed, since the data required to estimate the coefficients is available to the decoder as well.

Forward-adaptive prediction methods with orders around 10 are widely used in speech coding, and can be employed for lossless 20 audio coding as well. The maximum order of most forward-adaptive lossless prediction schemes is still rather small, e.g.,  $K = 32$ . An exception is the special 1-bit lossless codec for the Super Audio CD, which uses prediction orders of up to 128.

25 On the other hand, backward-adaptive FIR filters with some

hundred coefficients are commonly used in many areas, e.g., channel equalization and echo cancellation. Most of these systems are based on the LMS algorithm or a variation thereof, which has also been proposed for lossless audio coding. Such 5 LMS-based coding schemes with high orders are applicable since the predictor coefficients do not have to be transmitted as side information, thus their number does not contribute to the data rate. However, backward-adaptive codecs have the drawback that the adaptation has to be carried out both in the 10 encoder and the decoder, making the decoder significantly more complex than in the forward-adaptive case.

#### **Forward-Adaptive Prediction**

As an exemplary embodiment of the present invention, forward 15 adaptive prediction will be given as an example in the description set forth herein. In forward-adaptive linear prediction, the optimal predictor coefficients  $h_k$  (in terms of a minimized variance of the residual) are usually estimated for each block by the coefficient estimating part 120 using 20 the autocorrelation method or the covariance method. The autocorrelation method, using the conventional Levinson-Durbin algorithm, has the additional advantage of providing a simple means to iteratively adapt the order of the predictor. Furthermore, the algorithm inherently calculates the 25 corresponding parcor coefficients as well.

Another aspect of forward-adaptive prediction is to determine a suitable prediction order. Increasing the order decreases the variance of the prediction error, which leads to a smaller bit rate  $R_e$  for the residual. On the other hand, the bit rate

5  $R_c$  for the predictor coefficients will rise with the number of coefficients to be transmitted. Thus, the task is to find the optimum order which minimizes the total bit rate. This can be expressed by minimizing the equation below:,

10 
$$R_{total}(K) = R_e(K) + R_c(K),$$

with respect to the prediction order  $K$ . As the prediction gain rises monotonically with higher orders,  $R_e$  decreases with  $K$ . On the other hand  $R_c$  rises monotonically with  $K$ , since an 15 increasing number of coefficients should be transmitted.

The search for the optimum order can be carried out efficiently by the coefficient estimating part 120, which determines recursively all predictors with increasing order. For each order, a complete set of predictor coefficients is 20 calculated. Moreover, the variance  $\sigma_e^2$  of the corresponding residual can be derived, resulting in an estimate of the expected bit rate for the residual. Together with the bit rate for the coefficients, the total bit rate can be determined in each iteration, i.e., for each prediction order.

The optimum order is found at the point where the total bit rate no longer decreases.

While it is obvious from the above equation that the coefficient bit rate has a direct effect on the total bit rate, a slower increase of  $R_e$  also allows to shift the minimum of  $R_{total}$  to higher orders (wherein  $R_e$  is smaller as well), which would lead to better compression. Hence, efficient yet accurate quantization of the predictor coefficients plays an important role in achieving maximum compression.

10

#### **Prediction orders**

In the present invention, the prediction order  $K$ , which decides the number of predictor coefficients for linear prediction, is determined. The prediction order  $K$  is also determined by the coefficient estimating part 120. Herein, information on the determined prediction order is included in the bitstream and then transmitted.

The configuration syntax (Table 6) includes information related to the prediction order  $K$ . For example, a 1-bit to 10-bit "max\_order" field corresponds to information indicating a maximum order value. The highest value of the 1-bit to 10-bit "max\_order" field is  $K=1023$  (e.g., 10-bit). As another information related to the prediction order  $K$ , the configuration syntax (Table 6) includes a 1-bit "adapt\_order" field, which indicates whether an optimum order for each block

exists. For example, when "adapt\_order = 1", an optimum order should be provided for each block. In a block\_data syntax (Table 8), the optimum order is provided as a 1-bit to 10-bit "opt\_order" field. Further, when "adapt\_order = 0", a separate optimum order is not provided for each block. In this case, the "max\_order" field becomes the final order applied to all of the blocks.

5 The optimum order (opt\_order) is decided based upon the value of max\_order field and the size ( $N_B$ ) of the corresponding 10 block. More specifically, for example, when the max\_order is decided as  $K_{max} = 10$  and "adapt\_order = 1", the opt\_order for each block may be decided considering the size of the corresponding block. In some case, the opt\_order value being larger than max\_order ( $K_{max} = 10$ ) is possible.

15 In particular, the present invention relates to higher prediction orders. In the absence of hierarchical block switching, there may be a factor of 4 between the long and the short block length (e.g. 4096 & 1024 or 8192 & 2048), in accordance with the embodiments. On the other hand, in the 20 embodiments where hierarchical block switching is implemented, this factor can be increased (e.g., up to 32), enabling a larger range (e.g., 16384 down to 512 or even 32768 to 1024 for high sampling rates).

25 In the embodiments where hierarchical block switching is implemented, in order to make better use of very long blocks,

higher maximum prediction orders may be employed. The maximum order may be  $K_{\max} = 1023$ . In the embodiments,  $K_{\max}$  may be bound by the block length  $N_B$ , for example,  $K_{\max} < N_B / 8$  (e.g.,  $K_{\max} = 255$  for  $N_B = 2048$ ). Therefore, using  $K_{\max} = 1023$  may require a 5 block length of at least  $N_B = 8192$ . In the embodiments, the "max\_order" field in the configuration syntax (Table 6) can be up to 10 bits and "opt\_order" field in the block\_data syntax (Table 8) can also be up to 10 bits. The actual number of bits in a particular block may depend on the maximum order 10 allowed for a block. If the block is short, a local prediction order may be smaller than a global prediction order. Herein, the local prediction order is determined from considering the corresponding block length  $N_B$ , and the global prediction order is determined from the "max\_order"  $K_{\max}$  in the 15 configuration syntax. For example, if  $K_{\max} = 1023$ , but  $N_B = 2048$ , the "opt\_order" field is determined on 8 bits (instead of 10) due to a local prediction order of 255. More specifically, the opt\_order may be determined based on the following equation:

20

```
opt_order = min (global prediction order, local prediction order);
```

And. the global and local prediction orders may be determined

by:

```
global prediction order = ceil(log2(maximum prediction
order +1))
```

5

```
local prediction order = max(ceil(log2((Nb>>3)-1)), 1)
```

In the embodiments, data samples of the subdivided block from a channel are predicted. A first sample of a current block is 10 predicted using the last K samples of a previous block. The K value is determined from the opt\_order which is derived from the above-described equation.

If the current block is a first block of the channel, no samples from the previous block are used. In this case, 15 prediction with progressive order is employed. For example, assuming that the opt\_order value is K=5 for a corresponding block, the first sample in the block does not perform prediction. The second sample of the block uses the first sample of the block to perform the prediction (as like K=1), 20 the third sample of the block uses the first and second samples of the block to perform the prediction (as like K=2), etc. Therefore, starting from the sixth sample and for samples thereafter, prediction is performed according to the opt\_order of K=5. As described above, the prediction order 25 increases progressively from K=1 to K=5.

The above-described progressive order type of prediction is very advantageous when used in the random access frame. Since the random access frame corresponds to a reference frame of the random access unit, the random access frame does not 5 perform prediction by using the previous frame sample. Namely, this progressive prediction technique may be applied at the beginning of the random access frame.

#### Quantization of Predictor Coefficients

10 The above-described predictor coefficients are quantized in the quantizing part 130 of FIG. 1. Direct quantization of the predictor coefficients  $h_k$  is not very efficient for transmission, since even small quantization errors may result 15 in large deviations from the desired spectral characteristics of the optimum prediction filter. For this reason, the quantization of predictor coefficients is based on the parcor (reflection) coefficients  $r_k$ , which can be calculated by the coefficient estimating part 120. As described above, for example, the coefficient estimating part 120 is processed 20 using the conventional Levinson-Durbin algorithm.

The first two parcor coefficients ( $\gamma_1$  and  $\gamma_2$  correspondingly) are quantized by using the following functions:

$$a_1 = \left\lfloor 64 \left( -1 + \sqrt{2} \sqrt{\gamma_1 + 1} \right) \right\rfloor;$$
$$a_2 = \left\lfloor 64 \left( -1 + \sqrt{2} \sqrt{-\gamma_2 + 1} \right) \right\rfloor;$$

while the remaining coefficients are quantized using simple 7-bit uniform quantizers:

$$a_k = \left\lfloor 64 \gamma_k \right\rfloor; \quad (k > 2).$$

5 In all cases the resulting quantized values  $a_k$  are restricted to the range  $[-64, 63]$ .

#### Entropy Coding

As shown in FIG. 1, two types of entropy coding are applied in 10 the present invention. More specifically, the first entropy coding part 140 is used for coding the above-described predictor coefficients. And, the second entropy coding part 180 is used for coding the above-described audio original samples and audio residual samples. Hereinafter, the two 15 types of entropy coding will now be described in detail.

#### First Entropy Coding of the predictor coefficient

The related art Rice code is used as the first entropy coding method according to the present invention. For example, 20 transmission of the quantized coefficients  $a_k$  is performed by producing residual values:

$$\delta_k = a_k - \text{offset}_k ,$$

which, in turn, are encoded by using the first entropy coding part 140, e.g., the Rice code method. The corresponding

5 offsets and parameters of Rice code used in this process can be globally chosen from one of the sets shown in Table 3, 4 and 5 below. A table index (i.e., a 2-bit "coef\_table") is indicated in the configuration syntax (Table 6). If "coef\_table = 11", this indicates that no entropy coding is 10 applied, and the quantized coefficients are transmitted with 7 bits each. In this case, the offset is always -64 in order to obtain unsigned values  $\delta_k = a_k + 64$  that are restricted to [0,127]. Conversely, if "coeff\_table = 00", Table 3 below is selected, and if "coeff\_table = 01", Table 4 below is selected. 15 Finally, if "coeff\_table = 11", Table 5 is selected.

When receiving the quantized coefficients in the decoder of FIG.2, the first entropy decoding part 220 reconstructs the predictor coefficients by using the process that the residual values  $\delta_k$  are combined with offsets to produce quantized

20 indices of parcor coefficients  $a_k$ :

$$a_k = \delta_k + \text{offset}_k .$$

Thereafter, the reconstruction of the first two coefficients

( $\gamma_1$  and  $\gamma_2$ ) is performed by using:

$$\text{par}_1 = \lfloor \hat{\gamma}_1 2^Q \rfloor = \Gamma(a_1);$$

$$\text{par}_2 = \lfloor \hat{\gamma}_2 2^Q \rfloor = -\Gamma(a_2);$$

wherein  $2^Q$  represents a constant ( $Q=20$ ) scale factor required

5 for integer representation of the reconstructed coefficients, and  $\Gamma()$  is an empirically determined mapping table (not shown as the mapping table may vary with implementation).

Accordingly, the three types of coefficient tables used for the first entropy coding are provided according to the 10 sampling frequency. For example, the sampling frequency may be divided to 48kHz, 96kHz, and 192kHz. Herein, each of the three Tables 3, 4, and 5 is respectively provided for each sampling frequency.

Instead of using a single table, one of three different 15 tables can be chosen for the entire file. The table should typically be chosen depending on the sampling rate. For material with 44.1 kHz, the applicant of the present invention recommends to use the 48 kHz table. However, in general, the table can also be chosen by other criteria.

20

Table 3: Rice code parameters used for encoding of quantized coefficients (48 kHz).

Coefficient #	Offset	Rice parameter
---------------	--------	----------------

1	-52	4
2	-29	5
3	-31	4
4	19	4
5	-16	4
6	12	3
7	-7	3
8	9	3
9	-5	3
10	6	3
11	-4	3
12	3	3
13	-3	2
14	3	2
15	-2	2
16	3	2
17	-1	2
18	2	2
19	-1	2
20	2	2
2k-1, k>10	0	2
2k, k>10	1	2

Table 4: Rice code parameters used for encoding of quantized coefficients (96 kHz).

Coefficient #	Offset	Rice parameter
1	-58	3
2	-42	4
3	-46	4
4	37	5
5	-36	4
6	29	4
7	-29	4
8	25	4
9	-23	4
10	20	4
11	-17	4
12	16	4
13	-12	4
14	12	3
15	-10	4
16	7	3
17	-4	4
18	3	3

19	-1	3
20	1	3
2k-1, k>10	0	2
2k, k>10	1	2

Table 5: Rice code parameters used for encoding of quantized coefficients (192 kHz).

Coefficient #	Offset	Rice parameter
1	-59	3
2	-45	5
3	-50	4
4	38	4
5	-39	4
6	32	4
7	-30	4
8	25	3
9	-23	3
10	20	3
11	-20	3
12	16	3
13	-13	3
14	10	3
15	-7	3
16	3	3
17	0	3
18	-1	3
19	2	3
20	-1	2
2k-1, k>10	0	2
2k, k>10	1	2

#### Second Entropy Coding of the Residual

The present invention contains two different modes of the coding method applied to the second entropy coding part 180 of FIG. 1, which will now be described in detail.

In the simple mode, the residual values  $e(n)$  are entropy coded

using Rice code. For each block, either all values can be encoded using the same Rice code, or the block can be further divided into four parts, each encoded with a different Rice code. The indices of the applied codes are transmitted, as 5 shown in FIG. 1. Since there are different ways to determine the optimal Rice code for a given set of data, it is up to the encoder to select suitable codes depending upon the statistics of the residual.

Alternatively, the encoder can use a more complex and 10 efficient coding scheme using BGMC mode. In the BGMC mode, the encoding of residuals is accomplished by splitting the distribution in two categories. The two types include residuals that belong to a central region of the distribution,  $|e(n)| < e_{\max}$ , and residuals that belong to its tails. The 15 residuals in tails are simply re-centered (i.e., for  $e(n) > e_{\max}$ ,  $e_r(n) = e(n) - e_{\max}$  is provided) and encoded using Rice code as described above. However, in order to encode residuals in the center of the distribution, the BGMC first splits the residuals into LSB and MSB components, then the BGMC encodes 20 MSBs using block Gilbert-Moore (arithmetic) codes. And finally, the BGMC transmits LSBs using direct fixed-lengths codes. Both parameters  $e_{\max}$  and the number of directly transmitted LSBs may be selected such that they only slightly affect the coding efficiency of this scheme, while allowing

the coding to be significantly less complex.

The configuration syntax (Table 6) and the block\_data syntax (Table 8) according to the present invention include information related to coding of the Rice code and BGMC code.

5 The information will now be described in detail

The configuration syntax (Table 6) first includes a 1-bit "bgmc\_mode" field. For example, "bgmc\_mode = 0" signifies the Rice code, and "bgmc\_mode = 1" signifies the BGMC code. The configuration syntax (Table 6) also includes a 1-bit "sb\_part"

10 field. The "sb\_part" field corresponds to information related to a method of partitioning a block to a sub-block and coding the partitioned sub-block. Herein, the meaning of the "sb\_part" field varies in accordance with the value of the "bgmc\_mode" field.

15 For example, when "bgmc\_mode = 0", in other words when the Rice code is applied, "sb\_part = 0" signifies that the block is not partitioned into sub-blocks. Alternatively, "sb\_part = 1" signifies that the block is partitioned at a 1:4 sub-block partition ratio. Additionally, when "bgmc\_mode = 1", in other words when the BGMC code is applied, "sb\_part = 0" signifies that the block is partitioned at a 1:4 sub-block partition ratio. Alternatively, "sb\_part = 1" signifies that the block is partitioned at a 1:2:4:8 sub-block partition ratio.

20 The block\_data syntax (Table 8) for each block corresponding to the information included in the configuration syntax (Table

6) includes 0-bit to 2-bit variable "ec\_sub" fields. More specifically, the "ec\_sub" field indicates the number of sub-blocks existing in the actual corresponding block. Herein, the meaning of the "ec\_sub" field varies in accordance with 5 the value of the "bgmc\_mode" + "sb\_part" fields within the configuration syntax (Table 6).

For example, "bgmc\_mode + sb\_part = 0" signifies that the Rice code does not configure the sub-block. Herein, the "ec\_sub" field is a 0-bit field, which signifies that no information is 10 included.

In addition, "bgmc\_mode + sb\_part = 1" signifies that the Rice code or the BGMC code is used to partition the block to sub-blocks at a 1:4 rate. Herein, only 1 bit is assigned to the "ec\_sub" field. For example, "ec\_sub = 0" indicates one sub-block (i.e., the block is not partitioned to sub-blocks), and "ec\_sub = 1" indicates that 4 sub-blocks are configured.

Furthermore, "bgmc\_mode + sb\_part = 2" signifies that the BGMC code is used to partition the block to sub-blocks at a 1:2:4:8 rate. Herein, 2 bits are assigned to the "ec\_sub" field. For 20 example, "ec\_sub = 00" indicates one sub-block (i.e., the block is not partitioned to sub-blocks), and, "ec\_sub = 01" indicates 2 sub-blocks. Also, "ec\_sub = 10" indicates 4 sub-blocks, and "ec\_sub = 11" indicates 8 sub-blocks.

The sub-blocks defined within each block as described above 25 are coded by second entropy coding part 180 using a difference

coding method. An example of using the Rice code will now be described. For each block of residual values, either all values can be encoded using the same Rice code, or, if the "sb\_part" field in the configuration syntax is set, the block 5 can be partitioned into 4 sub-blocks, each encoded sub-block having a different Rice code. In the latter case, the "ec\_sub" field in the block-data syntax (Table 8) indicates whether one or four blocks are used.

While the parameter  $s[i = 0]$  of the first sub-block is 10 directly transmitted with either 4 bits (resolution  $\leq 16$  bits) or 5 bits (resolution  $> 16$  bits), only the differences  $(s[i] - s[i-1])$  of following parameters  $s[i > 0]$  are transmitted. These differences are additionally encoded using appropriately chosen Rice codes again. In this case, the Rice code parameter 15 used for differences has the value of "0".

### Syntax

According to the embodiment of the present invention, the syntax of the various information included in the audio 20 bitstream are shown in the tables below. Table 6 shows a configuration syntax for audio lossless coding. The configuration syntax may form a header periodically placed in the bitstream, may form a header of each frame; etc. Table 7 shows a frame-data syntax, and Table 8 shows a block-data 25 syntax.

Table 6: Configuration syntax.

Syntax	Bits
ALSSpecificConfig()	
{	
samp_freq;	32
samples;	32
channels;	16
file_type;	3
resolution;	3
floating;	1
msb_first;	1
frame_length;	16
random_access;	8
ra_flag;	2
adapt_order;	1
coef_table;	2
long_term_prediction;	1
max_order;	10
block_switching;	2
bgmc_mode;	1
sb_part;	1
joint_stereo;	1
mc_coding;	1
chan_config;	1
chan_sort;	1
crc_enabled;	1
RLSLMS	1
(reserved)	6
if (chan_config) {	
chan_config_info;	16
}	
if (chan_sort) {	
for (c = 0; c < channels; c++)	
chan_pos[c];	8
}	
header_size;	16
trailer_size;	16
orig_header[];	head r_siz e * 8
orig_trailer[];	trail er_si ze * 8
if (crc_enabled) {	
crc;	32
}	
if ((ra_flag == 2) && (random_access > 0)) {	

50

```
    for (f = 0; f < (samples - 1  
frame_length) + 1; f++) {  
    ra_unit_size  
    }  
}  
}
```

32

Table 7: Frame\_data syntax.

Syntax	Bits
frame_data()	
{	
if ((ra_flag == 1) && (frame_id %	
random_access == 0)) {	32
ra_unit_size	
}	
if (mc_coding && joint_stereo) {	
js_switch;	1
byte_align;	
}	
if (!mc_coding    js_switch) {	
for (c = 0; c < channels; c++) {	
if (block_switching) {	
bs_info;	8,16,
}	32
if (independent_bs) {	
for (b = 0; b < blocks; b++) {	
block_data(c);	
}	
}	
else{	
for (b = 0; b < blocks; b++) {	
block_data(c);	
block_data(c+1);	
}	
c++;	
}	
}	
}	
else{	
if (block_switching) {	
bs_info;	8,16,
}	32
}	
for (b = 0; b < blocks; b++) {	
for (c = 0; c < channels; c++) {	
block_data(c);	
channel_data(c);	

<pre>         }     }     if (floating)     {         num_bytes_diff_float;         diff_float_data();     } } </pre>	32
---	----

Table 8: Block\_data syntax.

Syntax	Bits
<pre> block_data() {     block_type;     if (block_type == 0) {         const_block;         js_block;         (reserved)         if (const_block == 1) {             {                 if (resolution == 8) {                     const_val;                 }                 else if (resolution == 16) {                     const_val;                 }                 else if (resolution == 24) {                     const_val;                 }                 else {                     const_val;                 }             }         }         else {             js_block;             if ((bgmc_mode == 0) &amp;&amp; (sb_part == 0) {                 sub_blocks = 1;             }             else if ((bgmc_mode == 1) &amp;&amp; (sb_part ==1) {                 ec_sub;                 sub_blocks = 1 &lt;&lt; ec_sub;             }             else {                 ec_sub;             }         }     } } </pre>	1 1 1 5 8 16 24 32 1 2 1

```

    sub_blocks = (ec_sub == 1) ? 4 : 1;
}
if (bgmc_mode == 0) {
    for (k = 0; k < sub_blocks; k++) {
        s[k];
    }
}
else {
    for (k = 0; k < sub_blocks; k++) {
        s[k], sx[k];
    }
}
sb_length = block_length / sub_blocks;
shift_lsbs;
if (shift_lsbs == 1) {
    shift_pos;
}
if (!RLSLMS) {
    if (adapt_order == 1) {
        opt_order;
    }
    for (p = 0; p < opt_order; p++) {
        quant_cof[p];
    }
}
}

```

varies  
varies  
1  
4  
1...10  
varies

### Compression Results

In the following, the lossless audio codec is compared with  
 5 two of the most popular programs for lossless audio  
 compression: the open-source codec FLAC and the Monkey's Audio  
 (MAC 3.97). Herein, the open-source codec FLAC uses forward-  
 adaptive prediction, and the Monkey's Audio (MAC 3.97) is a  
 backward-adaptive codec used as the current state-of-the-art  
 10 algorithm in terms of compression. Both codecs were run with  
 options providing maximum compression (i.e., flac -8 and mac-

c4000). The results for the encoder are determined for a medium compression level (with the prediction order restricted to  $K = 60$ ) and a maximum compression level ( $K = 1023$ ), both with random access of 500 ms. The tests were conducted on a 5 1.7 GHz Pentium-M system, with 1024 MB of memory. The test comprises nearly 1 GB of stereo waveform data with sampling rates of 48, 96, and 192 kHz, and resolutions of 16 and 24 bits.

#### 10 **Compression Ratio**

In the following, the compression ratio is defined as:

$$C = \frac{\text{CompressedFileSize}}{\text{OriginalFileSize}} * 100\%,$$

15 wherein smaller values indicate better compression. The results for the examined audio formats are shown in Table 9 (192 kHz material is not supported by the FLAC codec).

20 **Table 9: Comparison of average compression ratios for different audio formats (kHz/bits).**

Format	FLAC	MAC	ALS medium	ALS maximum
48/16	48.6	45.3	45.5	44.7
48/24	68.4	63.2	63.3	62.7
96/24	56.7	48.1	46.5	46.2

192/24	-	39.1	37.7	37.6
Total	-	48.9	48.3	47.8

The results show that ALS at maximum level outperforms both FLAC and Monkey's Audio for all formats, but particularly for high-definition material (i.e., 96 kHz / 24-bit and above).

5 Even at medium level, ALS delivers the best overall compression.

### Complexity

The complexity of different codecs strongly depends on the 10 actual implementation, particularly that of the encoder. As mentioned above, the audio signal encoder of the present invention is an ongoing development. Thus, we restrict our analysis to the decoder, a simple C code implementation with no further optimizations. The compressed data were generated 15 by the currently best encoder implementation. The average CPU load for real-time decoding of various audio formats, encoded at different complexity levels, is shown in Table 10. Even for maximum complexity, the CPU load of the decoder is only around 20-25%, which in return means that file based decoding 20 is at least 4 to 5 times faster than real-time.

Table 10 : Average CPU load (percentage on a 1.7 GHz Pentium-M), depending on audio format (kHz/bits) and ALS

encoder complexity.

Format	ALS low	ALS medium	ALS maximum
48/16	1.6	4.9	18.7
48/24	1.8	5.8	19.6
96/24	3.6	12.0	23.8
192/24	6.7	22.8	26.7

The codec is designed to offer a large range of complexity levels. While the maximum level achieves the highest compression at the expense of slowest encoding and decoding speed, the faster medium level only slightly degrades compression, but decoding is significantly less complex than for the maximum level (i.e., approximately 5% CPU load for 48 kHz material). Using a low-complexity level (i.e.,  $K \leq 15$ , Rice coding) degrades compression by only 1 to 1.5% compared to the medium level, but the decoder complexity is further reduced by a factor of three (i.e., less than 2% CPU load for 48 kHz material). Thus, audio data can be decoded even on hardware with very low computing power.

While the encoder complexity may be increased by both higher maximum orders and a more elaborate block switching algorithm (in accordance with the embodiments), the decoder may be affected by a higher average prediction order.

The foregoing embodiments (e.g., hierarchical block switching) and advantages are merely examples and are not to be construed as limiting the appended claims. The above teachings can be

applied to other apparatuses and methods, as would be appreciated by one of ordinary skill in the art. Many alternatives, modifications, and variations will be apparent to those skilled in the art.

5

#### Industrial Applicability

It will be apparent to those skilled in the art that various modifications and variations can be made in the present invention without departing from the spirit or scope of the invention. For example, aspects and embodiments of the present invention can be readily adopted in another audio signal codec like the lossy audio signal codec. Thus, it is intended that the present invention covers the modifications and variations of this invention.

15

## [CLAIMS]

1. A method of processing an audio signal, the method comprising:

5       independently subdividing at least first and second channels in a frame of the audio signal into blocks if the first and second channels are not correlated with each other, at least two of the blocks having different block lengths;

10      correspondingly subdividing the first and second channels into blocks such that the lengths of the blocks into which the second channel is subdivided correspond to the lengths of the blocks into which the first channel is subdivided if the first and second channels are correlated with each other, at least two of the blocks having different block lengths.

15      2. The method of claim 1, further comprising:

20      interleaving the subdivided blocks of the first and second channels if the first and second channels are correspondingly subdivided.

25      3. The method of claim 2, wherein the independently and correspondingly subdividing steps subdivide the first and second channels according to a subdivision hierarchy, the

subdivision hierarchy has more than one level, and each level is associated with a different block length.

4. The method of claim 3, wherein a superordinate level of the subdivision hierarchy is associated with a block length double a block length associated with a subordinate level.

5. The method of claim 3, wherein the independently and correspondingly subdividing steps subdivide a block of the superordinate level to obtain two blocks at the subordinate level.

6. The method of claim 3, wherein if the first and second channels have a length of  $N$ , then the independently and correspondingly subdividing steps subdivide the first and second channel into the plurality of blocks such that each block has a length of one of  $N/2$ ,  $N/4$ ,  $N/8$ ,  $N/16$  and  $N/32$ .

7. The method of claim 3, further comprising:  
20 generating information indicating the subdivision of the first and second channels into the blocks.

8. The method of claim 7, wherein the generating step generates the information such that a length of the information depends on a number of levels in the subdivision

hierarchy.

9. The method of claim 7, wherein the generating step generates the information such that the information includes a

5 number of information bits, and the information bits indicate the subdivision of the first and second channels into the blocks.

10. The method of claim 9, wherein each information bit is

10 associated with a level in the subdivision hierarchy and is associated with a block at the associated level, and each information bit indicates whether the associated block was subdivided.

15 11. The method of claim 10, wherein if the information bit has a value of 1, then the associated block is subdivided, and if the information bit has a value of 0, then the associated block is not subdivided.

20 12. The method of claim 2, further comprising:

sending the information.

13. The method of claim 2, further comprising:

predicting current data samples in the first and second  
25 channels based on previous data samples, a number of the

previous data samples used in the predicting step being the prediction order; and

obtaining a residual of the current data samples based on the predicted data samples.

5

14. The method of claim 13, wherein the predicting step progressively increases the prediction order to a desired prediction order as previous data samples become available.

10 15. The method of claim 14, wherein

the prediction order for an initial data sample having no previous data samples is zero, and the predicting step generates zero as the predicted initial data sample; and the obtaining step effectively does not change the

15 initial data sample as a result of the predicted initial data sample being zero.

16. The method of claim 14, further comprising:

determining the desired prediction order for each block

20 based on a maximum permitted prediction order and a length of the block.

17. The method of claim 13, further comprising:

determining an optimum prediction order for each block

25 based on a maximum permitted prediction order and a length of

the block.

18. The method of claim 17, wherein the determining step comprises:

5 determining a global prediction order based on the maximum permitted prediction order;

determining a local prediction order based on the length of the block; and

selecting a minimum one of the global prediction order 10 and the local prediction order as the optimum prediction order.

19. The method of claim 13, wherein if the frame is a random access frame, which is a frame to be encoded such that previous frames are not necessary to decode the frame,

15 the predicting step progressively increases the prediction order to a desired prediction order as previous data samples from only the random access frame become available.

20 20. The method of claim 1, wherein the subdivided blocks of the first and second channels are not interleaved if the first and second channels are not correlated with each other.

21. The method of claim 20, wherein the independently and 25 correspondingly subdividing steps subdivide the first and

second channels according to a subdivision hierarchy, the subdivision hierarchy has more than one level, and each level is associated with a different block length.

5 22. The method of claim 21, wherein a superordinate level of the subdivision hierarchy is associated with a block length double a block length associated with a subordinate level.

10 23. The method of claim 21, wherein the independently and correspondingly subdividing steps subdivide a block of the superordinate level to obtain two blocks at the subordinate level.

15 24. The method of claim 21, wherein if the first and second channels have a length of  $N$ , then the independently and correspondingly subdividing steps subdivide the first and second channel into the plurality of blocks such that each block has a length of one of  $N/2$ ,  $N/4$ ,  $N/8$ ,  $N/16$  and  $N/32$ .

20 25. The method of claim 21, further comprising:  
generating information indicating the subdivision of the first and second channels into the blocks.

25 26. The method of claim 25, wherein the generating step generates the information such that a length of the

information depends on a number of levels in the subdivision hierarchy.

27. The method of claim 25, wherein the generating step

5 generates the information such that the information includes a number of information bits, and the information bits indicate the subdivision of the first and second channels into the blocks.

10 28. The method of claim 27, wherein each information bit is associated with a level in the subdivision hierarchy and is associated with a block at the associated level, and each information bit indicates whether the associated block was subdivided.

15

29. The method of claim 28, wherein if the information bit has a value of 1, then the associated block is subdivided, and if the information bit has a value of 0, then the associated block is not subdivided.

20

30. The method of claim 20, further comprising:  
sending the information.

31. The method of claim 20, further comprising:

25 predicting current data samples in the first and second

channels based on previous data samples, a number of the previous data samples used in the predicting step being the prediction order; and

obtaining a residual of the current data samples based  
5 on the predicted data samples.

32. The method of claim 31, wherein the predicting step progressively increases the prediction order to a desired prediction order as previous data samples become available.

10

33. The method of claim 32, wherein

the prediction order for an initial data sample having no previous data samples is zero, and the predicting step generates zero as the predicted initial data sample; and  
15 the obtaining step effectively does not change the initial data sample as a result of the predicted initial data sample being zero.

34. The method of claim 32, further comprising:

20 determining the desired prediction order for each block based on a maximum permitted prediction order and a length of the block.

35. The method of claim 31, further comprising:

25 determining an optimum prediction order for each block

based on a maximum permitted prediction order and a length of the block.

36. The method of claim 35, wherein the determining step

5 comprises:

determining a global prediction order based on the maximum permitted prediction order;

determining a local prediction order based on the length of the block; and

10 selecting a minimum one of the global prediction order and the local prediction order as the optimum prediction order.

37. The method of claim 31, wherein if the frame is a random access frame, which is a frame to be encoded such that

15 previous frames are not necessary to decode the frame,

the predicting step progressively increases the

prediction order to a desired prediction order as

previous data samples from only the random access frame become available.

20

38. A method of processing an audio signal, the method

comprising:

independently switching lengths of blocks into which each of a plurality of channels in an audio data frame are

25 divided if the plurality of channels are not correlated

with each other; and

switching lengths of blocks into which the plurality of channels in the frame are divided such that the block lengths of each channel are switched to a same length at

5 a same time if the plurality of channels are correlated with each other;

wherein the frame is divided into a plurality of blocks, and at least two of the blocks in the frame have different block lengths.

10

39. A method of encoding an audio signal, comprising:

independently subdividing at least first and second channels in a frame of the audio signal into blocks if the first and second channels are not correlated with each other, at least two of the blocks having different

15

block lengths;

correspondingly subdividing the first and second channels into blocks such that the lengths of the blocks into which the second channel is subdivided correspond to the

20

lengths of the blocks into which the first channel is subdivided if the first and second channels are correlated with each other, at least two of the blocks having different block lengths; and

encoding the blocks to produce a compressed bitstream.

25

40. A method of decoding an audio signal, comprising:

receiving an audio data frame having at least first and second channels, the first and second channels having been independently subdivided into blocks if the first and second channels are not correlated with each other,  
5 and the first and second channels having been correspondingly subdivided into blocks such that the lengths of the blocks into which the second channel is subdivided correspond to the lengths of the blocks into which the first channel is subdivided if the first and second channels are correlated with each other, at least two of the blocks having different block lengths in each of the first and second channels; and  
10 decoding the first and second channels.

15

41. An apparatus for encoding an audio signal, comprising:


an encoder configured to independently subdivide at least first and second channels in a frame of the audio signal into blocks if the first and second channels are not correlated with each other, at least two of the blocks having different block lengths;  
20 the encoder configured to correspondingly subdivide the first and second channels into blocks such that the lengths of the blocks into which the second channel is subdivided correspond to the lengths of the blocks into  
25

which the first channel is subdivided if the first and second channels are correlated with each other, at least two of the blocks having different block lengths; and the encoder configured to encode the blocks to produce a 5 compressed bitstream.

42. An apparatus for decoding an audio signal, comprising:


a decoder configured to receive an audio data frame having at least first and second channels, the first and 10 second channels having been independently subdivided into blocks if the first and second channels are not correlated with each other, and the first and second channels having been correspondingly subdivided into channels having been correspondingly subdivided into blocks such that the lengths of the blocks into which the 15 second channel is subdivided correspond to the lengths of the blocks into which the first channel is subdivided if the first and second channels are correlated with each other, at least two of the blocks having different block lengths in each of the first and second channels; and 20 the decoder configured to decode the first and second channels.

FIG. 1




2/6

FIG. 2




3/6

FIG. 3



4/6

**FIG. 4**

5/6

FIG. 5

(a)	level 0	N			(0)0000 0000		
(b)	level 1	N/2		N/4	N/4		(0)101 0000
(c)	level 2	N/4	N/4	N/4	N/2		(0)110 0000
(d)	level 3	N/4	N/8	N/8	N/4	N/4	(0)111 0100
(e)		N/4	N/2		N/4		not possible
(f)		N/8	N/4	N/4	N/8	N/4	N/4

6/6

FIG. 6

