



(51) International Patent Classification:
H04B 10/07 (2013.01)

(21) International Application Number:

PCT/CN2016/087122

(22) International Filing Date:

24 June 2016 (24.06.2016)

(25) Filing Language:

English

(26) Publication Language:

English

(71) Applicant: **HUAWEI TECHNOLOGIES CO., LTD.** [CN/CN]; Huawei Administration Building, Bantian, Longgang District, Shenzhen, Guangdong 518129 (CN).

(72) Inventors: **JIANG, Zhiping**; 173 Windance Cres., Kanata, Ontario K2W 0A5 (CA). **LIU, Tejia**; Huawei Administration Building, Bantian, Longgang District, Shenzhen, Guangdong 518129 (CN). **YANG, Hong**; Huawei Administration Building, Bantian, Longgang District, Shenzhen, Guangdong 518129 (CN). **JIN, Dajiang**; Huawei Administration Building, Bantian, Longgang District, Shenzhen, Guangdong 518129 (CN). **SI, Minggang**; Huawei Administration Building, Bantian, Longgang District, Shenzhen, Guangdong 518129 (CN).

(81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PA, PE,

PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

(84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, KM, ML, MR, NE, SN, TD, TG).

Declarations under Rule 4.17:

— as to applicant's entitlement to apply for and be granted a patent (Rule 4.17(ii))

Published:

— with international search report (Art. 21(3))

(54) Title: METHOD AND APPARATUS FOR PROVIDING A PILOT TONE




Figure 6

(57) Abstract: The disclosure is directed at a method and system for optical telecommunications performance monitoring via a dual frequency pilot tone. By applying a dual frequency pilot tone, with a first pilot tone frequency selected from a low frequency band and a second pilot tone frequency selected from a high frequency band, either simultaneously or alternatively, to a wavelength channel, one of the pilot tone frequencies may be adaptively selected to improve wavelength channel monitoring. More specifically, stimulated Raman scattering (SRS) caused crosstalk and chromatic dispersion (CD) caused pilot fading which adversely affect performance monitoring of the wavelength channel may be reduced.



METHOD AND APPARATUS FOR PROVIDING A PILOT TONE

FIELD OF THE DISCLOSURE

The disclosure is directed generally at optical telecommunications and more
5 specifically at a method and apparatus for optical channel monitoring.

BACKGROUND OF THE DISCLOSURE

In Dense Wavelength Division Multiplexing (DWDM) systems, light at multiple
wavelengths is modulated with streams of digital information, and then the modulated light
10 beams at different wavelengths, termed "wavelength channels", are combined for joint
propagation in an optical fiber.

To identify wavelength channels in a DWDM system, a pilot tone may be applied to
communication channels within the optical telecommunications system. The pilot tone is
typically a low frequency modulation of a channel's optical power level. The pilot tone may
15 be used for channel optical performance monitoring, and may also carry information
associated with the channel, such as, but not limited to, its wavelength, baud rate,
modulation format and other identification information for supervisory, control, equalization,
continuity, synchronization, or reference purposes.

By providing this pilot tone, channel power can be monitored by a low cost, low speed
20 pilot-tone detector.

In many current systems, the pilot tone is subject to degradation caused by the
interaction and superposition of optical signals in the transmission fiber.

Therefore, there is a need for an improved system and method for pilot tone based
optical performance monitoring.

25

SUMMARY OF THE DISCLOSURE

The disclosure is directed at a method and system for optical telecommunications
performance monitoring by using dual frequency pilot tones. By applying a dual frequency
pilot tone to a wavelength channel, or channel, one of the pilot tone frequencies may be
30 adaptively selected to improve wavelength channel monitoring power accuracy. In one
embodiment, the first pilot tone frequency is selected from a low frequency band and the
second pilot tone frequency is selected from a high frequency band. The dual frequency pilot

tone is applied either simultaneously or alternatively to the system. By applying a dual frequency pilot tone, stimulated Raman scattering (SRS) and chromatic dispersion (CD) issues or effects which adversely affect performance monitoring of the wavelength channel may be reduced.

5 In one aspect of the disclosure, there is provided a method of optical telecommunications performance monitoring which includes detecting a pilot tone associated with a wavelength channel, the pilot tone including a first frequency in a first frequency range and a second frequency in a second frequency range. One of the frequencies of the pilot tone is then selected to obtain the wavelength channel information. In another aspect, each
10 of the frequencies of the pilot tone carries identical channel information. In one aspect of the disclosure, the first frequency range is between 30 MHz and 60 MHz and the second frequency range is between 125 MHz and 155 MHz.

 In another aspect, there is provided another method of optical telecommunications performance monitoring which includes applying a dual frequency pilot tone to a channel. In
15 another aspect of the disclosure, the dual frequency pilot tone includes a first frequency in a first frequency range and a second frequency in a second frequency range. In another aspect of the disclosure, the first frequency range is selected to lessen chromatic dispersion effects and the second frequency range is selected to lessen stimulated Raman scattering (SRS) effects.

20 In yet a further aspect, there is provided a pilot tone modulated onto a wavelength channel, the pilot tone including a first frequency within a first frequency range and a second frequency located within a second frequency range.

DRAWINGS OF THE DISCLOSURE

25 The following figures illustrate various aspects and embodiments of the system, method and apparatus disclosed herein:

 Figure 1a is a schematic diagram of an optical telecommunications system;

 Figure 1b is a schematic diagram of a channel within the optical telecommunications system of Figure 1a;

30 Figure 2 is a schematic diagram of a pilot tone;

 Figure 3 is a schematic diagram reflecting how stimulated Raman scattering (SRS) affects optical telecommunication systems having multiple channels;

Figure 4a is a graph illustrating frequency dependency of SRS for a transmission link based on a large effective area fiber (LEAF);

Figure 4b is a graph illustrating frequency dependency of SRS for a transmission link based on an SSMF optical fiber;

5 Figure 5a is a schematic diagram of an optical channel spectrum;

Figure 5b is a graph illustrating chromatic dispersion (CD) induced pilot tone power fading vs. pilot tone frequency;

Figure 6 is a method of implementing a dual frequency pilot tone;

10 Figure 7a is a graph illustrating SRS induced cross-talk vs. pilot tone frequency in low and high frequency bands;

Figure 7b is a graph illustrating CD induced pilot tone power fading vs. pilot tone frequency in low and high frequency bands;

Figure 8a is a schematic diagram of an embodiment of applying a dual frequency pilot tone for an optical telecommunications system;

15 Figure 8b is a schematic diagram of another embodiment of applying a dual frequency pilot tone for an optical telecommunications system; and

Figure 9 is a flowchart outlining a method of frequency selection for a dual frequency pilot tone.

20 DETAILED DESCRIPTION

The disclosure is directed at a method and system for performing channel monitoring within an optical telecommunications system. The method and system of the disclosure uses a dual frequency pilot tone. One of the dual frequencies is selected from a low frequency band, or range, while the other is selected from a high frequency band, or range. In one
25 embodiment, the low frequency band is between 30 MHz and 60 MHz and the high frequency band is between 125 MHz and 155 MHz. Use of a dual frequency pilot tone assists the system to mitigate adverse operating conditions within the optical telecommunication system.

In order to reduce issues with stimulated Raman Scattering (SRS), a high frequency
30 pilot tone is preferred. In order to reduce accumulated chromatic dispersion issues, a low frequency pilot tone is preferred. Therefore, the disclosure is directed at providing a dual

frequency pilot tone for a wavelength channel whereby both pilot tone frequencies may carry the same, or identical data, or wavelength channel information.

Turning to Figure 1a, a schematic diagram of an optical telecommunications system is shown. The optical telecommunications system, or optical network, 100 includes a set of nodes 102a-102g which are connected with each other via individual optical transmission fibers 103. The nodes 102 may be connected with each other via more than one transmission fiber 103. Signals transmitted along these individual transmission fibers 103 produce a plurality of wavelength channels, or channels, 104, each wavelength channel including light at a particular wavelength modulated with a high-speed digital stream of information or data. For ease of understanding, a transmission node is seen as the node 102a which is delivering data while a destination, or receiving, node 102g is seen as a node which is receiving the data. In some cases, communication between two nodes may not be direct. By way of example, communication between the transmission node 102a and the destination node 102g is such that the data passes through other nodes, such as 102b and 102e between the transmission node 102a and the destination node 102g.

In order to monitor the wavelength channels 104 being transmitted over the transmission fibers 103, pilot tones are used. A pilot tone is typically a low frequency modulation of a channel's optical power level. Distinct pilot tones may be associated with each particular wavelength channel within the network 100. The pilot tones may include information such as characteristics of the associated wavelength channel. These characteristics may include, but are not limited to, power, source/destination identification (ID), wavelength, modulation format or baud rate or any other characteristics or combination of those characteristics.

The pilot tones are modulated onto the wavelength channels 104 travelling between the transmission nodes 102a – 102g. Detection of these pilot tones provides an identification of which channels 104 are being transmitted over which transmission fiber 103 at any time within the network 100, which is particularly useful when multiple channels 104 are transmitted over a same transmission fiber 103.

Within the network 100 are a set of pilot tone detectors 106 which detect these pilot tones. In one embodiment, the pilot tone detectors 106 include a low-speed photodiode and a digital signal processor (DSP).

Turning to Figure 1b, a schematic diagram showing a portion of the optical telecommunications system of Figure 1a is provided. Figure 1b shows the connection between two nodes 102a and 102b which are connected by the transmission fiber 103. Optical amplifiers 105 are provided to amplify the channel 104. In Figure 1b, one of the nodes 102a may be seen as the source, or transmission, node, and the second of the nodes 102b may be seen as the destination node. In the embodiment of Figure 1b, although individual pilot tone detectors 106 are shown at specific locations within the transmission fiber 103 between the two nodes 102, the pilot tone detectors 106 may be located anywhere within the network 100. Depending on the type of nodes 102a or 102b, the nodes 102a or 102b may include a reconfigurable optical add/drop multiplexor (ROADM) 107 coupled to receivers 110 and transmitters 112 for dropping and adding channels. For example, if the node 102 is an amplifier node, the node 102 would not include any receiver or transmitter, however, if the node 102 is an access node, there may be 0, one or multiple receivers 110 and transmitters 112. Accordingly, the wavelength channels 104 may terminate at a destination node 102b or propagate further, as shown with an arrow to the right of the node 102b.

Turning to Figure 2, a schematic representation of an optical signal is provided. The optical signal includes high-speed data 200 which is modulated onto light at a certain wavelength. The modulation of the light generates a wavelength channel. The data modulation frequency of the wavelength channel is typically in the GHz range. The optical signal also includes a pilot tone 202. The pilot tone may be used for supervisory, control, equalization, continuity, synchronization, or reference purposes for the optical telecommunications system 100. The frequency of the pilot tone 202 is preferably much less than the data modulation frequency of the wavelength channel. For example, the frequency of the pilot tone 202 may be at tens or hundreds of MHz or below.

Currently, a single frequency pilot tone is used to transmit information relating to an associated wavelength channel to assist in monitoring performance of the telecommunication system. In multiple channel optical telecommunications systems, or networks, stimulated Raman scattering (SRS) caused crosstalk is experienced. Use of the single frequency pilot tone is adversely affected by the SRS crosstalk. To overcome this problem, the SRS crosstalk is suppressed by increasing the frequency of the single frequency pilot tone.

Within these optical telecommunication systems, different wavelength channels are transmitted along the optical transmission fibers to allow the nodes 102 to transmit information therebetween. SRS is a nonlinear optical effect whereby energy from a shorter wavelength channel is partially transferred to a longer wavelength channel. This effect may occur between any two channels, although it is more pronounced between neighboring channels.

When a first wavelength channel is modulated with a pilot tone, this first pilot tone is partially transferred to another wavelength channel due to SRS effect. This creates a ghost tone on this other channel. Without the ghost tone, the pilot tone detected for this other channel is proportional to its corresponding channel power. With SRS caused ghost tones, the detected pilot tone of the other channel has contributions from pilot tones of other wavelength channels, such as the pilot tone of the first wavelength channel. The power measurement accuracy for the other channel is reduced due to the ghost tone or tones.

Turning to Figure 3, a schematic diagram reflecting how SRS affects optical telecommunication systems having multiple optical channels is shown. Due to SRS effects, a pilot tone frequency f_1 initially applied on wavelength 1 (λ_1) will also appear on wavelengths 2 (λ_2) and 3 (λ_3). Similarly, a pilot tone frequency f_2 initially applied on wavelength 2 (λ_2) may also appear on wavelengths 1 (λ_1) and 3 (λ_3). Pilot tone frequency f_3 initially applied on wavelength 3 (λ_3) may also appear on wavelengths 1 (λ_1) and 2 (λ_2). The SRS caused crosstalk depends on a number of factors. These factors include the number of channels in the transmission fiber, channel wavelengths, the optical power of the channels, number of fiber spans, fiber type, fiber length etc. SRS crosstalk may cause significant power measurement error in a pilot tone based optical performance monitoring. In some scenarios, the error is so big that pilot tone based optical performance monitoring is not beneficial and may be useless.

Turning to Figures 4a and 4b, graphs outlining SRS crosstalk values with respect to pilot tone frequencies are shown. These graphs reflect the SRS crosstalk dependency on pilot tone frequency. In Figure 4a, the graph reflects SRS crosstalk values on a Y-axis against pilot tone frequency (in MHz) on the X-axis for a dispersion uncompensated LEAF system while Figure 4b shows the same for a dispersion uncompensated standard single mode fiber (SSMF) system. The span length is 80km. In each SRS crosstalk scenario, there were 80 channels in the C band with a signal channel being the first channel.

With respect to Figure 4a, an optical transmission link including a LEAF optical fiber had chromatic dispersion which was uncompensated over the 80km span with -1 dBm channel fiber (or individual fiber) input power. An optical transmission link including an SSMF optical fiber (Figure 4b) had chromatic dispersion which was also uncompensated
5 over the 80km span with +1 dBm per channel fiber input power.

For the 80 channels within the system, the energy of a pilot tone associated with one of the channels is partially transferred to the other 79 channels and seen as ghost tones. In this manner, the pilot tone frequency of one wavelength channel is seen, in some form, on every other channel. As these ghost tones propagate through the network, different phase is
10 added to different ghost tones which may result in these ghost tones partially cancelling each other out when detected. In order to keep the ghost tones out of phase, a higher frequency pilot tone is preferred.

As can be seen for the current examples, the level of SRS crosstalk with respect to the frequency of the pilot tone is reduced as the pilot tone frequency increases. A higher
15 frequency pilot tone is preferred to reduce or minimize SRS crosstalk effects. Although only a single span length has been shown, it is understood that even if the span lengths are different, a general trend remains whereby a pilot tone having a higher frequency results in smaller SRS crosstalk effects between the channels. However, when a higher frequency pilot tone is used, other adverse effects may be introduced, such as chromatic dispersion
20 (CD) fading which relates to the phenomenon in which the phase velocity of a wavelength depends on its frequency.

With respect to CD effects, Figure 5a provides a schematic diagram showing an optical channel spectrum while Figure 5b provides a graph showing pilot tone electrical power change vs pilot tone frequency at some accumulated chromatic dispersions. In Figure
25 5b, pilot tone electrical power change (in dB) is shown on the Y-axis and pilot tone frequency (in MHz) is shown on the X-axis.

When modulation is applied to a continuous wave (CW) light, its spectrum is broadened. In other words, this results in the channel spectrum being broadened. A channel with a broadened spectrum may be seen as a channel including an infinite number
30 of frequency components.

A pilot tone is then applied on every frequency component. Initially, the phases of the pilot tone associated with all frequency components are the same such that the total pilot

tone power is at an initial value. When the frequency components propagate through the transmission fiber, each associated pilot tone experiences a different phase change such that the total pilot tone power is reduced. This differential phase change is caused by chromatic dispersion. With chromatic dispersion, the total pilot tone power is reduced from the initial value. This affects the reading or detection by the pilot tone detector.

As will be understood, the modeling of this CD fading effect involves an infinite number of frequency components. To simplify this modeling, the broadened channel spectrum can be considered as having only two discrete frequency components seen as arrows 500 and 502 in Figure 5a. The left arrow 500 represents the spectrum on the left side and the right arrow 502 represents the spectrum on the right side. The distance $\Delta\lambda_{\text{eff}}$ may be taken as approximately equal to half of the signal spectrum width. Although this picture is highly simplified, through simulations and experiments, it may be considered as a very good approximation.

For instance, as shown in Figure 5a, when light at a wavelength represented by the left arrow 500 and light at a wavelength represented by the right arrow 502 are modulated by the same frequency, a phase difference is introduced between the two signals as they propagate along the transmission fiber (or optical channel). This is due to the fact that the light at the optical frequencies represented by the arrows 500 and 502 propagates at different speeds along the transmission fiber. The different speeds are caused by the chromatic dispersion. As the light portions at both frequencies 500 and 502 are modulated with the same pilot tone, the pilot tone may become faded or lose power, due to destructive interference between the pilot tone waveforms of the light portions at the frequencies 500 and 502, whereby the initial value of pilot tone power of the channel is reduced. The CD-caused fading effects typically increase as pilot tone frequencies increase. At certain combinations of $\Delta\lambda_{\text{eff}}$, CD magnitude, and optical fiber length, the different pilot tone frequencies may cancel themselves out, leading to a complete disappearance of the pilot tone.

A large CD may lead to a low signal to noise ratio (SNR) and/or a large power measurement error of the pilot tone, which adversely affects pilot tone based monitoring of channels within the telecommunication system.

In order to compensate for CD fading, an accumulated CD value is required. The accumulated CD value is either known by the system or may be calculated. In one

embodiment, the accumulated CD value is a product of the length of the fiber span and a dispersion coefficient while a total accumulated chromatic dispersion may be seen as a sum of the accumulated CD from all of the fiber spans that the channel propagates upon being detected. Since CD fading is dependent on the optical signal spectrum, CD fading is therefore dependent on wavelength characteristics such as baud rate and spectral shape.

When the accumulated CD fading increases, the power within the pilot tone is reduced which results in the low SNR and power measurement error. The power change can be represented by the equation:

$$\Delta P_{dB} = 10 \log_{10} [(1 + \cos(2\pi f_{PT} CD \Delta \lambda_{eff}) / 2)]$$

where f_{PT} is the pilot tone frequency, CD is the accumulated chromatic dispersion between a transmitter and the pilot tone detector, $\Delta \lambda_{eff}$ is a fitting parameter or the effective spectral width of the channel being sensed (typically half of the spectral width). The pilot tone frequency is known based on the design of the system, the accumulated CD is calculated (as described above) and the fitting parameter is obtained by comparing measurement results and/or theoretical results from the equation.

As can be seen in the graph of Figure 5b, there is less power change when the frequency of the pilot tone is at a lower value such as below 60 MHz, suggesting that a lower frequency pilot tone is preferred for reducing CD effects. Therefore, unlike the preferred pilot tone frequency for reducing SRS which is more desirable at a higher frequency, a lower frequency pilot tone is preferred for reducing CD fading or for compensating against CD effects.

Therefore, in order to overcome some of the disadvantages and problems in current systems, a novel method and system for optical performance monitoring via a dual frequency pilot tone is disclosed. By supplying a dual frequency pilot tone, the pilot tone detector can adaptively select the preferred frequency pilot tone based on characteristics of the network. The dual frequency pilot tone can be applied either simultaneously or alternatively to the channel.

One advantage of the current disclosure is that by having a pilot tone at two different frequencies, current issues with single frequency pilot tone systems are reduced or mitigated. As each channel is modulated with the two pilot tone frequencies (both carrying the same, or identical, channel information), the pilot tone in the high frequency band can be adaptively

selected to reduce or suppress SRS effects while the pilot tone in the low frequency band can be adaptively selected to reduce the CD fading effects .

For channels with a small accumulated chromatic dispersion, such as dispersion compensated channels or dispersion uncompensated channels with low dispersion fiber, the pilot tone in the high frequency band is preferably selected. An example of such a system is a large effective area fiber (LEAF) system. For dispersion un-compensated channels, the pilot tone in the low frequency band is preferably selected.

Turning to Figure 6, a flowchart outlining a method of providing a dual frequency pilot tone for an optical telecommunications system is shown. Initially, a first and a second frequency are selected 600 for the dual frequency pilot tone. The first frequency is preferably selected from a low frequency band while the second frequency is selected from a high frequency band. The frequency bands are determined based on SRS crosstalk and CD fading characteristics of the system. In a preferred embodiment, these SRS crosstalk and CD fading characteristics are determined via experimental studies performed on the system or simulations performed based on parameters of the system. In this manner, the low and high frequency bands may be determined prior to installation or operation of the system. Selection of the pilot tone frequency in the low frequency band is to lessen chromatic dispersion effects when it is detected. Selection of the pilot tone frequency in the high frequency band is to lessen SRS effects on the pilot tone when it is detected. These dual frequency pilot tones are then associated with different wavelengths propagating within the network.

In operation, the associated dual frequency pilot tones are then applied 602 to their associated wavelength channels in the optical telecommunications system 100. For channels with dual polarizations, the selected frequencies may either be applied simultaneously (concurrently) to X/Y polarization within the wavelength channel or applied alternatively (consecutively) to X/Y polarization within the communication channel.

Turning to Figure 7a, a graph showing crosstalk versus pilot tone frequency is shown. On the Y-axis of the graph is the level of crosstalk (measured in dB) while on the X-axis is the pilot tone frequency (in MHz). As can be seen in the current example, within a low frequency band (such as between 30 to 60 MHz), the level of crosstalk is around -20 to -25 dB for systems having one to eight spans. Within a high frequency band (such as between

130 and 155 MHz), the cross-talk is around -40 dB for each of the systems having one to eight spans. In the high frequency band, the SRS effect is suppressed.

Turning to Figure 7b, a graph showing pilot tone electrical power change vs pilot tone frequency is shown. On the Y-axis of this graph, the pilot tone electrical power change (in dB) is shown while on the X-axis, the pilot tone frequency (in MHz) is shown. At a low frequency band (such as between 30 to 60 MHz), the electrical power change is around 0 to -2 for accumulated chromatic dispersion values between 5000 ps/nm to 30000 ps/nm. At the higher frequency band (such as between 130 and 155 MHz), the electrical power change is quite varied for accumulated chromatic dispersion values between 5000 ps/nm to 30000 ps/nm.

Therefore, for the current system as reflected in Figures 7a and 7b, to reduce SRS effects, a pilot tone in the high frequency band is preferred and to reduce CD effects, a pilot tone in the low frequency band is preferred. In other words, one of the pilot tone frequencies is selected from a range between 30 to 60 MHz and a second of the pilot tone frequencies is selected from a range between 125 and 155MHz. It is appreciated that for different systems, the frequency bands, or ranges, may differ.

Turning to Figure 8a, a schematic diagram reflecting an embodiment of how the dual frequency pilot tone is applied to a wavelength channel is shown. In modern optical communication systems, e.g. coherent systems, both polarizations are used to carry information. In the current embodiment, the dual frequency pilot tone is applied to the X/Y polarization channels simultaneously whereby both frequencies carry the identical channel information. As can be seen, for both the X and Y polarization channels, both a high and low frequency pilot tone are simultaneously transmitted over each channel. In the current embodiment, each pilot tone frequency is transmitted for a single pilot tone bit before being switched to the other frequency pilot tone. In this embodiment, both frequencies of the dual frequency pilot tone exist at all times within each of the polarization channels. Based on the characteristics of the network, the pilot tone detector 106 can then adaptively select one of the two pilot tone frequencies to obtain the information being transmitted by the pilot tone.

Turning to Figure 8b, a schematic diagram reflecting another embodiment of how the dual frequency pilot tone may be applied to a channel is shown. In the current embodiment, the dual frequencies of the pilot tone are applied alternatively to the X and Y polarization channels. Both frequencies of the dual-frequency pilot tone carry the same data.

In operation, as schematically shown in Figure 8b, for the X polarization channel, the low frequency pilot tone is transmitted for one pilot tone bit and then replaced with the high frequency pilot tone for one bit. The opposite transmission occurs within the Y polarization channel with the high frequency pilot tone being delivered for one pilot tone bit and then replaced with the low frequency pilot tone for one pilot tone bit. In this embodiment, while only one frequency exists for each polarization channel at any given time, both frequencies exist in the system at all times. As one of the frequencies is transmitted in one polarization channel, the other frequency is transmitted in the other polarization channel. The pilot tone detector 106 can then adaptively select one of the two pilot tone frequencies to obtain the information being transmitted by the pilot tone based on the characteristics of the system.

Turning to Figure 9, a method of adaptive pilot tone detection or selection is shown. In the method of Figure 9, the flowchart shows how a pilot tone detector determines which pilot tone of the dual frequency pilot tone to use in order to retrieve channel information.

Initially, the pilot tone detector detects at least one of the frequencies of the dual frequency pilot tone 900. After detecting the at least one of the frequencies, a lightpath of the channel associated with the pilot tone detector 106 is determined 902. This lightpath information is generally known and can be retrieved from network management software. In one embodiment, the information may be retrieved via a central, or distributed, controller or processing unit. The lightpath information may also be based on a best lightpath as determined by the controller. The chromatic dispersion of the wavelength channel is then calculated, accumulated or obtained 904. In one embodiment, the chromatic dispersion may be calculated between a transmitter within a node and a pilot tone detector. This can be seen as an accumulated chromatic dispersion value. As discussed above, the accumulated CD value is seen as the product of the length of the propagated fiber span (or optical channel) and a dispersion co-efficient. After determining the accumulated chromatic dispersion value, an optical pilot tone power error caused by the accumulated chromatic dispersion fading is calculated 906. The pilot tone power error can be calculated based on the equation disclosed above using specific values relating to the channel characteristics. This pilot tone power error is then compared to a threshold value, such as 1 or 2 dB, to determine if the calculated optical pilot tone power error is less than the threshold value 908. If the optical pilot tone power error caused by CD is deemed to be more than the threshold, the low frequency pilot tone is adaptively selected and if the optical pilot tone power error is deemed

to be less than the threshold, the high frequency pilot tone is adaptively selected. If the optical pilot tone power error is equal to the threshold, either pilot tone frequency can be selected. The selected pilot tone frequency is then used to derive the power of the channel along with any other characteristics, if available or necessary.

5 In the preceding description, for purposes of explanation, numerous details are set forth in order to provide a thorough understanding of the embodiments. However, it will be apparent to one skilled in the art that these specific details may not be required. In other instances, well-known structures may be shown in block diagram form in order not to obscure the understanding. For example, specific details are not provided as to whether
10 elements of the embodiments described herein are implemented as a software routine, hardware circuit, firmware, or a combination thereof.

Embodiments of the disclosure or components thereof can be provided as or represented as a computer program product stored in a machine-readable medium (also referred to as a computer-readable medium, a processor-readable medium, or a computer
15 usable medium having a computer-readable program code embodied therein). The machine-readable medium can be any suitable tangible, non-transitory medium, including magnetic, optical, or electrical storage medium including a diskette, compact disk read only memory (CD-ROM), memory device (volatile or non-volatile), or similar storage mechanism. The machine-readable medium can contain various sets of instructions, code sequences,
20 configuration information, or other data, which, when executed, cause a processor or controller to perform steps in a method according to an embodiment of the disclosure. Those of ordinary skill in the art will appreciate that other instructions and operations necessary to implement the described implementations can also be stored on the machine-readable medium. The instructions stored on the machine-readable medium can be executed by a
25 processor, controller or other suitable processing device, and can interface with circuitry to perform the described tasks.

The above-described embodiments are intended to be examples only. Alterations, modifications and variations can be effected to the particular embodiments by those of skill in the art without departing from the scope, which is defined solely by the claims appended
30 hereto.

What is claimed is:

1. A method of optical telecommunications performance monitoring comprising:
applying a dual frequency pilot tone to a wavelength channel, wherein the dual frequency pilot tone includes a first frequency in a first frequency range and a second frequency in a second frequency range.
2. The method of claim 1 wherein first frequency range is between 30 MHz and 60 MHz and the second frequency range is between 125 MHz and 155 MHz.
3. The method of claim 2 wherein the first frequency range is selected to lessen chromatic dispersion effects.
4. The method of claim 2 wherein the second frequency range is selected to lessen stimulated Raman scattering (SRS) effects.
5. The method of claim 1 wherein applying comprises:
applying both frequencies simultaneously to an X polarization channel of the wavelength channel; and
applying both frequencies simultaneously to a Y polarization channel of the wavelength channel.
6. The method of claim 1 wherein applying comprises:
applying both frequencies, in an alternating manner, to an X polarization channel of the wavelength channel; and
applying both frequencies, in an alternating manner, to a Y polarization channel of the wavelength channel.
7. A method of optical telecommunications performance monitoring comprising:
detecting a pilot tone associated with a wavelength channel, the pilot tone including a first frequency in a first frequency range and a second frequency in a second frequency range; and

selecting one of the frequencies of the pilot tone to obtain the wavelength channel information.

8. The method of claim 7 wherein each of the frequencies carries identical wavelength channel information.

9. The method of claim 7 wherein the first frequency range is between 30 MHz and 60 MHz and the second frequency range is between 125 MHz and 155 MHz.

10. The method of claim 9 wherein selecting comprises:
 calculating an accumulated chromatic dispersion value by:
 determining a lightpath of the wavelength channel; and
 accumulating chromatic dispersion along the lightpath.

11. The method of claim 10 wherein selecting further comprises:
 calculating a pilot tone power error value for the wavelength channel based on the accumulated chromatic dispersion value;
 comparing the pilot tone power error value with a threshold value; and
 selecting the first frequency if the pilot tone power error value is more than the threshold value.

12. The method of claim 10 wherein the pilot tone power error value is represented by:

$$\Delta P_{dB} = 10 \log_{10} [(1 + \cos(2\pi f_{PT} CD \Delta \lambda_{eff}) / 2]$$

where f_{PT} is a pilot tone frequency, CD is an accumulated chromatic dispersion between a transmitter and a pilot tone detector, and $\Delta \lambda_{eff}$ is a fitting parameter or an effective spectral width of the wavelength channel being sensed.

13. A pilot tone modulated onto a wavelength channel, the pilot tone comprising:
 a first frequency, the first frequency located within a first frequency range; and
 a second frequency, the second frequency located within a second frequency range.

14. The pilot tone of claim 13 wherein each of the frequencies carries identical wavelength channel information.
15. The pilot tone of claim 13 wherein the first frequency range is selected to lessen chromatic dispersion effects.
16. The pilot tone of claim 15 wherein the first frequency range is between 30 MHz and 60 MHz.
17. The pilot tone of claim 13 wherein the second frequency range is selected to lessen stimulated Raman scattering (SRS) effects.
18. The pilot tone of claim 17 wherein the second frequency range is between 125 MHz and 155 MHz.




Figure 1a




Figure 1b




Figure 2




Figure 3




Figure 4b





Figure 4a



Optical Channel Spectrum

Figure 5a




Figure 5b




Figure 6




Figure 7b




Figure 7a




Figure 8a




Figure 8b




Figure 9

INTERNATIONAL SEARCH REPORT

International application No.

PCT/CN2016/087122

A. CLASSIFICATION OF SUBJECT MATTER		
H04B 10/07(2013.01)j		
According to International Patent Classification (IPC) or to both national classification and IPC		
B. FIELDS SEARCHED		
Minimum documentation searched (classification system followed by classification symbols) H04J, H04B, H04W, H04Q7/-, H04L		
Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched		
Electronic data base consulted during the international search (name of data base and, where practicable, search terms used) CPRSABS, CNABS, CNTXT, CNKI, VEN, EPODOC, IEEE: WDM, Wavelength Division Multiplexing, optical, channel, path, monitoring, pilot, tone, dual, two, first, second, frequency, Raman Scattering, SRS, chromatic dispersion		
C. DOCUMENTS CONSIDERED TO BE RELEVANT		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 2003067646 A1 (PING WAI WAN ET AL.) 10 April 2003 (2003-04-10) paragraphs [0002], [0025] to [0057] and figures 1 to 5	1, 7
A	CN 102870351 A (HUAWEI TECHNOLOGIES CO., LTD.) 09 January 2013 (2013-01-09) the whole document	1-12
A	CN 103378906 A (JUNIPER NETWORKS INC) 30 October 2013 (2013-10-30) the whole document	1-12
A	WO 2010072423 A1 (ERICSSON TELEFON AB L MET AL.) 01 July 2010 (2010-07-01) the whole document	1-12
<input type="checkbox"/> Further documents are listed in the continuation of Box C. <input checked="" type="checkbox"/> See patent family annex.		
* Special categories of cited documents: "A" document defining the general state of the art which is not considered to be of particular relevance "E" earlier application or patent but published on or after the international filing date "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified) "O" document referring to an oral disclosure, use, exhibition or other means "P" document published prior to the international filing date but later than the priority date claimed "T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art "&" document member of the same patent family		
Date of the actual completion of the international search 30 December 2016		Date of mailing of the international search report 12 January 2017
Name and mailing address of the ISA/CN STATE INTELLECTUAL PROPERTY OFFICE OF THE P.R.CHINA 6, Xitucheng Rd., Jimen Bridge, Haidian District, Beijing 100088 China		Authorized officer LU,Jing
Facsimile No. (86-10)62019451		Telephone No. (86-10)62412158

Box No. II Observations where certain claims were found unsearchable (Continuation of item 2 of first sheet)

This international search report has not been established in respect of certain claims under Article 17(2)(a) for the following reasons:

1. Claims Nos.: **13-18**
because they relate to subject matter not required to be searched by this Authority, namely:
[1] the subject matter of claims 13-18 merely relate to presentations of information, and therefore, according to the criteria set out in Rule 39.1(v), relate to subject matter for which an international search is not required.
2. Claims Nos.:
because they relate to parts of the international application that do not comply with the prescribed requirements to such an extent that no meaningful international search can be carried out, specifically:
3. Claims Nos.:
because they are dependent claims and are not drafted in accordance with the second and third sentences of Rule 6.4(a).

INTERNATIONAL SEARCH REPORT
Information on patent family members

International application No.

PCT/CN2016/087122

Patent document cited in search report			Publication date (day/month/year)	Patent family member(s)			Publication date (day/month/year)
US	2003067646	A1	10 April 2003	US	7054556	B2	30 May 2006
				CA	2358382	A1	05 April 2003
				CA	2358382	C	09 September 2008
CN	102870351	A	09 January 2013	CN	102870351	B	08 April 2015
				WO	2013185343	A1	19 December 2013
CN	103378906	A	30 October 2013	US	2013286847	A1	31 October 2013
				CN	103378906	B	06 July 2016
				EP	2661004	A2	06 November 2013
				US	9100139	B2	04 August 2015
				CN	105871500	A	17 August 2016
				EP	2661004	A3	07 September 2016
WO	2010072423	A1	01 July 2010	US	2012051739	A1	01 March 2012