

(19) World Intellectual Property Organization  
International Bureau



(43) International Publication Date  
22 November 2001 (22.11.2001)

PCT

(10) International Publication Number  
WO 01/89108 A1

(51) International Patent Classification<sup>7</sup>: H04B 1/707 (74) Agent: WHITE, Andrew, G.; Internationaal Octrooibureau B.V., Prof Holstlaan 6, NL-5656 AA Eindhoven (NL).

(21) International Application Number: PCT/EP01/04594 (81) Designated State (national): JP.

(22) International Filing Date: 24 April 2001 (24.04.2001) (84) Designated States (regional): European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR).

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data: 0011493.4 13 May 2000 (13.05.2000) GB

(71) Applicant: KONINKLIJKE PHILIPS ELECTRONICS N.V. [NL/NL]; Groenewoudseweg 1, NL-5621 BA Eindhoven (NL).

(72) Inventor: GOODINGS, Christopher, J.; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL).

**Published:**

- with international search report
- before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.



WO 01/89108 A1

(54) Title: METHOD AND APPARATUS FOR CODE PHASE TRACKING

(57) **Abstract:** A method of code phase tracking for CDMA type communication is disclosed together with apparatus including a GPS receiver (10 to 15) for the same. The method uses a modified early-minus-late correlation function to determine the code phase error between a target pseudorandom noise code of an incoming signal and locally generated replica codes. The early-minus-late correlation function is modified compared to the true function whereby the gradient of the modified function at zero code phase error is increased. This may be achieved by modifying the early-minus-late correlation function after its derivation. Alternatively, it may be modified by modifying variables from which it is derived and in particular, by modifying the either or both of the power spectrums of the subject signal or the early and late replica code signals whereby at least one odd harmonic is reduced in size or removed; at least one even harmonic is increased in size; or the bandwidth is truncating between harmonics so as to excise an adjacent even harmonic.

## DESCRIPTION

**METHOD AND APPARATUS FOR CODE PHASE TRACKING**

5 This invention relates to a method of code phase tracking for code division multiple access (CDMA) type communication and to apparatus for the same.

10 The invention is of particular benefit to the field of global positioning systems (GPS) and is described with reference to GPS hereafter. However, such reference should not be interpreted as limiting the scope of the invention to merely GPS. For example, the invention is equally applicable to CDMA communication between mobile cellular telephones and associated networks.

15 At present, GPS is most notably associated with the Navigation System with Time and Ranging (NAVSTAR) GPS, an all weather, spaced based navigation system developed and operated by the US Department of Defense, however, the general principles underlying GPS are universal and not merely limited to NAVSTAR. Accordingly, GPS hereafter refers to any global positioning system comprising a plurality of CDMA radio transmitters at 20 different locations and a receiver which determines its location based on the time of arrival of the transmissions of the radio transmitters.

25 As is well known, a GPS receiver may implement a pseudorandom noise (PRN) code correlation loop in which early (E), prompt (P) and late (L) replica codes of satellite PRN codes are continuously generated, and compared to the incoming satellite PRN codes as received by the receiver. Using a code phase discriminator calculated as a function of the correlation, it is then possible to determine whether a target incoming code has been acquired; if the code phase discriminator exceeds a predetermined threshold level, the target incoming code and the locally generated replica codes can be 30 assumed to be in phase, i.e. the code is acquired. If not, the code generator produces the next series of replicas with a phase shift, typically of one chip, and the code phase discriminator is recalculated. Assuming carrier phase lock,

a linear code sweep should eventually result in the target incoming code being in phase with that of the locally generated replica codes and therefore, if detected, code acquisition.

Once the code is acquired, a code phase lock loop may be used to

5 track the code, typically employing an early-minus-late code correlation function in order to determine the code phase error between the target incoming code and the locally generated replica codes. As code phase shift is the basis for pseudorange measurements, the accuracy to which the pseudoranges can be measured and ultimately to which the position of the

10 GPS receiver can be estimated depends on the accuracy to which the code phase lock loop can determine the code phase error.

It is therefore an object of the invention to provide a method and apparatus for code phase tracking able to more accurately determine the code

15 phase error between a target pseudorandom noise code of an incoming signal and locally generated replica codes.

According to the present invention, a method of code phase tracking is provided together with a receiver comprising an antenna and a signal processor for the same. The method comprises the steps of:

20 (a) receiving a subject signal containing a target pseudorandom noise code;

(b) generating a series of signals containing early and late replica codes corresponding to the target code;

25 (c) correlating the subject signal with the early and late replica code signals and returning respective early and late correlation values; and

(d) determining the code phase error between the target code and the replica codes from a modified early-minus-late correlation function derived from the early and late correlation values, the modified early-minus-late correlation function being such that its gradient at zero code

30 phase error is increased compared to the true early-minus-late correlation function.

Increasing the gradient of the early-minus-late correlation function at the zero code phase error enables the occurrence of zero code phase error to be determined more accurately.

The early-minus-late correlation function may be modified after its 5 derivation or, alternatively, prior to its derivation by modifying either the subject signal, the early and late replica code signals or the early and late correlation values.

Modifying any one of the parameters from which the early-minus-late correlation function is derived may enable the necessary signal processing to 10 be simplified. For example, modification of the subject signal may be achieved using relatively simple front-end analogue circuitry and modification of the early and late replica code signals may be achieved either by processing unmodified replica signals, say by filtering, or by direct generation of the appropriate sequence, especially if done in the digital domain.

15 Modification of the subject signal and / or the early and late replica code signals preferably includes modification of their respective power spectrums by at least one of the following: reducing in size or removing at least one odd harmonic; increasing in size at least one even harmonic; and truncating the bandwidth between harmonics so as to excise an adjacent even harmonic.

20 There is believed there is a direct relationship between the power spectrums of the subject signal / replica signals and the early-minus-late correlation function such that the aforementioned harmonic manipulation increases the gradient of the early-minus-late correlation function at the point of zero code phase error. This relationship together with its effect on the 25 accuracy to which the occurrence of zero code phase error can be determined is explained below.

The invention further provides a receiver comprising a signal processor for modifying the power spectrum of a received subject signal containing a target pseudorandom noise code whereby the power spectrum of the subject 30 signal has either at least one odd harmonic which is reduced in size or removed; at least one even harmonic which is increased in size; or a reduced

bandwidth which is truncated between harmonics so as to excise an adjacent even harmonic.

The invention yet further provides a receiver comprising an antenna for receiving a subject signal containing a target pseudorandom noise code; and a signal processor comprising a generator for generating a series of signals containing early and late replica codes corresponding to the target code, a correlator for correlating the subject signal with the early and late replica code signals and returning respective early and late correlation values, and means for determining the code phase error between the target code and the replica codes from a modified early-minus-late correlation function derived from the early and late correlation values, such that the gradient of the modified early-minus-late correlation function at zero code phase error is increased compared to the true early-minus-late correlation function.

The above receiver may modify the early-minus-late correlation function by modifying either the subject signal, the early and late replica code signals or the early and late correlation values prior to deriving the early-minus-late correlation function. In particular, but not exclusively, the receiver may modify the early-minus-late correlation function by modifying the subject signal or the early and late replica code signals whereby either or both of their respective power spectrums have either at least one odd harmonic which is reduced in size or removed; at least one even harmonic which is increased in size; or a reduced bandwidth which is truncated between harmonics so as to excise an adjacent even harmonic.

The above and other features and advantages of the present invention will be apparent from the following description, by way of example, of an embodiment of a method of code phase tracking and a GPS receiver according to the present invention with reference to the accompanying drawings in which:

Figure 1 shows, schematically, an SPS GPS receiver according to the present invention;

Figure 2 shows, schematically, the receiver channels and receiver processor of the GPS receiver of figure 1 in greater detail;

Figure 3 is a graph showing an idealised early-minus-late correlation function for 1.0 MHz and 4.0 MHz bandwidths;

5 Figure 4 is a graph showing the gradient of the early-minus-late correlation function plotted against the bandwidth of the incoming signal for both unmodified and modified incoming signals; and

Figures 5A and 5B are graphs showing normalised power spectrums for both an unmodified and a modified incoming signal respectively.

10

The general principles underlying GPS and methods and apparatus for its implementation are known. For example, see GPS Principles and Applications (Editor, Kaplan) ISBN 0-89006-793-7 Artech House, hereinafter "Kaplan".

15

As is well known, each NAVSTAR GPS satellite transmits two carrier frequencies; L1, the primary frequency at 1575.42 MHz and L2, the secondary frequency at 1227.60 MHz. The carrier frequencies are modulated by spread spectrum codes with a PRN sequence unique to each satellite and also by the navigation data message. The L1 signal is modulated the coarse / acquisition (C/A) code and the precision (P[Y]) code whereas the L2 signal is modulated by the P[Y] code only. The P[Y] codes relate to the precise positioning service (PPS) primarily for military and select government agency users whereas the C/A relates to the standard positioning service (SPS) for which there is currently unrestricted access.

20

Figure 1 shows, schematically, the architecture of an SPS GPS receiver according to the present invention. GPS radio frequency (RF) signals are received by an antenna 10 and pre-processed in a pre-processor 11 by preamplification, passive bandpass filtering in order to minimise out-of-band RF interference, further filtering to filter out first harmonics of the power spectrum of the incoming signal; down converting to an intermediate frequency (IF) and analog to digital conversion. Digitised IF signals are then provided to each of n digital receiver channels 12 in which they are acquired and tracked

in co-operation with the receiver processor 13 for the purpose of acquiring navigation information. Such methods for acquisition and tracking are well known, for example, see chapter 4 (GPS satellite signal characteristics) & chapter 5 (GPS satellite signal acquisition and tracking), Kaplan *ibid*. Using 5 acquired navigation information and the time of arrival of the transmissions, the navigation processor 14 calculates the position of the receiver using conventional algorithms and that position is displayed on a display 15 to the user.

The pre-processor 11 will be typically implemented in the form of front 10 end analogue circuitry with the digital receiver channels 12, the receiver processor 13 and the navigation processor 14 implemented in the form of a general purpose microprocessor or a microprocessor embedded in a GPS application specific integrated circuit (ASIC).

Figure 2 shows, schematically, the receiver channel co-operating with 15 the receiver processor in greater detail. In order to retrieve the information on the incoming signal, a carrier wave (CW) must be removed and this is done by the receiver generating in-phase (I) and quadrature phase (Q) replica carrier wave signals using a carrier wave generator 21. The replica carrier waves ideally have the same frequency as the received signal, however, due to 20 Doppler shift caused by the relative movement between the receiver and orbiting satellites, the frequency of the GPS signals as received in the receiver normally differs from the precise satellite transmission frequency. In order to accurately replicate the frequency of the received carrier wave, a conventional carrier wave phase lock loop is employed. Although perhaps undesirable, it is 25 possible to omit the carrier phase lock stage altogether as the Doppler shift of the carrier and its associated effect on the code phase discriminator is reasonably small.

In order to acquire code phase lock, early (E), prompt (P) and late (L) 30 replica codes of the PRN sequences are continuously generated by a code generator 22 at a frequency related to the received carrier (i.e. nominal plus Doppler). The replica codes are then correlated with the I and Q signals to produce three in-phase correlation components (IE, IL, IP) and three

quadrature phase correlation components (QE, QL, QP), typically by integration in an integrator 23 over substantially the whole of the PRN code. In the receiver processor 13, a code phase discriminator is calculated as a function of the correlation components on which a threshold test is applied and

5 a phase match declared if the code phase discriminator is high. If not, the code generator produces the next series of replicas with single chip phase advance and the code phase discriminator is recalculated. Any declared phase match is validated by recalculating the discriminator. A linear phase sweep will eventually result in the incoming PRN code being in phase with that of the

10 locally generated replica and thus code acquisition.

Once the code is acquired, a code phase lock loop employing an early-minus-late correlation function is used to track the code. The early-minus-late correlation function is modified compared to the true early-minus-late correlation function because of the aforementioned filtering out of the first

15 harmonics of the power spectrum of the incoming signal. As a consequence, the code phase lock loop provides an enhanced code phase error signal relating to the time difference between the incoming signal and the two local generated replicas.

Without wishing to be bound by any theory, the inventor believes the

20 following analysis explains the relationship between the accuracy to which the code phase lock loop can determine the code phase error, the gradient of the early-minus-late correlation function at zero code phase error and the aforementioned power spectrum manipulation.

As previously stated, the accuracy to which the pseudoranges can be

25 measured and ultimately to which the position of the GPS receiver can be estimated. The relationship between the code phase error measurement ( $\Delta t$ ) and an associated pseudorange error measurement ( $\Delta d$ ) can be expressed as:

$$\Delta d \approx c \Delta t \quad [\text{Equation 1}]$$

30 where  $c$  is the speed of light. Thus, if the accuracy of the pseudorange measurement is to be determined to 1 metre, the code loop error (after

averaging for noise) must be to within 3.3ns, or about 1/300  $T_c$  where  $T_c$  is the GPS L1 C/A signal chip period.

Curves 31 and 32 of figure 3 shows the true, normalised, early-minus-late (E-L) correlation function for signal bandwidths of 1.0 MHz and 4.0 MHz 5 respectively where the E-L correlation is normalised by the prompt (P) correlation value. In a GPS receiver using early-minus-late code phase tracking, the code phase tracking error ( $\Delta t$ ) can therefore be approximated whereby:

$$\Delta t = \frac{1}{g} \Delta \left\{ \frac{E - L \pm n_e \pm n_l}{P \pm n_p} \right\} \quad [\text{Equation 2}]$$

10 where  $g$  is the gradient of the (E-L)/P graph at  $t=0$ ;  $E$ ,  $L$  and  $P$  are correlation measurements; and  $n_e$ ,  $n_l$  and  $n_p$  are early, late and prompt correlation measurement noise respectively.

Assuming the noise to be small and uncorrelated, at  $E-L = 0$ , the code phase error  $\Delta t$  can be expressed as follows:

$$15 \quad \Delta t \approx \frac{1}{g} \frac{\sqrt{2} n}{P} \quad [\text{Equation 3}]$$

where  $n$  is the magnitude of the effective noise.

It is therefore possible to define a figure of merit (FOM) which is approximately directly proportional to the receiver accuracy:

$$\text{FOM} = \frac{d(E - L)}{dt} \Big|_{t=0} \times n \quad [\text{Equation 4}]$$

20 A finite length pseudorandom noise code may be approximated to an ideal random binary code. Accordingly, there is no periodicity of the correlation and therefore no line quantisation of the correlation power spectrum.

The power spectrum of the correlation is given by the Fourier transform of the correlation power. Since there is no Fourier transform of a truly random 25 binary code, in order to obtain the power spectrum, the Fourier transform of

the autocorrelation function is calculated. For a binary code having an amplitude of  $\pm A$ , the autocorrelation function is the classic triangular shape with a base length of  $\pm 1$  code chip and a maximum correlation power of  $A^2$ . This can be expressed as follows:

$$5 \quad R(\tau) = A^2 \left( 1 - \frac{|\tau|}{T_c} \right) \text{ for } |\tau| \leq T_c \quad [\text{Equation 5}]$$

$$R(\tau) = 0 \text{ for } |\tau| > T_c$$

where  $T_c$  is the chip period for the C/A code). The Fourier transform of this is given by:

$$S(\omega) = A^2 T_c \sin c^2 \frac{\omega T_c}{2} \quad [\text{Equation 6}]$$

As the correlation power can be derived from the inverse Fourier transform of the correlation power spectrum, it is therefore possible to use the power spectrum as a starting point for the derivation of the correlation function shape and size. Also, the power spectrum can be modified to reflect the consequences of any front-end filter characteristics and the Fourier transform taken of the resulting spectrum to derive the correlation characteristics. 10  
15 Although this does not take account of several significant effects, such as the low resolution ADC in an actual system, the qualitative results appear to be consistent with theorised models.

To do this, an idealised power spectrum is first generated over a range of frequencies (say  $\pm 8\text{MHz}$  or  $\pm 12\text{MHz}$  in  $0.02\text{MHz}$  steps) and held in a vector. 20  
The vector can then be "filtered" by multiplying individual elements by a transmission factor. The simplest form of filtering only uses filter transmissions of zero or one. The power spectrum is normalised to an amplitude,  $A$ , of unity.

The precise correlation can then be generated from the power spectrum by taking the inverse Fourier transform. This is a vector containing the 25 correlation as a function of time, expressed in terms of the chip period  $T_c$ . The total length of the vector (i.e. the range of time) is inversely proportional to the

10

frequency step size of the power spectrum and the correlation step size is inversely proportional to the total range of the power spectrum.

The early-minus-late correlation can be generated by a sparse matrix operation on the precise correlation vector.

5                    $EL(t) = M_{(E-L)} \cdot P(t)$

where  $EL(t)$  is a column vector containing the (E-L) correlation result,  $P(t)$  is a column vector containing the precise correlation result and  $M_{(E-L)}$  is a square matrix whose dimension is the same as the vector lengths. The matrix  $M_{(E-L)}$  is mainly zero but contains elements of  $\pm 1$  on diagonals which perform the (E-L) arithmetic operation. An example is shown below:

$$M_{(E-L)} = \begin{pmatrix} 0 & 0 & 1 & 0 & 0 & 0 & \dots & 0 \\ 0 & 0 & 0 & 1 & 0 & 0 & \dots & 0 \\ -1 & 0 & 0 & 0 & 1 & 0 & \dots & 0 \\ 0 & -1 & 0 & 0 & 0 & 1 & \dots & 0 \\ 0 & 0 & -1 & 0 & 0 & 0 & \dots & 1 \\ 0 & 0 & 0 & -1 & 0 & 0 & \dots & 0 \\ \vdots & \vdots & \vdots & \vdots & \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & 0 & 0 & -1 & 0 & \dots & 0 \end{pmatrix} \quad [Equation 7]$$

The distance of the leading element of each diagonal from the top-left corner of the matrix gives the early-minus-late spacing and will depend on the time resolution of the correlation vector.

15                  In figure 4, curve 41 shows the FOM, i.e. the gradient of the early-minus-late correlation function, varying with the half-bandwidth of incoming signal. This is due to the shape of the correlation peak being modified by the varying sum of its Fourier components. The reason for the variation in FOM with bandwidth is further explained by the power spectrum of the correlation 20 described by curve 51 in figure 5A. The power spectrum has nulls at 1,2,3...n MHz. Between 0 and 1MHz, even Fourier components contribute to the power, between 1 and 2 MHz odd Fourier components contribute to the power (etc.). These even and odd components eventually mix to form the ideal triangular correlation shape. However, even components serve to increase the 25 steepness of the correlation shape around  $t=Tc/2$  while odd components serve

to decrease the steepness. For half-chip (E-L) correlators, an increase in the steepness of the correlation shape at  $T_c/2$  results in an increased (E-L) gradient at  $t=0$  and therefore an improved FOM.

The idea behind this invention is to selectively allow the even 5 components of the signals to contribute to the correlation while blocking the odd components. In practice, to limit the required bandwidth, only the first few components would be used. The resulting modified power spectrum is described by curve 52 in figure 5B, suggesting that the FOM can be increased by about 14% in this way.

10 Even greater increases in the FOM can be achieved by artificially adapting the shape of the correlation. Curve 53 of figure 5B described the situation where the odd components have been removed and the first harmonic even components increased by a factor of 2. The FOM is now increased by a factor of about 28%. Thus, this invention provides a method of 15 increasing the accuracy of a GPS system which uses code tracking only.

As previously stated, in a GPS receiver of the type shown schematically in figures 1 and 2, the pre-processing, receiver channel and receiver processor will typically be implemented in the form of front end analogue circuitry combined with either a general purpose microprocessor or a microprocessor 20 embedded in a GPS application specific integrated circuit. Implementation of a method of code phase tracking according to the present invention, including the example as described below, may be accomplished by appropriate analogue circuitry design and / or microprocessor programming. Of course, such design and programming is well known and would be accomplished by 25 one of ordinary skill in the art of GPS and CDMA communication without undue burden.

## CLAIMS

1. A method of code phase tracking comprising the steps of:
  - (a) receiving a subject signal containing a target pseudorandom noise code;
  - (b) generating a series of signals containing early and late replica codes corresponding to the target code;
  - (c) correlating the subject signal with the early and late replica code signals and returning respective early and late correlation values; and
  - (d) determining the code phase error between the target code and the replica codes from a modified early-minus-late correlation function derived from the early and late correlation values, the modified early-minus-late correlation function being such that its gradient at zero code phase error is increased compared to the true early-minus-late correlation function.
2. A method according to claim 1 wherein the early-minus-late correlation function is modified by modifying either the subject signal, the early and late replica code signals or the early and late correlation values prior to deriving the early-minus-late correlation function.
3. A method according to claim 2 wherein at least one odd harmonic of the power spectrum of the subject signal is reduced in size or removed.
4. A method according to claim 2 wherein at least one even harmonic of the power spectrum of the subject signal is increased in size.
5. A method according to claim 2 wherein the bandwidth of the power spectrum of the subject signal is truncated between harmonics so as to excise an adjacent even harmonic.

6. A method according to claim 2 wherein at least one odd harmonic of the power spectrum at least one of the early and late replica code signals is reduced in size or removed.

5

7. A method according to claim 2 wherein at least one even harmonic of the power spectrum at least one of the early and late replica code signals is increased in size.

10

8. A method according to claim 2 wherein the bandwidth of the power spectrum at least one of the early and late replica code signals is truncated between harmonics so as to excise an adjacent even harmonic.

15

9. A method of code phase tracking substantially as hereinbefore described with reference to the figures.

20

10. A receiver comprising an antenna for receiving a subject signal containing a target pseudorandom noise code; and a signal processor for implementing a method of code phase correlation according to any preceding claim.

25

11. A receiver comprising a signal processor for modifying the power spectrum of a received subject signal containing a target pseudorandom noise code so that the power spectrum of the subject signal has either at least one odd harmonic which is reduced in size or removed; at least one even harmonic which is increased in size; or a reduced bandwidth which is truncated between harmonics so as to excise an adjacent even harmonic.

30

12. A receiver comprising an antenna for receiving a subject signal containing a target pseudorandom noise code and a signal processor, the signal processor comprising a generator for generating a series of signals containing early and late replica codes corresponding to the target code, a

correlator for correlating the subject signal with the early and late replica code signals and returning respective early and late correlation values, and means for determining the code phase error between the target code and the replica codes from a modified early-minus-late correlation function derived from the 5 early and late correlation values, such that the gradient of the modified early-minus-late correlation function at zero code phase error is increased compared to the true early-minus-late correlation function.

13. A receiver according to claim 12 wherein the early-minus-late 10 correlation function is modified by modifying either the subject signal, the early and late replica code signals or the early and late correlation values prior to deriving the early-minus-late correlation function.

14. A receiver according to claim 13 wherein at least one odd 15 harmonic of the power spectrum of the subject signal is reduced in size or removed.

15. A receiver according to claim 13 wherein at least one even harmonic of 20 the power spectrum of the subject signal is increased in size.

16. A receiver according to claim 13 wherein the bandwidth of the power spectrum of the subject signal is truncated between harmonics so as to excise an adjacent even harmonic.

25

17. A receiver according to claim 13 wherein at least one odd harmonic of the power spectrum at least one of the early and late replica code signals is reduced in size or removed.

30 18. A receiver according to claim 13 wherein at least one even harmonic of the power spectrum at least one of the early and late replica code signals is increased in size.

19. A receiver according to claim 13 wherein the bandwidth of the power spectrum at least one of the early and late replica code signals is truncated between harmonics so as to excise an adjacent even harmonic.

5

20. A receiver substantially as hereinbefore described with reference to the figures.

1/3




FIG. 1




FIG. 2

2/3




FIG. 3




FIG. 4

3/3




FIG. 5A




FIG. 5B

# INTERNATIONAL SEARCH REPORT

International Application No  
PCT/EP 01/04594

**A. CLASSIFICATION OF SUBJECT MATTER**  
IPC 7 H04B1/707

According to International Patent Classification (IPC) or to both national classification and IPC

**B. FIELDS SEARCHED**

Minimum documentation searched (classification system followed by classification symbols)  
IPC 7 H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, INSPEC, WPI Data, PAJ

**C. DOCUMENTS CONSIDERED TO BE RELEVANT**

Category	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	<p>WILDE A: "EXTENDED TRACKING RANGE DELAY-LOCKED LOOP" COMMUNICATIONS - GATEWAY TO GLOBALIZATION. PROCEEDINGS OF THE CONFERENCE ON COMMUNICATIONS. SEATTLE, JUNE 18 - 22, 1995, PROCEEDINGS OF THE CONFERENCE ON COMMUNICATIONS (ICC), NEW YORK, IEEE, US, vol. 2, 18 June 1995 (1995-06-18), pages 1051-1054, XP000533156 ISBN: 0-7803-2487-0 page 1051, right-hand column, line 10 -page 1052, right-hand column, line 34; figures 1-4</p> <p>---</p> <p style="text-align: center;">-/-</p>	2,10,13
A	<p>page 1051, right-hand column, line 10 -page 1052, right-hand column, line 34; figures 1-4</p> <p>---</p> <p style="text-align: center;">-/-</p>	3-8, 14-19

Further documents are listed in the continuation of box C.

Patent family members are listed in annex.

° Special categories of cited documents :

- \*A\* document defining the general state of the art which is not considered to be of particular relevance
- \*E\* earlier document but published on or after the international filing date
- \*L\* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- \*O\* document referring to an oral disclosure, use, exhibition or other means
- \*P\* document published prior to the international filing date but later than the priority date claimed

- \*T\* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- \*X\* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- \*Y\* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- \*&\* document member of the same patent family

Date of the actual completion of the international search

2 October 2001

Date of mailing of the international search report

10/10/2001

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2  
NL - 2280 HV Rijswijk  
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,  
Fax: (+31-70) 340-3016

Authorized officer

Nilsson, M

## INTERNATIONAL SEARCH REPORT

Inte[redacted] Application No  
PCT/EP 01/04594

## C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category °	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US 5 495 499 A (FENTON PATRICK ET AL) 27 February 1996 (1996-02-27) abstract column 2, line 41 -column 3, line 53 column 9, line 4 - line 41; figure 3 column 11, line 4 -column 12, line 11; figures 4,7 -----	2,10,13

**FURTHER INFORMATION CONTINUED FROM PCT/ISA/ 210**

Continuation of Box I.2

Claims Nos.: 1 part, 2 part, 9, 20

Present claims 1 and 12 relate to a method/apparatus defined by reference to a desirable characteristic or property, namely increased accuracy in a tracking loop.

The claims 1 and 12 cover all methods/apparatus having this characteristic or property, whereas the application provides support within the meaning of Article 6 PCT and/or disclosure within the meaning of Article 5 PCT for only a very limited number of such methods/apparatus.

In the present case, the claims so lack support, and the application so lacks disclosure, that a meaningful search over the whole of the claimed scope is impossible.

Claims 1 and 12 also lacks clarity (Article 6 PCT). An attempt is made to define the method/apparatus by reference to a result to be achieved. Again, this lack of clarity in the present case is such as to render a meaningful search over the whole of the claimed scope impossible.

Claims 9 and 20 contain references to the drawings. According to Rule 6.2(a) PCT, claims should not contain such references except where absolutely necessary, which is not the case here.

Consequently, the search has been carried out for those parts of the claims which appear to be clear, supported and disclosed, namely those parts relating to the methods/apparatus mentioned in the description at pages 7-10 (Increasing the accuracy by suppressing the odd harmonics in the E-L correlation error function).

The applicant's attention is drawn to the fact that claims, or parts of claims, relating to inventions in respect of which no international search report has been established need not be the subject of an international preliminary examination (Rule 66.1(e) PCT). The applicant is advised that the EPO policy when acting as an International Preliminary Examining Authority is normally not to carry out a preliminary examination on matter which has not been searched. This is the case irrespective of whether or not the claims are amended following receipt of the search report or during any Chapter II procedure.

**INTERNATIONAL SEARCH REPORT**

Information on patent family members

Int'l Application No  
PCT/EP 01/04594

Patent document cited in search report		Publication date		Patent family member(s)	Publication date
US 5495499	A	27-02-1996	US	5390207 A	14-02-1995
			US	5101416 A	31-03-1992
			US	5809064 A	15-09-1998
			US	5734674 A	31-03-1998
			AT	187254 T	15-12-1999
			AU	660757 B2	06-07-1995
			AU	3197193 A	29-07-1993
			CA	2087909 A1	25-07-1993
			CN	1080059 A , B	29-12-1993
			DE	69327119 D1	05-01-2000
			DE	69327119 T2	21-06-2000
			DK	552975 T3	27-03-2000
			EP	0552975 A2	28-07-1993
			ES	2141129 T3	16-03-2000
			SG	43672 A1	14-11-1997
			US	5414729 A	09-05-1995
			CA	2055105 A1	29-05-1992
			DE	69121066 D1	29-08-1996
			DE	69121066 T2	30-01-1997
			DE	488739 T1	20-04-1995
			EP	0488739 A1	03-06-1992
			JP	2931462 B2	09-08-1999
			JP	4269682 A	25-09-1992
			SG	43678 A1	14-11-1997