



- (51) **International Patent Classification:**
H05B 33/08 (2006.01) *H05B 37/02* (2006.01)
- (21) **International Application Number:**
PCT/EP2016/055680
- (22) **International Filing Date:**
16 March 2016 (16.03.2016)
- (25) **Filing Language:** English
- (26) **Publication Language:** English
- (30) **Priority Data:**
15161297.5 27 March 2015 (27.03.2015) EP
- (71) **Applicant:** AMS AG [AT/AT]; Schloss Premstätten, Tobelbader Str. 30, 8141 Unterpremstätten (AT).
- (72) **Inventors:** GAMPERL, David; Rosengrabenweg 3, 8230 Hartberg (AT). PAURITSCH, Manfred; Glesingerstr. 44, 8054 Graz (AT). TRUPPE, Herbert; Walter-Goldschmidt-Gasse 51, 8042 Graz (AT).
- (74) **Agent:** ASSOCIATION NO. 175; EPPING HERMANN FISCHER PATENTANWALTSGESELLSCHAFT MBH; Schloßschmidstr. 5, 80639 München (DE).

(81) **Designated States** (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.


(84) **Designated States** (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, KM, ML, MR, NE, SN, TD, TG).

Published:

— with international search report (Art. 21(3))

(54) **Title:** LIGHTING CONTROL SYSTEM AND METHOD FOR GENERATING SUPPLY CURRENTS FOR LED CHANNELS

Fig 1



(57) **Abstract:** A lighting control system (LCS) for generating supply currents for at least two LED channels (CH1, CH2, CHn) comprises at least two controlled current sources for generating a supply current for a corresponding LED channel based on a corresponding control signal. The system further comprises at least two signal combiners for generating the corresponding control signals based on a synchronization signal (VSYNC) that comprises periodic starting pulses and on a combination of a magnitude dimming signal and a pulse dimming signal corresponding to one of the LED channels. The signal combiners are designed such that changes of the respective control signals come into effect only with a respective time offset with respect to one of the starting pulses of the synchronization signal.

Description

LIGHTING CONTROL SYSTEM AND METHOD FOR GENERATING SUPPLY
CURRENTS FOR LED CHANNELS

5

The invention relates to a lighting control system and to a method for generating supply currents for at least two LED channels. Such LED channels may be particularly used for driving segmented LED backlights.

10

Conventional displays produce white background illumination either by a cold cathode tube, white light-emitting diodes, LEDs, or by a combination of red, green and blue LEDs.

Because of their fast turn-on time, backlights with LEDs allow control of the brightness by means of pulse modulation. Such LED backlights will be considered further here.

For subjective increase of contrast, the LED backlighting of a display is typically subdivided into segments, each with its own driving and thus its own brightness control. The task of determining the brightness is conventionally performed by a digital video processor. The segments are conventionally driven by means of pulse modulated signals. However, with the use of conventional pulse modulation techniques, a dynamic range of the desired brightness may be insufficient, in particular in view of backlight systems for 4K or UHD TV sets. For example, the high dynamic range, HDR, specification requires an increased dynamic range for the brightness.

An object to be achieved is to provide an improved concept for controlling LED channels with an improved dynamic range for the brightness to be achieved.

This object is achieved with the subject-matter of the independent claims. Embodiments and developments are subject-matter of the dependent claims.

5 The improved concept is based on the idea that supplying a plurality of LED channels with individual supply currents is not only based on the width of a pulse-width modulated signal but also on a magnitude of such pulses. Hence, the resulting supply currents are not only defined by the time during which
10 this current is supplied to the LED channel but also by an individual current value. To this end for each of the LED channels an individual pulse dimming signal and an individual magnitude dimming signal are provided, which are the basis the for the current generation. Furthermore, for each of the
15 LED channels to be supplied, an individual time offset with respect to a common synchronization signal like a vertical sync, VSYNC, is provided. Changes of the supply currents come only into effect with the respective time offset of the LED channel to be supplied. Hence, negative effects on
20 neighboring channels when brightness parameters for this channel change, can be avoided. For example, both the magnitude dimming signal and the pulse dimming signal for each channel are synchronized with the synchronization signal, taking into account the respective time offset.

25

For example, an external video processor provides a brightness value for each of the LED channels. The respective magnitude dimming signals and pulse dimming signals may be generated from these brightness values by a single processing
30 unit. Hence, an efficient combination of pulse width and magnitude of the pulsed supply current can be achieved without influencing other channels.

In an embodiment of a lighting control system according to the improved concept supply currents for a first LED channel and at least a second LED channel are generated. For example, supply currents for a plurality of LED channels are

5 generated. The system comprises a first controlled current source for generating a first supply current for the first LED channel based on a first controlled signal, and, similarly, a second controlled current source for generating a second supply current for the second LED channel based on a
10 second control signal. The system further comprises a first signal combiner for generating the first controlled signal based on a synchronization signal that comprises periodic starting pulses and on a combination of a first magnitude dimming signal and a first pulse dimming signal. Similarly, a
15 second signal combiner is provided for generating the second control signal based on the synchronization signal and on a combination of a second magnitude dimming signal and a second pulse dimming signal. The first and the second signal combiner are designed such that changes of the respective
20 first and second control signals come into effect only with a respective time offset with respect to one of the starting pulses of the synchronization signal.

For example, the time offset for the first signal combiner is
25 different from the time offset for the second signal combiner. More generally speaking, if a plurality of LED channels is to be supplied, a dedicated signal combiner and a dedicated controlled current source are provided for each of the LED channels to be supplied. In this case, the time
30 offset is different for each of the signal combiners.

For example, all of the control signals generated by the signal combiners are pulse-width modulated signals that are

defined by a pulse amplitude, which depends on the respective magnitude dimming signal, and by a pulse duration, which depends on the respective pulse dimming signal.

- 5 Furthermore, for example, all of the control signals generated by the signal combiners have a common cycle length for each of the starting pulses, and each of the control signals has an individual cycle start that is determined by the respective time offset for that control signal. One cycle
10 may be defined by the time between two starting pulses of the synchronization signal. However, this cycle length may vary with possible changes of the synchronization signal. The cycle start of each control signal may be defined by a transition from a first state to a second state, the second
15 state resulting in a current being produced by the associated controlled current source. In other words, the cycle start may be defined by the time instant when the supply current flows with a desired amplitude.
- 20 According to some of such implementations, a change of the pulse amplitude of each one of the control signals comes only into effect with a respective cycle start of said control signal.
- 25 In some implementations, a ratio between the pulse duration of each control signal and a cycle length of said control signal is less than or equal to one. Such a ratio may be expressed as a duty cycle of the respective control signal. If the ratio is less than one, there are time periods in the
30 control signal, respectively the supply current, where the control signal, respectively the supply current, returns to a zero value or to another predefined basis value.

However, if the ratio is equal to one, there are no such zero phases and the value of the control signal, respectively the resulting supply current, is only determined by the magnitude dimming signal for the associated LED channel. In other
5 words, a mere analog control of the supply current may be performed this way. However, also in this case, changes come only into effect with the respective time offset for said LED channel. Hence, each of the LED channels finds a change of the respective magnitude dimming signal to come into effect
10 at different times that are defined by the respective time offsets of the channels.

In some implementations each of the signal combiners is designed for generating a respective analog amplitude signal
15 based on the respective magnitude dimming signal, and for generating a respective pulse switching signal based on the respective pulse dimming signal, on the synchronization signal and on the respective time offset. The respective control signal is generated by modulating said analog
20 amplitude signal with said pulse switching signal. For example, the modulation is performed by switching on and off the analog amplitude signal based on the state of the pulse switching signal. For example, the analog amplitude signal is generated by a digital-to-analog converter, DAC, based on a
25 digital magnitude dimming signal.

In the various embodiments, the time offset for each channel may be preset for each of said signal combiners. For example, the time offset is preset once only in a production phase of
30 the control system, or in an initialization phase, e.g. at the start-up of the control system in each case.

In some implementations, the lighting control system according to the improved concept further comprises a signal processing unit for generating a set of pairs of a magnitude dimming signal and a pulse dimming signal based on a set of
5 brightness values for a plurality of LED channels to be supplied. With respect to the above explanations, for example a first pair of said set includes the first magnitude dimming signal and the first pulse dimming signal, and a second pair of said set includes the second magnitude dimming signal and
10 the second pulse dimming signal.

In some of such implementations, the signal processing unit generates one pair of magnitude dimming signal and pulse dimming signal for each brightness value provided. In other
15 words, the set of pairs and the set of brightness values are equinumerous.

In an alternative implementation the signal processing unit is configured to generate said set of pairs based on a
20 predefined subset of the set of brightness values, such that said set of pairs and said subset are equinumerous. For example, if the lighting control system has a predefined, limited number of supply outputs for such a number of LED channels, and the number of brightness values, respectively
25 LED channels, to be supplied is higher, two or more of such lighting control systems may be operated together such that each of the lighting control systems is dedicated to a specific sub-set of the full set of brightness values. The distribution of brightness values to different lighting
30 control systems may be controlled by pre-programming or by providing additional control information.

In view of the above description of the lighting control system and its various embodiments, also a method for generating supply currents for supplying a plurality of LED channels according to the improved concept is provided. The
5 method comprises, for each of the LED channels to be supplied, generating a control signal for said LED channel based on a synchronization signal, which comprises periodic starting pulses, and on a combination of a magnitude dimming signal for said LED channel and a pulse dimming signal for
10 said LED channel. Changes of said control signal come into effect only with a defined time offset with respect to one of the starting pulses of the synchronization signal. A supply current for said LED channel is generated by means of a controlled current source dedicated to said LED channel based
15 on said control signal.

Various embodiments of such a method become apparent for the skilled reader from the description of the various
embodiments of the lighting control system above.

20 Several exemplary embodiments according to the improved concept are described in greater detail below with reference to the figures. In the figures, elements with identical function or meaning are identified by the same reference
25 symbols. Hence, such elements may not be described repeatedly.

In the figures:

30 Figure 1 shows an example implementation of a lighting control system with LED channels to be supplied;

Figure 2 shows an example time signal diagram in an example implementation of the improved concept;

Figure 3 shows a further example time signal diagram in an example implementation of the improved concept; and

Figure 4 shows an example implementation of signal processing according to the improved concept.

Figure 1 shows an example embodiment of a lighting control system LCS according to the improved concept that is designed for providing supply currents ILED1, ILED2, ..., ILEDn to a plurality of LED channels CH1, CH2, ..., CHn. For example, the LED channels are part of a backlight of a liquid crystal display, LCD, wherein each LED channel is dedicated to a defined area of the display. For example, such a display may be part of a 4K TV set or ultrahigh definition, UHD, TV set. Hence, the lighting control system LCS may be a backlight control system for such applications.

The lighting control system LCS comprises, for each of the LED channels CH1, CH2, ..., CHn to be supplied, a respective controlled current source CS1, CS2, ..., CSn and an associated signal combiner SC1, SC2, ..., SCn. The signal combiners SC1, SC2, ..., SCn are provided with a first synchronization signal VSYNC and, optionally, with a second synchronization signal HSYNC. Furthermore, each of the signal combiners receives a pair of dimming signals that is individual for each signal combiner. In particular, each of said pairs comprises a magnitude dimming signal and a pulse dimming signal. Such a set of pairs is denoted with MD, PD in Figure 1. The set of pairs MD, PD may be provided by a signal processing unit SPU that is designed for generating the respective pairs of

magnitude dimming signal and pulse dimming signal from respective brightness values BV provided at an input of the signal processing unit SPU. This will be explained in greater detail below in conjunction with Figure 4.

5

Each of the signal combiners SC1, SC2, ..., SCn is configured for generating a respective control signal CC1, CC2, ..., CCn that controls the respective controlled current source CS1, CS2, ..., CSn for the associated channel. The generation of
10 said control signals is based on the synchronization signal VSYNC that comprises periodic starting pulses and on a combination of the magnitude dimming signal and the pulse dimming signal of said channel.

15 The synchronization signal VSYNC may be the vertical synchronization signal of a video image that separates video fields, e.g. two images to be displayed. The periodic starting pulses of the synchronization signal may be indicating the beginning of a new image, for example.

20

For each of the signal combiners SC1, SC2, ..., SCn there is a specific time offset defined. Such time offset may be dependent on a time sequence of areas to be illuminated by the various LED channels CH1, CH2, ..., CHn. In particular, the
25 time offsets of all channels may be different. The signal combiners are designed such that changes of their output, namely the respective control signals CC1, CC2, ..., CCn, come into effect only with the respective time offset of said channel with respect to one of the starting pulses of the
30 synchronization signal VSYNC. For example, in each cycle of the synchronization signal VSYNC, defined by a respective starting pulse and the following starting pulse, any changes to the control signal come only into effect at a time instant

defined by the starting pulse plus the associated time offset of said channel.

Referring now to Figure 2, this figure shows a time signal
5 diagram of the synchronization signal VSYNC and supply
currents ILED1, ILED2, ILED2 and ILEDn. Further supply
currents are left out in this diagram for reasons of a better
overview. Respective starting pulses of the synchronization
signal VSYNC are present at time instants t0, t2, t4 and t6,
10 each of the starting pulses indicating the beginning of a new
signal period, e.g. a new image frame.

The supply currents shown in Figure 2 are formed of pulse
signals, in particular pulse width modulated signals with a
15 specific pulse width and a specific magnitude for each LED
channel and each signal period. Each of the pulses starts an
offset time O1, O2, O3, On after the starting pulse of the
synchronization signal VSYNC. For example, the first supply
current ILED1 has a time offset of O1, the second supply
20 current ILED2 has a time offset of O2, the third supply
current ILED3 has a third time offset of O3 and the nth
supply current ILEDn has an nth time offset On.

For example, at the time instant t1 a new pair of dimming
25 signals, namely a magnitude dimming signal and a pulse
dimming signal, is provided for each of the LED channels to
the corresponding signal combiner. However, as can be seen
from Figure 2, the changes do not come into effect
immediately but only with the beginning of the next pulse of
30 the supply current after the following starting pulse of the
synchronization signal VSYNC at time t2. Moreover, with
respect to the last, nth channel with supply current ILEDn,
the current pulse around time instant t2 belongs to the

previous signal period and the changes provided at t_1 only become apparent at the time $t_2 + O_n$, thus after the time instant t_3 . For example, at the time instants t_3 and t_5 new respective sets of pairs of magnitude dimming signals and pulse dimming signals may be provided to the system.

With respect to the second supply current I_{LED2} in Figure 2, it should be noted that the signal generation according to the improved concept also makes it possible to provide boosted current pulses with a relatively short pulse width and a relatively high magnitude. For example, for such short boost pulses it may also be possible to drive the LED channel with a current that is two to four times higher than a current allowed for continuous operation of the LED channel. However, the actual boosting factor depends on the specific application or implementation and is not limited to the given example.

It should be further noted that the pulse width and pulse magnitude of each of the supply currents can be set individually for each signal period defined by the synchronization signal VS_{YNC} and for each LED channel separately. The time offsets $O_1, O_2, O_3, \dots, O_n$ may be predefined based on the application and implementation of the LED channels. For example, in the application of a backlight system for an LCD, the offset times may be defined by the position of the LED channel and the time at which an image is displayed on the LCD at said position. Hence, image display and backlighting are synchronized. Furthermore, the desired brightness for each image frame at each position can be controlled efficiently and with little or no influence on neighboring channels according to the improved concept.

Referring back to Figure 1, the control signals CC1, CC2, ..., CCn generated by the signal combiners SC1, SC2, ..., SCn are pulse width modulated signals that are defined by a pulse amplitude, which depends on the respective magnitude dimming
5 signal, and by a pulse duration, which depends on the respective pulse dimming signal, as shown in the diagram of Figure 2. Furthermore, all of the control signals generated by the signal combiners have a common cycle length for each of the starting pulses.

10

As shown in the diagram of Figure 2, preferably each one of the controlled signals has an individual cycle start that is determined by the respective time offset for said controlled signal. Hence, a change of the pulse amplitude of each one of
15 the control signals and, as a consequence, of the resulting supply currents, comes only into effect with a respective cycle start of said control signal. For example, controlled current sources are formed of voltage controlled current sources, which may be implemented by a transistor, in
20 particular a field-effect transistor, having a controlled current throughput depending on its control voltage. However, other forms of controlled current sources are well-known in the art.

25 Figure 1 further shows an example implementation for each of the signal combiners. In this example implementation, each signal combiner comprises a signal generator SG1, SG2, ..., SGn having two outputs, of which one controls a digital-to-analog converter DAC and of which the other controls a pulse-width
30 modulation generator PWM. Accordingly, the signal generator in conjunction with the DAC generates an analog amplitude signal based on the respective magnitude dimming signal, and in conjunction with the PWM generator generates a pulse

switching signal based on the respective pulse dimming signal. Furthermore, these signal generations preferably are dependent on at least one of the synchronization signal VSYNC and on the respective time offset for the associated channel.

5

For example, the time offset may be stored in the signal generator. For example, the time offset may be applied using the optional horizontal synchronization signal HSYNC, which separates scan lines by respective pulses. For example, the synchronization signal HSYNC has single short pulses which indicate the start of every line. Hence, the time offset for each channel may be expressed and/or implemented in the form of a number of sync pulses of the second synchronization signal HSYNC.

10

15

Having generated the analog amplitude signal and the associated pulse switching signal, the resulting control signal may be generated by modulating said analog amplitude signal with said pulse switching signal. For example, in the embodiment of Figure 1, this is done by controlling a switch that carries the analog amplitude signal with the pulse switching signal.

20

It should be noted that the example implementation of Figure 1 with respect to the signal combiners SC1 is only one of many possible options to generate the control signals.

25

Without going into detail, the control signals may also be generated by producing the pulsed signals as a digital signal in a digital signal processor and converting them into analog form by means of respective digital-to-analog converters.

30

Referring now to Figure 3, this figure shows another time signal diagram of the synchronization signal VSYNC and supply

currents, as in Figure 2. However, in contrast to the signals of Figure 2, the supply currents are not provided as a pulsed signal having zero value phases or defined low value phases but have fixed values throughout each cycle.

5

For example, as described for Figure 2, at the time instants t_1 new pairs of pulse dimming signal and magnitude dimming signal are provided, wherein the pulse dimming signals indicate a ratio between the pulse duration of each control
10 signal and a cycle length of said control signal to be equal to one. In other words, the effective value of the supply current is only determined by the magnitude dimming signal.

However, as described before for Figure 2, the changes
15 provided at instant t_1 come only into effect after the respective time offsets O_1 , O_2 , O_3 , O_n after the next starting pulse of the synchronization signal VSYNC at time instant t_2 .

20 Referring back to Figure 1, the lighting control system LCS can both be used for control applications, where a pulse duration is varied based on the pulse dimming signal or remains unvaried, thus always being on, depending on a specific pulse dimming signal. In both cases, the
25 synchronization of the magnitude dimming signal with respect to the time offset is performed.

Referring now to Figure 4, as indicated above, the signal processing unit SPU may be designed for generating a set MD,
30 PD of pairs of a magnitude dimming signal and a pulse dimming signal based on a set BV of brightness values for a plurality of LED channels to be supplied. In some implementations the generation of the set MD, PD may be based on a predefined

subset of the set BV, such that only the subset of brightness values is used for generating corresponding pairs of magnitude dimming signals and pulse dimming signals.

5 Preferably, the cardinality of such a subset corresponds to the number of LED channels to be supplied by one instance of a lighting control system. For example, if the cardinality of the set BV of brightness values is higher than the number of channels that can be supplied by one instance of a lighting
10 control system, several instances of such lighting control systems may be operated so to say in parallel, each lighting control system operable for supplying a different set of LED channels. The signal processing unit may be integrated into the lighting control system or may be external to the
15 lighting control system. Each instance of a lighting control system may be implemented in a separate semiconductor chip package, with or without the signal processing unit.

Figure 4 describes the function of the signal processing unit
20 with respect to the generation of the set MD, PD of pairs of magnitude dimming signals and pulse dimming signals from a set BV of brightness values. In particular, in the example implementation of Figure 4, several subsets of cardinality 4 are formed in the set BV, and each subset is used for
25 generating a respective set of four pairs of magnitude dimming signals and pulse dimming signals. In particular, the first subset consisting of brightness values BV1, BV2, BV3, BV4 is evaluated to generate the set of pairs with respective magnitude dimming signals MD1, MD2, MD3, MD4 and pulse
30 dimming signals PD1, PD2, PD3, PD4. In the same fashion, the subset with the brightness values BV5 to BV8 is processed to pairs MD5, PD5 to MD8, PD8.

In the present example, the set BV consist of N elements of brightness values, resulting in the same number of pairs. More generally speaking, each predefined subset of the brightness values is equinumerous to the corresponding set of
5 pairs. It should be noted that the number of elements of each subset being 4 has been chosen for explanatory reasons only and could be greater or less, depending on the number of LED channels that can be supplied by the lighting control system, in particular one instance of a lighting control system.

Claims

1. A lighting control system (LCS) for generating supply currents (ILED1, ILED2, ILEDn) for a first LED channel (CH1) and at least a second LED channel (CH2, CHn), the system comprising
 - a first controlled current source (CS1) for generating a first supply current (ILED1) for the first LED channel (CH1) based on a first control signal (CC1);
 - 10 - a second controlled current source (CS2) for generating a second supply current (ILED2) for the second LED channel (CH2) based on a second control signal (CC2);
 - a first signal combiner (SC1) for generating the first control signal (CC1) based on a synchronization signal (VSYNC) that comprises periodic starting pulses and on a combination of a first magnitude dimming signal (MD1) and a first pulse dimming signal (PD1); and
 - 15 - a second signal combiner (SC2) for generating the second control signal (CC2) based on the synchronization signal (VSYNC) and on a combination of a second magnitude dimming signal (MD2) and a second pulse dimming signal (PD2); wherein
 - the first and the second signal combiner are designed such that changes of the respective first and second control signals (CC1, CC2) come into effect only with a respective time offset with respect to one of the starting pulses of the synchronization signal (VSYNC).
 - 20
 - 25
2. The lighting control system (LCS) according to claim 1, wherein the time offset for the first signal combiner (SC1) is different from the time offset for the second signal combiner (SC2).
- 30

3. The lighting control system (LCS) according to claim 1 or 2, wherein all of the control signals generated by the signal combiners are pulse-width modulated signals that are defined by a pulse amplitude, which depends on the respective magnitude dimming signal, and by a pulse duration, which depends on the respective pulse dimming signal.

4. The lighting control system (LCS) according to claim 3, wherein all of the control signals generated by the signal combiners have a common cycle length for each of the starting pulses, and each one of the control signals has an individual cycle start that is determined by the respective time offset for said control signal.

5. The lighting control system (LCS) according to claim 4, wherein a change of the pulse amplitude of each one of the control signals comes only into effect with a respective cycle start of said control signal.

6. The lighting control system (LCS) according to one of claims 3 to 5, wherein a ratio between the pulse duration of each control signal and a cycle length of said control signal is less than or equal to one.

7. The lighting control system (LCS) according to one of claims 1 to 6, wherein each of the signal combiners is designed for generating a respective analog amplitude signal based on the respective magnitude dimming signal, for generating a respective pulse switching signal based on the respective pulse dimming signal, on the synchronization signal (VSYNC) and on the respective time offset, and for generating the respective control signal

by modulating said analog amplitude signal with said pulse switching signal.

8. The lighting control system (LCS) according to one of claims 1 to 7, wherein the time offset is preset, once-only or in an initialization phase, for each of said signal combiners.

9. The lighting control system (LCS) according to one of claims 1 to 8, further comprising a signal processing unit (SPU) for generating a set of pairs of a magnitude dimming signal and a pulse dimming signal, a first pair of said set including the first magnitude dimming signal (MD1) and the first pulse dimming signal (PD1) and a second pair of said set including the second magnitude dimming signal (MD2) and the second pulse dimming signal (PD2), based on a set of brightness values (BV1, BV2) for a plurality of LED channels to be supplied.

10. The lighting control system (LCS) according to claim 9, wherein the signal processing unit (SPU) is configured to generate said set of pairs based on a predefined subset of the set of brightness values, said set of pairs and said subset being equinumerous.

11. A method for generating supply currents (ILED1, ILED2, ILEDn) for supplying a plurality of LED channels (CH1, CH2, CHn), the method comprising, for each of the LED channels to be supplied:

- generating a control signal (CC1, CC2, CCn) for said LED channel based on a synchronization signal (VSYNC), which comprises periodic starting pulses, and on a combination of a magnitude dimming signal (MD1, MD2) for said LED

channel and a pulse dimming signal (PD1, PD2) for said LED channel, wherein changes of said control signal (CC1, CC2, CHn) come into effect only with a defined time offset with respect to one of the starting pulses of the synchronization signal (VSYNC); and

- generating, by means of a controlled current source (CS1, CS2, CSn) dedicated to said LED channel, a supply current for said LED channel based on said control signal.

12. The method according to claim 11, wherein the time offset is different for each of the LED channels (CH1, CH2, CHn) to be supplied.

13. The method according to claim 11 or 12, wherein, for each of the LED channels (CH1, CH2, CHn) to be supplied, said control signal is a pulse-width modulated signal that is defined by a pulse amplitude, which depends on said magnitude dimming signal for said LED channel, and by a pulse duration, which depends on said pulse dimming signal for said LED channel.

14. The method according to claim 13, wherein all of the control signals generated for each of the LED channels have a common cycle length for each of the starting pulses, and each one of said control signals has an individual cycle start that is determined by the time offset for the LED channel to be supplied.

15. The method according to claim 14, wherein, for each of the LED channels (CH1, CH2, CHn) to be supplied, a change of the pulse amplitude of said control signal comes only into effect with a respective cycle start of said control signal.

16. The method according to one of claims 13 to 15,
wherein a ratio between the pulse duration of each
control signal and a cycle length of said control signal
is less than or equal to one.

5

17. The method according to one of claims 11 to 16,
wherein, for each of the LED channels (CH1, CH2, CHn) to
be supplied, a respective analog amplitude signal is
generated based on the respective magnitude dimming
signal, a respective pulse switching signal is generated
based on the respective pulse dimming signal, on the
synchronization signal (VSYNC) and on the respective time
offset, and the respective control signal is generated by
modulating said analog amplitude signal with said pulse
switching signal.

10

15

18. The method according to one of claims 11 to 17,
wherein the time offset is preset, once-only or in an
initialization phase, for each of the LED channels (CH1,
CH2, CHn) to be supplied.

20

19. The method according to one of claims 11 to 18, further
comprising generating a set of pairs of a magnitude
dimming signal and a pulse dimming signal, each pair of
said set of pairs including the magnitude dimming signal
for one of the LED channels (CH1, CH2, CHn) to be
supplied and the associated pulse dimming signal of said
LED channel, based on a set of brightness values (BV1,
BV2, BVn) for each of the LED channels to be supplied.

25

30

20. The method according to claim 19,
wherein said set of pairs is generated based on a

predefined subset of the set of brightness values, said set of pairs and said subset being equinumerous.

Fig 1




Fig 2




Fig 3





Fig 4



INTERNATIONAL SEARCH REPORT

International application No
PCT/EP2016/055680

A. CLASSIFICATION OF SUBJECT MATTER
INV. H05B33/08 H05B37/02
ADD.

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
H05B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

EPO-Internal, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y	WO 2007/023454 A1 (KONINKL PHILIPS ELECTRONICS NV [NL]; PHILIPS LUMILEDS LIGHTING CO [US]) 1 March 2007 (2007-03-01) page 6, lines 10-16 - page 7, lines 1-7; figures 4,7,11,12 page 10, last line -----	1-20
Y	WO 2008/000465 A1 (AUSTRIAMICROSYSTEMS AG [AT]; PAURITSCH MANFRED [AT]) 3 January 2008 (2008-01-03) page 2, lines 19-22 - page 6, lines 1-9; figures 4, 5 -----	1-20
Y	US 2009/079359 A1 (SHTEYNBERG ANATOLY [US] ET AL) 26 March 2009 (2009-03-26) paragraphs [0119], [0142], [0157]; figures 4,5,16,25 ----- -/-	1-20



Further documents are listed in the continuation of Box C.



See patent family annex.

* Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier application or patent but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

18 May 2016

Date of mailing of the international search report

25/05/2016

Name and mailing address of the ISA/

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040,
Fax: (+31-70) 340-3016

Authorized officer

Müller, Uta

INTERNATIONAL SEARCH REPORT

International application No
PCT/EP2016/055680

C(Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y	US 2010/020004 A1 (SMITH ERIC [US]) 28 January 2010 (2010-01-28) paragraphs [0042], [0049], [0052]; figures 4-8 -----	1-20
Y	US 2014/139131 A1 (PARK JUNG EUI [KR] ET AL) 22 May 2014 (2014-05-22) figure 2 -----	1-20
Y	US 2012/019160 A1 (LEE HUNG-CHING [TW] ET AL) 26 January 2012 (2012-01-26) figure 1 -----	1-20
Y	WO 2011/058687 A1 (PANASONIC CORP [JP]; UEDA RYUJI; YAMAMOTO YASUNORI) 19 May 2011 (2011-05-19) figures 1,6, 9A, 9B, 10 -----	1-20
Y	US 2014/333859 A1 (ZHANG HUA [CN] ET AL) 13 November 2014 (2014-11-13) paragraphs [0010], [0012], [0033], [0036]; figures 1,2 -----	1-20
Y	US 2009/284459 A1 (WALLENER DAMIR [CA] ET AL) 19 November 2009 (2009-11-19) paragraphs [0009], [0023], [0027] -----	1-20

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/EP2016/055680

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO 2007023454	A1	01-03-2007	CN 101253813 A 27-08-2008
			EP 1922902 A1 21-05-2008
			JP 5281236 B2 04-09-2013
			JP 2007066897 A 15-03-2007
			TW I419100 B 11-12-2013
			US 2007046485 A1 01-03-2007
			WO 2007023454 A1 01-03-2007
WO 2008000465	A1	03-01-2008	DE 112007001559 T5 18-06-2009
			GB 2452439 A 04-03-2009
			JP 5328646 B2 30-10-2013
			JP 2009542020 A 26-11-2009
			KR 20090034911 A 08-04-2009
			US 2008007497 A1 10-01-2008
			WO 2008000465 A1 03-01-2008
US 2009079359	A1	26-03-2009	US 2009079359 A1 26-03-2009
			US 2011115394 A1 19-05-2011
US 2010020004	A1	28-01-2010	NONE
US 2014139131	A1	22-05-2014	KR 20140064519 A 28-05-2014
			US 2014139131 A1 22-05-2014
US 2012019160	A1	26-01-2012	TW 201206246 A 01-02-2012
			US 2012019160 A1 26-01-2012
WO 2011058687	A1	19-05-2011	JP 2011107259 A 02-06-2011
			WO 2011058687 A1 19-05-2011
US 2014333859	A1	13-11-2014	CN 103198799 A 10-07-2013
			DE 112013006696 T5 03-12-2015
			GB 2524213 A 16-09-2015
			JP 2016511438 A 14-04-2016
			US 2014333859 A1 13-11-2014
			WO 2014146308 A1 25-09-2014
US 2009284459	A1	19-11-2009	CA 2665561 A1 13-11-2009
			US 2009284459 A1 19-11-2009