



(12) **DEMANDE DE BREVET CANADIEN**
CANADIAN PATENT APPLICATION

(13) **A1**

(86) Date de dépôt PCT/PCT Filing Date: 2018/04/18 (87) Date publication PCT/PCT Publication Date: 2019/06/13 (85) Entrée phase nationale/National Entry: 2020/06/05 (86) N° demande PCT/PCT Application No.: CN 2018/083622 (87) N° publication PCT/PCT Publication No.: 2019/109570 (30) Priorités/Priorities: 2017/12/09 (CN201711299706.2); 2017/12/12 (CN201711322872.X)	(51) Cl.Int./Int.Cl. <i>H04W 72/12</i> (2009.01) (71) Demandeur/Applicant: HUAWEI TECHNOLOGIES CO., LTD., CN (72) Inventeurs/Inventors: LIU, XIANDA, CN; LIU, KUNPENG, CN; SHEN, ZUKANG, CN; CHENG, YAN, CN (74) Agent: GOWLING WLG (CANADA) LLP
---	--

(54) Titre : PROCÉDE DE SONDAGE DE CANAL ET EQUIPEMENT D'UTILISATEUR
(54) Title: CHANNEL MEASUREMENT METHOD AND USER EQUIPMENT

400




FIG. 3

(57) **Abrégé/Abstract:**

Provided in an embodiment of the present invention is a method for indication of a codebook. The invention specifies a precoding number sequence so as to reduce computation complexity for a UE unit. Also provided in the embodiment of the present invention is a user equipment unit. The technical solution provided in the embodiment of the present invention can optimize an indication of a codebook.

ABSTRACT

Embodiments of the present invention provide a codebook indication method, so as to reduce calculation complexity of UE by specifying a serial number sequence of precoding. The embodiments of the present invention further provide user equipment.

- 5 The technical solutions provided in the embodiments of the present invention may optimize indication of a codebook.

CHANNEL MEASUREMENT METHOD AND USER EQUIPMENT

TECHNICAL FIELD

[0001] Embodiments of the present invention relate to channel measurement
5 technologies, and in particular, to a channel measurement method and user equipment.

BACKGROUND

[0002] New Radio (new radio, NR) of a fifth generation (5th-Generation, 5G)
mobile communications technology supports a codebook-based uplink transmission
mode. A base station may configure at least one sounding reference signal (Sounding
10 Reference Signal, SRS) resource through higher-layer signaling. User equipment
(User equipment, UE) sends an SRS on the SRS resource based on the SRS resource
configured by the base station and indication signaling. The base station receives and
measures the SRS sent by the user equipment. When the base station schedules the
user to send uplink data, the base station indicates an SRS resource indication (SRS
15 resource indication, SRI), a transmission rank (Transmission rank indication, TRI),
and a transmission precoding matrix (Transmission precoding matrix indication,
TPMI) through downlink control information (DCI Downlink control information,
DCI). The UE determines, according to the indication information, a quantity of
transmission layers and a precoding manner that are used for sending data. The TRI
20 and the TPMI may be jointly coded, in other words, a quantity of transmission layers
and precoding matrix information can both be indicated by a state in one DCI field.
The quantity of transmission layers may be selected from a set {1, 2, 3, 4} and be
indicated, and the TPMI is selected and indicated based on Table 1 to Table 4.

Table 1. Codebook of one-layer transmission

Codebook index	One-layer transmission $\nu=1$								Minimum coherence capability
12–27	NR downlink codebook configured to code words in Codebook mode =1 and $O_1=2$								Fully coherent
4–11	$\frac{1}{2} \begin{bmatrix} 1 \\ 0 \\ 1 \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ 0 \\ -1 \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ 0 \\ j \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ 0 \\ -j \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 1 \\ 0 \\ 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 1 \\ 0 \\ -1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 1 \\ 0 \\ j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 1 \\ 0 \\ -j \end{bmatrix}$	Partially coherent
0–3	$\frac{1}{2} \begin{bmatrix} 1 \\ 0 \\ 0 \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 1 \\ 0 \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 0 \\ 1 \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 0 \\ 0 \\ 1 \end{bmatrix}$					Incoherent

Table 2. Codebook of two-layer transmission

Codebook index	Two-layer transmission $\nu=2$				Minimum coherence capability
6–9	$\frac{1}{2} \begin{bmatrix} 1 & 0 \\ 0 & 1 \\ 1 & 0 \\ 0 & -j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 0 \\ 0 & 1 \\ 1 & 0 \\ 0 & j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 0 \\ 0 & 1 \\ -j & 0 \\ 0 & 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 0 \\ 0 & 1 \\ -j & 0 \\ 0 & -1 \end{bmatrix}$	Partially coherent
10–13	$\frac{1}{2} \begin{bmatrix} 1 & 0 \\ 0 & 1 \\ -1 & 0 \\ 0 & -j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 0 \\ 0 & 1 \\ -1 & 0 \\ 0 & j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 0 \\ 0 & 1 \\ j & 0 \\ 0 & 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 0 \\ 0 & 1 \\ j & 0 \\ 0 & -1 \end{bmatrix}$	
14–21	NR downlink codebook configured to code words in Codebook mode =1, $O_1=2$, and $i_{1,3}=0$				Fully coherent
0–3	$\frac{1}{2} \begin{bmatrix} 1 & 0 \\ 0 & 1 \\ 0 & 0 \\ 0 & 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 0 \\ 0 & 0 \\ 0 & 1 \\ 0 & 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 0 \\ 0 & 0 \\ 0 & 0 \\ 0 & 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 & 0 \\ 1 & 0 \\ 0 & 1 \\ 0 & 0 \end{bmatrix}$	Incoherent

4-5	$\frac{1}{2} \begin{bmatrix} 0 & 0 \\ 1 & 0 \\ 0 & 0 \\ 0 & 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 & 0 \\ 0 & 0 \\ 1 & 0 \\ 0 & 1 \end{bmatrix}$		
-----	--	--	--	--

Table 3. Codebook of three-layer transmission

Codebook index	Three-layer transmission $v=3$				Minimum coherence capability
3-6	NR downlink codebook configured to Codebook mode =1-2, $O_1=2$, and $\{0,2\}$				Fully coherent
1-2	$\frac{1}{2} \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 1 & 0 & 0 \\ 0 & 0 & 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ -1 & 0 & 0 \\ 0 & 0 & 1 \end{bmatrix}$			Partially coherent
0	$\frac{1}{2} \begin{bmatrix} 1 & 0 & 0 \\ 0 & 1 & 0 \\ 0 & 0 & 1 \\ 0 & 0 & 0 \end{bmatrix}$				Incoherent

Table 4. Codebook of four-layer transmission

Codebook index	Four-layer transmission $v=4$				Minimum coherence capability
3-6	NR downlink codebook configured to Codebook mode =1-2, $O_1=2$, $i_{1,1} = 0$, and $i_{1,3} = 0$				Fully coherent
1-2	$\frac{1}{2\sqrt{2}} \begin{bmatrix} 1 & 1 & 0 & 0 \\ 0 & 0 & 1 & 1 \\ 1 & -1 & 0 & 0 \\ 0 & 0 & 1 & -1 \end{bmatrix}$	$\frac{1}{2\sqrt{2}} \begin{bmatrix} 1 & 1 & 0 & 0 \\ 0 & 0 & 1 & 1 \\ j & -j & 0 & 0 \\ 0 & 0 & j & -j \end{bmatrix}$			Partially coherent
0	$\frac{1}{2} \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix}$				Incoherent

[0003] For each rank, there are three types of coherence capabilities, and each type of coherence capability is corresponding to at least one precoding matrix. For

example, in Table 1, 16 precoding matrices can be selected from for "fully coherent", eight precoding matrices may be selected from for "partially coherent", and four precoding matrices may be selected from for "incoherent". The UE reports three types of coherence capabilities. The base station indicates a codebook subset limitation through RRC signaling, and a codebook subset limitation is used to indicate a codebook selection range for the TPMI. The codebook subset limitation includes three states respectively indicating "fully coherent", "partially coherent", and "incoherent". A specific indication method is as follows: One state is used to indicate that a codebook set indicated by the TPMI includes a codebook corresponding to "fully coherent", a codebook corresponding to "partially coherent", and a codebook corresponding to "incoherent". Another state is used to indicate that a codebook set indicated by the TPMI includes a codebook corresponding to "partially coherent" and a codebook corresponding to "incoherent". The other state is used to indicate that a codebook set indicated by the TPMI includes a codebook corresponding to "incoherent". Only one of the three states can be indicated. If the UE reports a partially coherent transmission capability, the base station cannot indicate that the codebook set indicated by the TPMI includes the codebook corresponding to "fully coherent". If the UE reports an incoherent transmission capability, the base station cannot indicate that the codebook set indicated by the TPMI includes the codebook corresponding to "fully coherent" and the codebook corresponding to "partially coherent". In this way, a size of the field obtained by jointly coding the TRI and the TPMI changes based on indications of the three states.

[0004] Table 1 to Table 4 are corresponding to a case in which the user equipment has four-antenna transmission and uses a cyclic prefix–orthogonal frequency division multiplexing (Cyclic Prefix–Orthogonal Frequency Division Multiple, CP-OFDM) waveform for sending data. When the user equipment has two-antenna transmission and uses a CP-OFDM waveform for sending data, a quantity of transmission layers is 1 or 2, and selection and indication of the TPMI are based on Table 5.

Table 5: Two-antenna codebook for a CP-OFDM waveform

Codebook index	One-layer transmission
----------------	------------------------

0–5	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ 0 \end{bmatrix}$	$\frac{1}{\sqrt{2}} \begin{bmatrix} 0 \\ 1 \end{bmatrix}$	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ 1 \end{bmatrix}$	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ -1 \end{bmatrix}$	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ j \end{bmatrix}$	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ -j \end{bmatrix}$	-	-
Codebook index	Two-layer transmission							
0–2	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 1 \\ 1 & -1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 & 1 \\ j & -j \end{bmatrix}$	-	-	-	-	-

[0005] When discrete Fourier transform–Spread–OFDM (DFT-Spread-OFDM, DFT-S-OFDM) is used, the quantity of transmission layers can only be 1, and selection and indication of the TPMI are based on Table 6 when the user equipment has two-antenna transmission, selection and indication of the TPMI are based on Table 7 when the user equipment has four-antenna transmission. In addition, the network device may use a higher-layer signaling indication to limit the quantity of transmission layers, so as to limit the selection of a subset from a set of maximum quantities of transmission layers to indicate the quantity of transmission layers and to indicate the TPMI. This can reduce signaling overheads for indicating the quantity of transmission layers and the TPMI.

Table 6: Two-antenna codebook for a DFT-S-OFDM waveform

Codebook index	One-layer transmission							
0–5	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ 0 \end{bmatrix}$	$\frac{1}{\sqrt{2}} \begin{bmatrix} 0 \\ 1 \end{bmatrix}$	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ 1 \end{bmatrix}$	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ -1 \end{bmatrix}$	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ j \end{bmatrix}$	$\frac{1}{\sqrt{2}} \begin{bmatrix} 1 \\ -j \end{bmatrix}$	-	-

Table 7: Four-antenna codebook for a DFT-S-OFDM waveform

Codebook index	One-layer transmission							
0–7	$\frac{1}{2} \begin{bmatrix} 1 \\ 0 \\ 0 \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 1 \\ 0 \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 0 \\ 1 \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 0 \\ 0 \\ 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ 0 \\ 1 \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ 0 \\ -1 \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ 0 \\ j \\ 0 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ 0 \\ -j \\ 0 \end{bmatrix}$

8-15	$\frac{1}{2} \begin{bmatrix} 0 \\ 1 \\ 0 \\ 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 1 \\ 0 \\ -1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 1 \\ 0 \\ j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 0 \\ 1 \\ 0 \\ -j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ 1 \\ 1 \\ -1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ 1 \\ j \\ j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ 1 \\ -1 \\ 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ 1 \\ -j \\ -j \end{bmatrix}$
16-23	$\frac{1}{2} \begin{bmatrix} 1 \\ j \\ 1 \\ j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ j \\ j \\ 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ j \\ -1 \\ -j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ j \\ -j \\ -1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ -1 \\ 1 \\ 1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ -1 \\ j \\ -j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ -1 \\ -1 \\ -1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ -1 \\ -j \\ j \end{bmatrix}$
24-27	$\frac{1}{2} \begin{bmatrix} 1 \\ -j \\ 1 \\ -j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ -j \\ j \\ -1 \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ -j \\ -1 \\ j \end{bmatrix}$	$\frac{1}{2} \begin{bmatrix} 1 \\ -j \\ -j \\ 1 \end{bmatrix}$	-	-	-	-

SUMMARY

[0006] Generally, user equipment (by way of example but not limitation, a terminal device such as a smartphone) sends an uplink reference signal (by way of example but not limitation, a sounding reference signal (Sounding Reference Signal, SRS)). An access device (by way of example but not limitation, a base station) receives the uplink reference signal, performs uplink channel measurement based on the uplink reference signal, determines an uplink transmission parameter, and notifies user equipment of the uplink transmission parameter by using, by way of example but not limitation, downlink control information (Downlink Control Information, DCI). The uplink transmission parameter may include, by way of example but not limitation, at least one of the following parameters: a channel quality indicator (Channel Quality Indicator, CQI), a rank indication (Rank Indication, RI), and a precoding matrix indicator (Precoding Matrix Indicator, PMI).

[0007] In the technical solutions provided in embodiments of the present invention, a transmission parameter entry set is used to organize transmission parameters. Specifically, each coherence capability is corresponding to one transmission parameter entry set. When determining a required transmission parameter entry (a transmission parameter entry indicated by transmission parameter indication information), the access device may traverse each transmission parameter entry in a transmission parameter entry set corresponding to a current coherence

capability, and determine a selected transmission parameter entry according to a principle of, by way of example but not limitation, channel capacity maximization or channel throughput maximization.

[0008] For a specific process of determining the foregoing information, refer to the prior art. For example, the access device may select a precoding matrix from a preset codebook according to the channel capacity maximization principle or the channel throughput maximization principle, and use a quantity of columns of the precoding matrix as a rank.

[0009] According to a first aspect, a transmission parameter indication method is provided, including:

generating transmission parameter indication information, wherein the transmission parameter indication information is used to indicate a transmission parameter entry selected from a transmission parameter entry set corresponding to a current coherence capability, and the transmission parameter entry is used to indicate a quantity of transmission layers and a precoding matrix; and

sending a transmission parameter indication information.

[0010] The transmission parameter indication method may be performed by an access device (such as a base station).

[0011] The selected transmission parameter entry may be sent by using DCI.

[0012] With reference to the first aspect, in a first possible implementation of the first aspect, the transmission parameter entry includes an index of the transmission parameter entry, a value of the quantity of transmission layers, and an index of the precoding matrix, and the precoding matrix is uniquely determined by using both the value of the quantity of transmission layers and the index of the precoding matrix. For example, when the value of the quantity of transmission layers is 1, an index 1 indicates a matrix A; or when the value of the quantity of transmission layers is 2, the index 1 indicates a matrix B. Therefore, the precoding matrix is uniquely determined by using both the value of the quantity of transmission layers and the index of the precoding matrix.

[0013] With reference to the first aspect, in a second possible implementation of the first aspect, the current coherence capability is one of the following capabilities:

"fully coherent";

"partial-coherent"; and

"incoherent".

[0014] With reference to the second possible implementation of the first aspect, a transmission parameter entry set corresponding to each coherence capability includes at least one transmission parameter entry, and a transmission parameter entry set corresponding to "incoherent" is a subset of a transmission parameter entry set corresponding to "partial-coherent", and the transmission parameter entry set corresponding to "partial-coherent" is a subset of a transmission parameter entry set corresponding to "fully coherent".

[0015] With reference to the first aspect, in a third possible implementation of the first aspect, the method further includes:

generating coherence capability indication information, wherein the coherence capability indication information is used to indicate the current coherence capability. One of the three coherence capabilities may be sent through RRC signaling before the transmission parameter indication information is generated.

[0016] With reference to the first aspect or the first to the third possible implementations of the first aspect, in a fourth possible implementation of the first aspect, the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
4	Two layers: TPMI=0	4	Two layers: TPMI=0	4	Two layers: TPMI=0
...	...	...	...	...	...
9	Two layers: TPMI=5	9	Two layers: TPMI=5	9	Two layers: TPMI=5
10	Three layers: TPMI=0	10	Three layers: TPMI=0	10	Three layers: TPMI=0
11	Four layers:	11	Four layers:	11	Four layers:

	TPMI=0		TPMI=0		TPMI=0
12	One layer: TPMI=4	12	One layer: TPMI=4		
...	...	...	...		
19	One layer: TPMI=11	19	One layer: TPMI=11		
20	Two layers: TPMI=6	20	Two layers: TPMI=6		
...	...	...	...		
27	Two layers: TPMI=13	27	Two layers: TPMI=13		
28	Three layers: TPMI=1	28	Three layers: TPMI=1		
29	Three layers: TPMI=2	29	Three layers: TPMI=2		
30	Four layers: TPMI=1	30	Four layers: TPMI=1		
31	Four layers: TPMI=2	31	Four layers: TPMI=2		
32	One layer: TPMI=12				
...	...				
47	One layer: TPMI=27				
48	Two layers: TPMI=14				
...	...				
55	Two layers: TPMI=21				
56	Three layers: TPMI=3				
...	...				
59	Three layers:				

	TPMI=6				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

[0017] With reference to the first aspect or the first to the fourth possible implementations of the first aspect, in a fifth possible implementation of the first aspect, the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
...	...	...	...	4	Two layers: TPMI=0
11	One layer: TPMI=11	11	One layer: TPMI=11	...	...
...	...	12	Two layers: TPMI=0	9	Two layers: TPMI=5
27	One layer: TPMI=27	...	...	10	Three layers: TPMI=0
28	Two layers: TPMI=0	17	Two layers: TPMI=5	11	Four layers: TPMI=0
...	...	...	...		
33	Two layers: TPMI=5	25	Two layers: TPMI=13		
...	...	26	Three layers: TPMI=0		
41	Two layers:	27	Three layers:		

	TPMI=13		TPMI=1		
...	...	...	...		
49	Two layers: TPMI=21	29	Four layers: TPMI=0		
50	Three layers: TPMI=0	30	Four layers: TPMI=1		
51	Three layers: TPMI=1	31	Four layers: TPMI=2		
...	...				
53	Three layers: TPMI=3				
...	...				
56	Three layers: TPMI=6				
57	Four layers: TPMI=0				
58	Four layers: TPMI=1				
...	...				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

[0018] According to a second aspect, a transmission parameter indication method is provided, including:

receiving transmission parameter indication information, wherein the
5 transmission parameter indication information is used to indicate a transmission parameter entry selected from a transmission parameter entry set corresponding to a current coherence capability, and the transmission parameter entry is used to indicate a quantity of transmission layers and a precoding matrix; and

determining the quantity of transmission layers and the precoding matrix
10 according to the transmission parameter indication information.

[0019] With reference to the second aspect, in a first possible implementation of

the second aspect, the transmission parameter entry includes an index of the transmission parameter entry, a value of the quantity of transmission layers, and an index of the precoding matrix, and the precoding matrix is uniquely determined by using both the value of the quantity of transmission layers and the index of the precoding matrix.

[0020] With reference to the second aspect, in a second possible implementation of the second aspect, the current coherence capability is one of the following capabilities:

"fully coherent";

"partial-coherent"; and

"incoherent".

[0021] With reference to the second possible implementation of the second aspect, a transmission parameter entry set corresponding to each coherence capability includes at least one transmission parameter entry, a transmission parameter entry set corresponding to "incoherent" is a subset of a transmission parameter entry set corresponding to "partial-coherent", and the transmission parameter entry set corresponding to "partial-coherent" is a subset of a transmission parameter entry set corresponding to "fully coherent".

[0022] With reference to the second aspect, in a third possible implementation of the second aspect, the method further includes:

generating coherence capability indication information, wherein the coherence capability indication information is used to indicate the current coherence capability.

[0023] With reference to the second aspect or the first to the third possible implementations of the second aspect, in a fourth possible implementation of the second aspect, the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...

3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
4	Two layers: TPMI=0	4	Two layers: TPMI=0	4	Two layers: TPMI=0
...	...	...	...	...	...
9	Two layers: TPMI=5	9	Two layers: TPMI=5	9	Two layers: TPMI=5
10	Three layers: TPMI=0	10	Three layers: TPMI=0	10	Three layers: TPMI=0
11	Four layers: TPMI=0	11	Four layers: TPMI=0	11	Four layers: TPMI=0
12	One layer: TPMI=4	12	One layer: TPMI=4		
...	...	...	...		
19	One layer: TPMI=11	19	One layer: TPMI=11		
20	Two layers: TPMI=6	20	Two layers: TPMI=6		
...	...	...	...		
27	Two layers: TPMI=13	27	Two layers: TPMI=13		
28	Three layers: TPMI=1	28	Three layers: TPMI=1		
29	Three layers: TPMI=2	29	Three layers: TPMI=2		
30	Four layers: TPMI=1	30	Four layers: TPMI=1		
31	Four layers: TPMI=2	31	Four layers: TPMI=2		
32	One layer: TPMI=12				
...	...				
47	One layer: TPMI=27				

48	Two layers: TPMI=14				
...	...				
55	Two layers: TPMI=21				
56	Three layers: TPMI=3				
...	...				
59	Three layers: TPMI=6				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

[0024] With reference to the second aspect or the first to the fourth possible implementations of the second aspect, in a fifth possible implementation of the second aspect, the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
...	...	...	...	4	Two layers: TPMI=0
11	One layer: TPMI=11	11	One layer: TPMI=11	...	...
...	...	12	Two layers: TPMI=0	9	Two layers: TPMI=5
27	One layer:	...	...	10	Three layers:

	TPMI=27				TPMI=0
28	Two layers: TPMI=0	17	Two layers: TPMI=5	11	Four layers: TPMI=0
...	...	...	...		
33	Two layers: TPMI=5	25	Two layers: TPMI=13		
...	...	26	Three layers: TPMI=0		
41	Two layers: TPMI=13	27	Three layers: TPMI=1		
...	...	...	...		
49	Two layers: TPMI=21	29	Four layers: TPMI=0		
50	Three layers: TPMI=0	30	Four layers: TPMI=1		
51	Three layers: TPMI=1	31	Four layers: TPMI=2		
...	...				
53	Three layers: TPMI=3				
...	...				
56	Three layers: TPMI=6				
57	Four layers: TPMI=0				
58	Four layers: TPMI=1				
...	...				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

[0025] According to a third aspect, an access device is provided, including:

a processing module, configured to generate transmission parameter indication information, wherein the transmission parameter indication information is used to indicate a transmission parameter entry selected from a transmission parameter entry set corresponding to a current coherence capability, and the
 5 transmission parameter entry is used to indicate a quantity of transmission layers and a precoding matrix; and

a transceiver module, configured to send the transmission parameter indication information.

[0026] With reference to the third aspect, in a first possible implementation of the
 10 third aspect, the transmission parameter entry includes an index of the transmission parameter entry, a value of the quantity of transmission layers, and an index of the precoding matrix, and the precoding matrix is uniquely determined by using both the value of the quantity of transmission layers and the index of the precoding matrix.

[0027] With reference to the third aspect, in a second possible implementation of
 15 the third aspect, the current coherence capability is one of the following capabilities:

"fully coherent";
 "partial-coherent"; and
 "incoherent".

[0028] With reference to the second possible implementation of the third aspect, a
 20 transmission parameter entry set corresponding to each coherence capability includes at least one transmission parameter entry, and a transmission parameter entry set corresponding to "incoherent" is a subset of a transmission parameter entry set corresponding to "partial-coherent", and the transmission parameter entry set corresponding to "partial-coherent" is a subset of a transmission parameter entry set
 25 corresponding to "fully coherent".

[0029] With reference to the third aspect, in a third possible implementation of the third aspect, the method further includes:

generating coherence capability indication information, where the coherence capability indication information is used to indicate the current coherence
 30 capability.

[0030] With reference to the third aspect or the first to the third possible implementations of the third aspect, in a fourth possible implementation of the third aspect, the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
4	Two layers: TPMI=0	4	Two layers: TPMI=0	4	Two layers: TPMI=0
...	...	...	...	...	...
9	Two layers: TPMI=5	9	Two layers: TPMI=5	9	Two layers: TPMI=5
10	Three layers: TPMI=0	10	Three layers: TPMI=0	10	Three layers: TPMI=0
11	Four layers: TPMI=0	11	Four layers: TPMI=0	11	Four layers: TPMI=0
12	One layer: TPMI=4	12	One layer: TPMI=4		
...	...	...	...		
19	One layer: TPMI=11	19	One layer: TPMI=11		
20	Two layers: TPMI=6	20	Two layers: TPMI=6		
...	...	...	...		
27	Two layers: TPMI=13	27	Two layers: TPMI=13		
28	Three layers: TPMI=1	28	Three layers: TPMI=1		
29	Three layers: TPMI=2	29	Three layers: TPMI=2		
30	Four layers: TPMI=1	30	Four layers: TPMI=1		

31	Four layers: TPMI=2	31	Four layers: TPMI=2		
32	One layer: TPMI=12				
...	...				
47	One layer: TPMI=27				
48	Two layers: TPMI=14				
...	...				
55	Two layers: TPMI=21				
56	Three layers: TPMI=3				
...	...				
59	Three layers: TPMI=6				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

[0031] With reference to the third aspect or the first to the fourth possible implementations of the third aspect, in a fifth possible implementation of the third aspect, the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3

...	...	...	...	4	Two layers: TPMI=0
11	One layer: TPMI=11	11	One layer: TPMI=11	...	...
...	...	12	Two layers: TPMI=0	9	Two layers: TPMI=5
27	One layer: TPMI=27	...	...	10	Three layers: TPMI=0
28	Two layers: TPMI=0	17	Two layers: TPMI=5	11	Four layers: TPMI=0
...	...	...	...		
33	Two layers: TPMI=5	25	Two layers: TPMI=13		
...	...	26	Three layers: TPMI=0		
41	Two layers: TPMI=13	27	Three layers: TPMI=1		
...	...	...	...		
49	Two layers: TPMI=21	29	Four layers: TPMI=0		
50	Three layers: TPMI=0	30	Four layers: TPMI=1		
51	Three layers: TPMI=1	31	Four layers: TPMI=2		
...	...				
53	Three layers: TPMI=3				
...	...				
56	Three layers: TPMI=6				
57	Four layers: TPMI=0				
58	Four layers: TPMI=1				

...	...				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

[0032] According to a fourth aspect, user equipment is provided, including:

a transceiver module, configured to receive transmission parameter indication information, wherein the transmission parameter indication information is used to indicate a transmission parameter entry selected from a transmission parameter entry set corresponding to a current coherence capability, and the transmission parameter entry is used to indicate a quantity of transmission layers and a precoding matrix; and

a processing module, configured to determine the quantity of transmission layers and the precoding matrix according to the transmission parameter indication information.

[0033] With the reference to the fourth aspect, in a first possible implementation of the fourth aspect, the transmission parameter entry includes an index of the transmission parameter entry, a value of the quantity of transmission layers, and an index of the precoding matrix, and the precoding matrix is uniquely determined by using both the value of the quantity of transmission layers and the index of the precoding matrix.

[0034] With reference to the fourth aspect, in a second possible implementation of the fourth aspect, the current coherence capability is one of the following capabilities:

"fully coherent";
"partial-coherent"; and
"incoherent".

[0035] With reference to the second possible implementation of the fourth aspect, a transmission parameter entry set corresponding to each coherence capability includes at least one transmission parameter entry, and a transmission parameter entry set corresponding to "incoherent" is a subset of a transmission parameter entry set corresponding to "partial-coherent", and the transmission parameter entry set corresponding to "partial-coherent" is a subset of a transmission parameter entry set corresponding to "fully coherent".

[0036] With reference to the fourth aspect, in a third possible implementation of the fourth aspect, the method further includes:

generating coherence capability indication information, wherein the coherence capability indication information is used to indicate the current coherence capability.

[0037] With reference to the fourth aspect or the first to the third possible implementations of the fourth aspect, in a fourth possible implementation of the fourth aspect, the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
4	Two layers: TPMI=0	4	Two layers: TPMI=0	4	Two layers: TPMI=0
...	...	...	...	...	...
9	Two layers: TPMI=5	9	Two layers: TPMI=5	9	Two layers: TPMI=5
10	Three layers: TPMI=0	10	Three layers: TPMI=0	10	Three layers: TPMI=0
11	Four layers: TPMI=0	11	Four layers: TPMI=0	11	Four layers: TPMI=0
12	One layer: TPMI=4	12	One layer: TPMI=4		
...	...	...	...		
19	One layer: TPMI=11	19	One layer: TPMI=11		
20	Two layers: TPMI=6	20	Two layers: TPMI=6		

...	...	...	...		
27	Two layers: TPMI=13	27	Two layers: TPMI=13		
28	Three layers: TPMI=1	28	Three layers: TPMI=1		
29	Three layers: TPMI=2	29	Three layers: TPMI=2		
30	Four layers: TPMI=1	30	Four layers: TPMI=1		
31	Four layers: TPMI=2	31	Four layers: TPMI=2		
32	One layer: TPMI=12				
...	...				
47	One layer: TPMI=27				
48	Two layers: TPMI=14				
...	...				
55	Two layers: TPMI=21				
56	Three layers: TPMI=3				
...	...				
59	Three layers: TPMI=6				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

[0038] With reference to the fourth aspect or the first to the fourth possible implementations of the fourth aspect, in a fifth possible implementation of the fourth aspect, the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
...	...	...	...	4	Two layers: TPMI=0
11	One layer: TPMI=11	11	One layer: TPMI=11	...	...
...	...	12	Two layers: TPMI=0	9	Two layers: TPMI=5
27	One layer: TPMI=27	...	...	10	Three layers: TPMI=0
28	Two layers: TPMI=0	17	Two layers: TPMI=5	11	Four layers: TPMI=0
...	...	...	...		
33	Two layers: TPMI=5	25	Two layers: TPMI=13		
...	...	26	Three layers: TPMI=0		
41	Two layers: TPMI=13	27	Three layers: TPMI=1		
...	...	...	...		
49	Two layers: TPMI=21	29	Four layers: TPMI=0		
50	Three layers: TPMI=0	30	Four layers: TPMI=1		
51	Three layers: TPMI=1	31	Four layers: TPMI=2		
...	...				

53	Three layers: TPMI=3				
...	...				
56	Three layers: TPMI=6				
57	Four layers: TPMI=0				
58	Four layers: TPMI=1				
...	...				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

BRIEF DESCRIPTION OF DRAWINGS

[0039] FIG. 1 is an example schematic diagram of a wireless communications network according to an embodiment of the present invention;

5 [0040] FIG. 2 is an example flowchart of a channel measurement method according to an embodiment of the present invention;

[0041] FIG. 3 is an example flowchart of a channel measurement method according to an embodiment of the present invention;

10 [0042] FIG. 4 is an example schematic diagram of a logical structure of a communications device according to an embodiment of the present invention; and

[0043] FIG. 5 is an example schematic diagram of a hardware structure of a communications device according to an embodiment of the present invention.

DESCRIPTION OF EMBODIMENTS

15 [0044] A next-generation wireless communications system currently in the research and development phase may also be referred to as a New Radio (New Radio, NR) system or a 5G system. The latest research shows that the next-generation

wireless communications standard supports semi-static channel measurement, and CSI obtained through semi-static channel measurement may be transmitted by using a physical uplink shared channel (Physical Uplink Shared Channel, PUSCH). In supporting semi-static channel measurement, one of problems to be resolved first is how to notify user equipment to start and stop semi-static channel measurement. Embodiments of the present invention provide a technical solution, which helps resolve the foregoing problem. The following describes the technical solutions provided in the embodiments of the present invention with reference to accompanying drawings and specific embodiments.

[0045] The embodiments of the present invention provide a communications device, and the communications device may be configured to implement the access device, or may be configured to implement the user equipment. The communications device includes a processor and a transceiver. The processor is configured to execute an operation of the processing module, and the transceiver is configured to execute an operation executed by the transceiver module.

[0046] In a specific implementation process, the processor may be configured to perform, by way of example but not limitation, baseband-related processing, and the transceiver may be configured to perform, by way of example but not limitation, radio frequency transmission/reception. The foregoing components may be separately disposed on mutually independent chips, or some or all of the foregoing components may be disposed on one chip. For example, the processor may be further classified into an analog baseband processor and a digital baseband processor. The analog baseband processor may be integrated with the transceiver on a same chip, and the digital baseband processor may be disposed on an independent chip. With continuous development of integrated circuit technologies, more components can be integrated on one chip. For example, a digital baseband processor may be integrated with a plurality of application processors (by way of example but not limitation, a graphics processing unit or a multimedia processor) on one chip. Such a chip may be referred to as a system on chip (System on Chip). Whether components are independently disposed on different chips or are disposed on one or more chips in an integrated manner depends on a specific requirement of a product design. Specific implementation forms of the foregoing components are not limited in the embodiments of the present invention.

[0047] The embodiments of the present invention further provide a processor,

configured to perform the foregoing methods. When these methods are being performed, processes of sending and receiving the information in the foregoing methods may be understood as processes in which the processor outputs the information and receives the input information. Specifically, when outputting the information, the processor outputs the information to the transceiver, so that the transceiver transmits the information. Further, after being output by the processor, the information may be processed in another manner before arriving at the transceiver. Similarly, when the processor receives the input information, the transceiver receives the information and inputs the information into the processor. Further, after the transceiver receives the information, the information may be processed in another manner before being input into the processor.

[0048] According to the foregoing principle, for example, the receiving transmission parameter indication information mentioned in the foregoing method may be understood as receiving the input transmission parameter indication information by the processor. For another example, sending the transmission parameter indication information may be understood as outputting the transmission parameter indication information by the processor.

[0049] In this way, for operations such as transmission, sending, and reception involving the processor, if there is no special description, or if the operations do not conflict with an actual function or an internal logic of the operations in related description, the operations may be more generally understood as outputting and input-reception operations performed by the processor, instead of transmission, sending, and reception operations directly performed by a radio frequency circuit and an antenna.

[0050] In a specific implementation process, the processor may be a dedicated processor performing these methods, or may be a processor that performs these methods by executing a computer instruction in a memory, for example, a general purpose processor. The memory may be a non-transitory (non-transitory) memory, for example, a read-only memory (Read Only Memory, ROM). The memory may be integrated with the processor on one chip, or the memory and the processor may be separately disposed on different chips. A type of the memory and a manner of disposing the memory and the processor are not limited in the embodiments of the present invention.

[0051] According to a twentieth aspect of the embodiments of the present

invention, a computer readable storage medium is provided, including an instruction. A computer performs the foregoing methods when the instruction runs on the computer. Further, the computer readable storage medium is a non-transitory computer readable storage medium.

5 [0052] According to a twenty-first aspect of the embodiments of the present invention, a computer program product that includes an instruction is provided. A computer performs the foregoing methods when the instruction runs on the computer.

[0053] FIG. 1 is an example schematic diagram of a wireless communications network 100 according to an embodiment of the present invention. As shown in FIG. 1,
10 the wireless communications network 100 includes base stations 102 to 106 and terminal devices 108 to 122. The base stations 102 to 106 may communicate with each other by using backhaul (backhaul) links (shown by straight lines between the base stations 102 to 106). The backhaul link may be a wired backhaul link (for example, an optical fiber and a copper wire) or a wireless backhaul link (for example,
15 microwave). The terminal devices 108 to 122 may communicate with the corresponding base stations 102 to 106 by using wireless links (shown by broken lines between the base stations 102 to 106 and the terminal devices 108 to 122).

[0054] The base stations 102 to 106 usually serve as access devices to provide a wireless access service for the terminal devices 108 to 122 that usually serve as user
20 equipment. Specifically, each base station is corresponding to a service coverage area (also referred to as a cell, as shown by elliptical areas in FIG. 1), and a terminal device entering the area may communicate with the base station by using a radio signal, so as to get a wireless access service provided by the base station. Service coverage areas of the base stations may overlap, and a terminal device in an overlapping area may
25 receive radio signals from a plurality of base stations. Therefore, the base stations may cooperate with each other to provide services for the terminal device. For example, the plurality of base stations may provide a service for the terminal device in the overlapping area by using a coordinated multipoint transmission/reception (Coordinated multipoint, CoMP) technology. For example, as shown in FIG. 1, service
30 coverage areas of the base station 102 and the base station 104 have an overlapping area and a terminal device 112 is located in the overlapping area. Therefore, the terminal device 112 may receive a radio signal from each of the base station 102 and the base station 104. The base station 102 and the base station 104 may cooperate with each other to provide a service for the terminal device 112. For another example,

as shown in FIG. 1, service coverage areas of the base station 102, the base station 104, and the base station 106 have a common overlapping area and a terminal device 120 is located in the overlapping area. Therefore, the terminal device 120 may receive a radio signal from each of the base stations 102, 104, and 106. The base stations 102, 104, and 106 cooperate with each other to provide a service for the terminal device 120.

[0055] The base station may also be referred to as a Node B (NodeB), an evolved NodeB (evolved NodeB, eNodeB), an access point (Access Point, AP), or the like, depending on which wireless communications technology is used. Alternatively, based on a size of a provided service coverage area, the base stations may be classified into a macro base station configured to provide a macro cell (Macro cell), a micro base station configured to provide a pico cell (Pico cell), and a femto base station configured to provide a femto cell (Femto cell). With continuous evolution of wireless communications technologies, a future base station may use another name.

[0056] The terminal devices 108 to 122 may be various wireless communications devices that have a wireless communication function, by way of example but not limitation, a mobile cellular phone, a cordless telephone, a personal digital assistant (Personal Digital Assistant, PDA), a smartphone, a notebook computer, a tablet computer, a wireless data card, a wireless modem (Modulator demodulator, Modem), or a wearable device such as a smart watch. With emergence of an Internet of Things (Internet of things, IoT) technology and a vehicle-to-everything (Vehicle-to-everything, V2X) technology, more devices without a communication function before, by way of example but not limitation, a home appliance, a transportation vehicle, a tool device, a service device, and a service facility, start to configure a wireless communications unit to obtain a wireless communication function, so as to access a wireless communications network and be remotely controlled. Such a device configured with a wireless communications unit has a wireless communication function, and therefore belongs to a wireless communications device. In addition, the terminal devices 108 to 122 may also be referred to as a mobile station, a mobile device, a mobile terminal, a wireless terminal, a handheld device, a client, and the like.

[0057] Each of the base stations 102 to 106 and the terminal devices 108 to 122 can be configured with a plurality of antennas, so as to support a MIMO (multiple-input multiple-output, Multiple Input Multiple Output) technology. Further,

the base stations 102 to 106 and the terminal devices 108 to 122 may support a single-user MIMO (Single-User MIMO, SU-MIMO) technology, or may support multi-user MIMO (Multi-User MIMO, MU-MIMO). The MU-MIMO may be implemented based on a space division multiple access (Space Division Multiple Access, SDMA) technology. Because a plurality of antennas are configured, the base stations 102 to 106 and the terminal devices 108 to 122 may also flexibly support a single-input single-output (Single Input Single Output, SISO) technology, a single-input multiple-output (Single Input Multiple Output, SIMO) technology, and a multiple-input single-output (Multiple Input Single Output, MISO) technology, so as to implement various diversity technologies (by way of example but not limitation, a transmit diversity and a receive diversity) and multiplexing technologies. The diversity technology may include but is not limited to a transmit diversity (Transmit Diversity, TD) technology and a receive diversity (Receive Diversity, RD) technology. The multiplexing technology may be a spatial multiplexing (Spatial Multiplexing) technology. The foregoing technologies may further include multiple implementation solutions. For example, the transmit diversity technology may include, by way of example but not limitation, a space time transmit diversity (Space-Time Transmit Diversity, STTD), a space-frequency transmit diversity (Space-Frequency Transmit Diversity, SFTD), a time switched transmit diversity (Time Switched Transmit Diversity, TSTD), a frequency switched transmit diversity (Frequency Switch Transmit Diversity, FSTD), an orthogonal transmit diversity (Orthogonal Transmit Diversity, OTD), a cyclic delay diversity (Cyclic Delay Diversity, CDD), and another diversity manner, and may further include a diversity manner derived from, evolving from, or combining any of the foregoing diversity manners. For example, currently, an LTE (Long Term Evolution, Long Term Evolution) standard uses a transmit diversity manner such as space time block coding (Space Time Block Coding, STBC), a space frequency block coding (Space Frequency Block Coding, SFBC), and the CDD. The transmit diversity is generally described above by using examples. A person skilled in the art should understand that the transmit diversity further includes implementations other than the foregoing examples. Therefore, the foregoing description should not be construed as a limitation on the technical solutions of the present invention. The technical solutions of the present invention should be understood as applicable to various possible transmit diversity solutions.

[0058] In addition, the base stations 102 to 106 and the terminal devices 108 to

122 may communicate with each other by using various wireless communications technologies, by way of example but not limitation, a Time Division Multiple Access (Time Division Multiple Access, TDMA) technology, a Frequency Division Multiple Access (Frequency Division Multiple Access, FDMA) technology, a Code Division Multiple Access (Code Division Multiple Access, CDMA) technology, Time Division-Synchronous Code Division Multiple Access (Time Division-Synchronous Code Division Multiple Access, TD-SCDMA), an orthogonal frequency division multiple access (Orthogonal FDMA, OFDMA) technology, a single carrier frequency division multiple access (Single Carrier FDMA, SC-FDMA) technology, a space division multiple access (Space Division Multiple Access, SDMA) technology, and a technology evolving or derived from these technologies. The foregoing wireless communications technologies are used in many wireless communications standards as a radio access technology (Radio Access Technology, RAT), thereby constructing various well-known wireless communications systems (or networks), including but not limited to Global System for Mobile Communications (Global System for Mobile Communications, GSM), CDMA 2000, wideband CDMA (Wideband CDMA, WCDMA), WiFi defined in a series of 802.22 standards, Worldwide Interoperability for Microwave Access (Worldwide Interoperability for Microwave Access, WiMAX), Long Term Evolution (Long Term Evolution, LTE), LTE-Advanced (LTE-Advanced, LTE-A), a system evolving from these wireless communications systems, and the like. Unless otherwise specified, the technical solutions provided in the embodiments of the present invention may be applied to the foregoing wireless communications technologies and wireless communications systems. In addition, the terms "system" and "network" can be interchanged.

25 **[0059]** It should be noted that the wireless communications network 100 shown in FIG. 1 is merely used as an example, and is not intended to limit the technical solutions of the present invention. A person skilled in the art should understand that in a specific implementation process, the wireless communications network 100 may further include another device, and may configure quantities of base stations and terminal devices based on a specific requirement.

30 **[0060]** FIG. 2 is an example flowchart of a channel measurement method 300 according to an embodiment of the present invention. In a specific implementation process, the method 300 may be performed by user equipment.

[0061] Step 302: Receive transmission parameter indication information, wherein

the transmission parameter indication information is used to indicate a transmission parameter entry selected from a transmission parameter entry set corresponding to a current coherence capability, and the transmission parameter entry is used to indicate a quantity of transmission layers and a precoding matrix.

5 [0062] Step 304: Send a transmission parameter indication information.

[0063] In Embodiment 1 of the present invention, a state in a field obtained by jointly coding a TRI and a TPMI is used to indicate the TRI and the TPMI used for data transmission. Each TRI value is corresponding to one group of precoding matrices, and the correspondence is shown in Table 1 to Table 4. When a quantity of transmission layers is indicated, a TPMI is used to indicate one precoding matrix selected from a group of precoding matrices corresponding to the quantity of transmission layers. Table 8 is an example of jointly coding a TRI and a TPMI. The indicated quantity of transmission layers, namely, the TRI, is indicated by using a layer x in the table, where a value range of x is {1, 2, 3, 4}. The indicated precoding matrix is indicated by using TPMI=y in the table, where y is a positive integer greater than or equal to 1, and a value range of y is determined based on a quantity of precoding matrices corresponding to three UE capabilities corresponding to each quantity of transmission layers in Table 1 to Table 4. In this embodiment, for each UE capability, indexes of the field obtained by jointly coding the TRI and the TPMI are sorted in an ascending order of ranks. As shown in Table 8, in case of a "fully coherent" transmission capacity, indexes 0 to 27 of the field indicate layer 1 transmission, and each index is corresponding to one precoding matrix index that is corresponding to the layer 1 transmission and that includes a codeword corresponding to "fully coherent", a codeword corresponding to "partially coherent", and a codeword corresponding to "incoherent". Indexes 28 to 49 of the field indicate layer 2 transmission, and each index is corresponding to one precoding matrix index that is corresponding to the layer 2 transmission and that includes a codeword corresponding to "fully coherent", a codeword corresponding to "partially coherent", and a codeword corresponding to "incoherent". Indexes 50 to 56 of the field indicate layer 3 transmission, and each index is corresponding to one precoding matrix index that is corresponding to the layer 3 transmission and that includes a codeword corresponding to "fully coherent", a codeword corresponding to "partially coherent", and a codeword corresponding to "incoherent". Indexes 57 to 61 of the field indicate layer 4 transmission, and each index is corresponding to one precoding matrix index that is

corresponding to the layer 4 transmission and that includes a codeword corresponding to "fully coherent", a codeword corresponding to "partially coherent", and a codeword corresponding to "incoherent".

Table 8. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
...	...	...	...	4	Two layers: TPMI=0
11	One layer: TPMI=11	11	One layer: TPMI=11	...	...
...	...	12	Two layers: TPMI=0	9	Two layers: TPMI=5
27	One layer: TPMI=27	...	...	10	Three layers: TPMI=0
28	Two layers: TPMI=0	17	Two layers: TPMI=5	11	Four layers: TPMI=0
...	...	...	...	12–15	Reserved
33	Two layers: TPMI=5	25	Two layers: TPMI=13		
...	...	26	Three layers: TPMI=0		
41	Two layers: TPMI=13	27	Three layers: TPMI=1		
...	...	...	...		
49	Two layers:	29	Four layers:		

	TPMI=21		TPMI=0		
50	Three layers: TPMI=0	30	Four layers: TPMI=1		
51	Three layers: TPMI=1	31	Four layers: TPMI=2		
...	...				
53	Three layers: TPMI=3				
...	...				
56	Three layers: TPMI=6				
57	Four layers: TPMI=0				
58	Four layers: TPMI=1				
...	...				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				
62–64	Reserved				

- [0064] A signaling indication in Table 8 is corresponding to a case in which the user equipment has four-antenna transmission, a maximum quantity of transmission layers is 4, and a CP-OFDM waveform is used for sending data. When the user equipment has two-antenna transmission, a CP-OFDM waveform is used for sending data, and a maximum quantity of transmission layers is 2, a signaling indication is designed according to the same principle, as shown in Table 9.

Table 9. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0

1	One layer: TPMI=1	1	One layer: TPMI=1
2	One layer: TPMI=2	2	Two layers: TPMI=0
...	...	3	Reserved
5	One layer: TPMI=5		
6	Two layers: TPMI=0		
...	...		
8	Two layers: TPMI=2		
9–15	Reserved		

[0065] When the user equipment has two-antenna transmission, a CP-OFDM waveform is used for sending data, and a maximum quantity of transmission layers is 1, a signaling indication is designed according to the same principle, as shown in Table 10.

Table 10. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1
2	One layer: TPMI=2	2–3	Reserved
...	...		
5	One layer: TPMI=5		
6–7	Reserved		

[0066] When DFT-S-OFDM is used and the user equipment has two-antenna transmission, a TPMI is indicated based on Table 10.

[0067] The signaling indication in Table 8 may further be corresponding to a case in which the user equipment has four-antenna transmission, a maximum quantity of transmission layers is 3 or 2, and a CP-OFDM waveform is used for sending data. When the user equipment has four-antenna transmission, a CP-OFDM waveform is used for sending data, and a maximum quantity of transmission layers is 1, a signaling indication is designed according to the same principle, as shown in Table 11.

Table 11. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
...	...	...	...		
11	One layer: TPMI=11	11	One layer: TPMI=11		
...	...	12–15	Reserved		
27	One layer: TPMI=27				
28–31	Reserved				

[0068] In Embodiment 2 of the present invention, a state in a field obtained by jointly coding a TRI and a TPMI is used to indicate the TRI and the TPMI used for data transmission. Each TRI value is corresponding to one group of precoding matrices, and the correspondence is shown in Table 1 to Table 4. When a quantity of transmission layers is indicated, a TPMI is used to indicate one precoding matrix selected from a group of precoding matrices corresponding to the quantity of transmission layers. Table 12 is an example of jointly coding a TRI and a TPMI. The indicated quantity of transmission layers, namely, the TRI, is indicated by using a layer x in the table, where a value range of x is {1, 2, 3, 4}. The indicated precoding matrix is indicated by using TPMI=y in the table, where y is a positive integer greater than or equal to 1, and a value range of y is determined based on a quantity of precoding matrices corresponding to three UE capabilities corresponding to each quantity of transmission layers in Table 1 to Table 4. In this embodiment, for partially coherent transmission, indexes of the field start from 0, precoding matrices corresponding to incoherent transmission are preferably sorted, and a sorting order is

the same as that of precoding matrix indexes corresponding to the incoherent transmission. Precoding matrix indexes corresponding to the partially coherent transmission are sorted after all the precoding matrix indexes corresponding to the incoherent transmission are sorted. For fully coherent transmission, indexes of the field start from 0, precoding matrices corresponding to incoherent transmission are preferably sorted, and a sorting order is the same as that of precoding matrix indexes corresponding to the incoherent transmission. Precoding matrix indexes corresponding to partially coherent transmission are sorted after all the precoding matrix indexes corresponding to the incoherent transmission are sorted. Precoding matrix indexes corresponding to the fully coherent transmission are sorted after all the precoding matrix indexes corresponding to the incoherent transmission are sorted.

Table 12. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
4	Two layers: TPMI=0	4	Two layers: TPMI=0	4	Two layers: TPMI=0
...	...	...	...	...	...
9	Two layers: TPMI=5	9	Two layers: TPMI=5	9	Two layers: TPMI=5
10	Three layers: TPMI=0	10	Three layers: TPMI=0	10	Three layers: TPMI=0
11	Four layers: TPMI=0	11	Four layers: TPMI=0	11	Four layers: TPMI=0
12	One layer: TPMI=4	12	One layer: TPMI=4	12–15	Reserved

...	...	...	...		
19	One layer: TPMI=11	19	One layer: TPMI=11		
20	Two layers: TPMI=6	20	Two layers: TPMI=6		
...	...	...	...		
27	Two layers: TPMI=13	27	Two layers: TPMI=13		
28	Three layers: TPMI=1	28	Three layers: TPMI=1		
29	Three layers: TPMI=2	29	Three layers: TPMI=2		
30	Four layers: TPMI=1	30	Four layers: TPMI=1		
31	Four layers: TPMI=2	31	Four layers: TPMI=2		
32	One layer: TPMI=12				
...	...				
47	One layer: TPMI=27				
48	Two layers: TPMI=14				
...	...				
55	Two layers: TPMI=21				
56	Three layers: TPMI=3				
...	...				
59	Three layers: TPMI=6				
60	Four layers: TPMI=3				

61	Four layers: TPMI=4				
62–64	Reserved				

- [0069] A signaling indication in Table 12 is corresponding to a case in which the user equipment has four-antenna transmission, a maximum quantity of transmission layers is 4, and a CP-OFDM waveform is used for sending data. When the user equipment has two-antenna transmission, a CP-OFDM waveform is used for sending data, and a maximum quantity of transmission layers is 2, a signaling indication is designed according to the same principle, as shown in Table13.

Table 13. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1
2	Two layers: TPMI=0	2	Two layers: TPMI=0
3	One layer: TPMI=2	3	Reserved
...	...		
6	One layer: TPMI=5		
7	Two layers: TPMI=1		
8	Two layers: TPMI=2		
9–15	Reserved		

- 10 [0070] When the user equipment has two-antenna transmission, a CP-OFDM waveform is used for sending data, and a maximum quantity of transmission layers is 1, a signaling indication is designed according to the same principle, as shown in Table 14.

Table 14. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Incoherent transmission
-------------	-----------------------------	-------------	-------------------------

0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1
2	One layer: TPMI=2	2–3	Reserved
...	...		
5	One layer: TPMI=5		
6–7	Reserved		

[0071] When DFT-S-OFDM is used and the user equipment has two-antenna transmission, a TPMI is indicated based on Table 14.

[0072] The signaling indication in Table 12 may further be corresponding to a case in which the user equipment has four-antenna transmission, a maximum quantity of transmission layers is 3 or 2, and a CP-OFDM waveform is used for sending data. When the user equipment has four-antenna transmission, a CP-OFDM waveform is used for sending data, and a maximum quantity of transmission layers is 1, a signaling indication is designed according to the same principle, as shown in Table 15.

10

Table 15. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
...	...	...	...		
11	One layer: TPMI=11	11	One layer: TPMI=11		
...	...	12–15	Reserved		
27	One layer: TPMI=27				

28-31	Reserved				
-------	----------	--	--	--	--

[0073] The technical details in the method 300 are described in detail above with reference to the method 200. Therefore, details are not described herein again.

[0074] FIG. 3 is an example flowchart of a channel measurement method 400 according to an embodiment of the present invention. In a specific implementation process, the method 400 may be performed by user equipment.

[0075] Step 402: Receive transmission parameter indication information.

[0076] Step 404: Determine a quantity of transmission layers and a precoding matrix according to the transmission parameter indication information.

10 [0077] In Embodiment 1 of the present invention, a state in a field obtained by jointly coding a TRI and a TPMI is used to indicate the TRI and the TPMI used for data transmission. Each TRI value is corresponding to one group of precoding matrices, and the correspondence is shown in Table 1 to Table 4. When a quantity of transmission layers is indicated, a TPMI is used to indicate one precoding matrix
15 selected from a group of precoding matrices corresponding to the quantity of transmission layers. Table 8 is an example of jointly coding a TRI and a TPMI. The indicated quantity of transmission layers, namely, the TRI, is indicated by using a layer x in the table, where a value range of x is {1, 2, 3, 4}. The indicated precoding matrix is indicated by using TPMI=y in the table, where y is a positive integer greater
20 than or equal to 1, and a value range of y is determined based on a quantity of precoding matrices corresponding to three UE capabilities corresponding to each quantity of transmission layers in Table 1 to Table 4. In this embodiment, for each UE capability, indexes of the field obtained by jointly coding the TRI and the TPMI are sorted in an ascending order of ranks. As shown in Table 8, in case of a "fully
25 coherent" transmission capacity, indexes 0 to 27 of the field indicate layer 1 transmission, and each index is corresponding to one precoding matrix index that is corresponding to the layer 1 transmission and that includes a codeword corresponding to "fully coherent", a codeword corresponding to "partially coherent", and a codeword corresponding to "incoherent". Indexes 28 to 49 of the field indicate layer 2
30 transmission, and each index is corresponding to one precoding matrix index that is corresponding to the layer 2 transmission and that includes a codeword corresponding to "fully coherent", a codeword corresponding to "partially coherent", and a codeword

corresponding to "incoherent". Indexes 50 to 56 of the field indicate layer 3 transmission, and each index is corresponding to one precoding matrix index that is corresponding to the layer 3 transmission and that includes a codeword corresponding to "fully coherent", a codeword corresponding to "partially coherent", and a codeword corresponding to "incoherent". Indexes 57 to 61 of the field indicate layer 4 transmission, and each index is corresponding to one precoding matrix index that is corresponding to the layer 4 transmission and that includes a codeword corresponding to "fully coherent", a codeword corresponding to "partially coherent", and a codeword corresponding to "incoherent".

10

Table 8. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
...	...	...	...	4	Two layers: TPMI=0
11	One layer: TPMI=11	11	One layer: TPMI=11	...	...
...	...	12	Two layers: TPMI=0	9	Two layers: TPMI=5
27	One layer: TPMI=27	...	...	10	Three layers: TPMI=0
28	Two layers: TPMI=0	17	Two layers: TPMI=5	11	Four layers: TPMI=0
...	...	...	...	12–15	Reserved
33	Two layers: TPMI=5	25	Two layers: TPMI=13		

...	...	26	Three layers: TPMI=0		
41	Two layers: TPMI=13	27	Three layers: TPMI=1		
...	...	...	...		
49	Two layers: TPMI=21	29	Four layers: TPMI=0		
50	Three layers: TPMI=0	30	Four layers: TPMI=1		
51	Three layers: TPMI=1	31	Four layers: TPMI=2		
...	...				
53	Three layers: TPMI=3				
...	...				
56	Three layers: TPMI=6				
57	Four layers: TPMI=0				
58	Four layers: TPMI=1				
...	...				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				
62–64	Reserved				

[0078] A signaling indication in Table 8 is corresponding to a case in which the user equipment has four-antenna transmission, a maximum quantity of transmission layers is 4, and a CP-OFDM waveform is used for sending data. When the user equipment has two-antenna transmission, a CP-OFDM waveform is used for sending data, and a maximum quantity of transmission layers is 2, a signaling indication is designed according to the same principle, as shown in Table 9.

Table 9. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1
2	One layer: TPMI=2	2	Two layers: TPMI=0
...	...	3	Reserved
5	One layer: TPMI=5		
6	Two layers: TPMI=0		
...	...		
8	Two layers: TPMI=2		
9–15	Reserved		

[0079] When the user equipment has two-antenna transmission, a CP-OFDM waveform is used for sending data, and a maximum quantity of transmission layers is 1, a signaling indication is designed according to the same principle, as shown in Table 10.

Table 10. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1
2	One layer: TPMI=2	2–3	Reserved
...	...		
5	One layer: TPMI=5		
6–7	Reserved		

[0080] When DFT-S-OFDM is used and the user equipment has two-antenna transmission, a TPMI is indicated based on Table 10.

[0081] The signaling indication in Table 8 may further be corresponding to a case

in which the user equipment has four-antenna transmission, a maximum quantity of transmission layers is 3 or 2, and a CP-OFDM waveform is used for sending data. When the user equipment has four-antenna transmission, a CP-OFDM waveform is used for sending data, and a maximum quantity of transmission layers is 1, a signaling indication is designed according to the same principle, as shown in Table 11.

Table 11. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
...	...	...	...		
11	One layer: TPMI=11	11	One layer: TPMI=11		
...	...	12–15	Reserved		
27	One layer: TPMI=27				
28–31	Reserved				

[0082] In Embodiment 2 of the present invention, a state in a field obtained by jointly coding a TRI and a TPMI is used to indicate the TRI and the TPMI used for data transmission. Each TRI value is corresponding to one group of precoding matrices, and the correspondence is shown in Table 1 to Table 4. When a quantity of transmission layers is indicated, a TPMI is used to indicate one precoding matrix selected from a group of precoding matrices corresponding to the quantity of transmission layers. Table 12 is an example of jointly coding a TRI and a TPMI. The indicated quantity of transmission layers, namely, the TRI, is indicated by using a layer x in the table, where a value range of x is {1, 2, 3, 4}. The indicated precoding

matrix is indicated by using $\text{TPMI}=y$ in the table, where y is a positive integer greater than or equal to 1, and a value range of y is determined based on a quantity of precoding matrices corresponding to three UE capabilities corresponding to each quantity of transmission layers in Table 1 to Table 4. In this embodiment, for partially

5 coherent transmission, indexes of the field start from 0, precoding matrices corresponding to incoherent transmission are preferably sorted, and a sorting order is the same as that of precoding matrix indexes corresponding to the incoherent transmission. Precoding matrix indexes corresponding to the partially coherent

10 incoherent transmission are sorted. For fully coherent transmission, indexes of the field start from 0, precoding matrices corresponding to incoherent transmission are preferably sorted, and a sorting order is the same as that of precoding matrix indexes corresponding to the incoherent transmission. Precoding matrix indexes corresponding to partially coherent transmission are sorted after all the precoding

15 matrix indexes corresponding to the incoherent transmission are sorted. Precoding matrix indexes corresponding to the fully coherent transmission are sorted after all the precoding matrix indexes corresponding to the incoherent transmission are sorted.

Table 12. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
4	Two layers: TPMI=0	4	Two layers: TPMI=0	4	Two layers: TPMI=0
...	...	...	...	...	...
9	Two layers: TPMI=5	9	Two layers: TPMI=5	9	Two layers: TPMI=5

10	Three layers: TPMI=0	10	Three layers: TPMI=0	10	Three layers: TPMI=0
11	Four layers: TPMI=0	11	Four layers: TPMI=0	11	Four layers: TPMI=0
12	One layer: TPMI=4	12	One layer: TPMI=4	12–15	Reserved
...	...	...	...		
19	One layer: TPMI=11	19	One layer: TPMI=11		
20	Two layers: TPMI=6	20	Two layers: TPMI=6		
...	...	...	...		
27	Two layers: TPMI=13	27	Two layers: TPMI=13		
28	Three layers: TPMI=1	28	Three layers: TPMI=1		
29	Three layers: TPMI=2	29	Three layers: TPMI=2		
30	Four layers: TPMI=1	30	Four layers: TPMI=1		
31	Four layers: TPMI=2	31	Four layers: TPMI=2		
32	One layer: TPMI=12				
...	...				
47	One layer: TPMI=27				
48	Two layers: TPMI=14				
...	...				
55	Two layers: TPMI=21				
56	Three layers: TPMI=3				

...	...				
59	Three layers: TPMI=6				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				
62–64	Reserved				

- [0083] A signaling indication in Table 12 is corresponding to a case in which the user equipment has four-antenna transmission, a maximum quantity of transmission layers is 4, and a CP-OFDM waveform is used for sending data. When the user equipment has two-antenna transmission, a CP-OFDM waveform is used for sending data, and a maximum quantity of transmission layers is 2, a signaling indication is designed according to the same principle, as shown in Table 13.

Table 13. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1
2	Two layers: TPMI=0	2	Two layers: TPMI=0
3	One layer: TPMI=2	3	Reserved
...	...		
6	One layer: TPMI=5		
7	Two layers: TPMI=1		
8	Two layers: TPMI=2		
9–15	Reserved		

- [0084] When the user equipment has two-antenna transmission, a CP-OFDM waveform is used for sending data, and a maximum quantity of transmission layers is 1, a signaling indication is designed according to the same principle, as shown in

Table 14.

Table 14. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1
2	One layer: TPMI=2	2–3	Reserved
...	...		
5	One layer: TPMI=5		
6–7	Reserved		

[0085] When DFT-S-OFDM is used and the user equipment has two-antenna transmission, a TPMI is indicated based on Table 14.

[0086] The signaling indication in Table 12 may further be corresponding to a case in which the user equipment has four-antenna transmission, a maximum quantity of transmission layers is 3 or 2, and a CP-OFDM waveform is used for sending data. When the user equipment has four-antenna transmission, a CP-OFDM waveform is used for sending data, and a maximum quantity of transmission layers is 1, a signaling indication is designed according to the same principle, as shown in Table 15.

Table 15. Example of jointly coding a TRI and a TPMI

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
...	...	...	...		

11	One layer: TPMI=11	11	One layer: TPMI=11		
...	...	12-15	Reserved		
27	One layer: TPMI=27				
28-31	Reserved				

[0087] The technical details in the method 400 are described in detail above with reference to the method 200. Therefore, details are not described herein again.

[0088] FIG. 4 is an example schematic diagram of a logical structure of a communications device 900 according to an embodiment of the present invention. In a specific implementation process, the communications device 900 may be the access device or the user equipment described above. As shown in FIG. 9, the communications device 900 includes a transceiver module 902 and a processing module 904.

[0089] When the communications device 900 is the user equipment, the transceiver module 902 may be configured to execute steps 302, 402, and 702, and the processing module 904 is configured to execute steps 304, 404, and 704.

[0090] When the communications device 900 is the access device, the transceiver module 902 may be configured to execute steps 504, 604, and 804, and the processing module 904 is configured to execute steps 502, 602, and 802.

[0091] FIG. 5 is an example schematic diagram of a hardware structure of a communications device 1000 according to an embodiment of the present invention. In a specific implementation process, the communications device 1000 may be the access device or the user equipment described above. As shown in FIG. 10, the communications device 1000 includes a processor 1002, a transceiver 1004, a plurality of antennas 1006, a memory 1008, an I/O (input/output, Input/Output) interface 1010, and a bus 1012. The memory 1008 is further configured to store an instruction 10082 and data 10084. In addition, the processor 1002, the transceiver 1004, the memory 1008, and the I/O interface 1010 are communicatively connected to each other by using the bus 1012, and the plurality of antennas 1006 are connected to the transceiver 1004. In a specific implementation process, the processor 1002, the transceiver 1004, the memory 1008, and the I/O interface 1010 may also be

communicatively connected to each other in a connection manner other than the bus 1012.

[0092] The processor 1002 may be a general processor, by way of example but not limitation, a central processing unit (Central Processing Unit, CPU), or may be a dedicated processor, by way of example but not limitation, a digital signal processor (Digital Signal Processor, DSP), an application-specific integrated circuit (Application Specific Integrated Circuit, ASIC), or a field programmable gate array (Field Programmable Gate Array, FPGA). In addition, the processor 1002 may be a combination of a plurality of processors. The processor 1002 may be a processor particularly designed to perform specific steps and/or operations, or may perform the specific steps and/or operations by reading and executing the instruction 10082 stored in the memory 1008. The processor 1002 may need to use the data 10084 when performing the specific steps and/or operations. Particularly, the processor 1002 is configured to perform an operation performed by the processing module 904.

[0093] The transceiver 1004 sends a signal by using at least one antenna in the plurality of antennas 1006, and receives a signal by using at least one antenna in the plurality of antennas 1006. Particularly, the transceiver 1004 is configured to perform an operation performed by the transceiver module 902.

[0094] The memory 1008 may include various types of storage media such as a random access memory (Random Access Memory, RAM), a read-only memory (Read Only Memory, ROM), a nonvolatile RAM (Non-Volatile RAM, NVRAM), a programmable ROM (Programmable ROM, PROM), an erasable PROM (Erasable PROM, EPROM), an electrically erasable PROM (Electrically Erasable PROM, EEPROM), a flash memory, an optical memory, and a register. The memory 1008 is specifically configured to store the instruction 10082 and the data 10084. The processor 1002 may perform specific steps and/or operations by reading and executing the instruction 10082 stored in the memory 1008, and may need to use the data 10084 when performing the specific operations and/or steps.

[0095] The I/O interface 1010 is configured to receive an instruction and/or data from a peripheral device, and output an instruction and/or data to the peripheral device.

[0096] It should be noted that in a specific implementation process, the communications device 1000 may further include another hardware component. No further examples are listed one by one in this application.

[0097] All or some of the foregoing embodiments may be implemented through software, hardware, firmware, or any combination thereof. When software is used to implement the embodiments, the embodiments may be implemented fully or partially in a form of a computer program product. The computer program product includes one or more computer instructions. When the computer program instructions are loaded and executed on the computer, the procedure or functions according to the embodiments of the present invention are all or partially generated. The computer may be a general-purpose computer, a dedicated computer, a computer network, or other programmable apparatuses. The computer instructions may be stored in a computer-readable storage medium or may be transmitted from a computer-readable storage medium to another computer-readable storage medium. For example, the computer instructions may be transmitted from a website, computer, server, or data center to another website, computer, server, or data center in a wired (for example, a coaxial cable, an optical fiber, or a digital subscriber line (DSL)) or wireless (for example, infrared, radio, and microwave, or the like) manner. The computer-readable storage medium may be any usable medium accessible by a computer, or a data storage device, such as a server or a data center, integrating one or more usable media. The usable medium may be a magnetic medium (for example, a floppy disk, a hard disk, or a magnetic tape), an optical medium (for example, a DVD), a semiconductor medium (for example, a Solid State Disk (SSD)), or the like.

[0098] To sum up, the foregoing descriptions are merely embodiments of the present invention, but are not intended to limit the protection scope of the present invention. Any modification, equivalent replacement, or improvement made without departing from the spirit and principle of the present invention shall fall within the protection scope of the present invention.

CLAIMS

What is claimed is:

1. A transmission parameter indication method, comprising:
generating transmission parameter indication information, wherein the
5 transmission parameter indication information is used to indicate a transmission
parameter entry selected from a transmission parameter entry set corresponding to a
current coherence capability, and the transmission parameter entry is used to indicate
a quantity of transmission layers and a precoding matrix; and
sending the transmission parameter indication information.
- 10 2. The method according to claim 1, wherein the transmission parameter entry
comprises an index of the transmission parameter entry, a value of the quantity of
transmission layers, and an index of the precoding matrix, and the precoding matrix is
uniquely determined by using both the value of the quantity of transmission layers
and the index of the precoding matrix.
- 15 3. The method according to claim 1, wherein the current coherence capability is
one of the following capabilities:
"fully coherent";
"partial-coherent"; and
"incoherent".
- 20 4. The method according to claim 3, wherein a transmission parameter entry set
corresponding to each coherence capability comprises at least one transmission
parameter entry, a transmission parameter entry set corresponding to "incoherent" is a
subset of a transmission parameter entry set corresponding to "partial-coherent", and
the transmission parameter entry set corresponding to "partial-coherent" is a subset of
25 a transmission parameter entry set corresponding to "fully coherent".
5. The method according to claim 1, further comprising:
generating coherence capability indication information, wherein the coherence
capability indication information is used to indicate the current coherence capability.
6. The method according to any one of claims 1 to 5, wherein the transmission
30 parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
----------------	--------------------------------	----------------	------------------------------------	----------------	----------------------------

0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
4	Two layers: TPMI=0	4	Two layers: TPMI=0	4	Two layers: TPMI=0
...	...	...	...	...	...
9	Two layers: TPMI=5	9	Two layers: TPMI=5	9	Two layers: TPMI=5
10	Three layers: TPMI=0	10	Three layers: TPMI=0	10	Three layers: TPMI=0
11	Four layers: TPMI=0	11	Four layers: TPMI=0	11	Four layers: TPMI=0
12	One layer: TPMI=4	12	One layer: TPMI=4		
...	...	...	...		
19	One layer: TPMI=11	19	One layer: TPMI=11		
20	Two layers: TPMI=6	20	Two layers: TPMI=6		
...	...	...	...		
27	Two layers: TPMI=13	27	Two layers: TPMI=13		
28	Three layers: TPMI=1	28	Three layers: TPMI=1		
29	Three layers: TPMI=2	29	Three layers: TPMI=2		
30	Four layers: TPMI=1	30	Four layers: TPMI=1		
31	Four layers: TPMI=2	31	Four layers: TPMI=2		

32	One layer: TPMI=12				
...	...				
47	One layer: TPMI=27				
48	Two layers: TPMI=14				
...	...				
55	Two layers: TPMI=21				
56	Three layers: TPMI=3				
...	...				
59	Three layers: TPMI=6				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

7. The method according to any one of claims 1 to 5, wherein the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
...	...	...	...	4	Two layers: TPMI=0

11	One layer: TPMI=11	11	One layer: TPMI=11	...	...
...	...	12	Two layers: TPMI=0	9	Two layers: TPMI=5
27	One layer: TPMI=27	...	...	10	Three layers: TPMI=0
28	Two layers: TPMI=0	17	Two layers: TPMI=5	11	Four layers: TPMI=0
...	...	...	...		
33	Two layers: TPMI=5	25	Two layers: TPMI=13		
...	...	26	Three layers: TPMI=0		
41	Two layers: TPMI=13	27	Three layers: TPMI=1		
...	...	...	...		
49	Two layers: TPMI=21	29	Four layers: TPMI=0		
50	Three layers: TPMI=0	30	Four layers: TPMI=1		
51	Three layers: TPMI=1	31	Four layers: TPMI=2		
...	...				
53	Three layers: TPMI=3				
...	...				
56	Three layers: TPMI=6				
57	Four layers: TPMI=0				
58	Four layers: TPMI=1				
...	...				

60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

8. A transmission parameter indication method, comprising:

receiving transmission parameter indication information, wherein the transmission parameter indication information is used to indicate a transmission parameter entry selected from a transmission parameter entry set corresponding to a current coherence capability, and the transmission parameter entry is used to indicate a quantity of transmission layers and a precoding matrix; and

determining the quantity of transmission layers and the precoding matrix according to the transmission parameter indication information.

9. The method according to claim 8, wherein the transmission parameter entry comprises an index of the transmission parameter entry, a value of the quantity of transmission layers, and an index of the precoding matrix, and the precoding matrix is uniquely determined by using both the value of the quantity of transmission layers and the index of the precoding matrix.

10. The method according to claim 8, wherein the current coherence capability is one of the following capabilities:

"fully coherent";

"partial-coherent"; and

"incoherent".

11. The method according to claim 10, wherein a transmission parameter entry set corresponding to each coherence capability comprises at least one transmission parameter entry, a transmission parameter entry set corresponding to "incoherent" is a subset of a transmission parameter entry set corresponding to "partial-coherent", and the transmission parameter entry set corresponding to "partial-coherent" is a subset of a transmission parameter entry set corresponding to "fully coherent".

12. The method according to claim 8, further comprising:

generating coherence capability indication information, wherein the coherence capability indication information is used to indicate the current coherence capability.

13. The method according to any one of claims 8 to 12, wherein the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
4	Two layers: TPMI=0	4	Two layers: TPMI=0	4	Two layers: TPMI=0
...	...	...	...	...	...
9	Two layers: TPMI=5	9	Two layers: TPMI=5	9	Two layers: TPMI=5
10	Three layers: TPMI=0	10	Three layers: TPMI=0	10	Three layers: TPMI=0
11	Four layers: TPMI=0	11	Four layers: TPMI=0	11	Four layers: TPMI=0
12	One layer: TPMI=4	12	One layer: TPMI=4		
...	...	...	...		
19	One layer: TPMI=11	19	One layer: TPMI=11		
20	Two layers: TPMI=6	20	Two layers: TPMI=6		
...	...	...	...		
27	Two layers: TPMI=13	27	Two layers: TPMI=13		
28	Three layers: TPMI=1	28	Three layers: TPMI=1		
29	Three layers: TPMI=2	29	Three layers: TPMI=2		
30	Four layers: TPMI=1	30	Four layers: TPMI=1		

31	Four layers: TPMI=2	31	Four layers: TPMI=2		
32	One layer: TPMI=12				
...	...				
47	One layer: TPMI=27				
48	Two layers: TPMI=14				
...	...				
55	Two layers: TPMI=21				
56	Three layers: TPMI=3				
...	...				
59	Three layers: TPMI=6				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

14. The method according to any one of claims 8 to 12, wherein the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3

...	...	...	...	4	Two layers: TPMI=0
11	One layer: TPMI=11	11	One layer: TPMI=11	...	...
...	...	12	Two layers: TPMI=0	9	Two layers: TPMI=5
27	One layer: TPMI=27	...	...	10	Three layers: TPMI=0
28	Two layers: TPMI=0	17	Two layers: TPMI=5	11	Four layers: TPMI=0
...	...	...	...		
33	Two layers: TPMI=5	25	Two layers: TPMI=13		
...	...	26	Three layers: TPMI=0		
41	Two layers: TPMI=13	27	Three layers: TPMI=1		
...	...	...	...		
49	Two layers: TPMI=21	29	Four layers: TPMI=0		
50	Three layers: TPMI=0	30	Four layers: TPMI=1		
51	Three layers: TPMI=1	31	Four layers: TPMI=2		
...	...				
53	Three layers: TPMI=3				
...	...				
56	Three layers: TPMI=6				
57	Four layers: TPMI=0				
58	Four layers: TPMI=1				

...	...				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

15. An access device, comprising:

a processing module, configured to generate transmission parameter indication information, wherein the transmission parameter indication information is used to indicate a transmission parameter entry selected from a transmission parameter entry set corresponding to a current coherence capability, and the transmission parameter entry is used to indicate a quantity of transmission layers and a precoding matrix; and

a transceiver module, configured to send the transmission parameter indication information.

16. The method according to claim 15, wherein the transmission parameter entry comprises an index of the transmission parameter entry, a value of the quantity of transmission layers, and an index of the precoding matrix, and the precoding matrix is uniquely determined by using both the value of the quantity of transmission layers and the index of the precoding matrix.

17. The method according to claim 15, wherein the current coherence capability is one of the following capabilities:

"fully coherent";

"partial-coherent"; and

"incoherent".

18. The method according to claim 17, wherein a transmission parameter entry set corresponding to each coherence capability comprises at least one transmission parameter entry, a transmission parameter entry set corresponding to "incoherent" is a subset of a transmission parameter entry set corresponding to "partial-coherent", and the transmission parameter entry set corresponding to "partial-coherent" is a subset of a transmission parameter entry set corresponding to "fully coherent".

19. The method according to claim 15, further comprising:

generating coherence capability indication information, wherein the coherence capability indication information is used to indicate the current coherence capability.

20. The method according to any one of claims 15 to 19, wherein the

transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
4	Two layers: TPMI=0	4	Two layers: TPMI=0	4	Two layers: TPMI=0
...	...	...	...	...	...
9	Two layers: TPMI=5	9	Two layers: TPMI=5	9	Two layers: TPMI=5
10	Three layers: TPMI=0	10	Three layers: TPMI=0	10	Three layers: TPMI=0
11	Four layers: TPMI=0	11	Four layers: TPMI=0	11	Four layers: TPMI=0
12	One layer: TPMI=4	12	One layer: TPMI=4		
...	...	...	...		
19	One layer: TPMI=11	19	One layer: TPMI=11		
20	Two layers: TPMI=6	20	Two layers: TPMI=6		
...	...	...	...		
27	Two layers: TPMI=13	27	Two layers: TPMI=13		
28	Three layers: TPMI=1	28	Three layers: TPMI=1		
29	Three layers: TPMI=2	29	Three layers: TPMI=2		
30	Four layers:	30	Four layers:		

	TPMI=1		TPMI=1		
31	Four layers: TPMI=2	31	Four layers: TPMI=2		
32	One layer: TPMI=12				
...	...				
47	One layer: TPMI=27				
48	Two layers: TPMI=14				
...	...				
55	Two layers: TPMI=21				
56	Three layers: TPMI=3				
...	...				
59	Three layers: TPMI=6				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

21. The method according to any one of claims 15 to 19, wherein the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer:	3	One layer: TPMI=3	3	One layer:

	TPMI=3				TPMI=3
...	...	...	...	4	Two layers: TPMI=0
11	One layer: TPMI=11	11	One layer: TPMI=11	...	...
...	...	12	Two layers: TPMI=0	9	Two layers: TPMI=5
27	One layer: TPMI=27	...	...	10	Three layers: TPMI=0
28	Two layers: TPMI=0	17	Two layers: TPMI=5	11	Four layers: TPMI=0
...	...	...	...		
33	Two layers: TPMI=5	25	Two layers: TPMI=13		
...	...	26	Three layers: TPMI=0		
41	Two layers: TPMI=13	27	Three layers: TPMI=1		
...	...	...	...		
49	Two layers: TPMI=21	29	Four layers: TPMI=0		
50	Three layers: TPMI=0	30	Four layers: TPMI=1		
51	Three layers: TPMI=1	31	Four layers: TPMI=2		
...	...				
53	Three layers: TPMI=3				
...	...				
56	Three layers: TPMI=6				
57	Four layers: TPMI=0				

58	Four layers: TPMI=1				
...	...				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

22. User equipment, comprising:

a transceiver module, configured to receive transmission parameter indication information, wherein the transmission parameter indication information is used to
5 indicate a transmission parameter entry selected from a transmission parameter entry set corresponding to a current coherence capability, and the transmission parameter entry is used to indicate a quantity of transmission layers and a precoding matrix; and
a processing module, configured to determine the quantity of transmission layers and the precoding matrix according to the transmission parameter indication
10 information.

23. The method according to claim 22, wherein the transmission parameter entry comprises an index of the transmission parameter entry, a value of the quantity of transmission layers, and an index of the precoding matrix, and the precoding matrix is uniquely determined by using both the value of the quantity of transmission layers
15 and the index of the precoding matrix.

24. The method according to claim 23, wherein the current coherence capability is one of the following capabilities:

"fully coherent";
"partial-coherent"; and
20 "incoherent".

25. The method according to claim 24, wherein a transmission parameter entry set corresponding to each coherence capability comprises at least one transmission parameter entry, a transmission parameter entry set corresponding to "incoherent" is a subset of a transmission parameter entry set corresponding to "partial-coherent", and
the transmission parameter entry set corresponding to "partial-coherent" is a subset of a transmission parameter entry set corresponding to "fully coherent".

26. The method according to claim 22, further comprising:

generating coherence capability indication information, wherein the coherence capability indication information is used to indicate the current coherence capability.

27. The method according to any one of claims 22 to 26, wherein the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1
...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
4	Two layers: TPMI=0	4	Two layers: TPMI=0	4	Two layers: TPMI=0
...	...	...	...	...	...
9	Two layers: TPMI=5	9	Two layers: TPMI=5	9	Two layers: TPMI=5
10	Three layers: TPMI=0	10	Three layers: TPMI=0	10	Three layers: TPMI=0
11	Four layers: TPMI=0	11	Four layers: TPMI=0	11	Four layers: TPMI=0
12	One layer: TPMI=4	12	One layer: TPMI=4		
...	...	...	...		
19	One layer: TPMI=11	19	One layer: TPMI=11		
20	Two layers: TPMI=6	20	Two layers: TPMI=6		
...	...	...	...		
27	Two layers: TPMI=13	27	Two layers: TPMI=13		
28	Three layers: TPMI=1	28	Three layers: TPMI=1		

29	Three layers: TPMI=2	29	Three layers: TPMI=2		
30	Four layers: TPMI=1	30	Four layers: TPMI=1		
31	Four layers: TPMI=2	31	Four layers: TPMI=2		
32	One layer: TPMI=12				
...	...				
47	One layer: TPMI=27				
48	Two layers: TPMI=14				
...	...				
55	Two layers: TPMI=21				
56	Three layers: TPMI=3				
...	...				
59	Three layers: TPMI=6				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

28. The method according to any one of claims 22 to 26, wherein the transmission parameter indication information is as follows:

Field index	Fully coherent transmission	Field index	Partially coherent transmission	Field index	Incoherent transmission
0	One layer: TPMI=0	0	One layer: TPMI=0	0	One layer: TPMI=0
1	One layer: TPMI=1	1	One layer: TPMI=1	1	One layer: TPMI=1

...	...	...	...	...	...
3	One layer: TPMI=3	3	One layer: TPMI=3	3	One layer: TPMI=3
...	...	...	...	4	Two layers: TPMI=0
11	One layer: TPMI=11	11	One layer: TPMI=11	...	...
...	...	12	Two layers: TPMI=0	9	Two layers: TPMI=5
27	One layer: TPMI=27	...	...	10	Three layers: TPMI=0
28	Two layers: TPMI=0	17	Two layers: TPMI=5	11	Four layers: TPMI=0
...	...	...	...		
33	Two layers: TPMI=5	25	Two layers: TPMI=13		
...	...	26	Three layers: TPMI=0		
41	Two layers: TPMI=13	27	Three layers: TPMI=1		
...	...	...	...		
49	Two layers: TPMI=21	29	Four layers: TPMI=0		
50	Three layers: TPMI=0	30	Four layers: TPMI=1		
51	Three layers: TPMI=1	31	Four layers: TPMI=2		
...	...				
53	Three layers: TPMI=3				
...	...				
56	Three layers: TPMI=6				

57	Four layers: TPMI=0				
58	Four layers: TPMI=1				
...	...				
60	Four layers: TPMI=3				
61	Four layers: TPMI=4				

1/3




FIG. 1

2/3

300




FIG. 2

400




FIG. 3

3/3

900




FIG. 4

1000




FIG. 5

400

402

接收第二传输控制信息

404

在第二传输控制信息满足第二预设条件时，
停止半静态信道测量，其中所述第二预设条
件包含下列条件之中的至少一种：所述第二
传输控制信息关联第二预设类型的无线网络
临时标识RNTI；所述第二传输控制信息中
的第二组信息的值符合第二预设规则

- 402 Receive second transmission control information
- 404 When the second transmission control information meets a second preset condition, stop semi-static channel sounding, wherein the second preset condition comprises at least one of the following conditions: the second transmission control information is associated with a radio network temporary identifier (RNTI) of a second preset type, or a value for a second set of information in the second transmission control information meets a second preset rule

图 3