



AU9344659

(12) PATENT ABRIDGMENT (11) Document No. AU-B-44659/93
(19) AUSTRALIAN PATENT OFFICE (10) Acceptance No. 659025

- (54) Title
PULSED PRESSURE SENSOR CIRCUIT AND METHOD THEREFOR
- International Patent Classification(s)
(51)^s **G01L 009/04 G01L 009/02**
- (21) Application No. : **44659/93** (22) Application Date : **13.08.93**
- (30) Priority Data
- (31) Number (32) Date (33) Country
954996 01.10.92 US UNITED STATES OF AMERICA
- (43) Publication Date : **14.04.94**
- (44) Publication Date of Accepted Application : **04.05.95**
- (71) Applicant(s)
MOTOROLA, INC.
- (72) Inventor(s)
JEFFREY BAUM; WARREN J. SCHULTZ
- (74) Attorney or Agent
PHILLIPS ORMONDE & FITZPATRICK , 367 Collins Street, MELBOURNE VIC 3000
- (56) Prior Art Documents
US 4798093
US 4736155
US 4362060
- (57) Claim

1. A pulsed pressure sensor circuit having increased sensitivity including:

a pulse generation circuit for providing a voltage pulse at an output; and

a pressure sensor having a bias input coupled to said output of said pulse generation circuit, a port exposed to ambient pressure, and an output for providing an output signal corresponding to said ambient pressure.

659025
AUSTRALIA

Patents Act

**COMPLETE SPECIFICATION
(ORIGINAL)**

Application Number:
Lodged:

Class

Int. Class

Complete Specification Lodged:
Accepted:
Published:

Priority

Related Art:

Name of Applicant:

Motorola, Inc.

Actual Inventor(s):

Jeffrey Baum
Warren J. Schultz

Address for Service:

PHILLIPS ORMONDE & FITZPATRICK
Patent and Trade Mark Attorneys
367 Collins Street
Melbourne 3000 AUSTRALIA

Invention Title:

PULSED PRESSURE SENSOR CIRCUIT AND METHOD THEREFOR

Our Ref : 337168
POF Code: 183224/1437

The following statement is a full description of this invention, including the best method of performing it known to applicant(s):

~~PULSED PRESSURE SENSOR CIRCUIT AND METHOD THEREFOR~~

Background of the Invention

5 This invention relates, in general, to pressure sensing circuits, and more particularly to pressure sensing circuits for measuring low pressures.

A common semiconductor pressure sensor, such as the MPX2010 sensor manufactured by Motorola Inc., uses a resistor bridge to generate
10 a differential voltage. The pressure sensor is biased with a D.C. voltage. The magnitude of the voltage determines the sensitivity and range of the pressure sensor. A port on the pressure sensor exposes a diaphragm which modifies resistance values in the resistor bridge when a pressure is applied. The pressure sensor outputs a differential voltage which is
15 proportional to the pressure at the port.

Measuring low pressures accurately can be a problem since the magnitude of the pressure sensor differential voltage output is reduced at the lower pressures. This is compounded by the fact that small pressure differences will produce minute incremental voltage changes
20 at the pressure sensor outputs which may be extremely difficult or impossible to resolve. There are pressure sensing circuits which attempt to overcome these problems but yield mixed results.

One technique commonly used is to amplify the differential output to a level where it can be easily measured or manipulated. A
25 high gain amplification stage (gain greater than 500) must be used for low pressure applications. An amplifier used in a high gain configuration may have stability problems or nonlinearities which affect accuracy. Poor signal to noise ratios may result due to the small signal levels.

30 A second technique which produces better results is to bias the pressure sensor at a higher D.C. voltage. The higher bias voltage will increase the differential output voltage at a given pressure, thus incremental pressure changes will also result in larger voltage changes from the pressure sensor. A lower gain amplification stage can be used



resulting in a higher signal to noise ratio and a more stable system. The drawback to this approach is that the bias voltage on the pressure sensor can only be increased so much. Power dissipation and other reliability/accuracy factors must be taken into account at the higher bias voltages.

It would be of great benefit if a pressure sensing circuit or method therefor could be developed which further increases sensitivity to allow accurate measurement of even lower pressures.

According to one aspect of the present invention there is provided a pulsed pressure sensor circuit having increased sensitivity including:

a pulse generation circuit for providing a voltage pulse at an output; and

a pressure sensor having a bias input coupled to said output of said pulse generation circuit, a port exposed to ambient pressure, and an output for providing an output signal corresponding to said ambient pressure.

According to a further aspect of the present invention there is provided a method for sensing pressure including:

exposing a port of a pressure sensor to ambient pressure;

providing a voltage pulse;

biasing said pressure sensor with said voltage pulse; and

measuring an output voltage of said pressure sensor wherein said output voltage is proportional to said ambient pressure.

According to a still further aspect of the present invention there is provided a pulsed pressure sensing circuit including:

a pulse generation circuit having a control input and an output;

a pressure sensor having a bias input coupled to said output of said pulse generation circuit, a first output, a second output, and a port exposing a diaphragm to a pressure to be measured;



an amplifier having a first input coupled to said first output of said pressure sensor, a second input coupled to said second output of said pressure sensor, and an output;

5 a voltage divider circuit having an input coupled to said output of said pulse generation circuit, and an output; and

means for calculating pressure having a first input coupled to said output of said amplifier, a second input coupled to said output of said voltage divider, a first output, and a second output coupled to said control input.


A preferred embodiment of the present invention will now be described with reference to the accompanying drawing wherein the single figure is a block diagram of a pulsed pressure sensor circuit in accordance with the present invention.

20

25

30

35



A pulsed pressure sensor circuit 11 is illustrated in the single figure which is simple, cost effective, and increases sensitivity for measuring low pressures. A large portion of the pressure sensing market place is for pressure sensor circuits which measure pressures below 10,000 pascals. An integral part of any pressure sensor circuit is a pressure sensor such as the aforementioned MPX2010. The pressure sensor receives a pressure to be sensed and outputs a voltage which is proportional to that pressure. A semiconductor pressure sensor is a very economical pressure sensor but is not typically used for measuring low pressures. Although cost effective, a silicon diaphragm is stiff and does not bend easily at low pressures (less than 10,000 pascals), thus its use has not been fully exploited in the low pressure sensor circuit market place. In the preferred embodiment, pulsed pressure sensor circuit 11 uses a semiconductor pressure sensor that produces a useable output voltage for pressures below 10,000 pascals. Pulse pressure sensor circuit 11 is not limited to low pressure measurements and can also be used for measuring pressures greater than 10,000 pascals.

A pulse generation circuit 12 has a control input 14 and an output 13. Pulse generation circuit 12 outputs a high voltage pulse of a predetermined magnitude and duration. Control input 14 is used to enable pulse generation circuit 12 to output a voltage pulse. Pulse generation circuit 12 could be designed with a programmable feature to vary the voltage pulse magnitude and duration for different applications but in this embodiment cost is a high priority, thus, pulse generation circuit 12 outputs a voltage pulse of fixed magnitude and duration responsive to an enabling signal supplied at input 14.

Pressure sensor 17 is indicated by a dashed line which surrounds sensor 17. Pressure sensor 17 has a first bias input 18, a second bias input 19, a first output 21, a second output 22, and a port exposed to a pressure to be measured as is generally well known. In the preferred embodiment, pressure sensor 17 is a semiconductor pressure sensor comprised of resistors R1-R6. Those skilled in the art will appreciate that resistors R1 and R2 are temperature compensation resistors and resistors R3,R4,R5, and R6 form a resistor bridge. The port (not

illustrated) is indicated by arrow 15 and exposes a diaphragm to a pressure. A pressure on the diaphragm modifies resistance values of the resistor bridge.

First input 18 is coupled to output 13 of pulse generation circuit 12. Second output 19 is typically coupled to ground. A voltage pulse from pulse generation circuit 12 biases pressure sensor 17. The voltage at outputs 21 and 22 will be equal when $R3=R4$ and $R5=R6$ in the resistor bridge. A pressure at the port changes the resistance values of the resistor bridge which creates a differential voltage across outputs 21 and 22 as is known. The amount of differential voltage change per unit pressure change is known as pressure sensor sensitivity. The sensitivity of pressure sensor 17 generally increases with increasing voltage across first and second bias inputs 18 and 19. For example, a ten volt bias voltage across pressure sensor 17 will yield a greater voltage change across outputs 21 and 22 than a five volt bias voltage for a similar pressure change. The advantage of a larger differential voltage change per unit pressure change is a reduced susceptibility to noise problems and an increased resolution in accurately measuring low pressures.

A differential to single-ended output amplifier 23 is used to amplify the differential voltage across outputs 21 and 22 of pressure sensor 17 to provide a single-ended output voltage. Amplifier 23 has a first input coupled to output 21 of pressure sensor 17, a second input coupled to output 22 of pressure 17, and an output 24. Amplifier 23 is set to a predetermined gain which is determined for a specific application. Factors which impact amplifier gain are the voltage pulse magnitude, signal level output from pressure sensor 17, and the type of circuitry receiving an output signal from amplifier 23. In the preferred embodiment, amplifier 23 is not set to an extremely large gain (typically less than 150), is low noise and has a fast settling time to minimize delay for output 24 to settle (or stabilize) in response to a pressure measurement.

A voltage divider 26 is used to produce a voltage proportional to the voltage pulse from pulse generation circuit 12. In the preferred

embodiment, voltage divider circuit 26 is a resistor divider comprising two series resistors. Voltage divider 26 has an input coupled to output 13 of pulse generation circuit 12 and an output 27 which is taken at the interconnection of the two series resistors, for example. The magnitude of the voltage pulse from pulse generation circuit 12 can be computed by measuring a voltage at output 27 and multiplying the measured voltage by a predetermined constant.

In the preferred embodiment, a microprocessor (MPU) 28, for instance a MC68HC05 microprocessor manufactured by Motorola Inc., serves as a means for calculating the relative pressure applied to sensor 17. Microprocessor 28 has an output coupled to control input 14 for enabling pulse generation circuit 12, an input coupled to output 24 of operational amplifier 23, an input coupled to output 27 of voltage divider circuit 26, and an output 29. Operational amplifier 24 and voltage divider circuit 26 each output an analog signal which is used to calculate pressure by microprocessor 28. The inputs of microprocessor 28 coupled to output 24 and output 27 each couple to an analog to digital converter input of MPU 28 which then converts each analog signal to a digital format. A channel or multiplexer is enabled within microprocessor 28 coupling the input to the analog to digital converter (within MPU 28). Microprocessor 28 calculates the pressure sensed by pressure sensor 19 from the inputs it receives and outputs a corresponding pressure indication (in digital format) at output 29.

The method of operation of pulsed pressure sensing circuit 11 is best illustrated by describing a sequence of events when measuring a pressure. It is important to note that using a voltage pulse to bias pressure sensor 17 allows a much greater voltage magnitude to be used (due to lower power dissipation) thus increasing pressure sensor sensitivity over the same pressure sensor biased at a lower D.C. bias potential. The voltage pulse can be characterized by its magnitude and duration. The magnitude of the voltage pulse is empirically determined for a pressure sensor and is based on long term reliability and pressure sensor accuracy. Preliminary data has shown that voltage magnitude can be increased approximately four times over the

recommended D.C. pressure sensor bias voltage. For example, a pressure sensor D.C. biased at 10 volts can now be pulsed at 40 volts for a fourfold increase in sensitivity.

5 A minimum duration for a voltage pulse can be determined by a minimum time needed to make an accurate/stable measurement. Two events must occur during this minimum time. First, pressure sensor 17 is biased and outputs a differential voltage at outputs 21 and 22 that is proportional to an ambient pressure at the port indicated by arrow 15. Second, amplifier 23 amplifies the differential voltage and output 24
10 must be at a stable voltage (amplifier settling time) for microprocessor 28 to sample. The maximum duration of the voltage pulse and its duty cycle in conjunction with the voltage magnitude must not sufficiently heat resistors R1-R6 to distort the measurement.

15 In a normal environment pressure changes occur at a relatively slow pace. Pressure measurements are generally taken at intervals of a millisecond or longer. A typical pulse duration for pulsed pressure sensing circuit 11 is 200 microseconds. This would indicate that most time between pressure measurements is dead time or time when pressure sensor 17 is idle. For this case, biasing pressure sensor 17 with a
20 voltage pulse not only increases sensitivity of the pressure sensor but also reduces power dissipation as no power is dissipated between voltage pulses.

25 A pressure sensing sequence begins with microprocessor 28 enabling pulse generation circuit 12. Output 13 of pulse generation circuit 12 outputs a voltage pulse which biases pressure sensor 17 and voltage divider 26. Pressure sensor 17 responds to a pressure at the port (indicated by arrow 15) generating a differential voltage across outputs 21 and 22. Amplifier 23 amplifies the differential voltage to provide a single-ended output voltage at output 24 which is received by
30 microprocessor 28. Output 24 of amplifier 23 must stabilize to a voltage before microprocessor 28 samples the voltage at output 24. A predetermined time after pulse generation circuit 12 is enabled, microprocessor 28 will sample the voltage at output 24 of amplifier 23 and output 27 of voltage divider circuit 26. The predetermined time is

chosen to insure that output 24 has stabilized to a voltage corresponding to the pressure at the port. Microprocessor 28 stores the voltage magnitude at output 24 and the voltage magnitude at output 27 in memory after converting to a digital format.

5 Voltage divider 26 is needed in this embodiment because the voltage magnitude of the voltage pulse is too large for the internal analog to digital converter in microprocessor 28. Voltage divider 26 outputs a reduced voltage which is proportional to the magnitude of the voltage pulse and can be converted to digital format by the analog to
10 digital converter (in microprocessor 28). The voltage magnitude of the voltage pulse can be obtained by simply multiplying the reduced voltage by a constant. Microprocessor 28, by sampling output 27 simultaneously with output 24, allows a lower tolerance on voltage magnitude generated by pulse generation circuit 12 since the exact
15 voltage is known (when sampled). The lower tolerance translates to reduced costs in building pulse generation circuit 12. An extremely accurate and stable voltage magnitude from pulse generation circuit 12 would render voltage divider circuit 26 unnecessary since the magnitude of a voltage pulse is known and could be stored in memory
20 of microprocessor 28.

An alternative to pulsing pressure sensor circuit 11 with a fixed magnitude voltage pulse is a dynamic pressure sensor circuit in which the voltage pulse magnitude is variable. Changing the voltage pulse magnitude changes the pressure range which can be sensed by the
25 dynamic pressure sensor circuit. As mentioned previously, using a high magnitude voltage pulse increases pressure sensor 17 sensitivity but reduces the range of pressure which can be measured. Likewise, reducing the magnitude of a voltage pulse decreases pressure sensor 17 sensitivity while increasing the range of pressure which can be
30 measured. Pulse generation circuit 12 and microprocessor 28 would be used in combination to control and output a voltage pulse of appropriate magnitude for a pressure sensing application. An example which illustrates the benefits of a dynamic pressure sensor circuit is an aircraft which needs precise pressure measurements at all altitudes. As

the aircraft travels from sea level to tens of thousands of feet it will experience significant changes in atmospheric pressure which cannot be measured accurately at all altitudes with a fixed sensor sensitivity. A dynamic pulsed pressure sensor would allow the pressure range to be
5 adjusted to optimize sensitivity of pressure sensor 17 for a specific pressure measurement.

In the preferred embodiment, pulsed pressure sensor circuit 11 is calibrated at the factory. For example, at zero pressure (or minimum pressure (P_{min})) pulsed pressure sensor circuit 11 is adjusted to output
10 a voltage of 0.5 volts at output 24 of amplifier 23. The zero pressure calibration voltage at output 24 is known as V_{off} (offset). Similarly, at maximum pressure (P_{max}) the pulsed pressure sensor circuit 11 is adjusted to output 4.5 volts. The maximum pressure calibration voltage at output 24 is known as V_{fs} (full-scale). A voltage magnitude
15 is measured at output 27 of voltage divider circuit 26 when V_{off} and V_{fs} is calibrated which is known as B_{cal} . A few constants are generated from these calibration values. The constants are stored in microprocessor 28 and used to calculate pressure. Listed below are the constants used to calculate pressure.

20 1) $V_{fs} - V_{off}$ is defined as a "voltage span" for a pressure measurement.

2) $(V_{fs} - V_{off})/B_{cal}$ is defined as a "normalized voltage span".

3) $(P_{max} * B_{cal}) / (V_{fs} - V_{off})$ is defined as S_n (normalized sensor sensitivity).

25 4) V_{off}/B_{cal} is defined as V_{offn} (normalized).

Sensor sensitivity S_n and the normalized minimum pressure voltage V_{offn} are stored in microprocessor 28 and used to calculate pressure. Outputs 24 and 27 are sampled by microprocessor 28 during a pressure measurement. The voltage magnitude sampled from output
30 24 of amplifier 23 is known as V_{out} . The voltage magnitude sampled from voltage divider circuit 26 is known as V_{div} . Pressure is calculated by microprocessor 28 and output in digital format at output 29 by the following equation.

$$5) \text{ Pressure} = [V_{out} - (V_{offn} * V_{div})] * [S_n * V_{div}]$$

Pulsed pressure sensor circuit 11 may drift from the calibration voltages set at the factory over time. The drift or change in voltage will decrease accuracy of the measurement. A simple method for eliminating this error is possible due to the linear relationship between bias voltage and sensitivity of pressure sensor 17. The voltage drift does not affect the slope of the linear relationship between bias voltage and sensitivity. For example, the initial calibration for pulsed pressure sensor circuit 11, at zero pressure (or minimum pressure), is set at 0.50 volts, if a recalibration measurement at zero pressure (or minimum pressure) yields a voltage at output 24 (measured by microprocessor 28) of 0.55 volts, pulsed pressure sensor circuit 11 has drifted from it's original setting by 0.05 volts. Output 27 of voltage divider circuit 26 must also be measured with the recalibration measurement. The voltage drift can be cancelled by simply replacing V_{off} and B_{cal} in the equations listed above with the new measured values. Recalibration for drift insures maximum accuracy for pulsed pressure sensor circuit 11.

By now it should be appreciated that there has been provided a pulsed pressure sensor circuit for sensing pressure. Pulsed pressure sensor circuit 11 increases sensitivity for low pressure measurements while maintaining low cost and low power consumption.

THE CLAIMS DEFINING THE INVENTION ARE AS FOLLOWS:

1. A pulsed pressure sensor circuit having increased sensitivity including:

5 a pulse generation circuit for providing a voltage pulse at an output; and

a pressure sensor having a bias input coupled to said output of said pulse generation circuit, a port exposed to ambient pressure, and an output for providing
10 an output signal corresponding to said ambient pressure.

2. The pulsed pressure sensor circuit of claim 1 wherein said pulse generation circuit has a control input responsive to an enabling signal applied thereto for providing said voltage pulse.

15 3. The pulsed pressure sensor circuit of claim 2 further including:

an amplifier having an input coupled to said output of said pressure sensor and an output; and

a voltage divider circuit having an input coupled to
20 said output of said pulse generation circuit and an output.

4. The pulsed pressure sensor circuit of claim 3 further including:

a microprocessor having a first input coupled to said output of said amplifier, a second input coupled to
25 said output of said voltage divider circuit, a first output for providing an enabling signal coupled to said control input of said pulse generation circuit, and a second output for providing pressure data.

30 5. The pulsed pressure sensor circuit of claim 4 wherein said pulse generation circuit is responsive to said enabling signal from said microprocessor for varying the magnitude of said voltage pulse to change sensitivity of said pressure sensor.

35



6. A method for sensing pressure ^{including:} ~~comprising:~~
exposing a port of a pressure sensor to ambient pressure;
providing a voltage pulse;
biasing said pressure sensor with said voltage pulse; and
5 measuring an output voltage of said pressure sensor wherein
said output voltage is proportional to said ambient pressure.

7. The method of claim 6 wherein said step of biasing said
pressure sensor includes:

10 adjusting sensitivity of said pressure sensor by changing the
voltage magnitude of said voltage pulse.

8. The method of claim 6 wherein said step of measuring an
output voltage includes:

15 amplifying said output voltage of said pressure sensor;
sampling said amplified output voltage at a predetermined time;
and
converting said voltage to a digital format.

9. The method of claim 8 further including:

sensing said voltage pulse;
reducing the magnitude of said voltage pulse;
sampling said reduced magnitude voltage pulse at a
predetermined time; and
25 converting said sampled voltage pulse to a digital format.



10. A pulsed pressure sensing circuit ^{including:} ~~comprising:~~
a pulse generation circuit having a control input and an output;
a pressure sensor having a bias input coupled to said output of
said pulse generation circuit, a first output, a second output, and a port
5 exposing a diaphragm to a pressure to be measured;
an amplifier having a first input coupled to said first output of
said pressure sensor, a second input coupled to said second output of
said pressure sensor, and an output;
a voltage divider circuit having an input coupled to said output
10 of said pulse generation circuit, and an output; and
means for calculating pressure having a first input coupled to
said output of said amplifier, a second input coupled to said output of
said voltage divider, a first output, and a second output coupled to said
control input.
- 15 11. A pulsed pressure sensor circuit substantially as herein
described with reference to the accompanying drawing.
12. A method for sensing pressure substantially as herein described
with reference to the accompanying drawing.

DATED: 12th August, 1993

PHILLIPS ORMONDE & FITZPATRICK

Attorneys for:

MOTOROLA, INC.

David B Fitzpatrick



PULSED PRESSURE SENSOR CIRCUIT AND METHOD THEREFOR

Abstract of the Disclosure

5

A pulsed pressure sensor circuit (11) with increased sensitivity for measuring low pressures. A pulse generation circuit (12) is enabled by a microprocessor (28) to output a voltage pulse. The voltage pulse biases a pressure sensor (17) which has a port exposed to a pressure to be
10 sensed. The pressure sensor (17) outputs a differential voltage which is proportional to the pressure at the port. The differential voltage is amplified by an amplifier (23) which has an output coupled to the microprocessor (28). A voltage divider circuit (26) is coupled to the pulse generation circuit (12) and has an output coupled to the
15 microprocessor (28). The microprocessor (28) samples the voltages at the output of the amplifier (23) and the output of the voltage divider circuit (26). Microprocessor (28) then calculates the pressure using the sampled voltages and data stored in memory.

44659/93

