




(86) Date de dépôt PCT/PCT Filing Date: 2008/04/18
(87) Date publication PCT/PCT Publication Date: 2008/11/06
(45) Date de délivrance/Issue Date: 2014/02/04
(85) Entrée phase nationale/National Entry: 2009/10/16
(86) N° demande PCT/PCT Application No.: EP 2008/054733
(87) N° publication PCT/PCT Publication No.: 2008/132073
(30) Priorités/Priorities: 2007/04/30 (US60/927,054);
2007/08/15 (US60/964,878)

(51) Cl.Int./Int.Cl. *H04J 11/00* (2006.01),
H04L 27/26 (2006.01)
(72) Inventeurs/Inventors:
HOOLI, KARI, FI;
HUGL, KLAUS, FI;
PAJUKOSKI, KARI, FI;
TIIROLA, ESA, FI
(73) Propriétaire/Owner:
NOKIA SIEMENS NETWORKS OY, FI
(74) Agent: SIM & MCBURNEY

(54) Titre : DECALAGE CYCLIQUE COORDONNE ET SAUT SEQUENTIEL POUR SEQUENCES D'ETALEMENT DE ZADOFF-CHU, ZADOFF-CHU MODIFIE OU PAR BLOCS
(54) Title: COORDINATED CYCLIC SHIFT AND SEQUENCE HOPPING FOR ZADOFF-CHU, MODIFIED ZADOFF-CHU, AND BLOCK-WISE SPREADING SEQUENCES



(57) Abrégé/Abstract:

A cyclic shift of a reference signal is quantized as a combination of a cell specific cyclic shift with an outcome of a pseudo-random hopping, and an indication of the cell specific cyclic shift is broadcast in the cell. In one embodiment the cyclic shift is quantized as a



(57) **Abrégé(suite)/Abstract(continued):**

modulo operation on a sum of the cell specific cyclic shift, the outcome of the pseudo-random hopping, and a user specific cyclic shift, in which case an indication of the user specific cyclic shift is sent in an uplink resource allocation and a user sends its cyclically shifted reference signal in the uplink resource allocated by the uplink resource allocation. The cyclic shift may also be quantized according to length of the reference signal as $\text{cyclic\_shift\_symbol} = (\text{cyclic\_shift\_value} * \text{length of the reference signal}) / 12$; where $\text{cyclic\_shift\_value}$ is between zero and eleven and $\text{cyclic\_shift\_symbol}$ is the amount of cyclic shift given in reference signal symbols.

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
6 November 2008 (06.11.2008)

PCT

(10) International Publication Number
WO 2008/132073 A1

(51) International Patent Classification:

H04J 11/00 (2006.01) **H04L 27/26** (2006.01)

FIN-90240 Oulu (FI). **TIIROLA, Esa** [FI/FI]; Porttikel-
lonkuja 12, FIN-90450 Kempele (FI).

(21) International Application Number:

PCT/EP2008/054733

(74) **Common Representative:** NOKIA SIEMENS NET-
WORKS OY; COO RTP IPR / Patent Admin., 80240
Munich (DE).

(22) International Filing Date: 18 April 2008 (18.04.2008)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:

60/927,054 30 April 2007 (30.04.2007) US
60/964,878 15 August 2007 (15.08.2007) US

(81) **Designated States** (*unless otherwise indicated, for every
kind of national protection available*): AE, AG, AL, AM,
AO, AT, AU, AZ, BA, BB, BG, BH, BR, BW, BY, BZ, CA,
CH, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE,
EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID,
IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LA, LC,
LK, LR, LS, LT, LU, LY, MA, MD, ME, MG, MK, MN,
MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PG, PH,
PL, PT, RO, RS, RU, SC, SD, SE, SG, SK, SL, SM, SV,
SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN,
ZA, ZM, ZW.

(71) **Applicant** (*for all designated States except US*): **NOKIA
SIEMENS NETWORKS OY** [FI/FI]; Karaportti 3, FIN-
02610 Espoo (FI).

(72) Inventors; and


(75) **Inventors/Applicants** (*for US only*): **HOOLI, Kari**
[FI/FI]; Nykäsenkankaantie 6 A 7, FIN-90650 Oulu (FI).
HUGL, Klaus [AT/FI]; Pohjoiskaari 4 B 19, FIN-00200
Helsinki (FI). **PAJUKOSKI, Kari** [FI/FI]; Purantie 3,

(84) **Designated States** (*unless otherwise indicated, for every
kind of regional protection available*): ARIPO (BW, GH,
GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM,
ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM),

[Continued on next page]

(54) **Title:** COORDINATED CYCLIC SHIFT AND SEQUENCE HOPPING FOR ZADOFF-CHU, MODIFIED ZADOFF-CHU,
AND BLOCK-WISE SPREADING SEQUENCES

FIG 17



(57) **Abstract:** A cyclic shift of a reference signal is quantized as a combination of a cell specific cyclic shift with an outcome of a pseudo-random hopping, and an indication of the cell specific cyclic shift is broadcast in the cell. In one embodiment the cyclic shift is quantized as a modulo operation on a sum of the cell specific cyclic shift, the outcome of the pseudo-random hopping, and a user specific cyclic shift, in which case an indication of the user specific cyclic shift is sent in an uplink resource allocation and a user sends its cyclically shifted reference signal in the uplink resource allocated by the uplink resource allocation. The cyclic shift may also be quantized according to length of the reference signal as $\text{cyclic\_shift\_symbol} = (\text{cyclic\_shift\_value} * \text{length of the reference signal}) / 12$; where $\text{cyclic\_shift\_value}$ is between zero and eleven and $\text{cyclic\_shift\_symbol}$ is the amount of cyclic shift given in reference signal symbols.

WO 2008/132073 A1

WO 2008/132073 A1



European (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MT, NL, NO, PL, PT, RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

— *before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments*

Published:

— *with international search report*

COORDINATED CYCLIC SHIFT AND SEQUENCE HOPPING FOR ZADOFF- CHU, MODIFIED ZADOFF-CHU, AND BLOCK-WISE SPREADING SEQUENCES

TECHNICAL FIELD:

[0001/2] The exemplary and non-limiting embodiments of this invention relate generally to wireless communications systems and, more specifically, relate to transmission/reception of ZC (Zadoff Chu) sequences including transitional ZC sequences as well as modified (e.g., extended or truncated) ZC sequences.

BACKGROUND:

[0003] The following abbreviations are herewith defined:

3GPP	third generation partnership project
ACK	acknowledgement
CAZAC	constant amplitude zero auto-correlation
CDM	code division multiplex
CQI	channel quality indication
DFT	discrete Fourier transform
DM	demodulation
e-	evolved (also known as LTE for e-UTRAN)
FDM/FDMA	frequency division multiplex/multiple access
IFFT	inverse fast Fourier transform
LB	long block
LTE	long term evolution (also known as 3.9G)
NACK	negative ACK
Node B	base station or BS (including (e-Node B)
OFDM	orthogonal frequency division multiplex
PUCCH	physical uplink control channel
RAN	radio access network
RS	radio link control
RU	reference signal
SIMO	single input multiple output
TTI	transmission time interval

UE	user equipment
UL	uplink
UMTS	universal mobile telecommunications system
UTRAN	UMTS terrestrial radio access network
V-MIMO	virtual multiple input/multiple output
ZC	Zadoff-Chu

[0004] Reference can be made to 3GPP TR 25.814, V7.0.0 (2006-06); TECHNICAL SPECIFICATION GROUP RADIO ACCESS NETWORK; PHYSICAL LAYER ASPECTS FOR EVOLVED UNIVERSAL TERRESTRIAL RADIO ACCESS (UTRA) (Release 7), such as generally in section 9.1 for a description of the SC-FDMA UL of e-UTRA. Referring to Figure 1A, which reproduces Figure 9.1.1-4 of 3GPP TR 25.814; according to that (former) format there are two blocks reserved for the pilot signal in the 3GPP LTE UL former frame format, referred to as short blocks SB1 and SB2. That format has been recently changed, and Figure 1B shows a generic format according to current adoption, taken from section 4.1, Figure 1 of 3GPP TS 36.211 (V1.0.0) (2007-03). It is seen at Figure 1B that according to the current format, there are no longer SBs but rather the structure is one subframe consisting of two slots, each of length 0.5 msec. The SBs of the older format are replaced by LBs in the newer format. Regardless of the particular format though (Figures 1A, 1B or otherwise), in each subframe there will be two pilots (2 pilot LBs in the latest format or more generically two pilot RSs). Additional LBs may also be used for this purpose (e.g., for transmitting out-band or out-time RSs), which may or may not be periodic.

[0005] More specifically, as is described in Section 9.1 of 3GPP TR 25.814, the basic uplink transmission scheme is single-carrier transmission (SC-FDMA) with cyclic prefix to achieve uplink inter-user orthogonality and to enable efficient frequency-domain equalization at the receiver side. Frequency-domain generation of the signal, sometimes known as DFT-spread OFDM (DFT S-OFDM), is assumed and illustrated in Figure 1C, which reproduces Figure 9.1.1-1 of 3GPP TR 25.814. This approach allows for a relatively high degree of commonality with the downlink OFDM scheme and the same parameters, e.g., clock frequency, can be reused.

[0006] The basic sub-frame structure formerly approved for the UL transmission is shown herein in Figure 1A; two short blocks (SB) and six long blocks (LB) are defined per

sub-frame, and two subframes span one TTI. Short blocks are used for reference signals for coherent demodulation and/or control/data transmission. Long blocks are used for control and/or data transmission. As seen at Figure 1B, there is no longer a distinction as between SBs and LBs but there are still two slots, each to bear one pilot sequence. The data could include either or both of scheduled data transmission and non-scheduled data transmission, and the same sub-frame structure is used for both localized and distributed transmission.

[0007] The Zadoff-Chu CAZAC sequence has been agreed upon as the pilot sequence for the LTE UL.

[0008] ZC sequences and their modified versions (i.e., truncated and/or extended ZC sequences) are therefore used as reference signals in the LTE uplink system, and will also be used on the physical uplink control channel (PUCCH). It has been decided in 3GPP that data-non-associated control signals such as ACK/NACK and CQI will be transmitted on PUCCH by means of ZC sequences. A paper entitled "MULTIPLEXING OF L1/L2 CONTROL SIGNALS BETWEEN UES IN THE ABSENCE OF UL DATA" (3GPP TSG RAN WG1 Meeting #47bis, Sorrento, Italy; January 15-19, 2007 by Nokia, document R1-070394) is a reference for those methods. Multiple UEs in a given cell share the same Zadoff-Chu sequence while keeping the orthogonality by using a cyclic shift specific to each UE. In this manner different ones of the UEs in a cell may multiplex their UL transmissions (e.g., non-data associated UL transmissions) on the same frequency and time resource (physical resource block/unit or PRB/PRU; currently 180 kHz in LTE). The orthogonality of the ZC sequences enables the receiving Node B to discern the different signals from one another. However, two problems arise.

[0009] First, ZC sequences of different lengths may occasionally have large cross correlation properties. This causes an interference problem for demodulation reference signals.

[0010] In order to avoid "code-domain" collisions on PUCCH, different cells/sectors should utilize different ZC mother sequences. This is a problem related to ZC sequences used in PUCCH in that there are not enough proper mother sequences for sufficient randomization, so in some instances adjacent cells operate with the same ZC mother sequence (sometimes

termed the base sequence).

[0011] Another issue related to PUCCH is that different UEs transmitting data-non-associated control signals in the same cell are separated only by means of different cyclic shifts of the same ZC sequence. The problem with this approach is that the sequences are not perfectly orthogonal against each other.

- Orthogonality is Doppler-limited with block-wise spreading performed in the time domain; and
- Orthogonality is delay-spread –limited when using cyclic shifts of ZC or CAZAC codes within a LB.

[0012] It is also noted that orthogonality problems will increase when some practical limitations such as power control errors are taken into account.

[0013] Figure 2 is a schematic diagram showing the available cyclic shifts for a ZC sequence of length 12 symbols. It is noted that orthogonality between different code channels varies widely; the best orthogonality is achieved between the code channels which have the largest difference in cyclic shift domain (e.g., cyclic shift #0 and cyclic shift #6 of Figure 2) whereas the worst orthogonality is between two adjacent cyclic shifts (e.g., cyclic shift #3 and cyclic shifts #2 and #4 of Figure 2).

[0014] The same issue is related also to the cyclic shifts of block-level spreading codes (see the above-referenced document R1-070394 for further details). Considering an extreme case where the Doppler spread is very high (i.e., due to the UE movement). It is noted that block level codes with adjacent cyclic shifts have the worst cross-correlation properties, and are therefore most difficult to distinguish from one another at the receiver after being multiplexed. Further detail as to addressing such Doppler shifts can be seen at U.S. Provisional Patent Application NO. 60/899,861, filed on February 5, 2007; and now PCT/IB2007/004134, filed on December 28, 2007.

[0015] Pseudo-random cyclic shift hopping is known in the art, as can be seen at a paper entitled: "CYCLIC SHIFT HOPPING FOR UPLINK SOUNDING REFERENCE SIGNAL" (3GPP TSG

WO 2008/132073

PCT/EP2008/054733

RAN WG1 Meeting #48, St. Louis, USA, February 12-16, 2007 by ETRI, document R1-070748).

[0016] Another relevant paper is entitled "NON-COHERENT ACK/NACK SIGNALING USING CODE SEQUENCES AS INDICATORS IN E-UTRAN UPLINK" (3GPP TSG RAN WG1 Meeting #47bis, Sorrento, Italy, January 15-19, 2007 by ETRI, document R1-070078). This paper proposes to use some kind of randomization for ACK/NACK signaling. It assumes that the ACK/NACK signal is transmitted without separate RS such that a certain cyclic shift of CAZAC code corresponds to an ACK and another cyclic shift corresponds to a NACK, respectively. Document R1-070078 appears to propose that mapping of ACK/NACK is done such that a one-to-one mapping relation between the ACK/NACK information and the transmission cyclic shifts in the second block is reversed against the mapping in the first long block LB, and the ACK/NACK information is conveyed in the amount of the cyclic shift.

[0017] This is seen to forego what the inventors see as the primary advantage of cyclic shifting: randomizing interference between different code channels when the same underlying mother ZC sequence is used. Where the cyclic shift is given by the ACK/NACK message the UE seeks to send, the orthogonality of the ZC codes cannot be maximized. As will be seen below, the inventors have devised a different approach to address the problem of too few ZC mother codes available to orthogonalize all ZC sequences in use by the various UEs.

SUMMARY:

[0018] In accordance with one exemplary aspect of the invention is a method that includes quantizing a cyclic shift of a reference signal as a combination of a cell specific cyclic shift with an outcome of a pseudo-random hopping, and broadcasting an indication of the cell specific cyclic shift.

[0019] In accordance with another exemplary aspect of the invention is an apparatus that includes a processor and a transmitter. The processor is configured to quantize a cyclic shift of a reference signal as a combination of a cell specific cyclic shift with an outcome of pseudo-random hopping. The transmitter is configured to broadcast an indication of the cell specific cyclic shift.

[0020] In accordance with another exemplary aspect of the invention is a computer readable memory embodying a program of instructions that are executable by a processor to perform actions directed toward determining a cyclic shift of a reference signal. In this embodiment the actions include quantizing a cyclic shift of a reference signal as a combination of a cell specific cyclic shift with an outcome of a pseudo-random hopping, and broadcasting an indication of the cell specific cyclic shift.

[0021] In accordance with another exemplary aspect of the invention is an apparatus that includes processing means (such as for example a digital processor, an ASIC, a FPGA, or the like) and communication means (such as for example a transmitter or transceiver configured to broadcast the cell specific cyclic shift wirelessly). The processing means is for quantizing a cyclic shift of a reference signal as a combination of a cell specific cyclic shift with an outcome of pseudo-random hopping. The communication means is for sending an indication of the cell specific cyclic shift over a wireless link

[0022] In accordance with another exemplary aspect of the invention is a method that includes determining a cell specific cyclic shift from a received indication of the cell specific cyclic shift, determining a quantized cyclic shift of a reference signal as a combination of the cell specific cyclic shift with an outcome of a pseudo-random hopping, and sending a reference signal that is cyclically shifted according to the determined quantized cyclic shift

[0023] In accordance with another exemplary aspect of the invention is a computer readable memory embodying a program of instructions that is executable by a processor to perform actions directed toward determining a cyclic shift of a reference signal. In this embodiment the actions include determining a cell specific cyclic shift from a received indication of the cell specific cyclic shift, determining a quantized cyclic shift of a reference signal as a combination of the cell specific cyclic shift with an outcome of a pseudo-random hopping, and sending a reference signal that is cyclically shifted according to the determined quantized cyclic shift.

[0024] In accordance with another exemplary aspect of the invention is an apparatus that

WO 2008/132073

PCT/EP2008/054733

includes a receiver, a processor and a transmitter. The receiver is configured to receive an indication of a cell specific cyclic shift. The processor is configured to determine from the received indication the cell specific cyclic shift, and also to determine a quantized cyclic shift of a reference signal as a combination of the cell specific cyclic shift with an outcome of a pseudo-random hopping. The transmitter is configured to send a reference signal that is cyclically shifted according to the determined quantized cyclic shift.

[0025] In accordance with another exemplary aspect of the invention is an apparatus that includes receiving means (such as for example a receiver or a transceiver), determining means (such as for example a processor, and ASIC or FPGA, or the like), and sending means (such as for example a transmitter or a transceiver). The receiving means is for receiving receive an indication of a cell specific cyclic shift. The determining means is for determining from the received indication the cell specific cyclic shift, and is also for determining a quantized cyclic shift of a reference signal as a combination of the cell specific cyclic shift with an outcome of a pseudo-random hopping. The sending means is for sending a reference signal that is cyclically shifted according to the determined quantized cyclic shift.

BRIEF DESCRIPTION OF THE DRAWINGS:

[0026] Embodiments of the invention are detailed below with particular reference to the attached drawing Figures.

[0027] Figure 1A reproduces Figure 9.1.1-4 of 3GPP TR 25.814 (V7.0.0), showing an earlier sub-frame format for the 3GPP LTE UL.

[0028] Figure 1B reproduces Figure 1 at section 4.1 of 3GPP TR 36.211 (V1.0.0), showing a recently-adopted sub-frame format (generic) for the 3GPP LTE UL.

[0029] Figure 1C reproduces Figure 9.1.1-1 of 3GPP TR 25.814, and shows frequency domain generation of the transmitted signal for the 3GPP LTE SC-FDMA UL.

[0030] Figure 2 is a schematic diagram illustrating all available cyclic shifts of CAZAC

WO 2008/132073

PCT/EP2008/054733

sequence over a single resource unit, arranged as a clock to show adjacent shift with poor orthogonality and opposed shifts with good orthogonality.

[0031] Figure 3 shows a simplified block diagram of various electronic devices that are suitable for use in practicing the exemplary embodiments of this invention.

[0032] Figures 4A-B are each similar to Figure 2 and showing different CAZAC sequence cyclic shift hopping patterns for use in different slots within any given transmission time interval.

[0033] Figure 5 is a table showing the combined data of Figures 4A-B in tabular format as may be stored in a network or portable wireless device.

[0034] Figure 6 is similar to Figures 4A-B showing, for different spreading factors, different block level cyclic shift hopping patterns.

[0035] Figure 7 is a table showing the data of Figure 6 in tabular format as may be stored in a network or portable wireless device.

[0036] Figure 8 is a prior art diagram of a transmission format for ACK/NACK signaling in UTRAN-LTE.

[0037] Figure 9 is a tabular format of combined CAZAC sequence cyclic shift hopping and block-wise spreading sequence cyclic shift hopping for the ACKs/NACKs sent according to Figure 8.

[0038] Figure 10 is a tabular format of an inter-TTI cyclic shift hopping pattern for twelve reference signals that repeats over one radio frame (ten transmission time intervals).

[0039] Figure 11 is similar to Figure 4A but showing the combined cyclic shift pattern for combined intra-TTI and inter-TTI shift hopping.

WO 2008/132073

PCT/EP2008/054733

[0040] Figure 12 is similar to Figure 4A illustrating cyclic shift patterns for each of three different SIMO/MIMO environments.

[0041] Figure 13 is a tabular format of a symbol-wise hopping pattern component randomizing for intra-cell interference for twelve cyclic shifts of CAZAC sequence that repeats over one radio frame slot (seven long blocks) when 12 UEs are multiplexed by CAZAC sequence cyclic shifts.

[0042] Figure 14 shows mapping between the LB number in a slot and the columns of symbol-wise hopping pattern.

[0043] Figure 15 is a tabular format of a symbol-wise hopping pattern component randomizing for intra-cell interference for twelve cyclic shifts of CAZAC sequence that repeats over one radio frame slot (seven long blocks) when 6 UEs are multiplexed by CAZAC sequence cyclic shifts.

[0044] Figure 16 is a tabular format of a symbol-wise hopping pattern component randomizing for inter-cell interference for twelve cyclic shifts of CAZAC sequence that repeats over one radio frame slot (seven long blocks).

[0045] Figure 17 is a process flow diagram according to an exemplary and non-limiting embodiment of the invention.

DETAILED DESCRIPTION:

[0046] Embodiments of this invention concern ZC cyclic shift hopping. The goal of the shift hopping in certain embodiments is to provide improved cross-correlation and interference averaging properties between the ZC sequences transmitted by multiple UEs. Embodiments of this invention present a coordinated cyclic shift hopping scheme that is applicable for both demodulation RS and PUCCH. In broad terms, an exemplary code hopping scheme presented herein can be divided into two distinct aspects: randomization inside a TTI and randomization outside the TTI. A particularly advantageous environment for this invention is the UL in a

UTRAN LTE system, though that itself is not a limitation to this invention since the sequence hopping techniques detailed herein may be used in any wireless system such as GSM (global system for mobile communication), HSDPA (high-speed data packet access), or any other system that might employ shifted CAZAC sequences/reference signals from a limited number of mother/base codes. Further, the invention is not limited to only ZC codes but to any CAZAC sequence, and the ZC codes detailed herein include modified (e.g., extended or truncated) ZC codes as well. As will be seen, both transmission and reception of such ZC sequences are detailed.

[0047] Reference is made first to Figure 3 for illustrating a simplified block diagram of various electronic devices that are suitable for use in practicing the exemplary embodiments of this invention. In Figure 3 a wireless network 1 is adapted for communication with a UE 10 via a Node B (base station) 12. The network 1 may include a serving gateway GW 14, or other radio controller function. The UE 10 includes a data processor (DP) 10A, a memory (MEM) 10B that stores a program (PROG) 10C, and a suitable radio frequency (RF) transceiver 10D for bidirectional wireless communications over a link 16 via one or more antennas 10E with the Node B 12, which also includes a DP 12A, a MEM 12B that stores a PROG 12C, and a suitable RF transceiver 12D and antenna 12E. The Node B 12 may communicate via a data path 18 (e.g., Iub) to the serving or other GW 14, which itself includes a DR 14A coupled to a MEM 14B storing a PROG 14C. The GW 14 may then communicate via another data interface to a core network (not shown) as well as to other GWs. At least one of the PROGs 10C, 12C and 14C is assumed to include program instructions that, when executed by the associated DP, enable the electronic device to operate in accordance with the exemplary embodiments of this invention, as will be discussed below in greater detail. In general, the exemplary embodiments of this invention may be implemented by computer software executable by the DP 10A of the UE 10 and the other DPs, or by hardware, or by a combination of software and/or firmware and hardware.

[0048] In general, the various embodiments of the UE 10 can include, but are not limited to, cellular telephones, personal digital assistants (PDAs) having wireless communication capabilities, portable computers having wireless communication capabilities, image capture devices such as digital cameras having wireless communication capabilities, gaming devices

having wireless communication capabilities, music storage and playback appliances having wireless communication capabilities, Internet appliances permitting wireless Internet access and browsing, as well as portable units or terminals that incorporate combinations of such functions.

[0049] The MEMs 10B, 12B and 14B may be of any type suitable to the local technical environment and may be implemented using any suitable data storage technology, such as semiconductor-based memory devices, magnetic memory devices and systems, optical memory devices and systems, fixed memory and removable memory. The DPs 10A, 12A and 14A may be of any type suitable to the local technical environment, and may include one or more of general purpose computers, special purpose computers, microprocessors, digital signal processors (DSPs) and processors based on a multi-core processor architecture, as non-limiting examples.

[0050] As noted above, it is convenient for this description to parse the invention into two components: randomization inside a TTI and randomization outside a TTI. Figures 4-9 detail randomization inside a TTI for different scenarios, and Figure 10 details randomization outside a TTI. Figure 11 combines the above two aspects to show total cyclic shift for a certain ZC sequence taking into account both intra-TTI shifts and inter-TTI shifts to arrive at the final shift of the sequence. A shifted ZC is alternatively termed the reference signal. Figure 12 shows the principle extended to a virtual MIMO scenario.

[0051] As will be detailed below, the specific example of Figures 4A-B and 5 shows the cyclic shift hopping principle for DM RS of minimum length (12 symbols). In fact, the DM RS length depends on the allocated bandwidth, which is a multiple of RUs. In LTE, the RUs are each 12 frequency pins. It follows then that the allowed cyclic shifts can be quantized according to the RS length of the minimum bandwidth allocation. For LTE with 12 frequency pins per RU, this means that there are always only 12 possible cyclic shift values for CAZAC sequence, regardless of the RS bandwidth. The possible cyclic shift values (*cyclic_shift_value*) are then $[0, 1, \dots, 11]$. Assuming a generation of the cyclic shifts so that cyclic shifts in time results, the actual cyclic shift in symbols is calculated as follows:

$$\text{Cyclic\_shift\_symbols} = \frac{\text{cyclic\_shift\_value} \times \text{RS\_length}}{12}. \quad [\text{Eq. 1}]$$

It is noted that quantization of the cyclic shift space is clearly beneficial from the signaling point of view. With large bandwidths, sequences which have a smaller cyclic shift difference than $\text{Cyclic\_shift\_symbols}$ calculated by Equation 1 will generally not have sufficient cross-correlation properties.

[0052] First is detailed randomization inside a TTI for the environment of CAZAC sequence cyclic shifts, described with reference to Figures 4A-B and 5 using all 12 possible cyclic shifts. Randomization inside a TTI is realized by means of pre-defined shift hopping pattern. There are two slots in each TTI (Slot #1 and Slot #2; Figure 1A shows a subframe or a single slot of a TTI and Figure 1B shows two slots within a single subframe). Figure 4A-B shows one embodiment of the shift-hopping principle. Figure 4A shows the shift hopping (allocation) pattern for the first slot, and Figure 4B shows the shift hopping (allocation) pattern for the second slot. The driving criterion is to maximize the cyclic shift separation with respect to the adjacent cyclic shifts within the TTI. This is seen at Figure 4B; adjacent shifts (e.g., #6 and #4 are adjacent to #11) are well separated from their adjacent shift in that second slot. Another criterion is to maximize the cyclic shift rotation between the 1st and the 2nd slot (the shift as between the same 'clock' position/TTI of Figures 4A and 4B). Figure 4A shows this as a clockwise rotation between the adjacent resources whereas with the randomized shifts illustrated in Figure 4B this shown as a counterclockwise rotation between the adjacent resources. The shift hopping pattern of Figures 4A-B is shown in numerical format in the table of Figure 5. Each 'clock' position of Figures 4A-B corresponds to one row ('resource number' or RU) of Figure 5, and each row informs the shift for one resource of one TTI. For example, at resource number 4 of Figure 5, the ZC sequence in slot #1 is shifted to shift position 4 and the ZC sequence in slot #2 of that same TTI is shifted to shift position 2, which are well spaced from one another as can be seen at Figure 4A.

[0053] Additionally, to avoid interference among adjacent cells, a cell-specific constant rotation for the cyclic shifts of slot#2 (with respect to the original hopping pattern of Figure 5) may be imposed in order to guarantee that the shift rotation from the 1st slot to the 2nd slot is

not the same between different (adjacent) cells. This can be illustrated as follows:

$$\text{Cyclic\_sft\_slot2}(\text{cell}) = \text{mod}(\text{Cyclic\_sft\_slot2} + \text{increment}(\text{cell}), \text{Num\_Shifts}) \text{ [Eq. 2]}$$

where “Num_Shifts” is the total number of allowed cyclic shifts (e.g., 12 in this example), and mod is a modulo operation (modulus after division). The cell-specific parameter “*increment*” varies between [0, 1, ... (Num_Shifts-1)]. This randomizes the shift among adjacent cells, to preempt the situation where adjacent cells shift from the same base ZC sequence.

[0054] It is noted that if the cyclic shifts are calculated in the time domain after the inverse fast Fourier transform IFFT block of Figure 1B, then Eq. 2 as written is not valid; in that instance IFFT oversampling should be taken into account.

[0055] Continuing with an exemplary intra-TTI cyclic shift aspect of the invention, now is described with reference to Figures 6-7 an example for block level spreading. Randomization for block-level spreading codes (ZC sequences and their modified versions) inside a TTI is achieved again by means of a pre-defined cyclic shift hopping pattern. In this case though, the ZC sequence length used in the block level spreading application depends on the spreading factor. An exemplary cyclic shift hopping pattern is shown at Figure 6 in ‘clock’ pairs for spreading factors SFs two through seven, and the same data is shown numerically in the table of Figure 7. As with the CAZAC sequence example above, note that for each SF the cyclic shift separation is maximized with respect to adjacent cyclic shifts in slot #2, and that the cyclic shift rotation is maximized between the first and second slots. Different columns are shown in Figure 6 for even versus odd SFs. The SF equals the number of long blocks in the subframe (see Figure 1A).

[0056] It should be noted that the hopping pattern shown at Figure 7 can be applied also for other block-wise spreading sequences that ZC or CAZAC sequences. In particular, hopping pattern with SF=4 is optimal for randomizing Doppler induced interference between Walsh-Hadamard sequences defined by Hadamard matrices.

[0057] Similar to that noted above in the CAZAC sequence example, it follows that an additional cell-specific constant rotation may be imposed for the cyclic shifts of slot#2 (with respect to the original hopping pattern shown in Figure 7), according to Equation 2 above and for the same reason; to forego cross-correlation among adjacent cells shifting the same base ZC sequence.

[0058] Now is described a specific implementation for intra-TTI cyclic shifts of ZC sequences in an ACK/NACK transmission that randomizes those sequences. The transmission format of ACK/NACK signaling on the PUCCH was agreed at the RAN1 #48bis meeting in Malta. Figure 8 illustrates that agreed upon format. There are three blocks reserved for pilot signals (darkened blocks) and four blocks reserved for data (the lighter blocks, which is where the ACK/NACK signal lies). Two consecutive slots (0.5 msec) equal one TTI (1.0 msec), and each physical resource unit PRU has twelve RUs identified in the table of Figure 9 by the index 'cyclic shift'.

[0059] According to an embodiment of the invention, both ZC sequences (the CAZAC sequence in a symbol such as at Figure 5 and the block level ZC spreading sequence such as at Figure 7) apply the proposed shift hopping principles separately. A cyclic shift randomization example using a specific cyclic shift according to an embodiment of the invention is shown in Figure 9. As seen there, the rotation in slot #1 for both data and pilots is identical to one another. However, the cyclic shift differs markedly once in slot #2 so as to randomize any cross correlation. In each of the slots for data or pilots, there are eighteen ACK/NACK resources in use in Figure 9 as evidenced by the darkened blocks reciting a shift number.

[0060] Now is described by example the other distinct aspect of the invention noted above, randomization as between different TTIs or inter-TTI randomization. Randomization outside one TTI is achieved by means of cell specific cyclic shift patterns. An important aspect of this inter-TTI randomization is to provide uncorrelated "ZC-to-ZC" cross-correlation properties from TTI to TTI.

[0061] A randomization pattern is generated according to the minimum DM reference signal

length, which continuing with the example above is 12 symbols. There are then 12 orthogonal shift hopping patterns with 12 cyclic shifts. This means that a reuse pattern of 1/12 is possible.

[0062] Figure 10 shows an example of the cell-specific cyclic shift permutation matrix for the CAZAC sequence. The pattern is periodic and its length equals to the length of one radio frame, in this instance 10 ms or equivalently 10 TTIs. The permutation matrix has been generated in such a way that all the possible cyclic shift changes (i.e., 0, 1, ... 11) take place in all 12 cells of the reuse pattern when the TTI index changes.

[0063] Randomization outside the TTI may also be imposed for the block-spreading codes following the teachings above for intra-TTI block spreading. As with the intra-TTI cyclic spreading, a pseudo-random hopping pattern (permutation matrix) for those codes would be generated separately and used separately or combined (as the wireless protocol may allow) with the CAZAC sequence cyclic shifts similar to that done at Figure 9 when combining the intra-TTI cyclic shifts. Alternatively and for inter-TTI randomization only, the same randomization matrix (e.g., that of Figure 10 or similar) may be used for both CAZAC sequence cyclic shifts and block level cyclic shifts.

[0064] Now that both intra-TTI cyclic shifts and inter-TTI cyclic shifts have been detailed with respect to both CAZAC sequences and block spreading codes, the combined cyclic shift hopping is derived from the component shifts. The net cyclic shift of the ZC sequence that is ultimately transmitted is simply the total cyclic shift for the given slot, which is obtained as a combination of resource or cell specific cyclic shift (slot #1, slot #2) combined with an outcome of cell-specific pseudo-random hopping. In a specific example, when the value of a cell-specific permutation matrix equals to 4 (rotation shift A of Figure 11 moving from 0 to 4) and the resource-specific cyclic shift is 4 (rotation shift B of Figure 11 moving from 4 to 8), then the actual cyclic shift for slot#1 is the combined result, or eight in Figure 11. The combined rotation for slot #2 will similarly be a combination of the cell-specific permutation matrix for the second slot (the intra-TTI shift) with the resource-specific cyclic shift for that second slot (the inter-TTI shift).

[0065] The total cyclic shift value for a certain slot of a TTI taking into account both intra-TTI and inter-TTI randomization can be illustrated as

$$\text{Cyclic\_sft\_value} = \text{mod}(\text{Cyclic\_hop\_intra}(\text{cell} / \text{resource}, \text{slot}) + \text{Cyclic\_hop\_inter}(\text{cell}, i), \text{Num\_Shifts})$$

[Eq. 3]

where i is the TTI index, Cyclic_hop_intra is the cyclic shift hopping pattern for intra-TTI hopping (e.g., Figures 5 and/or 7), Cyclic_hop_inter is the cyclic shift hopping pattern for inter TTI hopping (e.g., Figure 10), Num_Shifts is the total number of allowed cyclic shifts (e.g., 12 in the example), and mod is a modulo operation (modulus after division). It is noted that cyclic shift allocation $\text{Cyclic\_hop\_inner}(\text{cell} / \text{resource}, \text{slot})$ can be configured to be cell-specific (e.g., DM RS) or resource specific (e.g., ACK/NACK using implicit signaling).

[0066] It was agreed at the RAN1 #49bis meeting that a symbol-wise cyclic shift hopping is applied on PUCCH. Cyclic shift hopping for each symbol on the PUCCH is discussed, particularly at section 4, in a paper entitled CYCLIC SHIFT HOPPING OF UL ACK CHANNELS (3GPP TSG RAN WG1 Meeting #49bis, Orlando, USA 25-29 June 2007 by Samsung, document R1-073149). The previously described cyclic shift hopping can be applied also with symbol-rate cyclic shift hopping, allowing for clearly structured hopping patterns over multiple TTIs. Two cases are considered:

- A symbol-wise hopping pattern is defined with a duration of a slot. Then the Cyclic_sft_value in Eq. 3 is used as an index referencing to a cyclic shift resource of a CAZAC sequence. This index is used in the definition of cyclic shift hopping pattern for the slot. For example, Cyclic_sft_value can provide cyclic shift value for the 1st long block LB.
- A symbol-wise hopping pattern is defined with a duration of a TTI. Then the Cyclic_hop_inter for inter-TTI hopping is used as an index referencing to a cyclic shift resource of a CAZAC sequence. This index is used in the definition of cyclic shift hopping pattern for the TTI. For example, Cyclic_sft_value can provide cyclic shift value for the 1st LB.

[0067] Other variations are possible, but since the above description provides an inter-TTI

shift pattern, an intra-TTI shift pattern, and a total shift pattern, any one of those patterns can be used as an index referencing to a cyclic shift resource for a symbol-wise hopping pattern in the slots of a TTI and among different TTIs.

[0068] Now symbol-wise cyclic shift hopping patterns with a duration of a slot are defined. These patterns are composed of two components, with the other providing intra-cell interference randomisation and the other providing inter-cell randomisation. Starting from the hopping pattern component randomizing intra-cell interference, the main criterion on the hopping pattern design is to minimize the occurrence, or the number of LBs, within a TTI when a particular pair of UEs uses neighbouring cyclic shifts. Only the pairs between UEs using the same block-wise spreading code are considered in the criterion, since the transmissions from UEs using different block-wise spreading codes are mutually orthogonal at low or moderate UE speeds.

[0069] Two different multiplexing scenarios are considered with intra-cell interference randomization: when either 12 or 6 UEs are multiplexed by CAZAC sequence cyclic shifts within a LB (Cyclic_shift_symbols in Eq.1). When 12 UEs are multiplexed by CAZAC sequence cyclic shifts, all 12 cyclic shifts can be used by UEs having the same block-wise spreading code. Hence the design of hopping pattern is focused on randomization of interference between even and odd cyclic shifts in particular. Figure 13 shows one cyclic shift hopping pattern according the design criterion. The multiplexing scenario of 12 UEs by CAZAC sequence cyclic shifts may be used on the transmission of scheduling requests, in which case the intra-cell interference randomization by symbol-wise cyclic shift hopping becomes crucial.

[0070] 6 UEs can be multiplexed by CAZAC sequence cyclic shifts in the case of CQI, ACK/NACK, or scheduling request transmission. In this scenario, different UEs having the same block-wise spreading code are separated by two cyclic shifts. Hence the design of hopping pattern is focused on randomization of interference among the even cyclic shifts as well as among the odd cyclic shifts, and only little attention is paid to the randomization between even and odd cyclic shifts. Another aspect of this scenario is that some of the LBs are used for reference signal (2 or 3 in the case of CQI or ACK/NACK, respectively) while

others are used to carry information (4 or 5 in the case of ACK/NACK or CQI, respectively). As a result, the cyclic shift hopping pattern does not need to have length of subframe and the length corresponding to the maximum number of either information or reference LBs is sufficient. To obtain the period of a subframe, some of the columns of the hopping pattern are repeated during the subframe. However, they are repeated so that the same columns are not repeated during the transmission of information LBs or during the transmission of reference symbols. One such mapping between hopping pattern columns and LB number in a slot is shown in Figure 14. It should be noted that such mapping allows for multiplexing of CQI and ACK/NACK transmissions from different UEs into one RU. Figure 15 shows one cyclic shift hopping pattern according the presented design criterion

[0071] Continuing with the component of symbol-wise hopping pattern randomizing inter-cell interference, the same principles as with inter-TTI randomization are applied. Randomization is achieved by means of cell specific cyclic shift patterns, and a randomization pattern is generated according to the sequence length within a LB, which continuing with the example above is 12 symbols. There are then 12 orthogonal shift hopping patterns with 12 cyclic shifts, meaning that a reuse pattern of 1/12 is possible.

[0072] Figure 16 shows an example of the cell-specific cyclic shift permutation matrix for the CAZAC sequence. The pattern is periodic and its length equals to the length of one slot, in this instance 0.5 ms or equivalently 7 LBs. The permutation matrix has been generated in such a way that all the possible cyclic shift changes (i.e., 0,1, ... 11) take place in all 12 cells of the reuse pattern when the TTI index changes.

[0073] The cyclic shift value for a certain LB taking into account intra-TTI and inter-TTI randomization as well as symbol-wise hopping can be illustrated as

$$\text{Cyclic\_Shift} = \text{mod}(\text{Symbol\_hop\_intra}(\text{Cyclic\_sft\_value}, m, c) + \text{Symbol\_hop\_inter}(\text{cell}, k), \text{Num\_Shifts})$$

[Eq. 4]

where Symbol_hop_intra is the component of symbol-wise hopping randomizing intra-cell interference (e.g. Figure 13 or 14), Cyclic_sft_value is the value given by Eq.3, k is the LB

index, m is the index mapping k index to hopping pattern columns, c is the parameter related to the resource allocation or block-wise spreading code and the transmission content, Symbol_hop_inter is the component of symbol-wise hopping randomizing inter-cell interference (e.g. Figure 16), Num_Shifts is the total number of allowed cyclic shifts (e.g., 12 in the example), and mod is a modulo operation (modulus after division).

[0074] Implementation of the shift hopping patterns can be based on a lookup table located/stored in a MEM of the UE 10 and of the Node B 12. Separate lookup tables may be used for randomization inside the TTI and randomization outside the TTI as well as for the intra-cell and inter-cell interference randomisation components of symbol-wise cyclic shift hopping in the manner described above.

[0075] An alternative to the stored lookup tables is to implement the functionality by means of simple equations, which may be implemented as software, firmware (integrated circuitry), or a combination. For example, Figure 5 can be implemented as the equations:

$\text{Cyclic\_sft\_slot2} = \text{mod}(6 - \text{Cyclic\_sft\_slot1}, 12),$ for even values of “Cyclic_sft_slot1”;
and by

$\text{Cyclic\_sft\_slot2} = \text{mod}(-\text{Cyclic\_sft\_slot1}, 12),$ for odd values of “Cyclic_sft_slot1”;

where N is the length of the sequence (in symbols).

[0076] Similarly, Figure 7 can be implemented as the equations:

$\text{Cyclic\_sft\_slot2} = \text{mod}(1 - \text{Cyclic\_sft\_slot1}, N),$ for even values of N ;

$\text{Cyclic\_sft\_slot2} = \text{mod}(1 + 2 * \text{Cyclic\_sft\_slot1}, N),$ for $N=3$;

$\text{Cyclic\_sft\_slot2} = \text{mod}(-2 + 3 * \text{Cyclic\_sft\_slot1}, N),$ for $N=5$; and

$$\text{Cyclic\_sft\_slot2} = \text{mod}(2 * \text{Cyclic\_sft\_slot1} + 1, N), \quad \text{for } N=7.$$

[0077] Intra-cell interference randomization hopping component in the scenario of 12 UEs multiplexed can be implemented as the equations:

$$\begin{aligned} \text{Symbol\_hop\_intra} = \\ \text{mod}(\text{Cyclic\_sft\_value} - \lfloor k_{LB} / 7 \rfloor \text{Cyclic\_sft\_value} / 2, 12), \end{aligned}$$

for even values of “Cyclic_sft_value” given by Eq. 3;

$$\begin{aligned} \text{Symbol\_hop\_intra} = \\ \text{mod}(\text{Cyclic\_sft\_value} + 2(k_{LB} - 1) - \lfloor k_{LB} / 7 \rfloor \left(\frac{\text{Cyclic\_sft\_value} + 1}{2} - 6 \right), 12), \end{aligned}$$

for odd values of “Cyclic_sft_value”, where $k_{LB} = 1, 2, \dots, 7$ is the index of LB in the slot.

[0078] Intra-cell interference randomization hopping component in the scenario of 6 UEs multiplexed can be implemented as the equations:

$$\begin{aligned} \text{Symbol\_hop\_intra} = \\ \text{mod}(2cs_{\text{index}} - \lfloor m_{LB} / 4 \rfloor cs_{\text{index}} - 2(cs_{\text{index}} - \text{mod}(cs_{\text{index}}, 3))(1 - \lceil m_{LB} / 4 \rceil) + c, 12), \end{aligned}$$

for even values of “Cyclic_sft_value” given by Eq. 3;

$$\begin{aligned} \text{Symbol\_hop\_intra} = \\ \text{mod}(2cs_{\text{index}} + 4(m_{LB} - 1) - \lfloor m_{LB} / 4 \rfloor (cs_{\text{index}} - 5) - (4 + 3/2(cs_{\text{index}} - \text{mod}(cs_{\text{index}}, 4)))(1 - \lceil m_{LB} / 4 \rceil) + c, 12), \end{aligned}$$

for odd values of “Cyclic_sft_value”, where $cs_{\text{index}} = \lfloor \text{Cyclic\_sft\_value} / 2 \rfloor$ thus ranging 0, 1, ..., 5, m_{LB} is as shown in Figure 14, $\lceil x \rceil$ is the smallest integer larger than or equal to x , $\lfloor x \rfloor$ is the largest integer smaller than or equal to x , parameter c can have values 0 or 1. The value for parameter c may be obtained as a remainder of $\text{Cyclic\_sft\_value} / 2$ or derived from the block spreading sequence index. It may be also a constant, a cell specific parameter, or an UE may use both values as in the case of CQI transmission utilizing two adjacent cyclic shifts.

[0079] These equations, as well as [Eq. 1], [Eq. 2], [Eq. 3], and [Eq. 4] above, may be embodied in software and executed by a digital signal processor such as the DP 10A, 12A, 14A, or by firmware/circuitry of an integrated circuit, or by some combination thereof.

[0080] The invention as detailed above by example offers multiple advantages over the cyclic

shift regimens known in the art. Specifically:

- Even-length patterns (randomization inside the TTI):
 - Cyclic shifts n and $\text{mod}(n+N/2, N)$ have always the smallest cross-correlation: maintaining this property during the randomization is beneficial in many applications.
 - o DM RS: It is always possible to provide the smallest possible cross-correlation between the UEs paired to operate in V-MIMO.
 - o Control channel application: It is possible to transmit ACK/NACK by means of RS (one cyclic shift corresponds to ACK and another cyclic shift NACK). Always the smallest possible cross-correlation between ACK/NACK.
 - o Block spreading application: Partial orthogonality properties are maximized (better Doppler protection). It is possible to maintain the orthogonality between the code channels also with very high UE speeds (e.g., 360 km/h) at the expense of multiplexing capacity.
 - Maximum cyclic shift rotation between the 1st and the 2nd slot.
 - Maximum cyclic shift separation with respect to adjacent cyclic shifts (between the 1st and 2nd slot).
- For odd-length patterns (randomization inside TTI):
 - Maximum cyclic shift rotation between the 1st and the 2nd slot.
 - Maximum cyclic shift separation with respect to adjacent cyclic shifts (between the 1st and 2nd slot).
- Straightforward signalling.
- Support for implicit signalling.

[0081] In a particular embodiment, the cyclic shift hopping is not fully configurable by the network/Node B (e.g., not on every allocation table AT/physical downlink control channel PDCCH it sends). The inventors deem the required signaling as overly burdensome if the

WO 2008/132073

PCT/EP2008/054733

used cyclic shifts need to be signaled in every UL/DL allocation grant (i.e, 12 cyclic shifts+2 slots requires at least 5 bits from the allocation grant signaling, a large signaling overhead commitment). Where the network/Node B cannot configure the cyclic shifts fully, radio link control RLC signaling and / or a sector specific broadcast channel provides the UEs with the relevant cyclic shift hopping sequences in current use, such as upon entry or re-entry of the UE into a cell.

[0082] It is noted that DM RS allocation in a V-MIMO application is a special case from the cyclic shift allocation point of view (compared to the SIMO case). Basically, in V-MIMO we need multiple cyclic shift resources per cell whereas in the SIMO case we need only a single cyclic shift per cell. Therefore,

- The SIMO case can rely on semi-static signaling: Cyclic shift allocation can be made cell or resource specific.
- In the V-MIMO case using only signaling, UEs should be put into 2 pre-determined groups corresponding to a pre-defined cyclic shift allocations (see for example Figures 4A-B). One concern with this approach is that the grouping will introduce some scheduler limitations on the network/Node B: it is not possible to schedule two UEs being allocated into the same cyclic shift group without collision of the RSs. This will reduce the potential gain of V-MIMO, though it is context-dependent as to whether the reduction would be significant or negligible.

[0083] Thereby, in the MIMO case it is advantageous to also use UE-specific signaling for the cyclic shifts. This information can be transmitted with UL resource allocation grant signaling (e.g., in an allocation table AT, also known as a packet data control channel PDCCH). That signaling would be used to signal the actual cyclic shift allocated for the particular UE in case of MIMO, such as a separate field with entries associated with each of the UEs being allocated or entries associated with only those UEs whose cyclic shift pattern is to be changed on the allocated resources as compared to its previous UL data transmission.

[0084] As an exemplary embodiment of this UE specific signaling with the UL resource allocation, the UE-specific information would include:

- 0 extra bits required in SIMO case;

- 1 extra bit required in 2x2 MIMO case (which one of the two resources is allocated to the given UE);
- 2 extra bits required in 4x4 MIMO case; and
- 3 extra bits required in MIMO case supporting more than 4 antennas.

[0085] For convenience, we term these extra bits in the UL allocation grant message as a “MIMO cyclic shift indicator”.

[0086] The MIMO-related cyclic shift signaling can be realized in two ways.

- a) Reserve always 1 or 2 bit extra signaling space (“MIMO cyclic shift indicator”) from the UL allocation grant. One can apply any of the various kinds of gray mapping for cyclic shifts and transmit antennas (i.e., a predetermined cyclic shift for a certain transmit antenna). For example:
 - “00” (or “0”) antenna #1
 - “11”, (or “1”) antenna #2
 - “01”, antenna #3
 - “10”, antenna #4
 - The SIMO case would then always transmit “0” or “00” in the extra bit field.
 - The 2x2 MIMO case would use “00” or “11” for the case that the two-bit signaling field is always reserved; otherwise “0” or “1” if only a one-bit field is used.
- b) Utilize slightly different allocation grant signaling for SIMO and MIMO
 - RLC signaling can be used to configure the presence of the “MIMO cyclic shift indicator”. This is a cell-specific configuration.
 - Configuration can be done also implicitly using the information on the cell-specific cyclic shift allocation (i.e., how many cyclic shifts are allocated in the given cell).
 - A pre-defined code puncturing scheme can be used to puncture the “MIMO cyclic shift indicator” into the existing UL allocation grant whenever needed.

[0087] As can be seen at Figure 12, the MIMO cyclic shift indicator is disregarded by the UE operating in SIMO mode, as only a single antenna is used and the MIMO cyclic shift

indicator bits “0” or “00” (if used) signaled to the SIMO UE with its UL resource allocation reflect the SIMO case cyclic shifting pattern. For the MIMO UEs (2x2 or 4x4) as seen at Figure 12, the MIMO cyclic shift indicator bits that are signaled to the MIMO UEs with their UL resource allocations are used in conjunction with the gray mapping of part a) above or with some other RLC signaling to inform the MIMO UEs how they are to adjust their cyclic shifting pattern for the next UL transmission. The network/NodeB determines how a particular UE is to change its cyclic shift pattern, and signals it accordingly, so as to ensure conflicts/interference is avoided in the cell.

[0088] So from each ZC sequence multiple reference signals are derived with a cyclic shift of the sequence. Multiple UEs in the given cell share the same Zadoff-Chu sequence while keeping the orthogonality by using a UE specific cyclic shift as detailed above. But due to different bandwidths of UE UL allocations in neighboring cells as well as due to channel estimation which requires effectively partial correlation of the sequences, the ideal cross-correlation properties of ZC sequences are lost, resulting in unacceptable (partial) cross-correlation properties arising. Randomization by cyclic shift hopping and sequence hopping addresses this problem in part, as detailed above. However, coordination of the hopping patterns is seen as a further improvement to the solution detailed above.

[0089] An ideal solution for ZC sequence hopping and coordination would allow for efficient averaging of reference signal cross-correlation while maintaining low signaling overhead and a flexible structure. A flexible solution allows for cross-correlation randomization by ZC sequence hopping as above, but also for sequence coordination and also for combining the aspects of sequence hopping and coordination. Otherwise the solution would restrict the possibilities for network planning as well as for advanced receivers mitigating RS cross-correlations.

[0090] Several options have been previously proposed:

- Sequence coordination. Since the number of available sequences is very limited with 1 resource block (RB) UL allocations, there are not sufficient sequences available to obtain acceptable partial cross-correlation properties in all scenarios. Since a large portion of cross-correlation values are unacceptably high for some

sequence pairs, sequence coordination with cyclic shift hopping does not provide a sufficient solution either in all scenarios.

- Sequence hopping. The proposed sequence hopping solutions result either in an inflexible solution, or in a large table of predefined sequence indexes, or in high signaling overhead.

[0091] However these solutions do not efficiently support both randomization by sequence hopping as well as coordination. The inventors are unaware of any prior art for a signaling arrangement that supports both randomization by sequence hopping and also sequence coordination.

[0092] It is noted that for intra-TTI sequence hopping, the length of the sequence hopping pattern is equal to the number of RS blocks within a TTI (two in the frame structures of Figures 1A and 1B), which we denote here as n , and the pattern is repeated periodically for each TTI. On the network side, the (e-)Node B 12 signals to the UE 10 the n sequence indexes for each possible UL allocation bandwidth. These sequence indexes are signaled on a radio resource control (RRC) message and / or on an eNodeB specific broadcast channel.

[0093] It is also possible to group the sequence indexes in a predetermined way and just signal the group index instead of sequence indexes of a certain group. These sequence groups can be cell-specific. The groups can be configurable or hardwired by the specification. It is also possible to perform sequence hopping outside the groups. This choice will increase the length of the hopping pattern in case that the number of sequences per group and bandwidth option is small (e.g., only 2). The UE 10 selects the used reference signal based on the bandwidth of the UL allocation and on the current RS block number. The cyclic shift hopping is applied on the top of sequence hopping/sequence coordination.

[0094] The signaling of the n sequence indexes is required for all UL allocation bandwidth options and, thus, may cause considerable signaling overhead. One option is two divide it into two parts. The first part contains n sequence indexes for the most essential allocation bandwidths and it may be signaled to the UE on a RACH response, as part of handover control signaling, and / or repeated relatively frequently on an e-NodeB specific broadcast

channel. The second part contains n sequence indexes for the remaining allocation bandwidth options and it may be signaled to the UE on a radio resource control (RRC) message and / or repeated less frequently on an eNodeB specific broadcast channel.

[0095] The need for signaling is considerably smaller in case of pre-determined sequence groups. Signaling of the cell-specific sequence group can be done on a broadcast channel with limited number of bits. However, in case that sequence indexes within the groups are configured, considerable signaling is required.

[0096] This offers several advantages. While requiring relatively low signalling overhead, it allows for:

- Both sequence coordination and sequence hopping are possible. In the sequence coordination, the same index / bandwidth is repeated n times. Sequence coordination may become an attractive option (e.g. in the case of an advanced e-Node B receiver) and is likely required for 1 RB UL allocations due to limited number of base sequences.
- The scheme is flexible. The sequence hopping pattern can be defined during the network planning and, if needed, updated during the operation of the network.

[0097] Figure 17 is a process flow diagram according to one non-limiting embodiment of the invention. At block 1702 the e-NodeB broadcasts an indication of the cell specific cyclic shift. In the particular instance of Figure 17 there are also user-specific cyclic shifts put into use, and so at block 1704 the e-NodeB sends to a particular user an indication of its user-specific cyclic shift in the uplink resource allocation for that particular user. Now (or earlier than either or both of blocks 1702 and 1704) the E-Node B quantizes at block 1706 the reference signal cyclic shifts as a combination of the cell specific cyclic shift which was indicated at block 1702 and the outcome of a pseudo-random hopping as seen at Equation [2] with the counterclockwise shift for slot 2. In an embodiment the cyclic shift is quantized as a modulo operation on a sum of the cell specific cyclic shift, the outcome of the pseudo-random hopping, and the user specific cyclic shift for which the indication was sent at block 1704. Now the particular user equipment receives at block 1708 the broadcast indication of the cell-specific cyclic shift, receives at block 1710 in its uplink resource allocation the indication of

the user-specific cyclic shift, and computes its cyclic shift just as the e-NodeB did. At block 1712 the UE sends to the e-NodeB, in the uplink resource that was allocated to it and which bore the indication of the user-specific cyclic shift, the reference signal which is cyclically shifted according to the modulo operation on the sum of the cell specific cyclic shift, the outcome of the pseudo-random hopping, and the user specific cyclic shift. The e-NodeB receives that signal and recognizes it as the demodulation reference signal for that particular user for that particular uplink resource that it allocated to that user.

[0098] While described in the context of UTRAN-LTE, it is within the scope of the exemplary embodiments of this invention to use the above described UE 10 and e-Node B 12 procedures for other types of wireless networks and the teachings herein are not limited to a particular wireless communication protocol.

[0099] It will be appreciated that embodiments of this invention provide a method, a device, a computer program tangibly embodied on a computer readable memory and executable by a processor, and an integrated circuit, to store a first cyclic shift hopping pattern adapted for intra-TTI shifting, to store a second cyclic shift hopping pattern adapted for inter-TTI shifting within a physical resource unit, to apply the first cyclic shift hopping pattern to a CAZAC sequence and to apply the second cyclic shift hopping pattern to the CAZAC sequence, and to transmit the CAZAC sequence according to a cyclic shift pattern that combines the first and the second cyclic hopping patterns.

[00100] In a particular embodiment, the first cyclic shift pattern is for CAZAC sequence, is for block level spreading for a specific spreading factor, or is a combination of both CAZAC sequence and block level spreading. In another particular embodiment, the second cyclic shift pattern is for CAZAC sequence, is for block level spreading for a specific spreading factor, or is a combination of both CAZAC sequence and block level spreading. In an embodiment, separation of cyclic shifts for either or both of the first and second patterns is maximized with respect to adjacent shifts. In another embodiment, cyclic shifts as between two slots is maximized. In yet another embodiment, the shift of at least one slot is rotated so as to avoid cross correlation with an adjacent cell. In yet another embodiment, the cyclic shifts of the patterns is quantized according to a reference signal of a minimum bandwidth

WO 2008/132073

PCT/EP2008/054733

allocation. In another embodiment the pattern defines x cyclic shifts and is reused each $1/x$, where x is a minimum demodulation reference signal length. In another embodiment the second pattern is periodic and defines a length equal to one radio frame. There are separate and simultaneous hopping patterns for base sequence hopping and for cyclic shift hopping, and the network may signal to a UE, by radio link control message or by broadcast message, which of n sequence indices of cyclic shift hopping patterns to use for its UL transmissions. These and other aspects are detailed above with particularity.

[00101] In general, the various embodiments may be implemented in hardware or special purpose circuits, software, logic or any combination thereof. For example, some aspects may be implemented in hardware, while other aspects may be implemented in firmware or software which may be executed by a controller, microprocessor or other computing device, although the invention is not limited thereto. While various aspects of the invention may be illustrated and described as block diagrams, flow charts, or using some other pictorial representation, it is well understood that these blocks, apparatus, systems, techniques or methods described herein may be implemented in, as non-limiting examples, hardware, software, firmware, special purpose circuits or logic, general purpose hardware or controller or other computing devices, or some combination thereof.

[00102] Embodiments of the inventions may be practiced in various components such as integrated circuit modules. The design of integrated circuits is by and large a highly automated process. Complex and powerful software tools are available for converting a logic level design into a semiconductor circuit design ready to be etched and formed on a semiconductor substrate.

[00103] Programs, such as those provided by Synopsys, Inc. of Mountain View, California and Cadence Design, of San Jose, California automatically route conductors and locate components on a semiconductor chip using well established rules of design as well as libraries of pre-stored design modules. Once the design for a semiconductor circuit has been completed, the resultant design, in a standardized electronic format (e.g., Opus, GDSII, or the like) may be transmitted to a semiconductor fabrication facility or "fab" for fabrication.

WO 2008/132073**PCT/EP2008/054733**

[00104] Various modifications and adaptations may become apparent to those skilled in the relevant arts in view of the foregoing description, when read in conjunction with the accompanying drawings. However, any and all modifications of the teachings of this invention will still fall within the scope of the non-limiting embodiments of this invention.

[00105] Furthermore, some of the features of the various non-limiting embodiments of this invention may be used to advantage without the corresponding use of other features. As such, the foregoing description should be considered as merely illustrative of the principles, teachings and exemplary embodiments of this invention, and not in limitation thereof.

What is claimed is:

1. A method comprising:
quantizing a cyclic shift of a reference signal as a combination of a cell specific cyclic shift with an outcome of a pseudo-random hopping; and
broadcasting an indication of the cell specific cyclic shift.
2. The method of claim 1, wherein the cyclic shift is quantized using the cell specific cyclic shift, the outcome of the pseudo-random hopping, and a user specific cyclic shift.
3. The method of claim 2, further comprising signaling an indication of the user specific cyclic shift in an uplink resource allocation.
4. The method of claim 3, wherein the uplink resource allocation comprises an allocation table of an e-UTRAN system.
5. The method of claim 4, executed by a Node B of an e-UTRAN system and where the reference signal comprises a demodulation reference signal.
6. The method of claim 2, wherein quantizing the cyclic shift comprises a modulo operation on a sum of the cell specific cyclic shift, the user specific cyclic shift and the outcome of pseudo-random hopping.
7. The method of any one of claims 1 to 6, wherein the pseudo random hopping is cell specific.
8. The method of any one of claims 1 to 7, wherein the cell specific cyclic shift operates to randomize cyclic shifts between transmission time intervals.
9. The method of claim 1, wherein the cyclic shift is quantized according to length of the reference signal.
10. The method of claim 9, wherein the reference signal is used to generate a cyclically shifted reference signal with cyclic shift according to:

$\text{cyclic\_shift\_symbol} = (\text{cyclic\_shift\_value} * \text{length of the reference signal}) / 12;$

wherein $\text{cyclic\_shift\_value}$ is between zero and eleven and $\text{cyclic\_shift\_symbol}$ is the amount of cyclic shift given in reference signal symbols.

11. An apparatus comprising:
 a processor configured to quantize a cyclic shift of a reference signal as a combination of a cell specific cyclic shift with an outcome of pseudo-random hopping; and
 a transmitter configured to broadcast an indication of the cell specific cyclic shift.
12. The apparatus of claim 11, wherein the processor is configured to quantize the cyclic shift using the cell specific cyclic shift, the outcome of the pseudo-random hopping, and a user specific cyclic shift.
13. The apparatus of claim 12, wherein the transmitter is further configured to signal an indication of the user specific cyclic shift in an uplink resource allocation.
14. The apparatus of claim 13, wherein the uplink resource allocation comprises an allocation table of an e-UTRAN system.
15. The apparatus of claim 14, wherein the apparatus comprises a Node B of an e-UTRAN system and where the reference signal comprises a demodulation reference signal.
16. The apparatus of claim 12, wherein the processor is configured to quantize the cyclic shift by performing a modulo operation on a sum of the cell specific cyclic shift, the user specific cyclic shift and the outcome of pseudo-random hopping.
17. The apparatus of any one of claims 11 to 16, wherein the pseudo random hopping is cell specific.
18. The apparatus of any one of claims 11 to 17, wherein the cell specific cyclic shift operates to randomize cyclic shifts between transmission time intervals.
19. The apparatus of claim 11, wherein the processor is configured to quantize the cyclic shift according to length of the reference signal.

20. The apparatus of claim 19, further comprising a receiver configured to receive a cyclically shifted reference signal, and wherein the processor is configured to generate a cyclically shifted reference signal for demodulating the received reference signal with cyclic shift according to:

$$\text{cyclic\_shift\_symbol} = (\text{cyclic\_shift\_value} * \text{length of the reference signal}) / 12;$$

wherein cyclic_shift_value is between zero and eleven and cyclic_shift_symbol is the amount of cyclic shift given in reference signal symbols.

21. The apparatus of claim 11, wherein the apparatus comprises an integrated circuit.

22. A computer readable memory embodying a program of instructions executable by a processor to perform actions directed toward determining a cyclic shift of a reference signal, the actions comprising:

quantizing a cyclic shift of a reference signal as a combination of a cell specific cyclic shift with an outcome of a pseudo-random hopping; and
broadcasting an indication of the cell specific cyclic shift.

23. The computer readable memory of claim 22, wherein the cyclic shift is quantized using the cell specific cyclic shift, the outcome of the pseudo-random hopping, and a user specific cyclic shift.

24. The computer readable memory of claim 23, the actions further comprising signaling an indication of the user specific cyclic shift in an uplink resource allocation.

25. The computer readable memory of claim 24, wherein the uplink resource allocation comprises an allocation table of an e-UTRAN system and the reference signal comprises a demodulation reference signal.

26. The computer readable memory of claim 23, wherein quantizing the cyclic shift comprises a modulo operation on a sum of the cell specific cyclic shift, the user specific cyclic shift and the outcome of pseudo-random hopping.

27. The computer readable memory of claim 22, wherein the cyclic shift is quantized according to length of the reference signal and generates a cyclically shifted reference signal with cyclic shift according to:

$$\text{cyclic\_shift\_symbol} = (\text{cyclic\_shift\_value} * \text{length of the reference signal}) / 12;$$

wherein cyclic_shift_value is between zero and eleven and cyclic_shift symbol is the amount of cyclic shift given in reference signal symbols.

28. An apparatus comprising:

processing means for quantizing a cyclic shift of a reference signal as a combination of a cell specific cyclic shift with an outcome of pseudo-random hopping; and

communication means for sending an indication of the cell specific cyclic shift over a wireless link.

29. The apparatus of claim 28, wherein the processing means comprises a digital processor and the communication means comprises a transmitter configured to broadcast the cell specific cyclic shift wirelessly.

30. A method comprising:

determining a cell specific cyclic shift from a received indication of the cell specific cyclic shift;

determining a quantized cyclic shift of a reference signal as a combination of the cell specific cyclic shift with an outcome of a pseudo-random hopping; and

sending a reference signal that is cyclically shifted according to the determined quantized cyclic shift.

31. The method of claim 30, wherein the quantized cyclic shift is determined using the cell specific cyclic shift, the outcome of the pseudo-random hopping, and a user specific cyclic shift.

32. The method of claim 31, wherein the indication of the cell specific cyclic shift is received over a broadcast channel, the method further comprising receiving an indication of the user specific cyclic shift in an uplink resource allocation and determining the user specific cyclic shift from the received indication of the user specific cyclic shift.

33. The method of claim 32, wherein the uplink resource allocation comprises an allocation table of an e-UTRAN system, and the reference signal that is cyclically shifted according to the determined quantized cyclic shift is sent in a resource allocated by the uplink resource allocation.
34. The method of claim 33, executed by a user equipment operating in an e-UTRAN system and where the reference signal comprises a demodulation reference signal.
35. The method of claim 31, wherein quantizing the cyclic shift comprises a modulo operation on a sum of the cell specific cyclic shift, the user specific cyclic shift and the outcome of pseudo-random hopping.
36. The method of any one of claims 30 to 35, wherein the pseudo random hopping is cell specific.
37. The method of any one of claims 30 to 36, wherein the cell specific cyclic shift operates to randomize cyclic shifts between transmission time intervals.
38. The method of claim 30, wherein the cyclic shift is quantized according to length of the reference signal.
39. The method of claim 38, wherein the sent reference signal that is cyclically shifted according to the determined quantized cyclic shift has cyclic shift according to:

$$\text{cyclic\_shift\_symbol} = (\text{cyclic\_shift\_value} * \text{length of the reference signal}) / 12;$$
wherein cyclic_shift_value is between zero and eleven and cyclic_shift_symbol is the amount of cyclic shift given in reference signal symbols.
40. A computer readable memory embodying a program of instructions executable by a processor to perform actions directed toward determining a cyclic shift of a reference signal, the actions comprising:
determining a cell specific cyclic shift from a received indication of the cell specific cyclic shift;
determining a quantized cyclic shift of a reference signal as a combination of the cell specific cyclic shift with an outcome of a pseudo-random hopping; and

sending a reference signal that is cyclically shifted according to the determined quantized cyclic shift.

41. The computer readable memory of claim 40, wherein the quantized cyclic shift is determined using the cell specific cyclic shift, the outcome of the pseudo-random hopping, and a user specific cyclic shift.

42. The computer readable memory of claim 41, wherein the indication of the cell specific cyclic shift is received over a broadcast channel, and where the indication of the user specific cyclic shift is received in an uplink resource allocation.

43. The computer readable memory of claim 42, wherein the uplink resource allocation comprises an allocation table of an e-UTRAN system, and the reference signal that is cyclically shifted according to the determined quantized cyclic shift is sent in a resource allocated by the uplink resource allocation.

44. The computer readable memory of claim 41, wherein quantizing the cyclic shift comprises a modulo operation on a sum of the cell specific cyclic shift, the user specific cyclic shift and the outcome of pseudo-random hopping.

45. The computer readable memory of claim 40, wherein the sent reference signal that is cyclically shifted according to the determined quantized cyclic shift has cyclic shift according to:

$\text{cyclic\_shift\_symbol} = (\text{cyclic\_shift\_value} * \text{length of the reference signal}) / 12;$

wherein cyclic_shift value is between zero and eleven and cyclic_shift_symbol is the amount of cyclic shift given in reference signal symbols.

46. An apparatus comprising:

a receiver configured to receive an indication of a cell specific cyclic shift;

a processor configured to determine from the received indication the cell specific cyclic shift, and to determine a quantized cyclic shift of a reference signal as a combination of the cell specific cyclic shift with an outcome of a pseudo-random hopping; and

a transmitter configured to send a reference signal that is cyclically shifted according to the determined quantized cyclic shift.

47. The apparatus of claim 46, wherein the processor is configured to determine the quantized cyclic shift using the cell specific cyclic shift, the outcome of the pseudo-random hopping, and a user specific cyclic shift.

48. The apparatus of claim 47, wherein the receiver is configured to receive the indication of the cell specific cyclic shift over a broadcast channel, the receiver further configured to receive an indication of the user specific cyclic shift in an uplink resource allocation;

and wherein the processor is configured to determine the user specific cyclic shift from the received indication of the user specific cyclic shift.

49. The apparatus of claim 48, wherein the uplink resource allocation comprises an allocation table of an e-UTRAN system, and the transmitter is configured to send the reference signal that is cyclically shifted according to the determined quantized cyclic shift in a resource that is allocated by the uplink resource allocation.

50. The apparatus of claim 49, wherein the apparatus comprises a user equipment operating in an e-UTRAN system and where the reference signal comprises a demodulation reference signal.

51. The apparatus of claim 47, wherein the processor is configured to quantize the cyclic shift by a modulo operation on a sum of the cell specific cyclic shift, the user specific cyclic shift and the outcome of pseudo-random hopping.

52. The apparatus of any one of claims 46 to 51, wherein the pseudo random hopping is cell specific.

53. The apparatus of any one of claims 46 to 52, wherein the cell specific cyclic shift operates to randomize cyclic shifts between transmission time intervals.

54. The apparatus of claim 46, wherein the cyclic shift is quantized according to length of the reference signal.

55. The apparatus of claim 54, wherein the sent reference signal that is cyclically shifted according to the determined quantized cyclic shift has cyclic shift according to:
cyclic_shift symbol= (cyclic_shift_value * length of the reference signal)/12;
wherein cyclic_shift value is between zero and eleven and cyclic_shift symbol is the amount of cyclic shift given in reference signal symbols.
56. The apparatus of any one of claims 46 to 55, wherein the apparatus comprises an integrated circuit.
57. An apparatus comprising:
receiving means for receiving receive an indication of a cell specific cyclic shift;
determining means for determining from the received indication the cell specific cyclic shift, and for determining a quantized cyclic shift of a reference signal as a combination of the cell specific cyclic shift with an outcome of a pseudo-random hopping;
and
sending means for sending a reference signal that is cyclically shifted according to the determined quantized cyclic shift.
58. The apparatus of claim 57, wherein:
the receiving means comprises a receiver;
the determining means comprises at least one digital processor; and
the sending means comprises a transmitter.

1/11

FIG 1A PRIOR ART




FIG 1B PRIOR ART







FIG 1C PRIOR ART



2/11



3/11

FIG 4A




FIG 4B




FIG 5

Resource number	Cyclic shift slot#1	Cyclic shift slot#2
0	0	6
1	1	11
2	2	4
3	3	9
4	4	2
5	5	7
6	6	0
7	7	5
8	8	10
9	9	3
10	10	8
11	11	1




FIG 7

Resource number	Cyclic shift slot# 1	Cyclic shift slot# 2					
		SF=2	SF=3	SF=4	SF=5	SF=6	SF=7
0	0	1	1	2	1	3	5
1	1	0	0	1	3	2	1
2	2	-	2	0	0	1	4
3	3	-	-	3	2	0	0
4	4	-	-	-	4	5	3
5	5	-	-	-	-	4	6
6	6	-	-	-	-	-	2

FIG 8 PRIOR ART




FIG 9

Data Slot #1					Slot #2				
Cyclic shift	Block-level code				Block-level code				
	0	1	2	3	0	1	2	3	
0	0		12		15		3		3rd ACK/NACK resource (implicit)
1		6				11			
2	1		13		14		2		
3		7				10			
4	2		14		13		1		
5		8				9			
6	3		15		12		0		
7		9				8			
8	4		16		17		5		
9		10				7			
10	5		17		16		4		
11		11				6			

Pilot Slot #1				Slot #2			
Cyclic shift	Block-level code			Block-level code			
	0	1	2	0	1	2	
0	0		12		3	15	
1		6		11			
2	1		13		2	14	
3		7		10			
4	2		14		1	13	
5		8		9			
6	3		15		0	12	
7		9		8			
8	4		16		5	17	
9		10		7			
10	5		17		4	16	
11		11		6			

FIG 10

cell-specific permutation	TTL index											
	i	i+1	i+2	i+3	i+4	i+5	i+6	i+7	i+8	i+9	i+10	i+11
1	0	1	3	6	10	3	9	4	0	9	0	1
2	1	4	9	4	1	0	1	4	9	4	1	4
3	2	7	3	2	4	8	4	3	5	10	2	7
4	3	10	9	11	6	4	7	3	2	5	3	10
5	4	1	2	8	8	11	9	1	10	11	4	1
6	5	4	8	6	11	8	1	1	7	6	5	4
7	6	6	1	2	0	2	2	11	2	0	6	6
8	7	9	7	0	3	11	6	11	11	7	7	9
9	8	0	0	9	5	6	8	9	7	1	8	0
10	9	3	6	6	7	2	11	9	4	8	9	3
11	10	6	0	4	10	10	2	8	0	2	10	6
12	11	9	6	2	1	7	6	8	9	9	11	9





FIG 13

Cyclic shift resource	Slot #1						
	LB1	LB2	LB3	LB4	LB5	LB6	LB7
0	0	0	0	0	0	0	0
1	1	3	5	7	9	11	6
2	2	2	2	2	2	2	1
3	3	5	7	9	11	1	7
4	4	4	4	4	4	4	2
5	5	7	9	11	1	3	8
6	6	6	6	6	6	6	3
7	7	9	11	1	3	5	9
8	8	8	8	8	8	8	4
9	9	11	1	3	5	7	10
10	10	10	10	10	10	10	5
11	11	1	3	5	7	9	11

FIG 14

mLB	LB1	LB2	LB3	LB4	LB5	LB6	LB7
	0	2	1	2	3	3	4
0	2	2	1	2	3	3	4

Reference signal LB

Information LB

ACK/NACK

CQI

10/11


FIG 15

		Slot1					
CS resource	Parameter a		mLB0	mLB1	mLB2	mLB3	mLB4
0	0	0	0	0	0	0	0
0	1	1	1	1	1	1	1
1	0	0	6	2	6	10	6
1	1	1	7	3	7	11	7
2	0	0	4	4	4	4	2
2	1	1	5	5	5	5	3
3	0	0	10	6	10	2	8
3	1	1	11	7	11	3	9
4	0	0	2	8	8	8	4
4	1	1	3	9	9	9	5
5	0	0	8	10	2	6	10
5	1	1	9	11	3	7	11

FIG 16

Slot1							
Cell:							
	LB1	LB2	LB3	LB4	LB5	LB6	LB7
0	1	7	8	9	1	9	4
1	8	4	3	10	4	8	11
2	2	9	4	8	7	2	2
3	4	1	6	2	6	11	0
4	7	0	2	11	3	5	9
5	3	11	10	1	9	4	7
6	6	3	1	5	8	0	10
7	10	5	7	7	5	7	3
8	5	8	5	6	0	6	8
9	9	10	9	4	10	1	6
10	0	6	0	0	2	10	1
11	11	2	11	3	11	3	5

FIG 17



1702: e-NodeB broadcast an indication of the cell specific cyclic shift

1708: UE determine the cell-specific cyclic shift from the broadcast indication

1704: e-NodeB sends in a uplink resource allocation an indication of a user-specific cyclic shift

1710: UE determine the user-specific cyclic shift from the indication in the resource allocation

1706: quantize the reference signal cyclic shifts as a combination of the cell specific cyclic shift (block 1702/1708) and an outcome of a pseudo-random hopping

[modulo operation on a sum of the cell specific cyclic shift (block 1702), the outcome of the pseudo-random hopping, and the user specific cyclic shift (block 1704/1710)]

1712: UE sends to the e-NodeB, in the allocated uplink resource, the reference signal which is cyclically shifted according to the quantization