

(12) DEMANDE DE BREVET CANADIEN
CANADIAN PATENT APPLICATION

(13) A1


(86) Date de dépôt PCT/PCT Filing Date: 2005/08/11
 (87) Date publication PCT/PCT Publication Date: 2006/02/23
 (85) Entrée phase nationale/National Entry: 2007/02/08
 (86) N° demande PCT/PCT Application No.: US 2005/028487
 (87) N° publication PCT/PCT Publication No.: 2006/020741
 (30) Priorité/Priority: 2004/08/12 (US60/601,338)

(51) Cl.Int./Int.Cl. H04B 7/04 (2006.01),
 H04B 7/208 (2006.01), H04J 11/00 (2006.01),
 H04L 27/26 (2006.01)

(71) Demandeur/Applicant:
 INTERDIGITAL TECHNOLOGY CORPORATION, US

(72) Inventeurs/Inventors:
 KWAK, JAEYOUNG, US;
 OLESEN, ROBERT LIND, US;
 BULTAN, AYKUT, US;
 ZEIRA, ELDAD, US;
 KOO, CHANG-SOO, US;
 OZLUTURK, FATIH, US;
 HUANG, YUEJIN, US;
 PASAD, KALPENDU R., US

(54) Titre : PROCEDE ET APPAREIL DE MISE EN OEUVRE DE CODAGE DE BLOCS A FREQUENCES SPATIALES
 DANS UN SYSTEME DE COMMUNICATION SANS FIL DE MULTIPLEXAGE PAR REPARTITION EN
 FREQUENCES ORTHOGONALES
 (54) Title: METHOD AND APPARATUS FOR IMPLEMENTING SPACE FREQUENCY BLOCK CODING



(57) Abrégé/Abstract:

The present invention is related to a method and apparatus for implementing space frequency block coding (SFBC) in an orthogonal frequency division multiplexing (OFDM) wireless communication system. The present invention is applicable to both a closed loop mode and an open loop mode. In the closed loop mode, power loading and eigen-beamforming are performed based on channel state information (CSI). A channel coded data stream is multiplexed into two or more data streams. Power loading is performed based on the CSI on each of the multiplexed data streams. SFBC encoding is performed on the data streams for each of the paired subcarriers. Then, eigen-beamforming is performed based on the CSI to distribute eigenbeams to multiple transmit antennas. The power loading may be performed on two or more SFBC encoding blocks or on each eigenmodes. Additionally, the power loading may be performed across subcarriers or subcarrier groups for weak eigenmodes.

(74) Agent: RIDOUT & MAYBEE LLP

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property Organization
International Bureau(43) International Publication Date
23 February 2006 (23.02.2006)

PCT

(10) International Publication Number
WO 2006/020741 A3

(51) International Patent Classification:

H04L 27/08 (2006.01)

(21) International Application Number:

PCT/US2005/028487

(22) International Filing Date: 11 August 2005 (11.08.2005)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:

60/601,338 12 August 2004 (12.08.2004) US

(71) Applicant (for all designated States except US): **INTER-DIGITAL TECHNOLOGY CORPORATION** [US/US]; 300 Delaware Avenue, Suite 527, Wilmington, DE 19801 (US).

(72) Inventors; and

(75) Inventors/Applicants (for US only): **KWAK, Jaeyoung** [KR/US]; 181 Nantucket Place, Morganville, NJ 07751 (US). **OLESEN, Robert, Lind** [US/US]; 3 Country Club Drive, Huntington, NY 11743 (US). **BULTAN, Aykut** [TR/US]; 16-70 Bell Blvd., Apt. 515, Bayside, NY 11360 (US). **ZEIRA, Eldad** [US/US]; 106 East Neck Road, Huntington, NY 11743 (US). **KOO, Chang-Soo** [US/US]; 281 Altesse Blvd., Melville, NY 11747 (US). **OZLUTURK, Fatih** [US/US]; 70 Willowdale Avenue, Port

Washington, NY 11050 (US). **HUANG, Yuejin** [CN/US]; 865 Broadway Avenue, Apt. 236A, Holbrook, NY 11741 (US). **PASAD, Kalpendu, R.** [IN/US]; 5 Chatham Court, Hicksville, NY 11801 (US).


(74) Agent: **BALLARINI, Robert, J.; VOLPE AND KOENIG, P.C.**, United Plaza, Suite 1600, 30 S. 17th Street, Philadelphia, PA 19103 (US).

(81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BW, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KM, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NA, NG, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SM, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.

(84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LT, LU, LV, MC, NL, PL, PT, RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

[Continued on next page]

(54) Title: METHOD AND APPARATUS FOR IMPLEMENTING SPACE FREQUENCY BLOCK CODING



(57) Abstract: The present invention is related to a method and apparatus for implementing space frequency block coding (SFBC) in an orthogonal frequency division multiplexing (OFDM) wireless communication system. The present invention is applicable to both a closed loop mode and an open loop mode. In the closed loop mode, power loading and eigen-beamforming are performed based on channel state information (CSI). A channel coded data stream is multiplexed into two or more data streams. Power loading is performed based on the CSI on each of the multiplexed data streams. SFBC encoding is performed on the data streams for each of the paired subcarriers. Then, eigen-beamforming is performed based on the CSI to distribute eigenbeams to multiple transmit antennas. The power loading may be performed on two or more SFBC encoding blocks or on each eigenmodes. Additionally, the power loading may be performed across subcarriers or subcarrier groups for weak eigenmodes.

WO 2006/020741 A3

WO 2006/020741 A3



Published:

— with international search report

(88) Date of publication of the international search report:

1 June 2006

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

[0001] METHOD AND APPARATUS FOR IMPLEMENTING
 SPACE FREQUENCY BLOCK CODING IN
 AN ORTHOGONAL FREQUENCY DIVISION
 MULTIPLEXING WIRELESS COMMUNICATION SYSTEM

[0002] FIELD OF INVENTION

[0003] The present invention is related to wireless communication systems. More particularly, the present invention is related to a method and apparatus for implementing space frequency block coding (SFBC) in an orthogonal frequency division multiplexing (OFDM) wireless communication system.

[0004] BACKGROUND

[0005] OFDM is a data transmission scheme where data is split into a plurality of smaller streams and each stream is transmitted using a sub-carrier with a smaller bandwidth than the total available transmission bandwidth. The efficiency of OFDM depends on choosing these sub-carriers orthogonal to each other. The sub-carriers do not interfere with each other while each carrying a portion of the total user data.

[0006] OFDM system has advantages over other wireless communication systems. When the user data is split into streams carried by different sub-carriers, the effective data rate on each subcarrier is much smaller. Therefore, the symbol duration is much larger. A large symbol duration can tolerate larger delay spreads. In other words, it is not affected by multipath as severely. Therefore, OFDM symbols can tolerate delay spreads without complicated receiver designs. However, typical wireless systems need complex channel equalization schemes to combat multipath fading.

[0007] Another advantage of OFDM is that the generation of orthogonal sub-carriers at the transmitter and receiver can be done by using inverse fast Fourier transform (IFFT) and fast Fourier transform (FFT) engines. Since the IFFT and FFT implementations are well known, OFDM can be implemented easily and does not require complicated receivers.

[0008] Multiple-input multiple-output (MIMO) refers to the type of wireless transmission and reception scheme where both a transmitter and a receiver employ more than one antenna. A MIMO system takes advantage of the spatial diversity or spatial multiplexing and improves signal-to-noise ratio (SNR) and increases throughput.

[0009] SFBC is a scheme for transmitting symbols of a space diversity coding on neighboring subcarriers rather than on the same subcarrier in the successive time slots. The SFBC avoids the problem of fast time variations in space time block coding. However, the channel needs to be constant over the subcarriers that combining takes place.

[0010]

SUMMARY

[0011] The present invention is related to a method and apparatus for implementing space frequency block coding (SFBC) in an orthogonal frequency division multiplexing (OFDM) wireless communication system. The present invention is applicable to both a closed loop mode and an open loop mode. In the closed loop mode, power loading and eigen-beamforming are performed based on channel state information (CSI). A channel coded data stream is multiplexed into two or more data streams. Power loading is performed based on the CSI on each of the multiplexed data streams. SFBC encoding is performed on the data streams for each of the paired subcarriers. Then, eigen-beamforming is performed based on the CSI to calculate eigenbeams over multiple transmit antennas. The power loading may be performed on two or more SFBC encoding blocks or on each eigenmodes. Additionally, the power loading may be performed across subcarriers or subcarrier groups for weak eigenmodes.

[0012] In accordance with the present invention, a robust channel estimation can be provided in all channel conditions, with or without channel information feedback, and low complexity is achieved at both transmitter and receiver. In addition, scalable solution can be used with any antenna configuration and backward compatibility is provided with enhanced

performance with 802.11a/g.

[0013] BRIEF DESCRIPTION OF THE DRAWINGS

[0014] Figure 1 is a block diagram of an OFDM-MIMO system implementing a closed loop mode.

[0015] Figure 2 is a block diagram of a system implementing open loop.

[0016] Figure 3 is a block diagram of a transmitter for depicting power loading.

[0017] Figure 4 is a diagram of an exemplary power loading and adaptive modulation and coding mapping between two pairs of modes.

[0018] Figure 5 shows an example of pairing of subcarrier groups for power/bit loading.

[0019] DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0020] Hereafter, the terminology "station" (STA) includes but is not limited to a user equipment, a wireless transmit/receive unit, a fixed or mobile subscriber unit, a pager, or any other type of device capable of operating in a wireless environment. When referred to hereafter, the terminology "access point" (AP) includes but is not limited to a Node-B, a base station, a site controller or any other type of interfacing device in a wireless environment.

[0021] The present invention will be described with reference to the drawing figures wherein like numerals represent like elements throughout. It should be noted that figures provided in the present invention are high level functional block diagrams and the functions implemented by the functional blocks may be implemented by more or less blocks. The features of the present invention may be incorporated into an integrated circuit (IC) or be configured in a circuit comprising a multitude of interconnecting components.

[0022] Embodiments of the present invention provide a transmitter implementing SFBC MIMO coding and receiver matched filter. Embodiments also provide transmitter channel precoding and receiver antenna processing as well as channel decomposition functions.

[0023] There are two modes of operation of the system: a closed loop and an open loop. The closed loop is used when channel state information (CSI) is available to the transmitter. The open loop is used when CSI is not available. A variant may be used for transmission to legacy STA where it provides diversity benefits.

[0024] In the closed loop mode, CSI is used to create virtual independent channels by decomposing and diagonalizing the channel matrix and by precoding at the transmitter. Given the eigenvalue spread of TGn channels the present invention employs a space-frequency orthogonal MIMO coding in the transmitter at the input to the channel precoder to increase robustness at the cost of decreasing data rate. Any coding scheme in MIMO has to deal with the diversity versus multiplexing gain trade off. It is desirable to have a trade off scheme that is best suited to particular channel statistics. An SFBC is chosen due to low mobility and the long coherence time of the channel. This scheme allows for receiver implementation simpler than a MMSE receiver. The combined solution enables higher throughput over a larger range. Embodiments of the present invention allow for per subcarrier power/bit loading and maintains a sustained robust link through closed loop operation with channel state feedback. Another potential benefit is that it is easily scalable to any number of antennas at both transmitter and receiver.

[0025] The CSI can be obtained at the transmitter either by feedback from the receiver or through exploiting channel reciprocity. Channel reciprocity is useful for mainly TDD based systems. In this case it is possible for the transmitter and receiver to independently estimate and decompose the channel. The channel update rate can be lowered when the SNR is high resulting in a reduced feedback bandwidth load. Latency requirements and feedback data rates are typically not significant to the inherent frequency non-selectivity of eigenvalues.

[0026] The closed loop mode requires calibrations of the transmitter to compensate amplitude and phase difference of the estimated channels in the uplink and downlink directions. This is done infrequently, for example during

STA association or under application control, and can use channel reciprocity for the estimation of the channel at both ends. In addition, a CQI (or SNR) per eigen-beam is fed back to the transmitter to support adaptive rate control.

[0027] Figure 1 is a block diagram of an OFDM-MIMO system 100 implementing a closed loop mode. The system 100 comprises a transmitter 110 and a receiver 130. The transmitter 110 comprises a channel encoder 112, a multiplexer 114, a power loading unit 116, a plurality of SFBC encoding units 118, a plurality of serial-to-parallel (S/P) converters 120, a plurality of eigen-beamformers 122, a plurality of IFFT units 124 and a plurality of transmit antennas (not shown). The channel encoder 112 encodes data preferably in accordance with a channel quality indicator (CQI) which is sent from the receiver 130. The CQI is used to determine a coding rate and modulation scheme per sub-carrier or group of sub-carriers. The coded data stream is multiplexed by the multiplexer 114 into two or more data streams.

[0028] The transmit power level of each data stream is adjusted by the power loading unit 116 based on feedback. The power loading unit 116 adjusts power levels with respect to the data rate of each eigenbeam to balance the total transmit power over all eigenbeams (or sub-carriers), which will be explained in detail below.

[0029] The SFBC encoding units 118 perform SFBC encoding on the data streams. SFBC encoding is done over eigen-beams and sub-carriers for each data rate that is transmitted. Eigen-beam and sub-carrier pairs are selected to ensure independent channels. OFDM symbols are carried on K sub-carriers. To accommodate SFBC, the sub-carriers are divided into L pairs of sub-carriers (or group of sub-carriers). The bandwidth of each group of sub-carriers should be less than the coherence bandwidth of the channel. However, when combined with eigen-beamforming this restriction is relaxed due to the frequency insensitivity of the eigen-beams.

[0030] The pairs of sub-carrier groups used by the block code are considered independent. The following is an example of the Alamouti type SFBC applied to an OFDM symbol:

$$\mathbf{S} = \begin{bmatrix} s_1 & -s_2^* \\ s_2 & s_1^* \end{bmatrix}.$$

[0031] Once the SFBC encoding units 118 construct OFDM symbols for all sub-carriers, the coded blocks are multiplexed by the S/P converters 120 and input to the eigen-beamformers 122. The eigen-beamformers 122 distribute the eigenbeams to the transmit antennas. The IFFT units 124 convert the data in frequency domain to the data in time domain.

[0032] The receiver 130 comprises a plurality of receive antennas (not shown), a plurality of FFT units 132, eigen-beamformers 134, SFBC decoding units 136, a combiner 138, a channel decoder 144, a channel estimator 140, a CSI generator 142 and a CQI generator 146.

[0033] The FFT units 132 convert the received samples to frequency domain and the eigen-beamformer 134, the SFBC decoding unit 136 and a channel decoder 144 perform the opposite operation which is performed at the transmitter 110. The combiner 138 combines the SFBC decoding results using maximal ratio combining (MRC).

[0034] The channel estimator 140 generates channel matrix using a training sequence transmitted from the transmitter and decomposes the channel matrix into two beam-forming unitary matrices U and V , (U for transmit and V for receive), and a diagonal matrix D per sub-carrier (or per sub-carrier group) by singular value decomposition (SVD) or eigenvalue decomposition. The CSI generator 142 generates CSI from the channel estimation results and the CQI generator generates a CQI based on the decoding results. The CSI and the CQI are sent back to the transmitter 110.

[0035] The channel matrix H between n_T transmit antennas and n_R receive antennas can be written as follows:

$$H = \begin{bmatrix} h_{11} & h_{21} & \cdots & h_{1,n_T} \\ h_{21} & h_{22} & \cdots & h_{2,n_T} \\ \vdots & \vdots & \ddots & \vdots \\ h_{n_R,1} & h_{n_R,2} & \cdots & h_{n_R,n_T} \end{bmatrix}$$

[0036] The channel matrix H is decomposed by SVD as follows:

$$H = UDV^H,$$

where U and V are unitary matrices and D is a diagonal matrix. $U \in \mathbb{C}^{n_R \times n_R}$ and $V \in \mathbb{C}^{n_T \times n_T}$. Then, for transmit symbol vector s , transmit precoding is simply performed as follows:

$$x = Vs \text{ (transmitted signal).}$$

[0037] The received signal becomes as follows:

$$y = HVs + n,$$

where n is the noise introduced in the channel. The receiver completes the decomposition by using a matched filter:

$$V^H H^H = V^H V D^H U^H = D^H U^H.$$

[0038] After normalizing channel gain for eigenbeams, the estimate of the transmit symbols s becomes

$$\begin{aligned} \hat{s} &= \alpha D^H U^H H V s + \eta \\ &= s + \eta \end{aligned}$$

[0039] s is detected without having to perform successive interference cancellation or MMSE type detector. $D^H D$ is a diagonal matrix that is formed by eigenvalues of H across the diagonal. Therefore, the normalization factor $\alpha = D^{-2}$. U are eigenvectors of HH^H , V are eigenvectors of $H^H H$ and D is a diagonal matrix of singular values of H (square roots of eigenvalues of HH^H).

[0040] Figure 2 is a block diagram of a system 200 implementing open loop mode in accordance with the present invention. The system 200 comprises a transmitter 210 and a receiver 230. In the open loop mode, a combination of space-frequency coding and spatial spreading in the

transmitter 210 provides diversity without requiring CSI. A variant of this scheme can be used when operating with legacy 802.11a/g STAs.

[0041] The transmitter 210 comprises a channel encoder 212, a multiplexer 214, a power loading unit 216, a plurality of SFBC encoding units 218, a plurality of serial-to-parallel (S/P) converters 220, a beamformer network (BFN) 222, a plurality of IFFT units 224 and a plurality of transmit antennas 226. As in the closed loop mode, the channel encoder 212 uses CQI to determine coding rate and modulation per sub-carrier or group of sub-carriers. The coded data stream is multiplexed by the multiplexer 214 into two or more data streams.

[0042] In the open loop, the eigen-beamformer is replaced with the Beam Forming Network (BFN) 222. The BFN 22 forms N beams in space, where N is the number of antennas 226. The beams are pseudo-randomly constructed by the BFN matrix operation. The independent sub-carrier groups used for the SFBC coding are transmitted on individual beams.

[0043] For legacy support, SFBC coding may not be performed. Instead diversity through beam permutation is performed which improves diversity and therefore the performance of legacy 802.11a/g equipment.

[0044] The receiver 230 comprises receive antennas 231, FFT units 232, a BFN 234, an SFBC decoding and combining unit 236 and a channel decoder 238. The FFT units 232 convert the received signal in time domain to the signal in frequency domain. The SFBC decoding and combining unit 236 decodes and combines symbols received from sub-carrier groups/eigen-beams and converts them from parallel to serial using a prior knowledge of the constellation size. Symbols are combined using MRC. The channel decoder 238 decodes the combined symbol and generates a CQI.

[0045] A first embodiment of power loading is explained hereinafter. The spatial processing is a combination of space-frequency coding and eigen-beamforming. This is performed to give the best compromise between the redundancy gains that SFBC affords and the spatial multiplexing that the eigen-beamformer provides. The power loading scheme operates across the

eigen-modes of the channel matrix. However, SFBC also introduces the constraint that the outputs of the coder have the same power loading no matter what the input power loading is due to the cross-operation inside the coder.

[0046] Figure 3 is a block diagram of a transmitter 110 for depicting power loading. Figure 3 illustrates 4x4 case as an example and the first embodiment of the power loading scheme will be explained with reference to 4x4 case. However, it should be noted that the 4x4 case can be extended to any other cases.

[0047] For a particular subcarrier k , four streams of data are mapped to 2 pairs of power loading/AMC modes. In other words the modulation order is selected the same for each pair of inputs. This is later mapped to pairs of eigenmodes. Output of the power loading unit 116 is applied to the dual 2x2 SFBC encoding units 118 and then passed on to the eigen-beamformer 122. The eigen-beamformer 122 maps the inputs to the eigen-modes of the channel through the preprocessing.

[0048] For all K subcarriers, the eigenvalues of the channel matrix are known at the transmitter. The channel energy for each eigenmode is defined as follows:

$$\alpha_i = \sum_{k=1}^K |\lambda_{i,k}|^2,$$

where $\lambda_{i,k}$ is the i -th eigenvalue for the k -th subcarrier's channel. Two SNIRs are defined for two coupled eigenmodes as follows:

$$\beta_{\text{mod1}} = \sum_{i=1}^{M/2} |\alpha_i|^2 \text{ and } \beta_{\text{mod2}} = \sum_{i=M/2+1}^M |\alpha_i|^2$$

where M is the number of eigenmodes. In other words, the eigenmodes are grouped such that half of the eigenmodes with the largest channel energy (or SNIR) are in one group and the other half with the weakest channel energies are in the other. Therefore, the harmonic SNIRs represent the total channel energy of the stronger and weaker eigenmodes. Channel energy is an indication of how robust the eigenmodes and hence the signal that is carried

over these eigenmodes would be. This information is used to apply different adaptive modulation and coding (AMC) and/or different power loading for each half as is explained in more detail subsequently. The separation of the coupled SNIRs are defined as follows:

$$\Delta_{\beta} = \beta_{\text{mod1}} - \beta_{\text{mod2}}$$

[0049] During the closed loop operation the transmitter 110 has the knowledge of current CSI from which it extracts the eigenvalues and preprocessing matrix. The transmitter 110 also infers the data rate that can be supported in the link, R_b , from the CSI. Then, power loading for a given, acceptable, CQI is an optimization between the number of bits that can be sent per OFDM symbol and the type of modulation that is to be used for each mode.

[0050] Using the channel energy calculated for eigenmode i as explained above, the maximum bit rate that can be supported for the channel condition is determined. Then, using the mode separation calculation above it is determined how the bit rate needs to be distributed between the two pairs of modes. Figure 4 is a diagram of an exemplary power loading and adaptive modulation and coding mapping between two pairs of modes. In this example, the bit rate that can be supported is 24 bits per OFDM symbol for the particular sub-carrier. The lowest modulation order satisfying the bit rate is found in Figure 4 as indicated by the dashed arrow. In this example, first and second modes (first pair of coupled modes) will be using 16 QAM and third and fourth modes (second pair of coupled modes) will be using 256 QAM.

[0051] Note that this mapping is described for one CQI that is acceptable and for one subcarrier. In the case of alternative MIMO configurations, such as 2x4, 2x2, etc, the same power loading scheme is applicable except that the total number of bits in the table entries are scaled down to represent the transmit capability and that power loading can be done on a single pair of modes.

[0052] A power loading scheme in accordance with a second embodiment is explained hereinafter. The eigenvalues per subcarrier ($\lambda_1(k) > \lambda_2(k) > \dots >$

$\lambda_{nT}(k)$) are ranked and eigenbeams (E^1, E^2, \dots, E^{nT}) are created by grouping the same ranked eigenvalues for all subcarriers as follows:

$$E^i = \{\lambda_i(1), \lambda_i(2), \dots, \lambda_i(K)\} \text{ for } i = 1, 2, \dots, nT,$$

where K is the number of subcarriers, nT is the number of transmit antennas and $\lambda_i(j)$ is the i -th eigenvalue of the j -th subcarrier. nT is an even number.

[0053] The average of the eigenvalues per eigenbeam are computed as follows:

$$\lambda_{av}^i = \frac{1}{K} \sum_{j=1}^K \lambda_i(j) \quad \text{for } i = 1, 2, \dots, nT.$$

[0054] The eigenbeams are paired to create Alamouti space-frequency blocks, such as $\{E^1, E^2\}_1, \{E^3, E^4\}_2, \dots, \{E^{2i-1}, E^{2i}\}_i \dots \{E^{nT-1}, E^{nT}\}_{nT/2}$. However, if the SNR of a pair is greater than SNR_{max} , then the second eigenbeam of the pair is replaced with the eigenbeam with the next lower eigenvalue average until its SNR is less than or equal to SNR_{min} .

$$SNR(i) = (\lambda_{av}^i + \lambda_{av}^{i+1}) / \sigma_n^2,$$

where σ_n^2 is the noise variance and SNR_{min} is the minimum required SNR for the highest data rate for a required quality of service. This step is repeated until all the eigenbeams are paired. Figure 5 shows an example of pairing of subcarrier groups for power/bit loading.

[0055] A data rate for each pair of eigenbeams are determined by mapping the SNR of a pair to the data rate for a given quality. The required SNRs may be adjusted for all pairs of eigenbeams to compensate for the measurement errors and make the total transmit power be constant.

[0056] A weight vector per pair of eigenbeams per subcarrier may be computed as follows:

$$w_k(i, j) = \sqrt{\frac{SNR(i)\sigma_n^2}{2\lambda_i(j)}},$$

where i is the i -th pair of eigenbeams, j is the j -th subcarrier.

[0057] In accordance with the third embodiment, in addition to the first or second embodiment, another power loading is applied across the sub-

carriers or group of sub-carriers for weak eigen-modes. In other word, instead of power loading being applied to all eigenmodes it can be applied only to those that are weaker and hence can benefit from the power loading the most. In such a case, those eigenmodes that are not power loaded can still have SFBC or other coding or can have different AMC settings individually, whereas those eigenmodes that power loaded share the same AMC setting for instance. Also, the eigenmodes of the channel are always ordered in power, from strongest to weakest. By pairing eigenmodes of similar power one may improve the power loading of the channel.

[0058] A spatial processing scheme is configurable to any number of receive and transmit antenna combinations. Depending on the number of antennas on each side, a combination of SFBC and eigen-beamforming options are used. The table below summarizes the various configurations supported and the state of the spatial processing and power loading that is applicable to each scenario.

| Antenna Configuration (Tx X Rx) | Space Frequency Block Code | Eigen-Beamforming |
|------------------------------------|-------------------------------|-------------------------------------|
| $M \times N$ ($M, N \neq 1$) | $M/2$ block codes | M beams at Tx N beams at Rcv |
| $1 \times N$ ($N \neq 1$) | not used | To be determined by receiver vendor |
| $M \times 1$ ($M \neq 1$) | $M/2$ block codes | M beams at Tx |

Table 1

[0059] Although the features and elements of the present invention are described in the preferred embodiments in particular combinations, each feature or element can be used alone without the other features and elements of the preferred embodiments or in various combinations with or without other features and elements of the present invention.

* * *

PCT/US05/23487 05052006 05 MAY 2006

PC 17052006/23487 05052006

What is claimed is:

1. A method for implementing space frequency block coding (SFBC) in an orthogonal frequency division multiplexing (OFDM) wireless communication system, the method comprising:

performing a channel coding on input data stream;

multiplexing the coded data stream to two or more data streams;

obtaining channel state information (CSI);

calculating channel energy for each of a plurality of eigenmodes for all subcarriers;

calculating harmonic signal-to-noise ratios (SNRs) for the eigenmodes based on the calculated channel energy;

calculating separation of the harmonic SNRs;

determining a data rate that can be supported based on the CSI;

determining bit rates distributed between the eigenmodes;

pairing subcarriers for SFBC encoding;

performing SFBC encoding on the data streams;

performing eigen-beamforming based on the CSI to distribute eigenbeams to a plurality of transmit antennas; and

performing inverse Fourier transform for converting the data stream to data in time domain for transmission.

2. The method of claim 1 wherein the subcarriers are divided into a plurality of groups of subcarriers.

3. The method of claim 2 wherein bandwidth of the group of subcarriers is less than coherence bandwidth of a channel.

4. (cancelled)

PCT/US04/284637, DISCLOSURES

5. The method of claim 1 further comprising the step of applying power optimization across each subcarrier or subcarrier group for weak eigenmodes.

6. A method for implementing space frequency block coding (SFBC) in an orthogonal frequency division multiplexing (OFDM) wireless communication system, the method comprising:

performing a channel coding on input data stream;

multiplexing the coded data stream to two or more data streams;

obtaining channel state information (CSI);

ranking eigenvalues per subcarrier;

generating eigenbeams by grouping the same ranked eigenvalues for all subcarriers;

calculating average of the eigenvalues per eigenbeam;

generating space-frequency blocks by pairing the eigenbeams;

determining a data rate for each pair of eigenbeams by mapping required signal-to-noise ratios (SNRs) of the pair of eigenbeams to data rates;

pairing subcarriers for SFBC encoding;

performing SFBC encoding on the data streams;

performing eigen-beamforming based on the CSI to distribute eigenbeams to a plurality of transmit antennas; and

performing inverse Fourier transform for converting the data stream to data in time domain for transmission.

7. The method of claim 6 further comprising a step of adjusting the required SNRs for all pairs of eigenbeams to compensate for measurement errors and make a total transmit power be constant.

8. The method of claim 6 further comprising a step of applying a weight vector per pair of eigenbeams.

PCT/US02/28437, 02/05/2006
PCT/US02/28437, 02/05/2006
05 MAY 2006

9. The method of claim 1 wherein the CSI is generated by and sent back from a receiver.

10. The method of claim 1 wherein the CSI is generated by a transmitter through channel reciprocity.

11. A method for implementing space frequency block coding (SFBC) in an orthogonal frequency division multiplexing (OFDM) wireless communication system, the method comprising:

- performing a channel coding on input data stream;
- multiplexing the coded data stream to two or more data streams;
- pairing subcarriers for SFBC encoding;
- performing SFBC encoding on the data streams;
- generating a plurality of beams by a beamforming network without channel state information and permuting the generated beams; and
- performing inverse Fourier transform for converting the data stream to data in time domain for transmission.

12. An apparatus for implementing space frequency block coding (SFBC) in an orthogonal frequency division multiplexing (OFDM) wireless communication system, the apparatus comprising:

- a channel coder configured to perform a channel coding on input data stream;
- a multiplexer configured to multiplex the coded data stream to two or more data streams;
- a power loading unit configured to calculate channel energy for each of a plurality of eigenmodes for all subcarriers, calculate harmonic signal-to-noise ratios (SNRs) for the eigenmodes from the channel energy, calculate separation of the harmonic SNRs, and determine data rates for the eigenmodes based on channel state information (CSI);

PEAVUS 05 MAY 2006

PC: T2110505, PROJ: 7, 05052016

a plurality of SFBC encoding units configured to perform SFBC encoding on the data streams for each pair of subcarriers;

a plurality of eigen-beamformers configured to perform eigen-beamforming based on the CSI to distribute eigenbeams to a plurality of transmit antennas;

a plurality of inverse Fourier transform units configured to perform inverse Fourier transform for converting the data stream to data in time domain for transmission; and

a plurality of antennas.

13. The apparatus of claim 12 wherein the subcarriers are divided into a plurality of groups of subcarriers.

14. The apparatus of claim 13 wherein bandwidth of the group of subcarriers is less than coherence bandwidth of a channel.

15. (cancelled)

16. The apparatus of claim 12 wherein the power loading unit is configured to apply power optimization across each subcarrier or subcarrier group for weak eigenmodes.

17. An apparatus for implementing space frequency block coding (SFBC) in an orthogonal frequency division multiplexing (OFDM) wireless communication system, the apparatus comprising:

a channel coder configured to perform a channel coding on input data stream; a multiplexer configured to multiplex the coded data stream to two or more data streams;

a power loading unit configured to rank eigenvalues per subcarrier, generate eigenbeams by grouping the same ranked eigenvalues for all subcarriers, calculate

PCT/US05/224487 05052006

an average of the eigenvalues per eigenbeam and determine a data rate for each pair of eigenbeams;

a plurality of SFBC encoding units configured to perform SFBC encoding on the data streams for each pair of subcarriers;

a plurality of eigen-beamformers configured to perform eigen-beamforming based on the CSI to distribute eigenbeams to a plurality of transmit antennas;

a plurality of inverse Fourier transform units configured to perform inverse Fourier transform for converting the data stream to data in time domain for transmission; and

a plurality of antennas.

18. The apparatus of claim 17 wherein the power loading unit is configured to adjust the required SNRs for all pairs of eigenbeams to compensate for measurement errors and make a total transmit power be constant.

19. The apparatus of claim 17 wherein the power loading unit is configured to apply a weight vector per pair of eigenbeams.

20. The apparatus of claim 12 wherein the CSI is generated by and sent back from a receiver.

21. The apparatus of claim 12 wherein the CSI is generated by a transmitter through channel reciprocity.

22. An apparatus for implementing space frequency block coding (SFBC) in an orthogonal frequency division multiplexing (OFDM) wireless communication system, the apparatus comprising:

a channel coder configured to perform a channel coding on input data stream;

a multiplexer configured to multiplex the coded data stream to two or more data streams;

FIGURE 1605/20467.05052006


a power loading unit configured to perform power loading based on channel state information (CSI) on each of the multiplexed data streams;


a plurality of SFBC encoding units configured to perform SFBC encoding on the data streams for each pair of subcarriers;

a beamforming network configured to generate a plurality of beams without channel state information and permuting the generated beams;

a plurality of inverse Fourier transform units configured to perform inverse Fourier transform for converting the data stream to data in time domain for transmission; and

a plurality of antennas.



**FIG. 2**

3/4






FIG. 3

4/4

**FIG. 4****FIG. 5**

