



US00RE42558E

(19) **United States**
(12) **Reissued Patent**
Chung et al.

(10) **Patent Number:** **US RE42,558 E**
(45) **Date of Reissued Patent:** **Jul. 19, 2011**

(54) **JOINT ADAPTIVE OPTIMIZATION OF SOFT DECISION DEVICE AND FEEDBACK EQUALIZER**

(75) Inventors: **Wonzoo Chung**, Kent, WA (US);
Thomas J. Endres, Seattle, WA (US);
Christopher D. Long, Maple Valley, WA (US)

(73) Assignee: **Omereen Wireless, LLC**, Dover, DE (US)

(21) Appl. No.: **12/390,368**

(22) Filed: **Feb. 20, 2009**
(Under 37 CFR 1.47)

Related U.S. Patent Documents

Reissue of:

(64) Patent No.: **7,180,942**
Issued: **Feb. 20, 2007**
Appl. No.: **10/327,280**
Filed: **Dec. 20, 2002**

U.S. Applications:

(63) Continuation-in-part of application No. 10/322,299, filed on Dec. 17, 2002, now abandoned.
(60) Provisional application No. 60/341,931, filed on Dec. 18, 2001.

(51) **Int. Cl.**
H03H 7/30 (2006.01)
H03H 7/40 (2006.01)
H03K 5/159 (2006.01)

(52) **U.S. Cl.** **375/233**
(58) **Field of Classification Search** **375/233,**
375/350, 229, 232

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

2,138,330	A	11/1938	Thompson
2,977,551	A	3/1961	Gibson et al.
3,386,033	A	5/1968	Copeland et al.
3,703,685	A	11/1972	Simopoulos et al.
3,714,659	A	1/1973	Firman
3,774,218	A	11/1973	Fowler
3,838,444	A	9/1974	Loughlin et al.
3,873,771	A	3/1975	Kleinerman et al.
3,924,060	A	12/1975	Bedford
3,974,449	A	8/1976	Falconer
3,984,624	A	10/1976	Waggner
3,999,005	A	12/1976	Dickinson
4,081,497	A	3/1978	Tokumitsu et al.

(Continued)

FOREIGN PATENT DOCUMENTS

EP 0308241 3/1989
(Continued)

OTHER PUBLICATIONS

Lucky, R.W.: "Techniques for adaptive equalization of digital communication systems" *Bell Systems Technical Journal*, vol. 45, No. 2, pp. 255-286, Feb. 1966.


(Continued)

Primary Examiner — Kevin Y Kim
(74) *Attorney, Agent, or Firm* — Perkins Coie LLP

(57) **ABSTRACT**

The present invention uses a novel adaptive soft decision device in order to jointly optimize decision device and DFE operation. The soft decision device receives the input and output samples of the slicer and generates a feedback sample by non-linearly combining them with respect to a single decision reference parameter. Moreover, the soft decision device provides novel error terms used to adapt equalizer coefficients in order to jointly optimize decision device and equalizer coefficients.

9 Claims, 7 Drawing Sheets



Equalizer 200

Exemplary embodiment of invention, showing a self-initializing decision feedback equalizer operating at precise baseband.

US RE42,558 E

Page 2

U.S. PATENT DOCUMENTS			FOREIGN PATENT DOCUMENTS		
4,115,778 A	9/1978	Snow	5,596,361 A	1/1997	Martinez
4,128,880 A	12/1978	Cray, Jr.	5,600,573 A	2/1997	Hendricks et al.
4,302,626 A	11/1981	Streeter	5,617,148 A	4/1997	Montgomery
4,310,920 A	1/1982	Hayes	5,666,168 A	9/1997	Montgomery et al.
4,316,215 A	2/1982	Yasumoto et al.	5,694,424 A	12/1997	Ariyavisitakul
4,322,842 A	3/1982	Martinez	5,714,965 A	2/1998	Taguchi
4,337,479 A	6/1982	Tomimoto et al.	5,734,853 A	3/1998	Hendricks et al.
4,379,947 A	4/1983	Warner	RE35,774 E	4/1998	Moura et al.
4,459,595 A	7/1984	Kramer et al.	5,742,902 A	4/1998	Shore
4,459,681 A	7/1984	Ohtsuka	5,809,086 A	9/1998	Ariyavisitakul
4,469,437 A	9/1984	Yuasa et al.	5,812,184 A	9/1998	Martinez
4,476,484 A	10/1984	Haskell	5,818,441 A	10/1998	Throckmorton et al.
4,513,415 A	4/1985	Martinez	5,818,845 A	10/1998	Moura et al.
4,523,225 A	6/1985	Masuda et al.	5,828,655 A	10/1998	Moura et al.
4,535,352 A	8/1985	Haskell	5,859,852 A	1/1999	Moura et al.
4,551,011 A	11/1985	Yuasa et al.	5,881,302 A	3/1999	Omata
4,575,225 A	3/1986	Yuasa et al.	5,909,253 A	6/1999	Jonnalagadda et al.
4,576,470 A	3/1986	Yuasa et al.	5,946,047 A	8/1999	Levan
4,587,495 A	5/1986	Osawa et al.	5,946,048 A	8/1999	Levan
4,589,011 A	5/1986	Rzeszewski	5,946,322 A	8/1999	Moura et al.
4,602,260 A	7/1986	Lindenmeier et al.	5,946,351 A	8/1999	Ariyavisitakul et al.
4,607,230 A	8/1986	Kaku et al.	5,956,346 A	9/1999	Levan
4,754,233 A	6/1988	Pickett	5,959,660 A	9/1999	Levan
4,821,097 A	4/1989	Robbins	5,959,997 A	9/1999	Moura et al.
4,870,489 A	9/1989	Ducret	5,994,891 A	11/1999	Hubbell
4,879,606 A	11/1989	Walter et al.	6,005,850 A	12/1999	Moura et al.
4,882,614 A	11/1989	Kageyama et al.	6,012,161 A	1/2000	Ariyavisitakul et al.
4,882,725 A	11/1989	Noda et al.	6,016,316 A	1/2000	Moura et al.
4,907,218 A	3/1990	Inoue et al.	6,018,526 A	1/2000	Liu et al.
4,926,244 A	5/1990	Isnardi	6,018,764 A	1/2000	Field et al.
4,928,177 A	5/1990	Martinez	6,034,678 A	3/2000	Hoarty et al.
4,944,032 A	7/1990	Kageyama et al.	6,047,159 A	4/2000	Powell et al.
4,958,230 A	9/1990	Jonnalagadda et al.	6,066,993 A	5/2000	Yamamoto et al.
4,985,769 A	1/1991	Yasumoto et al.	6,073,030 A	6/2000	Nair et al.
5,006,926 A	4/1991	Tsinberg	6,100,883 A	8/2000	Hoarty
5,019,830 A	5/1991	Harada	6,104,727 A	8/2000	Moura et al.
5,036,386 A	7/1991	Yasumoto et al.	6,192,384 B1	2/2001	Dally et al.
5,038,402 A	8/1991	Robbins	6,201,536 B1	3/2001	Hendricks et al.
5,087,975 A	2/1992	Citta et al.	6,226,323 B1	5/2001	Tan et al.
5,093,718 A	3/1992	Hoarty et al.	6,240,133 B1	5/2001	Sommer et al.
5,103,295 A	4/1992	Uwabata et al.	6,268,774 B1	7/2001	Soumyanath
5,103,310 A	4/1992	Gibson et al.	6,305,020 B1	10/2001	Hoarty et al.
5,126,998 A	6/1992	Stem, Jr.	6,310,548 B1	10/2001	Stephens, Jr. et al.
5,132,988 A	7/1992	Fisher et al.	6,314,134 B1	11/2001	Werner et al.
5,134,464 A	7/1992	Basile et al.	6,356,586 B1	3/2002	Krishnamoorthy et al.
5,142,353 A	8/1992	Kageyama et al.	6,366,613 B2	4/2002	Sommer et al.
5,151,783 A	9/1992	Faroudja	6,370,571 B1	4/2002	Medin, Jr.
5,172,126 A	12/1992	Naito	6,377,529 B1	4/2002	Lee et al.
5,177,604 A	1/1993	Martinez	6,385,237 B1	5/2002	Tsui et al.
5,214,501 A	5/1993	Cavallerano et al.	6,426,973 B1	7/2002	Madhow et al.
5,220,420 A	6/1993	Hoarty et al.	6,433,835 B1	8/2002	Hartson et al.
5,235,619 A	8/1993	Beyers, II et al.	6,510,553 B1	1/2003	Hazra
5,243,423 A	9/1993	DeJean et al.	6,680,971 B1	1/2004	Tazebay et al.
5,247,351 A	9/1993	Cho	6,754,277 B1	6/2004	Heinzelman et al.
5,270,817 A	12/1993	Hayashi et al.	6,754,715 B1	6/2004	Cannon et al.
5,276,507 A	1/1994	Uwabata et al.	6,829,298 B1	12/2004	Abe et al.
5,287,180 A	2/1994	White	6,834,039 B1	12/2004	Kelly et al.
5,293,633 A	3/1994	Robbins	7,180,942 B2	2/2007	Chung et al.
5,321,514 A	6/1994	Martinez	2001/0022813 A1	9/2001	Tan et al.
5,327,460 A	7/1994	Batruni	2002/0056140 A1	5/2002	Oishi et al.
5,357,284 A	10/1994	Todd	2002/0059597 A1	5/2002	Kikinis et al.
5,379,324 A	1/1995	Mueller et al.	2002/0104083 A1	8/2002	Hendricks et al.
5,386,239 A	1/1995	Wang et al.	2002/0186764 A1	12/2002	Amin et al.
5,430,661 A	7/1995	Fisher et al.	2003/0095590 A1	5/2003	Fuller et al.
5,442,403 A	8/1995	Yasumoto et al.	2003/0156603 A1	8/2003	Rakib et al.
5,448,299 A	9/1995	Yang et al.			
5,461,426 A	10/1995	Limberg et al.			
5,534,933 A	7/1996	Yang	EP	0308241 A2	3/1989
5,550,578 A	8/1996	Hoarty et al.	EP	0577351	1/1994
5,550,579 A	8/1996	Martinez	EP	0577351 A2	1/1994
5,557,316 A	9/1996	Hoarty et al.	EP	1156634	11/2001
5,559,559 A	9/1996	Jungo et al.	EP	1156634 A1	11/2001
5,563,664 A	10/1996	Yang et al.	WO	WO 92/22983	12/1992
5,579,055 A	11/1996	Hamilton et al.	WO	WO-9222983 A2	12/1992
5,585,975 A	12/1996	Bliss	WO	WO 94/23470	10/1994
5,586,121 A	12/1996	Moura et al.	WO	WO-9423470 A1	10/1994
5,587,743 A	12/1996	Montgomery et al.	WO	WO 95/01676	1/1995
5,589,872 A	12/1996	Martinez	WO	WO-9501676 A1	1/1995
			WO	WO 99/55087	10/1999

WO	WO-9955087	A1	10/1999
WO	WO 02/07425		1/2002
WO	WO-0207425	A2	1/2002
WO	WO02084965	A1	10/2002
WO	WO-02084965	A1	10/2002

OTHER PUBLICATIONS

- Godard, D.N., "Self-recovering equalization and carrier tracking in two-dimensional data communication systems," *IEEE Transactions on Communications*, 1980, vol. 28, No. 11, pp. 1867-1875.
- Treichler, J.R. et al. "A new approach to multipath correction of constant modulus signals," *IEEE Transactions on Acoustics, Speech, and Signal Processing*, Apr. 1983 vol. ASSP-31, No. 2, pp. 459-472.
- Casas et al., "Current approaches to blind decision feedback equalization," *Signal processing advances in wireless and mobile communications: trends in channel estimation and equalization*, Aug. 1999, 45 pgs.
- Daneshmand et al., "Finite Wordlength Requirements for Adaptive Signal Processing Elements in Digital QAM ADSL Systems," *Communications, 1994, Supercomm/ICC 94, Conference Record Serving Humanity Through Communications*, May 1, 1994.
- Naito et al., "Adaptive Equalization Based on Internal Model Principle for Time-Varying Fading Channels," *IEEE*, Oct. 1, 2001, p. 363-368.
- Evans, G. "More Tools of the Trade: Modulators, Inside Custom A/V," <http://www.hometeam.com/beta/0009customav.shtml>. NetMedia, MM73/NMOD3 Triple Play Modulator Installation Manual, Net Media, Tucson AZ (undated).
- Ciciora et al., "Embedding high-speed data in analog signals," *CED Magazine*, Dec. 2001, pp. 92-100.
- Ciciora et al., "Modem Cable Television Technology, Video, Voice and Data Communications," 1999.
- Ormiston et al., "Compact Low Noise Receiving Antenna," *IEEE Electronics Letters*, Jul. 9, 1998, vol. 34, No. 14, pp. 1367-1368.
- Tooley et al., "Active Receiving Antenna," *Practical Wireless*, Mar. 1981 vol. 57, No. 3, pp. 52-55.
- Chen, B. "The Key to Unlocking Network Assets: Increasing Capacity by Embedding Content in Current Video Transmission," *CED Magazine*, Dec. 2001, <http://www.cedmagazine.com/ced/2001/1201/12f.htm>.
- "WavePhore and the Canadian Broadcasting Corporation," Mar. 29, 1995, WavePhore Press Release.
- "Technology Offers TV Broadcasters An Avenue Into Interactive Services," *Investor's Business Daily*, Apr. 19, 1993.
- "WavePhore and Belcom Sign Agreement to Co-Develop Russian Data Broadcasting System," Apr. 10, 1995, WavePhore Press Release.
- Press Release of WavePhore entitled FCC Proposed to Allow Digital Data Transmission Within the Video Portion of TV Broadcasts, in Response to WavePhore's Request, (two pages believed to have been released Apr. 25, 1995).
- "WavePhore Stock is On Roll," *The Indianapolis News*, May 23, 1995.
- "WavePhore Set Technology Alliance," *the Business Daily*, May 8, 1995.
- "Intel and WavePhore Sign Technology and Investment Agreement," Press Release, May 5, 1995.
- "Tempe Firm, Intel Team Up to Send Data Via TV," Advertisement, May 6, 1995.
- "Skyway System Rides TV Signals to Distribute Data Speed Key to WavePhore Technology," *Arizona Business Gazette*, Jul. 13, 1995.
- "Motivated CEO Leads WavePhore," *Arizona Business Gazette*, Jul. 13, 1995.
- "WavePhore Develops Data Casting System for Television Azteca in Mexico," Aug. 8, 1995, Press Release.
- "WavePhore and Arizona State University Launch Distance Learning Services," Aug. 17, 1995, WavePhore Press Release.
- "Digital Data Transmission Within the Video Portion of Television Broadcast Station Transmissions," MM.
- Glasford, "Fundamentals of Television Engineering," 1995, McGraw-Hill, 1995.
- Fink, "Television Engineering," 2nd Ed., 1952, McGraw-Hill.
- Eilers, "TV Multichannel Sound—The BTSC System," *IEEE Transactions on Consumer Electronics*, Aug. 1984.
- Taylor, "The Vestigial Sideband and Other Tribulations," *National Cable Television Association*, 1988, Technical Papers, p. 203.
- "HDTV & Vestigial Sideband Syndrome," *IEEE Transactions on Broadcasting*, Mar. 1990, p. 8.
- "Wave Generation & Shaping," Leonard Strauss, Chapters 1 and 2, 1970, McGraw-Hill.
- Ciciora et al., "A Tutorial on Ghost Cancelling in Television Systems," *IEEE Transactions on Consumer Electronics*, vol. CE-25, No. 1, Feb. 1979, pp. 9-44.
- Rhyne, "Fundamentals of Digital Systems Design," *Basic Concepts*, Ch 1, pp. 1-27, 1973, Prentice-Hall, Inc.
- Hill et al., "Introduction to Switching Theory & Logical Design," 1968, John Wiley & Sons.
- Tanenbaum, A., "Computer Networks," 1996, Prentice-Hall.
- Spohn, D.L., "Data Network Design," 1993, McGraw-Hill.
- Nordholt, et al., "A New Approach to Active Antenna Design," *IEEE Transactions on Ant. And Prop.*, Nov. 1980, vol. AP-28, No. 6.
- Kaufman, C., "Network Security," 1995, Prentice-Hall.
- Ariyavisitakul et al., "Joint Coding and Decision Feedback Equalization for Broadband Wireless Channels," *IEEE*, Dec. 1998, pp. 1670-1678, vol. 19, No. 9.
- Ariyavisitakul et al., "Joint Coding and Decision Feedback Equalization for Broadband Wireless Channels," Dec. 1998, *IEEE Journal on Selected Areas in Communications*, vol. 16, No. 9, pp. 1670-1678.*
- Godard, D. N.: "Self-recovering equalization and carrier tracking in two-dimensional data communication systems," *IEEE Transactions on Communications*, vol. 28, No. 11, pp. 1867-1875, Nov. 1980.
- Treichler, J. R., and Agee, B.G.: "A new approach to multipath correction of constant modulus signals," *IEEE Transactions on Acoustics, Speech, and Signal Processing*, vol. ASSP-31, No. 2, pp. 459-472, Apr. 1983.
- Casas R. A., et al.: "Current approaches to blind decision feedback equalization," in the textbook, "Signal processing advances in wireless and mobile communications: trends in channel estimation and equalization," edited by G. Giannakis, et al., Prentice Hall, Upper Saddle River, NJ, 2000.
- Communications, 1994. Supercomm/ICC '94, Conference Record, "Serving Humanity Through Communications," May 1, 1994. ISBN:0780318250.
- Ciciora, Dukes, Hartson, Hoarty, *Embeddings high-speed data in analog signals* CED Magazine, Dec. 2001, p. 92-100.
- Modern Cable television Technology: Video, Voice, and Data Communications, 1999 Walter Ciciora, James Farmer, David Large, Morgan Kaufman ISBN I-55860-416-2.
- CED Magazine, Dec. 2001. <http://www.cedmagazine.com/ced/2001/1201/12f.htm>.
- Press Release of WavePhore, Inc. entitled "WavePhore and the Canadian Broadcasting Corporation Enter an Agreement to Deliver Data Broadcasting Nationwide in Canada," dated Mar. 29, 1995.
- Advertisement in *Investor's Business Daily*, "Technology Offers TV Broadcasters An Avenue Into Interactive Services", Monday, Apr. 19, 1993.
- News Release of WavePhore, entitled "WavePhore and Belcom Sign Agreement to Co-Develop Russian Data Broadcasting System" (two pages, believed to have been released Apr. 10, 1995).
- Advertisement in *The Indianapolis News*, WavePhore Stock Is On Roll, dated May 23, 1995.
- Advertisement in *Investor's Business Daily*, Intel, WavePhore Set Technology Alliance, dated Monday, May 8, 1995.
- Press Release, entitled Intel and WavePhore Sign Technology And Investment Agreement, (two pages, believed to have been released May 5, 1995).
- Advertisement, *The Arizona Republic Business*, "Tempe firm, Intel Team Up to Send Data via TV", dated Saturday, May 6, 1995.
- Advertisement, *Arizona Business Gazette*, entitled "Skyway System Rides TV Signals to Distribute Data—Speed Key to WavePhore Technology", dated Jul. 13, 1995.
- Advertisement, *Arizona Business Gazette*, entitled "Motivated CEO Leads WavePhore", dated Jul. 13, 1995.

Press Release of WavePhore, entitled WavePhore Develops Data Casting System for Television Azteca in Mexico (two pages, believed to have been released Aug. 8, 1995).

Press Release of WavePhore, entitled WavePhore and Arizona State University Launch Distance Learning Service, (two pages, believed to have been released Aug. 17, 1995).

“Digital Data Transmission Within the Video Portion of Television Broadcast Station Transmissions”.

G.M. Glasford, *Fundamentals of Television Engineering*, McGraw-Hill 1955.

D.G. Fink, *Television Engineering*, 2nd Edition, McGraw-Hill 1952.

C.G. Eilers, “TV Multichannel Sound—The BTSC System,” IEEE Transactions on Consumer electronics, Aug. 1984.

Taylor, “The Vestigial Sideband and Other Tribulations,” p. 203 of the 1988 National Cable Television Association Technical Papers.

“HDTV & Vestigial Sideband Syndrome” in the IEEE Transactions on Broadcasting, Mar. 1990, p. 8.

Wave Generation & Shaping, Leonard Strauss, McGraw-Hill 1970, Chapters 1 and 2.

W. Ciclora et al., “A Tutorial on Ghost Canceling in Television Systems,” IEEE Transactions on Consumer Electronics, vol. CE-25, No. 1, Feb. 1979, pp. 9-44.

V. Thomas Rhyme, *Fundamentals of Digital System Design*.

Hill, et al.—*Introduction to Switching Theory & Logical Design*, John Wiley & Sons 1968, SBN 471 39880 K.

Tanenbaum, A. “*Computer Networks*,” Prentice Hall 1996, ISBN 0-1-349945-6.

Spohn, D.L., “*Data Network Design*,” McGraw Hill, 1993 ISBN 0-07-06-360-X.

Nordholt, et al.: “A New Approach to Active Antenna Design”, IEEE Transactions on Ant. And Prop., Nov. 1980, vol. AP-28, No. 6.

Kaufman, C., “*Network Security*,” Prentice Hall, 1995 ISBN 0-13-061466-1.

* cited by examiner





Figure 1: Typical prior-art communication system that may be employed for transmission of digital signals.



Equalizer 200

Figure 2: Exemplary embodiment of invention, showing a self-initializing decision feedback equalizer operating at precise baseband.




Figure 3: Block Diagram of Soft Decision Device




Figure 4: 16-QAM constellation and selection region for Soft Decision Device




Figure 5b: Soft decision device parameter




Figure 5a : Real part of equalizer output






Figure 5c: Soft Decision Device



Equalizer 600

Figure 6: Alternative embodiment of invention showing equalizer forward and feedback filters operating on passband samples.



Equalizer 600

Figure 7: Alternative embodiment of invention showing forward filter operating on passband samples, and feedback filter operating on baseband samples.

**JOINT ADAPTIVE OPTIMIZATION OF SOFT
DECISION DEVICE AND FEEDBACK
EQUALIZER**

Matter enclosed in heavy brackets [] appears in the original patent but forms no part of this reissue specification; matter printed in italics indicates the additions made by reissue.

[CONTINUATION IN PART] *CROSS-REFERENCE
TO RELATED APPLICATIONS*

[This] *This patent application is a reissue application for commonly assigned U.S. Pat. No. 7,180,942, issued on Feb. 20, 2007 from U.S. patent application Ser. No. 10/327,280, filed on Dec. 20, 2002, which is a continuation-in-part of that certain U.S. Ser. No. 10/322,299, filed Dec. 17, 2002 now abandoned, entitled "Self-Initializing Decision on Feedback Equalizer With Automatic Gain Control;" Endres, Long, Cunningham and Ray, inventors, which relies on U.S. Ser. No. 60/341,931, filed Dec. 18, 2001 entitled "Self-Initializing Decision Feedback Equalizer With Automatic Gain Control."* These documents are incorporated herein by this reference.

FIELD OF INVENTION

The present invention relates to adaptive optimization techniques for Decision Feedback Equalizers in order to compensate for distortions introduced in digital communications systems using modulation techniques such as Quadrature Amplitude Modulation (QAM) or Pulse Amplitude Modulation (PAM).

BACKGROUND

In digital communication systems, the digital information bits are mapped to symbols drawn from a finite set of discrete real or complex numbers. These symbols are used to modulate a radio frequency (RF) carrier's frequency, amplitude and/or phase. For example, a quadrature oscillator can be used to modulate the complex symbols onto the amplitude and phase of the RF carrier, and the signaling is referred to as Quadrature Amplitude Modulation (QAM). The time interval between symbols is referred to as the symbol or baud interval, and the inverse of this interval is referred to as the symbol or baud rate.

Most modem digital communication systems use a symbol rate that sends thousands or millions of symbols per second, over propagation media including satellite links through the earth's atmosphere, terrestrial links from towers to fixed or mobile land-based receivers, or wired links using ancient twisted-pair copper connections or more sophisticated fiber optic connections. Such media are dispersive, causing fading and reflections that result in multiple path delays arriving at the receiver. Such behavior is known as multipath, and causes symbols to smear across multiple symbol boundaries, which is referred to as inter-symbol interference (ISI). Moreover, mismatches in transmitter and receiver filtering induce ISI. Noise is added to the received signal from transmitter and receiver component imperfections, and from sources through the propagation path. At the receiver, an equalizer is used to mitigate the effects of ISI and noise induced in the entire channel, including transmitter, propagation medium, and front-end receiver processing. Since the exact channel characteristics are not known a priori at the receiver, the equalizer is usually implemented with adaptive methods.

A common type of equalizer uses adaptive filters, and the adjustment of filter coefficients can be done in a variety of ways. Trained equalization methods rely on the embedding of a pre-determined sequence in the transmitted data, referred to as a training or reference sequence. The receiver stores or generates a replica of the training sequence, and to the extent that the received sequence differs from the training sequence, an error measure is derived to adjust equalizer coefficients. Usually, equalizer coefficient convergence relies on multiple transmissions of the training sequence, and the channel characteristics are also time varying. Hence, periodic re-training is necessary.

A common method of trained coefficient adaptation uses the Least Mean Squares (LMS) algorithm, which minimizes a Mean Squared Error (MSE) cost function with a stochastic gradient descent update rule as described in a paper entitled "The complex LMS algorithm," by Widrow, McCool, and Ball, in The Proceedings of the IEEE, vol. 63, no. 4, pp. to 719-720, April 1975.

Unfortunately, the training sequence needed for LMS takes up valuable bandwidth that could be used for data transmissions. Hence, methods that do not rely on a reference signal, or derive a reference signal from the data itself, are desirable. Such methods are referred to as blind equalization methods. A common blind equalization method replaces the reference signal in the LMS algorithm with the receiver's best guess at the data, and is therefore referred to as Decision Directed LMS (DD-LMS), as proposed in a paper entitled "Techniques for adaptive equalization of digital communication systems," by R. W. Lucky, in the Bell Systems Technical Journal, vol. 45, no. 2, pp. 255-286, February 1966. Unfortunately, DD-LMS needs a reasonably low percentage of incorrect decisions to prevent algorithm divergence, and is therefore impractical from a cold-start initialization. Other blind algorithms are usually used from a cold-start.

The Constant Modulus Algorithm (CMA), proposed independently by Godard and Treichler ("Self-recovering equalization and carrier tracking in two-dimensional data communication systems," by D. N. Godard, in IEEE Transactions on Communications, vol. 28, no. 11, pp. 1867-1875, October 1980, and "A new approach to multipath correction of constant modulus signals," by J. R. Treichler, and B. G. Agee, in IEEE Transactions on Acoustics, Speech, and Signal Processing, vol. ASSP-31, no. 2, pp. 459-472, April 1983) has rapidly become the most popular blind equalization algorithm in practice, and is well-studied in the archival literature, due to its robustness to realistic signaling environments and LMS-like computational complexity and asymptotic performance. Instead of minimizing a MSE cost function, CMA minimizes a quartic Constant Modulus (CM) cost function that penalizes dispersion at the equalizer output.

Though both LMS and CMA were originally introduced using a linear transversal, or finite impulse response (FIR) equalizer structure, a Decision Feedback Equalizer (DFE) is generally believed to provide superior ISI cancellation with less noise gain than an FIR equalizer structure. A DFE acts to additively cancel ISI by subtracting filtered decisions (or best guesses, also known as hard decisions) from the sampled received signals. The feedback structure embeds a FIR filter in a feedback loop, fed by symbol estimates, and therefore has infinite impulse response (IIR). Like the DD-LMS algorithm, the DFE architecture requires a low percentage of incorrect decisions to prevent algorithm divergence and error propagation, a phenomenon whereby an incorrect decision causes more incorrect decisions due to the recursive structure of the DFE. Therefore, a DFE requires alternative adaptive strategies from a cold-start. Several techniques based on adaptive

IIR filtering have been proposed as summarized in a chapter entitled "Current approaches to blind decision feedback equalization," by R. A. Casas et al., in the textbook, "Signal processing advances in wireless and mobile communications: trends in channel estimation and equalization," edited by G. Giannakis, et al., Prentice Hall, Upper Saddle River, N.J., 2000.

Though adaptive IIR filtering approach for blind DFE initialization can achieve successful cold start up, its performance is significantly less optimal than DD-LMS/DFE and mechanical switch from IIR adaptation to DD-LMS adaptation usually exhibits performance degradation in transient period, and thus, in dealing with time varying channels. In order to achieve better transition between IIR adaptation and DD-LMS/DFE Endres et. al in Provisional Application No. 60,341,931, filed Dec. 17, 2001 entitled "Self-initializing decision feedback equalizer with automatic gain control" proposed linearly combining IIR adaptation and DD-LMS adaptation of the DFE coefficients.

On the other hand, it has been recognized that DFE is not robust under severe noise environment due to error propagation rooted in its recursive structure. Recent studies such as in "Joint Coding and Decision Feedback Equalization for Broadband Wireless Channels," by Ariyavisitakul et al in IEEE Journals on Selected Areas in Comm. Vol. 16, No. 9, December 1998 proposed a soft decision device approach to reduce MSE of DFE output by replacing the hard decisions with cleverly estimated soft decisions.

The present invention combines the soft decision device approach and the seamless transition between IIR adaptation and DD-LMS adaptation. Unlike the linear combination of IIR and DD-LMS adaptations, this present invention uses a family of non-linear soft decision devices approximating the optimal soft decision device studied in soft-decision DFE literatures. According to the selection rule inferred from the non-linear soft decision device, DFE coefficients are updated by selected error signals between IIR adaptation and DD-LMS adaptation on a symbol-by-symbol basis, which jointly optimizes the soft decision device and DFE adaptation.

SUMMARY

In accordance with the present invention, a Decision Feedback Equalizer (DFE) uses input samples to the feedback filter that are generated from a novel adaptive soft decision device. The soft decision device receives the input and output samples of the slicer and generates a feedback sample based on a novel non-linear decision rule. Moreover, the soft decision device provides novel error terms used to adapt equalizer coefficients.

BRIEF DESCRIPTION OF DRAWINGS

Other aspects, features, and advantages of the present invention will become more fully apparent from the following detailed description, the appended claims, and the accompanying drawings in which:

FIG. 1 shows a typical prior art communication system that may be employed for transmission of digital signals;

FIG. 2 shows an exemplary embodiment of the present invention, showing a self-initializing decision feedback equalizer operating at precise baseband;

FIG. 3 describes the Soft Decision Device in the present invention;

FIG. 4 shows a 16-QAM constellation selection regions for Soft Decision Device in the present invention;

FIG. 5a shows the in-phase component of the equalizer output from a computer simulation of the preferred embodiment of the present invention;

FIG. 5b shows the soft decision parameter $\lambda(n)$ trajectory from a computer simulation of the preferred embodiment of the present invention;

FIG. 5c illustrates the input-output relation of the Soft Decision Device for a given $\lambda(n)$ and constellation;

FIG. 6 shows an alternative embodiment of the present invention, with equalizer forward and feedback filters operating on passband samples; and

FIG. 7 shows an alternative embodiment of the present invention, with equalizer forward filter operating on passband samples, and equalizer feedback filter operating on baseband samples.

DETAILED DESCRIPTION

FIG. 1 depicts a typical prior art digital communication system. Transmitter station 100 is coupled to receiver 150 by propagation medium 147. The propagation medium could be a cable, telephone twisted-pair wire, satellite link, terrestrial link, or fiber optic connection, for example. Transmitter station 100 includes an information source 110, that contains the content such as data, audio, or video, which is to be communicated to the receiver 150. The information source 110 is coupled to encoder 120, which formats the information in a manner suitable for digital communication, typically in accordance with a given standard or protocol. The encoder 120 is coupled to modulator 140, which is also coupled to a quadrature oscillator 130. The modulator 140 uses the signal from the quadrature oscillator 130 to modulate the encoded information provided by encoder 120 onto a suitable Radio Frequency (RF) carrier frequency in amplitude and phase. The modulated signal from modulator 140 is coupled to transmit antenna 145 for transmission into propagation medium 147.

The receiver 150 receives the RF signal from propagation medium 147 via receiver antenna 149. Receiver antenna 149 is coupled to tuner 160. Tuner 160 is set to receive the RF signal in the desired frequency range, while rejecting signals in nearby or adjacent frequency ranges. Tuner 160 may provide automatic gain control at the RF frequency and also downconvert the received signal to an intermediate frequency (IF) before passing the signal to the Front End Processing block 165. Front End Processing block 165 samples the signal with an analog-to-digital converter and contains an automatic gain control circuit that scales the signal to the proper dynamic range in accordance with the analog-to-digital converter. Front End Processing block 165 may further include a digital downconversion in frequency, and performs a quadrature demodulation to split the signal into in-phase (I) and quadrature-phase (Q) samples. Front End Processing block 165 is coupled to Timing Recovery module 170 that determines a correct sampling phase. Timing Recovery module 170 may adjust the sampling phase by interpolating the data samples, or adjusting the phase and sampling frequency of the analog-to-digital converter in Front End Processing block 165. Timing Recovery module 170 is coupled to Equalizer 175, which is used to mitigate the distortions, such as intersymbol interference and noise, that are introduced by the propagation medium 147, transmitter 100, receiver Tuner 160, receiver Front End Processing block 165, and receiver Timing Recovery module 170. Equalizer 175 is coupled to Carrier Recovery module 180, which detects residual offset in frequency and phase. The detected carrier offset in Carrier Recovery module may be supplied back to the Equalizer 175

for translation of equalized samples to precise baseband, or used to adjust the downconversion process in Front End Processing block 165, or both. The output of Equalizer 175 is coupled to Error Correction module 185, which detects and corrects bit errors in the recovered bit stream. The Error Correction module 185 is coupled to Decoder 190, which decodes the bit stream in accordance with the standard or protocol used in the Encoder 120 of Transmitter 100. The decoded bits from Decoder 190 represent the recovered information source, consisting of data, audio, or video, and are supplied to a user interface 195. The present invention is embodied in the Equalizer 175 portion of the communication system.

Baseband/Baseband Equalization

FIG. 2 shows an exemplary embodiment of the present invention. An Equalizer 200 receives complex data $\tilde{r}(n)$ that is input to mixer 285. The mixer 285 also receives a signal from carrier recovery loop 280, $e^{-j\theta(n)}$, that is an estimate of the conjugate of the carrier offset. Methods of carrier recovery are well known to one skilled in the art, and may be found, for example, in chapter 16 of the text "Digital Communication" by E. A. Lee and D. G. Messerschmitt, Kluwer Academic Publishers, 1994, which is incorporated herein by reference. The carrier recovery loop 280 and mixer 285 are shown as dashed lines, to represent that translation to precise baseband is done prior to equalization, and may be done anywhere prior to equalization in the signal processing chain. For example, some systems embed pilot tones or pulses to aid synchronization, allowing translation to precise baseband in the receiver front end, prior to equalization. In this exemplary embodiment of the invention, the equalizer 200 operates on samples that have been translated to precise baseband.

The output of mixer 285 is a received signal, $r(n)$, that is at precise baseband, and is input to forward filter 210. Forward filter 210 may operate at the baud rate or faster, in which case the equalizer is said to be fractionally-spaced, and exploits temporal diversity. Also, the forward filter 210 may receive multiple inputs, as from multiple antennae, to exploit spatial diversity. Temporal or spatial diversity uses a multi-channel forward filter. For simplicity, however, a single forward filter 210 is shown, and extension to a multi-channel model is understood by one skilled in the art.

Filtering

Forward filter 210 is a finite impulse response (FIR) filter, computing its output according to the convolution sum

$$x(n) = f_0(n)r(n) + f_1(n)r(n-1) + f_2(n)r(n-2) + \dots + f_{L_f}(n)r(n-L_f)$$

where $r(n)$ is the sample sequence input to forward filter 210, $x(n)$ is the output sample sequence of forward filter 210, f_i are the forward filter coefficients (or parameters,) and L_f is the number of forward filter coefficients. Note that the forward filter coefficients are also shown with time index n to indicate that the forward filter 210 is adaptive.

The feedback filter 220 is not multi-channel, and is a FIR filter that calculates its output according to the convolution sum

$$y(n) = g_0(n)v(n) + g_1(n)v(n-1) + g_2(n)v(n-2) + \dots + g_{L_g}(n)v(n-L_g)$$

where $v(n)$ is the sample sequence input to feedback filter 220, $y(n)$ is the output sample sequence of feedback filter 220, g_i are the feedback filter coefficients (or parameters,) and L_g is the number of feedback filter coefficients. Note that the feedback filter coefficients are also shown with time index n to indicate that the feedback filter 220 is adaptive. Though the

feedback filter 220 is a FIR filter, it is embedded in a feedback loop, so that the equalizer has an overall impulse response that is infinite.

Adder 275 combines the outputs of forward filter 210 and feedback filter 220, $x(n)$ and $y(n)$, respectively, to form sample sequence $w(n)$. Sample sequence $w(n)$ is referred to as slicer inputs. The slicer inputs, $w(n)$, are input to slicer 240. Slicer 240 is a nearest-element decision device that outputs a hard decision, $\hat{w}(n)$, corresponding to the source alphabet member with closest Euclidean distance to its input sample. The slicer input $w(n)$ and the hard decisions, $\hat{w}(n)$, from slicer 240 are input to the Soft Decision Device 230.

Soft Decision Device

FIG. 3 describes the Soft Decision Device in accordance with the present invention. The slicer input $w(n)$ is splitted into real and imaginary components. For the real and imaginary parts of $w(n)$, $w_{re}(n)$ and $w_{im}(n)$ respectively, the Boundary Value Generator 320 produces the nearest decision boundary values $\check{w}_{re}(n)$ and $\check{w}_{im}(n)$ by treating $w_{re}(n)$ and $w_{im}(n)$ as a Pulse Amplitude Modulated (PAM) signals, which belong to a alphabet set

$$\{-(2M-1)\Gamma, \dots, -3\Gamma, -\Gamma, \Gamma, 3\Gamma, \dots, (2M-1)\Gamma\}$$

where the constellation unit Γ and PAM level M are determined from the QAM level.

$$\check{w} = \underset{2k\Gamma}{\operatorname{argmin}} |w - 2k\Gamma|,$$

for $k = -M+1, \dots, M-1$.

with $|\cdot|$ denoting absolute value, or magnitude. Remind that the hard decision of a PAM signal is defined by

$$\hat{w} = \underset{(2k-1)\Gamma}{\operatorname{argmin}} |w - (2k-1)\Gamma|,$$

for $k = -M+1, \dots, M-1$.

FIG. 4 illustrates the relation among $w(n)$ (420), $\hat{w}(n)$ (430), $\check{w}_{re}(n)$ (440), and $\check{w}_{im}(n)$ (440) for a 16-QAM constellation.

In FIG. 3 the Soft Decision Generator 330 generates the soft decision based on the comparison between the distance between the nearest boundary values from the slicer input, $|w_{re}(n) - \check{w}_{re}(n)|$ and $|w_{im}(n) - \check{w}_{im}(n)|$, and a decision reference parameter $\lambda(n)$, according to

$$v(n) = \begin{cases} \frac{w(n) - \check{w}(n)}{\lambda(n)} & \text{if } |w_{re}(n) - \check{w}_{re}(n)| < \lambda(n) \text{ or } |w_{im}(n) - \check{w}_{im}(n)| < \lambda(n) \\ \hat{w}(n) & \text{else} \end{cases}$$

where $\check{w}(n) = \check{w}_{re}(n) + j\check{w}_{im}(n)$.

The soft decision device is made adaptive by adaptation of the decision reference parameter $\lambda(n)$. The decision reference parameter $\lambda(n)$ is initialized by $\lambda(0) = 1$ and adjusted from 0 to 1 depending on the signal quality. The Soft Decision Optimizer 350 optimizes the decision reference parameter $\lambda(n)$. The decision reference parameter $\lambda(n)$ can be approximately optimized by setting $\lambda(n) = E|w(n) - \hat{w}(n)|^2 / E|w(n)|^2$ with $E\{\cdot\}$

denoting statistical expectation) and can be adjusted each symbol instance using the leakage integrator

$$\lambda(n)=(1-\rho_\lambda)\lambda(n-1)+\rho_\lambda|w(n)-\hat{w}|^2/\Delta$$

where Δ is chosen to normalize $|w(n)-\hat{w}|^2$ (for example average signal power, $\Delta=E|w(n)|^2$) and ρ_λ is the leakage term and is chosen less than or equal to one and greater than or equal to zero.

Alternatively, $\lambda(n)$ can be updated on a block by block base based on the block estimation of $E|w(n)-\hat{w}(n)|^2/E|w(n)|^2$, or using training signals instead of $\hat{w}(n)$ for the training periods. Furthermore, the combining weight $\lambda(n)$ may be compared to two thresholds, T_U and T_L . If $\lambda(n)>T_U$, then $\lambda(n)$ is set to one; if $\lambda(n)<T_L$, then $\lambda(n)$ is set to zero

Error Signal Generation and Coefficient Adaptation

Adaptation of the forward filter **210** coefficients and feedback filter **220** coefficients uses a stochastic gradient descent update rule:

$$f_i(n+1)=f_i(n)-\mu_f\Phi^*(n)e(n)$$

$$g_i(n+1)=g_i(n)-\mu_g\phi^*(n)e(n)$$

where $(\cdot)^*$ represents complex conjugation, and μ_f and μ_g are small, positive stepsizes governing algorithm convergence rate, tracking capabilities and stochastic jitter. Using simplified updates, the data used in the adaptation equations are set to $\Phi(n)=r(n)$ and $\phi(n)=v(n)$. The baseband error term $e(n)$ that updates the forward filter **210** and feedback filter **220** at each baud instance is selected by Error Signal Generator **340** in Soft Decision Device **300** and is calculated according to

$$e(n) = \begin{cases} e_1(n) & \text{if } |w_{re}(n) - \tilde{w}_{re}(n)| < \lambda(n) \text{ or } |w_{im}(n) - \tilde{w}_{im}(n)| < \lambda(n) \\ e_2(n) & \text{else} \end{cases}$$

The preferred embodiment of the present invention uses a Constant Modulus Algorithm (CMA) error term of order $p=2$ (as described by Godard in "Self recovering equalization and carrier tracking in two-dimensional data communication systems") for $e_1(n)$ and a Decision-Directed LMS (DD-LMS) error term for $e_2(n)$. For example, CMA and DD-LMS error terms may be calculated according to

$$e_{cma} = \left(\frac{w(n) - \tilde{w}(n)}{\lambda(n)} + \tilde{w}(n) \right) \cdot \left(\left| \frac{w(n) - \tilde{w}(n)}{\lambda(n)} + \tilde{w}(n) \right|^2 - \gamma \right)$$

$$e_{dd-lms} = w(n) - \tilde{w}(n)$$

where γ is a real scalar referred to as the CM dispersion constant or Godard radius, and is usually calculated as $\gamma=E\{|s(n)|^4\}/E\{|s(n)|^2\}$ for source sequence $s(n)$, (These error terms are said to be baseband, since they are derived from samples at precise baseband.)

The intuition behind this error term generation is that the slicer inputs near hard decision boundaries are treated less reliable signals than the slicer inputs near hard decision samples. The Error Signal Generator **340** separates the unreliable signals and reliable signals, and apply IIR adaptation for the unreliable signals after proper resealing. For the reliable signals the conventional DD-LMS is applied.

Other choices of error terms may include CMA error terms of order other than $p=2$; those derived from the Bussgang

class of cost functions, as described in chapter 2 of "Blind Deconvolution," Prentice Hall, written by S. Bellini, edited by S. Haykin, 1994; single-axis error terms which use real-part extraction, as described in a paper by A. Shah et al, entitled "Global convergence of a single-axis constant modulus algorithm," Proceedings of the IEEE statistical signal and array processing workshop, Pocono Manor, Pa., August, 2000; or error terms derived from other blind or non-blind criteria.

Setting $\Phi(n)=r(n)$ and $\phi(n)=v(n)$ in the above equations used to adapt forward filter **210** and feedback filter **220** coefficients is referred to as "simplified updates," since the step known as regressor filtering is omitted. True cost function minimization requires an extra stage of filtering for the regressor data of the forward filter **210** and the feedback filter **220** in the adaptation process, using the current equalizer coefficients. Such regressor filtering is typically omitted in practice due to implementation burden. Regressor filtering is described in Chapter 5 of "Theory and design of adaptive filters" by J. R. Treichler, C. R. Johnson, Jr., and M. G. Larimore, Prentice Hall, 2001. One skilled in the art would recognize how to modify the regressor data used in the adaptation equations above to incorporate the extra stage of regressor filtering.

FIGS. **5a** and **5b** illustrate the equalizer output and soft decision reference parameter $\lambda(n)$ in operation from a computer simulation of the preferred embodiment of the present invention. The source signal is 4-QAM (QPSK) data passed through a closed-eye channel that has rapid time variation at the 5,000th baud sample. There are 10,000 baud samples, with adaptation of equalizer coefficients and decision reference parameter at the start of the simulation. The leakage value for Soft Decision Device optimization is $\rho_\lambda=0.01$. Thresholds for the combining weight are set to $T_U=1$ and $T_L=0$.

FIG. **5a** shows the real part of slicer inputs converging to correct decisions as adaptation is processed. Sudden dispersion at the 5,000th baud sample is due to sudden change of the multipath channel.

FIG. **5b** shows the trajectory of decision reference parameter $\lambda(n)$, initialized to unity, and converging towards zero when channel is static, and optimizing the adaptation and soft decision device when channel is varying.

FIG. **5c** draws the soft decision device as a function of slicer input for various choice of decision reference parameter $\lambda(n)$ in this simulation. For $\lambda(n)=0$ the soft decision device agrees with hard limiter and DFE is operating with DD-LMS algorithm. As $\lambda(n)$ increases the region of unreliable signals are increased too and DFE is operating with the conventional CMA in that region.

Passband/Passband Equalization

An alternative embodiment of the present invention is shown in FIG. **5**, in which the equalizer **500** operates in the passband; that is, not at precise baseband. Equalizer **500** is similar to equalizer **200** in FIG. **2**, so only the differences in equalizer **500** of FIG. **5** are described.

Forward filter **510** and feedback filter **520** produce data by convolution sums in an analogous manner to that described for the exemplary embodiment in FIG. **2**, yielding passband signals $x(n)$ and $y(n)$, respectively. The outputs of forward filter **510** and feedback filter **520** are combined in adder **590**, yielding the passband sample $\tilde{w}(n)$. This sample is translated to precise baseband (or de-rotated) slicer input $w(n)$ in multiplier **555** by multiplication with the conjugate of the carrier offset, $e^{-j\theta(n)}$, provided by carrier recovery loop **585**. The slicer **540** is a nearest-element decision device that outputs a

hard decision, $\hat{w}(n)$, corresponding to the source alphabet member with closest Euclidean distance to its input sample. The slicer input and hard decision samples are input to the Soft Decision Device and the soft decision $v(n)$ is translated back to the passband in multiplier 560 by multiplication with the carrier offset $e^{j\theta(n)}$, provided by the carrier recovery loop 585.

Though soft decision is made actually in baseband, equalizer adaptation must use an error term that is in the passband. The translation rules between passband and baseband error terms are given by:

$$e_{dd-lms}^{passband} = e_{dd-lms} \cdot e^{j\theta(n)}$$

$$e_{CMA}^{passband} = e_{CMA} \cdot e^{j\theta(n)}$$

Since both forward filter 510 and feedback filter 520 operate in the passband, they are updated with passband error terms.

Passband/Baseband Equalization

FIG. 6 shows equalizer 600, an alternative embodiment of the present invention, in which the forward filter 610 operates on passband data, while the feedback filter 650, and all processing after multiplier 645, operate at precise baseband. Forward filter 610 operates on received passband data $r(n)$ and calculates output $x_{pb}(n)$ via the convolution sum discussed for the filtering process of equalizer 200 in FIG. 2.

Multiplier 645 translates the output of forward filter 610 to precise baseband by multiplication with the conjugate of the carrier offset estimate, $e^{-j\theta(n)}$, provided by carrier recovery loop 685. The remainder of the equalizer 600 operates analogously to the equalizer 200 in FIG. 2, except that the equalizer control module 630 receives also the carrier offset estimate from carrier recovery loop 685 to produce a passband error term, $e_{pb}(n)$, as well as a baseband error term, $e(n)$. Feedback filter 620 operates on baseband data, and thus is adapted with the baseband error terms described for operation of equalizer 200 in FIG. 2. However, since forward filter 610 in FIG. 6 processes passband data, it is adapted by passband error terms that are generated by rotating the baseband error term with the current offset of the carrier recovery estimate, $e^{j\theta(n)}$.

One skilled in the art would understand that the equations described herein may include scaling, change of sign, or similar constant modifications that are not shown for simplicity. One skilled in the art would realize that such modifications can be readily determined or derived for the particular implementation. Thus, the described equations may be subject to such modifications, and are not limited to the exact forms presented herein.

The present invention has been described using Quadrature Amplitude Modulation (QAM) signals with complex signal processing, unless specifically noted. However, one skilled in the art would realize that the techniques described herein may be applied to a receiver processing Phase-Shift Keyed (PSK), Pulse Amplitude Modulation (PAM), or other signals.

As would be apparent to one skilled in the art, the various functions of equalization, signal combining, and automatic gain control may be implemented with circuit elements or may also be implemented in the digital domain as processing steps in a software program. Such software may be employed in, for example, a digital signal processor, microcontroller, or general-purpose computer.

The present invention can be embodied in the form of methods and apparatuses for practicing those methods. The present invention can also be embodied in the form of program code embodied in tangible media, such as floppy diskettes, CD-ROMs, hard drives, or any other machine-readable storage medium, wherein, when the program code is loaded into and executed by a machine, such as a computer, the machine becomes an apparatus for practicing the invention. The present invention can also be embodied in the form of program code, for example, whether stored in a storage medium, loaded into and/or executed by a machine, or transmitted over some transmission medium, such as over electrical wiring or cabling, through fiber optics, or via electromagnetic radiation, wherein, when the program code is loaded into and executed by a machine, such as a computer, the machine becomes an apparatus for practicing the invention. When implemented on a general-purpose processor, the program code segments combine with the processor to provide a unique device that operates analogously to specific logic circuits.

It will be further understood that various changes in the details, materials, and arrangements of the parts which have been described and illustrated in order to explain the nature of this invention may be made by those skilled in the art without departing from the principle and scope of the invention as expressed in the following claims.

What is claimed is:

1. A method for operating forward and feedback filters in a communications receiver having a decision feedback equalizer, said communications receiver having a decision feedback equalizer, said communications receiver responsive to a received signal to form slicer input samples and hard decision samples corresponding to said slicer output samples, said method comprising:

non-linearly combining said slicer input samples and said hard decision samples to form a soft decision samples in a soft decision device; and

the said soft decision device being adaptively adjusted to control contributions of said slicer input samples and said hard decision samples to form said soft decision samples; and

said soft decision device generating error signals to adjust said forward and feedback filters; and

operating said forward and feedback filters by coupling a composite decision samples to said feedback filter and by adapting said forward and feedback filters with said error signals.

2. The method of claim 1, wherein said decision feedback equalizer operates in passband.

3. The method of claim 1, wherein said feedback filter operates in baseband.

4. A receiver having a decision feedback equalizer, said receiver responsive to a received signal to form slicer input samples and hard decision samples corresponding to said slicer output samples, said receiver comprising:

a forward filter;

a feedback filter;

a slicer that is capable of generating the slicer output samples; and

a soft decision device that is capable of non-linearly combining said slicer input samples and said hard decision samples to form soft decision samples, said soft decision device further being adaptively adjusted to control contributions of said slicer input samples and said hard decision samples to form said soft decision samples,

11

further wherein said soft decision device is capable of generating error signals to adjust said forward and feedback filters;
wherein said forward and feedback filters are capable of coupling a composite decision samples to said feedback filter and by adapting said forward and feedback filters with said error signals. 5
5. *The receiver of claim 4, wherein said decision feedback equalizer operates in passband.*
6. *The receiver of claim 4, wherein said feedback filter* 10
operates in baseband.

12

7. *The receiver of claim 5, wherein said forward filter and said feedback filter operate in the passband.*
8. *The receiver of claim 6, wherein said forward filter operates in passband.*
9. *The receiver of claim 4 wherein said forward filter has a plurality of coefficients that are updated using a stochastic gradient descent rule.*

* * * * *

UNITED STATES PATENT AND TRADEMARK OFFICE
CERTIFICATE OF CORRECTION

PATENT NO. : RE42,558 E
APPLICATION NO. : 12/390368
DATED : July 19, 2011
INVENTOR(S) : Chung et al.

Page 1 of 2

It is certified that error appears in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

Title Page 3, item (56), under "Other Publications", in Column 1, Line 43, delete "pages" and insert -- pages, --.

Title Page 3, item (56), under "Other Publications", in Column 2, Line 3, delete "Vestigial" and insert -- Vestigial --.

Title Page 3, item (56), under "Other Publications", in Column 2, Line 5, delete "Vestigial" and insert -- Vestigial --.

Title Page 3, item (56), under "Other Publications", in Column 2, Line 17, delete "McGaw-Hill." and insert -- McGraw-Hill. --.

Title Page 3, item (56), under "Other Publications", in Column 2, Line 32, delete "Transactins" and insert -- Transactions --.

Title Page 3, item (56), under "Other Publications", in Column 2, Line 43, delete "Embeddings" and insert -- Embedding --.


Title Page 3, item (56), under "Other Publications", in Column 2, Line 45, delete "television" and insert -- Television --.

Title Page 3, item (56), under "Other Publications", in Column 2, Line 59, delete "Adverstisement" and insert -- Advertisement --.

Title Page 3, item (56), under "Other Publications", in Column 2, Line 61, delete "Adverstisement" and insert -- Advertisement --.

Title Page 3, item (56), under "Other Publications", in Column 2, Line 68, delete "entitle" and insert -- entitled --.

Signed and Sealed this
Tenth Day of January, 2012



David J. Kappos
Director of the United States Patent and Trademark Office

CERTIFICATE OF CORRECTION (continued)

Page 2 of 2

U.S. Pat. No. RE42,558 E

Title Page 4, item (56), under “Other Publications”, in Column 1, Line 14, delete “Vestigal” and insert -- Vestigial --.

Title Page 4, item (56), under “Other Publications”, in Column 1, Line 16, delete “Vestigal Sidebank” and insert -- Vestigial Sideband --.

Title Page 4, item (56), under “Other Publications”, in Column 2, Line 6, delete “Rhyme,” and insert -- Rhyne, --.

Title Page 4, item (56), under “Other Publications”, in Column 2, Line 15, delete “Printice” and insert -- Prentice --.