




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H04L 27/22	A2	(11) International Publication Number: WO 99/27689 (43) International Publication Date: 3 June 1999 (03.06.99)
(21) International Application Number: PCT/IB98/01808 (22) International Filing Date: 13 November 1998 (13.11.98) (30) Priority Data: 97203648.7 21 November 1997 (21.11.97) EP (71) Applicant: KONINKLIJKE PHILIPS ELECTRONICS N.V. [NL/NL]; Groenewoudseweg 1, NL-5621 BA Eindhoven (NL). (71) Applicant (for SE only): PHILIPS AB [SE/SE]; Kottbygatan 7, Kista, S-164 85 Stockholm (SE). (72) Inventors: GIELIS, Gerardus, Christiaan, Maria; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL). VAN DE PLASSCHE, Rudy, Johan; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL). (74) Agent: SCHOENMAKER, Maarten; Internationaal Octrooibureau B.V., P.O. Box 220, NL-5600 AE Eindhoven (NL).		(81) Designated States: JP, KR, European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE). Published <i>Without international search report and to be republished upon receipt of that report.</i>

(54) Title: DEMODULATION UNIT AND METHOD OF DEMODULATING A QUADRATURE SIGNAL



(57) Abstract

To demodulate a quadrature input signal (S_i) (for example, frequency shift) a demodulation unit (DEM) is used, comprising a PLL (P) having a complex mixer (M) and a controlled oscillator (V). Normally, a limiter has to be used to keep the loop gain independent of the amplitude of the quadrature input signal. In the PLL, a divider (DEL) is coupled between the mixer (M) and the oscillator (V) to divide the two mixed components (S_{m1} , S_{m2}) of the quadrature signal supplied by the mixer.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece			TR	Turkey
BG	Bulgaria	HU	Hungary	ML	Mali	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MN	Mongolia	UA	Ukraine
BR	Brazil	IL	Israel	MR	Mauritania	UG	Uganda
BY	Belarus	IS	Iceland	MW	Malawi	US	United States of America
CA	Canada	IT	Italy	MX	Mexico	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NE	Niger	VN	Viet Nam
CG	Congo	KE	Kenya	NL	Netherlands	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NO	Norway	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	NZ	New Zealand		
CM	Cameroon			PL	Poland		
CN	China	KR	Republic of Korea	PT	Portugal		
CU	Cuba	KZ	Kazakhstan	RO	Romania		
CZ	Czech Republic	LC	Saint Lucia	RU	Russian Federation		
DE	Germany	LI	Liechtenstein	SD	Sudan		
DK	Denmark	LK	Sri Lanka	SE	Sweden		
EE	Estonia	LR	Liberia	SG	Singapore		

Demodulation unit and method of demodulating a quadrature signal

Description

The invention relates to a demodulation unit for demodulating a quadrature input signal having at least two components, comprising a controlled oscillator for supplying a quadrature oscillator signal in dependence upon a control signal, and a mixer for mixing the quadrature input signal with the quadrature oscillator signal from the controlled oscillator and for supplying at least two mixed components, the mixer and the oscillator being incorporated in a PLL.

The invention also relates to a divider and a mixer for use in such a demodulation unit and to a receiver provided with such a demodulation unit.

The invention further relates to a method of demodulating a quadrature input signal having at least two components, wherein a quadrature oscillator signal is supplied in dependence upon a control signal and the quadrature input signal is mixed with the quadrature oscillator signal, and wherein at least two mixed components are supplied.

Such a demodulation unit and method may be used for, for example demodulating both AM and FM-modulated signals for radio, television, and communication receivers, etc., and for, for example "zero-IF" generation for QAM/QPSK signals and VSB signals, in which the PLL then comprises, for example, a COSTAS loop.

In addition to a synchronous demodulation function, such a demodulation unit also has a frequency-shift function.

In the present invention, a quadrature signal is also understood to be a real signal, which is a simplification of the signal to one of the two axes (X,Y) of the quadrature signal, in which both components are either equal or one of the components is zero.

A demodulation unit of this type is known from European patent application EP-A 0 579 100. This application describes a demodulation unit which comprises a PLL with a quadrature mixer and a controlled oscillator. This demodulation unit is intended to regain the phase and amplitude information of the carrier from the incoming signal.

A drawback of such a demodulation unit is that it is not very well possible

to demodulate both FM and AM signals without taking extra measures as regards filtering, etc. Such a demodulation unit may also have acquisition problems, inter alia, due to amplitude variations.

To eliminate amplitude variations of the input signal, an extra bandpass
5 filter and a limiter will have to be used for generating the carrier signal by means of the PLL. When the amplitude of the incoming signal varies, the lock-in range of the PLL will vary. Moreover, an amplitude variation of the control signal results in phase modulation of the carrier signal, which will distort the demodulated output signal.

If the PLL is used as an FM demodulator (for example, for TV sound),
10 the amplitude variation of the input signal will result in a distortion of the demodulated output signal.

In a known digital or analog PLL, the limiter and filtering function must
be incorporated in the carrier-generating circuit for demodulating AM signals. When
demodulating FM signals, the limiter precedes the PLL so as to eliminate unwanted
15 amplitude variations.

It is an object of the invention to obviate the above-mentioned drawbacks.
To this end, a demodulation unit according to the invention is characterized in that the PLL
also comprises a divider for dividing the at least two mixed components by each other and
20 for supplying the output signal as a control signal to the oscillator, and a filtering unit for
filtering one or more components and/or signals.

By making use of a divider in the PLL for dividing the two components
by each other, amplitude variations of the input signal will be prevented from causing
demodulation distortion or acquisition problems. By eliminating the amplitude variation, the
25 loop gain and, hence, the lock-in range remain constant. Moreover, by performing the
division in the PLL, it is no longer necessary to use a limiter and/or extra filtering function
for demodulating AM or FM signals.

The invention may be used in both digital and analog complex
demodulation units.

30 In one embodiment, the divider may be implemented as a linear CORDIC
preventing a division by zero. In one embodiment, the mixer may be implemented as a
circular CORDIC. A CORDIC (CO-ordinate Rotation DIgital Computer) is known per se
from, for example United States patent US-A 5,230,011 (PHN 13.500) and United States
patent application no. 08/704200 (PHN 15.428). In these implementations, a very efficient

digital embodiment of a demodulation unit is obtained.

The measures as described in dependent claim 4 have the advantage that each mixed component is separately filtered for filtering the sum frequency(ies) which have been added by mixing for the case where the input signals are real signals. If the input
5 signals are complex signals, but not ideal signals, the components should also be filtered before the division takes place. Furthermore, the filters have the customary loop filter function of a PLL.

According to the invention, a receiver comprises such a demodulation unit.

10 A method according to the invention is characterized by dividing the at least two mixed components by each other and supplying the output signal as a control signal for generating the oscillator signal, and by filtering one or more components and/or signals. In an integrated solution, the different functions may be incorporated in a CPU, wherein the division in the control loop prevents amplitude variations of the input signal from influencing
15 the demodulated signal.

These and other aspects of the invention are apparent from and will be elucidated with reference to the embodiments described hereinafter.

20 In the drawing:

Fig. 1 is a block diagram of an embodiment of a demodulation unit according to the invention, and

Fig. 2 is a block diagram of an embodiment of a mixer according to the invention.

25 Fig. 1 is a block diagram of an embodiment of a demodulation unit DEM according to the invention.

Inputs I_1 and I_2 of the demodulation unit receive a complex input signal S_i which consists of the components S_{i1} and S_{i2} . These components are applied to a mixer M. In
30 this mixer, these components are mixed with components S_{v1} and S_{v2} of a quadrature oscillator signal S_v from a controlled oscillator V.

Outputs of the mixer M supply mixed components S_{m1} and S_{m2} , which outputs are coupled to outputs O_1 and O_2 for supplying output signals S_{o1} and S_{o2} (for example, complex AM signals) and, in this embodiment, are coupled via low-pass filters L_1

and L_2 to a divider DEL for dividing the two filtered mixed components S_{d1} and S_{d2} by each other.

The output signal of the divider S_{del} is coupled to the controlled oscillator V. The output of the divider is also coupled to a third output O_3 of the demodulation unit DEM for supplying an output signal S_{o3} (for example, an FM signal).

In this embodiment, the mixer M, the low-pass filters L_1 and L_2 , the divider DEL and the controlled oscillator V jointly constitute a PLL P. The inputs I_1 and I_2 of the demodulation unit DEM receive complex input signals from, for example a complex input filter (not shown) as described in, for example United States patent application no. 08/52704 (PHN 15.001) which is herein incorporated by reference.

In this embodiment, the mixer M is a complex mixer and may be, for example a circular CORDIC as described in United States patent US-A 5,230,011 (PHN 13.500) and United States patent application no. 08/704200 (PHN 15.428), both of which are herein incorporated by reference.

Fig. 2 shows an embodiment of the mixer M in greater detail. In this embodiment, the mixer M comprises multipliers VER and adders OPT.

In the mixer M, the input signals S_{i1} and S_{i2} are mixed with the oscillator signals S_{v1} and S_{v2} from the controlled oscillator V (see Fig. 1). The signals S_{m1} and S_{m2} are then obtained:

$$S_{m1} = S_{i1} * S_{v1} - S_{i2} * S_{v2}$$

$$S_{m2} = S_{i2} * S_{v1} + S_{i1} * S_{v2}$$

$$\text{If } S_{i1} = \sin\alpha, S_{i2} = \cos\alpha \text{ and } S_{v1} = \cos\beta, S_{v2} = \sin\beta,$$

this yields

$$S_{m1} = \sin\alpha\cos\beta - \cos\alpha\sin\beta = \sin(\alpha-\beta)$$

$$S_{m2} = \cos\alpha\cos\beta + \sin\alpha\sin\beta = \cos(\alpha-\beta)$$

For a real input signal S_i and hence $S_{i1} = S_{i2}$, the above-mentioned formulas thus yield both the difference and the sum frequency.

The mixer M is used, inter alia, for shifting the frequency, for example to the baseband. This is achieved by mixing the components S_{i1} and S_{i2} of the input signal S_i with the components S_{v1} and S_{v2} of the oscillator signal S_v from the controlled oscillator V.

For demodulating AM signals, no separate circuits for generating the carrier and demodulating the signal are required in the demodulation unit according to the invention. In an embodiment of the mixer as a circular CORDIC, these functions are

interwoven because the multipliers for the demodulation function are also product detectors for the PLL. For example, AM signals are supplied at the outputs O_1 and O_2 of the demodulation unit DEM (see Fig. 1.).

5 The signals S_{m1} and S_{m2} are subsequently filtered by means of the low-pass filters L_1 and L_2 (see Fig. 1).

By incorporating the low-pass filters in the two signal paths, it will be possible to separately filter each mixed component for filtering the sum frequency(ies) which have been added by mixing for the case where the input signals are real signals. If the input signals are complex signals, but not ideal signals, the components should also be filtered
10 before the division takes place.

Furthermore, the filters have the customary loop filter function of a PLL.

In this embodiment, the inputs of the divider D convey the signals S_{d1} and S_{d2} . After division, the signal S_{del} is obtained. The signal S_{del} is applied to the controlled oscillator V and will be further available at the output O3 as signal S_{o3} (for example, an FM
15 signal).

The signals S_{i2} , S_{m1} , S_{d1} and S_{v1} represent the cos-component (in-phase component) of the relevant complex signal, and the signals S_{i1} , S_{m2} , S_{d2} and S_{v2} represent the sin-component (quadrature component) of the relevant complex signal.

By incorporating the divider DEL in the PLL, amplitude variations of the
20 input signal S_i are prevented from influencing the control signal (S_{del}) of the PLL and, hence, the lock-in range of the PLL.

The demodulation unit DEM according to the invention may be used in radio, television and communication receivers, etc. The demodulation unit may be used in, for example a receiver for receiving a modulated carrier with asymmetrical side bands (PHN
25 16.471), a receiver for receiving multistandard signals (PHN 16.489), etc.

The divider DEL may also be implemented with, for example a linear CORDIC providing also a safeguard for division by "0".

To improve the operation of the demodulation unit DEM and notably the PLL, it is advantageous to incorporate an extra control in the control loop, preventing the
30 PLL from "jumping" between 0° and 180° , which impedes the lock-in. In this case, the output signal S_{del} of the divider DEL is applied to the oscillator V via a multiplexer. The output of the multiplexer is fed back via a flipflop to a second input of the multiplexer.

In this embodiment, the sign bit of the signal S_{d2} (the msb bit in a two's complement) is applied to the control input of the multiplexer, so that the multiplexer applies

the signal S_{del} to the oscillator V in the case of a positive signal S_{d2} and applies the signal stored in the flipflop to the oscillator in the case of a negative signal S_{d2} . Consequently, the PLL will lock in much better and synchronize to, for example the zero-crossing of the tan function.

5 It is of course also possible to apply the signal S_{del} in an unchanged form to the oscillator at a negative signal S_{d2} , and to apply the signal stored in the flipflop at a positive signal S_{d2} .

 It will be evident that a demodulation unit, a divider and a mixer, a receiver, and a method according to the invention may be adapted in any way within the
10 protective scope of the present invention.

 Reference numerals in the claims should not be construed as limiting these claims.

 Instead of the hardware embodiment shown, it is also possible to incorporate the different functions in a CPU. The functions are then software-controlled.

15 The invention provides the possibility of improving the operation of the demodulation unit and simultaneously simplifying the demodulation unit and the PLL. This is achieved by incorporating a divider in the PLL, with which variations of the PLL control signal due to amplitude variations of the input signal are prevented.

Claims

1. A demodulation unit for demodulating a quadrature input signal having at least two components, comprising
 - a controlled oscillator for supplying a quadrature oscillator signal in dependence upon a control signal, and
 - 5 a mixer for mixing the quadrature input signal with the quadrature oscillator signal from the controlled oscillator, and for supplying at least two mixed components, the mixer and the oscillator being incorporated in a PLL, characterized in that the PLL also comprises
 - a divider for dividing the at least two mixed components by each other and for
 - 10 supplying the output signal as a control signal to the oscillator, and
 - a filtering unit for filtering one or more components and/or signals.
2. A demodulation unit as claimed in claim 1, characterized in that the divider comprises a linear CORDIC.
3. A demodulation unit as claimed in claim 1, characterized in that the mixer
- 15 comprises a circular CORDIC.
4. A demodulation unit as claimed in claim 1, characterized in that the filtering unit comprises a first and a second low-pass filter (L_1 , L_2) which are coupled between the mixer and the divider.
5. A demodulation unit as claimed in claim 1, characterized in that the PLL
- 20 incorporates a multiplexer and a flipflop for applying only the output signal of the divider to the controlled oscillator in the case of either a positive or a negative value of a mixed component received at one of the inputs of the divider, whereas in the other case, the value stored in the flipflop is supplied.
6. A divider for use in a demodulation unit, characterized in that the divider
- 25 is adapted to divide at least two mixed components by each other and to supply the output signal as a control signal.
7. A mixer for use in a demodulation unit, characterized in that the mixer is adapted to mix a quadrature input signal with a quadrature oscillator signal and to supply at least two mixed components.

8. A receiver comprising a tuner for converting a signal to be received into a signal to be demodulated, and a complex input filter for converting the signal to be demodulated into a quadrature signal to be demodulated, characterized in that the receiver comprises a demodulation unit as claimed in claim 1.

5 9. A method of demodulating a quadrature input signal having at least two components, wherein a quadrature oscillator signal is supplied in dependence upon a control signal, and

the quadrature input signal is mixed with the quadrature oscillator signal, and wherein at least two mixed components are supplied,

10 characterized in that the method further comprises the steps of

dividing the at least two mixed components by each other and supplying the output signal as a control signal for generating the oscillator signal, and

filtering one or more components and/or signals.




FIG. 1




FIG. 2