

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
26 October 2006 (26.10.2006)

PCT

(10) International Publication Number
WO 2006/113873 A2

(51) International Patent Classification:

H04B 1/713 (2006.01)

(21) International Application Number:

PCT/US2006/014879

(22) International Filing Date: 19 April 2006 (19.04.2006)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:

60/672,575	19 April 2005 (19.04.2005)	US
60/691,755	16 June 2005 (16.06.2005)	US
11/209,246	22 August 2005 (22.08.2005)	US

(71) Applicant (for all designated States except US): **QUALCOMM INCORPORATED** [US/US]; 5775 Morehouse Drive, San Diego, California 92121 (US).

(72) Inventor; and

(75) Inventor/Applicant (for US only): **PALANKI, Ravi** [IN/US]; 7699 Palmilla Drive, #3209, San Diego, California 92122 (US).

(74) Agents: **WADSWORTH, Philip, R.** et al.; 5775 Morehouse Drive, San Diego, California 92121 (US).

(81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM,

AT, AU, AZ, BA, BB, BG, BR, BW, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, LY, MA, MD, MG, MK, MN, MW, MX, MZ, NA, NG, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SM, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.

(84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LT, LU, LV, MC, NL, PL, PT, RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Declarations under Rule 4.17:


- as to applicant's entitlement to apply for and be granted a patent (Rule 4.17(ii))
- as to the applicant's entitlement to claim the priority of the earlier application (Rule 4.17(iii))

Published:

- without international search report and to be republished upon receipt of that report

[Continued on next page]

(54) Title: FREQUENCY HOPPING DESIGN FOR SINGLE CARRIER FDMA SYSTEMS



(57) **Abstract:** Systems and methodologies are described that facilitate frequency hopping in a single carrier FDMA wireless environment by dynamically altering user offsets with time to obtain interference diversity. A channel tree can be utilized with nodes that are assigned values. User devices can be assigned to such nodes, a path between an assigned node and a root node in the channel tree can be evaluated, and a table lookup can be performed to determine an identity of a subcarrier set to assign to the user device assigned to a given node, as well as a number of subcarriers to be assigned to the user device. Additionally, node values can be dynamically varied during a communication event to alter path values and thus alter subcarrier set assignments.



For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

FREQUENCY HOPPING DESIGN FOR SINGLE CARRIER FDMA SYSTEMS

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] This application claims benefit under 35 U.S.C. § 119(e) from U.S. Provisional Patent application Serial No. 60/672,575 entitled Frequency Hopping In Interleaved Frequency Division Multiple Access Communication Systems, and filed April 19, 2005, and Provisional Patent Application Serial No. 60/691,755 filed June 15, 2005 the entirety of which is hereby incorporated by reference.

Reference to Co-Pending Applications for Patent

[0002] The present Application for Patent is related to the following co-pending U.S. Patent Application Serial No. 11/173,873, filed June 30, 2005 assigned to the assignee hereof, and expressly incorporated by reference herein.

BACKGROUND

I. Field

[0003] The following description relates generally to wireless communications, and more particularly to mitigating interference between user devices in nearby communication sectors by employing frequency hopping in a single carrier FDMA network environment.

II. Background

[0004] Wireless communication systems have become a prevalent means by which a majority of people worldwide has come to communicate. Wireless communication devices have become smaller and more powerful in order to meet consumer needs and to improve portability and convenience. The increase in processing power in mobile devices such as cellular telephones has lead to an increase in demands on wireless network transmission systems. Such systems typically are not as easily updated as the cellular devices that communicate there over. As mobile device capabilities expand, it can be difficult to maintain an older wireless network system in a manner that facilitates fully exploiting new and improved wireless device capabilities.

[0005] More particularly, frequency division based techniques typically separate the spectrum into distinct channels by splitting it into uniform chunks of bandwidth, for example, division of the frequency band allocated for wireless communication can be

split into 30 channels, each of which can carry a voice conversation or, with digital service, carry digital data. Each channel can be assigned to only one user at a time. One known variant is an orthogonal frequency division technique that effectively partitions the overall system bandwidth into multiple orthogonal subbands. These subbands are also referred to as tones, carriers, subcarriers, bins, and frequency channels. Each subband is associated with a subcarrier that can be modulated with data. With time division based techniques, a band is split time-wise into sequential time slices or time slots. Each user of a channel is provided with a time slice for transmitting and receiving information in a round-robin manner. For example, at any given time t , a user is provided access to the channel for a short burst. Then, access switches to another user who is provided with a short burst of time for transmitting and receiving information. The cycle of "taking turns" continues, and eventually each user is provided with multiple transmission and reception bursts.

[0006] A typical wireless communication network (*e.g.*, employing frequency, time, and code division techniques) includes one or more base stations that provide a coverage area and one or more mobile (*e.g.*, wireless) terminals that can transmit and receive data within the coverage area. A typical base station can simultaneously transmit multiple data streams for broadcast, multicast, and/or unicast services, wherein a data stream is a stream of data that can be of independent reception interest to a mobile terminal. A mobile terminal within the coverage area of that base station can be interested in receiving one, more than one or all the data streams carried by the composite stream. Likewise, a mobile terminal can transmit data to the base station or another mobile terminal. Such communication between base station and mobile terminal or between mobile terminals can be degraded due to channel variations and/or interference power variations. For example, the aforementioned variations can affect base station scheduling, power control and/or rate prediction for one or more mobile terminals.

[0007] In the case of OFDMA-based systems, the particular waveforms and power required to transmit communication signals thereon typically exhibit an undesirably high peak-to-average ratio (PAR), which limits the coverage of OFDMA systems due to the inefficiencies of non-linear power amplifiers. Single carrier FDMA systems can mitigate problems associated with an undesirably high PAR, but are still subject to a variety of limitations that create a need in the art for a system and/or methodology of

mitigating interference between mobile devices and/or sectors in such wireless network systems.

SUMMARY

[0008] The following presents a simplified summary of one or more embodiments in order to provide a basic understanding of such embodiments. This summary is not an extensive overview of all contemplated embodiments, and is intended to neither identify key or critical elements of all embodiments nor delineate the scope of any or all embodiments. Its sole purpose is to present some concepts of one or more embodiments in a simplified form as a prelude to the more detailed description that is presented later.

[0009] According to an aspect, a method of generating transmission symbols can comprise generating at least one single-carrier FDMA symbol, assigning a set of subcarriers to transmit the at least one symbol, generating at least one other single carrier FDMA symbol, and varying subcarrier set assignments according to a predetermined pattern for transmission of the at least one other single-carrier FDMA symbol. Varying the subcarrier set assignments can comprise changing an assignment of at least one offset in a predetermined set of offsets. The predetermined pattern can be delineated by transmission of a number of frames, expiration of a time period, *etc.*, and subcarrier set assignments can be varied at fixed intervals delineated by the transmission of a predetermined number of single-carrier FDMA symbols. Additionally, assigning subcarriers to a user device can comprise generating a channel tree including a plurality of nodes, assigning each child node a node value that represents a non-negative integer, and assigning a user device to a node in the channel tree to define the subcarrier set assigned to the user device.

[0010] According to another aspect, an apparatus that facilitates frequency hopping for single carrier FDMA communication can comprise a memory and a processor coupled with the memory, the processor configured to assign an offset to a user device and to vary the offset for the user device according to a predetermined pattern. Nodes in the channel tree can be assigned values, and the processor can read the channel tree along a path from the node assigned to the user device to the first child node of a root node in the channel tree and evaluate a value for the path. Additionally, the processor can be further configured to perform a table lookup to identify an offset corresponding to the value of the path from the node assigned to the user device to the root node and assigns

to at least one of the user devices the identified offset. The user device can thus be assigned an offset corresponding to the value of the path to the node assigned to the user device from the root node. The processor can periodically permute node value assignments of one or more nodes in the channel tree to change the offset of the user device by changing the value of the path from the user-assigned node to the root node.

[0011] According to yet another aspect, an apparatus can comprise means for generating at least one single-carrier FDMA symbol, means for assigning a set of subcarriers to transmit the at least one symbol, means for generating at least one other single carrier FDMA symbol, and means for varying subcarrier set assignments, according to a predetermined pattern for transmission of the at least one other single-carrier FDMA symbol. The means for assigning can comprise means for allocating a node in a channel tree to the user device and means for assigning a value to each node in the channel tree and means for reading a path in the channel tree from an allocated user node to a root node to determine a value for nodes in the path that identifies the set of subcarriers to assign to the user device and a number of subcarriers to include in the set. The means for varying subcarrier set assignments can periodically alter values assigned to one or more nodes in the channel tree to vary the value of the path between the allocated user node and the root node. The means for assigning can assign a new set of subcarriers associated with the varied value of the path from the allocated user node to the root node upon variation by the means for varying subcarrier set assignments.

[0012] Yet another aspect relates to a computer-readable medium having stored thereon computer-executable instructions for assigning an offset-related entity to a user device and periodically varying the offset for the user device based at least in part on the assigned entity. The computer-readable medium can further comprise instructions for assigning a value to each node of a channel tree, allocating a node to at least one user device to assign a subcarrier set to the at least one user device, and permuting node values according to a pattern to change the subcarrier set assigned to the at least one user device.

[0013] Still another aspect relates to a wireless communication device that comprises a memory comprising information corresponding to a plurality of offset assignments for transmission of single-carrier FDMA symbols and a processor, coupled with the memory, the processor configured to vary the offset assignments according to a predetermined pattern based upon the information. The information can correspond to

values for nodes of a channel tree, and the nodes can correspond to root nodes and child nodes. Additionally, the channel tree can be a non-binary channel tree wherein each node has one or more child nodes. Moreover, node values can correspond to values generated by reading the channel tree along a path from the node assigned to the user device to the first child node of a root node in the channel tree and evaluating a value for the path. Information related to node values, offsets, assignments, and the like can be stored in a look-up table in the wireless communication device.

[0014] To the accomplishment of the foregoing and related ends, the one or more embodiments comprise the features hereinafter fully described and particularly pointed out in the claims. The following description and the annexed drawings set forth in detail certain illustrative aspects of the one or more embodiments. These aspects are indicative, however, of but a few of the various ways in which the principles of various embodiments may be employed and the described embodiments are intended to include all such aspects and their equivalents.

BRIEF DESCRIPTION OF THE DRAWINGS

[0015] FIG. 1 illustrates a binary channel tree that can be employed in conjunction with a single carrier FDMA network to facilitate varying user device offsets in accordance with various aspects.

[0016] FIG. 2 is an illustration of a binary channel tree that facilitates determining an offset for a user in a single carrier FDMA wireless communication environment in accordance with various aspects. .

[0017] FIG. 3 is an illustration of a non-binary channel tree wherein user devices are allocated nodes in the tree and each node is assigned a value in accordance with various aspects.

[0018] FIG. 4 illustrates a system that facilitates frequency hopping in a single carrier FDMA wireless communication environment in accordance with one or more aspects.

[0019] FIG. 5 is an illustration of a system that facilitates employing a frequency hopping technique in a single carrier FDMA environment, such as an IFDMA wireless communication environment in accordance with various aspects.

[0020] FIG. 6 is an illustration of a system that facilitates employing a frequency hopping technique in a single carrier FDMA environment, such as an LFDMA wireless communication environment in accordance with various aspects.

[0021] FIG. 7 is an illustration of a system that facilitates frequency hopping in a single carrier FDMA wireless communication environment in accordance with various aspects.

[0022] FIG. 8 is an illustration of a system that facilitates frequency hopping technique in an FDMA wireless communication environment in accordance with various aspects.

[0023] FIG. 9 is an illustration of a methodology for generating a signal using an IFDMA protocol, such as can be employed in conjunction with a frequency hopping protocol to improve interference diversity.

[0024] FIG. 10 is an illustration of a methodology for performing frequency hopping in conjunction with an IFDMA modulation protocol in accordance with one or more aspects.

[0025] FIG. 11 illustrates a methodology for generating a signal using an LFDMA protocol, such as can be employed in conjunction with a frequency hopping protocol in accordance with one or more aspects.

[0026] FIG. 12 illustrates a methodology for altering offset assignments for users in an LFDMA wireless communication environment in accordance with one or more aspects.

[0027] FIG. 13 is an illustration of a wireless network environment that can be employed in conjunction with the various systems and methods described herein in accordance with one or more aspects.

DETAILED DESCRIPTION

[0028] Various embodiments are now described with reference to the drawings, wherein like reference numerals are used to refer to like elements throughout. In the following description, for purposes of explanation, numerous specific details are set forth in order to provide a thorough understanding of one or more embodiments. It may be evident, however, that such embodiment(s) may be practiced without these specific details. In other instances, well-known structures and devices are shown in block diagram form in order to facilitate describing one or more embodiments.

[0029] As used in this application, the terms “component,” “system,” and the like are intended to refer to a computer-related entity, either hardware, a combination of hardware and software, software, or software in execution. For example, a component may be, but is not limited to being, a process running on a processor, a processor, an object, an executable, a thread of execution, a program, and/or a computer. One or more components may reside within a process and/or thread of execution and a

component may be localized on one computer and/or distributed between two or more computers. Also, these components can execute from various computer readable media having various data structures stored thereon. The components may communicate by way of local and/or remote processes such as in accordance with a signal having one or more data packets (*e.g.*, data from one component interacting with another component in a local system, distributed system, and/or across a network such as the Internet with other systems by way of the signal).

[0030] Furthermore, various embodiments are described herein in connection with a subscriber station. A subscriber station can also be called a system, a subscriber unit, mobile station, mobile, remote station, access point, base station, remote terminal, access terminal, user terminal, user agent, a user device, or user equipment. A subscriber station may be a cellular telephone, a cordless telephone, a Session Initiation Protocol (SIP) phone, a wireless local loop (WLL) station, a personal digital assistant (PDA), a handheld device having wireless connection capability, or other processing device connected to a wireless modem.

[0031] Moreover, various aspects or features described herein may be implemented as a method, apparatus, or article of manufacture using standard programming and/or engineering techniques. The term "article of manufacture" as used herein is intended to encompass a computer program accessible from any computer-readable device, carrier, or media. For example, computer readable media can include but are not limited to magnetic storage devices (*e.g.*, hard disk, floppy disk, magnetic strips...), optical disks (*e.g.*, compact disk (CD), digital versatile disk (DVD)...), smart cards, flash memory devices (*e.g.*, card, stick, key drive...), and integrated circuits such as read only memories, programmable read only memories, and electrically erasable programmable read only memories.

[0032] In order to facilitate frequency hopping, a single carrier FDMA modulation technique can be employed in a wireless network. For example, interleaved frequency division multiplexing (IFDM) can be employed to retain the benefits associated with orthogonal frequency division multiplexing (OFDM) protocols. In addition, in some cases, single carrier FDMA modulation techniques may have a lower peak-to-average (PAR) ratio problem compared with OFDM. Similarly, according to a related aspect, localized frequency division multiplexing (LFDM) can be employed, which can also exhibit a lower PAR while retaining other benefits associated with OFDM protocols.

LFDMA is also known as “narrow-band” FDMA, Classical FDMA, or just FDMA, and is a single carrier FDMA protocol.

[0033] OFDMA modulation symbols are in the frequency domain, and therefore the time domain signal obtained by performing a fast Fourier technique on the modulation symbol sequence can have an undesirably high PAR. By comparison, IFDMA modulation symbols are in the time domain, and therefore IFDMA modulation techniques do not exhibit the high PARs typically associated with OFDMA techniques. Thus, IFDMA (and similarly LFDMA) modulation protocols reduce undesirably high PAR and problems associated therewith.

[0034] In an IFDMA system, a total of N_{FFT} subcarriers can be utilized, which are divided among a plurality of users. Each user can be allocated N carriers (where N can vary from user to user), as well as a user-specific subcarrier offset, U . Thus, a user with offset U occupies carriers $\{U, U+N_{\text{FFT}}/N, U+2N_{\text{FFT}}/N \dots U+(N-1)N_{\text{FFT}}/N\}$. For example, in an IFDMA system a total of N_{FFT} subcarriers can be divided among several users. Each user can be allocated N carriers (where N can vary from user device to user device), as well as a user device-specific subcarrier offset, U , where $0 \leq U < N_{\text{FFT}}/N$. When a user device transmits N modulation symbols $[d_0 d_1 d_2 \dots d_{N-1}]$, the user device constructs an IFDMA symbol by performing the following acts:

(1) Repeating the N symbols to obtain a total of N_{FFT} symbols

$$[d_0 d_1 d_2 \dots d_{N-1} d_0 d_1 d_2 \dots d_{N-1} d_0 d_1 d_2 \dots d_{N-1} \dots d_0 d_1 d_2 \dots d_{N-1}]$$

(2) Multiplying the k^{th} symbol in the sequence by $e^{-j k \Phi U}$ where $\Phi = 2\pi / N_{\text{FFT}}$

$$[d_0 d_1 e^{-j\Phi U} d_2 e^{-2j\Phi U} \dots d_{N-1} e^{-(N-1)j\Phi U} \dots d_{N-2} e^{-(N_{\text{FFT}}-2)j\Phi U} d_{N-1} e^{-(N_{\text{FFT}}-1)j\Phi U}]$$

(3) Optionally copying the last N_{CP} symbols of the above symbol to the beginning (cyclic prefix)

$$[\dots d_{N-2} e^{-(N_{\text{FFT}}-2)j\Phi U} d_{N-1} e^{-(N_{\text{FFT}}-1)j\Phi U}] [d_0 d_1 e^{-j\Phi U} \dots d_{N-1} e^{-(N-1)j\Phi U} \dots d_{N-1} e^{-(N_{\text{FFT}}-1)j\Phi U}]$$

[0035] A resulting IFDMA symbol can then be converted to an analog symbol modulated using a carrier and transmitted in a manner similar to that in which an OFDMA symbol is transmitted. The foregoing is illustrative of IFDMA symbol generation on both a reverse link and a forward link. Additionally, since the IFDMA

signal is periodic in the time domain (with the exception of the phase, $e^{-jk\Phi U}$), the signal can occupy a “comb” in frequency (*e.g.*, only a set of N equally spaced subcarriers have a non-zero power, ...). More specifically, a user with offset U occupies the set of subcarriers $\{U, U+N_{\text{FFT}}/N, U+2N_{\text{FFT}}/N \dots U+(N-1)N_{\text{FFT}}/N\}$, wherein the total set of subcarriers is indexed from 0 to $N_{\text{FFT}}-1$, such that user device orthogonality can be maintained because user devices with different offsets occupy different subcarrier sets.

[0036] Similarly, in an LFDMA system, a user can be allocated a number N of contiguous subcarriers (*e.g.*, subcarriers that are consecutive in the frequency domain, ...). For example, a total of N_{FFT} subcarriers can exist, which can be divided among several users. Each user can be allocated a user-specific subcarrier offset, U , such that a user with offset U occupies carriers $[U, U+1, \dots, U+N-1]$. a user can be allocated a number N of contiguous subcarriers (*e.g.*, subcarriers that are consecutive in the frequency domain, ...). Each user can be allocated N contiguous carriers (where N can vary from user device to user device), as well as a user-specific subcarrier offset, U , where $0 \leq U < N_{\text{FFT}}-N$, and where the total set of subcarriers is indexed from 0 to $N_{\text{FFT}}-1$. A user that transmits a set of N modulation symbols $[d_0 d_1 d_2 \dots d_{N-1}]$ can generate a transmission signal by performing the following acts:

- (1) Taking an N -point fast Fourier transform (FFT) of $[d_0 d_1 d_2 \dots d_{N-1}]$ to obtain $[D_0 D_1 D_2 \dots D_{N-1}]$
- (2) Placing $[D_0 D_1 D_2 \dots D_{N-1}]$ in the allocated sub-carriers $[U, U+1, \dots U+N-1]$.
- (3) Taking an N_{FFT} -point inverse fast Fourier transform to obtain N_{FFT} time domain samples.
- (4) Optionally copying the last N_{CP} time domain samples to the beginning of the symbol as a cyclic prefix to obtain the LFDMA time domain symbol.

[0037] Referring now to the drawings, **Fig. 1** illustrates a binary channel tree 100 that can be employed in conjunction with a single carrier FDMA network to facilitate varying user device offsets in accordance with various aspects. The tree 100 comprises a plurality of nodes, each of which can be associated with a user device. For example, a

first node 102 is associated with user A, and nodes 104 and 106 are assigned to users B and C, respectively. Various embodiments described herein facilitate changing user offsets, *e.g.* hopping sets of offset subcarriers. User offset variations can be performed using symbol rate hopping techniques (*e.g.*, varied upon transmission of each symbol), block hopping techniques (*e.g.*, varied upon transmission of a plurality of symbols), and the like. Additionally, a lookup table comprising information related to offsets, subcarrier sets, *etc.*, can be employed to facilitate assigning and varying assignment of offsets to users. Offset assignment variation can be performed according to a predefined pattern, such as upon transmission of a single symbol, a predetermined number of symbols, a variable number of symbols, a fixed or variable time period, a fixed or variable number of frames, *etc.*

[0038] When employing an IFDMA protocol or an LFDMA protocol, in a system with $N_{\text{FFT}} = 2^n$ assignable subcarriers, a particular user may be allotted $N = 2^m$ subcarriers (where m is less than or equal to n). Additionally, different users can have different values of m . The binary tree 100 can facilitate assigning user offsets despite the variance of m between users. For instance, each user can be assigned a node in the tree 100 as described above. A tree-reading algorithm can be employed to compute an offset for a given user. Embodiments of such algorithms and approaches are discussed with regard to Fig. 2.

[0039] Additionally, in conjunction with various aspects set forth herein, offset assignment can be a function of a permutation protocol by which a predetermined set of offsets is permuted through nodes in a channel tree, and thus permuted through a set of user devices, allocated to nodes in the channel tree. For instance, nodes in channel tree 100 can be assigned a first set of offsets, and such offset assignments can be varied according to a predetermined pattern (*e.g.*, every frame, every 2 frames, every symbol or group thereof, every one or more nanoseconds, *etc.*). Additionally, permutation protocols, predetermined offset sets, schedules, and the like can be unique to individual sectors and/or regions in a wireless network.

[0040] Fig. 2 is an illustration of a binary channel tree 200 that facilitates determining an offset for a user in a single carrier FDMA wireless communication environment in accordance with various aspects. Tree 200 comprises a plurality of nodes, each of which has either a “0” value or “1” value. Nodes can be assigned to users of the

wireless network, and offsets for each user can be evaluated by reading tree 200 in either an upward or downward direction.

[0041] For example, when employing an IFDMA protocol in conjunction with the wireless network, a “0” and a “1” are assigned to each child of a parent node. The assignment can vary from time to time and from sector to sector, in order to facilitate frequency hopping and interference diversity. The offset, U , of each user of the IFDMA-based network is the sequence read upward from the user-assigned node, wherein the user-assigned node represents the most significant bit in the offset U , and the root node’s child node represents the least significant bit in the offset U . Thus, user A has offset 1, because it is assigned the first child node of the root node. User B has offset 0, as the most significant bit in user B’s offset is a “0” and is read upward through the “0” child node of the root node, for an overall value of “00.” User C has offset 2, as user C is assigned a “1” node that is read upward through the “0” child node of the root node for a total value of 10 binary, or 2 decimal. Information related to offsets associated with user-assigned nodes can be retrieved from a lookup table comprising such information upon assignment of a particular offset to a user.

[0042] Additionally, user device node allocation can be related to a number of subcarriers required by the particular user device. For instance, user A is allocated to a first child node in tree 200 such that there are two bits in user A’s lineage (*e.g.*, user A’s allocated child node and the root node). In a scenario in which N_{FFT} is 512 (*e.g.* a 9-bit-deep tree), user A can have a subcarrier requirement of at least $N_{FFT}/2$. Users B and C have a lineage three bits long, including the root node, and so are positioned on a third binary bit that represents a decimal value of 4. Thus, users B and C’s offsets can comprise a number of subcarriers equal to $N_{FFT}/4$, and so on. It will be appreciated that the number of bits, nodes, users, total subcarriers, and the like described herein are illustrative in nature and should not be interpreted in a limiting sense and may also vary by the system design parameters. Rather, the various embodiments, aspects, systems, methods, techniques, *etc.*, set forth herein can employ any suitable number of the above in order to achieve interference diversity and frequency hopping.

[0043] According to a related example, when employing an LFDMA protocol, the binary tree 200 can be read from top to bottom to determine a user’s offset. Node assignments of “0” and “1” can vary with time and between sectors in a wireless network. Thus, an offset for a user is an n -bit quantity that can be padded with 0s for

the least significant bits if necessary. When reading tree 200 in a downward direction, user A has offset 2 (*e.g.*, 10 binary), user B has offset 0 (*e.g.*, 00 binary), and user C has offset 1 (*e.g.*, 01 binary). Information related to such offsets can be gleaned from a lookup table and can correspond to, in this example, $N_{\text{FFT}}/2$, 0, and $N_{\text{FFT}}/4$, respectively. Numbers of subcarriers associated with respective offsets can then be assigned to users.

[0044] It will be appreciated by one skilled in the art that although various embodiments described herein relate to IFDMA and LFDMA protocols, such embodiments can be employed in conjunction with any suitable OFDMA system. Additionally, the binary value assignments of some nodes and their ancestors can be performed on a sector-independent basis, such that a user allocated to such a node can retain the same offset regardless of which sector the user is in. In this manner, frequency reuse can be supported, for example when sectors do not use such nodes, while sectors that do employ such nodes can allocate weaker users thereto.

[0045] Fig. 3 is an illustration of a non-binary channel tree 300 wherein user devices are allocated nodes in the tree and each node is assigned a value in accordance with various aspects. Non-binary channel tree 300 is similar to the binary assignment tree described with regard to Fig. 2. However, node assignments within channel tree 300 are not limited to binary values of 1 or 0, but rather can comprise any non-negative integer. For example, for a node having four children, the child nodes can be assigned values 0-3, (*e.g.*, binary values 00, 01, 10, and 11, integer values of 0, 1, 2, and 3, *etc.*), while a parent node with only a pair of child nodes can have its children assigned values of 0 and 1, as set forth with regard to the binary channel tree of Fig. 2.

[0046] In non-binary channel tree 300, a number of subcarriers corresponding to a particular node can depend not only on the distance of the node to the root node, but also on the number of sibling nodes of each ancestor of the particular node. For instance, node A can have $N_{\text{FFT}}/16$ carriers because node A's parent is one of four siblings, and therefore receives $N_{\text{FFT}}/4$ subcarriers, which are then further divided into fourths among the four children of node A's parent (*e.g.*, node A and its three siblings), which results in an assignment to node A of $1/4$ of $N_{\text{FFT}}/4$, or $N_{\text{FFT}}/16$ subcarriers. Node B can be assigned $N_{\text{FFT}}/8$ subcarriers because it has one sibling and its parent is one of four siblings. Thus, node B can be assigned $1/2$ of its parent's $N_{\text{FFT}}/4$ subcarrier assignment, or $N_{\text{FFT}}/8$ subcarriers. Nodes C and D, being nodes in a set of four siblings directly pendant from the root node of non-binary channel tree 300, can each receive a

subcarrier assignment equal to $N_{\text{FFT}}/4$. Information related to nodal relationships, offsets and/or subcarrier sets, and the like, can be stored in a lookup table that can be traversed in order to determine a user's assigned offset. It will be appreciated that the non-binary channel tree can be employed to facilitate assigning either or both of IFDMA and LFDMA subcarrier sets.

[0047] When performing offset computation in conjunction with an IFDMA communication environment, offsets can be computed by reading channel tree 300 from bottom to top. For instance, node A has an offset of 1101 when read through its parent toward the root node, and can be assigned offset 13 comprising $N_{\text{FFT}}/16$ subcarriers. Node D can receive offset 2 (e.g., 10 binary). It will be noted that nodes B and C are depicted as having offset values of 3 (e.g., 011, and 11, respectively). In such a scenario, both nodes can be assigned offset 3, and will not be assigned such offset simultaneously, but rather alternately in order to mitigate conflict.

[0048] In an LFDMA communication environment, offsets can be computed by reading the non-binary channel tree 300 from top to bottom (e.g., from a root node down through to a particular child node). A 0-padding technique can be employed to pad the offset values read from the root node to the child node based at least in part on a value of N_{FFT} . For example, if $N_{\text{FFT}} = 512$, then a total of 9 bits are required to represent N_{FFT} as a binary number. 0-padding can be employed to pad each offset read with zeros until the offset is a 9-bit value. For example, A has an offset of 0111 when read from the root node to node A, which can be padded with 5 zeros to make A's offset a 9-bit number, 0111-00000 = 224. Thus node A can be assigned offset 224, which, according to the example, will comprise $512/16$, or 32, carriers. Similarly, node B has offset 011-000000 = 192, node C has offset 11-0000000 = 384, and node D has offset 10-00000000 = 256. Described more generally, node A has an offset equal to $9N_{\text{FFT}}/16$, node B is assigned offset to $3N_{\text{FFT}}/8$, node C is assigned offset to $3N_{\text{FFT}}/4$, and node D is assigned offset to $N_{\text{FFT}}/2$.

[0049] It will be appreciated that non-binary channel tree 300 can employ a set of predetermined offsets that can be permuted among user devices and/or nodes as described above with regard to Figure 1. Additionally, changing the offsets can be performed according to a predetermined pattern, (e.g., every frame, every symbol, upon expiration of a time period, etc.) and such schedules can be sector-specific.

[0050] With respect to Figs. 1-3, the assignments and hopping sequences of the nodes may be transmitted from a base station to a user device in initialization over time. This may be updated as appropriate. For example, assignments can be determined by reading the look-up tables at the user device for transmission to the base station, uplink, and for reception at the user device, downlink, based upon instructions transmitted from the base station. The instructions may, according to an aspect, comprise an identifier of a sequence, which may be repeated depending on the length of sequence that is stored at the user device. In other aspects, the node values may be updated regularly, based upon control channel messages from the base station.

[0051] In some embodiments, the channel assignments and single carrier transmissions may only apply to the uplink while the downlink transmissions use one or more OFDM schemes. In these cases, one or more OFDM type access schemes may be utilized on the downlink that are independent from the schemes utilized on the uplink.

[0052] Fig. 4 illustrates a system 400 that facilitates frequency hopping in a single carrier FDMA wireless communication environment in accordance with one or more aspects. A frequency hopping component 402 is operatively associated with a base station 408 (*e.g.*, an access point). Wireless network 404 can comprise one or more base stations 408 in one or more sectors and/or regions comprising a plurality of sectors, *etc.*, as will be appreciated by one skilled in the art. User devices 406 can comprise, without being limited to, cellular phones, smartphones, PDAs, laptop computers, personal computers, and/or any other suitable device with which a user can communicate over wireless network 404. A separate frequency hopping component 410 resides at the user device 406 and can vary the offsets according to instructions from frequency hopping component 402.

[0053] Frequency hopping component 402 can vary node value assignments for one or more user devices 406 allocated to nodes in a channel tree, such as the trees described with regard to Figs. 1, 2, and 3. Node values (*e.g.*, non-binary, binary, *etc.*) can be assigned to nodes in the channel tree and the tree can be traversed to determine an overall offset assignment. In the case of a binary channel tree, child nodes of each parent node in the channel tree can be assigned a 1 and a 0, such that each parent node has a 1-child and a 0-child. User devices 406 can be allocated to such nodes, and, depending on the particular single carrier FDMA protocol employed, frequency hopping component 402 can read the binary tree to evaluate user offset assignments and can

evaluate a lookup table comprising information related to respective offsets (*e.g.*, offset identity, subcarrier number, ...). Additionally, frequency hopping component 402 can change node value assignments (*e.g.*, 1s and 0s and/or other binary node values, non-binary node values, *etc.*) for different sectors and at different times in order to facilitate frequency hopping and alteration of user offset assignments. It is to be appreciated that frequency hopping component 402 can be integral to one or more base stations 408 in wireless network 404 and/or to user device(s) 406.

[0054] While Fig. 4, depicts the frequency hopping component 402 as residing in the base station, it should be noted that frequency hopping component 402 may be implemented as a combination of functionality in both base station 408, a base station controller (not shown), or the like of wireless network 404, and in user device 406 (*e.g.*, frequency hopping component 410). In such aspects, it may be possible to contain separate look-up tables in user device 406 and base station 408 which each correspond to offsets, which are known to both devices, *e.g.* by instructions from base station 408 that corresponds to user device 406, or some other means.

[0055] In various embodiments, where the frequency hopping component 402 resides in the base station 408, the user device 406 may have a look-up table that corresponds to a sequence for varying the offset U based upon instructions, commands, or the like transmitted from the base station 408 and generated by frequency hopping component 402.

[0056] **Fig. 5** is an illustration of a system 500 that facilitates employing a frequency hopping technique in a single carrier FDMA environment, such as an IFDMA wireless communication environment in accordance with one or more aspects. A frequency hopping component 502 is operatively associated with and integral to a base station 508. A separate frequency hopping component 512 resides at the user device 506 and will vary the offsets according to instructions from frequency hopping component 502.

[0057] Additionally, frequency hopping components 502 and 512 are respectively associated with an IFDMA components 510 and 514, which facilitates wireless communication using an IFDMA protocol. For example, in an IFDMA system a total of N_{FFT} subcarriers can be divided among several user devices 506. Each user device 506 can be allocated N carriers (where N can vary from user device to user device), as well as a user device-specific subcarrier offset, U , where $0 \leq U < N_{\text{FFT}}/N$. When a user

device 506 transmits N modulation symbols $[d_0 d_1 d_2 \dots d_{N-1}]$, user device 506 constructs an IFDMA symbol by performing the following acts:

- (1) Repeating the N symbols to obtain a total of N_{FFT} symbols

$$[d_0 d_1 d_2 \dots d_{N-1} d_0 d_1 d_2 \dots d_{N-1} d_0 d_1 d_2 \dots d_{N-1} \dots d_0 d_1 d_2 \dots d_{N-1}]$$

- (2) Multiplying the k^{th} symbol in the sequence by $e^{-j k \Phi U}$ where $\Phi = 2\pi / N_{\text{FFT}}$

$$[d_0 d_1 e^{-j \Phi U} d_2 e^{-2j \Phi U} \dots d_{N-1} e^{-(N-1)j \Phi U} \dots d_{N-2} e^{-(N_{\text{FFT}}-2)j \Phi U} d_{N-1} e^{-(N_{\text{FFT}}-1)j \Phi U}]$$

- (3) Optionally copying the last N_{CP} symbols of the above symbol to the beginning (cyclic prefix)

$$[\dots d_{N-2} e^{-(N_{\text{FFT}}-2)j \Phi U} d_{N-1} e^{-(N_{\text{FFT}}-1)j \Phi U}] [d_0 d_1 e^{-j \Phi U} \dots d_{N-1} e^{-(N-1)j \Phi U} \dots d_{N-1} e^{-(N_{\text{FFT}}-1)j \Phi U}]$$

[0058] A resulting IFDMA symbol can then be converted to an analog symbol modulated using a carrier and transmitted. The foregoing is illustrative of IFDMA symbol generation on both a reverse link and a forward link. Additionally, since the IFDMA signal is periodic in the time domain (with the exception of the phase, $e^{-j k \Phi U}$), the signal can occupy a “comb” in frequency (*e.g.*, only a set of N equally spaced subcarriers have a non-zero power, ...). More specifically, a user device 506 with offset U occupies the set of subcarriers $\{U, U+N_{\text{FFT}}/N, U+2N_{\text{FFT}}/N \dots U+(N-1)N_{\text{FFT}}/N\}$, wherein the total set of subcarriers is indexed from 0 to $N_{\text{FFT}}-1$, such that user device orthogonality can be maintained because user devices with different offsets occupy different subcarrier sets. Frequency hopping component 502 can generate, or store look-up tables that correspond to, offsets, node value assignments, *etc.*, and can assign user devices 506 to nodes as described with regard to Figs. 1-3. Additionally, where an IFDMA protocol is utilized, frequency hopping component 502 can read the tree from the root node downward to identify a particular user device’s offset U . It is to be appreciated that the manner of assigning user devices to particular nodes can encompass arbitrary assignments, node assignments in a channel tree using non-binary node values, binary node values, or any other suitable manner of associating offsets with nodes and/or user devices 506. Moreover, it will be understood that node value assignments can be varied arbitrarily, randomly, according to a predetermined pattern and/or upon an occurrence of an event (*e.g.* transmission of one or more symbols, one or more frames, expiration of a time period, ...) *etc.*

[0059] While Fig. 5 depicts the frequency hopping component 502 as residing in the base station, it should be noted that frequency hopping component 502 may be implemented as a combination of functionality in both base station 508, base station controller (not shown) and in user device 506 (*e.g.*, frequency hopping component 512). In such aspects, it may be possible to contain separate look-up tables in user device 506 and base station 508 which each correspond to sequences for offset U for the user device, which are known to both devices, *e.g.* by instructions from base station 508 that corresponds to user device 506, or some other means.

[0060] In the embodiments, where the frequency hopping component 502 resides in the base station 508, the user device 506 may have a look-up table that corresponds to a sequence for varying the offset U based upon instructions, commands, or the like transmitted from the base station 508 and generated by frequency hopping component 502.

[0061] **Fig. 6** is an illustration of a system 600 that facilitates employing a frequency hopping technique in a single carrier FDMA environment, such as an LFDMA wireless communication environment in accordance with one or more aspects. System 600 comprises a frequency hopping component 602 that is operatively associated with an access point 608. A separate frequency hopping component 614 resides at the user device 606 and will vary the offsets according to instructions from frequency hopping component 602.

[0062] Frequency hopping component 602 can be further operatively associated with an IFDMA component 610 that facilitates communication over wireless network 604 as described above with regard to Fig. 5. Additionally and/or alternatively, frequency hopping component 602 can be further operatively coupled to an LFDMA component 612, which can facilitate LFDMA communication between base station 608 and user device 606. Similarly, frequency hopping component 614 can be operatively coupled to an IFDMA component 616 and an LFDMA component 618 in user device 606.

Frequency hopping component 602 can generate a channel tree for offset assignment to user device 606, such that each of a plurality of user devices 606 can be allocated to a node in the offset tree. Each node in the tree can have a value, and such node values can be changed by frequency hopping component 602 from time to time and/or from sector to sector to provide interference diversity and frequency hopping functionality. Upon a determination of a value associated with a particular node, frequency hopping

component 602 can perform a table lookup to evaluate an associated offset for assignment to a user device 606.

[0063] With regard to LFDMA components 612 and 618, a user device 606 can be allocated a number N of contiguous subcarriers (*e.g.*, subcarriers that are consecutive in the frequency domain, ...). For example, in an LFDMA system a total of N_{FFT} subcarriers can be divided among several user devices 606. Each user device 606 can be allocated N contiguous carriers (where N can vary from user device to user device), as well as a user device-specific subcarrier offset, U , where $0 \leq U < N_{\text{FFT}} - N$, and where the total set of subcarriers is indexed from 0 to $N_{\text{FFT}} - 1$. A user device that transmits a set of N modulation symbols $[d_0 \ d_1 \ d_2 \ \dots \ d_{N-1}]$ can generate a transmission signal by performing the following acts:

- (1) Taking an N -point fast Fourier transform (FFT) of $[d_0 \ d_1 \ d_2 \ \dots \ d_{N-1}]$ to obtain $[D_0 \ D_1 \ D_2 \ \dots \ D_{N-1}]$
- (2) Placing $[D_0 \ D_1 \ D_2 \ \dots \ D_{N-1}]$ in the allocated sub-carriers $[U, U+1, \dots U+N-1]$.
- (3) Taking an N_{FFT} -point inverse fast Fourier transform to obtain N_{FFT} time domain samples.
- (4) Optionally copying the last N_{CP} time domain samples to the beginning of the symbol as a cyclic prefix to obtain the LFDMA time domain symbol.

[0064] In the above example of LFDMA signal generation, different user devices 606 can be allocated disjoint sets of subcarriers to ensure that user devices 606 are orthogonal to each other. Frequency hopping component 602 can then generate an assignment tree and evaluate assignments of user devices 606 to nodes therein as described with regard to Figs. 1-3, and, where an LFDMA protocol is utilized, can read the tree from the root node downward to identify a particular user device's offset, U .

[0065] While Fig. 6 depicts frequency hopping component 602 as residing in the base station, it should be noted that frequency hopping component 602 may be implemented as a combination of functionality in both base station 608, base station controller (not shown), or the like of wireless network 604, and in user device 606 (*e.g.*, frequency

hopping component 614). In such aspects, it may be possible to contain separate look-up tables in user device 606 and base station 608, which each correspond to sequences for offset U for the user device 606, which are known to both devices, *e.g.* by instructions from base station 608 that corresponds to the user device 606, or some other means.

[0066] In the embodiments, where the frequency hopping component 602 resides in the base station 608, the user device 606 may have a look-up table that corresponds to a sequence for varying the offset U based upon instructions, commands, or the like transmitted from the base station 608 and generated by frequency hopping component 602.

[0067] Additionally, IFDMA components 610 and 616 and LFDMA components 612 and 618 can be employed in conjunction with one another to facilitate generation of subcarrier assignments that comprise equally spaced subcarriers that span less than the total available bandwidth, in accordance with various aspects set forth herein.

Moreover, fast hopping techniques can be employed, potentially over a fraction of the available bandwidth when employing an IFDMA protocol. On a typical OFDMA uplink, a user device can be assigned a set of subcarriers, which is kept constant for a time to permit the user device to estimate the channel over that set of subcarriers.

However, if the user device's assignment is large enough that the user device can estimate the channel over the entire bandwidth, then a symbol rate hopping protocol (*e.g.*, varying a subcarrier set assignment for a user device upon transmission of each symbol) can be utilized because there is no detriment in hopping upon each symbol.

[0068] Fig. 7 is an illustration of a system 700 that facilitates frequency hopping in a single carrier FDMA wireless network environment. A frequency hopping component 702 may be operatively associated with a base station 708 in a wireless network 704. A separate frequency hopping component 718 resides at the user device 706 and can vary the offsets according to instructions from frequency hopping component 702.

[0069] Wireless network 704 can comprise one or more base stations 708 in one or more sectors and/or regions comprising a plurality of sectors, *etc.*, as will be appreciated by one skilled in the art. User devices 706 can comprise, without being limited to, cellular phones, smartphones, PDAs, laptop computers, personal computers, and/or any other suitable device with which a user can communicate over wireless network 704. Frequency hopping component 702 in base station 708 can be associated with an

IFDMA component 710 and/or an LFDMA component 712, or any other suitable single carrier FDMA system, to facilitate symbol generation as described above with regard to the preceding figures. Similarly, frequency hopping component 718 in user device 706 can be operatively coupled to each of an IFDMA component 720 and an LFDMA component 722.

[0070] Base station 708 and/or user device 706 can additionally and respectively comprise memories 714 and 724 that are operatively coupled to frequency hopping components 702 and 718, and that store information related to channel tree generation or pre-generated channel tree information that may be utilized, node value assignment (*e.g.*, non-binary, binary, integer, *etc.*) of nodes in the channel tree, user device node allocation, tree-reading algorithms (*e.g.*, top-down for LFDMA, bottom-up for IFDMA, ...), signal generation algorithms (*e.g.*, for generating signals using IFDMA, LFDMA, single carrier FDMA, ...), time tables for node value assignment variation (*e.g.*, frequency hopping, ...), lookup tables related to offset information and/or node value assignments, and any other suitable information related to providing interference diversity (*e.g.*, frequency hopping) to mitigate interference of one or more user devices 706. Processors 716 and 726 can be operatively connected to frequency hopping components 702 and 718, respectively, and/or memories 714 and 724 to facilitate analysis of information related to frequency hopping, node assignment and/or allocation to one or more user devices 706, tree-reading algorithms, signal generation, and the like. It is to be appreciated that processor 716 can be a processor dedicated to analyzing and/or generating information received by frequency hopping component 702, a processor that controls one or more components of base station 708, and/or a processor that both analyzes and generates information received by frequency hopping component 702 and controls one or more components of base station 708. In a similar manner, processor 726 can be a processor dedicated to analyzing information received by frequency hopping component 718, a processor that controls one or more components of user device 706, and/or a processor that both analyzes information received by frequency hopping component 718 and controls one or more components user device 706.

[0071] Memories 714 and 724 can additionally store protocols associated with generating signals, symbols, channel trees, lookup tables, *etc.*, such that user device 706 and/or base station 708 can employ stored protocols and/or algorithms to achieve

interference diversity as described herein. It will be appreciated that the data store (*e.g.*, memories) components described herein can be either volatile memory or nonvolatile memory, or can include both volatile and nonvolatile memory. By way of illustration, and not limitation, nonvolatile memory can include read only memory (ROM), programmable ROM (PROM), electrically programmable ROM (EPROM), electrically erasable ROM (EEPROM), or flash memory. Volatile memory can include random access memory (RAM), which acts as external cache memory. By way of illustration and not limitation, RAM is available in many forms such as synchronous RAM (SRAM), dynamic RAM (DRAM), synchronous DRAM (SDRAM), double data rate SDRAM (DDR SDRAM), enhanced SDRAM (ESDRAM), Synchlink DRAM (SLDRAM), and direct Rambus RAM (DRRAM). The memories 714 and 724 of the subject systems and methods is intended to comprise, without being limited to, these and any other suitable types of memory.

[0072] While Fig. 7 depicts frequency hopping component 702 as residing in the base station 708, it should be noted that frequency hopping component 702 may be implemented as a combination of functionality in both base station 708, base station controller (not shown), or the like of wireless network 704, and in user device 706 (*e.g.*, frequency hopping component 718). In such aspects, it may be possible to contain separate look-up tables in user device 706 and base station 708 which each correspond to sequences for offset U for the user device, which are known to both devices, *e.g.* by instructions from base station 708 that corresponds to the user device 706, or some other means.

[0073] In the embodiments, where the frequency hopping component 702 resides in the base station 708, the user device 706 may have a look-up table that corresponds to a sequence for varying the offset U based upon instructions, commands, or the like transmitted from the base station 708 and generated by frequency hopping component 702.

[0074] **Fig. 8** is an illustration of a system 800 that facilitates frequency hopping technique in an FDMA wireless network environment in accordance with various aspects. A frequency hopping component 802 is operatively associated with a base station 808. A separate frequency hopping component 824 resides at the user device 806 and can vary the offsets according to instructions from frequency hopping component 802.

[0075] Wireless network 804 can comprise one or more base stations 808, repeaters, transceivers, *etc.* (not shown) in one or more sectors and/or regions comprising a plurality of sectors, *etc.*, as will be appreciated by one skilled in the art. User devices 806 can comprise, without being limited to, cellular phones, smartphones, PDAs, laptop computers, personal computers, and/or any other suitable device with which a user can communicate over wireless network 804. Frequency hopping component 802 in base station 808 can be operatively associated with an IFDMA component 810 and/or an LFDMA component 812, or any other suitable single carrier FDMA system, to facilitate communication symbol generation as described above with regard to the preceding figures. Likewise, frequency hopping component 824 in user device 806 can be operatively associated with either or both of an IFDMA component 826 and an LFDMA component 828. Frequency hopping component 802 can be further associated with an assignment component 820 in base station 808 that assigns nodes to user devices 806, based at least in part on offset information stored in a lookup table, which can be retained in memory 814 and/or memory 830. Such assignments can be transmitted to an assignment receiver 822 in user device 806 and decoded by frequency hopping component 824 in user device 806. Assignment component 820 can assign a nodes in the channel tree to user devices, and frequency hopping component 802 can vary offsets (*e.g.*, by permuting/changing node value assignments) to maintain offset diversity and facilitate mitigating interference between user devices 806 and/or network sectors over which user devices 806 communicate. Additionally, frequency hopping component 802 can assign node values to nodes in a binary channel tree, such as described with regard to Fig. 2, and/or to nodes in a non-binary channel tree, such as described with regard to Fig. 3, in order to facilitate providing offsets to user devices 806. Moreover, frequency hopping component 802 can employ a non-binary channel tree in conjunction with the permutation protocol to optimize interference reduction.

[0076] Frequency hopping component 802 can assign subcarrier sets (*e.g.*, offsets) to user devices 806 for transmission of one or more symbols during a communication event, as described above. For example, frequency hopping component 802 can generate and/or transmit an offset assignment at a first point in time, and such assignment can be varied (*e.g.*, by changing node value assignments) according to a predetermined pattern (*e.g.*, after transmission/receipt of each symbol, group of symbols, one or more frames, ...). To further this example, subcarrier set assignments to

user devices 806 can be varied after a predetermined period, which can be delineated by transmission of a fixed number of symbols (*e.g.*, IFDMA symbols, LFDMA symbols, or any other suitable single-carrier FDMA symbols).

[0077] Assignment receiver 822 in user device 806 receives a subcarrier set assignment (*e.g.*, an offset assignment) to permit user device 806 to exert control over an assigned set of subcarriers for transmission of one or more symbols (*e.g.*, IFDMA, LFDMA, ...) during a communication event. Assignment receiver 822 can receive and/or accept a node assignment and an offset for device 806 can be determined at a first point in time. A second offset can then be determined and/or computed upon alteration of node value assignments after a predetermined time period (*e.g.*, after transmission/receipt of each symbol, group of symbols, ...). According to this example, offset assignments to user device 806 can be varied (*e.g.*, by varying node values for nodes to which user devices are assigned, *etc.*) after a predetermined period that can be delineated by transmission of a number of symbols (*e.g.*, IFDMA symbols, LFDMA symbols, or any other suitable single-carrier FDMA symbols). Furthermore, base station 808 can employ a memory 814, a processor 816, and an AI component 818 to facilitate assignment, assignment variation, acknowledgement, utilization, and the like in conjunction with the various frequency hopping protocols described herein. User device 806 can employ a memory 830, processor 832, and AI component 834 for like purposes.

[0078] AI components 818 and 834 can be respectively and operatively associated with frequency hopping components 802 and 824 in either or both of base station 808 and user device 806, and can make inferences regarding channel tree generation, node value assignments and alterations thereto, user device 806 node allocation, *etc.* As used herein, the term to “infer” or “inference” refers generally to the process of reasoning about or inferring states of the system, environment, and/or user from a set of observations as captured *via* events and/or data. Inference can be employed to identify a specific context or action, or can generate a probability distribution over states, for example. The inference can be probabilistic—that is, the computation of a probability distribution over states of interest based on a consideration of data and events.

Inference can also refer to techniques employed for composing higher-level events from a set of events and/or data. Such inference results in the construction of new events or actions from a set of observed events and/or stored event data, whether or not the events

are correlated in close temporal proximity, and whether the events and data come from one or several event and data sources.

[0079] According to an example, AI components 818 and/or 834 can infer an appropriate tree structure for representing user device offsets based at least in part on, for instance, channel quality, detected interference, number of available subcarriers, number of user devices 806 operating over wireless network 804, *etc.* According to this example, it can be determined that a particular sector or sectors in wireless network 804 are experiencing high transmission volume, and the like. AI component 818, in conjunction with processor 816 and/or memory 814, can determine that interference between user devices 806 and/or sectors is high. AI component 818 can infer that a frequency adjustment is appropriate to increase interference diversity and alleviate the interference problem, and can direct frequency hopping component 802 to alter child node value assignments in a channel tree, which will have the result of altering offset assignments to user devices 806 allocated to such altered child nodes. In such a case, AI component 818 can facilitate frequency hopping in the most cost-effective manner possible to mitigate inter-cell interference and improve interference diversity. It will be appreciated that the foregoing examples are illustrative in nature and are not intended to limit the scope of inferences that can be made by AI components 818 and 834 or the manner in which AI components 818 and 834 make such inferences.

[0080] While Fig. 8 depicts frequency hopping component 802 as residing in the base station 808, it should be noted that frequency hopping component 802 may be implemented as a combination of functionality in both base station 808, base station controller (not shown), or the like of wireless network 804, and in user device 806 (*e.g.*, frequency hopping component 824). In such aspects, it may be possible to contain separate look-up tables in user device 806 and base station 808 which each correspond to sequences for offset U for the user device, which are known to both devices, *e.g.* by instructions from base station 808 that corresponds to the user device 806, or some other means.

[0081] In the embodiments, where the frequency hopping component 802 resides in the base station 808, the user device 806 may have a look-up table that corresponds to a sequence for varying the offset U based upon instructions, commands, or the like transmitted from the base station 808 and generated by frequency hopping component 802.

[0082] Fig. 9 is an illustration of a methodology 900 for generating a signal using an IFDMA protocol, such as can be employed in conjunction with a frequency hopping protocol to improve interference diversity. At 902, a user device can initiate generation of a signal comprising N modulation symbols, for example, $[d_0 d_1 d_2 \dots d_{N-1}]$, by repeating the N symbols to obtain a total of N_{FFT} symbols such that:

$$[d_0 d_1 d_2 \dots d_{N-1} d_0 d_1 d_2 \dots d_{N-1} d_0 d_1 d_2 \dots d_{N-1} \dots d_0 d_1 d_2 \dots d_{N-1}]$$

[0083] At 904, the user device can multiply the k^{th} symbol in the sequence by $e^{-jk\Phi U}$, where $\Phi = 2\pi / N_{FFT}$, such that:

$$[d_0 d_1 e^{-j\Phi U} d_2 e^{-2j\Phi U} \dots d_{N-1} e^{-(N-1)j\Phi U} \dots d_{N-2} e^{-(N_{FFT}-2)j\Phi U} d_{N-1} e^{-(N_{FFT}-1)j\Phi U}]$$

[0084] At 906, cyclic prefix can optionally be added to the signal by copying the last N_{CP} symbols of the signal generated at 904 to the beginning of the symbol expression, such that:

$$[\dots d_{N-2} e^{-(N_{FFT}-2)j\Phi U} d_{N-1} e^{-(N_{FFT}-1)j\Phi U}] [d_0 d_1 e^{-j\Phi U} \dots d_{N-1} e^{-(N-1)j\Phi U} \dots d_{N-1} e^{-(N_{FFT}-1)j\Phi U}]$$

[0085] Method 900 can be employed in an IFDMA communication environment in conjunction with frequency hopping techniques set forth herein to mitigate interference between users and/or sectors in a wireless communication environment. It will be appreciated by one skilled in the art that although various methods and/or systems herein are described with regard to an IFDMA system, a suitable FDMA system arrangement having the described features and/or advantages of the IFDMA system can be employed.

[0086] Fig. 10 is an illustration of a methodology 1000 for performing frequency hopping in conjunction with an IFDMA modulation protocol in a wireless network communication environment. At 1002, a channel tree can be generated to facilitate frequency hopping of user offsets. The channel tree can have a root node, and each child node of the root node and/or other parent nodes in the tree can be assigned a node value (e.g., non-binary, binary, integer, etc.) In the case of a binary channel tree, described here for purposes of simplicity of illustration, each child node can have a binary value of 0 or 1, such that a parent node has a 0-child and a 1-child. Nodes can be

allocated to user devices depending on subcarrier needs of the user devices, such that a user device requiring a relatively large number of subcarriers can be allocated a node closer to the root node than a user device requiring a relatively small number of subcarriers as detailed with regard to Figs. 1-3. In certain aspects, the channel tree is pre-generated and the nodes, their relationship and values are stored in a memory in the form of a look-up table or the like.

[0087] At 1004, node sequences for user devices can be read upward from a user's allocated node to a first child node of the channel tree to determine a value for the user's offset, as detailed with regard to Figs. 2 and 3. Information related to an offset identified at 1004 can be gleaned from a lookup table to facilitate assigning a specific subcarrier set to the user. For example, a user allocated a node having a value of 1 that depends from parent node with a value of 1, which in turn depends from a root node of the tree, can be assigned offset 3. Additionally, because the user-allocated node is three nodes from the top of the tree (inclusive of the allocated node and the root node, which is not read for purposes of offset U determination, but is counted for subcarrier number determination), it can be assigned a number of offset subcarriers equal to $N_{\text{FFT}}/4$. According to another example illustrating a binary channel tree, a user having an allocated node that is four nodes from the root node (including the root node) and has a lineage of all 1s (*e.g.*, allocated node=1, parent=1, grandparent=1, root node) can be assigned offset 7 (*e.g.*, binary 111), which can have a number of subcarriers equal to $N_{\text{FFT}}/8$, *etc.* According to yet another example, if the above lineage were 101 (*e.g.*, allocated node=1, parent=0, grandparent=1, root node), the user can be assigned offset 5 having a number of subcarriers equal to $N_{\text{FFT}}/8$, *etc.*

[0088] At 1006, IFDMA symbols can be generated as detailed with regard to Fig. 9. Such symbols/signals can be converted to an analog signal at 1008 to facilitate transmission thereof. At 1010, node value assignments can be modified to facilitate frequency hopping to mitigate interference. For example, one or more child node value assignments in the channel tree can be altered in order to vary the offset actually associated with the node allocated to a user. For instance, in the above example, the user assigned offset 7 (*e.g.*, 111 binary) comprising $N_{\text{FFT}}/8$ subcarriers can have its parent node pair altered at 1010 so that its node allocation lineage becomes 101 binary, which in turn can result in a reassignment of offset 5 to the user, , and so on. According to the example, the user's node allocation can be static during node value assignment

variation to ensure that the user retains a number of subcarriers equal to $N_{\text{FFT}}/8$.

Additionally, user offset modification can be performed according to a predetermined schedule and/or according to a trigger event, such as upon transmission of every IFDMA symbol (symbol rate hopping), every few symbols (block hopping), *etc.*

[0089] It will be appreciated that although the foregoing examples describe a channel tree that utilizes binary node value assignments, non-binary values can be assigned to such nodes. Moreover, parent nodes can have any suitable number of child nodes associated therewith to facilitate allocating offsets to user devices and performing frequency hopping to mitigate interference.

[0090] Fig. 11 illustrates a methodology 1100 for generating a signal using an LFDMA protocol, such as can be employed in conjunction with a frequency hopping protocol to improve interference diversity. At 1102, a user device can initiate generation of a signal comprising N modulation symbols, for example, $[d_0 d_1 d_2 \dots d_{N-1}]$, by taking an N -point fast Fourier transform (FFT) of the N modulation symbols to obtain $[D_0 D_1 D_2 \dots D_{N-1}]$. The transformed symbols can then be placed in allocated subcarriers $[U, U+1, \dots U+N-1]$ at 1304. At 1106, an N_{FFT} -point inverse fast Fourier transform can be performed to obtain N_{FFT} time domain samples. If desired, cyclic prefix can optionally be added to the symbol at 1108 by copying the last N_{CP} time domain samples to the beginning of the symbol to obtain the LFDMA time domain symbol.

[0091] Method 1100 can be employed to generate an LFDMA communication signal in conjunction with a frequency hopping technique to mitigate inter-device and/or inter-sector interference. For example, frequency hopping can be performed upon each LFDMA symbol (*e.g.*, utilizing a symbol rate hopping technique), upon every few LFDMA symbols (*e.g.*, utilizing a block hopping technique, *etc.*

[0092] Fig. 12 illustrates a methodology 1200 for altering offset assignments for users in an LFDMA wireless communication environment. At 1202, channel tree can be generated to map user offset assignments, and nodes in the tree can be allocated to individual users in a wireless network. Node allocation can be performed in a manner similar to that described with regard to Figs 1, 2, and 3. In certain aspects, the channel tree is pre-generated and the nodes, their relationship and values are stored in a memory in the form of a look-up table or the like.

[0093] At 1204, the channel tree can be read from top to bottom to evaluate user offset assignments. Although the following example describes binary node value assignments

for purposes of simplicity, it will be appreciated that non-binary values, and/or any other suitable values, can be assigned to nodes in the channel tree. For instance, a user allocated a node having a value of 1 that depends from parent node with a value of 0, which in turn depends from a root node of the tree, can be assigned offset 1.

Additionally, because the user-allocated node is three nodes from the top of the tree (inclusive of the root node, which is not read for purposes of offset U determination, but is counted for subcarrier number determination), it can be assigned a number of offset subcarriers equal to $N_{FFT}/4$. According to another example, a user having an allocated node that is four nodes from the root node (including the root node) and has a lineage of 110 binary (*e.g.*, allocated node=1, parent=1, grandparent=0, root node) can be assigned offset 6 (*e.g.*, binary 110), which can have a number of subcarriers equal to $N_{FFT}/8$, *etc.* According to yet another example, if the above lineage were 101 (*e.g.*, allocated node=1, parent=0, grandparent=1, root node), the user can be assigned offset 5 having a number of subcarriers equal to $N_{FFT}/8$, *etc.*

[0094] At 1206, an LFDMA signal can be generated as described with regard to Figure 10 and converted to an analog signal for transmission. At 1208, node value assignments in the channel tree can be varied to facilitate frequency hopping, such as is described with regard to Fig. 10. If desired, user node allocation can be maintained (*e.g.*, static) during node value assignment variation to maintain a constant distance from the root node of the offset tree, which in turn can facilitate ensuring that a precise number of subcarriers are assigned to a given user despite frequency hopping. According to a related aspect, a user whose frequency and/or subcarrier requirements have changed since a previous node allocation iteration can be dynamically reallocated to a node higher or lower on the channel tree based at least in part on information related to the user's resource requirements. In this manner, frequency hopping can be employed in a single carrier FDMA system, such as an LFDMA system to improve interference diversity and provide a more robust communication experience to users of the wireless network employing method 1200.

[0095] Fig. 13 shows an exemplary wireless communication system 1300. The wireless communication system 1300 depicts one base station and one terminal for sake of brevity. However, it is to be appreciated that the system can include more than one base station and/or more than one terminal, wherein additional base stations and/or terminals can be substantially similar or different for the exemplary base station and terminal

described below. In addition, it is to be appreciated that the base station and/or the terminal can employ the systems (Figs. 1-8) and/or methods (Figs. 9-12) described herein to facilitate wireless communication there between.

[0096] Referring now to Fig. 13, on a downlink, at access point 1305, a transmit (TX) data processor 1310 receives, formats, codes, interleaves, and modulates (or symbol maps) traffic data and provides modulation symbols ("data symbols"). A symbol modulator 1315 receives and processes the data symbols and pilot symbols and provides a stream of symbols. A symbol modulator 1320 multiplexes data and pilot symbols on the proper subbands, provides a signal value of zero for each unused subband, and obtains a set of N transmit symbols for the N subbands for each symbol period. Each transmit symbol may be a data symbol, a pilot symbol, or a signal value of zero. The pilot symbols may be sent continuously in each symbol period. It will be appreciated that the pilot symbols may be time division multiplexed (TDM), frequency division multiplexed (FDM), or code division multiplexed (CDM). Symbol modulator 1320 can transform each set of N transmit symbols to the time domain using an N -point IFFT to obtain a "transformed" symbol that contains N time-domain chips. Symbol modulator 1320 typically repeats a portion of each transformed symbol to obtain a corresponding symbol. The repeated portion is known as a cyclic prefix and is used to combat delay spread in the wireless channel.

[0097] A transmitter unit (TMTR) 1320 receives and converts the stream of symbols into one or more analog signals and further conditions (*e.g.*, amplifies, filters, and frequency upconverts) the analog signals to generate a downlink signal suitable for transmission over the wireless channel. The downlink signal is then transmitted through an antenna 1325 to the terminals. At terminal 1330, an antenna 1335 receives the downlink signal and provides a received signal to a receiver unit (RCVR) 1340. Receiver unit 1340 conditions (*e.g.*, filters, amplifies, and frequency downconverts) the received signal and digitizes the conditioned signal to obtain samples. A symbol demodulator 1345 removes the cyclic prefix appended to each symbol, transforms each received transformed symbol to the frequency domain using an N -point FFT, obtains N received symbols for the N subbands for each symbol period, and provides received pilot symbols to a processor 1350 for channel estimation. Symbol demodulator 1345 further receives a frequency response estimate for the downlink from processor 1350, performs data demodulation on the received data symbols to obtain data symbol

estimates (which are estimates of the transmitted data symbols), and provides the data symbol estimates to an RX data processor 1355, which demodulates (*i.e.*, symbol demaps), deinterleaves, and decodes the data symbol estimates to recover the transmitted traffic data. The processing by symbol demodulator 1345 and RX data processor 1355 is complementary to the processing by symbol modulator 1315 and TX data processor 1310, respectively, at access point 1305.

[0098] On the uplink, a TX data processor 1360 processes traffic data and provides data symbols. A symbol modulator 1365 receives and multiplexes the data symbols with pilot symbols, performs symbol modulation, and provides a stream of symbols. The pilot symbols may be transmitted on subbands that have been assigned to terminal 1330 for pilot transmission, where the number of pilot subbands for the uplink may be the same or different from the number of pilot subbands for the downlink. A transmitter unit 1370 then receives and processes the stream of symbols to generate an uplink signal, which is transmitted by the antenna 1335 to the access point 1305.

[0099] At access point 1305, the uplink signal from terminal 1330 is received by the antenna 1325 and processed by a receiver unit 1375 to obtain samples. A symbol demodulator 1380 then processes the samples and provides received pilot symbols and data symbol estimates for the uplink. An RX data processor 1385 processes the data symbol estimates to recover the traffic data transmitted by terminal 1335. A processor 1390 performs channel estimation for each active terminal transmitting on the uplink. Multiple terminals may transmit pilot concurrently on the uplink on their respective assigned sets of pilot subbands, where the pilot subband sets may be interlaced.

[00100] Processors 1390 and 1350 direct (*e.g.*, control, coordinate, manage, *etc.*) operation at access point 1305 and terminal 1335, respectively. Respective processors 1390 and 1350 can be associated with memory units (not shown) that store program codes and data. Processors 1390 and 1350 can also perform computations to derive frequency and impulse response estimates for the uplink and downlink, respectively.

[00101] In further aspects, it is possible to provide a multi-antenna transmitter. In such aspects, a demultiplexer may be provided at the input of TX data processor 1310, which generates multiple streams of data that are separately processed coded and modulated according to different subbands. Additionally, MIMO processing may be provided at the output of the TX data processor 1310 or modulator 1320 so that multiple transmit streams are created prior to transmission but after data processing. At the

receiver 1330 various techniques may be utilized to decode the signals from the multiple antennas.

[00102] For a multiple-access system (*e.g.*, a frequency division multiple-access (FDMA) system, *etc.*), multiple terminals may transmit concurrently on the uplink. For such a system, the pilot subbands may be shared among different terminals. The channel estimation techniques may be used in cases where the pilot subbands for each terminal span the entire operating band (possibly except for the band edges). Such a pilot subband structure would be desirable to obtain frequency diversity for each terminal. The techniques described herein may be implemented by various means. For example, these techniques may be implemented in hardware, software, or a combination thereof. For a hardware implementation, the processing units used for channel estimation may be implemented within one or more application specific integrated circuits (ASICs), digital signal processors (DSPs), digital signal processing devices (DSPDs), programmable logic devices (PLDs), field programmable gate arrays (FPGAs), processors, controllers, micro-controllers, microprocessors, other electronic units designed to perform the functions described herein, or a combination thereof. With software, implementation can be through modules (*e.g.*, procedures, functions, and so on) that perform the functions described herein. The software codes may be stored in memory unit and executed by the processors 1390 and 1350.

[00103] What has been described above includes examples of one or more embodiments. It is, of course, not possible to describe every conceivable combination of components or methodologies for purposes of describing the aforementioned embodiments, but one of ordinary skill in the art may recognize that many further combinations and permutations of various embodiments are possible. Accordingly, the described embodiments are intended to embrace all such alterations, modifications and variations that fall within the spirit and scope of the appended claims. Furthermore, to the extent that the term “includes” is used in either the detailed description or the claims, such term is intended to be inclusive in a manner similar to the term “comprising” as “comprising” is interpreted when employed as a transitional word in a claim.

CLAIMS

What is claimed is:

1. A method of generating transmission symbols, comprising:
generating at least one single-carrier FDMA symbol;
assigning a set of subcarriers to transmit the at least one symbol;
generating at least one other single carrier FDMA symbol; and
varying subcarrier set assignments according to a predetermined pattern for
transmission of the at least one other single-carrier FDMA symbol.
2. The method of claim 1, varying the subcarrier set assignments comprises
changing an assignment of at least one offset in a predetermined set of offsets.
3. The method of claim 1, wherein the predetermined pattern is delineated by
transmission of a number of frames.
4. The method of claim 1, wherein the predetermined pattern is delineated by
expiration of a time period.
5. The method of claim 1, the subcarrier set assignments are varied at fixed
intervals delineated by the transmission of a predetermined number of single-carrier
FDMA symbols.
6. The method of claim 5, assigning subcarriers to a user device comprises:
generating a channel tree including a plurality of nodes;
assigning each child node a node value that represents a non-negative integer;
and
assigning a user device to a node in the channel tree to define the subcarrier set
assigned to the user device.

7. The method of claim 1, further comprising employing an IFDMA protocol to generate transmission symbols for transmission of the at least one single carrier FDMA symbol.
8. The method of claim 1, further comprising reading a channel tree from bottom to top to determine the subcarrier set.
9. The method of claim 8, further comprising reading a path in the channel tree from a user device-assigned node upward to a root node of the tree.
10. The method of claim 9, further comprising assessing value of nodes in the path, beginning with the user device-assigned node and ending with the first child node of the root node.
11. The method of claim 10, further comprising performing a table lookup to identify the subcarrier set corresponding to the value of the path from the user device-assigned node to the first child node of the root node, and assigning the user device the identified subcarrier set.
12. The method of claim 9, further comprising periodically varying node value assignments to alter user-device subcarrier set assignments.
13. The method of claim 9, wherein each node is assigned a non-binary value.
14. The method of claim 9, wherein each node is assigned a binary value.
15. The method of claim 1, further comprising employing an IFDMA protocol to generate transmission symbols and varying subcarrier set assignments upon transmission of each symbol when a subcarrier set assignment is of a size that warrants channel estimation over the entirety of available bandwidth.

16. The method of claim 1, further comprising employing an LFDMA protocol to generate transmission symbols for transmission of the at least one single carrier FDMA symbol.

17. The method of claim 1, wherein subcarrier assignments are varied as a function of at least one of sector identity and time.

18. An apparatus that facilitates frequency hopping for single carrier FDMA communication, comprising
a memory; and
a processor coupled with the memory, the processor configured to assign an offset to a user device and to vary the offset for the user device according to a predetermined pattern.

19. The apparatus of claim 18, wherein the processor is further configured to utilize a channel tree with a plurality of nodes and to assign nodes in the channel tree to respective user devices.

20. The apparatus of claim 19, wherein the channel tree is a non-binary channel tree wherein each node has one or more child nodes.

21. The apparatus of claim 19, wherein each child node is assigned a non-binary value.

22. The apparatus of claim 19, wherein the processor is further configured to read the channel tree along a path from the node assigned to the user device to the first child node of a root node in the channel tree and evaluates a value for the path.

23. The apparatus of claim 22, wherein the processor is further configured to perform a table lookup to identify an offset corresponding to the value of the path from the node assigned to the user device to the root node and assigns to at least one of the user devices the identified offset.

24. The apparatus of claim 23, wherein the user device is assigned an offset corresponding to the value of the path to the node assigned to the user device from the root node.

25. The apparatus of claim 24, wherein the processor is further configured to periodically permute node value assignments of one or more nodes in the channel tree to change the offset of the user device by changing the value of the path from the user-assigned node to the root node.

26. The apparatus of claim 19, wherein the processor is further configured to read the channel tree along a path from the first child node of a root node to a node assigned to the user device in the channel tree and evaluates a value for the path.

27. The apparatus of claim 19, wherein the channel tree is a non-binary channel tree having a plurality of nodes, each of which is assigned a value that represents a non-negative integer.

28. The apparatus of claim 19, wherein the processor is further configured to read the channel tree in an upward direction to determine an offset assignment for a user device employing an IFDMA communication protocol and in a downward direction to determine an offset assignment for a user device employing an LFDMA communication protocol.

29. The apparatus of claim 19, wherein the processor is further configured to periodically permute offset assignments between respective user devices by altering node value assignments.

30. The apparatus of claim 18, wherein the processor is further configured to employ a symbol rate hopping technique to alter node value assignments of one or more nodes upon transmission of each symbol by the user device.

31. The apparatus of claim 30, the frequency hopping component is configured to employ a block hopping technique to alter node value assignments of one or more nodes upon transmission of a block of more than one symbol by the user device.

32. An apparatus comprising:
means for generating at least one single-carrier FDMA symbol;
means for assigning a set of subcarriers to transmit the at least one symbol;
means for generating at least one other single carrier FDMA symbol; and
means for varying subcarrier set assignments, according to a predetermined pattern for transmission of the at least one other single-carrier FDMA symbol.

33. The apparatus of claim 32, the means for assigning comprises means for allocating a node in a channel tree to the user device and means for assigning a value to each node in the channel tree.

34. The apparatus of claim 33, the means for assigning further comprises means for reading a path in the channel tree from an allocated user node to a root node to determine a value for nodes in the path that identifies the set of subcarriers to assign to the user device and a number of subcarriers to include in the set.

35. The apparatus of claim 34, the means for varying periodically alters values assigned to one or more nodes in the channel tree to vary the value of the path between the allocated user node and the root node.

36. The apparatus of claim 35, the means for assigning assigns a new set of subcarriers associated with the varied value of the path from the allocated user node to the root node.

37. The apparatus of claim 36, the means for varying alters node values upon transmission of the at least one single carrier FDMA symbol.

38. A computer-readable medium having stored thereon computer-executable instructions for:

assigning an offset-related entity to a user device; and
periodically varying the offset for the user device based at least in part on the assigned entity.

39. The computer-readable medium of claim 38, further comprising instructions for:
assigning a value to each node of a channel tree;
allocating a node to at least one user device to assign a subcarrier set to the at least one user device; and
permuting node values according to a pattern to change the subcarrier set assigned to the at least one user device.

40. The computer-readable medium of claim 39, further comprising instructions for reading a path between the node allocated to the at least one user device and a root node in the channel tree.

41. The computer-readable medium of claim 40, further comprising instructions for determining a subcarrier set to assign to the at least one user device based at least in part on a path value derived from the values of nodes in the path.

42. The computer-readable medium of claim 40, further comprising instructions for determining a number of subcarriers to assign to the at least one user device based at least in part on the number of nodes in the path, inclusive of the root node and the node allocated to the at least one user device.

43. The computer readable-medium of claim 38, wherein the instruction to permute comprises instructions for computing an offset for the user device based at least in part on the assigned entity.

44. A wireless communication device comprising:
a memory comprising information corresponding to a plurality of offset assignments for transmission of single-carrier FDMA symbols; and
a processor coupled with the memory, the processor configured to vary the offset assignments according to a predetermined pattern based upon the information.

45. The wireless communication device of claim 44, wherein the information corresponds to values for nodes of a channel tree.
46. The wireless communication device of claim 45, wherein the nodes correspond to root nodes and child nodes.
47. The wireless communication device of claim 45, wherein the channel tree is a non-binary channel tree wherein each node has one or more child nodes.
48. The wireless communication device of claim 45, wherein values correspond to values generated by reading the channel tree along a path from the node assigned to the user device to the first child node of a root node in the channel tree and evaluates a value for the path.
49. The wireless communication device of claim 45, wherein the information comprises a look-up table.
50. A method of generating transmission symbols, comprising:
generating at least one single-carrier FDMA symbol at a user device;
assigning a set of subcarriers to transmit the at least one symbol based upon user information at the user device;
generating at least one other single carrier FDMA symbol at the user device; and
altering subcarrier set assignments according to a predetermined offset change based upon the information for transmission of the at least one other single-carrier FDMA symbol.
51. The method of claim 50, further comprising reading a value from a look-up table and wherein altering the subcarrier set assignments comprises changing the assignment by altering the current subcarrier set location by the value.

52. The method of claim 50, wherein the predetermined pattern is delineated by transmission of a number of frames.

53. The method of claim 50, wherein the predetermined pattern is delineated by expiration of a time period.

54. The method of claim 50, the subcarrier set assignments are varied at fixed intervals delineated by the transmission of a predetermined number of single-carrier FDMA symbols.

55. The method of claim 1, further comprising employing an IFDMA protocol to generate transmission symbols and varying subcarrier set assignments upon transmission of each symbol when a subcarrier set assignment is of a size that warrants channel estimation over the entirety of available bandwidth.

56. The method of claim 1, further comprising employing an LFDMA protocol to generate transmission symbols for transmission of the at least one single carrier FDMA symbol.





FIG. 1

2/13

**FIG. 2**






FIG. 3

4/13

**FIG. 4**

5/13

**FIG. 5**




FIG. 6




FIG. 7






FIG. 8

9/13

**FIG. 9**

10/13

**FIG. 10**

11/13




FIG. 11

12/13




FIG. 12




FIG. 13