



(22) Date de dépôt/Filing Date: 2008/07/03

(41) Mise à la disp. pub./Open to Public Insp.: 2009/03/25

(45) Date de délivrance/Issue Date: 2012/04/10

(30) Priorité/Priority: 2007/09/25 (JP2007-247867)

(51) Cl.Int./Int.Cl. *H02P 9/02* (2006.01),
F02D 29/06 (2006.01), *H02J 7/14* (2006.01)


(72) Inventeurs/Inventors:
SAITO, KENJIRO, JP;
SHIBATA, KAZUMI, JP

(73) Propriétaire/Owner:
HONDA MOTOR CO., LTD., JP

(74) Agent: DENNISON ASSOCIATES

(54) Titre : REGULATEUR D'ENERGIE

(54) Title: POWER GENERATION CONTROL DEVICE



(57) Abrégé/Abstract:

To reduce engine torque fluctuations due to load by power generation and perform minimum power generation. An engine speed N_e and a crank angle based on a top dead center are detected by using pitch signals input from a crank angle sensor. Charge period storing means preliminarily stores a plurality of charge periods different in length as a function of engine speed N_e . These charge periods correspond to some of the four strokes of the engine where the friction is low. Charge period determining means

(57) **Abrégé(suite)/Abstract(continued):**

compares a present crank angle and a charge period corresponding to a present engine speed and outputs a charge control signal to an AND gate when the present crank angle falls within this charge period. A duty decided by a regulated voltage control block is input into duty setting means. When the AND gate is opened, the duty from the duty setting means is input into a switching circuit.

ABSTRACT OF THE DISCLOSURE

To reduce engine torque fluctuations due to load by power generation and perform minimum power generation. An engine speed N_e and a crank angle based on a top dead center are detected by using pitch signals input from a crank angle sensor. Charge period storing means preliminarily stores a plurality of charge periods different in length as a function of engine speed N_e . These charge periods correspond to some of the four strokes of the engine where the friction is low. Charge period determining means compares a present crank angle and a charge period corresponding to a present engine speed and outputs a charge control signal to an AND gate when the present crank angle falls within this charge period. A duty decided by a regulated voltage control block is input into duty setting means. When the AND gate is opened, the duty from the duty setting means is input into a switching circuit.

POWER GENERATION CONTROL DEVICE

FIELD OF THE INVENTION

5 The present invention relates to a power generation control device, and more particularly to a power generation control device for controlling power generation so that an output current generated from an engine driven generator is supplied to a battery and a load in only a predetermined region in the engine strokes where a friction in the engine is low.

10 BACKGROUND OF THE INVENTION

In a vehicle adapted to be driven by an engine, such as a motorcycle and a four-wheel vehicle, a generator adapted to be driven by the engine is provided. A battery for supplying electric power to be used in the vehicle is charged with an output current generated from the generator. Further, in general, an on-vehicle
15 generator serves also as an engine starting motor.

It is known that the amount of power generation by an on-vehicle generator is variably controlled according to load on an engine in the vehicle. For example, JP-A-H3-504407 discloses an AC generator type battery charging method such
20 that a power generation function is stopped when a battery voltage reaches a predetermined level, wherein when a heavy load is applied to an engine, the power generation function of the AC generator is stopped or reduced in spite of the fact that the charged condition of the battery is lower than the predetermined level, thereby preventing a reduction in efficiency of the engine.

25

Further, Japanese Patent Laid-open No. Hei 3-212200 discloses a device for controlling a field winding current according to electrical load condition or operational condition of an automobile, wherein when knocking occurs, the field current in a generator is controlled or stopped.

5

In the existing power generation control device or charge control device as described in JP-A-H3-504407 or Japanese Patent Laid-open No. Hei 3-212200, the amount of power generation can be limited when the load on the engine is large, thereby suppressing an increase in engine load. In a four-stroke cycle engine, a friction (a force acting in a direction opposite to the direction of movement of a piston during the operation of the engine from the viewpoint of engine function) differs according to engine stroke. Accordingly, in the case that the amount of power generation is controlled according to only the loaded condition of the engine without considering this friction, it is difficult to reduce torque fluctuations due to the difference in this friction between the strokes.

10
15

Particularly in the case that the engine is operated in a low engine speed region, the output torque of the engine is generally low. Accordingly, even though the amount of power generation is limited, there is a possibility that the engine operation may become unstable due to the torque fluctuations caused by the difference in friction between the strokes. In other words, there is a case that even though the amount of power generation is controlled according to only the loaded condition of an engine in general, the smoothness of the engine operation cannot be largely improved.

20
25

It is accordingly an object of the present invention to provide a power generation control device which can smooth the torque particularly in a low engine speed region by controlling the amount of power generation in consideration of the friction in each stroke.

30

SUMMARY OF THE INVENTION

In accordance with a first aspect of the present invention, there is provided a power generation control device for a generator adapted to be driven by a four-stroke cycle engine, the power generation control device including a switching

- 3 -

circuit for controlling an output current from the generator; and power generation period control means for operating the switching circuit in only a predetermined power generation period in the four strokes of the engine; wherein the power generation period ranges from the expansion stroke to the intake stroke of the four strokes.

According to the first aspect, power generation is performed in only the power generation period set in the range from the expansion stroke to the intake stroke where the friction is low, so that a load due to this power generation is added to the friction in the engine itself. Accordingly, the torque can be made uniform between these strokes where the friction is low and the other stroke where the friction is large, thereby stabilizing an intake efficiency.

In accordance with a second aspect of the present invention, the power generation period is set according to engine speed so that the lower the engine speed, the more the start of the power generation period is shifted toward the expansion stroke and the shorter the range of the power generation period.

According to the second aspect, the lower the engine speed, the shorter the range of the power generation period. In particular, power generation is performed in the expansion stroke where the friction is lower. Accordingly, the influence of load due to the power generation can be minimized and minimum power generation can be performed at the same time. Further, fuel economy can be improved by such minimum power generation.

In accordance with a third aspect of the present invention, the power generation period is effective only between a predetermined idling speed and a predetermined charge starting speed higher than the idling speed; and the switching circuit is operated in all of the four strokes in an engine speed region higher than or equal to the charge starting speed to thereby perform power generation control in all of the four strokes.

According to the third aspect, power generation is performed only in a relatively low engine speed region ranging from the idling speed to the charge starting

speed. Accordingly, as compared with the case that power generation is performed in a low engine speed region with low torque over the four strokes, an increase in load due to power generation can be suppressed. Accordingly, engine operation in the low engine speed region can be stabilized.

5

In accordance with a fourth aspect of the present invention, the generator is connected to a battery adapted to be charged by the output current from the generator; and the switching circuit is driven in accordance with a duty decided so that a terminal voltage of the battery is converged to a predetermined regulated voltage.

10

According to the fourth aspect, in a system for supplying electric power generated from the generator to the battery, charge control of the battery can be performed with reference to the predetermined regulated voltage.

15

BRIEF DESCRIPTION OF THE DRAWINGS

Preferred embodiments of the invention are shown in the drawings, wherein:

FIG. 1 is a diagram showing a system configuration of a charge control device according to a preferred embodiment of the present invention.

20

FIG. 2 is a diagram showing the relation between engine speed and charge period according to the preferred embodiment.

FIG. 3 is a graph showing the output characteristic of a generator.

25

FIG. 4 is a block diagram showing the function of an essential part of an FET driver.

FIG. 5 is a schematic diagram showing the positional relation between a crank angle sensor and a sensor magnet.

30

FIG. 6 is a schematic diagram for illustrating the operation of top dead center detecting means.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

5 A preferred embodiment of the present invention will now be described with reference to the drawings. FIG. 1 is a diagram showing a system configuration of a charge control device according to a preferred embodiment of the power generation control device of the present invention.

10 In FIG. 1, reference numeral 1 denotes a generator. The generator 1 is composed of an inner rotor 2 and an outer stator 3. The inner rotor 2 is connected to one end of a crankshaft 5 of a four-stroke cycle engine 4. The outer stator 3 has a three-phase output winding 6, which is connected to the input side of a switching circuit 7. The output side of the switching circuit 7 is connected to a battery 8 and a load 9. The switching circuit 7 is a three-phase bridge circuit composed of six FETs 71, 72, 73, 74, 75, and 76. Reference numeral 10 denotes an FET driver as an
15 output control device for changing the duty phases of the FETs 71 to 76 of the switching circuit 7 to thereby perform duty control.

The inner rotor 2 of the generator 1 is provided with a sensor magnet 11 having a predetermined number of magnetic poles arranged in the circumferential
20 direction thereof. The adjacent magnetic poles have different polarities. A crank angle sensor 12 is opposed to the circumferential surface of the sensor magnet 11. The crank angle sensor 12 is composed of a plurality of magnetoelectric transducers (Hall elements). In this preferred embodiment, the sensor magnet 11 has eight magnetic poles. In other words, the magnetic poles are arranged at 45°
25 intervals. On the other hand, the crank angle sensor 12 has three Hall elements arranged at 15° intervals. These Hall elements successively output detection signals (which will be hereinafter referred to as "pitch signals") at 15° intervals. The detection signals from the Hall elements are input into the FET driver 10.

30 The FET driver 10 performs switching control in a predetermined stroke of the four strokes of the engine where the friction is low, according to engine speed, thus supplying a current I to the battery 8 and the load 9.

The outline of the charge control in this preferred embodiment will now be described with reference to FIG. 2. In FIG. 2, the horizontal axis represents crank angle α and the vertical axis represents engine speed N_e . The horizontal axis is provided with a scale marked at 15° intervals in accordance with the output from the crank angle sensor 12. The left end of this scale corresponds to the compression top dead center (top position). When the crankshaft 5 of the engine 4 is rotated, an expansion stroke, exhaust stroke, intake stroke, and compression stroke are successively repeated at 180° intervals from the top position as a start point.

10

A plurality of charge periods, or power generation periods are shown along this scale, and these charge periods are different according to engine speed N_e . More specifically, different charge periods A, B, C, D, and E are set according to engine speed N_e . The charge period A is set to a range from the initial stage of the expansion stroke to the initial stage of the exhaust stroke (crank angle of 30° to 210°). The charge period B is set to a range slightly delayed from the charge period A (crank angle of 45° to 240°). The charge period C is set to a range from the middle of the expansion stroke to the end of the exhaust stroke (crank angle of 90° to 360°). The charge period D is set to a range from the middle of the expansion stroke to the end of the intake stroke (crank angle of 90° to 540°). In this manner, charging is performed in only the limited different ranges starting from the expansion stroke of the four strokes in a predetermined engine speed region from a predetermined idling speed N_{eID} to a predetermined normal charge starting speed N_{eCH} higher than the idling speed N_{eID} . In an engine speed region higher than the normal charge starting speed N_{eCH} , the charge period E is set to a range including all of the four strokes, so that charge control is performed in all of the four strokes according to load condition and battery voltage.

30

In the expansion stroke, maximum torque can be obtained by the combustion of fuel in the engine, so that there is a low possibility that the engine speed may become unstable when a load due to power generation is applied to the engine. In the compression stroke, the friction is large and the torque is low, so that the load due to power generation has a large effect on the engine speed. In this

preferred embodiment, when the engine speed N_e is less than the normal charge starting speed N_{eCH} , charging is stopped in the compression stroke where the load due to power generation has a large effect on the engine speed, whereas charging is performed in only the expansion stroke to the intake stroke where the load due to power generation has a small effect on the engine speed.

FIG. 3 is a graph showing the basic output characteristic of the generator 1. In FIG. 3, the horizontal axis represents engine speed N_e and the vertical axis represents output current I . As apparent from FIG. 3, when the engine speed N_e reaches the idling speed N_{eID} , charging is started. Until the engine speed N_e reaches the normal charge starting speed N_{eCH} , normal charge is not performed, that is, charging is performed in only the predetermined charge periods as described above with reference to FIG. 2 (which will be hereinafter referred to as "periodic charge"). When the engine speed N_e reaches the normal charge starting speed N_{eCH} , the periodic charge is ended and the charge amount is controlled in all of the four strokes of the engine according to load condition and battery voltage. The engine speed region from the idling speed N_{eID} to the normal charge starting speed N_{eCH} is referred to as a periodic charge region, and the engine speed region higher than the normal charge starting speed N_{eCH} is referred to as a normal charge region.

FIG. 4 is a block diagram showing the function of an essential part of the FET driver 10. As shown in FIG. 4, the FET driver 10 includes a charge period control block 101, regulated voltage control block 102, duty setting means 103, and AND gate 104.

The charge period control block 101 includes a mechanical angle counter 13, top dead center detecting means 14, crank angle detecting means 15, engine speed detecting means 16, charge period storing means 17, and charge period determining means 18.

The mechanical angle counter 13 is composed of a first counter 131 for counting pitch signals input at 15° intervals and a second counter 132 incrementing its counter value by 1 every time six pitch signals are counted by the first counter

131. In other words, the counter value of the second counter 132 is increased one by one at 90° intervals. The initial value of the counter value of the second counter 132 is "0", and the maximum value of the counter value of the second counter 132 is "7". Accordingly, the counter value of the second counter 132 is circulated at 720° intervals, i.e., with the cycle of the four strokes of the engine 4.

The top dead center detecting means 14 decides the compression top dead center at the position where the counter value of the second counter 132 is "0". However, the compression top dead center cannot be determined only by the counter value of the second counter 132. In this preferred embodiment, the compression top dead center is determined by the counter value of the second counter 132 and an external signal. As the external signal, an FI signal deciding a fuel injection timing in fuel injection control may be used. The FI signal is output in a predetermined period near the compression top dead center, so as to inject the fuel. Accordingly, when the increment of the counter value of the second counter 132 is detected in the output period of the FI signal, the timing of the increment of this counter value is determined as the compression top dead center. After the compression top dead center is determined, the counter value of the second counter 132 is reset to "0".

The crank angle detecting means 15 detects a crank angle with reference to the compression top dead center according to the counter value from the second counter 132 of the mechanical angle counter 13 and the pitch signals. For example, in the case that three pitch signals are input from the time the counter value "0" is input, the crank angle is detected as 45° ($0^\circ + 15^\circ \times 3 = 45^\circ$). In the case that four pitch signals are input from the time the counter value "2" is input, the crank angle is detected as 240° ($90^\circ \times 2 + 15^\circ \times 4 = 240^\circ$).

The engine speed detecting means 16 monitors the period of the pitch signals and detects the engine speed N_e determined by this period. The charge period storing means 17 preliminarily stores a table showing the correspondence between the charge periods A to E and the engine speed N_e . Each charge period is set in units of 15°. When inputting an engine speed N_e from the engine speed detecting means 16, the charge period storing means 17 outputs data indicating

the charge period corresponding to this engine speed N_e to the charge period determining means 18. The charge period determining means 18 compares the charge period input from the charge period storing means 17 and the crank angle input from the crank angle detecting means 15, and outputs a charge control
5 signal in the case that the crank angle falls within the charge period.

The regulated voltage control block 102 includes regulated voltage detecting means 19, regulated voltage setting means 20, voltage comparing means 21, and duty changing means 22. The regulated voltage setting means 20 preliminarily
10 stores a regulated voltage set value V_{ref} . The regulated voltage set value V_{ref} is a predetermined battery voltage value of 14.5 V. The regulated voltage detecting means 19 detects a present battery voltage V_b as a regulated voltage and outputs it to the voltage comparing means 21. The voltage comparing means 21 compares the regulated voltage set value V_{ref} and the detected voltage value V_b ,
15 and outputs the result of comparison to the duty changing means 22.

The duty changing means 22 changes the duty of any one of the FETs according to the result of comparison between the input voltage values V_{ref} and V_b . More specifically, when the detected voltage value V_b is smaller than the regulated
20 voltage set value V_{ref} , the duty is increased, whereas when the detected voltage value V_b is larger than the regulated voltage set value V_{ref} , the duty is decreased. The duty changing means 22 outputs a duty changing signal for increasing or decreasing the duty as mentioned above. The amount of change in the duty may be a fixed value or may be variable according to the deviation of
25 the detected voltage value V_b from the regulated voltage set value V_{ref} . More specifically, when the deviation is large, the amount of change in the duty may be increased, whereas when the deviation is small, the amount of change in the duty may be decreased. The duty changing signal is input into the duty setting means 103. The duty setting means 103 outputs the duty changed above and a
30 drive command for the switching circuit 7 to the AND gate 104.

On the other hand, the charge control signal from the charge period determining means 18 is input as a gate signal into the AND gate 104. Accordingly, while the charge control signal is ON, the duty and the drive command for the switching

- 10 -

circuit 7 output from the duty setting means 103 are input into the switching circuit 7. The switching circuit 7 is driven in response to the drive signal output from the duty setting means 103, and a given one of the FETs 71 to 76 is kept on during the phase according to the input duty in accordance with a predetermined switching pattern. While this FET is ON, the current generated in the three-phase output winding 6 of the generator 1 is supplied to the battery 8 and the load 9.

FIG. 5 is a schematic diagram showing the positional relation between the crank angle sensor 12 and the sensor magnet 11. As shown in FIG. 5, the sensor magnet 11 is a ringlike permanent magnet, which has a plurality of N poles and S poles alternately arranged at 45° intervals. The crank angle sensor 12 is composed of three Hall elements 12a, 12b, and 12c opposed to the outer circumferential surface of the sensor magnet 11. These three Hall elements 12a, 12b, and 12c are arranged at 15° intervals. Outputs from the Hall elements 12a, 12b, and 12c are input through an OR gate 25 to the first counter 131. In other words, the pitch signals are formed at 15° intervals according to the positional relation between the sensor magnet 11 and the Hall elements 12a to 12c.

FIG. 6 is a schematic diagram for illustrating the operation of the top dead center detecting means 14. As shown in FIG. 6, every time six pitch signals are detected (i.e., every time a mechanical angle of 90° is detected), the counter value of the second counter 132 is incremented from "0" to "7", and this cycle is repeated. Further, while the FI signal is ON, the counter value of the second counter 132 is reset to "0".

More specifically, the temporary counter value prior to resetting shown at the top position in FIG. 6 and the FI signal shown at the middle position in FIG. 6 are put into AND to obtain a decisive counter value shown at the bottom position in FIG. 6. As a result, the counter values 0 to 2 are determined as the expansion stroke, the counter values 2 to 4 are determined as the exhaust stroke, the counter values 4 to 6 are determined as the intake stroke, and the counter values 6 to 8 are determined as the compression stroke.

- The switching circuit 7 performs switching of the FETs 71 to 76 in accordance with a predetermined switching pattern to convert the current generated by the generator 1 into a direct current. In a low engine speed region from the idling speed NeID to the normal charge starting speed NeCH, charging is performed in only the charge periods A to D. Accordingly, a masking pattern is preliminarily set in a time period other than the charge periods A to D, and all the FETs 71 to 76 are turned off in this time period to thereby stop the output from the generator 1.
- 10 As described above, the charging current is changed according to engine stroke, resulting in variations in battery voltage. To cope with this problem, the regulated voltage detecting means 19 reads a plurality of voltage values for the battery voltage in each stroke of the engine and detects the average of these voltage values as the battery voltage (regulated voltage). This average may be
- 15 weighted according to the charge periods A to E. More specifically, when charging is performed in only the charge periods A to D of all the engine strokes, the average is multiplied by a coefficient less than 1.0, whereas when charging is performed in all the engine strokes (the charge period E), the average is multiplied by a coefficient of 1.0.
- 20 As described above, the top dead center detecting means 14 detects the top dead center by performing an AND operation between the temporary counter value and the FI signal at 90° intervals to thereby obtain the decisive counter value. As a modification, the top dead center may be determined by calculating an average
- 25 of engine speeds at 90° intervals and setting the counter value "0" at the mechanical angle where the difference in this average in all the engine strokes becomes maximum. This modification is suitable for an engine with a carburetor in which the FI signal cannot be obtained.
- 30 In this preferred embodiment, the engine strokes are detected and a predetermined region of the engine strokes where the friction is low is set as a charge period. As a modification, the charge period may be made variable in consideration of load condition. For example, a crank angular velocity in the predetermined region prior to the compression stroke may be detected, and if the

crank angular velocity detected above is less than a reference value, it is determined that the load is high, so that the charge period is shortened. More specifically, even though the charge period is set to the charge period D determined by a certain engine speed, for example, the charge period is
5 shortened to stop charging at the end of the exhaust stroke rather than at the end of the intake stroke in the case that the load is determined to be high. In other words, the charge period is varied to the charge period C. Further, even though the charge period is set to the charge period C determined by a lower engine speed, the charge period is shortened to stop charging at the initial stage of the
10 exhaust stroke rather than at the end of the exhaust stroke in the case that the load is determined to be high. In other words, the charge period is varied to the charge period A or B.

Although various preferred embodiments of the present invention have been
15 described herein in detail, it will be appreciated by those skilled in the art, that variations may be made thereto without departing from the spirit of the invention or the scope of the appended claims.

THE EMBODIMENTS OF THE INVENTION IN WHICH AN EXCLUSIVE PROPERTY OR PRIVILEGE IS CLAIMED ARE DEFINED AS FOLLOWS:

1. A power generation control device for a generator driven by a four cycle engine having an expansion stroke, an exhaust stroke, an intake stroke and a compression stroke, the power generation control device comprising:
 - a switching circuit for controlling an output current from the generator; and
 - a power generation period control device configured to operate the switching circuit to output the output current from the generator in only a predetermined power generation period of the four cycle engine, wherein the power generation period ranges from the expansion stroke to the intake stroke of the four cycle engine.
2. The power generation control device according to claim 1, wherein the power generation period is set according to an engine speed of the four cycle engine,
 - said power generation period at a low engine speed having a start point shifted toward a start point of the expansion stroke;
 - said power generation period at a higher engine speed being shifted away from the start point of the expansion stroke.
3. The power generation control device according to claim 1 or 2 wherein the power generation period is varied to have a short duration at low engine speed and to increase in duration as the engine speed increases.
4. The power generation control device according to claim 2 or 3 wherein:
 - the power generation period is effective only when the engine speed is between a predetermined idling speed and a predetermined charge starting speed higher than the idling speed; and
 - the switching circuit is operated in all of the four strokes when the engine speed is higher than or equal to the charge starting speed to thereby perform power generation control in all of the four strokes.
5. The power generation control device according to claims 1, 2, 3 or 4 wherein the generator is connected to a battery to be charged by an output

current from the generator, and the switching circuit is driven in accordance with a duty so that a terminal voltage of the battery is converged to a predetermined regulated voltage.

6. The power generation control device according to claim 2 or 3 wherein the power generation period is further set according to a load connected to the switching circuit such that a duration of the power generation period is decreased as the load increases.

7. The power generation control device according to any one claim of claims 1 to 6, wherein:

the power generation period is effective only when an engine speed of the four-stroke cycle engine is between a predetermined idling speed and a predetermined charge starting speed higher than the idling speed; and

the switching circuit is operated in all of the four strokes when the engine speed is higher than or equal to the charge starting speed to thereby perform power generation control in all of the four strokes.

8. A power generation control device for a generator driven by a four cycle engine having an expansion stroke, an exhaust stroke, an intake stroke and a compression stroke, the power generation control device comprising:

a switching circuit for controlling an output current from the generator; and

a power generation period control device configured to operate the switching circuit to output the output current in only a predetermined power generation period between the expansion stroke and the intake stroke and to stop outputting the output current during the compression stroke when an engine speed of the four-stroke cycle engine is between a predetermined idle speed and a predetermined charge starting speed.

9. The power generation control device according to claim 8, wherein a start point of the power generation period is located within the expansion stroke, and the start point of the power generation period is located within the expansion stroke, and the start point of the power generation period and a length of the power generation period are based on the engine speed, wherein the lower the engine speed, the earlier the start point of the power generation

WH-13372CA
SN 2,636,971

- 15 -

period occurs within the expansion stroke and the shorter the duration of the power generation period.

10. The power generation control device according to claim 8 or 9 wherein the duration of the power generation period is decreased as a load connected to the switching circuit increases.

11. The power generation control device according to claim 8, 9 or 10 wherein the generator is connected to a battery charged by an output current from the generator, and the switching circuit is driven in accordance with a duty so that a terminal voltage of the battery is converged to a predetermined regulated voltage.




FIG. 1

FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6

