




(22) Date de dépôt/Filing Date: 2005/06/14
 (41) Mise à la disp. pub./Open to Public Insp.: 2006/01/26
 (45) Date de délivrance/Issue Date: 2013/01/08
 (62) Demande originale/Original Application: 2 570 748
 (30) Priorités/Priorities: 2004/06/18 (US60/580,809);
 2004/12/22 (US11/022,519)

(51) Cl.Int./Int.Cl. *H04B 1/7077* (2011.01),
H04B 1/76 (2006.01)
 (72) Inventeurs/Inventors:
 KHANDEKAR, AAMOD, US;
 AGRAWAL, AVNEESH, US
 (73) Propriétaire/Owner:
 QUALCOMM INCORPORATED, US
 (74) Agent: SMART & BIGGAR

(54) Titre : ACQUISITION DE SIGNAUX DANS UN SYSTEME DE COMMUNICATION SANS FIL
 (54) Title: SIGNAL ACQUISITION IN A WIRELESS COMMUNICATION SYSTEM



(57) Abrégé/Abstract:

Each base station transmits a TDM pilot 1 having multiple instances of a pilot-1 sequence generated with a PN1 sequence and a TDM pilot 2 having at least one instance of a pilot-2 sequence generated with a PN2 sequence. Each base station is assigned a

(57) **Abrégé(suite)/Abstract(continued):**

specific PN2 sequence that uniquely identifies that base station. A terminal uses TDM pilot 1 to detect for the presence of a signal and uses TDM pilot 2 to identify base stations and obtain accurate timing. For signal detection, the terminal performs delayed correlation on received samples and determines whether a signal is present. If a signal is detected, the terminal performs direct correlation on the received samples with PN1 sequences for K_1 different time offsets and identifies K_2 strongest TDM pilot 1 instances. For time synchronization, the terminal performs direct correlation on the received samples with PN2 sequences to detect for TDM pilot 2.

ABSTRACT

Each base station transmits a TDM pilot 1 having multiple instances of a pilot-1 sequence generated with a PN1 sequence and a TDM pilot 2 having at least one instance of a pilot-2 sequence generated with a PN2 sequence. Each base station is assigned a specific PN2 sequence that uniquely identifies that base station. A terminal uses TDM pilot 1 to detect for the presence of a signal and uses TDM pilot 2 to identify base stations and obtain accurate timing. For signal detection, the terminal performs delayed correlation on received samples and determines whether a signal is present. If a signal is detected, the terminal performs direct correlation on the received samples with PN1 sequences for K_1 different time offsets and identifies K_2 strongest TDM pilot 1 instances. For time synchronization, the terminal performs direct correlation on the received samples with PN2 sequences to detect for TDM pilot 2.

SIGNAL ACQUISITION IN A WIRELESS COMMUNICATION SYSTEM

This application is a divisional of Canadian Patent Application No. 2,570,748 filed June 14, 2005.

BACKGROUND

I. Field

[0002] The present invention relates generally to communication, and more specifically to techniques for performing signal acquisition in a wireless communication system.

II. Background

[0003] In a communication system, a base station processes (e.g., encodes and symbol maps) data to obtain modulation symbols, and further processes the modulation symbols to generate a modulated signal. The base station then transmits the modulated signal via a communication channel. The system may use a transmission scheme whereby data is transmitted in frames, with each frame having a particular time duration. Different types of data (e.g., traffic/packet data, overhead/control data, pilot, and so on) may be sent in different parts of each frame.

[0004] A wireless terminal in the system may not know which base stations, if any, near its vicinity are transmitting. Furthermore, the terminal may not know the start of each frame for a given base station, the time at which each frame is transmitted by the base station, or the propagation delay introduced by the communication channel. The terminal performs signal acquisition to detect for transmissions from base stations in the system and to synchronize to the timing and frequency of each detected base stations of interest. Via the signal acquisition process, the terminal can ascertain the timing of each detected base station and can properly perform the complementary demodulation for that base station.

[0005] The base stations typically expend system resources to support signal acquisition, and the terminals also consume resources to perform acquisition. Since

signal acquisition is overhead needed for data transmission, it is desirable to minimize the amount of resources used by both the base stations and terminals for acquisition.

[0006] There is therefore a need in the art for techniques to efficiently perform signal acquisition in a wireless communication system.

SUMMARY

[0007] Techniques to efficiently perform signal acquisition in a wireless communication system are described herein. In an embodiment, each base station transmits two time division multiplexed (TDM) pilots. The first TDM pilot (or "TDM pilot 1") is composed of multiple instances of a pilot-1 sequence that is generated with a first pseudo-random number (PN) sequence (or "PN1" sequence). Each instance of the pilot-1 sequence is a copy or replica of the pilot-1 sequence. The second TDM pilot (or "TDM pilot 2") is composed of at least one instance of a pilot-2 sequence that is generated with a second PN sequence (or "PN2" sequence). Each base station is assigned a specific PN2 sequence that uniquely identifies that base station among neighboring base stations. To reduce computation for signal acquisition, the available PN2 sequences for the system may be arranged into M_1 sets. Each set contains M_2 PN2 sequences and is associated with a different PN1 sequence. Thus, M_1 PN1 sequences and $M_1 \cdot M_2$ PN2 sequences are available for the system.

[0008] A terminal may use TDM pilot 1 to detect for the presence of a signal, obtain timing, and estimate frequency error. The terminal may use TDM pilot 2 to identify a specific base station transmitting a TDM pilot 2. The use of two TDM pilots for signal detection and time synchronization can reduce the amount of processing needed for signal acquisition.

[0009] In an embodiment for signal detection, the terminal performs a delayed correlation on received samples in each sample period, computes a delayed correlation metric for the sample period, and compares this metric against a first threshold to determine whether a signal is present. If a signal is detected, then the terminal obtains coarse timing based on a peak in the delayed correlation. The terminal then performs direct correlation on the received samples with PN1 sequences for K_1 different time offsets within an uncertainty window and identifies K_2 strongest TDM pilot 1 instances, where $K_1 \geq 1$ and $K_2 \geq 1$. If each PN1 sequence is associated with M_2 PN sequences, then each detected TDM pilot 1 instance is associated with M_2 pilot-2 hypotheses. Each

74769-1552 D

3

pilot-2 hypothesis corresponds to a specific time offset and a specific PN2 sequence for TDM pilot 2.

[0010] In an embodiment for time synchronization, the terminal performs direct correlation on the received samples with PN2 sequences for the different pilot-2 hypotheses to detect for TDM pilot 2. The terminal only needs to evaluate M_2 PN sequences for each detected TDM pilot 1 instance, instead of all $M_1 \cdot M_2$ possible PN2 sequences. The terminal computes a direct correlation metric for each pilot-2 hypothesis and compares this metric against a second threshold to determine whether TDM pilot 2 is present. For each detected TDM pilot 2 instance, the base station transmitting the TDM pilot 2 is identified based on the PN2 sequence for the pilot-2 hypothesis, and the timing for the base station is given by the time offset for the hypothesis.

According to one aspect of the present invention, there is provided a method of transmitting pilot in a communication system, comprising: obtaining a first pseudo-random number (PN) sequence and a second PN sequence used to uniquely identify a transmitting entity; generating a first time division multiplexed (TDM) pilot based on the first PN sequence; generating a second TDM pilot based on the second PN sequence; transmitting the first TDM pilot in a first portion of each transmission interval; and transmitting the second TDM pilot in a second portion of each transmission interval.

According to another aspect of the present invention, there is provided a method of transmitting pilot in a communication system, comprising: generating a first time division multiplexed (TDM) pilot with a first pseudo-random number (PN) sequence in a set of first PN sequences; generating a second TDM pilot with a second PN sequence in a set of second PN sequences associated with the first PN sequence, wherein different sets of second PN sequences are associated with different first PN sequences in the set of first PN sequences; transmitting the first TDM pilot in a first portion of each transmission interval; and transmitting the second TDM pilot in a second portion of each transmission interval.

74769-1552 D

3a

According to still another aspect of the present invention, there is provided a method of transmitting pilot in a communication system, comprising: generating a plurality of time division multiplexed (TDM) pilots with a plurality of pseudo-random number (PN) sequences identifying a transmitting entity; and
5 transmitting the plurality of TDM pilots in a plurality of time intervals of each transmission interval with TDM pilot transmission.

According to yet another aspect of the present invention, there is provided an apparatus in a communication system, comprising: a processor operative to generate a first time division multiplexed (TDM) pilot with a first pseudo-random
10 number (PN) sequence in a set of first PN sequences and to generate a second TDM pilot with a second PN sequence in a set of second PN sequences associated with the first PN sequence, wherein different sets of second PN sequences are associated with different first PN sequences in the set of first PN sequences; and a multiplexer operative to multiplex the first TDM pilot in a first portion of each transmission interval
15 and to multiplex the second TDM pilot in a second portion of each transmission interval.

According to a further aspect of the present invention, there is provided an apparatus in a communication system, comprising: means for generating a first time division multiplexed (TDM) pilot with a first pseudo-random number (PN)
20 sequence in a set of first PN sequences; means for generating a second TDM pilot with a second PN sequence in a set of second PN sequences associated with the first PN sequence, wherein different sets of second PN sequences are associated with different first PN sequences in the set of first PN sequences; means for transmitting the first TDM pilot in a first portion of each transmission interval; and
25 means for transmitting the second TDM pilot in a second portion of each transmission interval.

According to yet a further aspect of the present invention, there is provided a processor-readable medium comprising instructions which, when executed by a processor, cause the processor to perform operations including:

74769-1552 D

3b

obtaining a first pseudo-random number (PN) sequence and a second PN sequence used to uniquely identify a transmitting entity; generating a first time division multiplexed (TDM) pilot based on the first PN sequence; generating a second TDM pilot based on the second PN sequence; sending the first TDM pilot in a first portion
5 of each transmission interval; and sending the second TDM pilot in a second portion of each transmission interval.

[0011] Various aspects and embodiments of the invention are described in further detail below.

BRIEF DESCRIPTION OF THE DRAWINGS

10 **[0012]** The features and nature of the present invention will become more apparent from the detailed description set forth below when taken in conjunction with the drawings in which like reference characters identify correspondingly throughout.

[0013] FIG. 1 shows a wireless communication system.

[0014] FIG. 2A shows TDM pilots 1 and 2 generated in the time domain.

15 **[0015]** FIG. 2B shows TDM pilots 1 and 2 generated in the frequency domain.

[0016] FIG. 3A shows synchronous pilot transmission on the forward link.

[0017] FIG. 3B shows staggered pilot transmission on the forward link.

[0018] FIG. 3C shows asynchronous pilot transmission on the forward link.

[0019] FIG. 3D shows time-varying pilot transmission on the forward link.

20 **[0020]** FIG. 4 shows a process performed by a terminal for signal acquisition.

[0021] FIG. 5 shows a block diagram of a base station and a terminal.

[0022] FIG. 6 shows a transmit (TX) pilot processor at the base station.

[0023] FIG. 7 shows a sync unit at the terminal.

74769-1552 D

3c

[0024] FIG. 8A shows a delayed correlator for TDM pilot 1.

[0025] FIG. 8B shows a direct correlator for TDM pilot 1.

DETAILED DESCRIPTION

[0026] The word “exemplary” is used herein to mean “serving as an example, instance, or illustration.” Any embodiment or design described herein as “exemplary” is not necessarily to be construed as preferred or advantageous over other embodiments or designs.

[0027] The signal acquisition techniques described herein may be used for single-carrier and multi-carrier communication systems. Furthermore, one or more TDM pilots may be used to facilitate signal acquisition. For clarity, certain aspects of the techniques are described below for a specific TDM pilot transmission scheme in a multi-carrier system that utilizes orthogonal frequency division multiplexing (OFDM). OFDM is a multi-carrier modulation technique that effectively partitions the overall system bandwidth into multiple (N_F) orthogonal frequency subbands. These subbands are also called tones, subcarriers, bins, and frequency channels. With OFDM, each subband is associated with a respective sub-carrier that may be modulated with data.

[0028] FIG. 1 shows a wireless communication system 100. System 100 includes a number of base stations 110 that support communication for a number of wireless terminals 120. A base station is a fixed station used for communicating with the terminals and may also be referred to as an access point, a Node B, or some other terminology. Terminals 120 are typically dispersed throughout the system, and each terminal may be fixed or mobile. A terminal may also be referred to as a mobile station, a user equipment (UE), a wireless communication device, or some other terminology. Each terminal may communicate with one or multiple base stations on the forward and reverse links at any given moment. The forward link (or downlink) refers to the communication link from the base stations to the terminals, and the reverse link (or uplink) refers to the communication link from the terminals to the base stations. For simplicity, FIG. 1 only shows forward link transmissions.

[0029] Each base station 110 provides communication coverage for a respective geographic area. The term “cell” can refer to a base station and/or its coverage area, depending on the context in which the term is used. To increase capacity, the coverage area of each base station may be partitioned into multiple regions (e.g., three regions). Each region may be served by a corresponding base transceiver subsystem (BTS). The term “sector” can refer to a BTS and/or its coverage area, depending on the context in which the term is used. For a sectorized cell, the base station for that cell typically

includes the BTSs for all of the sectors of that cell. For simplicity, in the following description, the term “base station” is used generically for both a fixed station that serves a cell and a fixed station that serves a sector. Thus, a “base station” in the following description may be for a cell or a sector, depending on whether the system has unsectorized or sectorized cells, respectively.

[0030] FIG. 2A shows an exemplary pilot and data transmission scheme for the forward link in system 100. Each base station transmits data and pilot in frames, with each frame 210 having a predetermined time duration. A frame may also be referred to as a slot or some other terminology. In an embodiment, each frame 210 includes a field 220 for TDM pilots and a field 230 for data. In general, a frame may include any number of fields for any type of transmission. A transmission interval refers to a time interval in which the TDM pilots are transmitted once. In general, a transmission interval may be a fixed time duration (e.g., a frame) or a variable time duration.

[0031] For the embodiment shown in FIG. 2A, field 220 includes a subfield 222 for TDM pilot 1 and a subfield 224 for TDM pilot 2. TDM pilot 1 has a total length of T_1 samples and comprises S_1 identical pilot-1 sequences, where in general $S_1 \geq 1$. TDM pilot 2 has a total length of T_2 samples and comprises S_2 identical pilot-2 sequences, where in general $S_2 \geq 1$. Thus, there may be one or multiple pilot-1 sequence instances for TDM pilot 1 and one or multiple pilot-2 sequence instances for TDM pilot 2. TDM pilots 1 and 2 may be generated in the time domain or the frequency domain (e.g., with OFDM).

[0032] FIG. 2A also shows an embodiment of TDM pilots 1 and 2 generated in the time domain. For this embodiment, each pilot-1 sequence is generated with a PN1 sequence having L_1 PN chips, where $L_1 > 1$. Each PN chip may take on a value of either +1 or -1 and is transmitted in one sample/chip period. TDM pilot 1 comprises S_1 complete pilot-1 sequences and, if $S_1 \cdot L_1 < T_1$, a partial pilot-1 sequence of length C_1 , where $C_1 = T_1 - S_1 \cdot L_1$. The total length of TDM pilot 1 is thus $T_1 = S_1 \cdot L_1 + C_1$. For the embodiment shown in FIG. 2A, TDM pilot 2 comprises one complete pilot-2 sequence generated with a PN2 sequence of length T_2 . In general, TDM pilot 2 may comprise S_2 complete pilot-2 sequences generated with a PN2 sequence of length L_2 and, if $S_2 \cdot L_2 < T_2$, a partial pilot-2 sequence of length C_2 , where $C_2 = T_2 - S_2 \cdot L_2$. The total length of TDM pilot 2 is then $T_2 = S_2 \cdot L_2 + C_2$.

[0033] As used herein, a PN sequence may be any sequence of chips that may be generated in any manner and preferably has good correlation properties. For example, a PN sequence may be generated with a generator polynomial, as is known in the art. The PN sequence for each base station (e.g., each sector) may also be a scrambling code used to randomize data. In this case, the TDM pilots may be generated by applying the scrambling code to a sequence of all ones or all zeros.

[0034] FIG. 2B shows an embodiment of TDM pilots 1 and 2 generated in the frequency domain using OFDM. For this embodiment, TDM pilot 1 comprises L_1 pilot symbols that are transmitted on L_1 subbands, one pilot symbol per subband used for TDM pilot 1. The L_1 subbands are uniformly distributed across the N_F total subbands and are equally spaced apart by S_1 subbands, where $S_1 = N_F / L_1$ and $S_1 \geq 1$. For example, if $N_F = 512$, $L_1 = 256$, and $S_1 = 2$, then 256 pilot symbols are transmitted on 256 subbands that are spaced apart by two subbands. Other values may also be used for N_F , L_1 , and S_1 . The L_1 pilot symbols for the L_1 subbands and $N_F - L_1$ zero signal values for the remaining subbands are transformed to the time domain with an N_F -point inverse discrete Fourier transform (IDFT) to generate a "transformed" symbol that contains N_F time-domain samples. This transformed symbol has S_1 identical pilot-1 sequences, with each pilot-1 sequence containing L_1 time-domain samples. A pilot-1 sequence may also be generated by performing an L_1 -point IDFT on the L_1 pilot symbols for TDM pilot 1. For OFDM, C rightmost samples of the transformed symbol are often copied and appended in front of the transformed symbol to generate an OFDM symbol that contains $N_F + C$ samples. The repeated portion is often called a cyclic prefix and is used to combat inter-symbol interference (ISI). For example, if $N_F = 512$ and $C = 32$, then each OFDM symbol contains 544 samples. Other OFDM subband structures with different numbers of total subbands and cyclic prefix lengths may also be used.

[0035] The PN1 sequence may be applied in the frequency domain by multiplying the L_1 pilot symbols with the L_1 chips of the PN1 sequence. The PN1 sequence may also be applied in the time domain by multiplying the L_1 time-domain samples for each pilot-1 sequence with the L_1 chips of the PN1 sequence.

[0036] TDM pilot 2 may be generated in the frequency domain in similar manner as described above for TDM pilot 1. For TDM pilot 2, L_2 pilot symbols are transmitted on

L_2 subbands that are evenly spaced apart by S_2 subbands, where $S_2 = N/L_2$ and $S_2 \geq 1$. The PN2 sequence may be applied in the time or frequency domain. If TDM pilots 1 and 2 are generated in the frequency domain, then the pilot-1 and pilot-2 sequences contain complex values instead of ± 1 . For the embodiment shown in FIG. 2B, TDM pilots 1 and 2 are each sent within one OFDM symbol. In general, each TDM pilot may include any number of OFDM symbols.

[0037] Neighboring base stations may use the same or different PN1 sequences for TDM pilot 1. A set of M_1 PN1 sequences may be formed, and each base station may use one of the M_1 PN1 sequences in this set. To reduce complexity, M_1 may be chosen to be a small positive number. In an embodiment, neighboring base stations use different PN2 sequences for TDM pilot 2, and the PN2 sequence for each base station is used to uniquely identify that base station among neighboring base stations.

[0038] To reduce computation for signal acquisition, each PN1 sequence may be associated with a different set of M_2 PN2 sequences. A composite set of $M_1 \cdot M_2$ different PN2 sequences is then available. Each base station may be assigned one of the PN2 sequences in the composite set as well as the PN1 sequence associated with the PN2 sequence assigned to the base station. Each base station thus uses a pair of PN1 and PN2 sequences that is different from the PN1 and PN2 sequence pairs used by neighboring base stations. M_1 and M_2 may be selected to be reasonably small values to reduce complexity but sufficiently large to ensure that no terminal will observe two base stations with the same PN2 sequence (e.g., $M_1 \cdot M_2 = 256$).

[0039] A terminal may use TDM pilot 1 to detect for the presence of a signal, obtain coarse timing, and estimate frequency error. The terminal may use TDM pilot 2 to identify a specific base station transmitting a TDM pilot 2 and to obtain more accurate timing (or time synchronization). The use of two separate TDM pilots for signal detection and time synchronization can reduce the amount of processing needed for signal acquisition, as described below. The duration or length of each TDM pilot may be selected based on a tradeoff between detection performance and the amount of overhead incurred for that TDM pilot. In an embodiment, TDM pilot 1 comprises two complete pilot-1 sequences each having a length of 256 chips (or $S_1 = 2$ and $L_1 = 256$), and TDM pilot 2 comprises one complete pilot-2 sequence having a length of 512 or 544 chips (or $S_2 = 1$, and $L_2 = 544$ for FIG. 2A and $L_2 = 512$ for FIG. 2B). In general,

TDM pilot 1 may comprise any number of pilot-1 sequences, which may be of any length, and TDM pilot 2 may also comprise any number of pilot-2 sequences, which may also be of any length.

[0040] FIG. 3A shows a synchronous pilot transmission scheme for the forward link. For this scheme, the base stations in the system are synchronous and transmit their TDM pilots at approximately the same time. A terminal can receive the TDM pilots from all base stations at approximately the same time, with any timing skew between the base stations being due to differences in propagation delays and possibly other factors. By synchronizing the TDM pilots from different base stations, interference by the TDM pilots from one base station on data transmissions by other base stations is avoided, which may improve data detection performance. Furthermore, interference from the data transmissions on the TDM pilots is also avoided, which may improve acquisition performance.

[0041] FIG. 3B shows a staggered pilot transmission scheme for the forward link. For this scheme, the base stations in the system are synchronous but transmit their TDM pilots at different times so that the TDM pilots are staggered. The base stations may be identified by the time at which they transmit their TDM pilots. The same PN sequence may be used for all base stations, and the processing for signal acquisition may be reduced dramatically with all base stations using the same PN sequence. For this scheme, the pilot transmission from each base station observes interference from the data transmissions from neighboring base stations.

[0042] FIG. 3C shows an asynchronous pilot transmission scheme for the forward link. For this scheme, the base stations in the system are asynchronous and each base station transmits its TDM pilots based on its timing. The TDM pilots from different base stations may thus arrive at different times at the terminal.

[0043] For the synchronous pilot transmission scheme shown in FIG. 3A, the TDM pilot transmission from each base station may observe the same interference from the TDM pilot transmissions from neighboring base stations in each frame. In this case, averaging the TDM pilots over multiple frames does not provide averaging gain since the same interference is present in each frame. The interference may be varied by changing the TDM pilots across frames.

[0044] FIG. 3D shows a time-varying pilot transmission scheme for the forward link. For this scheme, each base station is assigned a set of M_B PN1 sequences for

TDM pilot 1, where $M_B > 1$. Each base station uses one PN1 sequence for TDM pilot 1 for each frame and cycles through the M_B PN1 sequences in M_B frames. Different base stations are assigned different sets of M_B PN1 sequences.

[0045] The set of M_B PN1 sequences for each base station may be viewed as a "long code" that spans across multiple frames. Each of the M_B PN1 sequences may be considered as a segment of the long code and may be generated with a different seed for the long code. To reduce receiver processing complexity, the same long code may be used for all base stations, and each base station may be assigned a different offset of the long code. For example, base station i may be assigned a long code offset of k_i , where k_i is within a range of 0 through $M_B - 1$. The PN1 sequences for base station i , starting at a designated frame, is then given as: $PN1_{k_i}$, $PN1_{k_i+1}$, $PN1_{k_i+2}$, and so on. Detection of a given PN1 sequence or long code offset, along with the frame in which the PN1 sequence is detected relative to the designated frame, can identify which set of PN1 sequences the detected PN1 sequence belongs to.

[0046] In general, improved acquisition performance may be achieved if all base stations in the system are synchronized and transmit their TDM pilots at the same time. However, this is not a necessary condition, and all or a subset of the base stations in the system may be asynchronous. For clarity, much of the following description assumes that the base stations are synchronous.

[0047] FIGS. 2A and 2B show the use of two TDM pilots, or TDM pilots 1 and 2. In general, any number of TDM pilots may be used to facilitate signal acquisition by the terminals. Each TDM pilot may be associated with a different set of PN sequences. A hierarchical structure may be used for the PN sequences. For example, TDM pilot 1 may be associated with M_1 possible PN1 sequences (or M_1 possible sets of PN1 sequences), each PN1 sequence may be associated with M_2 possible PN2 sequences, each PN2 sequence may be associated with M_3 possible PN3 sequences, and so on. Each PN1 sequence may be assigned to a large number of base stations in the system, each PN2 sequence may be assigned to a smaller number of base stations, and so on. In general, each TDM pilot may be generated with a PN sequence or without a PN sequence. For simplicity, the following description assumes the use of two TDM pilots generated with two PN sequences selected from two different sets of PN sequences.

[0048] The terminal performs different processing for signal detection and time synchronization. The use of different PN sequences for TDM pilots 1 and 2 allows the terminal to split up the processing for these two tasks, as described below.

1. Delayed Correlation for TDM pilot 1

[0049] At a terminal, the received sample for each sample period may be expressed as:

$$r(n) = h(n) \otimes s(n) + w(n) = y(n) + w(n) , \quad \text{Eq (1)}$$

where n is an index for sample period;

$s(n)$ is a time-domain sample sent by a base station in sample period n ;

$h(n)$ is a complex channel gain observed by sample $s(n)$;

$r(n)$ is a received sample obtained by the terminal for sample period n ;

$w(n)$ is the noise for sample period n ;

$y(n) = h(n) \otimes s(n)$; and

\otimes denotes a convolution operation.

[0050] TDM pilot 1 is a periodic signal composed of S_1 instances of the pilot-1 sequence. The terminal may perform delayed correlation to detect for the presence of an underlying periodic signal (e.g., TDM pilot 1) in the received signal. The delayed correlation may be expressed as:

$$C(n) = \sum_{i=0}^{N_1-1} r^*(n-i) \cdot r(n-i-L_1) , \quad \text{Eq (2)}$$

where $C(n)$ is a delayed correlation result for sample period n ;

N_1 is the length or duration of the delayed correlation; and

“*” denotes a complex conjugate.

The delayed correlation length (N_1) may be set to the total length of TDM pilot 1 (T_1) minus the length of one pilot-1 sequence (L_1) and minus a margin (Q_1) to account for ISI effects at the edges of TDM pilot 1, or $N_1 = T_1 - L_1 - Q_1$. For the embodiment shown in FIGS. 2A and 2B with TDM pilot 1 comprising two pilot-1 sequences, the delayed correlation length N_1 may be set to pilot-1 sequence length, or $N_1 = L_1$.

[0051] Equation (2) computes a correlation between two received samples $r(n-i)$ and $r(n-i-L_1)$ that are spaced apart by L_1 sample periods, which is the pilot-1 sequence length. This correlation, which is $c(n-i) = r^*(n-i) \cdot r(n-i-L_1)$, removes the effect of the communication channel without requiring a channel gain estimate. N_1 correlations are computed for N_1 different pairs of received samples. Equation (2) then accumulates the N_1 correlation results $c(n)$ through $c(n-N_1+1)$ to obtain the delayed correlation result $C(n)$, which is a complex value.

[0052] A delayed correlation metric may be defined as the squared magnitude of the delayed correlation result, as follows:

$$S(n) = |C(n)|^2, \quad \text{Eq (3)}$$

where $|x|^2$ denotes the squared magnitude of x .

[0053] The terminal may declare the presence of TDM pilot 1 if the following condition is true:

$$S(n) > \lambda \cdot |E_{rx}|^2, \quad \text{Eq (4)}$$

where E_{rx} is the energy of the received samples and λ is a threshold value. The energy E_{rx} may be computed based on the received samples used for the delayed correlation and is indicative of the temporally local energy. Equation (4) performs a normalized comparison, where the normalization is based on the energy of the received samples for TDM pilot 1, if it is present. The threshold value λ may be selected to trade off between detection probability and false alarm probability for TDM pilot 1. Detection probability is the probability of correctly indicating the presence of TDM pilot 1 when it is present. False alarm probability is the probability of incorrectly indicating the presence of TDM pilot 1 when it is not present. High detection probability and low false alarm probability are desirable. In general, a higher threshold value reduces both detection probability and false alarm probability.

[0054] Equation (4) shows the use of an energy-based threshold to detect for TDM pilot 1. Other thresholding schemes may also be used for TDM pilot detection. For example, if an automatic gain control (AGC) mechanism automatically normalizes the

energy of the received samples, then an absolute threshold may be used for TDM pilot detection.

[0055] If the terminal is equipped with multiple (R) antennas, then the delayed correlation result $C_j(n)$ may be computed for each antenna j as shown in equation (2). The delayed correlation results for all antennas may be coherently combined as follows:

$$C_{total}(n) = \sum_{j=1}^R C_j(n) . \quad \text{Eq (5)}$$

The squared magnitude of the combined delayed correlation result, or $|C_{total}(n)|^2$, may be compared against a normalized threshold $\lambda \cdot \sum_{j=1}^R E_j^2$, where E_j is the received energy for antenna j .

[0056] The terminal computes an N_1 -point delayed correlation $C(n)$ for each sample period n based on the received sample sequence $\{r(n-i)\}$ and the delayed received sample sequence $\{r(n-i-L_1)\}$, as shown in equation (2). If $S_1 = 2$, then the magnitude of the delayed correlation has a triangular shape when plotted against sample period n . The delayed correlation result has a peak value at sample period n_p . This peak occurs when the delayed correlation spans the duration of the two pilot-1 sequences. If the delayed correlation is performed as described above and in the absence of noise, then sample period n_p is "close to" the end of the second pilot-1 sequence for TDM pilot 1. The imprecision in the peak location is due to ISI effects at the edges of TDM pilot 1. The magnitude of the delayed correlation result falls off gradually on both sides of sample period n_p , since the signal is periodic over only a portion of the delayed correlation duration for all other sample periods.

[0057] The terminal declares the presence of TDM pilot 1 if the delayed correlation metric $S(n)$ crosses the predetermined threshold in any sample period, as shown in equation (4). This sample period occurs on the left or leading edge of the triangular shape. The terminal continues to perform the delayed correlation (e.g., for the next L_1 sample periods) in order to detect for the peak in the delayed correlation result. If TDM pilot 1 has been detected, then the location of the delayed correlation peak is used as a coarse time estimate. This time estimate may not be very accurate because (1) the delayed correlation result has a gradual peak and the location of the peak may be

inaccurate in the presence of noise and (2) ISI at the edges of the TDM pilot 1 causes degradation in the delayed correlation result.

[0058] In an alternative embodiment, the delayed correlation is performed across an entire frame to obtain a delayed correlation metric for each sample period in the frame. The largest delayed correlation metric in the frame is then provided as the location of the detected TDM pilot 1 and the coarse time estimate. This embodiment performs TDM pilot 1 detection without the use of a threshold and may also reduce false peak detection due to interference from, e.g., a frequency division multiplexed (FDM) pilot that is transmitted continuously across the data portion of each frame by neighboring base stations and/or the base station being detected. Other schemes (which may employ more sophisticated detection logic) may also be used to detect for the presence of TDM pilot 1 and to determine the location of the delayed correlation peak.

[0059] The delayed correlation is essentially used to detect for the presence of an underlying periodic signal. The delayed correlation is thus immune to multipath degradations but still captures multipath diversity. This is because a periodic signal remains periodic in the presence of multipath. Furthermore, if multiple base stations transmit periodic signals simultaneously, then the composite signal at the terminal is also periodic. For synchronous pilot transmission as shown in FIG. 3A, TDM pilot 1 essentially observes no interference (for the purpose of delayed correlation) and is affected mainly by thermal noise. As a result, the signal-to-noise ratio (SNR) or carrier-to-interference ratio (C/I) for TDM pilot 1 may be higher than the SNR for other transmissions. The higher SNR for TDM pilot 1 allows the terminal to achieve good detection performance with a shorter TDM pilot 1 duration, which reduces overhead.

[0060] The terminal may obtain a coarse frequency error estimate based on the delayed correlation result $C(n)$. If the frequency of a radio frequency (RF) oscillator used for frequency downconversion at the terminal is offset from the center frequency of the received signal, then the received samples have a phase ramp in the time domain and may be expressed as:

$$r(n) = y(n) \cdot e^{j2\pi \Delta f \cdot T_c \cdot n} + w(n) , \quad \text{Eq (6)}$$

where Δf is the frequency offset/error and T_c is one chip period. Equation (6) differs from equation (1) by the phase ramp $e^{j2\pi\Delta f \cdot T_c \cdot n}$ caused by frequency error Δf in the RF oscillator at the terminal.

[0061] If the expression for the received samples in equation (6) is used for the delayed correlation in equation (2), then the phase of the delayed correlation result (assuming no noise) may be expressed as:

$$2\pi \cdot \Delta f \cdot L_1 \cdot T_c = \arg \{C(n)\} , \quad \text{Eq (7)}$$

where $\arg \{x\}$ is the argument of x , which is the arctangent of the imaginary part of x over the real part of x . The frequency error Δf may be obtained by dividing the phase of the delayed correlation result by $2\pi \cdot L_1 \cdot T_c$, as follows:

$$\Delta f = \frac{\arg \{C(n)\}}{2\pi \cdot L_1 \cdot T_c} . \quad \text{Eq (8)}$$

[0062] The frequency error estimate in equation (8) is valid if the phase of the delayed correlation result is within a range of $-\pi$ to π , or $2\pi \cdot \Delta f \cdot L_1 \cdot T_c \in (-\pi, \pi)$. A frequency error that is too large cannot be detected by the delayed correlation. Thus, the frequency error should be maintained less than a maximum allowable range. For example, $|\Delta f|$ should be less than 9.75 KHz or 4.65 parts per million (ppm) if the center frequency is 2.1 GHz. For a conservative design, the frequency error may be constrained to an even smaller range, e.g., $|\Delta f| < 2.5$ ppm. A larger frequency error may be tolerated and detected by reducing the length of pilot-1 sequence. However, a shorter pilot-1 sequence also degrades signal detection performance.

[0063] The frequency error Δf may be corrected in various manners. For example, the frequency of the RF oscillator at the terminal may be adjusted via a phase-locked loop (PLL) to correct for the frequency error. As another example, the received samples may be digitally rotated as follows:

$$r'(n) = r(n) \cdot e^{-j2\pi\Delta f \cdot T_c \cdot n} , \quad \text{Eq (9)}$$

where $r'(n)$ is a frequency-corrected sample. The terminal may also perform resampling of the frequency-corrected samples to account for frequency error of the clock used for sampling, which may be generated from the same RF oscillator.

2. Direct Correlation for TDM Pilot 1

[0064] The peak of the delayed correlation gives an approximate location of TDM pilot 1. The actual location of TDM pilot 1 falls within an uncertainty window (denoted as W_u) that is centered at the location n_p of the delayed correlation peak. Computer simulations for an exemplary system indicate that there is a high likelihood of TDM pilot 1 falling within ± 35 sample periods of the peak location n_p when a single base station is transmitting. When multiple base stations are transmitting in a synchronous system, the uncertainty window depends on the lag or delay between the arrival times of the signals transmitted by these base stations. This lag is dependent on the distance between the base stations. As an example, a distance of 5 kilo meter (km) corresponds to a lag of approximately 80 sample periods, and the uncertainty window is about ± 80 sample periods. In general, the uncertainty window is dependent on various factors such as the system bandwidth, the TDM pilot 1 duration, the received SNR for TDM pilot 1, the number of base stations transmitting TDM pilot 1, the time delay for different base stations, and so on.

[0065] The terminal may perform direct correlation to detect for strong instances of TDM pilot 1 within the uncertainty window. For each time offset within the uncertainty window, the terminal may perform direct correlation for each of the M_1 possible PN1 sequences that may be used for TDM pilot 1. Alternatively, the terminal may perform direct correlation for each PN1 sequence used by a base station in a candidate set for the terminal. This candidate set may contain base stations (e.g., sectors) identified by the base stations with which the terminal is in communication, base stations that the terminal has identified itself via a low-rate search, and so on. In any case, each pilot-1 hypothesis corresponds to (1) a specific time offset where TDM pilot 1 from a base station may be present and (2) a specific PN1 sequence that may have been used for the TDM pilot 1.

[0066] The direct correlation for TDM pilot 1 for pilot-1 hypothesis (n, m) , with time offset of n and PN1 sequence of $p_m(i)$, may be expressed as:

$$D_m(n) = \sum_{i=0}^{N_{1d}-1} r^*(i-n) \cdot p'_m(i) , \quad \text{Eq (10)}$$

where n is the time offset for pilot-1 hypothesis (n,m) , which falls within the uncertainty window, or $n \in W_u$;

$p'_m(i)$ is the i -th chip in an extended PN1 sequence for pilot-1 hypothesis (n,m) ;

$D_m(n)$ is a direct correlation result for pilot-1 hypothesis (n,m) ; and

N_{1d} is the length of the direct correlation for TDM pilot 1 (e.g., $N_{1d} = S_1 \cdot L_1$).

The extended PN1 sequence $p'_m(i)$ is obtained by repeating the PN1 sequence $p_m(i)$ for pilot-1 hypothesis (n,m) as many times as needed to obtain N_{1d} PN chips. For example, if the direct correlation is performed over two pilot-1 instances, or $N_{1d} = 2 \cdot L_1$, then the PN1 sequence $p_m(i)$ of length L_1 is repeated twice to obtain the extended PN1 sequence $p'_m(i)$ of length $2L_1$.

[0067] For each PN1 sequence to be evaluated, the terminal may perform direct correlation at every half chip within the uncertainty window in order to reduce degradation due to sample timing error at the terminal. For example, if the uncertainty window is ± 80 chips, then the terminal may perform 320 direct correlations for each PN1 sequence, which corresponds to an uncertainty of 80 sample periods in each direction from the uncertainty window center at sample period n_p . If all M_1 PN1 sequences are evaluated, then the total number of direct correlations for TDM pilot 1 is $320 \cdot M_1$. In general, the terminal performs K_1 direct correlations for K_1 different time offsets for each PN1 sequence to be evaluated, or $K_1 \cdot M_1$ direct correlations if all M_1 PN1 sequences are evaluated.

[0068] The direct correlation is used to identify strong instances of TDM pilot 1 in the received signal. After performing all of the direct correlations for TDM pilot 1, the terminal selects K_2 strongest TDM pilot 1 instances having the largest direct correlation results. Each detected TDM pilot 1 instance is associated with a specific time offset and a specific PN1 sequence, e.g., the k -th detected TDM pilot 1 instance is associated with time offset n_k and PN1 sequence $p_k(i)$. The terminal may also compare the direct correlation metric for each detected TDM pilot 1 instance against a normalized threshold and discard the instance if its metric is below the threshold. In any case, K_2

may be a small value for initial acquisition when the terminal is attempting to detect for the strongest base station. For handoff between base stations, K_2 may be a larger value to allow for detection of signal paths belonging to the strongest base station as well as weaker base stations. Computer simulations indicate that $K_2 = 4$ may be sufficient for initial acquisition and $K_2 = 16$ may be sufficient to detect for multiple base stations for handoff.

[0069] The direction correlation may also be performed in the frequency domain. For frequency domain direct correlation, an N_F -point discrete Fourier transform (DFT) is performed on N_F received samples for a given time offset n to obtain N_F frequency-domain values for the N_F total subbands. The frequency-domain values for subbands without pilot symbols are set to zero. The resultant N_F frequency-domain values are then multiplied with N_F pilot symbols that include the PN1 sequence for a pilot-1 hypothesis being evaluated. The N_F resultant symbols may be accumulated to obtain a direct correlation result for the pilot-1 hypothesis at time offset n . Alternatively, an N_F -point IDFT may be performed on the N_F resultant symbols to obtain N_F time-domain values, which corresponds to different time offsets. In any case, the correlation results may be post-processed as described above to identify the K_2 strongest TDM pilot 1 instances.

3. Direct Correlation for TDM Pilot 2

[0070] The terminal evaluates the K_2 detected TDM pilot 1 instances by performing direct correlation on the received samples for TDM pilot 2 with PN2 sequences. For each detected TDM pilot 1 instance, the terminal determines the set of M_2 PN2 sequences $\{s_{\ell,k}(i)\}$ associated with the PN1 sequence $p_k(i)$ used for that detected TDM pilot 1 instance. Each detected TDM pilot 1 instance may thus be associated with M_2 pilot-2 hypotheses. Each pilot-2 hypothesis corresponds to (1) a specific time offset where TDM pilot 2 from a base station may be present and (2) a specific PN2 sequence that may have been used for the TDM pilot 2. For each pilot-2 hypothesis, the terminal performs direct correlation on the received samples for TDM pilot 2 with the PN2 sequence for that hypothesis to detect for the presence of TDM pilot 2.

[0071] The direct correlation for TDM pilot 2 for pilot-2 hypothesis (k, ℓ) , with time offset of n_k and PN2 sequence of $s_{\ell,k}(i)$, may be expressed as:

$$G_{\ell}(n_k) = \sum_{i=0}^{N_2-1} r^*(i-n_k) \cdot s_{\ell,k}(i) , \quad \text{Eq (11)}$$

where $s_{\ell,k}(i)$ is the i -th chip in the PN2 sequence for pilot-2 hypothesis (k, ℓ) ;

$r(i-n_k)$ is the i -th received sample for time offset n_k ;

$G_{\ell}(n_k)$ is a direct correlation result for pilot-2 hypothesis (k, ℓ) ; and

N_2 is the length of the direct correlation for TDM pilot 2.

The direct correlation length may be set to the length of the pilot-2 sequence (i.e., $N_2 = L_2$) or the length of TDM pilot 2 (i.e., $N_2 = T_2$) if $T_2 \neq L_2$.

[0072] A direct correlation metric for TDM pilot 2 may be defined as the squared magnitude of the direct correlation result, as follows:

$$H_{\ell}(n_k) = |G_{\ell}(n_k)|^2 . \quad \text{Eq (12)}$$

The terminal may declare the presence of TDM pilot 2 if the following condition is true:

$$H_{\ell}(n_k) > \mu \cdot E_{\text{rx}} , \quad \text{Eq (13)}$$

where E_{rx} is the energy of the received samples and μ is a threshold value for TDM pilot 2. The energy E_{rx} may be computed based on the received samples used for the direct correlation for TDM pilot 2 and is indicative of the local energy. The threshold value μ may be selected to trade off between detection probability and false alarm probability for TDM pilot 2.

[0073] If the terminal is equipped with multiple (R) antennas, then the direct correlation $G_{\ell,j}(n_k)$ may be computed for each antenna j for a given hypothesis (k, ℓ) , as shown in equation (11). The direct correlation results for all R antennas may be non-coherently combined as follows:

$$H_{\text{total},\ell}(n_k) = \sum_{j=1}^R |G_{\ell,j}(n_k)|^2 . \quad \text{Eq (14)}$$

Equation (14) assumes that the path delay at all R antennas is the same, but the magnitudes of the channel gains for the R antennas are independent. The composite

direct correlation metric $H_{total,\ell}(n_k)$ may be compared against a normalized threshold $\mu \cdot E_{rx_total}$, where E_{rx_total} is the total energy for all R antennas.

[0074] The λ and μ thresholds are used for detection of TDM pilots 1 and 2, respectively. These thresholds determine the detection probability as well as the false alarm probability. Low λ and μ thresholds increase the detection probability but also increase false alarm probability, and the converse is true for high λ and μ thresholds. For a given threshold, the detection probability and false alarm probability generally increase with increasing SNR. The λ and μ thresholds may be appropriately selected such that (1) the detection rates for the delayed correlation and direct correlation, respectively, are sufficiently high even at low SNRs, and (2) the false alarm rates for the delayed correlation and direct correlation, respectively, are sufficiently low even at high SNRs.

[0075] A detection probability of P_{det} corresponds to a misdetection probability of $(1 - P_{det})$. A misdetection is not detecting a pilot that is present. A misdetection of TDM pilot 1 has the effect of extending acquisition time, until the next transmission of TDM pilot 1 is received. If TDM pilot 1 is transmitted periodically (e.g., every 20 milliseconds), then a misdetection of TDM pilot 1 is not problematic.

[0076] A false alarm for the delayed correlation for TDM pilot 1 is not catastrophic since the subsequent direct correlation for TDM pilot 2 will most likely catch this false alarm as a bad hypothesis, i.e., this hypothesis will most likely fail the normalized comparison in equation (13). An adverse effect of a delayed correlation false alarm is extra computation for the direct correlations for both TDM pilots 1 and 2. The number of delayed correlation false alarms should be kept small, e.g., to a given target delayed correlation false alarm probability for any one frame. A false alarm for the direct correlation for TDM pilot 2 results in an increased false alarm probability for the overall system. The false alarm rate for TDM pilot 2 may be reduced by performing direct correlation with only PN2 sequences used by the base station(s) in the candidate set. A large frequency error that exceeds a maximum allowable range is not corrected nor detected by the direct correlations for TDM pilots 1 and pilot 2, and hence has the same effect as a false alarm.

[0077] A mechanism may be used to recover from a false alarm event in the direct correlation for TDM pilot 2. If the direct correlation for TDM pilot 2 declares

detection, then the terminal should be able to demodulate the data and control channels sent by the base station after the frequency and/or time tracking loops have converged. The terminal may check for a false alarm by attempting to decode a control channel. For example, each base station in the system may broadcast a control channel on the forward link to send assignment and acknowledgment to terminals within its coverage area. This control channel may be required to have a high (e.g., 99%) detection probability for satisfactory system operation and may utilize a strong error detection code, e.g., a 16 bit cyclic redundancy check (CRC), which corresponds to a false alarm probability of $0.5^{16} \approx 1.5 \times 10^{-5}$. When the direct correlation for TDM pilot 2 declares detection, the terminal may attempt to decode one or more packets or messages sent on this control channel. If the decoding fails, then the terminal may declare a false alarm and restart the acquisition process.

[0078] FIG. 4 shows a flow diagram of an acquisition process 400 performed by the terminal. The terminal performs delayed correlation on the received samples to detect for the presence of TDM pilot 1 (block 410). This may be achieved by performing delayed correlation for each sample period and comparing the delayed correlation metric $S(n)$ against the normalized threshold. If TDM pilot 1 is not detected, as determined in block 412, then the terminal returns to block 410 to perform delayed correlation in the next sample period. However, if TDM pilot 1 is detected, then the terminal estimates the frequency error in the received sample and corrects for the frequency error (block 414).

[0079] The terminal then performs direct correlation on either the received samples or the frequency-corrected samples with PN1 sequences for K_1 different time offsets and identifies K_2 best detected TDM pilot 1 instances having K_2 largest direct correlation results for TDM pilot 1 (block 416). Each detected TDM pilot 1 instance is associated with a specific time offset and a specific PN1 sequence. The terminal may evaluate M_2 pilot-2 hypotheses for each detected TDM pilot 1 instance, with each pilot-2 hypothesis being associated with a specific time offset and a specific PN2 sequence. For each pilot-2 hypothesis, the terminal performs direct correlation on the received or frequency-corrected samples with the PN2 sequence for the hypothesis and compares the direct correlation metric $H_t(n_k)$ against the normalized threshold to detect for the presence of TDM pilot 2 (block 418).

[0080] If TDM pilot 2 is not detected, as determined in block 420, then the terminal returns to block 410. Otherwise, the terminal may attempt to decode a control channel to check for false alarm (block 422). If the control channel is successfully decoded, as determined in block 424, then the terminal declares successful acquisition (block 426). Otherwise, the terminal returns to block 410.

[0081] The acquisition process may be performed in stages, as shown in FIG. 4. Stage 1 covers the delayed and direct correlations for TDM pilot 1 and is generally used for signal detection. Stage 1 includes substage 1 for the delayed correlation for TDM pilot 1 and substage 2 for the direct correlation for TDM pilot 1. Stage 2 covers the direct correlation for TDM pilot 2 and is used for time synchronization and base station identification. Stage 3 covers the decoding of a control channel and is used to check for false alarm. Signal acquisition may also be performed with fewer than all of the stages and substages shown in FIG. 4. For example, stage 3 may be omitted, substage 2 may be omitted, and so on.

[0082] The terminal performs initial acquisition (e.g., upon power up) if it is not already receiving a signal from a base station. The terminal typically does not have accurate system timing for initial acquisition and may thus perform direct correlation for TDM pilot 1 over a larger uncertainty window in order to ensure detection of TDM pilot 1. For initial acquisition, the terminal may only need to search for the strongest base station, and may thus select a smaller number of detected TDM pilot 1 instances for subsequent evaluation.

[0083] The terminal may perform handoff acquisition to search for better (e.g., stronger) base stations to receive service from. For the staggered pilot transmission scheme shown in FIG. 3B or the asynchronous pilot transmission scheme shown in FIG. 3C, the terminal may continually search for strong base stations by performing delayed correlation as a background task while the terminal is communicating with one or more base stations in an active set. The delayed correlation provides coarse timing for the strong base stations found by the search. For the synchronous pilot transmission scheme shown in FIG. 3A, the timing of the base stations in the active set may be used as the coarse timing of other strong base stations. In any case, the terminal may perform direct correlation for TDM pilot 2 for all new base stations with sufficiently high received signal strength. Since the terminal already has accurate system timing from the base station(s) in the active set, the terminal does not need to use the coarse time

estimate from the delayed correlation and may perform direct correlation over an uncertainty window centered at the timing of the base station(s) in the active set. The terminal may initiate a handoff to another base station having stronger received signal strength than that of the base station(s) in the active set.

[0084] For clarity, a specific pilot transmission scheme with two TDM pilots has been described above. The use of two TDM pilots may reduce computation at the terminal since signal acquisition may be performed in two parts – the signal detection and time synchronization. The delayed correlation for signal detection may be efficiently performed with just one multiply for each sample period, as described below. Each direct correlation requires multiple (N_{1d} or N_2) multiplies. The number of direct correlations to compute is dependent on the number of PN sequences to be evaluated and may be large (e.g., $K_1 \cdot M_1$ direct correlations for TDM pilot 1, and $K_2 \cdot M_2$ direct correlations for TDM pilot 2). The pre-processing with TDM pilot 1 can greatly reduce the amount of processing required for TDM pilot 2.

[0085] M_1 PN1 sequences may be used for TDM pilot 1, and M_2 PN2 sequences may be used for TDM pilot 2 for each PN1 sequence, which gives a total of $M_1 \cdot M_2$ PN2 sequences. The choice of M_1 and M_2 affects the complexity of acquisition and the false alarm probability, but has little or no effect on the detection probabilities for the delayed correlation and direct correlation (for the same threshold values). As an example, if $K_1 = 320$ direct correlations are performed for each PN1 sequence (e.g., for a lag of 80 chips) and $K_2 = 16$ direct correlations are performed for each PN2 sequence (e.g., for handoff acquisition), then the total number of direct correlations is $K_1 \cdot M_1 + K_2 \cdot M_2 = 320 \cdot M_1 + 16 \cdot M_2$. If $M_1 \cdot M_2 = 256$ PN2 sequences are needed for the system, then computation is minimized if $M_1 = 4$ and $M_2 = 64$, and the number of direct correlations is 2304. In general, any values may be chosen for M_1 and M_2 depending on various factors such as, e.g., the total number of PN2 sequences required by the system, the uncertainty window size (or K_1), the number of detected TDM pilot 1 instances to evaluate (K_2), and so on. Complexity may also be reduced by searching for pilots with PN sequences used by base station(s) in the candidate set.

[0086] The TDM pilots may also carry data. For example, TDM pilot 2 may be used to send one or more bits of information, which may be embedded in the PN2 sequence used by each base station. Instead of having $M_1 \cdot M_2$ PN2 sequences for

TDM pilot 2, one bit of information may be conveyed by using $2 \cdot M_1 \cdot M_2$ PN2 sequences for TDM pilot 2. Each base station may then be assigned a pair of PN2 sequences and may use one PN2 sequence in the pair to convey an information bit value of '0' and use the other PN2 sequence in the pair to convey an information bit value of '1'. The number of hypothesis to evaluate for acquisition doubles because there is twice the number of possible PN2 sequences. After acquisition, the PN2 sequence is known and the associated information bit value can be ascertained. More information bits may be conveyed by using a larger set of PN2 sequences for each base station. If the data modulation consists of multiplying the PN2 sequence by a phase factor, then no additional correlations are required. This is because only at the magnitude of the correlation is examined and the phase is ignored.

[0087] Signal acquisition may also be performed with a single TDM pilot. For example, each base station may transmit a TDM pilot using a PN sequence that uniquely identifies that base station. The terminal receives the TDM pilots from all base stations and performs delayed correlation on the received samples for signal detection. If a signal is detected, then the terminal may perform direct correlation on the received samples for the TDM pilot with all of the PN sequences and at different time offsets (or $K_1 \cdot M_1 \cdot M_2$ direct correlations, which may be much larger than $K_1 \cdot M_1 + K_2 \cdot M_2$). From the direct correlation results, the terminal can identify each base station transmitting the TDM pilot and determine its timing. Alternatively, the terminal may perform direct correlation on the received samples for the TDM pilot with a limited set of PN sequences (e.g., for base stations in the candidate set) to reduce complexity.

[0088] In addition to the TDM pilot(s), each base station in an OFDM-based system may transmit a frequency division multiplexed (FDM) pilot on one or more pilot subbands, which are subbands designated for the FDM pilot. Each base station may transmit the FDM pilot in data field 230 in FIG. 2A and may apply a unique PN sequence on the pilot symbols sent on the pilot subband(s). The first PN chip in this PN sequence may be used for the FDM pilot in symbol period 1, the second PN chip may be used for the FDM pilot in symbol period 2, and so on. The PN sequence used for the FDM pilot may be the same as, or different from, the PN2 sequence used for TDM pilot 2. The FDM pilot may be used to improve acquisition performance, e.g., to reduce false alarm rate. The FDM pilot may also be used to uniquely identify the base stations in the

system. For example, a smaller number of PN2 sequences may be used for TDM pilot 2, and the FDM pilot may be used to resolve any ambiguity among base stations.

[0089] The direct correlations for TDM pilots 1 and 2 compute the received signal strength at specific time offsets. The base stations are thus identified based on their strongest signal paths, where each signal path is associated with a particular time offset. A receiver in an OFDM-based system can capture the energy for all signal paths within the cyclic prefix. Thus, base stations may be selected based on a total energy metric instead of a strongest path metric.

[0090] For a synchronous system, the base stations may transmit their TDM pilots 1 and 2 at the same time, as shown in FIG. 3A. Alternatively, the base stations may transmit their TDM pilots staggered in time, as shown in FIG. 3B. For staggered TDM pilots, the terminal may obtain delayed correlation peaks at different time offsets and may compare these peaks in order to select the strongest base station.

[0091] Some or all of the base stations in the system may be asynchronous. In this case, the TDM pilots from different base stations may not arrive coincidentally with each other. The terminal may still be able to perform the signal acquisition described above to search for and acquire pilots from the base station. However, if the base stations are asynchronous, then the TDM pilot 1 from each base station may observe interference from other base stations, and detection performance for the delayed correlation degrades because of the interference. The duration of the TDM pilot 1 may be extended to account for the interference and achieve the desired detection performance (e.g., the desired detection probability for TDM pilot 1).

4. System

[0092] FIG. 5 shows a block diagram of a base station 110x and a terminal 120x, which are one base station and one terminal in system 100. At base station 110x, a TX data processor 510 receives different types of data (e.g., traffic/packet data and overhead/control data) and processes (e.g., encodes, interleaves, and symbol maps) the received data to generate data symbols. As used herein, a "data symbol" is a modulation symbol for data, a "pilot symbol" is a modulation symbol for pilot (which is data that is known *a priori* by both the base station and terminals), and a modulation symbol is a complex value for a point in a signal constellation for a modulation scheme (e.g., M-PSK, M-QAM, and so on).

[0093] An OFDM modulator 520 multiplexes the data symbols onto the proper subbands and performs OFDM modulation on the multiplexed symbols to generate OFDM symbols. A TX pilot processor 530 generates TDM pilots 1 and 2 in the time domain (as shown in FIG. 5) or the frequency domain. A multiplexer (Mux) 532 receives and multiplexes TDM pilots 1 and 2 from TX pilot processor 530 with the OFDM symbols from OFDM modulator 520 and provides a stream of samples to a transmitter unit (TMTR) 534. Transmitter unit 534 converts the sample stream into analog signals and further conditions (e.g., amplifies, filters, and frequency upconverts) the analog signals to generate a modulated signal. Base station 110x then transmits the modulated signal from an antenna 536 to terminals in the system.

[0094] At terminal 120x, the transmitted signals from base station 110x as well as other base stations are received by an antenna 552 and provided to a receiver unit (RCVR) 554. Receiver unit 554 conditions (e.g., filters, amplifies, frequency downconverts, and digitizes) the received signal to generate a stream of received samples. A synchronization (sync) unit 580 obtains the received samples from receiver unit 554 and performs acquisition to detect for signals from the base stations and determine the timing of each detected base station. Unit 580 provides timing information to an OFDM demodulator 560 and/or a controller 590.

[0095] OFDM demodulator 560 performs OFDM demodulation on the received samples based on the timing information from unit 580 and obtains received data and pilot symbols. OFDM demodulator 560 also performs detection (or matched filtering) on the received data symbols with a channel estimate (e.g., a frequency response estimate) and obtains detected data symbols, which are estimates of the data symbols sent by base station 110x. OFDM demodulator 560 provides the detected data symbols to a receive (RX) data processor 570. RX data processor 570 processes (e.g., symbol demaps, deinterleaves, and decodes) the detected data symbols and provides decoded data. RX data processor 570 and/or controller 590 may use the timing information to recover different types of data sent by base station 110x. In general, the processing by OFDM demodulator 560 and RX data processor 570 is complementary to the processing by OFDM modulator 520 and TX data processor 510, respectively, at base station 110x.

[0096] Controllers 540 and 590 direct operation at base station 110x and terminal 120x, respectively. Memory units 542 and 592 provide storage for program codes and data used by controllers 540 and 590, respectively.

[0097] FIG. 6 shows a block diagram of an embodiment of TX pilot processor 530 at base station 110x. For this embodiment, TX pilot processor 530 generates TDM pilots 1 and 2 in the time domain. Within TX pilot processor 530, a PN1 generator 612 generates the PN1 sequence assigned to base station 110x, and a PN2 generator 614 generates the PN2 sequence assigned to base station 110x. Each PN generator may be implemented with, for example, a linear feedback shift register (LFSR) that implements a generator polynomial for the PN sequence. PN generators 612 and 614 may be initialized with the proper values corresponding to the PN1 and PN2 sequences assigned to base station 110x. A multiplexer 616 receives the outputs from PN generators 612 and 614 and provides the output from each PN generator at the appropriate time, as determined by a TDM_Ctrl signal.

[0098] The TDM pilots may also be generated in the frequency domain, as described above. In this case, the PN1 and PN2 sequences from PN generators 612 and 614, respectively, may be provided to OFDM modulator 520 and used to multiply the frequency-domain pilot symbols or the time-domain samples for the TDM pilots.

[0099] FIG. 7 shows a block diagram of an embodiment of sync unit 580 at terminal 120x. Sync unit 580 includes a TDM pilot 1 processor 710 and a TDM pilot 2 processor 740. Within TDM pilot 1 processor 710, a delayed correlator 720 performs delayed correlation on the received samples and provides a delayed correlation result $C(n)$ for each sample period. A pilot/peak detector 722 detects for the presence of TDM pilot 1 in the received signal based on the delayed correlation results and, if a signal is detected, determines the peak of the delayed correlation. A frequency error detector 724 estimates the frequency error in the received samples based on the phase of the delayed correlation result at the detected peak, as shown in equation (8), and provides the frequency error estimate. A frequency error correction unit 726 performs frequency error correction on the received samples and provides frequency-corrected samples. A direct correlator 730 performs direct correlation on the frequency-corrected samples (as shown in FIG. 7) or the received samples (not shown) for different time offsets in the uncertainty window, which is centered at the detected peak location, and provides direct correlation results for TDM pilot 1. A peak detector 732 detects for the K_2 strongest instances of TDM pilot 1 within the uncertainty window.

[00100] Within TDM pilot 2 processor 740, a direct correlator 750 performs direct correlation on the received or frequency corrected samples for different pilot-2

hypotheses determined by the K_2 strongest detected TDM pilot 1 instances from peak detector 732 and provides direct correlation results for these pilot-2 hypotheses. A pilot detector 752 detects for presence of TDM pilot 2 by performing the normalized comparison shown in equation (13). Pilot detector 752 provides the identity as well as the timing of each detected base station as the detector output.

[00101] FIG. 8A shows a block diagram of an embodiment of delayed correlator 720 for TDM pilot 1. Within delayed correlator 720, a shift register 812 (of length L_1) receives and stores the received sample $r(n)$ for each sample period n and provides a delayed received sample $r(n - L_1)$, which has been delayed by L_1 sample periods. A sample buffer may also be used in place of shift register 812. A unit 816 also obtains the received sample $r(n)$ and provides a complex-conjugated received sample $r^*(n)$. For each sample period n , a multiplier 814 multiplies the delayed received sample $r(n - L_1)$ from shift register 812 with the complex-conjugated received sample $r^*(n)$ from unit 816 and provides a correlation result $c(n) = r^*(n) \cdot r(n - L_1)$ to a shift register 822 (of length N_1) and a summer 824. For each sample period n , shift register 822 receives and stores the correlation result $c(n)$ from multiplier 814 and provides a correlation result $c(n - N_1)$ that has been delayed by N_1 sample periods. For each sample period n , summer 824 receives and sums the output $C(n - 1)$ of a register 826 with the result $c(n)$ from multiplier 814, further subtracts the delayed result $c(n - N_1)$ from shift register 822, and provides its output $C(n)$ to register 826. Summer 824 and register 826 form an accumulator that performs the summation operation in equation (2). Shift register 822 and summer 824 are also configured to perform a running or sliding summation of the N_1 most recent correlation results $c(n)$ through $c(n - N_1 + 1)$. This is achieved by summing the most recent correlation result $c(n)$ from multiplier 814 and subtracting out the correlation result $c(n - N_1)$ from N_1 sample periods earlier, which is provided by shift register 822.

[00102] FIG. 8B shows a block diagram of an embodiment of direct correlator 730 for TDM pilot 1. Within direct correlator 730, a buffer 842 stores the received samples. When the peak of the delayed correlation for TDM pilot 1 has been detected, a window generator 832 determines the uncertainty window and provides controls to evaluate each of the pilot-1 hypotheses. Generator 832 provides a time offset and a PN1 sequence for

each pilot-1 hypothesis. Buffer 842 provides the proper sequence of (conjugated) samples for each pilot-1 hypothesis based on the indicated time offset. A PN generator 834 generates the proper PN1 sequence at the indicated time offset. A multiplier 844 multiplies the samples from buffer 842 with the PN1 sequence from PN generator 834. For each pilot-1 hypothesis, an accumulator 846 accumulates the N_{1d} results from multiplier 844 and provides the direct correlation result for that hypothesis.

[00103] Direct correlator 750 for TDM pilot 2 may be implemented in similar manner as direct correlator 730 for TDM pilot 1, albeit with the following differences. Generator 832 generates the controls to evaluate the K_2 detected TDM pilot 1 instances from peak detector 732 instead of the K_1 time offsets within the uncertainty window. PN generator 834 generates the proper PN2 sequence instead of the PN1 sequence. Accumulator 846 performs accumulation over N_2 samples instead of N_{1d} samples.

[00104] The signal acquisition techniques described herein may be implemented by various means. For example, these techniques may be implemented in hardware, software, or a combination thereof. For a hardware implementation, the processing units used to generate and transmit the TDM pilot(s) may be implemented within one or more application specific integrated circuits (ASICs), digital signal processors (DSPs), digital signal processing devices (DSPDs), programmable logic devices (PLDs), field programmable gate arrays (FPGAs), processors, controllers, micro-controllers, microprocessors, other electronic units designed to perform the functions described herein, or a combination thereof. The processing units used to perform acquisition may also be implemented within one or more ASICs, DSPs, and so on.

[00105] For a software implementation, the signal acquisition techniques may be implemented with modules (e.g., procedures, functions, and so on) that perform the functions described herein. The software codes may be stored in a memory unit (e.g., memory unit 542 or 592 in FIG. 5) and executed by a processor (e.g., controller 540 or 590). The memory unit may be implemented within the processor or external to the processor, in which case it can be communicatively coupled to the processor via various means as is known in the art.

[00106] As used herein, OFDM may also include an orthogonal frequency division multiple access (OFDMA) architecture where multiple users share the OFDM channels.

[00107] Headings are included herein for reference and to aid in locating certain sections. These headings are not intended to limit the scope of the concepts described

therein under, and these concepts may have applicability in other sections throughout the entire specification.

[00108] The previous description of the disclosed embodiments is provided to enable any person skilled in the art to make or use the present invention. Various modifications to these embodiments will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other embodiments without departing from the scope of the invention. Thus, the present invention is not intended to be limited to the embodiments shown herein but is to be accorded the widest scope consistent with the principles and novel features disclosed herein.

74769-1552D

30

CLAIMS:

1. A method of transmitting pilot in a communication system, comprising:
obtaining a first pseudo-random number (PN) sequence and a second PN sequence used to uniquely identify a transmitting entity;
- 5 generating a first time division multiplexed (TDM) pilot based on the first PN sequence;
generating a second TDM pilot based on the second PN sequence;
transmitting the first TDM pilot in a first portion of each transmission interval; and
- 10 transmitting the second TDM pilot in a second portion of each transmission interval.
2. The method of claim 1, wherein the generating the first TDM pilot comprises
generating a pilot sequence based on the first PN sequence, and
- 15 generating the first TDM pilot with at least one instance of the pilot sequence.
3. The method of claim 1, wherein the generating the second TDM pilot comprises
generating a pilot sequence based on the second PN sequence, and
- 20 generating the second TDM pilot with at least one instance of the pilot sequence.
4. The method of claim 1, wherein the generating the first TDM pilot comprises generating the first TDM pilot in frequency domain with a first set of pilot symbols for a first set of subcarriers, and wherein the generating the second TDM

74769-1552D

31

pilot comprises generating the second TDM pilot in the frequency domain with a second set of pilot symbols for a second set of subcarriers.

5. The method of claim 1, wherein the obtaining the first PN sequence and the second PN sequence comprises

5 identifying the first PN sequence from among a set of first PN sequences available for the first TDM pilot, and

identifying the second PN sequence from a set of second PN sequences associated with the first PN sequence.

6. The method of claim 1, wherein the transmitting the second TDM pilot
10 comprises transmitting the second TDM pilot in the second portion, after the first portion, of each transmission interval.

7. A method of transmitting pilot in a communication system, comprising:

generating a first time division multiplexed (TDM) pilot with a first pseudo-random number (PN) sequence in a set of first PN sequences;

15 generating a second TDM pilot with a second PN sequence in a set of second PN sequences associated with the first PN sequence, wherein different sets of second PN sequences are associated with different first PN sequences in the set of first PN sequences;

20 transmitting the first TDM pilot in a first portion of each transmission interval; and

transmitting the second TDM pilot in a second portion of each transmission interval.

8. The method of claim 7, wherein the generating the first TDM pilot comprises generating the first TDM pilot with the first PN sequence in time domain,
25 and wherein the generating the second TDM pilot comprises generating the second TDM pilot with the second PN sequence in time domain.

74769-1552D

32

9. The method of claim 7, wherein the generating the first TDM pilot comprises generating the first TDM pilot in frequency domain with a first set of pilot symbols for a first set of subcarriers, and wherein the generating the second TDM pilot comprises generating the second TDM pilot in the frequency domain with a
5 second set of pilot symbols for a second set of subcarriers.
10. The method of claim 7, wherein the generating the first TDM pilot comprises

generating a first pilot sequence with the first PN sequence, and

generating the first TDM pilot with at least one instance of the first pilot
10 sequence.
11. The method of claim 10, wherein the generating the first pilot sequence comprises generating the first pilot sequence with the first PN sequence and having a length equal to the length of the first PN sequence.
12. The method of claim 7, wherein the generating the first TDM pilot
15 comprises generating the first TDM pilot with a different first PN sequence for each of a plurality of transmission intervals.
13. The method of claim 7, wherein the generating the first TDM pilot comprises identifying the first PN sequence from among the set of first PN sequences, the first PN sequence corresponding to a code offset selected from
20 among a plurality of possible code offsets.
14. The method of claim 10, wherein the generating the second TDM pilot comprises

generating a second pilot sequence with the second PN sequence, and

generating the second TDM pilot with at least one instance of the
25 second pilot sequence.

74769-1552D

33

15. The method of claim 14, wherein the generating the second pilot sequence comprises generating the second pilot sequence with the second PN sequence and having a length equal to the length of the second PN sequence.

16. The method of claim 14, wherein the generating the second pilot
5 sequence comprises generating the second pilot sequence with the second PN sequence and having a longer length than the first pilot sequence.

17. The method of claim 7, further comprising:

generating a third TDM pilot with a third PN sequence; and

transmitting the third TDM pilot in a third portion of each transmission
10 interval.

18. The method of claim 7, further comprising:

generating a frequency division multiplexed (FDM) pilot; and

transmitting the FDM pilot in a third portion of each transmission
interval.

15 19. The method of claim 7, further comprising:

generating a frequency division multiplexed (FDM) pilot with the second
PN sequence; and

transmitting the FDM pilot in a third portion of each transmission
interval.

20 20. The method of claim 7, further comprising:

generating a frequency division multiplexed (FDM) pilot with a third PN
sequence; and

transmitting the FDM pilot in a third portion of each transmission
interval.

74769-1552D

34

21. The method of claim 7, further comprising:

identifying the first PN sequence from among a set of M1 possible first PN sequences; and

5 identifying the second PN sequence from among the set of second PN sequences associated with the first PN sequence and including M2 second PN sequences, where M1 is one or greater and M2 is greater than one.

22. The method of claim 7, further comprising:

10 identifying the second PN sequence assigned to a base station transmitting the first and second TDM pilots, wherein neighboring base stations in the communication system are assigned different second PN sequences.

23. The method of claim 7, further comprising:

15 identifying the first and second PN sequences assigned to a base station transmitting the first and second TDM pilots, wherein neighboring base stations in the communication system are assigned different combinations of first and second PN sequences.

24. A method of transmitting pilot in a communication system, comprising:

generating a plurality of time division multiplexed (TDM) pilots with a plurality of pseudo-random number (PN) sequences identifying a transmitting entity; and

20 transmitting the plurality of TDM pilots in a plurality of time intervals of each transmission interval with TDM pilot transmission.

25. The method of claim 24, further comprising:

identifying a PN sequence for each of the plurality of TDM pilots from among a set of PN sequences available for the TDM pilot.

25 26. The method of claim 24, further comprising:

74769-1552D

35

identifying a first PN sequence for a first TDM pilot from among a set of PN sequences available for the first TDM pilot; and

for each remaining TDM pilot among the plurality of TDM pilots,

determining a subset of PN sequences associated with a PN sequence
5 used for another TDM pilot transmitted in a prior time interval, and

identifying a PN sequence for the remaining TDM pilot from among the subset of PN sequences.

27. An apparatus in a communication system, comprising:

a processor operative to generate a first time division multiplexed
10 (TDM) pilot with a first pseudo-random number (PN) sequence in a set of first PN sequences and to generate a second TDM pilot with a second PN sequence in a set of second PN sequences associated with the first PN sequence, wherein different sets of second PN sequences are associated with different first PN sequences in the set of first PN sequences; and

15 a multiplexer operative to multiplex the first TDM pilot in a first portion of each transmission interval and to multiplex the second TDM pilot in a second portion of each transmission interval.

28. The apparatus of claim 27, wherein the processor is operative to generate a first pilot sequence with the first PN sequence, generate the first TDM
20 pilot with at least one instance of the first pilot sequence, generate a second pilot sequence with the second PN sequence, and generate the second TDM pilot with least one instance of the second pilot sequence.

29. The apparatus of claim 27, wherein the processor is operative to identify the first PN sequence from among a set of M1 possible first PN sequences
25 and to identify the second PN sequence from among the set of second PN sequences associated with the first PN sequence and including M2 second PN sequences, where M1 is one or greater and M2 is greater than one.

74769-1552D

36

30. The apparatus of claim 27, further comprising:

a transmitter unit operative to transmit the first and second TDM pilots aligned in time with first and second TDM pilots from at least one other base station.

31. The apparatus of claim 27, further comprising:

5 a transmitter unit operative to transmit the first and second TDM pilots asynchronously with respect to first and second TDM pilots from at least one other base station.

32. The apparatus of claim 27, further comprising:

10 a transmitter unit operative to transmit the first and second TDM pilots staggered in time with respect to first and second TDM pilots from at least one other base station.

33. The apparatus of claim 27, wherein the first and second TDM pilots for each base station are transmitted in a time interval assigned to the base station.

15 34. The apparatus of claim 27, wherein neighboring base stations in the communication system are assigned different combinations of first and second PN sequences.

35. The apparatus of claim 27, wherein neighboring base stations in the communication system are assigned different second PN sequences.

20 36. The apparatus of claim 27, wherein the communication system utilizes orthogonal frequency division multiplexing (OFDM).

37. An apparatus in a communication system, comprising:

means for generating a first time division multiplexed (TDM) pilot with a first pseudo-random number (PN) sequence in a set of first PN sequences;

25 means for generating a second TDM pilot with a second PN sequence in a set of second PN sequences associated with the first PN sequence, wherein

74769-1552D

37

different sets of second PN sequences are associated with different first PN sequences in the set of first PN sequences;

means for transmitting the first TDM pilot in a first portion of each transmission interval; and

5 means for transmitting the second TDM pilot in a second portion of each transmission interval.

38. The apparatus of claim 37, wherein the means for generating the first TDM pilot comprises means for generating a first pilot sequence with the first PN sequence and means for generating the first TDM pilot with at least one instance of
10 the first pilot sequence, and

wherein the means for generating the second TDM pilot comprises means for generating a second pilot sequence with the second PN sequence and means for generating the second TDM pilot with at least one instance of the second pilot sequence.

15 39. The apparatus of claim 37, wherein neighboring base stations in the communication system are assigned different second PN sequences or different combinations of first and second PN sequences.

40. A processor-readable medium comprising instructions which, when executed by a processor, cause the processor to perform operations including:

20 obtaining a first pseudo-random number (PN) sequence and a second PN sequence used to uniquely identify a transmitting entity;

generating a first time division multiplexed (TDM) pilot based on the first PN sequence;

generating a second TDM pilot based on the second PN sequence;

25 sending the first TDM pilot in a first portion of each transmission interval; and

74769-1552D

38

sending the second TDM pilot in a second portion of each transmission interval.




FIG. 1





FIG. 2A




FIG. 2B




FIG. 3A




FIG. 3B

Asynchronous Pilot Transmission




FIG. 3C




FIG. 3D




FIG. 4

8/10




FIG. 5




FIG. 6




FIG. 7

