



(22) Date de dépôt/Filing Date: 2009/08/04

(41) Mise à la disp. pub./Open to Public Insp.: 2010/02/08

(45) Date de délivrance/Issue Date: 2013/07/30

(30) Priorité/Priority: 2008/08/08 (CN200810048732.2)

(51) Cl.Int./Int.Cl. *H02P 5/74* (2006.01),
H02P 27/06 (2006.01)


(72) Inventeur/Inventor:
ZHOU, SHUNXIN, CN

(73) Propriétaire/Owner:
ZHOU, SHUNXIN, CN

(74) Agent: SIM & MCBURNEY

(54) Titre : SYSTEME PERMETTANT DE REALISER LA COMMANDE DE VITESSE A FREQUENCE VARIABLE DE ROTOR DE MANIERE ASYNCHRONES ET SIMULTANEE PAR L'ENTRAINEMENT DE MULTIPLES MOTEURS AU MOYEN D'UN CONVERTISSEUR

(54) Title: SYSTEM FOR REALIZING ROTOR VARIABLE FREQUENCY SPEED CONTROL ASYNCHRONOUSLY AND SIMULTANEOUSLY BY DRIVING MULTIPLE MOTORS VIA ONE INVERTER



(57) Abrégé/Abstract:

A system for realizing rotor variable frequency speed control asynchronously and simultaneously by driving multiple motors via one inverter, comprises a motor group, a rectifier group, a chopper group, an isolator group, an amperite group, a power capacitor group, an inverter, a speed feedback voltage detector group, and a current feedback voltage detector group. Using inversion control theory, the voltage output by the inverter is taken as an inverse electromotive force of each functional motor to drive each chopper to work in real time thereby to allow multiple motors to operate asynchronously and simultaneously. This system may be used in crane operations. As the crane rises, redundant electricity is fed back to the motor via an inverter, and as the crane lowers, the motor will generate electricity, and the electricity is fed back to the motor via the inverter.



ABSTRACT

A system for realizing rotor variable frequency speed control asynchronously and simultaneously by driving multiple motors via one inverter, comprises a motor group, a rectifier group, a chopper group, an isolator group, an amperite group, a power capacitor group, an inverter, a speed feedback voltage detector group, and a current feedback voltage detector group. Using inversion control theory, the voltage output by the inverter is taken as an inverse electromotive force of each functional motor to drive each chopper to work in real time thereby to allow multiple motors to operate asynchronously and simultaneously. This system may be used in crane operations. As the crane rises, redundant electricity is fed back to the motor via an inverter, and as the crane lowers, the motor will generate electricity, and the electricity is fed back to the motor via the inverter.

SYSTEM FOR REALIZING ROTOR VARIABLE FREQUENCY SPEED CONTROL
ASYNCHRONOUSLY AND SIMULTANEOUSLY BY DRIVING MULTIPLE MOTORS VIA
ONE INVERTER

5 Field of the Invention

[0001] The present invention relates to a motor rotor variable frequency speed control system, and in particular, to a system for realizing rotor variable frequency speed control asynchronously and simultaneously by driving multiple motors via one inverter.

10 Background of the Invention

[0002] Motor is the prime mover in each operating mechanism of a crane, blower fan and water pump. It converts electric energy into mechanical energy. Taking crane as an example, motors can drive a crane to perform various different mechanism movements such as lifting (or falling), luffing, revolving and walking, thereby accomplishing the field
15 operation task of the crane.

[0003] Fig.1 is a schematic diagram showing a traditional crane to realize variable frequency speed control using motors of different jobs. It can be seen from the figure that, the system converts the constant voltage constant frequency AC power supply provided by an electric network into DC power supply via a rectifier bridge, and then
20 converts the DC power supply, by an intermediate circuit, into AC power supply of different working frequencies via an inverter bridge, so as to drive the motor to rotate.

[0004] It is supposed that: the frequency of the electric network power supply is f_o , and the working frequency of the motor is f_m ,

[0005] Then, $f_m = \xi f_o$ is true,

25 **[0006]** Here, ξ is slip ratio.

[0007] During the field operation of a crane, it usually requires to accomplish four different operations, lifting, luffing, revolving and walking. Therefore, each corresponding actuating mechanism needs a different motor to provide different electric energy that will be converted to a different mechanical energy. In other words, during

different operations of the crane, the motor rotating speed needed is different, that is, the working frequency f_m of the motor is different. However, in the traditional motor variable frequency speed control system, one inverter bridge can only convert the working frequency of one motor and carry out variable frequency speed control on one motor, which is so called "one-driving-one" technology. Apparently, for the four different operations of the crane, four inverter circuits are required to realize "AC-DC-AC" conversion during which transduction is performed twice. Thus, the respective working frequency needed by multiple motors will be generated, so that the lifting, luffing, revolving and walking operation during the field operation of the crane will be accomplished respectively.

[0008] In conclusion, for the above traditional motor speed control system, its frequency adjustment range is broad, and it will not be limited by the frequency of the electric network; not only the forced transduction, but also the load transduction, may be employed. For such a speed control system, except that the loss of slipping function is great and the efficiency is low at low speed, most prominently, four inverters are required, thus the system will be bulky, massy and costly, and it will be very difficult to implement.

[0009] In recent years, with the rapid development of frequency conversion technologies, especially with the application of vector control technologies and direct torque control technology, frequency conversion technology becomes increasingly mature, and it takes the leading position in AC transmission due to its broad speed control range, high steady speed precision, rapid dynamic response and its capability of reversible operation in the four quadrants of the rectangular axis. Its speed control capability can completely match that of DC transmission, and there appears a tendency that DC transmission is being replaced by it. However, in the frequency conversion technologies employed by overseas jack mechanisms, it still uses one frequency converter for one function, and one inverter bridge is equipped for one frequency converter; for the four functions during the normal operation of a crane, four inverter bridges are still needed. If energy feedback function is to be added to the variable frequency speed control system, another four inverter bridges need to be added, which

is nonpaying apparently. Therefore, for the related products of many overseas companies, "one-driving-one" mode is still employed to accomplish the normal operation of a crane, for example, the products such as YASKAWA (Japan), Siemens (Germany), ABB (Switzerland) and Schneider (France), which can be seen
 5 everywhere in related application field in China, and of which the prices are very high.

[0010] Directed to the serious faults of the above existing frequency conversion technologies, studies have been made by the inventor on how to drive four motors via one inverter so as to realize rotor variable frequency speed control via the turnon
 10 and turnoff of each chopper and make a crane to accomplish four works such as lifting, luffing, revolving and walking in real time when the inverter is positioned at its minimum inverting angle during the operation of the crane. Patent applications have been filed successively by the inventor, and three utility model patents have been granted by State Intellectual Property Office of the People's Republic of China, with
 15 the Patent Number of "ZL002324369", "ZL012122475" and "ZL2007200870857" respectively. At the same time, two patents for invention, with the application number of "2008100941476" and "2008100482526", have been filed this year. However, problems, such as how to provide appropriate forward and inverse output control voltage to effectively turn on and turn off each chopper, how to collect the rotor
 20 phase voltage and the rectifier output DC to rapidly establish a grid control electric field by the chopper so as to guarantee the normal and orderly work of the system, and how to make the system work reasonably according to the rated power of the motor, still need to be solved allsidedly.

25 Summary of the Invention

[0011] It is a first object of an aspect of the present invention to provide a system for realizing rotor variable frequency speed control asynchronously and simultaneously by driving multiple motors via one full-bridge inverter. That is, when on-line control is carried out on multiple motors, the voltage output by one and the
 30 same inverter is taken as an additional inverse electromotive force of each functional motor to drive each functional chopper to work in real time, thereby multiple motors may operate asynchronously and simultaneously.

[0012] The second object of an aspect of the invention is to provide a system for realizing rotor variable frequency speed control asynchronously and simultaneously by driving multiple motors via one half-bridge inverter. That is, when on-line control is carried out on multiple motors, the voltage output by one and the same inverter is taken as an additional inverse electromotive force of each functional motor to drive each functional chopper to work in real time, thereby multiple motors may operate asynchronously and simultaneously.

[0013] The third object of an aspect of this invention is to make the system have an energy feedback and recycle function, so that the energy source may be saved effectively.

[0014] The fourth object of an aspect of the invention is a motor rotor variable frequency speed control in which full bridge active inversion or half bridge active inversion is realized by one system.

[0015] To attain the above objects of aspects, this invention employs the following technical solutions:

[0016] A system for realizing rotor variable frequency speed control asynchronously and simultaneously by driving multiple motors via one inverter, comprising:

[0017] a motor group, which comprises four motors, M1, M2, M3 and M4, for asynchronously and simultaneously accomplishing various jobs of a crane, such as lifting, luffing, revolving and walking;

[0018] a rectifier group, which comprises four rectifier bridges, Z1, Z2, Z3 and Z4, for rectifying AC signals with different frequencies provided by motor rotors connected therewith;

[0019] an amperite group, which comprises two amperites, L7 and L8, for providing an instantaneous current to make the system work normally;

[0020] a chopper group, which comprises four choppers, IGBT1, IGBT2, IGBT3 and IGBT4, for realizing the continuous adjustment of a DC current by adjusting the conductive rate of each chopper and thus continuously adjusting the motor rotor current, so as to attain the object of motor rotor variable frequency speed control; it must be noted that, when the conductive rate of the chopper is 100%, the motor rotating speed

will be the rated rotating speed;

[0021] an isolator group, which comprises eight isolators, D_1 , D_2 , D_3 , D_4 , D_5 , D_6 , D_7 and D_8 , for maintaining the continuity and guaranteeing the normal work of the system at minimum working current;

5 **[0022]** a full-bridge inverter or a half-bridge inverter, which, after rectifying the AC with different frequencies output by each motor rotor to DC, is adapted to invert the DC to a power supply with the same frequency and the same phase as the industrial AC power supply, realize the conversion of AC to DC and DC to AC, and feed back the energy to the motor or the electric network;

10 **[0023]** a current feedback voltage detector group, comprising four voltage detectors, U_{I1} , U_{I2} , U_{I3} and U_{I4} , which is located in parallel with resistors through which the current feedback contained in the above rectifier bridge passes, for detecting each corresponding current feedback DC, converting it into voltage form and sending it to the input terminal of the corresponding signal processor; and

15 **[0024]** a speed feedback voltage detector group, comprising four voltage detectors, U_{V1} , U_{V2} , U_{V3} and U_{V4} , which is located between any two lines of the above motor rotor, for detecting the AC voltage with different frequencies between any two lines of each motor, and converting it into DC voltage and sending it to the input terminal of the corresponding signal processor.

20 **[0025]** In the invention, when online control is carried out on multiple motors using inversion control theory technology, according to the rated power of the motor, the voltage output by a full-bridge inverter or a half-bridge inverter is taken as an additional inverse electromotive force of each functional motor, and asynchronous and simultaneous operation of each motor is realized via the real-time work of the choppers
25 of each functional motor, thereby the field operations of a crane, such as lifting, luffing, revolving and walking, can be realized.

[0026] In the invention, during the rising operation of the crane, based on that the motor rotor is connected to an active inversion system, redundant electric energy is always fed back to the motor or the electric network via the inverter; but, during the

falling operation of the crane, DC excitation is input to the two phase of the motor stator, thus the motor actually becomes a generator, and it is in power generating state, and moreover, the electric energy generated is again fed back to the motor or the electric network via the same inverter, so that energy recovery is realized, and
 5 energy source is saved effectively.

[0027] When the invention is applied in a high-power system, a full-bridge inverter will be used to drive multiple motors to realize rotor variable frequency speed control asynchronously and simultaneously; however, when the invention is applied in an intermediate-power system or a low-power system, a half-bridge inverter will be
 10 used to drive multiple motors to realize rotor variable frequency speed control asynchronously and simultaneously. For the conversion of its operating state, the phase voltage of each motor rotor collected, the rectifier DC and the main command voltage given by the motorman are comprehensively processed in real time by a microprocessor control center set externally under the control of its master program,
 15 so that the effective turnon and turnoff of each chopper may be controlled, and motor rotor variable frequency speed control may be realized. Automatic protection, state display and man-machine conversation may also be performed on overload limitation, failure monitoring, overspeed limitation, position restriction phase failure and undervoltage, overcurrent and wind velocity of the crane by adding an auxiliary
 20 circuit and in conjunction with appropriate software support, thus highly intellectualized and real-time control can be realized.

[0027a] According to another object of an aspect of the invention there is provided a system for realizing rotor variable frequency speed control asynchronously and simultaneously by driving multiple motors via one inverter, the system comprising: a
 25 motor group; a rectifier group; a chopper group; an isolator group; an amperite group; a power capacitor group; an inverter; a speed feedback voltage detector; and a current feedback voltage detector, wherein the respective rotors of four motors M1, M2, M3 and M4 in said motor group are respectively connected to the respective corresponding input terminals of four rectifiers Z1, Z2, Z3 and Z4 in said rectifier
 30 group in turn, the respective cathodes E of four choppers IGBT1, IGBT2, IGBT3 and IGBT4 in said chopper group respectively intersect with the anodes of the respective corresponding three rectifier diodes of four rectifiers Z1, Z2, Z3 and Z4 in said

rectifier group at a point D, in turn, said inverter is a full-bridge inverter, which comprises six silicon controlled inverters KP1, KP2, KP3, KP4, KP5 and KP6, and the three connection points of the output terminals KP1 and KP4, KP2 and KP5, KP3 and KP6 are respectively connected to the ends A, B and C of a three-phase industrial AC power supply in turn, and then connected to the respective stators of the four motors M1, M2, M3 and M4 in said motor group, said isolator group comprises eight isolators D1, D2, D3, D4, D5, D6, D7, and D8, wherein isolators D1 and D5, isolators D2 and D6, isolators D3 and D7, isolators D4 and D8 are respectively connected in series, the respective anodes of said isolators D1, D2, D3 and D4 are respectively connected to the output terminals of the respective corresponding resistors R1, R2, R3 and R4 and the anodes C of said choppers IGBT1, IGBT2, IGBT3 and IGBT4, in turn, and the cathodes of said isolators D5 and D6 are simultaneously connected to the input terminal of current limiting inductor L7 in said amperite group, while the cathodes of said isolators D7 and D8 are simultaneously connected to the input terminal of current limiting inductor L8 in said amperite group.

[0027b] According to another aspect of the invention there is provided a system for realizing rotor variable frequency speed control asynchronously and simultaneously by driving multiple motors via one inverter, the system comprising: a motor group; a rectifier group; a chopper group; an isolator group; an amperite group; a power capacitor group; an inverter; a speed feedback voltage detector; and a current feedback voltage detector, wherein the respective rotors of four motors M1, M2, M3 and M4 in said motor group are respectively connected to the respective corresponding input terminals of the four rectifiers Z1, Z2, Z3 and Z4 in said rectifier group in turn, the respective cathodes E of the four choppers IGBT1, IGBT2, IGBT3 and IGBT4 in said chopper group respectively intersect with the anodes of the respective corresponding three rectifier diodes of the four rectifiers Z1, Z2, Z3 and Z4 in said rectifier group at a point D, in turn, and said inverter is a half-bridge inverter, which comprises three silicon controlled inverters KP1, KP2 and KP3, and via a circuit formed by connecting three fuses FU1, FU2 and FU3 with three inductors L1, L2 and L3 in series and then via the respective other end of said three inductors L1, L2 and L3, the respective cathodes thereof simultaneously intersect

with the respective cathodes E of said four choppers IGBT1, IGBT2, IGBT3 and IGBT4 in said chopper group and the respective other end of the four capacitors C13, C14, C15 and C16 in said power capacitor group at said point D, in turn.

[0028] For the whole system of the invention, it has such characteristics as
5 simple circuit, small size, low cost, high reliability and energy saving.

Brief Description of the Drawings

[0029] Fig.1 is a schematic diagram showing a traditional system for a crane to realize variable frequency speed control using motors for different jobs;

10 **[0030]** Fig.2A and Fig.2B are schematic diagrams showing the electrical principle of a system for realizing rotor variable frequency speed control asynchronously and simultaneously by driving multiple motors via a full-bridge inverter in the first embodiment of the invention and by driving multiple motors via a half-bridge inverter in

the second embodiment of the invention.

[0031] Description of Symbols in the drawings:

1: Motor Group: M_1 , M_2 , M_3 and M_4

2: Rectifier Group: Z_1 , Z_2 , Z_3 and Z_4

3: Chopper Group: $IGBT_1$, $IGBT_2$, $IGBT_3$ and $IGBT_4$

4: Isolator Group: D_1 , D_2 , D_3 , D_4 , D_5 , D_6 , D_7 and D_8

5: Amperite Group: L_7 and L_8

6: Power Capacitor Group: C_{13} , C_{14} , C_{15} and C_{16}

7: Inverter: KP_1 , KP_2 , KP_3 , KP_4 , KP_5 and KP_6 are full-bridge inverter; KP_1 , KP_2 and KP_3 are half-bridge inverter

8: Speed Feedback Voltage Detector Group: U_{V1} , U_{V2} , U_{V3} and U_{V4}

9: Current Feedback Voltage Detector Group: U_{I1} , U_{I2} , U_{I3} and U_{I4}

Detailed Description of the Embodiments

[0032] Referring to Fig.2A and Fig.2B, which show the first and the second preferred embodiment of the invention.

[0033] It can be seen from Fig.2A and Fig.2B that, the first embodiment of the invention consists, as a whole, of motor group 1, rectifier group 2, chopper group 3, isolator group 4, amperite group 5, power capacitor group 6, inverter 7, speed feedback voltage detector 8 and current feedback voltage detector 9, wherein:

[0034] the respective rotors of the four motors M_1 , M_2 , M_3 and M_4 in said motor group 1 are respectively connected to the respective corresponding input terminals of the four rectifiers Z_1 , Z_2 , Z_3 and Z_4 in rectifier group 2 in turn;

[0035] the respective cathodes E of four choppers $IGBT_1$, $IGBT_2$, $IGBT_3$ and $IGBT_4$ in said chopper group 3 respectively intersect the anodes of the respective corresponding three rectifier diodes of four rectifiers Z_1 , Z_2 , Z_3 and Z_4 in rectifier group 2 at one point, i.e., point D, in turn;

[0036] said inverter 7 is a full-bridge inverter, which comprises 6 silicon controlled invertors, i.e., KP_1 , KP_2 , KP_3 , KP_4 , KP_5 and KP_6 , and three connection points of output

terminals KP_1 and KP_4 , KP_2 and KP_5 , KP_3 and KP_6 are respectively connected to the ends A, B and C of a three-phase industrial AC power supply in turn, and then connected to the respective stators of four motors M_1 , M_2 , M_3 and M_4 in motor group 1.

[0037] said isolator group 4 comprises eight isolators, i.e., D_1 , D_2 , D_3 , D_4 , D_5 , D_6 , D_7 and D_8 , wherein D_1 and D_5 , D_2 and D_6 , D_3 and D_7 , D_4 and D_8 are respectively connected in series in turn;

[0038] wherein, the respective anodes of isolators D_1 , D_2 , D_3 and D_4 are respectively connected to the output terminals of the respective corresponding resistors R_1 , R_2 , R_3 and R_4 and the anodes C of choppers $IGBT_1$, $IGBT_2$, $IGBT_3$ and $IGBT_4$, in turn; and

[0039] the cathodes of isolators D_5 and D_6 are simultaneously connected to the input terminal of current limiting inductor L_7 in amperite group 5, while the cathodes of isolator D_7 and D_8 are simultaneously connected to the input terminal of current limiting inductor L_8 in amperite group 5.

[0040] The connection points of isolators D_1 and D_5 , D_2 and D_6 , D_3 and D_7 , D_4 and D_8 connected in series in said isolator group 4 are respectively connected to the respective one end of capacitors C_{13} , C_{14} , C_{15} and C_{16} in power capacitor group 6, in turn, and a T-shaped structure is formed.

[0041] Said power capacitor group 6 comprises four capacitors, i.e., C_{13} , C_{14} , C_{15} and C_{16} , and the respective other end thereof simultaneously intersects the respective cathodes E of choppers $IGBT_1$, $IGBT_2$, $IGBT_3$ and $IGBT_4$ in chopper group 3 at one point, i.e., point D.

[0042] Said amperite group 5 comprises two current limiting inductors, i.e., L_7 and L_8 , and the output terminal of current limiting inductor L_7 is connected to the zero line end N of the three-phase industrial AC power supply, while the output terminal of current limiting inductor L_8 is simultaneously connected to one end of inductors L_4 , L_5 and L_6 in inverter 7 at one point.

[0043] It may also be seen from Fig.2A and Fig.2B that, the second embodiment of the invention consists, as a whole, of motor group 1, rectifier group 2, chopper group 3, isolator group 4, amperite group 5, power capacitor group 6, inverter 7, speed feedback

voltage detector group 8 and current feedback voltage detector group 9, wherein:

[0044] the respective rotors of the four motors M_1 , M_2 , M_3 and M_4 in said motor group 1 are respectively connected to the respective corresponding input terminals of the four rectifiers Z_1 , Z_2 , Z_3 and Z_4 in rectifier group 2 in turn;

5 **[0045]** the respective cathodes E of four choppers $IGBT_1$, $IGBT_2$, $IGBT_3$ and $IGBT_4$ in said chopper group 3 respectively intersect the anodes of the respective corresponding three rectifier diodes of four rectifiers Z_1 , Z_2 , Z_3 and Z_4 in rectifier group 2 at one point, i.e., point D, in turn;

[0046] Said inverter 7 is a half-bridge inverter, which comprises three silicon controlled
10 invertors, i.e., KP_1 , KP_2 and KP_3 , and via a circuit formed by connecting three fuses FU_1 , FU_2 and FU_3 with three inductors L_1 , L_2 and L_3 in series and then via the respective other end of three inductors L_1 , L_2 and L_3 , the respective cathodes thereof respectively intersect the respective cathodes E of four choppers $IGBT_1$, $IGBT_2$, $IGBT_3$ and $IGBT_4$ in chopper group 3 and the respective other end of four capacitors C_{13} , C_{14} ,
15 C_{15} and C_{16} in power capacitor group 6 at one point, i.e., point D, in turn.

[0047] Said inverter 7 is a half-bridge inverter, and the respective anodes of the three silicon controlled invertors KP_1 , KP_2 and KP_3 thereof are respectively connected to the ends A, B and C of a three-phase industrial AC power supply in turn, and then connected to the respective stators of the four motors M_1 , M_2 , M_3 and M_4 in motor group
20 1.

[0048] The output terminal of current limiting inductor L_7 in said amperite group 5 is connected to the zero line end N of an industrial AC power supply, and a three-phase zero-type active inversion bridge structure is formed.

[0049] The above embodiment only directs to illustrate the technical characteristics
25 and implementability of the invention. It must be noted that, in addition to being used by a crane to perform multiple different mechanism movements such as lifting, luffing, revolving and walking so as to accomplish the field operation task, the invention may also be applicable for any place where multiple motors need to be driven to asynchronously and simultaneously realize a real-time work, for example, the control on

different temperature and humidity in each weaving workshop of weaving industry; control on different flow and flow rate in each hydraulic power station; steel plate hoisting and splicing, component hole riveting, hull moving and overturning, weight float welding in shipbuilding industry; block hoisting of large-scale buildings and
5 block erection of petrochemical equipment and other fields. The scope of the claims should not be limited by the preferred embodiments set forth in the examples, but should be given the broadest interpretation consistent with the description as a whole.

What is claimed is:

1. A system for realizing rotor variable frequency speed control asynchronously and simultaneously by driving multiple motors via one inverter, the system comprising:

a motor group; a rectifier group; a chopper group; an isolator group; an amperite group; a power capacitor group; an inverter; a speed feedback voltage detector; and a current feedback voltage detector, wherein

the respective rotors of four motors M1, M2, M3 and M4 in said motor group are respectively connected to the respective corresponding input terminals of four rectifiers Z1, Z2, Z3 and Z4 in said rectifier group in turn,

the respective cathodes E of four choppers IGBT1, IGBT2, IGBT3 and IGBT4 in said chopper group respectively intersect with the anodes of the respective corresponding three rectifier diodes of four rectifiers Z1, Z2, Z3 and Z4 in said rectifier group at a point D, in turn,

said inverter is a full-bridge inverter, which comprises six silicon controlled inverters KP1, KP2, KP3, KP4, KP5 and KP6, and the three connection points of the output terminals KP1 and KP4, KP2 and KP5, KP3 and KP6 are respectively connected to the ends A, B and C of a three-phase industrial AC power supply in turn, and then connected to the respective stators of the four motors M1, M2, M3 and M4 in said motor group,

said isolator group comprises eight isolators D1, D2, D3, D4, D5, D6, D7, and D8, wherein isolators D1 and D5, isolators D2 and D6, isolators D3 and D7, and isolators D4 and D8 are respectively connected in series,

the respective anodes of said isolators D1, D2, D3 and D4 are respectively connected to the output terminals of the respective corresponding resistors R1, R2, R3 and R4 and the anodes C of said choppers IGBT1, IGBT2, IGBT3 and IGBT4, in turn, and

the cathodes of said isolators D5 and D6 are simultaneously connected to the input terminal of current limiting inductor L7 in said amperite group, while the cathodes of said isolators D7 and D8 are simultaneously connected to the input terminal of current limiting inductor L8 in said amperite group.

2. The system according to claim 1, wherein:

the connection points of said isolators D1 and D5, isolators D2 and D6, isolators D3 and D7, and isolators D4 and D8 connected in series in said isolator group are respectively connected to the respective one end of capacitors C13, C14, C15 and C16 in said power capacitor group in turn, and thus a T-shaped structure is formed.

3. The system for according to claim 1, wherein:

said power capacitor group comprises four capacitors C13, C14, C15 and C16, and the respective other end thereof simultaneously intersects with the respective cathodes E of said choppers IGBT1, IGBT2, IGBT3 and IGBT4 in said chopper group at said point D.

4. The system according to claim 1, wherein:

the output terminal of said current limiting inductor L7 is connected to the zero line end N of said three-phase industrial AC power supply, while the output terminal of said current limiting inductor L8 is connected to one end of said inductors L4, L5 and L6 at one point simultaneously.

5. A system for realizing rotor variable frequency speed control asynchronously and simultaneously by driving multiple motors via one inverter, the system comprising:

a motor group; a rectifier group; a chopper group; an isolator group; an amperite group; a power capacitor group; an inverter; a speed feedback voltage detector; and a current feedback voltage detector, wherein

the respective rotors of four motors M1, M2, M3 and M4 in said motor group are respectively connected to the respective corresponding input terminals of the four rectifiers Z1, Z2, Z3 and Z4 in said rectifier group in turn,

the respective cathodes E of the four choppers IGBT1, IGBT2, IGBT3 and IGBT4 in said chopper group respectively intersect with the anodes of the respective corresponding three rectifier diodes of the four rectifiers Z1, Z2, Z3 and Z4 in said rectifier group at a point D, in turn, and

said inverter is a half-bridge inverter, which comprises three silicon controlled inverters KP1, KP2 and KP3, and via a circuit formed by connecting three fuses FU1, FU2 and FU3 with three inductors L1, L2 and L3 in series and then via the respective

other end of said three inductors L1, L2 and L3, the respective cathodes thereof simultaneously intersect with the respective cathodes E of said four choppers IGBT1, IGBT2, IGBT3 and IGBT4 in said chopper group and the respective other end of the four capacitors C13, C14, C15 and C16 in said power capacitor group at said point D, in turn.

6. The system according to claim 6, wherein:

the respective anodes of said three silicon controlled inverters KP1, KP2 and KP3 are respectively connected to the ends A, B and C of a three-phase industrial AC power supply in turn, and then connected to the respective stators of said four motors M1, M2, M3 and M4 in said motor group.

7. The system according to claim 6, wherein:

the output terminal of current limiting inductor L7 in said amperite group is connected to the zero line end N of an industrial AC power supply, and thus a three-phase zero-type active inversion bridge structure is formed.

380V~




FIG. 1

(PRIOR ART)




FIG. 2A




FIG. 2B

N A B C

380V~

C
B
A

