

(12) **DEMANDE DE BREVET CANADIEN**
CANADIAN PATENT APPLICATION

(13) **A1**

(86) Date de dépôt PCT/PCT Filing Date: 2007/10/01
(87) Date publication PCT/PCT Publication Date: 2008/04/10
(85) Entrée phase nationale/National Entry: 2009/03/31
(86) N° demande PCT/PCT Application No.: JP 2007/069197
(87) N° publication PCT/PCT Publication No.: 2008/041675
(30) Priorités/Priorities: 2006/10/03 (JP2006-272352);
2006/11/01 (JP2006-298313);
2007/01/09 (JP2007-001855)


(51) **Cl.Int./Int.Cl.** *H04J 11/00* (2006.01),
H04B 1/707 (2006.01)

(71) **Demandeur/Applicant:**
NTT DOCOMO, INC., JP

(72) **Inventeurs/Inventors:**
KAWAMURA, TERUO, JP;
HIGUCHI, KENICHI, JP;
SAWAHASHI, MAMORU, JP

(74) **Agent:** OYEN WIGGS GREEN & MUTALA LLP

(54) Titre : DISPOSITIF UTILISATEUR, DISPOSITIF DE STATION DE BASE, ET PROCEDE
(54) Title: USER APPARATUS, BASE STATION APPARATUS AND METHOD



(57) **Abrégé/Abstract:**

A user device creates an uplink control channel including at least one of downlink transmission acknowledgment information and channel state information. When no resource is allocated for uplink data channel transmission, the uplink control channel is transmitted by a predetermined dedicated band. The uplink control channel includes a plurality of unit block sequences obtained by multiplying all the chips of the Casaque code sequence for the user device by the same factor.

ABSTRACT

A user apparatus generates an uplink control channel including at least one of acknowledgement
5 information and channel condition information on an
downlink, and transmits the uplink control channel in
a predefined dedicated band if no resource is assigned
to transmit an uplink data channel. The uplink control
channel includes multiple unit block sequences resulting
10 from multiplication of the same factor with all chips
of a CAZAC code sequence for the user apparatus.

DESCRIPTION

USER APPARATUS, BASE STATION APPARATUS AND METHOD

5 TECHNICAL FIELD

The present invention relates to the technical field of mobile communication and more particularly relates to user apparatuses, base station apparatuses and methods for use in mobile communication
10 systems.

BACKGROUND ART

In this technical field, some research and development on next-generation communication systems
15 have been intensively accelerated. In currently anticipated communication systems, a single-carrier scheme may be promising for use in uplinks from the viewpoint of wider coverage while avoiding increase in PAPR (peak-to-Average Power Ratio). Also in these
20 communication systems, both uplink and downlink radio resources may be assigned in channels shared between multiple users depending on respective communication conditions of the users. Operations for determining such assignment may be referred to as scheduling. For
25 appropriate scheduling in uplinks, each user apparatus transmits a pilot channel to a base station, and the base station evaluates channel condition of the uplinks based on reception quality. Also for scheduling in downlinks, the base station transmits a pilot channel to the user
30 apparatus, and the user apparatus informs the base station of information (CQI: Channel Quality Indicator) indicative of channel conditions based on reception quality of the pilot channel. The base station evaluates the channel conditions of the downlinks based on the CQIs

reported from the user apparatuses and accordingly schedules the downlinks.

Uplink control channels may include two types of control information, control information (requisite control information or first control information) that must be transmitted concomitantly to uplink data channels, and control information (second control information) that may be transmitted independent of the presence of the uplink data channels. The first control information may include information necessary to demodulate the data channels such as data channel modulation schemes and channel coding rates. The second control information may include downlink channel CQI information, downlink data channel acknowledgement information (ACK/NACK), resource assignment requests and/or others. Accordingly, the user apparatus may transmit only the first control information, only the second control information or both the first and second control information in the uplink control channels.

In the case where a resource block (radio resource) is assigned for transmission of the uplink data channel, the first control information (and the second control information as needed) may be transmitted in that resource block. On the other hand, if no uplink data channel is transmitted, it is assumed that the second control information is transmitted in a dedicated resource (dedicated band). Some examples of such band utilization are outlined below.

FIG. 1 illustrates exemplary uplink band utilization. In the illustrated example, two types of resource units of greater and smaller data sizes are provided. The larger resource unit may have a bandwidth F_{RB1} of 1.25 MHz and a duration T_{RB} of 0.5 ms. The smaller resource unit may have a bandwidth F_{RB2} of 375 kHz and

the duration T_{RB} of 0.5 ms. The duration may be referred to as a unit transmission period, a transmission time interval (TTI) or a subframe. The duration may correspond to duration of a single radio packet. Six
5 resources are arranged in the direction of frequency axis, and the smaller resources are arranged in the rightmost and leftmost locations. Various arrangement patterns of the resources can be designed as long as both the transmitter side and the receiver side have knowledge
10 of them. In the illustrated example, uplinks are scheduled to transmit control channels (first control channels) being concomitant to uplink data channels together with the second control channels as needed in partial intervals in the larger resources (second, third,
15 fourth and fifth resource blocks). Also in the smaller resources (first and sixth resources), transmission timings of user apparatuses are adjusted to transmit control channels (second control channels) for the case of no transmission of the uplink data channels. In
20 addition, two smaller resources are used to transmit the first control channel for a certain user apparatus. In the illustrated example, the second control channel for user apparatus A is transmitted in the sixth resource in the second subframe and the first resource in the third
25 subframe. Similarly, the second control channel for user apparatus B is transmitted in the sixth resource in the third subframe and the first resource in the fourth subframe. In this manner, the second control channels are transmitted such that they are hopped with respect
30 to the frequency axis and the time axis. As a result, time and frequency diversities can be obtained, resulting in higher reliability of successful demodulation of the second control channels at the base station.

FIG. 2 illustrates another exemplary uplink

band utilization. Similar to the example illustrated in FIG. 1, two types of resource units of greater and smaller data sizes are provided. In this example, the subframe duration T_{RB} is subdivided into two subintervals for the smaller resources (first and sixth resources). In the illustrated example, the second control channel for user apparatus A is transmitted in the first subinterval (the first half of the subframe interval) of the first resource in the first subframe and in the second subinterval (the second half of the subframe interval) of the sixth resource in the first subframe. The second control channel for user apparatus B is transmitted in the first subinterval of the sixth resource in the first subframe and in the second subinterval of the first resource in the first subframe. The same transmission may be also performed in the third and fifth subframes. In this manner, the second control channels are transmitted so that they are hopped with respect to the frequency axis and the time axis. As a result, time and frequency diversities can be obtained, resulting in higher reliability of successful demodulation of the second control channels at the base station. In addition, the transmission of the control channel for user apparatus A may be completed within the single subframe, and the transmission of the control channel for user apparatus B may be also completed within the single subframe. Thus, this example may be preferred from the viewpoint of shorter transmission latency of the uplink control channels. This technique is described in non-patent document 1 "3GPP, R1-061675", for example.

DISCLOSURE OF INVENTION

[PROBLEM TO BE SOLVED BY THE INVENTION]

In FIGS. 1 and 2, the smaller resources may

be illustrated in such a manner that the whole resource may be occupied by user apparatus A or B as "CONTROL A" and "CONTROL B", but the resource may be shared between several user apparatuses from the viewpoint of efficient utilization of the resource. For example, it can be conceived that the several user apparatuses share a dedicated band in accordance with frequency division multiplexing (FDM) scheme. If the multiplexing is simply effected in the FDM scheme for the users, however, a smaller band can be occupied for each of the users, and thus a smaller number of chips can be included in the band (lower chip rate). As a result, a smaller number of orthogonal code sequences can be used in a pilot channel to differentiate the user apparatuses, which may increase interference levels. In addition, if it is accepted that a transmission bandwidth of an uplink control channel may vary frequently depending on the amount of user multiplexing and/or others, a base station must transmit modified transmission bandwidths to the user apparatuses for individual modifications. This may increase the amount of downlink control information (signaling overhead) and accordingly decrease transfer efficiency of data channels. Also, it can be conceived that resources in a dedicated band may be shared in accordance with a code division multiplexing (CDM) scheme as applied in W-CDMA based mobile communication systems. In the CDM scheme, a wider band can be occupied by a single user. However, interference power level may become higher, resulting in degraded signal quality. If the same user multiplexes and transmits acknowledgement information (ACK/NACK) and channel condition information (CQI) in accordance with the CDM scheme, there may be a risk of increase in peak power.

One object of the present invention is to

obtain a larger number of orthogonal code sequences and reduce variations of transmission bands in multiplexing of uplink control channels from multiple user apparatuses in the case where the uplink control channels including
5 at least one of acknowledgement information (ACK/NACK) for downlink data channels and information (CQI) indicative of downlink channel conditions are transmitted from the user apparatuses in accordance with the single-carrier scheme.

10

[MEANS FOR SOLVING THE PROBLEM]

The present invention is applied to a user apparatus for transmitting at least an uplink control channel to a base station apparatus in accordance with
15 a single-carrier scheme. The user apparatus includes an acknowledgement information generation unit configured to generate acknowledgement information indicative of a positive response or a negative response to a downlink data channel, a channel condition generation unit
20 configured to generate channel condition information indicative of a downlink channel condition, a control channel generation unit configured to generate an uplink control channel including at least one of the acknowledgement information and the channel condition
25 information, and a transmission unit configured to transmit the uplink control channel in a predefined dedicated band if no resource is assigned to transmit an uplink data channel. The uplink control channel includes one or more unit blocks including a sequence
30 resulting from multiplication of a uniform factor with all chips of an orthogonal code sequence for the user apparatus.

[ADVANTAGE OF THE INVENTION]

According to the embodiments of the present invention, it is possible to obtain a larger number of orthogonal code sequences and reduce variations of transmission bands in multiplexing of uplink control channels from multiple user apparatuses in the case where the uplink control channels including at least one of acknowledgement information (ACK/NACK) for downlink data channels and information (CQI) indicative of downlink channel condition are transmitted from the user apparatuses in accordance with the single-carrier scheme.

BRIEF DESCRIPTION OF DRAWINGS

FIG. 1 illustrates exemplary band assignment for use in a mobile communication system;

FIG. 2 illustrates another exemplary band assignment for use in a mobile communication system;

FIG. 3 is a block diagram illustrating a user apparatus according to one embodiment of the present invention;

FIG. 4 illustrates exemplary arrangements of a TTI, subframes and blocks;

FIG. 5 illustrates exemplary arrangements of factors multiplied in long blocks LBs;

FIG. 6 is a diagram schematically illustrating characteristics of CAZAC codes;

FIG. 7 is a block diagram illustrating an exemplary base station apparatus according to one embodiment of the present invention;

FIG. 8 is a flowchart illustrating an exemplary operation according to one embodiment of the present invention;

FIG. 9 is a flowchart of exemplary identification of code information from broadcast

information and an assignment number;

FIG. 10 illustrates exemplary CAZAC codes, cyclic shift amounts and bands resulting from execution of the flowchart in FIG. 9;

5 FIG. 11 is a block diagram illustrating a user apparatus using block spreading codes according to one embodiment of the present invention;

FIG. 12 is a block diagram illustrating a base station apparatus using block spreading codes according
10 to one embodiment of the present invention;

FIG. 13 illustrates an exemplary arrangement of factors multiplied in long blocks;

FIG. 14 illustrates an exemplary arrangement of factors and block spreading codes in long blocks;

15 FIG. 15 illustrates exemplary arrangements of first through twelfth factors and block spreading codes multiplexed in long blocks;

FIG. 16 is a block diagram illustrating a user apparatus using block spreading codes according to one
20 embodiment of the present invention;

FIG. 17 illustrates transmission data sequences resulting from multiplication of orthogonal code sequences mapped to long blocks; and

FIG. 18 is a block diagram illustrating a base
25 station apparatus using block spreading codes according to one embodiment of the present invention.

LIST OF REFERENCE SYMBOLS

302: CQI estimation unit
30
304: ACK/NACK determination unit
306: block-wise modulation pattern
generation unit
308: block-wise modulation unit
310: discrete Fourier transform (DFT) unit

312: subcarrier mapping unit
 314: inverse fast Fourier transform (IFFT)
 unit
 316: cyclic prefix (CP) application unit
 5 318: multiplexing unit
 320: RF transmission circuit
 322: power amplifier
 324: duplexer
 330: code information identification unit
 10 332: CAZAC code generation unit
 334: cyclic shift unit
 335: block spreading unit
 336: frequency setting unit
 338: pilot signal generation unit
 15 340: transmission data sequence generation
 unit
 702: duplexer
 704: RF reception circuit
 706: reception timing estimation unit
 20 708: fast Fourier transform (FFT) unit
 710: channel estimation unit
 712: subcarrier demapping unit
 714: frequency domain equalization unit
 716: inverse discrete Fourier transform
 25 (IDFT) unit
 718: demodulation unit
 720: retransmission control unit
 722: scheduler
 724: code information setting unit

30

BEST MODE FOR CARRYING OUT THE INVENTION

According to one aspect of the present invention, an uplink control channel including at least one of acknowledgement information and channel condition

information is transmitted in a predefined dedicated band if no resource is assigned to transmit an uplink data channel. The uplink control channel includes several unit block sequences (long blocks) resulting from
5 multiplication of the same factor with all chips of an orthogonal code sequence (typically, a CAZAC code sequence) for a user apparatus. Thus, if the base station apparatus processes uplink control channels supplied from multiple user apparatuses on a per unit
10 block sequence, the base station apparatus can separate the user apparatuses appropriately without orthogonality among the user apparatuses. Since the acknowledgement information or the channel condition information may have a relatively small amount of
15 information, they can be fully represented in one or more factors multiplied with a CAZAC code.

According to one aspect of the present invention, an uplink control channel being not concomitant to an uplink data channel may include a CAZAC
20 code sequence resulting from a number of iterations corresponding to the number of long blocks as well as some multiplier factors and a pilot channel generated from the CAZAC code sequence. Thus, as long as the base station apparatus processes the uplink control channel
25 on a per long block basis or on a per short block basis, characteristics of the CAZAC code sequence would not be lost. This means that good orthogonality separation characteristics among user apparatuses is not only achieved but also the CAZAC codes for long blocks can
30 be used as reference signals for channel estimation, path search and/or others. Since not only a small number of short blocks including pilot channels but also a large number of long blocks included in uplink control channels are used for the channel estimation and/or others, it

is possible to significantly improve the accuracy of the channel estimation and/or the path search.

According to one aspect of the present invention, uplink control channels from a large number of user apparatuses may be multiplexed in accordance with a code division multiplexing (CDM) scheme or a frequency division multiplexing (FDM) scheme with CAZAC codes, but the CDM scheme is provided with higher priority. For this reason, transmission bands of user apparatuses have to be modified as little as possible. Under the FDM scheme in this case, a band may have to be divided less narrowly than $1/(\text{user multiplexing order})$. As a result, a larger number of code sequences for differentiating user apparatuses can be obtained while maintaining relatively wider transmission bands for uplink control channels. A smaller number of band types have to be provided in the FDM scheme, resulting in prevention of frequent modifications of the transmission bands. Another reason of preventing frequent modifications of the transmission bandwidth is that even if the transmission bandwidths of uplink control channels are frequently modified, it would be hard to significantly improve signal quality due to relatively smaller sizes of the acknowledgement information (ACK/NACK) and the channel condition information (CQI). Rather, it would be better to reduce overhead through infrequent modifications of the transmission bandwidths and focus on transmission power control for the signal quality.

According to one aspect of the present invention, an orthogonal code sequence may be represented in a set of factors (block spreading codes) multiplied with multiple unit blocks having the same contents. The unit block may include a sequence resulting from multiplication of the same factor (a factor provided

separately from the block spreading codes) with all chips of the orthogonal code sequence. The use of block spreading codes can further increase possible code multiplexing orders. Thereby, the effect of preventing frequent modifications of the transmission bands due to increase or decrease in user multiplexing orders can be further enhanced.

[First Embodiment]

FIG. 3 is a block diagram illustrating a user apparatus according to one embodiment of the present invention. In FIG. 3, a CQI estimation unit 302, an ACK/NACK determination unit 304, a block-wise modulation pattern generation unit 306, a block-wise modulation unit 308, a discrete Fourier transform (DFT) unit 310, a subcarrier mapping unit 312, an inverse fast Fourier transform (IFFT) unit 314, a cyclic prefix (CP) application unit 316, a multiplexing unit 318, a RF transmission circuit 320, a power amplifier 322, a duplexer 324, a code information identification unit 330, a CAZAC code generation unit 332, a cyclic shift unit 334, a frequency setting unit 336 and a pilot signal generation unit 338 are illustrated.

The CQI estimation unit 302 measures and supplies a measure indicative of downlink channel condition, that is, a channel quality indicator (CQI). The CQI may be derived, for example, by measuring reception quality (which may be represented as SIR, SINR or others) of a pilot channel transmitted from a base station and converting the measured reception quality into a numerical value. For example, the measured reception quality (SIR) may be converted into a numerical value indicating which one in 32 levels the reception quality is classified into and may be accordingly derived

as a CQI represented in form of 5 bits.

The ACK/NACK determination unit 304 determines whether each packet in a received downlink data channel includes an error and supplies the determination result as acknowledgment information. The acknowledge information may be represented as either acknowledgement (ACK) indicating that the packet has no error or non-acknowledgement (NACK) indicating that the packet has an error. The acknowledgement information has only to represent the presence of an error in the received packet. Accordingly, the acknowledgement information can be represented in one bit but may be represented in more than one bit.

The block-wise modulation pattern generation unit 306 generates block-wise modulation patterns from the CQI and the acknowledgement information (ACK/NACK). A predefined number of blocks are included in a subframe, and in turn several subframes may constitute a transmission time interval (TTI) serving as a resource assignment unit.

FIG. 4 illustrates exemplary arrangements of a TTI, subframes and blocks. In this illustration, the TTI of 1.0 ms includes two subframes of 0.5 ms, and each of the subframes includes six long blocks (LBs) and two short blocks (SBs). For example, the long block may have a duration of $66.7 \mu s$, and the short block may have a duration of $33.3 \mu s$. These numerical values are simply illustrative and can be modified as needed. In general, the long block is used to transmit data (control channels, data channels or others) unknown at the receiver side, and the short block is used to transmit data (pilot channels or others) known at the receiver side. In the illustrated example, one TTI is configured to have twelve long blocks (LB1-LB12) and four short blocks (SB1-SB4).

The block-wise modulation pattern generation unit 306 in FIG. 3 determines correspondence between one or more of the twelve long blocks (LB1-LB12) and bits for representing the CQI and correspondence between one or more of the twelve long blocks (LB1-LB12) and bits for representing the acknowledgement information (ACK/NACK). The user apparatus has several cases of transmission in uplink control channels, that is, a case of transmission of only the CQI, a case of transmission of only the acknowledgement information (ACK/NACK), and a case of transmission of both the CQI and the acknowledgement information. Thus, (A) all the twelve blocks may be associated with the CQI, (B) all the twelve blocks may be associated with the acknowledgement information, and/or (C) some of the twelve blocks may be associated with the CQI and the others may be associated with the acknowledgement information. Even in any of the cases, one factor is provided in each of the twelve blocks, and a total of twelve factors (first through twelfth factors) are provided in one TTI.

FIG. 5 illustrates exemplary arrangements of factors associated with long blocks (LBs). In the illustrated (A), only the acknowledgement information (ACK/NACK) is transmitted. In one embodiment, "1"s are assigned to all the twelve factors for positive acknowledgement (ACK), and "-1"s are assigned to all the twelve factors for negative acknowledgement (NACK). In FIG. 5, a combination of factors "1"s and "-1"s is illustrated for another example of the negative acknowledgement (NACK). These specific values for the factors are simply illustrative, and any other values for the factors can be used as long as the twelve factors for the positive acknowledgement are differentiated in total from the twelve factors for the negative

acknowledgement. Also, the acknowledgement information does not have to be represented in the twelve factors and can be represented in one or more factors. In some embodiments, ACK/NACK may be differentiated from each other in one factor. In other embodiments, ACK/NACK may be differentiated from each other in two factors such as (+1, +1) and (+1, -1). In other embodiments, ACK/NACK may be differentiated from each other in more than two factors. It may be the easiest determination that one factor is used to differentiate between ACK and NACK. From the viewpoint of improved determination precision, phase change of multiple factors is preferably used to differentiate between ACK and NACK. Further, the factors are not limited to "+1" and "-1" and may be any other complex numbers. Note that the factors "+1" and "-1" are advantageous in that simple sign inversion is enabled. This is why the same factor can be multiplied with all chips of a certain CAZAC code sequence as described below.

20 In the case where a base station has misidentified ACK as NACK, an unnecessary packet may be potentially retransmitted to the user apparatus. On the other hand, in the case where the base station has misidentified NACK as ACK, the user apparatus potentially cannot receive a packet necessary for packet combination, which may lead to packet loss and/or degrade quality significantly through the improper packet combination of new packets. Therefore, ACK/NACK patterns as represented in one or more factors are preferably set to prevent more significant misidentification of NACK as ACK.

In the illustrated (B), only the CQI is transmitted. In the illustration, the CQI is represented in five bits, and it is assumed that the

individual bits are represented as CQI1, CQI2, CQI3, CQI4 and CQI5 in descending order from the upper bit. One long block is associated with any bit of the five bits. In other words, a factor for each of the twelve blocks may
5 be any of the CQI1 through CQI5. In the illustration, one TTI is designed to transmit upper bits more times than or equal to lower bits. The most significant bit CQI1 is assigned to four blocks, CQI2 is assigned to three blocks, CQI3 is assigned to two blocks, CQI4 is also
10 assigned to two blocks, and the lowest significant bit CQI5 is assigned to one block. In this manner, even if some errors occur, the CQI values can be prevented from varying drastically.

In the illustrated (C), the acknowledgement
15 information (ACK/NACK) and the CQI are transmitted in the same TTI from the same user. In the illustration, three blocks are associated with the acknowledgement information (ACK/NACK), and the remaining nine blocks are associated with the CQI. Even in the case where the
20 same user transmits the acknowledgement information (ACK/NACK) and the CQI, if several TTIs are available, the schemes (A) and (B) may be used. Also, when the channel condition becomes worse, for example, when a user moves from the cell center to the cell edge, the user
25 may stop reporting the CQI and supply only feedback of ACK/NACK. Information items to be transmitted in uplink control channels may be modified as needed, for example, through signaling from an upper layer.

In this manner, the block-wise modulation
30 pattern generation unit 306 in FIG. 3 provides one factor for each of the twelve blocks and accordingly provides twelve factors (first factor through twelfth factor) in total for one TTI.

The block-wise modulation unit 308 in FIG. 3

multiplies the first factor with all chips of a CAZAC code sequence (whose length can be associated with the length of one long block) assigned to the user apparatus to arrange the first long block, multiplies the second
5 factor with all chips of the same CAZAC code sequence to arrange the second long block, and so on. Similarly, the block-wise modulation unit 308 arranges the twelfth long block by multiplying the twelfth factor with all chips of the same CAZAC code sequence and finally derives
10 an informational sequence transmitted in one TTI. The CAZAC code sequence commonly used for all the blocks is an orthogonal code sequence assigned in a residing cell to identify the user apparatus, and some characteristics are described below.

15 The discrete Fourier transform (DFT) unit 310 performs discrete Fourier transform to convert time-series information into frequency domain information.

 The subcarrier mapping unit 312 performs
20 mapping in the frequency domains. In particular, if a frequency division multiplexing (FDM) scheme is used to multiplex multiple user apparatuses, the subcarrier mapping unit 312 maps signals to a band assigned in the frequency setting unit 336. The FDM scheme includes two
25 types of FDM schemes, that is, a localized FDM scheme and a distributed FDM scheme. In the localized FDM scheme, successive bands on the frequency axis are assigned to an individual user. In the distributed FDM scheme, downlink signals are generated to have multiple
30 discontinuous frequency components distributed across a wide band (a dedicated band F_{RB2} to uplink control channels).

 The inverse fast Fourier transform (IFFT) unit 314 performs inverse Fourier transform to inversely

convert frequency domain signals into time domain signals.

The cyclic prefix (CP) application unit 316 applies a cyclic prefix (CP) to information to be transmitted. The cyclic prefix (CP) serves as a guard interval to absorb multipath propagation delay and some differences of reception timings between several users at a base station.

The multiplexing unit 318 multiplexes the information into a pilot channel to generate transmission symbols. The pilot channel is transmitted in short blocks (SB1, SB2) illustrated as the frame configuration in FIG. 4.

The RF transmission circuit 320 performs digital-analog conversion, frequency conversion, band limiting and/or others to transmit the transmission symbols in a radio frequency.

The power amplifier 322 adjusts transmission power.

The duplexer 324 splits into transmission signals and reception signals for simultaneous communication.

The code information identification unit 330 identifies code information including a CAZAC code sequence (sequence number) for use in the user apparatus, a cyclic shift amount of the CAZAC code sequence and transmission band related information. The code information may be derived from broadcast information supplied via broadcast channels or transmitted from a base station separately. Such separate transmission may be performed through signaling from an upper layer such as a L3 control channel. As described in the second embodiment below, the code information identification unit 330 determines which orthogonal code sequence is

represented by a set of factors (block spreading code) multiplied with multiple blocks.

The CAZAC code generation unit 332 generates a CAZAC code sequence in accordance with a sequence number
5 specified in the code information.

The cyclic shift unit 334 derives other codes by rearranging the CAZAC code sequence in a cyclic manner in accordance with the cyclic shift amount specified in the code information.

10 CAZAC codes are overviewed below.

As illustrated in FIG. 6, it is assumed that a certain CAZAC code A has L in code length. For convenience, it is assumed that the code length corresponds to a duration of L samples or L chips, but
15 this assumption is not essential to the present invention. A sequence of Δ samples (illustrated in a shaded portion) including an end or L-th sample of a CAZAC code A is shifted to the head of the CAZAC code A, resulting in another code B as illustrated in the lower portion of FIG. 6. In this case, the CAZAC codes A and B are mutually orthogonal with respect to Δ ($\Delta = 0, \dots, (L-1)$). In other words, a certain CAZAC code and a code resulting from cyclical shift of that CAZAC code will be mutually
20 orthogonal. Thus, if one CAZAC code sequence of the code length L is provided, a set of L mutually orthogonal codes can be theoretically provided. A certain CAZAC code A is not orthogonal to another CAZAC code C that cannot be obtained through cyclic shift of the CAZAC code A. However, the cross-correlation value between the CAZAC
25 code A and a random code not being any CAZAC code may be significantly greater than that between the CAZAC code A and the CAZAC code C. Thus, the CAZAC code may be preferred from the viewpoint of reduction in the cross-correlation (interference) between codes being
30

not mutually orthogonal.

In this embodiment, each user apparatus uses a CAZAC code selected among a set of CAZAC codes having the above-mentioned characteristic, that is, a set of
 5 code sequences derived by cyclically shifting a certain CAZAC code. In this embodiment, L/L_{Δ} codes obtained by cyclically shifting a basic CAZAC code in a set of L mutually orthogonal codes by Δ ($\Delta = n \times L_{\Delta}$ and $n = 0, 1, \dots, (L-1)/L_{\Delta}$) are actually used as a pilot channel of a mobile
 10 station. The value of L_{Δ} is determined based on the amount of multipath propagation delay. In this manner, uplink control channels transmitted from individual user apparatuses can properly maintain mutual orthogonality relationship even under multipath propagation
 15 environments. The CAZAC codes are described in detail in D.C.Chu, "Polyphase codes with good periodic correlation properties", IEEE Trans. Inform. Theory, vol.IT-18, pp. 531-532, July 1972; 3GPP, R1-050822, and Texas Instruments, "On allocation of uplink sub-channels
 20 in EUTRA SC-FDMA", for example.

The frequency setting unit 336 in FIG. 3 indicates which frequency each user apparatus uses if the FDM scheme is applied to uplink control channels from multiple user apparatuses.

25 The pilot signal generation unit 338 supplies a pilot channel to be included in an uplink control channel. As mentioned above, the pilot channel is transmitted in short blocks (SB1, SB2) illustrated in the frame configuration in FIG. 4. The pilot channel is
 30 also arranged in any CAZAC code assigned to each user apparatus. The CAZAC code for the pilot channel may be specified by a sequence number and a cyclic shift amount. In general, the long block and the short block have different lengths, different durations or different

numbers of chips, and thus a CAZAC code C_L in the long block (LB) and a CAZAC code C_S in the short block may be separately provided. Note that the same user apparatus uses both the short block and the long block, there may
5 be some relationship between the CAZAC codes C_L and C_S . For example, a portion of the C_L may be included in the C_S .

FIG. 7 illustrates a base station apparatus according to one embodiment of the present invention.
10 In FIG. 7 a duplexer 702, a RF reception circuit 704, a reception timing estimation unit 706, a fast Fourier transform (FFT) unit 708, a channel estimation unit 710, a subcarrier demapping unit 712, a frequency domain equalization unit 714, an inverse discrete Fourier
15 transform (IDFT) unit 716, a demodulation unit 718, a retransmission control unit 720, a scheduler 722 and a code information setting unit 724 are illustrated.

The duplexer 702 splits into transmission signals and reception signals for simultaneous
20 communication.

The RF reception circuit 704 performs digital-analog conversion, frequency conversion, band limiting and/or others for processing reception symbols in a baseband.

25 The reception timing estimation unit 706 identifies a reception timing based on a synchronization channel or a pilot channel in a reception signal.

The fast Fourier transform (FFT) unit 708 performs Fourier transform and converts time-series
30 information into frequency domain information.

The channel estimation unit 710 estimates uplink channel condition based on reception condition of an uplink pilot channel and supplies information for channel compensation.

The subcarrier demapping unit 712 performs demapping in frequency domains. This operation is performed corresponding to mapping in the frequency domains performed by individual user apparatuses.

5 The frequency domain equalization unit 714 performs equalization on reception signals based on channel estimation values.

 The inverse discrete Fourier transform (IDFT) unit 716 performs inverse Fourier transform for
10 conversion of the frequency domain signals into time domain signals.

 The demodulation unit 718 demodulates reception signals. In this embodiment, uplink control channels are demodulated, and the CQI for downlink
15 channels and/or acknowledgement information (ACK/NACK) to downlink data channels are supplied.

 The retransmission control unit 720 provides a new packet or a retransmission packet corresponding to the acknowledgement information (ACK/NACK).

20 The scheduler 722 determines assignment of downlink resources based on the CQI for downlinks and/or other criteria. Also, the scheduler 722 determines assignment of uplink resources based on reception results of pilot channels transmitted from user apparatuses
25 and/or other criteria. The determined assignment is supplied as scheduling information. The scheduling information specifies a frequency, a duration, a transmission format (data modulation scheme, channel coding rate and/or others) for signal transmission.

30 Based on the assignment determined by the scheduler 722, the code information setting unit 724 specifies code information including a sequence number indicative of an uplink CAZAC code for use in a user apparatus, a cyclic shift amount, an available frequency

band and/or others. The code information may be commonly transmitted to the user apparatuses via broadcast channels or indicated individually to the user apparatuses. In the former case, it is required that
5 each user apparatus can uniquely derive the code information for the user apparatus itself from the broadcast information.

FIG. 8 illustrates an operation according to one embodiment of the present invention. In this
10 exemplary operation, general code information relating to all user apparatuses is transmitted in broadcast channels. Each of the user apparatuses uniquely derives code information specific to itself from the broadcast information. The general code information may include
15 an information item indicating that N CAZAC code sequences ($C\#1, C\#2, \dots, C\#N$) are used in a cell, an information item indicating that M cyclic shift amounts ($0, L_A, \dots, (M-1) \times L_A$) are possible for each sequence, an information item indicating that the FDM scheme is used
20 and F bands ($Bw1, Bw2, \dots, BwF$) are available, and/or other information items, for example.

At step B1, the base station apparatus performs downlink scheduling to transmit a downlink control channel (L1/L2 control channel), a downlink data
25 channel and a pilot channel to a user apparatus.

At step M1, the user apparatus identifies information (code information for that user apparatus) on codes for use in an uplink control channel based on information in the downlink control channel.

30 FIG. 9 illustrates an exemplary identification for identifying the code information available in step M1. For simplicity, two CAZAC code sequences ($C\#1, C\#2$) are provided. Also, three cyclic shift amounts ($0, L_A, 2L_A$) are provided for each of the

sequences. Also, two available bands ($Bw1$, $Bw2$) are provided. Accordingly, twelve ($2 \times 3 \times 2 = 12$) user apparatuses can be differentiated. These values are simply illustrative, and any other appropriate values
 5 may be used.

At step S1, a user apparatus checks an assignment number P ($=1, 2, \dots, 12$) for the user apparatus itself as specified in a downlink L1/L2 control channel.

At step S2, the user apparatus determines
 10 whether the assignment number P is greater than 3. If the determination is NO ($P=1, 2, 3$), the user apparatus determines that the sequence number $C\#1$, the cyclic shift amount $(P-1) \times L_{\Delta}$ and the band $Bw1$ are assigned. On the other hand, if the assignment number is greater than 3,
 15 the process control proceeds to step S3.

At step S3, the user apparatus determines whether the assignment number P is greater than 6. If the determination is NO ($P=4, 5, 6$), the user apparatus determines that the sequence number $C\#1$, the cyclic shift
 20 amount $(P-4) \times L_{\Delta}$ and the band $Bw2$ are assigned. On the other hand, if the assignment number is greater than 6, the process control proceeds to step S4.

At step S4, the user apparatus determines whether the assignment number P is greater than 9. If
 25 the determination is NO ($P=7, 8, 9$), the user apparatus determines that the sequence number $C\#2$, the cyclic shift amount $(P-7) \times L_{\Delta}$ and the band $Bw1$ are assigned. On the other hand, if the assignment number is greater than 9 ($P=10, 11, 12$), the user apparatus determines that the
 30 sequence number $C\#2$, the cyclic shift amount $(P-10) \times L_{\Delta}$ and the band $Bw2$ are assigned.

FIG. 10 illustrates exemplary CAZAC codes, cyclic shift amounts and bands resulting from execution of the flowchart in FIG. 9. As illustrated, user

apparatuses are first multiplexed in accordance with a code division multiplexing (CDM) scheme under the same CAZAC code sequence. If the number of user apparatuses additionally increases, the user apparatuses are

5 code-multiplexed in another band under the same CAZAC code sequence. Then, the CDM scheme is applied to each of the available bands. In other words, although both the CDM and the FDM are applied, the application of the CDM is provided with higher priority. In the case where

10 user apparatuses are multiplexed exceeding the number of user apparatuses that can be differentiated under a certain CAZAC code sequence in accordance with the CDM and the FDM schemes, another CAZAC code sequence is provided, and these user apparatuses are multiplexed in

15 accordance with the CDM and/or the FDM schemes. It is assumed that N CAZAC code sequences ($C\#1, C\#2, \dots, C\#N$) are used within a cell, M cyclic shift amounts ($0, L_\Delta, \dots, (M-1) \times L_\Delta$) are provided for each of the sequences, the FDM scheme is applied, and F bands ($Bw1, Bw2, \dots, BwF$) are available. Under these assumptions, a sequence

20 number of the CAZAC code is represented as an integer resulting from rounding up of $(P/(M \times F))$. The $((P - (n-1) \times (M \times F)) / M)$ -th band is used. The cyclic shift amount is represented as a product of L_Δ and $(P - ((n-1) \times (M \times$

25 $F)) - (f-1) \times M = P \bmod M$.

In the embodiment illustrated in conjunction with FIGS. 9 and 10, when assignment number or user multiplexing order exceeds three, another band $Bw2$ starts to be used. On the other hand, even if the user

30 multiplexing order is greater than three and less than or equal to six, the same band $Bw1$ may be used and another CAZAC code sequence $C\#2$ may be instead used. The CAZAC codes $C\#1$ and $C\#2$ have the relationship that they cannot be derived from each other through cyclic shift and are

not mutually orthogonal. On the other hand, the CAZAC codes C#1 and C#2 have a relatively cross-correlation value.

In this manner, code information for each user apparatus can be identified from the broadcast information and the assignment information P. The identified code information is transmitted to the CAZAC code generation unit 332, the cyclic shift unit 334, the frequency setting unit 336 and the pilot signal generation unit 338 in FIG. 3.

At step M2 in FIG. 8, the user apparatus determines whether each packet in a downlink data channel includes an error. This error determination may be realized in a CRC (Cyclic Redundancy Check) scheme, for example. Alternatively, the error determination may be realized in any other appropriate error detection schemes as well known in the art. The user apparatus determines which of a positive response (ACK) indicative of no error (or if an error occurs, the error is acceptable) and a negative response (NACK) indicative of the presence of an error is to be replied for each packet. The acknowledgement information is configured from the positive response (ACK) and the negative response (NACK).

At step M3, the user apparatus measures reception quality of a downlink pilot channel and derives the CQI through conversion the measured reception quality into a numerical value within a certain range. For example, if the reception quality is represented in 32 levels, the CQI represented in 5 bits can be derived through conversion of the current reception quality such as SIR into a numerical value indicating which level the reception quality belongs to.

Steps M2 and M3 are not necessarily performed in that order. The determination of the acknowledgement

information and the measurement of the CQI may be performed at any suitable time points.

At step M4, an uplink control channel is generated to indicate one or both of the acknowledgement information (ACK/NACK) and the CQI to the base station. As mentioned above, the block-wise modulation pattern generation unit in FIG. 3 provides one factor for each of 12 blocks and thus will provide 12 factors (first to twelfth factors) in total for each TTI. One or more of the twelve factors represent the acknowledgement information or the CQI. The uplink control channel may have the frame arrangement as illustrated in FIGS. 4 and 5. For example, the first long block (LB1) is generated by multiplying the first factor across one (cyclically shifted) CAZAC code sequence assigned to the user apparatus. The second long block (LB2) is generated by multiplying the second factor with the same CAZAC code sequence. Similarly, the K-th long block (LBK) is generated by multiplying the k-th factor with the same CAZAC code sequence. In this manner, a frame for the uplink control channel is configured to have the twelve long blocks.

The uplink control channel generated as mentioned above is transmitted from the user apparatus to the base station in a dedicated band.

At step B2, the base station apparatus receives and demodulates the uplink control channels from multiple user apparatuses. Although the user apparatuses transmit the similar uplink control channels, the user apparatuses may use CAZAC code sequences of different cyclic shift amounts, different bands or different CAZAC code sequences. As mentioned above, only one factor is totally multiplied with the CAZAC code sequence for different long blocks, and thus the base

station apparatus can add the uplink control channels received from the user apparatuses in the same phase. As a result, the orthogonality between CAZAC codes with different cyclic shift amounts of the same sequence can be maintained, and thus the base station apparatus can orthogonally separate individual signals from the user apparatuses. Even if non-orthogonal CAZAC codes are used, the user apparatuses can be differentiated at an interference level lower than random sequences. In addition, the base station apparatus can determine contents of the acknowledgement information and/or the CQI by determining the first through twelfth factors used in the uplink control channels for the respective user apparatuses.

At step B3, the base station apparatus performs retransmission control, resource assignment and/or other operations based on the acknowledgement information (ACK/NACK) and/or the CQI transmitted from the user apparatus in the uplink control channel.

20

[Second Embodiment]

FIG. 11 is a block diagram illustrating a user apparatus using block spreading codes according to the second embodiment of the present invention. The illustrated user apparatus is the almost same as the user apparatus in FIG. 3, but they differ in utilization of a block spreading code (BLS). The user apparatus in FIG. 11 includes a block spread unit 335. The block spread unit 335 provides a set of a predefined number of factors (block spreading codes), each of which is multiplied with each long block (LB). The block spreading code is an orthogonal code sequence, and information supplied from the code information identification unit 330 specifies which orthogonal code sequence is used.

FIG. 12 illustrates a base station apparatus using block spreading codes according to the second embodiment of the present invention. The illustrated base station apparatus is the almost same as the base station apparatus in FIG. 7, but they differ in
 5 utilization of a block spreading code (BLS). The base station apparatus in FIG. 12 specifies information (code information) indicating which block spreading code is used as well as a sequence number indicative of a CAZAC
 10 code sequence, a cyclic shift amount and an available frequency band.

FIG. 13 illustrates exemplary subframes for a first user apparatus UE1 and a second user apparatus UE2 without multiplication of block spreading codes.
 15 Although the first and second user apparatuses use a certain CAZAC code sequence (CAZAC1), the first and the second user apparatuses use different cyclic shift amounts Δ . Accordingly, two subframes transmitted from the user apparatuses are mutually orthogonal. "Mod.a"
 20 represents data, that is, a multiplier factor, modulated into the first long block for the first user apparatus UE1. "Mod.a" to "Mod.f" correspond to the first to sixth factors (or the seventh to eighth factors) for the first user apparatus UE1. "Mod.u" to "Mod.z" correspond to the
 25 first to sixth factors (or the seventh to eighth factors) for the second user apparatus UE2.

FIG. 14 illustrates one example where block spreading codes are multiplied with individual long blocks for the first and second user apparatuses UE1,
 30 UE2. In the illustrated example, a certain factor is provided for each of the long blocks for the user apparatuses (in addition to modulation data). This factor constitutes a block spreading code (BLSC), and as enclosed in dashed boxes in the illustration,

orthogonal codes (1, 1) and (1, -1) are provided for the first and second user apparatuses UE1, UE2, respectively. As mentioned in conjunction with the first embodiment, as long as the same factor (value) are multiplied with one or more long blocks, a CAZAC code for arranging the long blocks maintains orthogonality. Thus, if a set of factors multiplied with each of the several blocks are arranged to be orthogonal between the user apparatuses, individual codes for the user apparatuses can be made orthogonal while maintaining the orthogonality of the CAZAC codes. Note that multiple blocks multiplied with one orthogonal code must have the same contents. In the illustrated example, the first and second factors for the first user apparatus UE1 are commonly "Mod.a", the third and fourth factors are commonly "Mod.b", and the fifth and sixth factors are commonly "Mod.c". Similarly, the first and second factors for the second user apparatus UE2 are commonly "Mod.x", the third and fourth factors are commonly "Mod.y", and the fifth and sixth factors are commonly "Mod.z". For this reason, a limited amount of information can be carried in the first and twelfth factors, but since a relatively smaller number of bits are required to represent ACK/NACK and/or others as mentioned in conjunction with FIG. 5, this restriction is not crucial.

Since the block spreading codes (1, 1) and (1, -1) can be used to differentiate the first and second user apparatuses UE1 and UE2, the same shift amount for the CAZAC codes may be used for the first and second user apparatuses. In other words, it is unnecessary to use different cyclic shift amounts Δ . For convenience, factors multiplied with long blocks have been described, but some factors may be multiplied with short blocks (SBs).

FIG. 15 illustrates exemplary arrangement of the first through twelfth factors and block spreading codes. In FIG. 15 (1), a similar example as FIG. 14 is illustrated, and it is assumed that an ACK as illustrated in FIG. 5 is represented by the first through twelfth factors. Further, in FIG. 15 (1), an orthogonal code sequence is multiplied for each pair of blocks, and the first and second user apparatuses can be differentiated.

In FIG. 15 (2), an exemplary case of the orthogonal spreading code length being equal to four is illustrated. In this case, four factors are multiplexed with four long blocks, and four user apparatuses are code-multiplexed. In the illustrated example, four orthogonal codes $(+1, +1, +1, +1)$, $(+1, -1, +1, -1)$, $(+1, +1, -1, -1)$ and $(+1, -1, -1, +1)$ are used. As mentioned above, in subframes transmitted from user apparatuses, the same data (for example, "Mod.a" for the first user apparatus) has to be modulated in four blocks. In this manner, the code length is not limited to two or four, and orthogonal codes of any other appropriate lengths may be used. The code length may be determined on the base station apparatus depending on the number of user apparatuses, bands and/or others, for example.

In FIG. 15 (3), an exemplary case of transmission of the CQI is illustrated. Similar to the case in FIG. 5 (B), individual bits for representing the CQI are illustrated as CQI1 through CQI5.

In this case, any appropriate orthogonal codes may be used. As illustrated, components of the orthogonal code may be "+1" and "-1" or may be represented as a phase factor such as $(1, 1, 1)$, $(1, \exp(j2\pi/3), \exp(j4\pi/3))$, and $(1, \exp(j4\pi/3), \exp(j2\pi/3))$.

According to this embodiment, a larger number of orthogonal multiplexing orders can be achieved than

those of the first embodiment by using not only cyclic shift amounts of CAZAC codes but also block spreading codes. In the case where the CDM and FDM schemes are used together, the CDM scheme increases the number of
5 available multiplexing orders, which may further reduce bandwidth modifications caused by application of the FDM scheme. Thus, it is possible to make reporting of the bandwidth modifications less frequent and reduce involved consumption of radio resources.

10

[Third Embodiment]

FIG. 16 illustrates a user apparatus using block spreading codes according to the third embodiment of the present invention. The illustrated user
15 apparatus differs from the user apparatus in FIG. 11 in that the user apparatus in FIG. 16 can transmit several bits to several tens of bits of information in one long block. The user apparatus in FIG. 16 includes a transmission data sequence generation unit 340 instead
20 of the block-wise modulation pattern generation unit. Also, the illustrated user apparatus does not use CAZAC sequences, and thus the CAZAC code generation unit 332 and the cyclic shift unit 334 are omitted.

The transmission data sequence generation
25 unit 338 generates a data sequence indicative of the acknowledgement information (ACK/NACK) or the CQI.

The block-wise modulation unit 308 associates a transmission data sequence supplied from the transmission data sequence generation unit 340 with one
30 long block and multiplies each long block with an orthogonal code sequence. Then, the block-wise modulation unit 308 multiplies each of the long blocks multiplied with the orthogonal code sequence with a set of a predefined number of factors (block spreading codes)

provided by a block spread unit 335 as described below.

The block spread unit 335 provides the set of factors (block spreading codes) and multiplies each of the factors with each long block (LB). The block spreading codes are orthogonal code sequences, and information supplied from the code information identification unit 330 specifies which orthogonal code sequence is used.

FIG. 17 illustrates exemplary generation of transmission data sequences multiplied with orthogonal code sequences mapped to long blocks.

Several bits to several tens of bits of data sequence indicative of the acknowledgement information (ACK/NACK) or the CQI, for example, " $a_1, a_2, \dots, a_N$ " (N is a positive integer), are generated. Also, an orthogonal sequence " $C_1, C_2, C_3, C_4, \dots, C_M$ " (M is a positive integer) is provided. For example, if the spreading rate is equal to M , " $C_1, C_2, C_3, \dots, C_M$ " is provided. An exemplary case of the spreading rate of four is described below, the present embodiment can be similarly applied to other cases of the spreading rate other than four.

An orthogonal sequence is multiplied with a data sequence. In other words, multiplications " $a_1 \times C_1$ ", " $a_1 \times C_2$ ", " $a_1 \times C_3$ ", " $a_1 \times C_4$ ", " $a_2 \times C_1$ ", ..., " $a_4 \times C_4$ " are carried out. Then, reordering is carried out for each multiplied orthogonal sequence.

As a result, a number of blocks corresponding to the spreading rate (spreading code sequence) are generated where the orthogonal sequence is multiplied with the data sequence. These blocks are mapped to long blocks and then are multiplied with the block spreading code.

In the user apparatuses according to the first and second embodiments, only one bit of information can

be transmitted in each long block. In this embodiment, however, several bits of information, for example, N bits of information, can be transmitted.

For example, in the case where the spreading rate is equal to four and transmission information has four bits, four bits can be transmitted in four long blocks, which may be substantially the same as transmission of one bit of information in one long block. However, in the case where the spreading rate is equal to four and transmission information has 12 bits, 12 bits can be transmitted in four long blocks, which means that three bits of information can be substantially transmitted in one long block.

FIG. 18 illustrates a base station apparatus using block spreading codes according to the third embodiment of the present invention. The illustrated base station apparatus is the almost same as the base station apparatus in FIG. 12, but they differ in that the base station apparatus in FIG. 18 does not have to set a sequence number indicative of a CAZAC code sequence and a cyclic shift amount. In the base station apparatus in FIG. 18, a code information setting unit 724 specifies information (code information) indicating which frequency band is available and what block spreading code is used.

Also in this embodiment, the block spreading code can be used to differentiate user apparatuses. For example, if the orthogonal spreading code length is equal to four, four factors are multiplied with each four long blocks. For example, if four user apparatuses are code-multiplexed, four orthogonal codes (+1, +1, +1, +1), (+1, -1, +1, -1), (+1, +1, -1, -1) and (+1, -1, -1, +1) are used. The code length is not limited to four, and orthogonal codes of any other appropriate lengths may

be used. The code length may be determined in the base station apparatus depending on the number of user apparatuses, bands and/or others, for example.

Note that any appropriate orthogonal codes
5 may be used. As illustrated, code components may be "+1" and "-1" or may be represented as a phase factor such as $(1, 1, 1)$, $(1, \exp(j2\pi/3), \exp(j4\pi/3))$, and $(1, \exp(j4\pi/3), \exp(j2\pi/3))$.

According to this embodiment, the block
10 spreading codes are used for orthogonal CDM transmission, and thus a larger number of bits can be transmitted than the first and second embodiments using cyclic shift amounts for CAZAC sequences.

Also, user apparatuses can be differentiated
15 through orthogonal codes (block spreading codes) multiplied among long blocks.

Also, orthogonal CDM is enabled through block spreading for other sequences where the block spreading is applied, for example, other sequences generated
20 through cyclic shift of CAZAC sequences as mentioned in conjunction with the second embodiment.

For convenience, the present invention has been described with reference to the distinct embodiments, but separation of the embodiments is not essential to
25 the present invention and two or more of the embodiments may be used together as needed. Some specific numerals have been used to facilitate understanding of the present invention, but unless otherwise noted, these numerals are simply illustrative and any other appropriate values
30 may be used.

The present invention has been described with reference to the specific embodiments of the present invention, but the embodiments are simply illustrative and variations, modifications, alterations and

substitutions could be contrived by those skilled in the art. For convenience of explanation, apparatuses according to the embodiments of the present invention have been described with reference to functional block
5 diagrams, but these apparatuses may be implemented in hardware, software or combinations thereof. The present invention is not limited to the above embodiments, and variations, modifications, alterations and substitutions can be made by those skilled in the art
10 without deviating from the spirit of the present invention.

This international patent application is based on Japanese Priority Applications No. 2006-272352 filed on October 3, 2006, No. 2006-298313 filed on
15 November 1, 2006 and No. 2007-001855 filed on January 9, 2007, the entire contents of which are hereby incorporated by reference.

CLAIMS

5

1. A user apparatus for transmitting at least an uplink control channel to a base station apparatus in accordance with a single-carrier scheme, the user apparatus comprising:

10

an acknowledgement information generation unit configured to generate acknowledgement information indicating a positive response or a negative response to a downlink data channel;

15

a channel condition generation unit configured to generate channel condition information indicating a downlink channel condition;

20

a control channel generation unit configured to generate an uplink control channel including at least one of the acknowledgement information and the channel condition information; and

25

a transmission unit configured to transmit the uplink control channel in a predefined dedicated band if no resource is assigned to transmit an uplink data channel,

30

wherein the uplink control channel includes one or more unit blocks including a sequence resulting from multiplication of a uniform factor with all chips of an orthogonal code sequence for the user apparatus.

2. The user apparatus as claimed in claim 1, wherein the orthogonal code sequence comprises a CAZAC

code sequence.

5

3. The user apparatus as claimed in claim 1, wherein the factor comprises "+1" or "-1".

10

4. The user apparatus as claimed in claim 1, wherein the acknowledgement information is represented in a set of factors multiplied with the one or more unit
15 blocks.

20

5. The user apparatus as claimed in claim 4, wherein the acknowledgement information is represented in factors multiplied with some unit blocks of the unit blocks, and the channel condition information is represented in factors multiplied with other unit blocks
25 of the unit blocks.

30

6. The user apparatus as claimed in claim 1, wherein individual bits for representing the channel condition information are represented in a set of factors multiplied with multiple unit blocks.

7. The user apparatus as claimed in claim 6,
5 wherein the number of unit blocks corresponding to upper
bits is greater than or equal to the number of unit blocks
corresponding to lower bits.

10

8. The user apparatus as claimed in claim 1,
wherein correspondence between assignment information
of resources to uplink control channels and the
15 orthogonal code sequence is set to derive the orthogonal
code sequence uniquely from the assignment information.

20

9. The user apparatus as claimed in claim 8,
wherein the correspondence is set such that if user
multiplexing order is lower than or equal to a predefined
first value, a code division multiplexing scheme with
25 a first CAZAC code sequence is applied in a first band
within the dedicated band and if the user multiplexing
order is higher than the first value and lower than or
equal to a predefined second value, the code division
multiplexing scheme with the first CAZAC code sequence
30 is applied in a second band within the dedicated band.

10. The user apparatus as claimed in claim 9,
wherein the correspondence is set such that if the user
multiplexing order is higher than the second value and
lower than or equal to a predefined third value, a code
5 division multiplexing scheme with a second CAZAC code
sequence is applied in the first band within the dedicated
band and if the user multiplexing order is higher than
the third value, the code division multiplexing scheme
with the second CAZAC code sequence is applied in the
10 second band within the dedicated band.

15 11. The user apparatus as claimed in claim 1,
wherein the orthogonal code sequence is represented in
a set of factors multiplied with multiple unit blocks
having the same contents.

20

12. A method for use in a user apparatus for
transmitting at least an uplink control channel to a base
25 station apparatus in accordance with a single-carrier
scheme, the method comprising:

generating an uplink control channel
including at least one of acknowledgement information
and channel condition information, the acknowledgement
30 information indicating a positive response or a negative
response to a downlink data channel, the channel
condition information indicating a downlink channel
condition; and

transmitting the uplink control channel in a

predefined dedicated band if no resource is assigned to transmit an uplink data channel,

wherein the uplink control channel includes one or more unit blocks including a sequence resulting from multiplication of a uniform factor with all chips of an orthogonal code sequence for the user apparatus.

10

13. A base station apparatus for receiving at least an uplink control channel from multiple user apparatuses in accordance with a single-carrier scheme, the base station apparatus comprising:

15 an extraction unit configured to extract at least one of acknowledgement information and channel condition information from an uplink control channel, the acknowledgement information indicating a positive response or a negative response to a downlink data channel, the channel condition information indicating a downlink channel condition;

20 a scheduling unit configured to schedule a new packet or a retransmission packet based on the channel condition information and the acknowledgement information; and

25 a transmission unit configured to transmit the new packet or the retransmission packet in a downlink data channel, wherein

30 the uplink control channel includes one or more unit blocks including a sequence resulting from multiplication of a uniform factor with all chips in an orthogonal code sequence for the user apparatuses, and

the extraction unit is configured to identify contents of at least one of the acknowledgement

information and the channel condition information by determining factors multiplied with unit blocks.

5

14. The base station apparatus as claimed in claim 13, wherein

the orthogonal code sequence comprises a
10 CAZAC code sequence, and

the base station apparatus indicates
orthogonal code sequences and transmission bands to the
user apparatuses to apply a code division multiplexing
scheme with a first CAZAC code sequence in a first band
15 within a band dedicated to an uplink control channel if
user multiplexing order is lower than or equal to a
predefined first value and to apply the code division
multiplexing scheme with the first CAZAC code sequence
in a second band within the dedicated band if the user
20 multiplexing order is higher than the first value and
lower than or equal to a predefined second value.

25

15. The base station apparatus as claimed in claim 14, wherein the base station apparatus indicates
orthogonal code sequences and transmission bands to the
user apparatuses to apply the code division multiplexing
30 scheme with a second CAZAC code sequence in the first
band within the dedicated band if the user multiplexing
order is higher than the second value and lower than or
equal to a predefined third value and to apply the code
division multiplexing scheme with the second CAZAC code

sequence in the second band within the dedicated band if the user multiplexing order is higher than the third value.

5

16. The base station apparatus as claimed in claim 13, wherein the orthogonal code sequence in the unit blocks is used as a reference signal for one or more of channel estimation, path search and synchronization detection.

15

17. The base station apparatus as claimed in claim 13, wherein the orthogonal code sequence is represented in a set of factors multiplied with multiple unit blocks having the same contents.

25

18. A method for use in a base station apparatus for receiving at least an uplink control channel from multiple user apparatuses in accordance with a single-carrier scheme, the method comprising:

extracting at least one of acknowledgement information and channel condition information from an uplink control channel, the acknowledgement information indicating a positive response or a negative response to a downlink data channel, the channel condition information indicating a downlink channel condition;

scheduling a new packet or a retransmission packet based on the channel condition information and the acknowledgement information; and

transmitting the new packet or the
5 retransmission packet in a downlink data channel, wherein
the uplink control channel includes one or more unit blocks including a sequence resulting from multiplication of a uniform factor with all chips in an orthogonal code sequence for the user apparatuses, and
10 the extracting at least one of
acknowledgement information and channel condition information comprises identifying contents of at least one of the acknowledgement information and the channel condition information by determining factors multiplied
15 with unit blocks.

20 19. A user apparatus for transmitting at least an uplink control channel to a base station apparatus in accordance with a single-carrier scheme, the user apparatus comprising:

an acknowledgement information generation
25 unit configured to generate acknowledgement information indicative of a positive response or a negative response to a downlink data channel;

a channel condition information generation unit configured to generate channel condition
30 information indicative of a downlink channel condition;

a control channel generation unit configured to generate an uplink control channel including at least one of the acknowledgement information and the channel condition information; and

a transmission unit configured to transmit the uplink control channel in a predefined dedicated band if no resource is assigned to transmit an uplink data channel, wherein

5 the uplink control channel includes multiple unit blocks of a predefined data size, and

an orthogonal code sequence is represented in a set of factors multiplied with multiple unit blocks having the same contents.

10

20. A method for use in a user apparatus for transmitting at least an uplink control channel to a base station apparatus in accordance with a single-carrier scheme, the method comprising:

generating an uplink control channel including at least one of acknowledgement information and channel condition information, the acknowledgement information indicating a positive response or a negative response to a downlink data channel, the channel condition information indicating a downlink channel condition; and

25 transmitting the uplink control channel in a predefined dedicated band if no resource is assigned to transmit an uplink data channel, wherein

the uplink control channel includes multiple unit blocks of a predefined data size, and

30 an orthogonal code sequence is represented in a set of factors multiplied with multiple unit blocks having the same contents.

21. A base station apparatus for receiving at least an uplink control channel from multiple user apparatuses in accordance with a single-carrier scheme, the base station apparatus comprising:

an extraction unit configured to extract at least one of acknowledgement information and channel condition information from an uplink control channel, the acknowledgement information indicating a positive response or a negative response to a downlink data channel, the channel condition information indicating a downlink channel condition;

a scheduling unit configured to schedule a new packet or a retransmission packet based on the channel condition information and the acknowledgement information; and

a transmission unit configured to transmit the new packet or the retransmission packet in a downlink data channel, wherein

the uplink control channel includes multiple unit blocks of a predefined data size,

an orthogonal code sequence is represented in a set of factors multiplied with multiple unit blocks having the same contents, and

the extraction unit is configured to identify contents of at least one of the acknowledgement information and the channel condition information by determining other factors multiplied with unit blocks.

30

22. A method for use in a base station

apparatus for receiving at least an uplink control channel from multiple user apparatuses in accordance with a single-carrier scheme, the method comprising:

- 5 extracting at least one of acknowledgement information and channel condition information from an uplink control channel, the acknowledgement information indicating a positive response or a negative response to a downlink data channel, the channel condition information indicating a downlink channel condition;
- 10 scheduling a new packet or a retransmission packet based on the channel condition information and the acknowledgement information; and
- transmitting the new packet or the retransmission packet in a downlink data channel, wherein
- 15 the uplink control channel includes multiple unit blocks of a predefined data size,
- an orthogonal code sequence is represented in a set of factors multiplied with multiple unit blocks having the same contents, and
- 20 the extracting at least one of acknowledgement information and channel condition information comprises identifying contents of at least one of the acknowledgement information and the channel condition information by determining other factors
- 25 multiplied with unit blocks.

30 23. A user apparatus for transmitting at least an uplink control channel to a base station apparatus in accordance with a single-carrier scheme, the user apparatus comprising:

an acknowledgement information generation

unit configured to generate acknowledgement information indicative of a positive response or a negative response to a downlink data channel;

5 a channel condition information generation unit configured to generate channel condition information indicative of a downlink channel condition;

a control channel generation unit configured to generate an uplink control channel including at least one of the acknowledgement information and the channel
10 condition information; and

a transmission unit configured to transmit the uplink control channel in a predefined dedicated band if no resource is assigned to transmit an uplink data channel, wherein

15 the uplink control channel includes multiple unit blocks of a predefined data size,

an orthogonal code sequence is represented in a set of factors multiplied with multiple unit blocks having the same contents, and

20 the unit blocks result from multiplication of a spreading code sequence with the control channel.

25

24. A method for use in a user apparatus for transmitting at least an uplink control channel to a base station apparatus in accordance with a single-carrier scheme, the method comprising:

30 generating an uplink control channel including at least one of acknowledgement information and channel condition information, the acknowledgement information indicating a positive response or a negative response to a downlink data channel, the channel

condition information indicating a downlink channel condition; and

transmitting the uplink control channel in a predefined dedicated band if no resource is assigned to
5 transmit an uplink data channel, wherein

the uplink control channel includes multiple unit blocks of a predefined data size,

an orthogonal code sequence is represented in a set of factors multiplied with multiple unit blocks
10 having the same contents, and

the unit blocks result from multiplication of a spreading code sequence with the control channel.

15

25. A base station apparatus for receiving at least an uplink control channel from multiple user apparatuses in accordance with a single-carrier scheme,
20 the base station apparatus comprising:

an extraction unit configured to extract at least one of acknowledgement information and channel condition information from an uplink control channel, the acknowledgement information indicating a positive
25 response or a negative response to a downlink data channel, the channel condition information indicating a downlink channel condition;

a scheduling unit configured to schedule a new packet or a retransmission packet based on the channel
30 condition information and the acknowledgement information; and

a transmission unit configured to transmit the new packet or the retransmission packet in a downlink data channel, wherein

the uplink control channel includes multiple unit blocks of a predefined data size,

an orthogonal code sequence is represented in a set of factors multiplied with multiple unit blocks
5 having the same contents,

the unit blocks result from multiplication of a spreading code sequence with the control channel, and

the extraction unit is configured to identify at least one of the acknowledgement information and the
10 channel condition information by determining other factors multiplied with unit blocks.

15

26. A method for use in a base station apparatus for receiving at least an uplink control channel from multiple user apparatuses in accordance with a single-carrier scheme, the base method comprising:

20 extracting at least one of acknowledgement information and channel condition information from an uplink control channel, the acknowledgement information indicating a positive response or a negative response to a downlink data channel, the channel condition
25 information indicating a downlink channel condition;

scheduling a new packet or a retransmission packet based on the channel condition information and the acknowledgement information; and

transmitting the new packet or the
30 retransmission packet in a downlink data channel, wherein the uplink control channel includes multiple unit blocks of a predefined data size,

an orthogonal code sequence is represented in a set of factors multiplied with multiple unit blocks

having the same contents,

the unit blocks result from multiplication of
a spreading code sequence with the control channel, and
the extracting at least one of

- 5 acknowledgement information and channel condition
information comprises identifying at least one of the
acknowledgement information and the channel condition
information by determining other factors multiplied with
unit blocks.

10

FIG.1




FIG.2




FIG. 3




FIG.4




FIG.5




FIG.6




FIG. 7




FIG.8




FIG.9





FIG.10






FIG. 12




FIG.13






FIG.14





ACK/NACK

OR CQI →
INFORMATION

ORTHOGONAL
SEQUENCE →

FIG.17

