

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
20 April 2006 (20.04.2006)

PCT

(10) International Publication Number
WO 2006/041338 A1

(51) International Patent Classification : G01S 13/02,
13/532

(21) International Application Number:
PCT/SE2004/001460

(22) International Filing Date: 13 October 2004 (13.10.2004)

(25) Filing Language: English

(26) Publication Language: English

(71) Applicant (for all designated States except US): TELEFONAKTIEBOLAGET L M Ericsson (publ) [SE/SE]; S-164 83 Stockholm (SE).

(72) Inventor; and

(75) Inventor/Applicant (for US only): FALK, Kent [SE/SE]; Timgatan 2, S-415 08, Göteborg (SE).

(74) Agent: ALBIHNS GÖTEBORG AB; Box 142, S-401 22 Göteborg (SE).

(81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BW, BY, BZ, CA, CH, CN,

CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NA, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.


(84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PL, PT, RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Declaration under Rule 4.17:
— of inventorship (Rule 4.17(iv))

Published:
— with international search report

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: IMPROVED WIDEBAND RADAR



(57) Abstract: The invention refers to a method and device for wideband radar, the method comprising: -generating a wideband signal (1, 6) with a bandwidth B; -copying the wideband signal (1, 6); -transmitting the wideband signal (6'); -receiving a returned echo signal (11) from the transmitted signal (6'); -dividing the copied signal into a number, N_f , of subsequent frequency bands b; -manipulating the copied and divided signal into an anticipated signal (10) by adding a number N_d of anticipated delays and a number of N_D Doppler stretches to the copied and divided signal for each N_f subsequent frequency band b; -dividing the received signal (17) into a number, N_f , of subsequent frequency bands b; - correlating corresponding frequency bands in the divided received signal (17) and the anticipated signal (10) giving $N_d N_D$ correlated signals (19) for determining range (R) to a target and velocity (v) of the target.

WO 2006/041338 A1

TITLE

IMPROVED WIDEBAND RADAR

TECHNICAL FIELD

The invention refers to a method and device for wideband radar. The method
5 comprises:

- generating a wideband signal with a bandwidth B;
- transmitting the wideband signal;
- receiving a returned echo signal from the transmitted signal, and;
- manipulating the stored signal for an estimate of the echo return for range
10 and velocity.

BACKGROUND ART

In the field of wideband radar systems it is known that range resolution is
inversely proportional to the bandwidth used for the radar. Furthermore, it is
known that velocity resolution depends inversely on integration of time. A
15 challenge in the design of broadband radar systems is to achieve velocity
resolution as good as the range resolution. The range resolution is normally
better than required.

Problems with existing solutions are low velocity resolution compared with
the range resolution. There is also a problem with a high jamming sensitivity
20 since it is not possible to exclude jammed parts of the frequency band.
Furthermore, there is also a problem with high dynamic range requirements
in the A/D-converters since jammed parts of the used frequency band cannot
be excluded before the A/D-converter and the dynamic range in the A/D-
converters must be able to handle the level of the jamming signal.

25 There is thus a need for an improved method and device for wideband radar.

DISCLOSURE OF INVENTION

The invention aims to remedy the above stated problem by a method and a device as stated below. The method is intended to be implemented in a radar system using a wideband signal, with bandwidth B . Examples of radar using
5 a wideband signal are Noise Radar and chirp pulse radar. The invention uses a signal generator for generating the wideband signal. The signal is copied and advantageously stored in a memory. The wideband signal is also transmitted by a sending antenna. The returned echo signal is received and amplified. Both the transmitted and received signal is divided into N_f
10 subsequent frequency bands b . The frequency bands b may have equal bandwidth B/N_f , but may also have different bandwidth. Suitable means for dividing the stored and received signal into frequency bands is a filter bank for analog signals or digital filters in case the stored and received signals have been converted into digital signals.

15 The return echo signal is delayed because of the transmitted signal making a round-trip propagating to a target and back to a receiving antenna. The transmitted signal also undergoes a Doppler Stretching when reflected by the target, due to the motion of the target, and becomes part of the return signal. When using a narrow band approximation, the Doppler Stretching becomes a
20 Doppler frequency shift.

The stored and divided signal is being manipulated such that anticipated delays and Doppler stretches are added to the stored signal for each N_f frequency band b . This manipulated signal is hereinafter called the anticipated signal and refers to one signal and thus one filter for each delay
25 (i.e. a number of N_d filters), and one signal and thus one filter for each Doppler stretch (i.e. a number of N_D filters).

The method comprises the step of correlating corresponding frequency bands b in the divided received signal and the anticipated signals, i.e. the N_d delayed and the N_D Doppler stretched copies of the transmitted signal are

correlated with the received signal. This results in a number of $N_d N_D$ (N_d times N_D) correlated signals representing each combination of delay and Doppler stretch. This procedure takes place in a correlator means comprising a correlation cluster giving the $N_d N_D$ correlated signals. The output from

5 the correlator cluster yields a high value if an anticipated signal is matched with a similar return signal and a low value if there is a mismatch. Here, match refers to two signals being identical or similar. In some literature, the term "match" or "correlated" refers to a probability or probability function describing the probability of a target hit, i.e. the probability of finding a target

10 at a range R with velocity v at a certain moment in time. The output from the correlator means is a number of correlated signals describing a range R and velocity v plane, and amplitudes in a direction orthogonal to the R and v plane. The amplitudes describe the high and low values in the correlated signal, i.e. if there is a match or nor. If there is a match the anticipated

15 scenario for a target hit is identical or at least similar to the return signal from a target hit. The correlated signals thus give an output revealing the range R and velocity v of a target.

In one embodiment of the invention, the $N_d N_D$ correlated signals are then averaged into a number of N_f averaged signals in order to give a good

20 estimate of the echo return for each range/delay and velocity/Doppler stretch combination. The range, delay and Doppler Stretch is dependent on each other according to:

$$T(t) = \frac{2vt}{c} + \frac{2R(0)}{c}$$

where T(t) refers to delay time which depends on the range R and where

25 R(0) is equal to the range at time t=0, and where v is equal to the target radial velocity and c is equal to the speed of light, and where $\frac{2vt}{c}$ refers to the Doppler Stretch.

The benefits of the invention will be discussed below.

In order to explain the invention further, a theoretical example will now be given. Starting from fairly general assumptions, the range resolution ΔR in radar is reciprocally proportional to the bandwidth B and the velocity resolution Δv is reciprocally proportional to the time for measurement T .

$$\Delta R \cong \frac{1}{B} \quad (1)$$

$$\Delta v \cong \frac{1}{T} \quad (2)$$

Furthermore, the product of ΔR and Δv is generally constant for a fix center frequency.

$$\Delta R \cdot \Delta v = C \quad (3)$$

Where C is a constant.

If the bandwidth B is divided into N_b equal parts with the bandwidth b . (The parts need not be equal, but it facilitates the below discussion.)

$$b = \frac{B}{N_b} \quad (4)$$

According to equation 1, the range resolution ΔR will thus increase with a factor N_b . Since it is possible to create a mean value over a number of N_b measurements, i.e. one measurement for each part with a bandwidth b , the range resolution is improved with a factor equal to the square root of N_b . The resulting range resolution ΔR_b thus becomes:

$$\Delta R_b = \frac{N_b \cdot \Delta R}{\sqrt{N_b}} = \sqrt{N_b} \cdot \Delta R \quad (5)$$

Equation 3 now gives that the velocity resolution Δv is improved with a factor equal to the square root of N_b . The resulting velocity resolution in Δv_b thus becomes:

$$\Delta v_b = \frac{\Delta v}{\sqrt{N_b}} \quad (6)$$

- 5 The desired improvement of velocity resolution has now been achieved at the expense of a lessened range resolution.

It is of course also possible to achieve the reverse effect. By dividing the time for measurement T into N_t parts, each with the length t , the range resolution will then be improved at the expense of a lessened velocity resolution

10 according to:

$$\Delta R_t = \frac{\Delta R}{\sqrt{N_t}} \quad (7)$$

$$\Delta v_t = \sqrt{N_t} \cdot \Delta v \quad (8)$$

End of example.

15 In one embodiment of the invention, the averaged signals are put through a detector means. The simplest form of a detector means may be described as a threshold circuit that gives logical "LOW" output below the threshold level and a logical "HIGH" output above the threshold level. A "LOW" output indicates large probability for "no target present" and a "HIGH" output indicates large probability for "target present". Furthermore, a detector may
20 also give target size information by using different threshold levels for different target sizes.

In one embodiment of the invention, the detected signals are processed in a logic means where the range (R) to a target and velocity (v) of the target is

determined. The logic circuit reports for which range/velocity combinations there is high probability for a target.

In one embodiment of the invention, the divided received signal is transmitted through a switch cluster comprising a number of N_f switches for clearing a
5 signal that is evidently wrong in order to reduce interference from both intentional and unintentional jamming. For example, all jammed frequency sub bands will be excluded in the calculation of the average value by opening the correct switches in the switch cluster.

One advantage of this procedure is that all jammed frequency sub bands will
10 be excluded in the calculation of the average value. For example, a 1 bit A/D converter may be used and the procedure excluding jammed parts of the frequency band gives graceful degradation.

The present invention has the advantage of gaining velocity resolution at the price of reduced range resolution, but where the range resolution still is good
15 enough for detecting moving targets such as air planes etc. The invention also gives a system with high immunity against interference and reduced dynamic range requirements in the A/D-converters.

Other advantages of the Invention are:

-Independent range and velocity resolution since there is no cross-correlation
20 between range and velocity resolution. Constant level contours in the ΔR - Δv plane are ellipses with main axes that coincide with the coordinate axes.

-Low jamming sensitivity.

-Low dynamic range requirements in the A/D-converters since the A/D-converters doesn't need to handle jamming. Simulation shows that only a few
25 decibels are lost when 1-bit A/D-converters are compared with infinite resolution.

- Low sampling rate in the A/D-converters since only a fraction of the total frequency band is handled in each A/D-converter.
 - Low probability of detection since the output power is spread over a large frequency band and in the continuous wave case over all available time.
 - 5 -Low probability of intercept since low probability of detection also gives low probability of intercept.
 - No linearity requirements on the transmitter since the reference signal is sampled after the power amplifier.
 - Simple waveform generation since there are no phase, amplitude or linearity
10 requirements on the waveform generator, but the noisier the better.
 - Low target area fluctuations since the target-area will be an average value over several frequency sub-bands, which gives lower fluctuations.
- A suitable bandwidth of the wideband signal is 10 GHz in the range 8-18 GHz, but other frequency ranges are also possible. The wideband signal is
15 preferably continuous but may be in the form of pulses.

Below you will find some definitions of expressions used in the application.

- Wideband ambiguity function. The ambiguity function describes the correlation between a reference and received signal, See equation 9 below.
- Coherent noise radar is a method for radar where both phase and amplitude
20 is correlated. In the non-coherent case only the amplitude of the signals is correlated. The present invention may use both types of wideband signals.

BRIEF DESCRIPTION OF DRAWINGS

The invention will below be described in connection to a number of drawings where;

Fig. 1 schematically shows a block diagram over the method and apparatus according to one embodiment of the invention, and where:

Fig. 2 schematically shows a three dimensional diagram over an example of an output from the method and apparatus according to fig. 1.

5 EMBODIMENTS OF THE INVENTION

Fig. 1 schematically shows a block diagram over the method and the radar and control device according to one embodiment of the invention. A wideband signal 1, with bandwidth B, is generated in a Wideband signal generator 2. The signal 1 is then processed in a band pass filter 3 (BP-filter) in order to remove frequency contents outside a filter bank. The filtered signal 4 is then enhanced in a power amplifier 5 and the enhanced signal 6 is then transmitted 6' via a transmitting antenna Tx.

The enhanced signal 6 is copied after the power amplifier 5 and is then frequency divided by a BP-filter bank 7 into a number of N_f frequency bands. The divided signals are then converted from analog signals into corresponding digital signals in an A/D-converter cluster 8. The A/D converted signals are stored in a Memory 9. The stored signals are then manipulated such that N_d anticipated delays and N_D Doppler stretches are added to the stored signal for each number N_f of frequency bands. This manipulated signal is hereinafter called the anticipated signals 10 and refers to a number of $N_d \cdot N_D$ (N_d times N_D) filters comprising one filter for each delay, i.e. a number of N_d filters for each delay and one filter for each Doppler stretch, i.e. a number of N_D filters for each Doppler stretch. The number of filters depends on the instrumented range, the range resolution, the velocity limits, the velocity resolution and the number of frequency sub-bands.

Each filter is optimized for one range and one velocity for the generated transmit signal.

A returned echo signal 11 is received by a receiving antenna Rx placed at a distance from the transmitting antenna Tx. The receiving antenna Rx may be placed several kilometres from the transmitting antenna Tx. The received signal 17 is transmitted via a filter 12, in order to exclude out of band signals, to a Low noise amplifier 13 where it is amplified before being transmitted to a filter bank. 14 The amplified signal is divided by the filter bank 14 into a number N_f of frequency bands, each with a bandwidth B/N_f , corresponding to the division of the copied signal 6. The filter bank may comprise a number N_f of BP-filters. The frequency bands do not have to be of equal size, but may be of different size, i.e. some frequency bands may have a greater bandwidth than other frequency bands. However, the frequency bands in the received and divided signal need to be divided in the same manner as the copied signal.

The divided signal is transmitted through a switch cluster 15 comprising a number of N_f switches. The switch cluster can be used to clear a signal that is evidently wrong. For example, all jammed frequency sub bands will be excluded in the calculation of the average value by opening the correct switches in the switch cluster.

The switched signal is converted by an A/D-converter 16 into a digital received signal.

The digital received signal is correlated with the anticipated signals 10 for corresponding frequency bands in a correlation cluster 18. The anticipated signals 10 corresponds to the filters representing each anticipated delay N_d and each anticipated Doppler stretched N_D . Hence, the correlator cluster 18 correlates the anticipated signals 10 and the digital received signals. Correlation refers to the process of comparing anticipated signals with received signals. If there is a match the correlation cluster reveals the location of a target in the range-velocity plane. The correlation may be done, for example, by multiplication, where the product for a match between an anticipated signal 10 and a digital received signal yields a high value and

where a mismatch yields a low value. The received signal may be weaker or somewhat different from the anticipated signal, but a match between an anticipated signal and a received signal gives a significantly higher value than for a mismatch correlation between the signals.

- 5 Furthermore, the invention is not limited to digital signals, but it is possible to arrange the correlation cluster to be able to handle analog signals as well as optical signals. In the latter cases, the match may then present itself as, for example, an interference value that is possible to detect.

The output from the correlation cluster is a number of $N_d N_D$ correlated
10 signals 19 for each combination of delay and Doppler stretch. The $N_d N_D$ correlated signals 19 for each combination of delay and Doppler stretch are then averaged in an averaging means 20 into a number of N_f average signals 21. The average of the N_f average signals 21 gives a good estimate of the echo return for each range (delay) and velocity (Doppler Stretch)
15 combination. The number of filters depends on the instrumented range, the range resolution, the velocity limits, the velocity resolution and the number of frequency sub-bands.

In figure 1 the average signals 21 are transmitted through a number of N_f detectors 22. A detector is a threshold circuit that gives logical "LOW" output
20 below the threshold level and a logical "HIGH" output above the threshold level. A "LOW" output indicates large probability for "no target present" and a "HIGH" output indicates large probability for "target present". The "HIGH" output may be a discrete value, such as the value one, indicating a target hit or may be a true value indicating a target hit and also the magnitude of the
25 effect in the signal. The "LOW" output may be a discrete value, such as the value zero, indicating that there is no target hit or may be a true value indicating no target hit and also the magnitude of the effect in the signal.

After the detector 22 the detected signals 23 are processed in a logic means 24 which gives an output signal for range-velocity combinations with high

probability of a target present. The logic means 24 may in its simplest form be a device that detects the "HIGH" in the detected signals. The logic means 24 finds the "HIGH" and determines from the position in the detected signals 23 in what position in the range-velocity plane the "HIGH", i.e. the target, is found. The output from the logic means 24 may thus be a number of possible target hits and their location in the range-velocity plane.

Fig. 2 schematically shows a three dimensional diagram over an example of an output $\chi (R, v)$ from the correlator cluster 18 according to the method and device according to fig. 1. Here the output $\chi (R, v)$ refers to the $N_d \cdot N_D$ correlated signals 19. The output $\chi (R, v)$ is calculated by use of equation 9 below for determining range (R) to a target and velocity (v) of the target

$$\chi(R, v) = D \int_{-\infty}^{\infty} \underbrace{\left[u \left(\frac{s (c_0 - v_r) - 2 R_0}{c_0 + v_r} \right) + n(s) \right]}_{\text{Received signal}} \underbrace{u^* \left(\frac{s (c_0 - v) - 2 R}{c_0 + v} \right)}_{\text{Anticipated signal}} ds \quad (9)$$

where:

-D is the attenuation due to target range and cross section.

15 -n(t) represents added noise.

- R_0 and v_r are target range and radial velocity respectively. R_0 may be defined at different points of time. For example, R_0 may be defined at the time of transmittal of the outgoing signal, or at target hit, or at receipt of the echoed signal, i.e. the return signal 11. Dependent on how R_0 is defined it is possible to use the inventive method for a specific target homing use, but the definition of R_0 is not important in a practical application. It is only of academic interest when comparing different versions of the "Wideband ambiguity function". The target range when the signal is transmitted is very similar to its range when the signal hits the target and also to its range when the signal is received.

-R and v are range and velocity variables.

The calculations are made with the following parameters:

-Receive antenna SNR equal to 0 dB

-Bandwidth B equal to 10 GHz

5 -n(t) is simulated as white noise with bandwidth B.

-The generator is a white noise source with bandwidth B.

-Band pass filter with bandwidth B.

- N_f equal to 100.

-Filter banks with 100, 100 MHz filters.

10 -One bit A/D-converters.

In figure 2 the simulation shows a result with a Target Range equal to 20 m and Target Velocity = 500 m/s. The target hit is indicated by a peak 25 in the diagram indicating the velocity of the target and the range to the target.

15 Referring to figure 2, the detector 22 in figure 1 has a threshold that eliminates the noise in the averaged correlated signals 21, and allows only signals above the threshold to pass. For example, the threshold level could be determined to allow only signals with a magnitude of the peak 25 to pass, or may be chosen so as to allow signals of lesser amplitude. Furthermore, the detector may comprise several threshold levels in order to separate
20 signals with different magnitudes which may be a sign of different target sizes. Here, magnitude refers to the effect as displayed in figure 2.

It should be noted that the invention is not limited to the use of a detector detecting averaged signals only, but a detector may be used directly on the correlated signals 19.

The invention is not limited to the above embodiment, but may be varied within the scope of the claims. For example, the wideband signal generator could be a noise source. The A/D-converters could have low resolution.

The antennas Tx and Rx must not be placed apart, but in order to achieve a
5 bi-static operation the antennas Tx, Rx must be placed apart in order to increase isolation between them. Placing the antennas apart is also a prerequisite for a continuous operation.

The entire logic structure according to the above embodiment could be performed with other means than for electricity, for example means for
10 manipulating light could be used, where the correlating means could be a junction between a number of light guiding means and where the correlating means uses light interference. Furthermore, different delays (range) could be made by use of light guiding means with different properties, for example length. Different Doppler stretches (velocity) could be made by use of light
15 guiding means with different properties, for example different refractive index. Furthermore, the filter bank could be a Bragg-cell.

CLAIMS

1. A method for wideband radar, the method comprising:

- generating a wideband signal (1, 6) with a bandwidth B;
- copying the wideband signal (1, 6);

5 -transmitting the wideband signal (6');

-receiving a returned echo signal (11) from the transmitted signal (6');

-dividing the copied signal into a number, N_f , of subsequent frequency bands b;

10 - manipulating the copied and divided signal into an anticipated signal (10) by adding a number N_d of anticipated delays and a number of N_D Doppler stretches to the copied and divided signal for each N_f subsequent frequency band b;

-dividing the received signal (17) into a number, N_f , of subsequent frequency bands b;

15 - correlating corresponding frequency bands in the divided received signal (17) and the anticipated signal (10) giving $N_d N_D$ correlated signals (19) for determining range (R) to a target and velocity (v) of the target.

2. A method according to claim 1, comprising the step of calculating the correlated signal by use of:

$$20 \quad \chi(R, v) = D \int_{-\infty}^{\infty} \underbrace{u\left(\frac{s(c_0 - v_r) - 2R_0}{c_0 + v_r}\right) + n(s)}_{\text{Received signal}} \underbrace{u^*\left(\frac{s(c_0 - v) - 2R}{c_0 + v}\right)}_{\text{Anticipated signal}} ds \quad (9)$$

for determining range (R) to a target and velocity (v) of the target, where ;

-D is the attenuation due to target range and cross section.

$-n(t)$ represents added noise.

$-R_0$ and v_r are target range and radial velocity respectively.

3. A method according to claim 1 or 2, comprising the step of averaging the N_d N_D correlated signals into a number of N_f averaged signals (21) for an
5 estimate of the echo return for each range/delay and velocity/Doppler stretch combination.
4. A method according to claim 3, comprising the step of processing the averaged signals in a detector means (22) giving rise to detector signals (23) comprising at least one logical LOW output below a threshold level and at
10 least one logical HIGH output above the threshold level.
5. A method according to claim 4, comprising the step of processing the detector signals (23) in a logical means (24) determining range (R) to a target and velocity (v) of the target.
6. A method according to any one of the preceding claims, comprising the
15 step of generating the wideband signal with means of a signal generator (2).
7. A method according to any one of the preceding claims, comprising the step of storing the copied and divided wideband signal (6) in a memory (9).
8. A method according to any one of the preceding claims, comprising the step of transmitting the generated signal (1) through a filter (3) in order to
20 remove frequency contents outside a filter bank and/or transmitting the received signal (17) through a filter (12) in order to exclude out of band signals.
9. A method according to any one of the preceding claims, comprising the step of amplifying the generated signal (1; 2) and/or the received signal (11).
- 25 10. A method according to any one of the preceding claims, comprising the step of transmitting the divided received signal (17) through a switch cluster

(15) comprising a number of N_f switches in order to clear a signal that is evidently wrong.

11. A method according to claim 10, comprising the step of converting the switched signal by an A/D-converter (16) into a digital received signal (17).

5 12. A method according to any one of the preceding claims, comprising the step of dividing the stored signal into frequency bands by use of a filter bank for analog signals or digital filters if the stored signal has been converted into a digital signal.

13. A control device for a wideband radar, arranged to carry out the steps of:

10 -generating a wideband signal (1, 6) with a bandwidth B;

-copying the wideband signal (1, 6);

-transmitting the wideband signal (6');

-receiving a returned echo signal (11) from the transmitted signal (6');

15 -dividing the copied signal into a number, N_f , of subsequent frequency bands b;

- manipulating the copied and divided signal into an anticipated signal (10) by adding a number N_d of anticipated delays and a number of N_D Doppler stretches to the copied and divided signal for each N_f subsequent frequency band b;

20 -dividing the received signal (17) into a number, N_f , of subsequent frequency bands b;

- correlating corresponding frequency bands in the divided received signal (17) and the anticipated signal (10) giving $N_d N_D$ correlated signals (19) for determining range (R) to a target and velocity (v) of the target.

14. Wideband radar arranged to carry out the method according to any one of claims 1-12.

Fig. 1





Fig. 2



INTERNATIONAL SEARCH REPORT

International application No.

PCT/SE 2004/001460

A. CLASSIFICATION OF SUBJECT MATTER

IPC7: G01S 13/02, G01S 13/532
According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC7: G01S

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

SE,DK,FI,NO classes as above

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

EPO-INTERNAL, WPI DATA, PAJ

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	Dawood M et al Generalised wideband ambiguity function of a coherent ultrawideband random noise radar in: IEE Proceedings- Radar, Sonar & Navigation, Vol. 150, no.5, 2003-10-02, pp 379-386 --	1-14
A	US 6121915 A (G.R. COOPER ET AL), 19 Sept 2000 (19.09.2000), figure 1, abstract -- -----	1-14

Further documents are listed in the continuation of Box C. See patent family annex.

* Special categories of cited documents:

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier application or patent but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance: the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance: the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

9 May 2005

Date of mailing of the international search report

18 -05- 2005

Name and mailing address of the ISA/
Swedish Patent Office
Box 5055, S-102 42 STOCKHOLM
Facsimile No. +46 8 666 02 86

Authorized officer

Göran Magnusson / MRo
Telephone No. +46 8 782 25 00

INTERNATIONAL SEARCH REPORT

Information on patent family members

01/04/2005

International application No.

PCT/SE 2004/001460

US 6121915 A 19/09/2000 NONE
