

Abstract

A power amplifier system is presented for amplifying an RF input signal. The system includes a vector modulator for receiving and modifying an input signal and providing therefrom a modified signal. The system also includes at least one power
5 amplifier the operation of which is monitored and the vector modulator is controlled in accordance with the monitoring.

H6646, 6-343

POWER AMPLIFIER HAVING MONITORING AND CIRCUIT PROTECTION

The present invention is directed to an RF power amplifier system for use in amplifying an RF input signal and is more particularly directed toward monitoring the system and providing protection for the system.

5 RF power amplifier systems are known for use in amplifying RF signals for broadcasting purposes including radio and television. Such power amplifiers may be employed in the broadcasting of either analog television signals, known as the NTSC, PAL, SECAM format, or digital signals, sometimes known as DTV format. When employed in television broadcasting, the frequency bandwidth for the television signals is 6 MHz. The television channels will be in
10 the UHF signal range from approximately 470 to 860 MHz.

The RF input signal to such a power amplifier is obtained from an RF exciter and, for example, this may take the form of a modulated RF carrier within a frequency band of 470 to 860 MHz with the bandwidth of any one channel being on the order of 6 MHz. This modulated RF input signal may have a magnitude on the order of 20 milliwatts. This input signal is
15 increased in magnitude to a much higher level such as on the order of 400 watts which represents a gain on the order of 43 dB.

These power amplifier systems are expected in many situations to be constantly operating so that a radio or television station employing such a power amplifier system may continuously broadcast.

20 The present invention includes a power amplifier system for use in amplifying an RF input signal comprising signal modulating means for receiving and modifying an input signal and providing therefrom a modified first signal, first switching means for, when closed, supplying said input signal to said modulating means, at least one power amplifier, second switching means for, when closed, applying a DC voltage source to said power amplifier, means
25 for monitoring the operation of said power amplifier and controlling said signal modulating means and said first and second switching means said signal modulating means varies the gain of said input signal and said monitoring and control means includes means for applying a gain control signal to said modulating means for controlling the gain of said input signal.

The invention also includes a power amplifier system for use in amplifying an RF input
30 signal comprising, signal modulating means for receiving and modifying an input signal and providing therefrom a modified first signal, first switching means for, when closed, supplying said input signal to said modulating means, N power amplifiers, divider means for dividing said first signal into N signals for respective application to said N power amplifiers to provide

H6646, 6-343

N amplified signals, second switching means for, when closed, applying a DC voltage source to each of said N power amplifiers, means for combining said N amplified signals to provide therefrom an amplified output signal for application to an output circuit, means for monitoring the operation of said N power amplifiers and controlling said signal modulating means and said
 5 first and second switching said signal modulating means varies the gain of said input signal and said monitoring and control means includes means for applying a gain control signal to said modulating means for controlling the gain of said input signal, or said modulating means varies the phase of said input signal and wherein said monitoring and controlling means includes means for applying a phase control signal to said modulating means for varying the
 10 phase of said input signal.

Conveniently, the power amplifier system for amplifying an RF input signal includes a modulator, such as a vector modulator, for receiving and modifying an input signal and providing therefrom a modified signal. The system includes at least one power amplifier the operation of which is monitored and the modulator is controlled in accordance with the
 15 monitoring.

Preferably, the vector modulator includes a gain varying means for varying the gain of the input signal in response to the monitored operation of the power amplifier.

Advantageously, the modulator includes signal phase varying means for varying the phase of the input signal in response to the monitoring of the operation of the system.

20 Suitably, a power detector detects the RMS power of the input signal and compares this with a reference and the operation of the amplifying system is adjusted in accordance with that comparison.

The invention will now be described, by way of example, with reference to the accompanying drawings, in which:

25 Fig. 1 is a schematic-block diagram illustration of apparatus employed in one embodiment of the invention;

Fig. 2 is a block diagram of a detector;

Fig. 3 is a schematic-block diagram of an integrator;

Fig. 4 is a flow diagram of one routine involved in the invention;

30 Fig. 5 is a flow diagram of another routine involved in the invention;

Fig. 6 is a flow diagram of another routine involved in the invention;

Fig. 7 is a flow diagram of another routine involved in the invention;

Fig. 8 is a flow diagram of another routine involved in the invention;

Fig. 9 is a flow diagram of another routine involved in the invention.

H6646, 6-343

Fig. 1 illustrates a power amplifier module or system which receives a modulated RF input signal at an input terminal 10 and amplifies the signal and supplies it to a load L, which may take the form of a transmitting antenna and associated equipment. The RF input signal may have a magnitude on the order of 20 milliwatts and have a frequency within the UHF frequency range between 470 and 860 MHz with a 6 MHz bandwidth for the television channel involved. The signal may be increased by the amplifier with a gain on the order of 43 dB so that the output signal as applied to the load L may be on the order of 400 watts.

The RF input signal is applied to the input terminal 10 and, thence, to a vector modulator. The vector modulator changes the magnitude and the phase of the RF signal. The modified RF signal from the vector modulator is then amplified by a driver DR to a higher level, such as 20 watts. The output, as taken from the driver DR, is then supplied to a power divider DV, sometimes referred to as a signal or power splitter, which divides the amplified signal by a factor of N. N signals are then applied to N power amplifiers PA-1 through PA-N, where N, for example, may be 12. The signals from the power amplifiers PA-1 through PA-N are then combined in a signal combiner CB to provide an output signal which is applied to the load L. The input signal is applied to a vector modulator 16 when the RF input switch 20 is closed. The RF switch 20 is controlled by a microcontroller MC, as will be explained in greater detail hereinafter. The microcontroller also controls the vector modulator to vary the phase and gain of the RF signal.

The driver DR amplifies the signal with a gain of approximately 14 dB to deliver an RF signal of approximately 20 watts to a divider DV. This divider serves as a power splitter and splits the applied RF signal into N portions. The divider applies N equal portions of the RF signal to respective power amplifiers PA-1 through PA-N. Each power amplifier includes a field effect transistor having its drain electrode connected through a suitable resistor, such as resistor R1 or R2 or RN, to a DC switch 40. When this switch is closed, it connects each drain electrode with a DC voltage source V_{DD} . This voltage source may, for example, be on the order of 32 volts.

The outputs from the power amplifiers PA-1 through PA-N are combined at the power combiner CB. The output signal at the output circuit 50 is on the order of 400 watts.

The microcontroller MC monitors the operation of the amplifier system and controls the system by varying the phase and or gain of the RF signal and controlling the operation of the RF switch 20 and the DC switch 40.

When the DC switch 40 is closed, current will flow in the power amplifiers PA-1 through PA-N. This current will flow through the associated resistors R1 through RN. A voltage is

H6646, 6-343

developed across each resistor. These voltages are supplied as current samples to the microprocessor MC which then determines whether the current levels are too high or too low and takes appropriate action. Also, when the switch 40 is closed current flows through resistor R0 and the driver DR. The voltage developed across this resistor is also supplied to the
5 microcontroller MC for analysis.

In addition to monitoring the current flowing through the various power amplifiers, the microcontroller also monitors peak and average power levels with the use of power detectors. These detectors include an input power detector 60 and output power detectors 62 and 64. The power detector 60 is connected to an input signal divider 70 and serves to provide DC output
10 signals V_{P1} and V_{A1} respectively representative of the input peak power and the input average power. The signal representative of the input peak power V_{P1} is compared with a reference V_{R1} at comparator 72. If the peak power V_{P1} exceeds the reference then an interrupt signal is supplied to the microprocessor MC which interrupts the routine being processed and enters a fault process to turn the power amplifier system off.

15 Detector 62 is connected to a incident signal coupler 80 coupled to the output transmission line 50. This detector 62 provides a DC voltage signal V_{P2} representative of the peak output power as well as a DC voltage V_{A2} which represents the average output power in the forward direction at the output transmission line 50. Signal V_{P2} is compared with a reference V_{R2} at comparator 74. If signal V_{P2} exceeds reference V_{R2} then an interrupt signal is supplied to
20 microcontroller MC which then enters a fault process routine to turn the power amplifier off. A coupler 82 is employed for sensing the reflected power and this coupler is connected to detector 64. This detector 64 serves to provide DC voltage signals including a signal V_{P3} representative of the peak reflected power and V_{A3} representative of the average reflected power. If signal V_{P3} exceeds a reference V_{R3} , then comparator 76 applies an interrupt signal to
25 the microcontroller MC which then enters a fault process routine to turn the power amplifier off. The monitored average power signals V_{A1} , V_{A2} and V_{A3} are supplied to the microcontroller MC which is programmed to vary the gain and/or phase of the RF signal as needed.

Each of the power detectors is constructed in the same fashion as detector 60. This detector includes an envelope demodulator 61 which receives a sample of an RF signal from
30 correspondingly input or output transmission lines. The carrier signal may, for example, be on the order of 600 MHz and the baseband for the television signal has a bandwidth of 6 MHz. The demodulator 61 effectively strips off the carrier signal (600 MHz) leaving only the demodulated baseband signal. This signal may be viewed as an analog positive signal and which is applied to the integrator 63 and a peak power detector 65.

H6646, 6-343

The integrator 63 provides an output signal in the form of voltage V_{A1} representative of the average input power whereas the peak detector 65 provides an output signal in the form of a voltage V_{P1} representative of the peak input power. The demodulator 61 and the integrator 63 form an RMS detector.

- 5 The integrator 63 located in each of the detectors 60, 62 and 64 may take the form as illustrated in Fig. 3.

The digital 8-VSB format refers to an 8 level vestigial sideband signal. The baseband of this signal is 6 MHz wide. It is desired to provide efficient power level control of the power amplifier system illustrated in Fig. 1. To achieve this, it is desirable to provide a power detector
10 that provides an output signal, V_{out} , which is proportional to the corresponding average power. In the past, circuit designers have typically employed true RMS detectors for converting an input baseband signal into a DC level proportional to the RMS power. This is done in accordance with the equation noted below.

$$V_{RMS} = \frac{\sqrt{\int_0^T V_{in}^2 dt}}{T}$$

- 15 At present, commercially available integrated circuits that perform this type of an equation are only suitable for use at low frequencies, such as up to 10 kHz. As such, they are not able to provide an RMS signal representative of a baseband signal that is of a substantially higher frequency, such as being 6 MHz wide as in the case of digital television signals. There is a need to provide a circuit that will deliver an output voltage
20 V_{out} which is proportional to the RMS value of the input voltage V_{in} without employing multiplication (such as V_{in} times V_{in} to obtain V_{in}^2). This is achieved with the circuit shown in Fig. 3 as described below.

The input voltage V_{in} is applied to an input terminal 100 and the output voltage V_{out} is obtained at an output terminal 102. A wideband operational amplifier 104 is
25 provided having an RC charge path connected to its positive or non-inverting input 106 and an RC discharge path is connected to its inverting or negative input 108. The charge path includes a resistor R1 and a capacitor C1 having their junction point connected to

H6646, 6-343

input 106 of amplifier 104. The other side of capacitor C1 is connected to circuit ground. The discharge path includes a resistor R2 and a capacitor C2 having their junction point connected to input 108 of the operational amplifier 104. The other side of capacitor C2 is connected to circuit ground. A diode D1 is connected between the output 105 of
 5 amplifier 104 and the circuit output 102. The circuit output 102 is connected to the negative input 108 of the amplifier 104 by way of a circuit path 110.

The circuit in Fig. 3 has separate RC circuits that define the charge and discharge time constants and thereby provides independently controlled charge and discharge times. The circuit may be tuned by changing the value of resistors R1 and R2 so that the
 10 ratio of the charge and discharge time constants allows the detector to deliver an output voltage V_{out} proportional to the RMS value of V_{in} . The manner of operation involved is presented below.

Consider a situation wherein the diode D1 is connected between output 105 and circuit output 102 and that $R2 \cdot C2 \geq R1 \cdot C1$.

15 In this situation, the voltages V_{out} and V_- will follow voltage V_+ as voltage V_+ increases. The moment voltage V_+ decreases, voltage V_{out} follows the discharge time $R2 \cdot C2$ until V_+ increases again and the operation repeats. Since voltage V_+ follows voltage V_{in} with a charge time constant $R1 \cdot C1$, then voltage V_{out} follows voltage V_{in} with the $C1 \cdot R1$ time constant on the rise and the $C2 \cdot R2$ time constant on the voltage V_{in} fall.

20 When the $R2 \cdot C2$ time constant is long enough ($\frac{1}{C2 \cdot R2} < f_{low}$

where f_{low} is the lowest frequency in the spectrum of the envelope demodulated signal) this allows creation of the voltage V_{out} anywhere in the range from voltage V_{in} max. to voltage V_{in} average by manipulating the $C1 \cdot R1$ time constant from $C1 \cdot R1 = 0$ to $C1 \cdot R1 = C2 \cdot R2$.

25 If the diode D1 is replaced by diode D2 (as shown by the broken line) the condition $R1 \cdot C1 \geq R2 \cdot C2$ results. If $R1 \cdot C1$ is long enough ($\frac{1}{C1 \cdot R1} < f_{low}$) then this allows creation

H6646, 6-343

of voltage V_{out} anywhere in the range from V_{in} average to V_{in} minimum, varying $C2 \cdot R2$ from $= C1 \cdot R1$ to zero.

In the power amplifier system of Fig. 1, it is contemplated that an 8-VSB baseband signal is involved. Its spectrum looks like white noise with a frequency range from 0 to 6 MHz and almost even distribution of power within the range. The goal is to tune the ratio of charge and discharge time constants for the detector to deliver voltage V_{out} proportional to the RMS value of voltage V_{in} without going through a multiplication ($V_{in} \cdot V_{in}$), which would require circuit complication.

This is achieved by referencing voltage V_{out} originated by 8-VSB modulated RF to voltage V_{out} originated by CW. Since the modulation baseband of the nonmodulated (CW) RF signal is equal to zero, voltage V_{in} is a DC voltage. The RMS value for the DC voltage is equal to the voltage itself. Applied as voltage V_{in} , it will appear as $V_{out} = V_{in}$ on the output of the detector. The level of this voltage V_{out} can be used as a reference of RMS voltage for a given average power of RF and, after switching from CW to 8-VSB signal with the same average power level, tune the time constants so that the voltage V_{out} shows the same value.

The way to tune the time constants is to adjust the values of resistors $R1$ and $R2$ to achieve a certain voltage V_{out} . Thus, the RMS detector delivers true RMS value for two kinds of RF modulations: CW (no modulation) and 8-VSB.

Fig. 3 shows a non-modulated continuous wave (CW) signal of a known power level P_r may be applied to the RF input terminal 10 (see Fig. 1). The value of voltage V_{out} is observed. The continuous wave may then be replaced with an 8-VSB source of the same known power level P_r . Again, the output voltage V_{out} is observed. Since the input power levels were the same P_r , the value of voltage V_{out} should be the same for both cases. If it is not the same, then the values of resistor $R1$ and $R2$ in the charge and discharge paths, are varied to change the ratio of the charge and discharge time constants. Once the output voltages are the same then the values of the resistors are fixed and thus they have been optimized to achieve the same voltage V_{out} for both CW and 8-VSB baseband signals.

Reference is now made to the flow diagrams of Fig. 4 through Fig. 9 which illustrate the manner in which the microcontroller MC is programmed.

H6646, 6-343

Attention is specifically directed to Fig. 4 which illustrates the flow diagram for the fault process routine 200 which is employed for turning off the power amplifier when a fault condition has been determined. In step 202, a "module off" indication has been made because a condition has been determined to be a fault and the module (i.e. the power amplifier of Fig. 1) is to be turned off. This may be accomplished by the microcontroller MC controlling the RF switch 20 and the DC switch 40 by opening the switches and by adjusting the modulator 16 for minimum gain.

The procedure then steps to a three-strike process 204 during which the power amplifier is turned on and the conditions are again monitored to determine if there is a fault condition. In this case, the power amplifier is turned on up to three times over a 10 second interval to determine whether the fault condition is present.

Thereafter, the procedure advances to step 206 which determines whether the power amplifier has been successfully turned on during the three-strike process. If it has been successful, then the procedure advances to step 209 and continues monitoring. If the attempt to restart the power amplifier is not successful, then the procedure advances to step 208 during which the power amplifier is shut down and not restarted. This shut down procedure involves the microcontroller commanding the RF switch 20 to open and commanding the DC switch 40 to open as well as turning down the gain of the vector modulator 16.

Fig. 5 illustrates an emergency process routine 250 which is employed by the microcontroller in the event that emergency level faults have been detected. This routine includes step 252 during which the microcontroller responds to an interrupt signal received from one of the peak power comparators 72, 74 or 76 to interrupt the microcontroller and enter into the fault process routine 200, described above with reference to Fig. 4, for purposes of turning off the power amplifier module of Fig. 1. As will be recalled, comparator 72 provides such an interrupt signal when the input peak power signal V_{P1} is greater than a reference signal V_{R1} . Similarly, comparator 74 provides such an interrupt signal when the output forward peak power signal V_{P2} exceeds a reference V_{R2} . Also comparator 76 provides such an interrupt signal when the reflected peak power signal V_{P3} exceeds a reference V_{R3} (representative of a VSWR excessive condition).

H6646, 6-343

Fig. 6 illustrates a fast monitor process routine 300. In this routine, a determination is made at step 302 as to whether any of the pallets or power amplifiers PA-1 through PA-N have an overloaded current condition. If so, then the procedure advances to the fault process 200 (see Fig. 4). If not, the procedure advances to step 304.

5 Before proceeding with step 304 attention is now directed to Fig. 7 which illustrates a routine for determining whether one of the power amplifiers PA-1 through PA-N has an over-current condition. This routine commences with a start step 303 and, in the monitoring operation, a current sample I_{S1} representative of the current flowing in the power amplifier PA-1 is obtained in step 305. In step 307, the current sample I_{S1} is compared with a reference sample I_H representative of a high level of acceptance. If the current sample exceeds this high level, the procedure advances to the fault process 200 discussed hereinbefore with reference to Fig. 4. This type of routine may be practiced for monitoring each of the power amplifiers PA-1 through PA-N.

Attention is again directed to routine 300 in Fig. 6. If none of the power amplifiers are current overloaded, as determined in step 302, the procedure advances to step 304 wherein a determination is made as to whether the input power is overloaded. In this step, a signal representative of the average input power is signal V_{A1} and this is compared with a reference of an acceptable level in the microcontroller MC. If an overload condition is determined, the procedure advances to the fault process 200.

20 If the input power is not overloaded, the procedure advances to step 308 at which a determination is made as to whether the output power is overloaded. This is accomplished by comparing the signal V_{A2} , representative of the average output power, with an acceptable reference level. If signal V_{A2} exceeds the reference level, the procedure advances to the fault process routine 200. If not, then the procedure advances to step 310.

In step 310 a determination is made as to whether the reflected power is overloaded. This is determined by comparing the average reflected power signal V_{A3} with a reference level and if the reflected power is overloaded, the procedure advances to the fault process routine 200.

30 Fig. 8 illustrates a slow monitor process routine 350. In this routine, a determination is made at step 352 as to whether the DC voltage (V_{DD}) is too high. This

H6646, 6-343

is accomplished by comparing the voltage with a reference level. If the voltage V_{DD} is too high, the procedure advances to the fault process 200. If not, the procedure advances to step 354.

In step 354, a determination is made as to whether the heat sink temperature is too high. This is obtained by comparing a signal representative of the heat sink temperature from a suitable source 81 with a reference. If the heat sink is overloaded, the procedure advances to the fault process routine 200. Otherwise, the procedure advances to step 356.

In step 356, a determination is made as to whether there has been an automatic gain control failure (AGC failure). If so, the procedure advances to the fault process routine 200. Otherwise, the monitoring operation continues.

Fig. 9 illustrates the automatic gain control (AGC) routine 400. This procedure includes step 402 during which a check is made as to whether any of the power amplifiers PA-1 through PA-N have failed and the procedure advances to step 404 at which a determination is made as to whether the number (N) of failed power amplifiers exceeds 3 (i.e. is $N > 3$). If yes, the procedure advances to the fault process routine 200. If not, then output power compensation is determined wherein the output power sample P_{out} (corresponding with the representative signal V_{p2}) is re-calculated by

multiplying the measured value of the output power by the ratio of $\frac{12}{12-N}$. In this example, the total number of power amplifiers is 12 and if no power amplifiers have failed then the new value of the power output is equal to the old value. However, if some of the power amplifiers have failed, then a new calculation can be made in accordance with the step 406 to determine value of the output power.

Thereafter the procedure advances to step 408. In this step, the control output signal variation ΔV is generated as presented in the block bearing the label 408.

The procedure then advances to step 410 at which a determination is made as to whether the absolute value of ΔV is greater than Δ_{MAX} (i.e. is $|\Delta V| > \Delta_{MAX}$). If so, the absolute value of ΔV (i.e. $|\Delta V|$) is made equal to the value of Δ_{MAX} in step 412.

The procedure then advances to step 414 wherein the vector magnitude of the

H6646, 6-343

control voltage vector Δ_{MAX} is updated so that it is equal to $\Delta_{MAX} + \Delta V$.

The procedure then advances to step 416 wherein a check is made that the control voltage vector V_M is greater than 0 but is less than the full scale value of V_M which is used herein as V_{MF} .

5 The procedure then advances to step 418 wherein the microcomputer reads the phase signals which are referred to as ϕ_1 and ϕ_2 from the external source 83 (Fig. 1). These signals are used in the following. The procedure advances to step 420 wherein a

determination is made that ϕ is greater than 0 but less than $\frac{\pi}{2}$ (i.e. $0 < \phi < \frac{\pi}{2}$).

10 The procedure then advances to step 422 wherein the vectors to be supplied to the vector modulator 16 are generated. This includes the I_{vector} which is equal to $V_M \cos \phi$ and the Q_{vector} which is equal to $V_M \sin \phi$.

The procedure now advances to step 424 wherein the I_{vector} and the Q_{vector} are supplied to the vector modulator 16 to vary the phase and gain of the signal being processed by the
15 vector modulator 16.

Thereafter, the procedure advances to step 426 during which a suitable time, such as 20 milliseconds, is waited. Then, the procedure advances to step 428 during which a determination is made as to whether or not the AGC control has failed. If so, the procedure advances to the fault process procedure 200 (see Fig. 4).

20 In summation, the automatic gain control procedure 400 serves to protect or control the operation of the power amplifier module (power amplifier system of Fig. 1) by determining how many of the power amplifiers PA-1 through PA-N have failed. If more than three have failed, the power amplifier system is shut down by employing the fault process routine 200 (Fig. 4). However, if a lesser number of power amplifiers have failed the vector modulator 16 is
25 controlled by the I_{vector} and Q_{vector} control signals to adjust the phase and gain of the signal being processed.

A power amplifier system is presented for amplifying an RF input signal. The system includes a vector modulator for receiving and modifying an input signal and providing therefrom a modified signal. The system also includes at least one power amplifier the
30 operation of which is monitored and the vector modulator is controlled in accordance with the monitoring.

Claims:

1. A power amplifier system for use in amplifying an RF input signal comprising signal modulating means for receiving and modifying an input signal and providing therefrom a modified first signal, first
5 switching means for, when closed, supplying said input signal to said modulating means, at least one power amplifier, second switching means for, when closed, applying a DC voltage source to said at least one power amplifier and controlling said signal modulating means and said first and second switching means said
10 signal modulating means varies the gain of said input signal and said monitoring and control means includes means for applying a gain control signal to said modulating means for controlling the gain of said input signal.
2. A system as claimed in claim 1 wherein said modulating means
15 varies the phase of said input signal and wherein said monitoring and controlling means includes means for applying a phase control signal to said modulating means for varying the phase of said input signal, said modulating means is a vector modulator for varying the phase and gain of said input signal in response to phase and gain
20 control signals, in which said monitoring and controlling means applies phase and gain control signals to said vector modulator.
3. A system as claimed in claim 1 or 2 including first power detector
25 means for detecting said input signal and providing therefrom an average input power signal representative of the average input power thereof, and a second power detector means connected to the output of said at least one power amplifier for providing an output average power signal representative of the average output
30 power thereof, said monitoring and controlling means includes means for comparing said input and output average power signals and controlling said modulating means including detector means for detecting said input signal and providing a first peak power signal representative of the peak power level of said input signal, means for comparing said first peak power signal with a first reference

2,280,471

5 signal and providing a first fault signal in accordance therewith, said monitoring and control means including means responsive to said first fault signal for controlling said at least one power amplifier, and said monitoring and control means controls said system by turning said at least one power amplifier off in response to said first fault signal.

10 4. A system as claimed in claim 1 including detector means for detecting the output power of said at least one power amplifier and providing a second peak power signal representative of the peak power value of aid output signal, means for comparing said second peak power signal with a second reference signal and providing a second fault signal, said monitoring and control means including means responsive to said fault signal for controlling said system said monitoring and control means controls said system by turning said at least one power amplifier off in response to said second fault signal.

15 5. A system as claimed in claim 1 including detector means for detecting output power reflected from a load associated with said at least one power amplifier and providing a third peak power signal representative of the peak power level of said reflected power, means for comparing said third peak power signal with a third reference signal and providing a third fault signal, said monitoring and control means including means responsive to said third fault signal for controlling said system said control means controls said system by turning said at least one power amplifier off in response to said third fault signal.

20 6. A system as claimed in claim 1 including means for monitoring the operation of said at least one power amplifier system and providing a fault signal in response to detecting a fault condition, and means responsive to said fault signal for turning said at least one power amplifier off and for thereafter turning said at least one power amplifier on and then repeating said turning off and turning on of said at least one power amplifier a plurality of times over a given

25

30

2,280,471

time internal to determine if the detected fault condition continues after repeated turning off and turning on of said system and if so, then turning said at least one power amplifier off without turning it on again, said detected fault condition is a condition in which said at least one power amplifier has an overloaded current condition or said detected fault condition is a condition in which power input to said at least one power amplifier is overloaded, or the detected fault condition is a condition in which power output from said at least one power amplifier is overloaded, said detected fault condition is a condition in which power reflected from a load associated with said at least one power amplifier is overloaded, or said detected fault condition is a condition wherein said DC voltage source is too high, or said detected fault condition is a condition wherein a heat sink associated with said at least one power amplifier is overloaded, or said fault condition is a condition in which an automatic gain control associated with said at least one power amplifier is overloaded.

7. A power amplifier system for use in amplifying an RF input signal comprising, signal modulating means for receiving and modifying an input signal and providing therefrom a modified first signal, first switching means for, when closed, supplying said input signal to said modulating means, N power amplifiers, divider means for dividing said first signal into N signals for respective application to said N power amplifiers to provide N amplified signals, second switching means for, when closed, applying a DC voltage source to each of said N power amplifiers, means for combining said N amplified signals to provide therefrom an amplified output signal for application to an output circuit, means for monitoring the operation of said N power amplifiers and controlling said signal modulating means and said first and second switching said signal modulating means varies the gain of said input signal and said monitoring and control means includes means for applying a gain control signal, to said modulating means for controlling the gain of said input signal,

2,280,471

or said modulating means varies the phase of said input signal and wherein said monitoring and controlling means includes means for applying a phase control signal to said modulating means for varying the phase of said input signal.


- 5 8. A system as claimed in claim 7 wherein said modulating means is a vector modulator for varying the phase and gain of said input signal in response to phase and gain control signals, said monitoring and controlling means applies phase and gain control signals to said vector modulator, including first power detector means for detecting
10 said input signal and providing therefrom an average input power signal representative of the average input power thereof, and a second power detector means connected to the output of said power amplifier for providing an output average power signal representative of the average output power thereof and, said
15 monitoring and controlling means includes means for comparing said input and output average power signals and controlling said modulating means.
9. A system as claimed in claim 7 including detector means for detecting said input signal and providing a first peak power signal
20 representative of the peak power level of said input signal, means for comparing said first peak power signal with a first reference signal and providing a first fault signal in accordance therewith, said monitoring and control means including means responsive to said first fault signal for controlling said amplifier, said monitoring and
25 control means control said system by turning said amplifier off in response to said first fault signal, including detector means for detecting the output power of said amplifier and providing a second peak power signal representative of the peak power value of said out put signal, means for comparing said second peak power signal
30 with a second reference signal and providing a second fault signal in accordance therewith, said monitoring and control means including means response to said second fault signal for controlling said system, and said monitoring and control means control said

2,280,471

system by turning said amplifier off in response to said second fault signal.

10. A system as claimed in claim 7 including detector means for detecting output power reflected from a load associated with said amplifier and providing a third peak power signal representative of the peak power level of said reflected power, means for comparing said third peak power signal with a third reference signal and providing a third fault signal said monitoring and control means including means responsive to said third fault signal for controlling said system, said control means controls said system by turning said amplifier off in response to said third fault signal, including means for monitoring the operation of said power amplifier system and providing a fault signal in response to detecting a fault condition, and means responsive to said fault signal for turning said amplifier off and for thereafter turning said amplifier a plurality of times over a given time interval to determine if the detected fault condition continues after repeated turning off and turning on of said system and if so, then turning said amplifier off without turning it on again.

20



4020GA

4020GA2




Fig.2




Fig.3

4020GA

4020GA3




Fig.5




Fig.4

4020GA

4020GA4




Fig.6




Fig.7

4020GA

4020GA5




Fig.9A




Fig.8

4020GA

4020GA6




Fig.9B

