

672443

PHA 40697
P/00/001
Section 29

AUSTRALIA
PATENTS ACT 1990

PATENT REQUEST: STANDARD PATENT

WE, being the person identified below as the Applicant, request the grant of a patent to the person identified below as the Nominated Person, for an invention described in the accompanying standard complete specification.

Full application details follow:

[71] Applicant: MAGNAVOX ELECTRONIC SYSTEMS COMPANY
Address: 1313 Production Road, Fort Wayne,
Indiana 46808, U.S.A.

[70] Nominated Person: MAGNAVOX ELECTRONIC SYSTEMS COMPANY
Address: 1313 Production Road, Fort Wayne,
Indiana 46808, U.S.A.

[54] Invention Title: "SPREAD SPECTRUM COMMUNICATION SYSTEM"

[72] Name(s) of actual inventor(s): Ralph W. SCHOOLCRAFT

[74] Address for service in Australia:- Patent & Trade Marks
Division, Philips Industries Holdings Limited 16th
Floor, The Philips Building, 15 Blue Street, North
Sydney. N.S.W. 2060.

Attorney Code PH

BASIC CONVENTION APPLICATION(S) DETAILS

[31] Application No.	[33] Country	Country Code	[32] Date of Applc.
979,123	U.S.A.	U.S.	20.11.92

Drawing Number recommended to accompany the Abstract: FIG.

S 042090 191193

For and on behalf of
MAGNAVOX ELECTRONIC SYSTEMS COMPANY

P. Mackenzie
P.W. Mackenzie (Attorney)

16/11/93
Date

AUSTRALIA

PATENTS ACT 1990


NOTICE OF ENTITLEMENT

(TO BE FILED BEFORE ACCEPTANCE)

WE, **MAGNAVOX ELECTRONIC SYSTEMS COMPANY** of 1313 Production Road, Fort Wayne, Indiana 46808-1187 U.S.A. being the applicant in respect of Application No.51811/93 state the following:-

1. The person nominated for the grant of the patent has entitlement from the actual inventor by virtue of an assignment.
2. The person nominated for the grant of the patent has entitlement from the applicant of the basic application by virtue of an assignment.
3. The basic application listed on the Patent Request Form is the first application made in a Convention country in respect of the invention.

For and on behalf of
MAGNAVOX ELECTRONIC SYSTEMS COMPANY


P.W. Mackenzie (Attorney)

08/06/94.
DATE



AU9351811

(12) PATENT ABRIDGMENT (11) Document No. AU-B-51811/93
(19) AUSTRALIAN PATENT OFFICE (10) Acceptance No. 672443

- (54) Title
SPREAD SPECTRUM COMMUNICATION SYSTEM
- (51)⁵ International Patent Classification(s)
H04L 009/20 H04L 027/20 H04L 027/22
- (21) Application No. : 51811/93 (22) Application Date : 19.11.93
- (30) Priority Data
- (31) Number (32) Date (33) Country
979123 20.11.92 US UNITED STATES OF AMERICA
- (43) Publication Date : 02.06.94
- (44) Publication Date of Accepted Application : 03.10.96
- (71) Applicant(s)
MAGNAVOX ELECTRONIC SYSTEMS COMPANY
- (72) Inventor(s)
RALPH W. SCHOOLCRAFT
- (74) Attorney or Agent
PHILIPS ELECTRONICS AUSTRALIA LIMITED , PO BOX 1138, NORTH SYDNEY NSW 2059
- (56) Prior Art Documents
US 5131006
- (57) Claim

1. A transmission system comprising a transmitter for applying a pseudo-noise (PN) modulated signal to a transmission channel and a receiver for receiving said pseudo-noise modulated signal from the channel, said receiver comprising correlation means, for correlating digitized samples of the received signal with locally generated PN code sequences, wherein the receiver comprises means to obtain correlation measurements over a plurality of consecutive time bins, demodulation means for demodulating the received signal to obtain potential baseband data relating to all of the time bins, and signal combining means, for combining usable baseband data components in proportion to their relative signal strengths.

7. A receiver for receiving a pseudo-noise modulated signal from the channel, said receiver comprising correlation means, for correlating digitized samples of the received signals with locally generated PN code sequences, wherein said receiver comprises means to obtain correlation measurements over a plurality of consecutive time bins, demodulation means for demodulating the received signals to obtain potential baseband data relating to all of the time bins, and signal combining means, for combining usable baseband data components in proportion to their relative signal strengths.

PHA40647

AUSTRALIA

PATENTS ACT 1990

COMPLETE SPECIFICATION
FOR A STANDARD PATENT

O R I G I N A L

Name of Applicant: MAGNAVOX ELECTRONIC SYSTEMS COMPANY
1313 Production Road, Fort Wayne,
Indiana 46808, U.S.A.

Actual Inventor(s): Ralph W. SCHOOLCRAFT

Address for Service: PATENT AND TRADE MARKS DIVISION,
PHILIPS INDUSTRIES HOLDINGS LIMITED
15 BLUE STREET,
NORTH SYDNEY, NSW 2060

Invention Title: "SPREAD SPECTRUM COMMUNICATION SYSTEM"

The following statement is a full description of this invention
including the best method of performing it known to us.

SPREAD SPECTRUM COMMUNICATION SYSTEM

The present invention is related to a transmission system comprising a transmitter for applying a pseudo-noise (PN) modulated signal to a transmission channel and a receiver for receiving said pseudo-noise modulated signal from the channel, said receiver comprising correlation means, for correlating digitized
 5 samples of the received signal with locally generated PN code sequences.

The invention is also related to a receiver for use in such a transmission system.

A transmission system according to the preamble is known from the book
 10 "Mobile Radio Communications" by Raymond Steele, published by Pentech Press Publishers London, pp. 45-51.

Digital modulation techniques for communication are well known, and include phase shift keying (PSK), where a constant amplitude carrier signal is selectively reversed in phase to indicate a binary change of state of a data signal.
 15 In quadriphase phase shift keying (QPSK), the modulated carrier can assume any of four phase states, as determined by pairs of data bits.

For security and other reasons, a modulated carrier signal may also be subject to spread spectrum modulation. A spread spectrum signal is, as the name implies, spread over a wide bandwidth and is relatively immune to eavesdropping
 20 and jamming. A technique uses a pseudo-random (PN) code sequence to obtain the desired spectral spreading. A PN sequence is a binary sequence that repeats itself after a large number of cycles. Thus the binary numbers in the sequence are not truly random, but if the repetition cycle of the sequence is long enough its spectrum shares many of the properties of random electromagnetic noise. In the
 25 context of a data transmitter, PN modulation may be effected by simply passing the data stream and the PN code sequence through an exclusive OR gate, to achieve PSK modulation of the data onto the PN code. Data bits are either inverted or not, depending on the presence or absence of a logical "1" bit in the PN code. The data symbol rate is typically many times slower than the PN code
 30 rate (referred to as the PN "chip" rate). The resulting digital data



stream is a PN code modulated by the slower data symbol stream, and is used to modulate a carrier signal in accordance with a digital modulation technique, such as QPSK, and the modulated carrier is transmitted. The present invention is concerned with systems of this general type, and particularly with such systems in which there
5 may be multiple transmission paths between a transmitter and a receiver.

Receiving and demodulating signals that have been subject to PN modulation requires that the same PN code sequence be generated in the receiver, and correlated with received signals to extract the data modulation. One type of correlation technique employs a digital matched filter to compare the received digital signal with
10 the locally generated version of the PN code. The digital filter produces an in-phase (I) signal and a quadrature (Q) signal from which a digital demodulator (such as a DPSK demodulator) can derive data values. Another function of the digital matched filter is to produce correlation measurements from which synchronization (sync) signals can be generated and used to handle multipath components in the received data signals. To
15 better understand this aspect of PN-modulated data transmission, some further background is needed.

Multipath components arise in rf communication systems of various types when a receiving antenna detects signals arriving non-simultaneously over different paths. Multiple transmission paths may result from various causes, such as from
20 atmospheric effects, or reflections from buildings or geographical features. In any event, a transmitted signal may produce multiple received signals of different strength. Conventionally, multipath errors are resolved in a PN correlator by selecting one or two correlation measurements having the highest signal strength, and using only these measurements during subsequent signal processing in which data demodulation is
25 completed. For example, a PN correlator may generate an output spanning a few microseconds, long enough to produce multiple correlation output peaks resulting from multipath errors. Typically a single correlation peak value is detected in a sync detector, which integrates over a suitably large number of symbols, and a time epoch associated with the detected correlation peak is used to control input to a data demodulator.

30 A practical characteristic of transmissions involving multipath errors is that the multipath conditions may vary rapidly with time, especially if the transmitter or receiver, or both, are in motion, or if a source of multipath reflections is in motion. Therefore, a path that provides the maximum signal strength at a receiver at one instant




in time may fade or disappear in the next instant, to be replaced by other signal paths providing different signal strengths. This effect leads to a deteriorated performance of the known transmission system.

5 An object of the invention is to provide a transmission system according to the preamble having an improved performance with respect to the known transmission system.

According to the present invention there is provided, a transmission system comprising a transmitter for applying a pseudo-noise (PN) modulated signal to a transmission channel and a receiver for receiving said pseudo-noise modulated
10 signal from the channel, said receiver comprising correlation means, for correlating digitized samples of the received signal with locally generated PN code sequences, wherein the receiver comprises means to obtain correlation measurements over a plurality of consecutive time bins, demodulation means for demodulating the received signal to obtain potential baseband data relating to all of the time bins, and
15 signal combining means, for combining usable baseband data components in proportion to their relative signal strengths.

In the transmission system according to the invention the autocorrelation function of the input signal is determined, and peaks in this autocorrelation function relating to multipath components are identified. Demodulated signals
20 corresponding to said identified multipath components are then combined to obtain a combined base band signal. The resulting simultaneous use of multipath signal components improves the overall signal quality and assures continuity of data reception in a dynamic multipath transmission medium.

According to an embodiment of the invention data symbols to be derived
25 from the received signals may change state at a data symbol rate, and each received symbol persists for a data symbol interval. The correlating step operates on successive segments of the received signal, and there is an integral number of segments in each data symbol interval. More specifically, the correlating step includes correlating a first segment of locally generated PN code with a moving segment of the received signal, to obtain a first set of correlation measurements
30 over multiple time bins relating to the signal segment, correlating successive subsequent segments of the locally generated PN code with successive moving segments of the received signal, to obtain multiple sets of correlation measurements similar to the first set, and integrating the first and successive sets of correlation
35 measurements over all of the segments in each data symbol interval. Thus for each data symbol interval, the correlation process yields a set of correlation measurements, such as sixty-four measurements, integrated over all segments in the symbol interval. In the presently preferred embodiment of the invention, there are



sixteen segments in each symbol interval, although this is not a critical limitation.

The multiple correlation measurements may be taken over successive time segments and then integrated over complete data symbol time intervals, to obtain multiple coherently integrated correlation measurements for each symbol time interval.

5 It is also an important aspect of the invention that data demodulation is performed for all of the time "bins," and then resulting multipath signal components are selected, based on the times of occurrence of peaks in the correlation measurements. The selected data values of the multipath components are then combined by weighting them in accordance with their signal strengths.

10 In the disclosed embodiment of the invention, the correlating step further comprises the steps of generating from the correlation measurements a set of in-phase (I) and quadrature (Q) signals for each data symbol interval; and generating from the I and Q signals a set of correlation magnitude signals approximately proportional to $(I^2 + Q^2)$, for each data symbol interval.

15 To generate sync signals relating to peaks in the correlation measurements, the method further comprises the steps of integrating the correlation magnitude signals over a selected number of data symbol intervals; detecting peaks in the integrated correlation magnitude signals; and generating from the detected peaks, sync signals indicative of the relative times of arrival associated with the multipath components.

20 In the preferred embodiment of the invention, the step of demodulating the received signals includes deriving multiple data values from the I and Q signals obtained for each data symbol interval, the multiple data values being associated with the times of arrival of multipath components. Further, the step of combining the usable baseband data components in proportion to their relative signal strengths includes accumulating selected ones of the multipath data values, under control of the generated sync signals, whereby the selected multipath data values are accumulated only if they correspond in time to significant correlation measurements.

25 A number of aspects of the manner in which receiver functions are implemented contribute to the desirable simplicity of the implementation, which can then be conveniently reduced in size and cost. One of these aspects involves the step of generating sets of correlation magnitude signals approximately proportional to $(I^2 + Q^2)$. In the preferred embodiment of the invention, this step includes determining the

30

magnitudes of the I and Q signals, without regard to sign, and adding the magnitudes of the I and Q signals.

In a further aspect of the invention, there is provided a receiver for receiving a pseudo-noise modulated signal from the channel, said receiver comprising correlation means, for correlating digitized samples of the received signals with locally generated PN code sequences, wherein said receiver comprises means to obtain correlation measurements over a plurality of consecutive time bins, demodulation means for demodulating the received signals to obtain potential baseband data relating to all of the time bins, and signal combining means, for combining usable baseband data components in proportion to their relative signal strengths.

It will be appreciated from the foregoing that the present invention represents a significant advance in the field of digital communication using PN modulation. In particular, the invention provides a novel technique for handling multipath transmissions, wherein correlation measurements are maintained over multiple time bins and data demodulation is also performed over multiple time bins, to yield multiple data values that can be conveniently filtered and combined in accordance with their relative multipath signal strengths. Other aspects and advantages of the invention will become apparent from the following more detailed description, taken in conjunction with the accompanying drawings.

Figure 1 is a block diagram of a transmitter employing quadriphase pseudo-noise (PN) modulation and phase shift keying (PSK) data modulation;

Figure 2 is a block diagram of a receiver for receiving and demodulating signals received from the transmitter of Figure 1;

Figure 3 is a block diagram of 512-chip PN digital matched filter correlator included in the receiver of Figure 2 and embodying the present invention;

Figure 4 is a block diagram of a 64x11 correlator, two of which are used in the 512-chip PN correlator of Figure 3;

Figure 5 is a block diagram of a sync detector for use in the receiver of Figure 2;

Figure 6 is a block diagram of a differential phase shift keying (DPSK) data demodulator and multipath combiner used in the receiver of Figure 2;

Figs. 7A through 7F are timing and vector diagrams illustrating the operation of the PN correlator of the invention; and

Figure 8 is a graph showing an example of the analog equivalent of the PN correlator output for successive data symbols, wherein the output for each symbol is derived from coherent integration of sixteen time segments of thirty-two chips each, as further explained below.

As shown in the drawings for purposes of illustration, the present invention is concerned with improvements in data transmission and reception using pseudo-noise (PN) modulation. PN modulation has been used in data transmission to spread the spectrum of the transmitted signals over a wide bandwidth. Spectral



spreading of the signals makes them more immune to eavesdropping and accidental or deliberate interference. A disadvantage of PN modulation is that demodulation equipment required in a receiver tends to be complex and bulky unless design compromises are made. One such compromise relates to the manner in which multipath signals are handled. Multipath transmissions arrive at the receiver at slightly different times and PN demodulation requires complex circuitry if all potential signal paths are to be considered throughout the PN demodulation and data demodulation process.

Typically, the received PN signals are correlated with a locally generated PN code sequence and, if multiple correlation peaks are detected, the strongest is selected as a time reference for use in data demodulation. This approach reduces the complexity of receiver circuitry, but at the expense of possible loss of data if the selected correlation peak is replaced by another one resulting from a different transmission path.

Figures 1 and 2 depict a transmitter and receiver, respectively, using phase shift keying (PSK) data modulation and quadriphase phase shift keying (QPSK) PN modulation. The functional blocks in these figures are general enough that they are descriptive both of the present invention and of numerous transmitters and receivers of the prior art.

The function of the transmitter (Figure 1) is to convert a data stream, received over line 10, to a modulated radio-frequency (rf) signal for transmission from an antenna 12. The data signals are shown as being input to a buffer 14 in which a slow PN code may be added, but this has no direct relevance to the present invention. Slow PN coding may be employed to facilitate acquisition of the signal at the receiver, but in the description of the receiver that follows it will be assumed that acquisition has been achieved. The data then passes into a quadriphase modulator 16 in which two types of modulation take place. A timing synthesizer 18, driven by a crystal oscillator 20, generates local oscillator (LO) signals which form the carrier signal to be transmitted. In PSK data modulation, the phase of the carrier signal is modulated in accordance with the state of the data signals, and can assume one of two phase states. In addition to data modulation performed in modulator 16, QPSK PN modulation is performed by changing the phase of the carrier signal in accordance with the state of two PN binary sequences, generated in a PN coder 22. Basically, QPSK PN modulation means that the phase of the carrier can assume any of four phase states as a function of the two PN code sequences. The present implementation uses staggered or offset QPSK (referred to as

SQPSK or QPSK), in which one of the code sequences is delayed by half of a "chip" interval. The PN code rate is faster than the data rate by some fairly large factor, such as 512, so that there will be 512 potential changes of the PN sequence during the time that one data symbol is presented. The PN code bits are referred to as "chips" and, in this example, there are 512 chips of PN code for each symbol time interval.

The data modulated and PN modulated carrier signal is next processed by an up/down converter 24, the purpose of which is simply to change the frequency to a convenient one for transmission from the antenna 12. A power amplifier 26 may also be interposed between the up/down converter 24 and the antenna 12. The power amplifier 26, together with the PN coder 22 and the timing synthesizer 18, may be controlled by common line 28. For those applications involving voice data, the control line 28 may be connected to a push-to-talk switch on a microphone (not shown). The transmitter also includes a clock counter 30 that receives clock signals from the timing synthesizer and generates timing signals for the PN coder 22 and other components of the transmitter. It will be appreciated that certain types of data may require other processing functions. For example, voice data will need to be digitized before modulation. However, the present invention pertains to any type of digital data transmission using PN modulation.

The receiver (Figure 2) also includes an antenna 12', a crystal oscillator 20' and a timing synthesizer 18'. Although these are shown as independent of the corresponding components in the transmitter, it will be understood that, in a practical embodiment, the components would be shared by the transmit and receive functions. Similarly, the receiver includes a clock counter 30' and a PN coder 22'. PN-modulated signals received through the antenna 12' are first down-converted and subjected to intermediate-frequency amplification, as shown in block 32. Output signals from this stage of the receiver are in-phase (I) and quadrature (Q) components of the received signal, also referred to as cosine signal samples and sine signal samples. These signals, still in analog form, are input to a 512-chip correlator 34, which also receives locally generated PN code sequences, referred to as A and B codes, from the PN coder 22'. The 512-chip correlator generates outputs of two types: two signals representative of the I and Q component samples of the received signal, still data modulated, and an amplitude signal representative of the instantaneous amplitude of the received signal and proportional to $(I^2 + Q^2)$. The latter signal is input to a sync detector 36, which generates timing signals indicative to the relative times of occurrence of correlation

peaks detected by the correlator 34.

The I and Q signals are passed to a DPSK demodulator 38. Based on successive input values of I and Q, the demodulator 38 regenerates a data stream, some of which may contain values equivalent to received electromagnetic noise. In a
5 multipath combiner, the data values emerging from the data demodulator 38 are subject to filtering by a sync signal generated by the sync detector 36. In receivers prior to this invention, the sync detector 36 would generate a sync signal related to a single selected correlation peak, ignoring possible other multipath peaks, and the combiner 40 could more properly be referred to as a multipath selector. In any event, selected data signals
10 may be stored temporarily in a buffer 42, before being transmitted over data line 44.

It will be understood from the foregoing general description of transmitter and receiver functions that, as in most communication systems, there are practical problems relating to acquisition of and synchronization with a received signal. Conventional solutions to these problems are assumed in this description of the present
15 invention, which is concerned principally with the correlation of a locally generated PN code with an incoming PN-modulated signal, and the novel manner in which multipath signals are handled.

Figure 3 shows the 512-chip correlator 34 in more detail. First, the sine and cosine signals are input to analog-to-digital (A/D) converters 50 and 50', which are
20 driven by a clock signal at a rate twice the PN chip rate and produces two digital data streams at the same rate, for input to respective correlators, referred to as 64x11 correlators 52 and 52'.

In this implementation of the invention, only the most significant bit of output from the A/D converters 50, 50' is used in the correlators 52, 52'. For most
25 applications, this is adequate, but degradation may occur in the presence of an interference signal that is frequency and phase coherent with the sampling process. In that case, the receiver may have to employ a conventional technique such as phase dithering of the sampling clock to effectively eliminate the interference, or the correlation process may have to be "deepened" to include A/D samples of 3 or 4 bits
30 instead of just the most significant bit.

Also input to the correlators 52, 52' at the same rate is a stream of locally generated PN codes, over line 54, a symbol clock rate signal, on line 56, and a clock at twice the chip rate, on line 57. As will be explained in more detail with reference to

Figure 4, correlator 52 generates a pair of signals proportional to $A \cos \theta$ and $B \sin \theta$, respectively, where A and B are constants and θ is the phase angle. Similarly, correlator 52' generates a pair of signals proportional to $-A \sin \theta$ and $B \cos \theta$, respectively. The cosine components are added in an adder circuit 58, to produce an output signal proportional to Q on line 60. Similarly, the sine components are added in another adder circuit 58', to produce an output signal proportional to I on line 60'. The required signal proportional to $I^2 + Q^2$ is generated in accordance with an approximation, by taking the magnitude of the Q component, using circuit 62, and the magnitude of the I component, using circuit 62'; then combining these two magnitudes in another adder circuit 64, to produce the approximated $I^2 + Q^2$ signal on line 66.

A traditional, but more costly, way to compute the required output signal would be based on the trigonometrical identity $\sin^2 \theta + \cos^2 \theta = 1$, but would require two signal squaring circuits. Instead, the presently preferred implementation uses the approximation $|\sin \theta| + |\cos \theta| \approx 1$. Since the sine and cosine terms are already available, implementation of this approach requires only the two absolute value circuits 62, 62' and the adder 64. Moreover, the approximation is sufficiently accurate because of the somewhat qualitative way that the results are subsequently used in the sync detector 36. As will be described below, the sync detector integrates the results over multiple sample intervals and makes a comparison with a preselected threshold value.

The two 64x11 correlators 52, 52' are identical in structure. One of these correlators is illustrated in Figure 4, and includes a first 64-bit shift register 70 into which the sine or cosine samples are serially shifted, and a second 64-bit shift register 72 into which the two PN code sequences (A and B) are serially shifted. In the receiver, the A and B PN code sequences are supplied to the shift register 72 in interlaced form, i.e. as alternating A and B codes. Both the interlaced PN codes and the signal samples are clocked into their respective registers 72, 70, at twice the code chip rate. When register 72 is filled with a new set of sixty-four code bits, the entire register is copied in parallel to a 64-bit fixed register 74. This parallel transfer takes place every sixty-four half-chip cycles, i.e. at $1/32$ of the chip rate.

Correlation also occurs at twice the chip rate, and involves a bit-by-bit comparison of the codes held stationary in register 74 and the input sample bits being shifted through register 70. At each comparison cycle, the odd-numbered bits in register 70 are compared with the A -code bits in register 74, using exclusive OR gates 76,

which function as modulo-two correlators. That is to say, when the inputs are the same the output will be logical "0" and when the inputs are different the output will be a logical "1." Similarly, the even-numbered bits in register 70 are compared with the B-code bits in register 74, using another set of exclusive OR gates 76'. Each of the
5 exclusive OR gates 76, 76' provides a one-bit match signal. The outputs of the upper set of exclusive OR gates 76 are combined in a summation circuit 80, and the outputs of the lower set of exclusive OR gates 76' are combined in another summation circuit 80'. Because there are thirty-two inputs to each of the summation circuits 80 and 80', the output of each is a quantity in the range 0-32, which requires a five-bit output line from
10 each of the summation circuits.

The remaining portion of the correlator performs a coherent integration function, and includes two adder circuits 82, 82', and two 64x11 shift registers 84, 84'. The term "64x11" means that each of the shift registers 84, 84' has sixty-four stages or positions, and that each stage is eleven bits "wide". Thus the digital quantities shifted
15 through the registers may be up to eleven bits long. The output of each shift register 84, 84' is fed back over line 86, 86' as an input to the corresponding adder circuit 82, 82'. The other inputs for the adders 82, 82' are derived from the summation circuits 80, 80', respectively. Although detailed timing circuitry has been omitted from the drawing for simplicity, it will be understood that the adders 82, 82' and the shift registers 84, 84' are also clocked at twice the chip rate. Thus, as correlation results emerge from the
20 summation circuits 80, 80', they are integrated with prior results in the adder circuits 82, 82' and then shifted through the shift registers 84, 84'.

Figure 8 helps provide an intuitive understanding of how the correlator of Figure 4 operates. At the beginning of a symbol interval, the shift registers 84, 84' are cleared, as indicated by the symbol clock signal on line 86. Then, after sixty-four half-chip cycles, the registers 84, 84' contain a set of sixty-four time-spaced accumulations from the summation circuits 80, 80'. The time interval spanning sixty-four half-chip cycles, or thirty-two chips, is referred to as a time "segment." In the illustrative embodiment, there are sixteen segments per symbol interval. At the end of subsequent
25 segments after the first one in a symbol interval, the shift registers 84, 84' contain digital quantities indicative of an accumulation of correlation results over all of the segments in the symbol interval processed up to that point. After sixteen segments have been processed, the shift registers 84, 84' contain quantities indicative of the

accumulated correlation results over all sixteen segments in the symbol interval. The first "trace" of Figure 8 is an analog equivalent of these accumulated correlation results taken over sixteen segments. Each "point" in the trace represents an accumulation of sixteen sets of thirty-two correlation bits from the exclusive OR gates 76. It will be understood, however, that there is no real analog implementation corresponding to Figure 8, which is solely for purposes of explanation.

The accumulated correlation results in the shift registers 84, 84' are shifted out of the registers at the end of each symbol interval, for further processing. This step may be accomplished by means of a "symbol modulo-16" clock signal, as shown in line 88, and a pair of multibit-wide AND gates 90, 90'. The timing signal on line 88 provides an enabling signal to the AND gates only during the sixteenth and last segment of the symbol interval. Therefore, during the last segment of each symbol interval, the accumulated correlation results for that interval are gated out of the shift registers 84, 84', as well as being fed back to the adder circuits 82, 82'. In an alternative implementation (not shown), the accumulated correlation results are gated from the outputs of the adders 82, 82' at the end of the symbol time interval.

It will be recalled from the discussion of Figure 3 that the data quantities output from the 64x11 correlators 52, 52' are used to generate I and Q signals, and to generate an approximated $I^2 + Q^2$ signal. The processing of the $I^2 + Q^2$ signal in the sync detector 36 will now be discussed with reference to Figure 5.

The sync detector includes an adder circuit 92, a 64-position shift register 94, a threshold compare circuit 96, and a feedback multiplier circuit 98. The $I^2 + Q^2$ signal on line 66 appears as a burst of sixty-four digital quantities, at the half-chip cycle rate, and in the last segment of each data symbol interval. These digital quantities are input to the adder circuit 96, the output of which feeds into the first position of the 64-position shift register 94. The last position of the register 94 feeds back to the adder circuit, through the feedback multiplier 98, and also supplies output to the threshold compare circuit 96. After the first burst of input quantities, the shift register 94 is filled with these quantities. After the next burst, corresponding to a second symbol interval, the register contains an accumulated set of data quantities. Operation of the adder circuit 92 and shift register 94 is similar to that of the 64x11 comparator, except that the multiplier 98 gives less weight to the accumulated totals than to the newly arriving values. In the presently preferred embodiment, the multiplier has a value less than unity

and equal to the fraction 31/32. After a selected number of symbol intervals of data have been processed, such as thirty, the accumulated data quantities are gated through the threshold compare circuit 96, using a gating arrangement similar to the AND gate 90 in Figure 4, but with a timing signal that enables the gate only during the 30th data burst. The accumulated data values for thirty consecutive symbols are shown by way of example in the last trace of Figure 8, in which the broken line indicates the preselected threshold imposed by the threshold compare circuit 96. What appears at the output of the threshold compare circuit 96, on line 100, is a filtered set of sync signals, corresponding only to the correlation peaks above the preselected threshold. The timing of each sync signal is indicative of a separate transmission medium multipath, and is used to select meaningful data from the data demodulation process that is performed in parallel with sync detection.

Data demodulation is performed using a digital implementation of a DPSK demodulator circuit 110 (Figure 6). The Q and I data quantities input on lines 60 and 60' are input to two 64-position shift registers 112, 112', clocked by bursts of timing signals at the half-chip rate, as indicated by line 114. The output of each register 112, 112' is connected to a multiplier circuit 116, 116', the other input of which is derived from the Q and I input lines 60, 60'. Thus, each input quantity is multiplied by its counterpart in the previous burst of inputs, i.e. associated with the previous data symbol. The outputs of the multipliers are added together in an adder circuit 118.

The multipliers 116, 116' and the adder 118 together perform a running dot product of the two digital representations of I and Q, in accordance with the formula:

$$(\text{Symbol}_s \sin) \times (\text{Symbol}_{s+1} \sin) + (\text{Symbol}_s \cos) \times (\text{Symbol}_{s+1} \cos)$$

The output of the adder 118, on line 120, consists of a burst of sixty-four data values for each data symbol interval. Clearly, some of these values will be derived from noise and will be of no interest. The only data values of interest will be those that correspond in time with the occurrence of correlation peaks generated in the PN demodulation process. These output values will be a decoded DPSK data bit with an amplitude proportional to the strength of the particular signal path to which it corresponds.

The final step in demodulation is to input the data values on line 120 to a gated accumulator 122, which is initially cleared by the symbol clock signal, on line 124, and is gated to receive and accumulate data only upon the occurrence of sync


signals on line 100. This is the process of multipath combining in accordance with the invention. The gated accumulator gives each data value a weight corresponding to the amplitude of the signal received over a particular path. At the end of the symbol interval, the gated accumulator contains a value indicative of the data value for symbol, as derived from possible multiple signal paths. This can be converted to a binary quantity, or the data value may be used in a "soft decoding" scheme of some kind.

Figures 7A-7F depict some illustrative code waveforms and corresponding vector representations that may be helpful in understanding operation of the PN correlation process. FIGS. 7A and 7B are illustrative A and B PN codes, which, it will be observed, can change state at a rate corresponding to the chip rate. Also, the B code transition times are offset from the A code transition times by one half-chip interval to achieve the phase stagger or offset required in staggered or offset QPSK (SQPSK or OQPSK). Figure 7C shows the vector representation of the transmitted OQPSK signals corresponding to the A and B codes in FIGS. 7A and 7B. It will be seen that there are four phase states corresponding to the four possible combinations of the A and B code states. Figure 7D shows the waveform of the interlaced A and B codes as generated in the receiver. Note that the interlaced code has possible state transitions at half-chip intervals. Finally, FIGS. 7E and 7F show the correlator A products and correlator B products in vector representation.

An important aspect of the invention is that correlation measurements are maintained in multiple (in this case sixty-four) time bins that can indicate some degree of correlation with signals received over more than one signal path to the receiver. Further, these measurements are maintained separately, but filtered using a threshold as desired, and used to make the best determination of a data value for each received symbol. The principal advantages of the technique of the invention are that multipath signals can be combined to provide a higher quality indication of data, and continuity of communication is assured because signals received over multiple paths are always being processed, rather than selectively discarded.

It will be appreciated from the foregoing that the present invention represents a significant advance in the field of data communications using PN modulation. In particular, the PN correlation technique of the invention provides a measure of correlation for possible multiple signal paths, and these measures of correlation can be used to combine multipath data signals to provide higher quality and

more reliable data communication. Although an embodiment of the invention has been described in detail by way of illustration, it will be appreciated that various modifications may be made without departing from the spirit and scope of the invention. Accordingly, the invention should not be limited except as by the appended claims.



CLAIMS:

1. A transmission system comprising a transmitter for applying a pseudo-noise (PN) modulated signal to a transmission channel and a receiver for receiving said pseudo-noise modulated signal from the channel, said receiver
 5 comprising correlation means, for correlating digitized samples of the received signal with locally generated PN code sequences, wherein the receiver comprises means to obtain correlation measurements over a plurality of consecutive time bins, demodulation means for demodulating the received signal to obtain potential baseband data relating to all of the time bins, and signal combining means, for
 10 combining usable baseband data components in proportion to their relative signal strengths.

2. A transmission system according to claim 1, wherein the data symbols to be derived from the received signal may change state at a data symbol rate, and each received symbol persists for a data symbol interval, the correlation
 15 means being arranged for operating on successive segments of the received signal, wherein there are an integral number of segments in each data symbol interval, and the correlation means includes means for correlating successive segments of the locally generated PN code with successive moving segments of the received signal, to obtain multiple sets of correlation measurements over multiple time bins relating
 20 to the signal segment, and means for integrating the successive sets of correlation measurements over all of the segments in each data symbol interval.

3. A transmission system according to claim 2, wherein the correlation means further comprises means for generating from the correlation measurements a set of in-phase (I) and quadrature (Q) signals for each data symbol
 25 interval, and means for generating from the I and Q signals a set of correlation magnitude signals approximately proportional to $(I^2 + Q^2)$, for each data symbol interval.

4. A transmission system according to claim 3, wherein the receiver further comprising means for integrating the correlation magnitude signals over a
 30 selected number of data symbol intervals, means for detecting peaks in the integrated correlation magnitude signals; and means for generating from the detected peaks sync signals indicative of the times of arrival of multipath components.



5. A transmission system according to claim 4, wherein the demodulation means includes means for deriving multiple data values from the I and Q signals obtained for each data symbol interval, the multiple data values being associated with the times of arrival of multipath components, and the means for
 5 combining the usable baseband data components in proportion to their relative signal strengths includes means for accumulating selected ones of the multiple data values, under control of the generated sync signals, whereby the multiple selected data values are accumulated only if they correspond in time to significant correlation measurements.

10 6. A transmission system according to claim 3, wherein the means for generating sets of correlation magnitude signals approximately proportional to $(I^2 + Q^2)$ includes means for determining the magnitudes of the I and Q signals, without regard to sign, and means for adding the magnitudes of the I and Q signals.

7. A receiver for receiving a pseudo-noise modulated signal from the
 15 channel, said receiver comprising correlation means, for correlating digitized samples of the received signals with locally generated PN code sequences, wherein said receiver comprises means to obtain correlation measurements over a plurality of consecutive time bins, demodulation means for demodulating the received signals to obtain potential baseband data relating to all of the time bins, and signal
 20 combining means, for combining usable baseband data components in proportion to their relative signal strengths.

8. A receiver according to claim 7, wherein the data symbols to be derived from the received signals may change state at a data symbol rate, and each received symbol persists for a data symbol interval, the correlation means being
 25 arranged for operating on successive segments of the received signal, wherein there are an integral number of segments in each data symbol interval, and the correlation means includes means for correlating successive segments of the locally generated PN code with successive moving segments of the received signal, to obtain multiple sets of correlation measurements over multiple time bins relating to
 30 the signal segment, and means for integrating the successive sets of correlation measurements over all of the segments in each data symbol interval.

9. A receiver according to claim 8, wherein the correlation means further comprises means for generating from the correlation measurements a set of in-phase (I) and quadrature (Q) signals for each data symbol interval, and means for
 35 generating from the I and Q signals a set of correlation magnitude signals approximately proportional to $(I^2 + Q^2)$, for each data symbol interval.



10. A receiver according to claim 9, wherein the receiver further comprising means for integrating the correlation magnitude signals over a selected number of data symbol intervals, means for detecting peaks in the integrated correlation magnitude signals; and means for generating from the detected peaks
5 sync signals indicative of the times of arrival of multipath components.

11. A receiver substantially as described herein with reference to Figures 2 to 6 of the accompanying drawings.

DATED this Twenty-sixth Day of July 1996
Magnavox Electronic Systems Company

10




Patent Attorneys for the Applicant
SPRUSON & FERGUSON

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195

ABSTRACT

"Spread spectrum communication system"

A pseudo-noise (PN) correlation and demodulation method and apparatus, in which received signals are correlated with locally generated PN codes and correlation measurements are maintained for multiple time bins corresponding to signals received over possible multiple paths. Instead of selecting one or a small number of significant correlation measurements to control data demodulation, the method of the invention performs data demodulation over the multiple time bins, and then selects data values corresponding to significant correlation measurements and combines the selected data values, weighting them in accordance with their relative strengths as determined during correlation. Use of the invention provides improved performance in terms of signal quality and continuity in the presence of multipath conditions. Careful selection of design parameters allows the improved performance to be obtained in a compact and easily portable implementation including transmitter and receiver modules.



10 11 93 51011




FIG. 4




FIG. 5




FIG. 6

4/4




FIG.7




FIG.8