



Office de la Propriété

Intellectuelle
du Canada

Un organisme
d'Industrie Canada

Canadian
Intellectual Property
Office

An agency of
Industry Canada

CA 2249276 C 2007/06/26

(11)(21) **2 249 276**

(12) **BREVET CANADIEN
CANADIAN PATENT**

(13) **C**

(22) Date de dépôt/Filing Date: 1998/10/05

(41) Mise à la disp. pub./Open to Public Insp.: 1999/04/06

(45) Date de délivrance/Issue Date: 2007/06/26

(30) Priorité/Priority: 1997/10/06 (JP9-290262)

(51) Cl.Int./Int.Cl. *C30B 29/04* (2006.01),
G01N 21/88 (2006.01), *G10K 11/36* (2006.01),
H03H 9/02 (2006.01)

(72) Inventeurs/Inventors:

FUJII, SATOSHI, JP;
SEKI, YUICHIRO, JP;
YOSHIDA, KENTARO, JP;
NAKAHATA, HIDEAKI, JP;
HIGAKI, KENJIRO, JP;
KITABAYASHI, HIROYUKI, JP;
UEMURA, TOMOKI, JP;
SHIKATA, SHIN-ICHI, JP

(73) Propriétaire/Owner:

SUMITOMO ELECTRIC INDUSTRIES, LTD., JP

(54) Titre : PLAQUETTE EN DIAMANT, METHODE D'EVALUATION D'UNE PLAQUETTE EN DIAMANT ET DISPOSITIF
DE TRAITEMENT DES ONDES ACOUSTIQUES DE SURFACE EN DIAMANT

(54) Title: DIAMOND WAFER, METHOD OF ESTIMATING A DIAMOND WAFER AND DIAMOND SURFACE ACOUSTIC
WAVE DEVICE

$R_a \leq 10 \text{ nm}$

Defect density $\leq 300/\text{cm}^2$

Carbon layer	$d \leq 10 \text{ nm}$
Diamond	$S \geq 19 \text{ cm}^2$ $P \leq 1.5 \times 10^8 \text{ Pa}$

(57) Abrégé/Abstract:

Surfaces of diamond crystals are examined by coating the surfaces with thin metal films, launching laser beams to the diamond surfaces in a slanting angle, detecting defects and particles on the diamond surfaces by the scattering of beams and counting the defects and particles by a laser scanning surface defect detection apparatus. Diamond SAW devices should be made on the diamond films or bulks with the defect density less than $300 \text{ particles cm}^{-2}$. Preferably, the diamond surfaces should have roughness less than $R_a 20 \text{ nm}$. Diamond SAW filters can be produced by depositing a piezoelectric film and making interdigital transducers on the low-defect density diamond crystals.

(74) Agent: MARKS & CLERK

ABSTRACT OF THE DISCLOSURE

Surfaces of diamond crystals are examined by coating the surfaces with thin metal films, launching laser beams to the diamond surfaces in a slanting angle, detecting defects and particles on the diamond surfaces by the scattering of beams and counting the defects and particles by a laser scanning surface defect detection apparatus. Diamond SAW devices should be made on the diamond films or bulks with the defect density less than 300 particles cm^{-2} . Preferably, the diamond surfaces should have roughness less than Ra20nm. Diamond SAW filters can be produced by depositing a piezoelectric film and making interdigital transducers on the low-defect density diamond crystals.

**DIAMOND WAFER, METHOD OF ESTIMATING A DIAMOND WAFER AND
DIAMOND SURFACE ACOUSTIC WAVE DEVICE**

This invention relates generally to a diamond wafer and a surface acoustic wave (SAW) device produced on the diamond wafer. This invention relates more specially to a 5 method of estimating diamond wafers which judges whether a diamond wafer is suitable for producing SAW devices or not. The estimation selects diamond wafers that have a low density of surface defects which enables manufacturers to produce a low loss SAW device. The diamond wafers can also be used as the substrates of microelectronic devices with microscopic wiring or the substrates of micromachines with microscopic structures.

10 Diamond enjoys the highest sound velocity among all the natural materials. The hardness is also the highest. The thermal conductivity is large. The band gap of diamond is 5.5eV which is an extremely high value among all known materials. Diamond is excellent in dynamical property, electrical property and electronic property. Diamond is used for dynamic devices and electronic devices that can take advantage of its excellent properties. 15 Improvements have been made by taking advantage of the outstanding properties of diamond in the technical fields of acoustics, optics and semiconductor. Exploitation of diamond will be effective for improving various properties of electronic, acoustic devices or for enlarging margins of operation of the devices.

20 A surface acoustic wave device (SAW device) is a good candidate for the use of diamond for improving its characteristics. Surface acoustic wave devices can be configured to be, for example, a radio frequency filter, a phase shifter, a convolver, an amplifier, etc. The SAW filter acts as an IF (intermediate frequency) filter of television sets or various filters of communication devices. A surface acoustic wave device is a device having a rigid base, a piezoelectric film stuck to the rigid base and interdigital transducers formed on both ends of

the piezoelectric film. Application of an AC voltage on the interdigital transducer causes an AC electric field on the piezoelectric film which deforms in proportion to the electric field. Since the electric field oscillates, the piezoelectric film alternatively expands and contracts in the horizontal direction between two interdigital transducers at the same frequency as the AC 5 voltage.

The piezoelectric film oscillates in the horizontal direction with the frequency of the AC signal. Since the piezoelectric film adheres to the rigid base, the rigid base also oscillates at the same frequency in the same manner. Since the rigid base repeats expansion and contraction at the interdigital transducer (IDT), the oscillation propagates as a 10 longitudinal elastic wave on the surface. The AC voltage applied on the interdigital transducer generates an elastic wave. The wavelength is determined by the period of the interdigital transducer. The elastic wave spreads from one interdigital transducer to the other interdigital transducer. The piezoelectricity is reversible. At the receiving interdigital transducer, the deformation oscillation induces an AC voltage between the components of the 15 electrode. As a whole, the AC signal propagates from one interdigital transducer to the other interdigital transducer by the elastic wave. The wave is called surface acoustic wave (SAW), because it propagates on the surface of the device.

The period of the interdigital transducer uniquely determines the wavelength λ of the surface acoustic wave. The rigidity and density of the rigid base determine the velocity v 20 of the SAW. The more rigid and lighter base brings about the higher SAW velocity. SAW velocity v is different from sound velocity which is equal to a square root of Young's modulus E divided by density ρ . As with sound velocity, the SAW velocity is higher for the rigid base of higher Young's modulus and lower density. A sound wave is an elastic wave passing through an inner portion of a material. SAW is another elastic wave propagating only on the 25 surface of the material. SAW differs from sound wave. SAW velocity is, in general, higher

than sound velocity.

Since the wavelength λ and the velocity v have been predetermined by the interdigital transducer and the physical property of the rigid base, the frequency f is also surely determined as $f = v/\lambda$. This is a unique value. Since f is a unique value, it is denoted 5 by f_0 . Namely, the SAW device has a filtering function which selectively allows only the SAW of f_0 to pass the device. SAWs of frequency different from f_0 attenuate. Transmittable SAW has a definite frequency f_0 which is determined by the material of the rigid base and the spatial period of the interdigital transducers. SAW devices have been applied to TV filters having a low allowable frequency of several megahertz to tens of 10 megahertz. Hopefully, SAW devices will be applied to far higher frequency filters, for instance, optical communication filters of 2.488GHz or wireless LAN filters in near future.

Raising frequency f_0 requires either narrowing a spatial period of interdigital transducers or increasing a SAW velocity v . The spatial period of interdigital transducers is limited by the current lithography technology. The only way is the increase of velocity v . 15 Diamond, as a rigid base, exhibits the highest SAW velocity among all natural materials. The application of diamond to SAW devices attracts attention. Diamond endows the SAW devices with the highest velocity which affords a moderately wide spatial period to the interdigital transducers.

High velocity is not the only requisite for a material used for SAW devices. Low 20 propagation loss is another important requirement for SAW materials. Loss is a key concept of the present invention. There are different losses in addition to the propagation loss. Losses are now briefly clarified. One is the Joule loss ΔE_r by the resistance of the interdigital transducers to which electric power is supplied. Another is an electromechanical conversion loss ΔE_c of energy accompanying the expansion and contraction of the 25 piezoelectric material by the AC electric field. The loss depends on the electromechanical

coefficient of the piezoelectric film. The interdigital transducer which converts electric power into mechanical power through the piezoelectric film has no selectivity of direction. The surface acoustic waves propagate in both directions perpendicular to the stripes of the interdigital transducers. Just half of the mechanical power spreads toward the counterpart 5 interdigital transducer. Another half (6dB) is a loss. This is called a bisection loss ΔE_b . Now a SAW starts from one interdigital transducer and some of the SAW arrives at the other interdigital transducer. The difference between the starting SAW power and arriving SAW power is the propagation loss ΔE_p . The aim of the present invention is a reduction of the propagation loss ΔE_p . At the other interdigital transducer, the piezoelectric film converts 10 the mechanical power of SAW into electric power of AC voltage with a conversion loss ΔE_c . The current flows in the receiving interdigital transducer with a resistance loss ΔE_r .

Total loss is a sum, $2\Delta E_r + 2\Delta E_c + \Delta E_b + \Delta E_p$, of the resistance loss $2\Delta E_r$, the conversion loss $2\Delta E_c$, the bisection loss ΔE_b and the propagation loss ΔE_p . ΔE_r is contingent upon interdigital transducers. ΔE_c is ruled by the piezoelectric material. 15 Geometry decides ΔE_b . Only the propagation loss ΔE_p depends upon the insulating material (rigid base). This invention aims at alleviating ΔE_p .

The insulator which has been most widely used as the material of the rigid base is glass. Glass is an inexpensive and low-loss insulator. ZnO/glass SAW filters have been popularly employed as TV intermediate frequency filters. Zinc oxide (ZnO) is a 20 piezoelectric material. ZnO/glass means a SAW filter having a glass substrate and a ZnO film deposited on the glass. In spite of low-loss and low-cost, glass SAW devices cannot raise operation frequency f_0 owing to the low SAW velocity v . Somebody has proposed new SAW devices having a harder rigid base than glass, for example, sapphire, quartz, LiNbO_3 and so on. These new materials give higher SAW velocity than glass owing to high Young's 25 modulus. However, the SAW velocities of sapphire SAW devices, quartz SAW devices or

LiNbO_3 SAW devices are still unsatisfactory for high frequency filters. Diamond is the most promising candidate which gives the highest SAW velocity due to the extreme rigidity.

Diamond SAW devices enable the current lithography technology to pattern interdigital transducers for a frequency higher than 1GHz owing to the high SAW velocity v.

5 However, the propagation loss ΔE_p is still large in diamond SAW devices. The large propagation loss ΔE_p leaves diamond SAW devices impractical. It is difficult to make a wide, flat, even, smooth and defect-free diamond film covering the whole of the device due to the extreme rigidity of diamond. It is further difficult to make a flat piezoelectric film on the defect-rich diamond film. Even if the piezoelectric film is produced, it is still a piezoelectric

10 film of poor quality. Many defects on the diamond surface and the shortness of the SAW wavelength raise the propagation loss ΔE_p and leave diamond SAW devices inoperative.

Since the frequency f is very high, the wavelength $\lambda = v/f$ is reduced to a similar size to the micro-cavities and micro-convexities. Acoustic phonons building the surface acoustics wave are scattered by the micro-defects, because phonons are mostly perturbed by

15 the objects of the same size as the wavelength. Besides the high propagation loss ΔE_p , the defects-rich diamond film decreases the yield of SAW devices by raising the rate of electrode-pattern cutting. Micro-defects prevent diamond SAW devices from growing to practical SAW devices through the large propagation loss ΔE_p and the low yield. Here "yield" means a ratio of the number of good products to the number of all products.

20 One purpose of the present invention is to produce diamond SAW devices having low propagation loss. Another purpose of the present invention is to enhance the yield of the diamond SAW devices. In addition to SAW devices, this invention can be applied to raising the yield of the production of microelectronic devices or micromachines making use of small wire patterns with a breadth less than $5.0 \mu \text{m}$ through reducing the rate of the wiring pattern

25 cutting.

Higher frequency requires SAW filters to make a still better piezoelectric film. The undercoating diamond film must be flat, smooth and defect-free for producing (Diamond)/(piezoelectric material) SAW devices. For this purpose, a simple and reliable estimation technique of diamond films is indispensable besides fabrication of good diamond

5 films. This invention proposes also a method for easily estimating diamond films.

Diamond films have been examined by observing micro-defects, micro-concavities or micro-convexities by scanning electron microscopes or atomic force microscopes.

① R. Gahlin, A. Alahelisten, S. Jacobson, "The effects of compressive stresses on the abrasion of diamond coatings", Wear 196 (1996) 226-233

10 ② S. K. Choi, D. Y. Jung, S.Y. Kweon, S. K. Jung, "Surface characterization of diamond films polished by thermomechanical polishing method", Thin Solid Films 279 (1996) 110-114

Microscope estimation is a straight and reliable method, since diamond surface is directly observed by a microscope. However, the field of vision is too narrow. The observation field is, e.g., about $10 \mu m \times 10 \mu m$ for a scanning electron microscope. In

15 general, a SAW device has a size of about $100 \mu m \times 100 \mu m$ to $20000 \mu m \times 20000 \mu m$. The area of a SAW device is far broader than the field of vision of microscopes. It would take very much time to observe the whole surface of a SAW device by microscopes. Microscope observation cannot be applied to the examination of diamond surfaces in the process of producing diamond SAW devices.

20 Namely, there is no estimation method available for examining diamond surface on an industrial scale.

Producing diamond SAW devices requires a comprehensive estimation method of examining the entire diamond surface at a stretch. If the diamond film can be easily examined, one can judge whether a piezoelectric film should be deposited on it or not. If the

25 diamond film is bad, the sample should be abandoned without coating it with a piezoelectric

film. Another purpose of the present invention is to propose a method of estimating physical properties (roughness, defects) of a diamond film.

The Inventors of the present invention tried to utilize a laser scanning surface defect detection apparatus for silicon wafers to examine diamond films of SAW devices. Diamond 5 is different from silicon in many physical properties. A laser scanning surface defect detection apparatus for silicon wafers cannot be readily used for estimating a diamond. Indeed, a laser scanning surface defect detection apparatus has never been used to examine diamond films. Fig. 4 shows a schematic view of the laser scanning surface defect detection apparatus.

10 The apparatus has an integral sphere, a laser, a lens and a photomultiplier. The inner wall of the integral sphere is a mirror. The integral sphere has an opening at the bottom. The semiconductor laser (L) is mounted at a niche on a side of the integral sphere for emitting an inspecting light beam slantingly down. The semiconductor laser can be replaced by a gas laser, e.g. a He-Ne laser. The integral sphere has an outlet (U) on the other 15 side for taking out a reflected beam. The inspection comprises the steps of mounting an object wafer on a stage, bringing the bottom opening of the integral sphere close to the wafer (KTW), irradiating a point (T) on the surface of the wafer by the laser beam (LT), and measuring the power of the reflected light (S). The incident beam angle is equal to the reflection angle. The laser (L) and the outlet (U) are determined to be symmetric in the 20 integral sphere. Then, $\angle LTK = \angle UTW$. If the surface is flat, all the reflected beams go out through the side opening (U). The photomultiplier detects no light. When a defect or a piece of dust lies on the object point (T), a portion of the laser beams is scattered by the defect or dust. The scattering beams impinge upon other parts of the wall of the integral sphere. The photomultiplier senses the scattered beams. Fig. 13 shows a bit of dust lying on the 25 surface of the wafer. Parallel laser beams are randomly reflected by the dust in the directions

E, F, G, etc. Reflected beams do not exit through the outlet (U) but impinge upon the inner wall of the integrated sphere and are reflected to the photomultiplier. The photomultiplier measures the scattering light with high sensitivity. The photomultiplier detects the existence of a dust at the sampling point (T) by an increase of its photocurrent. The bigger the dust is,
5 the stronger the scattering light becomes. The reflected light power is in proportion to the size of the dust. It is easy to understand the scattering of light by dust. However, the photomultiplier can also detect geometrical surface defects. Fig.14 shows a notch, a surface defect, on the surface of the silicon wafer. Silicon has a high refractive index ($n=3.5$) and high absorption for the visible light emitted from the laser. The complex refractive index
10 $n+jk$ of silicon has a large real part n and a large imaginary part k for the visible light. Laser light is strongly reflected at the interface between air and silicon. The notch (M) scatters the beam in other directions (MH) than that of the outlet (U). The scattered beams are again reflected by the inner wall of the integral sphere and arrive at the photomultiplier for generating a photocurrent. The existence of dust or a defect on the object point of the silicon
15 wafer can easily be detected by the random scattering of light beams.

Since a Si wafer is a wide disc, defects and dust of all the portions are inspected by moving the stage in the two-dimensional XY-plane with regard to the integral sphere. There are two modes of movement of the stage. One is an assembly of rotation and parallel displacement of the shaft. The sampling point (T) moves in a spiral. This mode is called a
20 spiral mode. The other is an assembly of x-direction displacement and y-direction displacement of the wafer. This is called a scanning mode. The overall movement enables the apparatus to detect dust or defects on the whole surface of the silicon wafer.

In the silicon semiconductor industry it is well known to use a laser scanning surface defect detection apparatus. It takes only a short time to examine a pretty wide silicon wafer
25 by the laser scanning surface defect detection apparatus. Unlike observation by a

microscope, the apparatus can measure the number or the density of defects or dust quantitatively over a wide range. However, the laser scanning surface defect detection apparatus cannot be readily used to examine the surface of diamond.

Diamond is transparent for the visible light emitted by the laser unlike silicon.

5 Namely, the complex refractive index $n+jk$ has a vanishing imaginary part $k=0$. The real part $n=2.4$ is also lower than the real part of silicon. The reflection rate is $r=(n-1)/(n+1)$ for the vertical incidence. Since n is small, the reflection rate is also small. Transparency allows the visible light to penetrate into the diamond crystal. Any notch (M) on diamond cannot reflect the laser light in Fig.3(a). A visible light beam passes a diamond bulk crystal
10 without loss along a light path LMP in Fig.3(a). If a diamond film is formed on an opaque substrate of a foreign material, the light passes the transparent diamond and arrives at the interface between the diamond film and the substrate. The beam is reflected by the foreign material substrate along the light path LNQ in Fig.3(a). Since diamond is transparent, the reflection occurs not on the diamond surface but on the interface between the diamond film
15 and the substrate. For this reason, the laser scanning surface defect detection apparatus cannot be applied to the examination of the surface of diamond. The Inventors thought that the laser scanning surface defect detection apparatus is a promising candidate for an inspection apparatus for diamond despite the difficulty of transparency.

One purpose of the present invention is to provide an improvement of the laser
20 scanning surface defect detection apparatus so that it would be suitable for examining surface defects of diamond. Another purpose of the present invention is to provide a diamond substrate which is suitable for use as the substrate of SAW devices by examining surface defects by the laser scanning surface defect detection apparatus. The further purpose of the present invention is to provide a method of selecting diamond substrates suitable to form a
25 piezoelectric film thereupon.

This invention coats a diamond film or substrate with a thin metal or non-metal film having a high reflection rate for the laser light. The thin film enables the laser scanning surface defect detection apparatus to detect defects or dust on a surface of the diamond, since the thin film reflects the laser light. The thin film should be made from a metal or non-metal

5 having a reflectance greater than 50%. The thickness of the coating film is less than 100nm. The surface of the coating has the same convexities and concavities as the surface of the diamond, since the coating film is thin enough. The coating layer transcribes the diamond surface. If the diamond has a surface defect (M), the coating layer has a similar surface defect (K), as shown in Fig.3(b). Most of the beams are reflected at the coating layer. The

10 rest penetrating into the coating layer is also reflected at the interface between the coating layer and the diamond. The material of the coating layer is, e.g., aluminum (Al), gold (Au), silver (Ag), copper (Cu), nickel (Ni) or so. Thin film of the metal has a sufficient reflection rate to the laser light. If the diamond has defects or dust, the coating layer has similar anomalies due to the defects or dust at the same spots. The formal anomalies reflect the

15 laser beams at random. Then the laser beams are scattered indirectly by the defects or dust on the diamond. The coating layer enables a conventional laser scanning surface defect detection apparatus to detect defects or dust on an object diamond. Thus, the laser scanning surface defect detection apparatus can now be used for the estimation of diamond surfaces.

Fig.2 shows a diamond crystal covered by a metal coating layer. The coated

20 diamond is examined with regard to defects or dust by the laser scanning surface defect detection apparatus. If dust lies on the surface, the dust itself scatters the laser light. The scattered light arrives at the photomultiplier. The existence of the dust can be surely detected by the apparatus. However, defect detection is a problem. As shown in Fig.3(b), the metal coating layer has the same geometric anomaly as the defect, because the metal layer

25 is thin enough. Most of the laser light is reflected at K point. The scattering beam goes

along KR. A part of the rest is reflected at M point. The scattered beams KR and MI are again reflected at some portions of the integral sphere and reach the photomultiplier. Thus, the existence of the defect is also detected by the apparatus. Therefore, the laser scanning surface defect detection apparatus which is inherently directed to examining Si wafers can 5 now be diverted to the examination of defects and dust on diamond surfaces by coating the object diamond with a thin opaque layer.

Diamond films are now examined by the laser scanning surface defect detection apparatus. The Inventors discovered that the critical density is 300 particles/cm² of the surface defect for diamond films by the examinations. Diamond films which have more than 10 300 particles/cm² defects shall be rejected for the substrate of SAW devices. The diamond films with defect density less than 300 particles/cm² shall be adopted as a substrate for SAW devices. The most important factor is the surface defect density for estimating diamond films as the substrate of SAW devices.

The surface roughness Ra of diamond films has an influence upon the quality of the 15 SAW devices in addition to surface defects. The surface should have a surface roughness lower than Ra 20 nm. In particular, less than Ra 10nm is preferable for the substrates of SAW devices. The roughness is the second criterion for estimating the quality of diamond films.

Another factor is the size of a diamond-coating wafer. Raising productivity requires 20 a wafer size of more than 2 inches of diameter. Namely, the surface area should be wider than 19cm² in the case of a circular wafer.

Inner stress is a further factor for defining a desirable diamond-coated wafer. If a wafer has a big inner stress, the mother materials, silicon or a metal, will be distorted. Distortion of the mother substrate deforms or bends the diamond film either in a convex or in 25 a concave. The deformation of the diamond film reflects the laser light unevenly. A slight

slanting of the wafer forbids the reflected light from going out through the outlet U and forces a part of the reflected light into the photomultiplier. Thus, inner stress should be weaker than 1.5×10^8 Pa (150MPa=1500bar). Besides, the distortion which is defined as the height of the center from the surface containing the periphery should be smaller than $\pm 40 \mu m$.

5 Of course, a pure diamond film is most suitable. But a diamond coated with a thin carbon is also allowable, since the diamond is directed for a substrate of SAW devices. In this case, the carbon overcoat layer should be less than 10nm in thickness. Fig.1 shows the following requirements for the diamond film for SAW devices in the present invention.

- (1) defect density $\leq 300/cm^2$
- 10 (2) surface roughness $\leq Ra10nm$
- (3) area $\geq 19 cm^2$
- (4) inner stress $\leq 150MPa$
- (5) carbon overcoating $\leq 10nm$.

Instead of a film, a freestanding, homogeneous diamond substrate without foreign 15 material substrate is also available. In the full diamond substrate, the thickness of the diamond crystal should be $100 \mu m$ to $2000 \mu m$. The complete diamond substrate makes excellent SAW devices.

Complex substrates having a foreign material, e.g. silicon, substrate and a diamond 20 film coating the substrate are, in general, made use for the substrate of SAW devices. The mother foreign material should have a thickness between $0 \mu m$ and $2000 \mu m$. At the limit of $0 \mu m$, the case coincides with the former full homogenous diamond substrate. The thickness of the diamond film should be more than $1 \mu m$. The mother substrate and the diamond film should have a roughness less than $Ra20nm$. In particular, the surface roughness of the diamond film preferably is less than $Ra10nm$.

25 (6) in the case of a homogeneous full diamond substrate, the thickness should be $100 \mu m$ to

2000 μ m.

(7) in the case of a diamond/mother complex substrate, the mother substrate thickness should be 0 μ m to 2000 μ m.

(8) in the case of a diamond/mother complex substrate, the diamond film thickness should be
5 more than 1 μ m.

(9) the surface roughness of the diamond film or substrate should be less than Ra20nm.

Although many proposals have been discussed and proved that diamond SAW devices would be superior in the SAW velocity to other materials, diamond SAW devices are suffering from extremely low yield due to the large propagation loss of the SAW devices
10 having piezoelectric films upon diamonds. The low yield resulted from the lack of the method of a preliminary examination of diamond crystals. Since the property of diamond films could not be measured, SAW devices made on the property-unknown diamond crystals were tested, which lowered the yield and raised the production cost. This invention provides an estimation method which can examine diamond films or bulks at a preparatory step of
15 making diamond SAW devices. This invention makes the best use of the laser scanning surface defect detection apparatus which prevails in silicon semiconductor industries. The laser scanning surface defect detection apparatus cannot be employed for examining diamond surfaces as it is. Preparatory coating of thin films of a metal or another opaque material enables the laser scanning surface defect detection apparatus to examine the defects of
20 diamond surfaces. The examination reveals the density of defects and dust on diamond films or bulks for determining whether piezoelectric films and electrodes should be made upon the diamond samples at a preliminary step. Diamond crystals having defect & dust density of more than 300 particles cm^{-2} cannot form good piezoelectric films and good interdigital transducers thereupon. Higher defect density than 300 particles cm^{-2} lowers the yield by
25 inviting electrode breaking or other default. Diamond surfaces of a defect density lower than

300 particles cm^{-2} pass the examination. The passed diamond enables manufacturers to produce low loss SAW filters available for high frequency by depositing piezoelectric films and making interdigital transducers on the diamond surfaces.

According to an aspect of the present invention there is provided a diamond wafer

5 comprising a diamond single crystal or polycrystal substrate synthesized by an ultrahigh pressure synthesis method or a vapor phase deposition method or a diamond substrate consisting of a diamond board or another material board and a single crystal or polycrystal diamond film synthesized upon the diamond board or another material board, characterized by surface defect density of less than 300 particles cm^{-2} which is measured by coating the

10 diamond surface with a thin opaque film, launching laser beams to the coated diamond surface from a laser scanning surface defect detection apparatus for letting the laser beams reflect at a surface of the coating film and an interface between the coating film and the diamond surface, and counting the beams scattered by surface defects or particles on the diamond surface. Additionally, the diamond wafer can have a distortion height of less than $\pm 40 \mu \text{m}$ at a center

15 for a reduced diameter to 50mm.

According to another aspect of the present invention there is provided a diamond wafer comprising a diamond single crystal or polycrystal substrate synthesized by an ultrahigh pressure synthesis method or a vapor phase deposition method or a diamond substrate consisting of a diamond board or another material board and a single crystal or polycrystal

20 diamond film synthesized upon the diamond board or another material board, and a piezoelectric film deposited upon the diamond substrate or the diamond film, characterized by surface defect density of less than 300 particles cm^{-2} which is measured by coating the piezoelectric film surface with a thin opaque film, launching laser beams to the coated piezoelectric film surface from a laser scanning surface defect detection apparatus for letting

25 the laser beams reflect at a surface of the coating film and an interface between the coating

film and the piezoelectric film surface, and counting the beams scattered by surface defects or particles on the diamond surface.

According to a further aspect of the present invention there is provided a diamond surface acoustic wave device comprising a diamond single crystal or polycrystal substrate being synthesized by an ultrahigh pressure synthesis method or a vapor phase deposition method and having surface defect density of less than 300 particles cm^{-2} or a diamond substrate consisting of a diamond board or another material board and a single crystal or polycrystal diamond film being synthesized upon the diamond board or another material board and having surface defect density of less than 300 particles cm^{-2} , the defect density being defined by $d \geq W/2$ and $h \geq 10\text{nm}$, where d is a diameter of a defect, W is the minimum width of electrodes and h is a depth or a height of the defect, a piezoelectric film deposited on the diamond substrate, and interdigital transducers produced on the piezoelectric film, wherein the defect density is measured by coating the diamond surface with a thin opaque film, launching laser beams to the coated diamond surface from a laser scanning surface defect detection apparatus for letting the laser beams reflect at a surface of the coating film and an interface between the coating film and the diamond surface, and counting the beams scattered by surface defects or particles on the diamond surface.

According to a further aspect of the present invention there is provided a diamond surface acoustic wave device comprising a diamond single crystal or polycrystal substrate being synthesized by an ultrahigh pressure synthesis method or a vapor phase deposition method and having surface defect density of less than 300 particles cm^{-2} or a diamond substrate consisting of a diamond board or another material board and a single crystal or polycrystal diamond film being synthesized upon the diamond board or another material board and having surface defect density of less than 300 particles cm^{-2} , the defect density being defined by $d \geq W/2$ and $h \geq 10\text{ nm}$, where d is a diameter of a defect, W is the minimum width

of electrodes and h is a depth or a height of the defect, interdigital transducers produced on the diamond substrate, and a piezoelectric film deposited on the interdigital transducers and on the diamond substrate, wherein the defect density is measured by coating the diamond surface with a thin opaque film, launching laser beams to the coated diamond surface from a laser scanning surface defect detection apparatus for letting the laser beams reflect at a surface of the coating film and an interface between the coating film and the diamond surface, and counting the beams scattered by surface defects or particles on the diamond surface.

5 In the accompanying drawings:

10 Fig.1 is a schematic front view of a diamond crystal having the conditions suitable for a substrate of SAW devices.

Fig.2 is a section of a sample of a diamond crystal coated with a metal film available for an examination by a laser scanning surface defect detection apparatus.

Fig.3(a) is a view of a defect on a diamond surface without coating, where a laser beam penetrates a transparent diamond crystal.

15 Fig.3(b) is a view of a defect on a diamond surface coated with a metal film, where a laser beam can detect the defect by being reflected at the metal surface.

Fig.4 is a sectional view of a laser scanning surface defect detection apparatus which has been used for examining surfaces of silicon wafers.

Fig.5 is a sectional view of a Si substrate and a diamond film deposited on the Si substrate by a microwave plasma CVD (chemical vapor deposition) method.

20 Fig.6 is a sectional view of a Si substrate and a diamond film polished by a diamond electrodeposited whetstone.

Fig.7 is a sectional view of a sample having a piezoelectric ZnO film deposited on the diamond/Si substrate.

Fig.8 is a sectional view of a sample having an aluminum film coating on the ZnO/diamond/Si substrate.

Fig.9 is a sectional view of a sample having interdigital transducers made by selective etching of the aluminum film by lithography.

5 Fig.10 is a graph of the frequency dependence of S12 of an embodiment SAW filter

of the present invention. The abscissa is the frequency (MHz) and the ordinate is the electric power ratio (dB).

Fig.11 is a graph of the frequency dependence of S11 of the same SAW filter. The abscissa is the frequency (MHz) and the ordinate is the electric power ratio (dB).

5 Fig.12 is a graph of the frequency dependence of S22 of the same SAW filter. The abscissa is the frequency (MHz) and the ordinate is the electric power ratio (dB).

Fig.13 is a section of a particle of dust lying on the diamond surface which scatters laser beams in random directions.

Fig.14 is a section of a defect which scatters a laser beam.

10 Fig.15 is a plan view of a part of an example of an interdigital transducer.

Diamond can be synthesized by two methods. One way produces a diamond bulk crystal from carbon at a high temperature under ultrahigh pressure. This bulk-production method is called an ultrahigh pressure synthesis. The other way produces a diamond thin film on a mother substrate by supplying hydrogen gas, hydrocarbon gas to the mother 15 substrate, exciting the gas by heat, light or microwave, inducing a chemical reaction of the gas and depositing the reaction product on the mother substrate at a high temperature under reduced pressure. This film-production method is called a vapor phase synthesis. Both methods can produce both diamond single crystals and diamond polycrystals. This invention can be applied both to single crystals and polycrystals of diamond.

20 However, the ultrahigh pressure method can make only a small-sized diamond crystal. A big diamond wafer of an area wider than 19cm² (2 inches in diameter) can be produced only by the vapor phase synthesis. In any cases, synthesized diamond crystals have some surface roughness which forbids making a uniform piezoelectric film on the diamond. Then, the diamond film should be polished mechanically or chemically.

25 This invention makes a diamond crystal shown in Fig.2 by synthesizing a diamond

crystal from materials by the methods, polishing the synthesized diamond crystal and coating the polished diamond with a thin metal film of a thickness less than 100nm. The diamond crystal is then examined by the laser scanning defect detection apparatus shown in Fig.4. The metal thin film reflects the laser beams at point (T) to the outlet (U), if no defect exists at 5 point (T). Hereafter the word "defects" broadly include intrinsic, crystallographical defects, hillocks , protrusions, concavities and dust particles on a crystal surface in the description. Geometric defects of the diamond are transcribed to the metal surface as shown in Fig.3(b). If a defect (a dust particle or an intrinsic defect) lies on the interface between the metal and the diamond, the laser beams are scattered to some spots of the integration sphere and are 10 reflected again to the photomultiplier. The photomultiplier senses the defects (dust particles or inherent defects) at point (T) by an increase of the photocurrent. Scanning the integration sphere on the wafer reveals the two-dimensional distribution of the defects including inherent defects and particles. 300 particles /cm² is the critical value for defect density. Diamond wafers having a defect density of more than 300 particles /cm² should be rejected. Diamond 15 wafers of a defect density less than 300 particles /cm² pass the examination. A diamond substrate with a thin carbon coating of less than 10nm is permitted for a diamond substrate for producing SAW devices. Preferable roughness of the coating carbon is less than Ra10nm. But less than Ra 20nm is allowable for the surface roughness of the carbon coating.

Preferably the diamond film should be wider than 2 inches in diameter (19cm²) for 20 the standpoint of the economy of wafer processes. However, SAW devices can be fabricated on a diamond wafer less than 19 cm² as long as the wafer satisfies the other requirements.

The method of fabricating a SAW device is explained by referring to Fig.5 to Fig.9. A homogenous diamond bulk crystal made by the ultrahigh pressure synthesis can be a starting substrate. However, this example adopts a diamond/mother complex substrate made 25 by the vapor phase synthesis method. This example shows a substrate consisting of a silicon

(Si) mother wafer and a diamond film deposited on the silicon wafer by the microwave plasma CVD method. Si single crystal wafer is the most popular mother board. Of course, the Si wafer in Fig. 5 can be replaced by a wafer of molybdenum (Mo), nickel (Ni), aluminum nitride (AlN), alumina (Al_2O_3), gallium arsenide (GaAs) or so. A wafer having a diameter 5 more than two inches (19cm^2) is desirable from the viewpoint of production efficiency.

The synthesized diamond film has a rugged surface having plenty of concavities and convexities. Then, the diamond surface is whetted by a diamond-electrodeposited whetstone which is produced by electrodepositing diamond powder on a turn-table. Fig.6 shows a dia/Si complex wafer polished and flattened by the diamond-electrodeposited 10 whetstone. The surface roughness should be less than Ra20nm. Preferably the surface should be further flattened to a smoothness less than Ra10nm. The flattened (dia/Si) wafer is now temporarily coated by evaporation with a thin metal, e.g., aluminum film as shown in Fig.2 or Fig.3(b) and examined by the laser scanning surface defect detection apparatus of Fig.4 for searching the defect density. The test clarifies the surface roughness ($\leq\text{Ra20nm}$), 15 the defect density ($\leq 300 \text{ particles cm}^{-2}$) and the carbon coating thickness ($\leq 10\text{nm}$) of the object dia/Si wafers. Wafers failing the test should be rejected.

Dia/Si wafers which passed the test are employed as substrates of SAW devices. The metal thin film is removed from the wafer. A piezoelectric film is deposited upon the wafer, for example, by sputtering. Fig.7 shows a zinc oxide (ZnO) film for the piezoelectric 20 film. Other piezoelectric materials, e.g., PZT, LiNbO_3 and LiTaO_3 are also available. A metal film, e.g., Al film is further formed on the piezoelectric film by sputtering or evaporation. Fig.8 shows the Al/ZnO/dia/Si wafer. Photolithography produces interdigital transducers on both sides on a SAW chip by masking the metal film with a resist and etching 25 of the metal by an etchant. Fig.9 shows the interdigital transducers formed on the wafer by photolithography. There are various types of interdigital transducers. Fig.15 denotes an

example of an interdigital transducer which consists of two branches having two reciprocally facing parallel stripes in a wavelength λ .

[EMBODIMENT 1: defect density and electrode breaking rate]

A SAW device is fabricated by a series of steps of growing a diamond film on a 5 mother material substrate, polishing the diamond film, depositing a piezoelectric film, evaporating a metal film on the piezoelectric film and etching the metal film through a mask. However, the estimation of the diamond should be finished before the formation of the piezoelectric film. Thus the electrode breaking rate should be measured by forming interdigital transducers directly on the diamond film without depositing the piezoelectric film 10 and counting the spots of breaking electrode patterns. If the diamond has a poor quality, the interdigital transducers would break at many spots. The factor affecting the electrode breaking rate has been sought by forming an interdigital transducer directly upon the diamond, measuring the defect density and considering the correlation between the breaking rate and the diamond film.

15 1. Growth of diamond films

A $35 \mu\text{m}$ thick diamond film is grown on the silicon wafer of a 1mm thickness by supplying hydrogen gas containing methane gas of 2 vol% and exciting the mixture gas by the microwave plasma CVD method. 100 samples are produced by growing 100 diamond films on 100 Si wafers along the same way. The surface roughnesses of the as-grown diamond 20 wafers are, in general, more than $\text{Ra}1 \mu\text{m}$.

(Condition of growing diamond films)

Substrate	silicon wafers: thickness 1 mm
Microwave power	150 W
Material gas	methane + hydrogen $\text{CH}_4:\text{H}_2 = 2:100$
	flux 50 sccm

Gas pressure	40 mTorr
Temperature(substrate temperature)	800°C
Thickness	35 μ m

The microwave CVD made dia/Si complex wafers as shown in Fig.5. The 100 samples were polished by a polishing machine having a diamond whetstone. The polishing brought about even dia/Si wafers having good smoothness of less than Ra2nm and few defects of less than 50 particles cm^{-2} defects which were bigger than 0.5 μ m in diameter as shown in Fig.6. The average thickness of the diamond films was 20 μ m. The X-ray diffraction pattern was examined by the X-ray diffraction apparatus. The diffraction pattern revealed an existence of a carbon layer on the diamond film. The thickness of the carbon layer was less than 10nm.

2. Deposition of a piezoelectric film

Preliminarily 30nm thick aluminum (Al) films were deposited upon the diamond films of the dia/Si samples by the DC sputtering method. The aluminum film coating enables the laser scanning surface defect detection apparatus to examine the surface defects on the diamonds.

(Condition for deposition of aluminum films)

Aluminum film thickness	30 nm
DC sputtering power	1.0 kW
Reaction gas	argon gas 50 sccm
Gas pressure	1.0 Pa (7.6mTorr)
Substrate temperature	room temperature

Since the Al films cover the dia/Si samples, the laser scanning surface defect detection apparatus can detect defects or dust on the diamond films. This apparatus shoots slantly the Al-coating diamond film with laser beams, and measures the power of the light

scattered from the defects or dust by the photomultiplier(or photomulti-tube). A defect is an inherent anomaly but dust is a foreign material lying on the diamond. If the diamond is smooth and flat with little defects, the scattering light power is weak. If the diamond is rugged with many defects, the scattered light power is strong. The defect density at the 5 object point is known by the photocurrent. As shown in Fig.4, since the wafer is moved in parallel or in spiral, the existence of defects or dust is examined at all points on the wafer. In the measurement, the bias voltage of the photomultiplier is 550V.

The relation between the size of defect and the scattered light power is preliminarily determined by the steps of coating a wafer with standard Latex granules of a definite diameter, 10 measuring the power of the light scattered at the granule, replacing the Latex granules with Latex granules of another diameter, measuring the power scattered by the Latex granule again and searching the relation between the granule sizes of Latex and the photocurrent.

Here, the purpose is to form interdigital transducers (IDTs) of a $1 \mu m$ line width. The Inventors think that defects with a small size less than half of the width have little 15 influence on the electrode formation. But defects with a large size more than half of the width decrease the yield of IDTs. The Inventors considered that the critical size (d) of defects should be determined as a half (W/2) of the width (W) of interdigital transducers. For the formation of the electrodes of a $1 \mu m$ width, it is important to know the number of the defects larger than $0.5 \mu m$. However without microscope observation, the sizes of 20 individual defects cannot be measured. Thus the defect was identified by employing Latex standard granules of a $0.5 \mu m$ diameter. A threshold photocurrent was determined as the current induced by a standard granule of a $0.5 \mu m$ diameter. A $0.5 \mu m$ diameter defect will cause the same increase of the scattering light power as the $0.5 \mu m$ Latex standard granule. The scattered light power is calibrated by Latex standard granules, since the size of the 25 standard granules is uniformly determined. Thus the apparatus can sense surface defects

which are larger than $0.5 \mu m$ in diameter.

Besides the diameter $d(\geq W/2)$, the depth or height (h) of a defect is another factor affecting the electrode breaking rate. Here, the critical depth (or height) is determined to be 10nm for a $1 \mu m$ width electrode. The defects which satisfy $d \geq W/2$ and $h \geq 10nm$ should 5 be detected and measured.

Ten samples were prepared by forming diamond films on ten silicon wafers by a similar method. Ten samples are symbolized by A, B, C, ..., J. Ten samples were examined with regard to the surface roughness and the defect/dust number. Table 1 shows the surface roughnesses (R_a) and defect numbers of ten samples. The aluminum films were removed, 10 when the defect measurement has once been done. The diamond surfaces appeared.

Interdigital transducers were made on the diamond layer of the dia/Si wafers. The electrode pattern breaking rates were measured. The former thin Al films aimed at measurement of defects. The present Al coating is directed to making electrodes. Both steps were, by chance, aluminum coating. But the purposes were different. The formerly 15 coated aluminum was eliminated. A plurality of interdigital transducers were made by evaporating or sputtering aluminum on the (dia/Si) wafers, making a mask pattern by photolithography, and etching the aluminum layer. A plurality of pairs of interdigital transducers were produced on each wafer. The devices were examined by supplying currents for searching the electrode breaking. The breaking rate was calculated by dividing 20 the number of the electrode-breaking devices by the total number of devices. The electrode breaking rate is also shown in Table 1. The breaking rate is given by an experimental equation which is called "Murphy's plot". Murphy's plot is expressed by $C \exp(-DA)$, where C is a constant, D is the defect density and A is the area of IDT patterns. This equation means that if the area for interdigital transducers is wider, the defect density should 25 be smaller for keeping the same yield.

It is a general agreement that if the defect size (W) is larger than a half of the minimum pattern width (d), the yield of the IDTs will decrease. For making electrodes having a width of $1 \mu \text{m}$, the defects larger than $0.5 \mu \text{m}$ tend to plague the formation of electrodes. Here the "defects" include dust particles and inherent defects. Table 1, the third 5 column, shows the result of measurement of the number of defects larger than $0.5 \mu \text{m}$ for (diamond wafer) samples A to I. Meandering patterns with 400 electrode stripes of a $1 \mu \text{m}$ length \times $500 \mu \text{m}$ width were formed in a spatial period of $1000 \mu \text{m} \times 500 \mu \text{m}$ on two inch diameter diamond wafers. The line width (length) of an individual stripe is $1 \mu \text{m}$. The distance between neighboring stripes was $1 \mu \text{m}$. Thus, 400 stripes have a width of about 10 $800 \mu \text{m}$. The total area of a wafer is about $19 \text{cm}^2 = 1900 \text{mm}^2$. One spatial period is $1000 \mu \text{m} \times 500 \mu \text{m} = 0.5 \text{mm}^2$. About 3800 sets of 400 electrode stripes were made on each diamond wafer. Then the electrodes were examined by supplying currents. Some electrodes turned out to be broken due to the roughness of the diamond film. The number of breaking 15 electrodes was counted for every diamond wafer sample. The breaking rates were also listed in Table 1.

TABLE 1. Roughness Ra(nm), Defect density and Breaking rate of aluminum electrodes of samples A to J of (dia/Si)-substrates

SAMPLE NO.	ROUGHNESS Ra (nm)	DEFECTS DENSITY (particles cm^{-2})	BREAKING RATE OF Al ELECTRODES(%)
A	7.2	80	0 %
B	8.2	287	0 %
C	7.6	462	1.2 %
D	8.3	812	4.8 %
E	8.9	1431	11.3 %
F	7.8	2436	33.8 %
G	9.8	3788	72.3 %
H	7.6	4689	91.8 %
I	8.2	6126	100 %
J	21.9	Not examined	Not made

The surface roughnesses Ra are dispersed between 7.2nm and 21.9nm. Sample J had too big surface roughness Ra=21.9nm which forbade the formation of interdigital transducers. Having the same roughness Ra=7.6nm, sample C and sample H have different breaking rates 1.2% and 91.8% respectively. This means that the surface roughness is not a critical factor 5 for determining the breaking rate.

Sample E with Ra=8.9nm shows a good breaking rate 11.3% which is much better than a breaking rate 100% of sample I of Ra=8.2nm. The breaking rates are reversed to Ra for samples E and I. Sample H, suffering from a high breaking rate of 91.8%, is useless for the substrate of SAW devices. However, a person who pays attention only to Ra would 10 consider that sample H must be a good substrate. Ra is not a reliable factor for foreseeing the quality of electrodes formed upon the sample.

Then, the breaking rates are now considered from a different standpoint. Sample B enjoys 0% of pattern breaking rate, since it has a small defect density of 287 particles/cm². Sample A exhibits 0 % breaking rate due to the very small defect density of 80 particles/cm². 15 Sample C has still a low defect density of 462 particles cm⁻² which suppresses the breaking rate to 1.2%. Sample D has a defect density of 812 particles cm⁻² which is about twice as many as sample C. The electrode breaking rate is also doubled to 4.8%. Sample F which has defects of 2436 particles cm⁻² is accompanied by a high breaking rate 33.8%. Sample G with a defect density 3788 particles cm⁻² is afflicted with a high breaking rate 72.3%. 20 Despite low Ra=7.6nm, sample H has a very high breaking rate 91.8% due to the large defect density of 4689 particles cm⁻². What these results tell is that the most important factor of determining the quality of electrodes is not the surface roughness Ra but the defect/dust density. Namely, the examination by the laser scanning surface defect detection apparatus gives the most suitable estimation for the surface states of diamond wafers.

25 An ideal condition is, of course, 0% of breaking rate. For 0% of breaking rate, the

defect (and dust) density should be less than 300 particles cm^{-2} , because sample B of 0 % has a defect density less than 300 particles cm^{-2} but sample C of 1.2% has a defect density more than 300 particles cm^{-2} . Thus, 300 particles cm^{-2} is the critical value ruling the break of electrode patterns. The roughness must be less than 20nm. The roughness is not a major 5 factor for determining the breaking rate. The roughness less than $\text{Ra}=10$ nm is more suitable for decreasing the breaking rate.

What affects the break of electrode patterns is not the surface roughness but the defect density. There has been no means for estimating defects of diamond crystals. The Inventors succeeded in examining the defect on diamond crystals by coating the object 10 diamond with a thin metal film and measuring the scattering light in the laser scanning surface defect detection apparatuses which have been widely employed for estimation of silicon wafers. The new estimation method using the laser scanning surface defect detection apparatus can give a definite requirement of diamond films or bulks suitable for the substrates of SAW devices. The preliminary estimation can prophesy that the object diamond crystals 15 are appropriate for the substrates for making piezoelectric films and producing interdigital transducers. SAW devices should be made only on the diamond substrates which passed the examination. The samples which fail in the examination should be rejected without making piezoelectric films and interdigital transducers (IDT). The estimation can save much time, energy and resources.

20 [EMBODIMENT 2: Measurement of propagation loss on samples having piezoelectric films]

The previous test tells us that sample A and sample B of less than 300 defects/ cm^2 are immune from electrode breaking. However the defect estimation is not sufficient to know the performance of SAW devices which are going to be made by depositing piezoelectric films and electrodes on the diamond substrates. Then, actual propagation loss 25 was measured on SAW devices made by depositing piezoelectric films on the dia/Si wafers of

sample A and sample B which passed the defect test and forming interdigital transducers on the piezoelectric films. No SAW devices were made on samples C to J which failed in the defect test.

1. Formation of piezoelectric films

5 Piezoelectric ZnO films of a 1050 nm thickness were formed upon the dia/Si substrates of sample A and sample B by an RF sputtering method.

(Condition of formation of ZnO piezoelectric film)

Substrates	dia/Si wafers : sample A, sample B	
Target	ZnO sintered plate	
10 RF power	500 W	(13.56MHz)
Reaction gas	Ar+O ₂	Ar:O ₂ =1:1
	gas flow	50 sccm
Gas pressure	20.0 Pa (152mTorr)	
Substrate temperature	150°C	
15 Speed of deposition	5 nm/min	
Thickness	1050 nm (1.05 μ m)	

Complex wafers of ZnO/dia/Si were made from samples A and B by the above way.

2. Formation of aluminum films

80 nm thick aluminum films were deposited upon the ZnO films for making 20 electrodes by a DC sputtering method.

(Condition of forming aluminum films)

DC sputtering power	1.0 kW
Reaction gas	Ar gas
	gas flow 50sccm
25 Gas pressure	1.0 Pa (7.6mTorr)

Substrate temperature room temperature

Thickness 80 nm

This step made further complex wafers of Al/ZnO/dia/Si.

3. Production of interdigital transducers

5 Interdigital transducers having the following parameters were formed by eliminating parts of the aluminum layer selectively by photolithography.

(Parameters of interdigital transducers)

Line Width of IDTs $0.8 \mu m$ (central frequency = 1.75 GHz)

Number of stripes 40 pairs double stripes (regular type)

10 Aperture of IDTs $50 \times$ wavelength

(wavelength = 8 stripe widths $\lambda = 6.4 \mu m$)

Distance between the centers of input- and output- transducers $50 \times$ wavelength

Fig.15 shows the IDT pattern. A unit pattern consists of two sets of stripe pairs. Two neighboring stripes belong to the same transducer. Four stripes construct one 15 wavelength. The width of a blank is equal to the width of a stripe. The wavelength is eight times as long as the stripe width ($\lambda = 8d$). Thus, SAW devices shown in Fig.9 have been fabricated.

Transmission loss and the conversion loss of the SAW devices were measured by a spectrum network analyzer (HP8753c). AC power of 1GHz to 2GHz was applied to one 20 side electrode (electrode 1). The electric power of the input electrode 1 and the electric power of the output (counterpart) electrode 2, that is, scattering parameters were measured. S11 is a reflection power ratio which is a quotient of the reflected power to the electrode 1 to the input power of the electrode 1, when the AC power is supplied to the electrode 1. S22 is a reflection power ratio which is a quotient of the reflected power to the electrode 2 to the 25 input power to the electrode 2, when AC power is supplied to the electrode 2. S12 is a

transmission power ratio which is a quotient of the power arrived at the electrode 2 to the input power to the electrode 1, when AC power is supplied to the electrode 1. S21 is a transmission power ratio which is a quotient of the power arrived at the electrode 1 to the input power to the electrode 2, when AC power is supplied to the electrode 2.

5 Fig.10 shows the transmission power ratio (S12) as a function of the frequency of signals. The abscissa is the frequency (MHz). The ordinate is the transmission power ratio (dB). 1.78 GHz (1780 MHz) gives a peak of the transmission power of -8.2dB. The frequency corresponds to $f=v/\lambda$, where v is the speed of the SAW and λ is the spatial wavelength of the interdigital transducer which is a predetermined parameter, as shown in
10 Fig.15. It is a matter of course that the transmission power ratio is the biggest at $1.78\text{GHz} = v/\lambda$. The maximum transmission power ratio is -0.82dB. The loss 8.2dB includes all the resistance loss at electrodes, the bilateral loss and the conversion loss. The real transmission loss can be calculated by subtracting these losses from the total loss 8.2dB.

15 The resistance loss is calculated to be 1.0 dB for an electrode stripe of a 80nm thickness and a $0.8\mu\text{m}$ width. The bilateral loss is 6db, because the power is halved at the input electrode. Fig.11 shows S11 and Fig.12 shows S22. The conversion loss is known from the loss of the flat regions of S11 or S22 except $f=1.78\text{GHz}$. The loss is about 0.3dB both for S11 and for S22. The conversion loss occurs at both the input and the output electrodes. Then, the conversion loss is 0.6dB at both electrodes. The sum of the
20 resistance loss, the bilateral loss and the conversion loss is 7.6dB. The total loss for 1.78GHz is 8.2dB from S12. The propagation loss is only 0.6dB which is a difference between the total loss 8.2dB and the sum 7.6dB of the three losses. 0.6dB is a small propagation loss.

25 This is the total propagation loss along the whole path from the input electrode to the output electrode. The distance between the centers of the electrodes is 50 times as long as

the wavelength. The propagation loss per wavelength is 0.012dB which is calculated by dividing 0.6dB by 50λ . The propagation loss $0.012\text{dB}/\lambda$ is a very small value for such a high frequency 1.8GHz. The low propagation loss is a very conspicuous advantage of the SAW devices of the present invention. Table 1 shows that sample A and sample B are free
5 from electrode breaking. Sample A has a surface defect density of 80 particles cm^{-2} which is far lower than the critical value 300 particles cm^{-2} . The surface roughness of sample A is $\text{Ra}7.2\text{nm}$. Sample B has a higher defect density of 287 particles cm^{-2} which is still lower than 300 particles cm^{-2} . Sample B exhibits the roughness of $\text{Ra}8.2\text{nm}$. Both sample A and sample B are endowed with low insertion loss of about 10dB.

10 Other samples C to I have definite electrode breaking rates and low yields for producing SAW devices. SAW devices have been fabricated on samples C to I in a similar manner. The electrodes of the SAW devices are examined by electric property measurement, optical microscope observation and electron microscope observation. Some SAW devices are suffering from electrode breaking. Others are immune from electrode breaking. The
15 properties of SAW devices without electrode breaking are tested. All the samples of C to I have insertion loss higher than 13dB. This examination reveals bad crystallographic properties of the piezoelectric films of samples C to I. The surface defects of diamond films worsen the crystallographic properties of the piezoelectric films. The bad crystallography of piezoelectric films raises the propagation loss of the SAW devices made on samples C to I.

20 This invention examines surface defects of diamond films or bulks by covering the object diamond surfaces with thin metal films and measuring defects by the laser scanning surface defect detection apparatus. The preliminary examination can foresee the properties of SAW devices which will be made on the diamond crystals. SAW devices should be fabricated only upon the samples having diamond surface of small defect density, for example,
25 less than 300 particles cm^{-2} . Here, the definition of a defect includes the critical size which

depends upon the period of the electrodes. Thus, the defect density of the same diamond is different for different periods of the electrodes of SAW devices. Low defect density diamond films or bulks bring about zero or small enough electrode breaking rates when electrodes are made thereon. Low propagation loss SAW devices can be produced by 5 depositing piezoelectric films on the low defect density diamonds and making interdigital transducers on the piezoelectric films.

The embodiments of the present invention in which an exclusive property or privilege is claimed are defined as follows:

1. A diamond wafer comprising:

a diamond single crystal or polycrystal substrate synthesized by an ultrahigh pressure synthesis method or a vapor phase deposition method or a diamond substrate consisting of a diamond board or another material board and a single crystal or polycrystal diamond film synthesized upon the diamond board or another material board;
characterized by surface defect density of less than 300 particles cm^{-2} which is measured by coating the diamond surface with a thin opaque film, launching laser beams to the coated diamond surface from a laser scanning surface defect detection apparatus for letting the laser beams reflect at a surface of the coating film and an interface between the coating film and the diamond surface, and counting the beams scattered by surface defects or particles on the diamond surface.

2. A diamond wafer comprising:

a diamond single crystal or polycrystal substrate synthesized by an ultrahigh pressure synthesis method or a vapor phase deposition method or a diamond substrate consisting of a diamond board or another material board and a single crystal or polycrystal diamond film synthesized upon the diamond board or another material board; and
a piezoelectric film deposited upon the diamond substrate or the diamond film;
characterized by surface defect density of less than 300 particles cm^{-2} which is measured by coating the piezoelectric film surface with a thin opaque film, launching laser beams to the coated piezoelectric film surface from a laser scanning surface defect detection apparatus for letting the laser beams reflect at a surface of the coating film and

an interface between the coating film and the piezoelectric film surface, and counting the beams scattered by surface defects or particles on the diamond surface.

3. The diamond wafer as claimed in claim 1, wherein the diamond substrate is used for making SAW devices or microelectronic devices having wiring patterns and the surface defects to be counted in are defects having widths larger than 50% of the smallest width of wiring patterns and having either depths deeper than 10nm or heights higher than 10nm.
4. The diamond wafer as claimed in claim 3, wherein roughness of the diamond surface is less than Ra20nm.
5. The diamond wafer as claimed in claim 4, wherein the diamond substrate has an area which is equal to or wider than 19cm².
6. The diamond wafer as claimed in claim 5, wherein inner stress in the diamond crystal is less than 1.5 X 10⁸ Pa.
7. The diamond wafer as claimed in claim 5, wherein the diamond wafer has a distortion height of less than $\pm 40 \mu m$ at a center.
8. The diamond wafer as claimed in claim 1, wherein the diamond substrate consists of a diamond board or another material board and a single crystal or polycrystal diamond film deposited on the board by a vapor phase synthesis method, the thickness of the board is 0 to 2000 μm and the thickness of the diamond film is more than 1 μm .

9. The diamond wafer as claimed in claim 1, wherein the thin opaque film coating the diamond surface for estimation is a metal film or a non-metal film of a reflection rate of more than 50%.
10. The diamond wafer as claimed in claim 9, wherein the metal film coating the diamond surface is an aluminum film deposited by sputtering.
11. A diamond surface acoustic wave device comprising:
 - a diamond single crystal or polycrystal substrate being synthesized by an ultrahigh pressure synthesis method or a vapor phase deposition method and having surface defect density of less than 300 particles cm^{-2} or a diamond substrate consisting of a diamond board or another material board and a single crystal or polycrystal diamond film being synthesized upon the diamond board or another material board and having surface defect density of less than 300 particles cm^{-2} ;
 - the defect density being defined by $d \geq W/2$ and $h \geq 10\text{nm}$, where d is a diameter of a defect, W is the minimum width of electrodes and h is a depth or a height of the defect;
 - a piezoelectric film deposited on the diamond substrate; and
 - interdigital transducers produced on the piezoelectric film;

wherein the defect density is measured by coating the diamond surface with a thin opaque film, launching laser beams to the coated diamond surface from a laser scanning surface defect detection apparatus for letting the laser beams reflect at a surface of the coating film and an interface between the coating film and the diamond surface, and counting the beams scattered by surface defects or particles on the diamond surface.

12. A diamond surface acoustic wave device comprising:
 - a diamond single crystal or polycrystal substrate being synthesized by an ultrahigh pressure synthesis method or a vapor phase deposition method and having surface defect density of less than 300 particles cm^{-2} or a diamond substrate consisting of a diamond board or another material board and a single crystal or polycrystal diamond film being synthesized upon the diamond board or another material board and having surface defect density of less than 300 particles cm^{-2} ;
 - the defect density being defined by $d \geq W/2$ and $h \geq 10 \text{ nm}$, where d is a diameter of a defect, W is the minimum width of electrodes and h is a depth or a height of the defect;
 - interdigital transducers produced on the diamond substrate; and
 - a piezoelectric film deposited on the interdigital transducers and on the diamond substrate;
- wherein the defect density is measured by coating the diamond surface with a thin opaque film, launching laser beams to the coated diamond surface from a laser scanning surface defect detection apparatus for letting the laser beams reflect at a surface of the coating film and an interface between the coating film and the diamond surface, and counting the beams scattered by surface defects or particles on the diamond surface.

Fig. 1

 $R_a \leq 10 \text{ nm}$ Defect density $\leq 300/\text{cm}^2$

Carbon layer	$d \leq 10 \text{ nm}$
Diamond	$P \leq 1.5 \times 10^8 \text{ Pa}$ $S \geq 19 \text{ cm}^2$

Fig. 2




Fig. 3 (a)






Fig. 3 (b)



Travis & Clark

Fig. 4

Laser scanning surface defect detection apparatus



Marks & Clark

Fig. 5

Synthesis of diamond by microwave plasma CVD




Fig. 6

Flattening of diamond surface by polishing




Fig. 7

Formation of ZnO film by sputtering




Fig. 8

Deposition of Al film by sputtering





Fig. 9

Formation of electrodes by photolithography



Thanks & Clark

Fig. 10





Fig. 11



Thanks Clark

electric
power
(dB)

Fig. 12


 S_{22} 

Fig. 13






Fig. 14



Randy Clark

Fig. 15



Travis & Clark

$R_a \leq 10 \text{ nm}$

Defect density $\leq 300/\text{cm}^2$

Carbon layer $d \leq 10 \text{ nm}$

Diamond $P \leq 1.5 \times 10^8 \text{ Pa}$
 $S \geq 19 \text{ cm}^2$