



- (51) **International Patent Classification:**
E21B 47/09 (2012.01) G01V 3/38 (2006.01)
G01V 3/18 (2006.01)
- (21) **International Application Number:**
PCT/US2015/037875
- (22) **International Filing Date:**
26 June 2015 (26.06.2015)
- (25) **Filing Language:** English
- (26) **Publication Language:** English
- (30) **Priority Data:**
14/318,327 27 June 2014 (27.06.2014) US
- (71) **Applicant (for CA only):** SCHLUMBERGER CANADA LIMITED [CA/CA]; 125 - 9 Avenue SE, Calgary, Alberta T2G 0P6 (CA).
- (71) **Applicant (for FR only):** SERVICES PETROLIERS SCHLUMBERGER [FR/FR]; 42 rue Saint Dominique, F-75007 Paris (FR).
- (71) **Applicant (for GB, JP, NL only):** SCHLUMBERGER HOLDINGS LIMITED; P.O. Box 71, Craigmuir Chambers, Road Town, Tortola, Virgin Islands, British, 1110 (VG).
- (71) **Applicant (for all designated States except AE, AO, BH, CA, CN, FR, GB, GH, IN, JP, LY, MA, MZ, NA, NG, NL, PH, SD, SY, US, VN):** SCHLUMBERGER TECHNOLOGY B.V. [NL/NL]; Parkstraat 83-89m, NL-2514 JG The Hague (NL).
- (71) **Applicant (for AE, AO, BF, BH, BJ, CF, CG, CI, CM, CN, GA, GH, GN, GQ, GW, IN, KM, LY, MA, ML, MR, MZ, NA, NE, NG, PH, SD, SN, SY, TD, TG, VN only):** PRAD RESEARCH AND DEVELOPMENT LIMITED; P.O. Box 71, Craigmuir Chambers, Road Town, Tortola, Virgin Island, British, 1110 (VG).
- (71) **Applicant (for US only):** SCHLUMBERGER TECHNOLOGY CORPORATION [US/US]; 300 Schlumberger Drive, Sugar Land, Texas 77478 (US).
- (72) **Inventor:** BROOKS, Andrew; 15531 Hermitage Oaks Drive, Tomball, Texas 77377 (US).
- (74) **Agents:** BALLEW, Kimberly et al.; 10001 Richmond Avenue, IP Administration Center of Excellence, Room 4720, Houston, Texas 77042 (US).
- (81) **Designated States (unless otherwise indicated, for every kind of national protection available):** AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM,

[Continued on next page]

(54) **Title:** MAGNETIC RANGING WHILE ROTATING




FIG. 3

(57) **Abstract:** A method for magnetic ranging includes rotating a downhole tool in a drilling well in sensory range of magnetic flux emanating from a target well. The downhole tool includes a magnetometer set and an accelerometer set rotatably coupled to the tool. The magnetometer set and the accelerometer set acquire corresponding magnetometer measurements and accelerometer measurements while rotating. The magnetometer measurements are transformed to a rotation independent reference frame to obtain rotation invariant measurements which are in turn processed to compute at least one of a distance and a direction from the drilling well to the target well.





DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, KM, ML, MR, NE, SN, TD, TG).

(84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH,

Published:

— with international search report (Art. 21(3))

MAGNETIC RANGING WHILE ROTATING

CROSS-REFERENCE TO RELATED APPLICATION

[0001] The present application claims priority from U.S. Non-Provisional Patent Application 14/318327, filed June 27, 2014, which is incorporated herein by reference in its entirety.

FIELD OF THE DISCLOSURE

[0002] Disclosed embodiments relate generally to magnetic ranging methods and more particularly to methods for magnetic ranging while drilling (i.e., while the drill string is rotating).

BACKGROUND INFORMATION

[0003] In subterranean drilling operations the need frequently arises to determine the relative location of the wellbore being drilled (the drilling well) with respect to a pre-existing offset wellbore (a target well). This need may exist for the purpose of avoiding a collision or making an interception, or for the purpose of maintaining a specified separation distance between the wells (e.g., as in well twinning operations such as steam assisted gravity drainage operations). Magnetic ranging techniques are commonly employed to determine the relative location of the target well, for example, by making magnetic field measurements in the drilling well. The measured magnetic field may be induced in part by ferromagnetic material or an electromagnetic source (or sources) in the

target well such that the measured magnetic field vector may enable the relative location of the target well to be computed.

[0004] Existing magnetic ranging techniques are similar to conventional static surveys in that they require drilling to be halted and the drill string to be held stationary in the drilling well while each magnetic survey is obtained. Magnetic ranging operations are therefore costly and time consuming. Moreover, magnetic ranging is similar to wellbore navigation in that the well path may be continuously adjusted in response to the ranging measurements. It may therefore be desirable to make ranging measurements as close to the bit as possible, in order to gain the earliest possible notification of required course adjustments. Owing to the rotation of the bit, measurements made close to the bit while drilling are made from a rotating platform (i.e., with rotating magnetic field sensors). There is a need in the art for magnetic ranging methods that employ magnetic field measurements made from a rotating platform (rotating sensors).

SUMMARY

[0005] A method for magnetic ranging is disclosed. A downhole drilling tool is rotated in a drilling well in sensory range of magnetic flux emanating from a target well. The downhole tool includes a magnetometer set and an accelerometer set rotatably coupled to the tool. The magnetometer set and the accelerometer set acquire corresponding magnetometer measurements and accelerometer measurements while rotating. The magnetometer measurements are transformed to a rotation independent reference frame to obtain rotation invariant measurements which are in turn processed to compute at least one of a distance and a direction from the drilling well to the target well.

[0006] The disclosed methods may enable magnetic ranging measurements to be acquired and processed while rotating the magnetic field sensors in the drilling well. The measurements may therefore be acquired and processed while drilling. Moreover, in embodiments in which the magnetic field sensors are mounted in a near-bit sensor sub below a mud motor, the ranging measurements may be acquired and processed while maintaining drilling fluid circulation.

[0007] This summary is provided to introduce a selection of concepts that are further described below in the detailed description. This summary is not intended to identify key or essential features of the claimed subject matter, nor is it intended to be used as an aid in limiting the scope of the claimed subject matter.

BRIEF DESCRIPTION OF THE DRAWINGS

[0008] For a more complete understanding of the disclosed subject matter, and advantages thereof, reference is now made to the following descriptions taken in conjunction with the accompanying drawings, in which:

[0009] FIG. 1 depicts one example of a conventional drilling rig on which disclosed methods may be utilized.

[0010] FIG. 2 depicts a lower BHA portion of the drill string shown on FIG. 1.

[0011] FIG. 3 depicts a flow chart of one disclosed method embodiment.

[0012] FIG. 4 depicts a schematic of the measured magnetic field in the transverse plane.

[0013] FIG. 5 depicts a plot of the transverse magnetometer outputs B_x and B_y as a function of time.

[0014] FIG. 6 depicts an example plot of the radial B_r and axial B_z magnetic fields as a function of measured depth for an example target well including a premagnetized casing string.

[0015] FIG. 7 depicts one example of a plot of the high side BHS versus right side BRS magnetic field components.

[0016] FIG. 8 depicts a plot of radial B_r and axial B_z magnetic fields verses axial position along the axis of target well having a residual remanent magnetism.

[0017] FIG. 9 depicts a flow chart of another disclosed method embodiment.

[0018] FIG. 10 depicts a schematic of the measured magnetic field including the Earth's field and target field in the transverse plane.

[0019] FIG. 11 depicts a flow chart of yet another disclosed method embodiment.

DETAILED DESCRIPTION

[0020] FIG. 1 depicts a drilling rig 20 suitable for using various method embodiments disclosed herein. The rig may be positioned over an oil or gas formation (not shown) disposed below the surface of the Earth 25. The rig 20 may include a derrick and a hoisting apparatus for raising and lowering a drill string 30, which, as shown, extends into wellbore 40 and includes a drill bit 32 and a near-bit sensor sub 50 (such as the iPZIG® tool available from PathFinder®, A Schlumberger Company, Katy, Texas, USA). Drill string 30 may further include a downhole drilling motor, a steering tool such as a rotary steerable tool, a downhole telemetry system, and one or more MWD or LWD tools including various sensors for sensing downhole characteristics of the borehole and the surrounding formation. The disclosed embodiments are not limited in these regards.

[0021] FIG. 1 further depicts a well twinning operation, such as a steam assisted gravity drainage (SAGD) operation, in which various disclosed method embodiments may be utilized. In common SAGD well twinning operations, a horizontal twin well 40 is drilled a substantially fixed distance above a horizontal portion of a target wellbore 80 (e.g., not deviating more than about 1 meter up or down or to the left or right of the target). In the depicted embodiment the target well 80 is drilled first, for example, using conventional directional drilling and MWD techniques. The target wellbore 80 may be magnetized, for example, via installing a plurality of premagnetized tubulars 85 in the wellbore or deploying a magnetic source 88 such as a DC or an AC electromagnet in the wellbore. Magnetic field measurements made while the drill string 30 rotates in the drilling well 40 (e.g., at sensor sub 50) may then be used to determine a relative distance and direction from the drilling well 40 to the target well 30 (as described in more detail below).

[0022] It will be understood by those of ordinary skill in the art that the deployment illustrated on FIG. 1 is merely an example. For example, while FIG. 1 depicts a SAGD operation, the disclosed embodiments are in no way limited to SAGD or other well twinning operations, but may be used in substantially any drilling operation in which it is desirable to determine the relative location of the drilling well with respect to an offset well. Such operations may be performed onshore (as depicted) or offshore.

[0023] FIG. 2 depicts the lower BHA portion of drill string 30 including drill bit 32 and near-bit sensor sub 50. In the depicted embodiment, sensor sub body 52 is threadably connected with the drill bit 32 and therefore configured to rotate with the bit 32. The depicted sensor sub 50 includes a tri-axial (three axis) accelerometer set 55 and a tri-axial magnetometer set 57. In the depicted embodiment, the sensors 55 and 57 being deployed in a near-bit sensor sub may be deployed close to the drill bit 32, for example, within two

meters, or even within one meter of the bit 32. However, it will be understood that the disclosed embodiments are not limited to the use of a near-bit sensor sub or to the deployment of the sensor close to the bit. Substantially any suitable measurement tool (such as a conventional MWD tool) including a magnetic field sensor may be utilized.

[0024] Suitable accelerometers and magnetometers for use in sensors 55 and 57 may be chosen from among any suitable commercially available devices known in the art. For example, suitable accelerometers may include Part Number 979-0273-001 commercially available from Honeywell, and Part Number JA-5H175-1 commercially available from Japan Aviation Electronics Industry, Ltd. (JAE). Other suitable accelerometers may include micro-electro-mechanical systems (MEMS) solid-state accelerometers, available, for example, from Analog Devices, Inc. (Norwood, Massachusetts). Such MEMS accelerometers may be advantageous for certain near bit sensor sub applications since they tend to be shock resistant, high-temperature rated, and inexpensive. Suitable magnetic field sensors may include conventional ring core flux gate magnetometers or conventional magnetoresistive sensors, for example, Part Number HMC-1021D, available from Honeywell.

[0025] FIG. 2 further includes a diagrammatic representation of the tri-axial accelerometer and tri-axial magnetometer sensor sets 55 and 67. By tri-axial it is meant that each sensor set includes three mutually perpendicular sensors, the accelerometers being designated as A_x , A_y , and A_z and the magnetometers being designated as B_x , B_y , and B_z . By convention, a right handed system is designated in which the z-axis accelerometer and magnetometer (A_z and B_z) are oriented substantially parallel with the borehole as indicated (although disclosed embodiments are not limited by such conventions). Each of the accelerometer and magnetometer sets may therefore be

considered as determining a transverse cross-axial plane (the x and y-axes) and an axial pole (the z-axis along the axis of the BHA).

[0026] By further convention, the gravitational field is taken to be positive pointing downward (i.e., toward the center of the Earth) while the magnetic field is taken to be positive pointing towards magnetic north. Moreover, also by convention, the y-axis is taken to be the toolface reference axis (i.e., gravity toolface T equals zero when the y-axis is uppermost and magnetic toolface M equals zero when the y-axis is pointing towards the projection of magnetic north in the transverse (xy) plane). Those of ordinary skill in the art will readily appreciate that the magnetic toolface M is projected in the xy plane and may be represented mathematically as: $\tan M = B_x/B_y$. Likewise, the gravity toolface T may be represented mathematically as: $\tan T = -A_x/-A_y$. Those of skill in the art will understand that the negative sign in the gravity toolface expression arises owing to the convention that the gravity vector is positive in the downward direction while the toolface reference direction is the high side of the borehole (the side facing upward).

[0027] It will be understood that the disclosed embodiments are not limited to the above described conventions for defining the borehole coordinate system. It will be further understood that these conventions can affect the form of certain of the mathematical equations that follow in this disclosure. Those of ordinary skill in the art will be readily able to utilize other conventions and derive equivalent mathematical equations.

[0028] FIG. 3 depicts a flow chart of one disclosed method embodiment 100. A sensor sub (e.g., sub 50) including accelerometers and magnetometers is rotated in a drilling well at 102 in sensory range of magnetic flux emanating from a target wellbore. Accelerometer and magnetometer measurements are acquired at 104 while rotating in 102. The acquired transverse magnetometer measurements may be transformed at 106 to

a reference frame that is independent of the sensor rotation in 102. The transformed measurements may then be processed at 108 to compute at least one of a distance and a direction from the drilling well to the target well.

[0029] During rotation at 102, the transverse sensor (accelerometers A_x and A_y and magnetometers B_x and B_y) measurements may be expressed mathematically, for example, as follows:

$$A_x = -A_{xy} \cdot \sin T \quad (1)$$

$$A_y = -A_{xy} \cdot \cos T \quad (2)$$

$$B_x = B_{xy} \cdot \sin M \quad (3)$$

$$B_y = B_{xy} \cdot \cos M \quad (4)$$

[0030] where A_{xy} represents the transverse component of the acceleration (e.g., due to gravity), B_{xy} represents the transverse component of the magnetic field, and T and M represent gravity and magnetic tool face as defined above. With reference to FIG. 4, recognizing that the toolface offset angle $T - M$ is independent of rotation (toolface offset depends on the wellbore attitude and the magnetic dip angle) enables the transverse measurements to be transformed into a reference frame that is independent of the rotation.

Equations 1-4 may be rearranged, for example, as follows:

$$B_x \cdot A_y - B_y \cdot A_x = B_{xy} \cdot A_{xy} \cdot \sin(T - M) \quad (5)$$

$$B_x \cdot A_x + B_y \cdot A_y = -B_{xy} \cdot A_{xy} \cdot \cos(T - M) \quad (6)$$

[0031] Equations 5 and 6 may be combined, for example, as follows to obtain the toolface offset ($T - M$):

$$(T - M) = \tan^{-1} \left[\frac{(B_x \cdot A_y - B_y \cdot A_x)}{(-B_x \cdot A_x - B_y \cdot A_y)} \right] \quad (7)$$

[0032] which as illustrated in FIG. 4 is the direction of the transverse component B_{xy} with respect to the highside (HS) of the wellbore. The magnitude of the transverse component B_{xy} may be obtained, for example, from one of the following equations:

$$B_{xy} = \sqrt{(B_x^2 + B_y^2)} \quad (8)$$

$$B_{xy} = \sqrt{2 \cdot \sigma(B_x) \cdot \sigma(B_y)} \quad (9)$$

[0033] where $\sigma(B_x)$ and $\sigma(B_y)$ represent the standard deviations of B_x and B_y . Note that both the magnitude B_{xy} and direction ($T - M$) of the transverse field given in Equations 7, 8, and 9 are invariant under drill string rotation.

[0034] Accelerometer measurements made while rotating (particularly while drilling) are generally noisy owing to vibration of the drill string. Therefore, it may be advantageous to average the transverse accelerometer measurements over a time period such as several seconds in order to obtain an accurate measure of the toolface offset. Since the transverse accelerometer measurements vary with rotation it is desirable to compute an average toolface offset, for example, as follows:

$$(T - M) = \tan^{-1} \left[\frac{\sum(B_x \cdot A_y - B_y \cdot A_x)}{\sum(-B_x \cdot A_x - B_y \cdot A_y)} \right] \quad (10)$$

[0035] where $\sum(\cdot)$ represents a summation of a number of accelerometer and magnetometer measurements (acquired over a period of time). In an embodiment in which the accelerometer and magnetometer measurements are acquired at 10 millisecond intervals, the measurements may be advantageously summed (averaged) over a time interval in a range from about 1 to about 300 seconds (e.g., about 30 seconds). The magnitude of the transverse component B_{xy} may be similarly averaged.

[0036] Turning to FIG. 5, the transverse magnetometer outputs may be plotted with time as the measurement tool rotates in the drilling well. As described above with respect to Equations 3 and 4, B_x and B_y vary sinusoidally with an amplitude equal to the magnitude of the transverse component B_{xy} . Moreover, as also depicted, the mean value for each sensor is equal to the sensor bias (over an integer number of periods). The mean values acquired during rotation may therefore enable the sensor biases to be removed (e.g., subtracted) prior to other processing. Upon removing the B_x and B_y biases, the toolface offset computed using Equation 9 is unaffected by transverse accelerometer bias (e.g., due to centripetal acceleration during rotation). Alternatively, the transverse accelerometer biases may be similarly removed in which case the toolface offset obtained via Equation 10 is unaffected by transverse magnetometer biases.

[0037] The transverse magnetic field may alternatively and/or additionally be expressed in terms of high side BHS and right side BRS components, for example, as follows:

$$BHS = B_{xy} \cdot \cos(T - M) \quad (11)$$

$$BRS = B_{xy} \cdot \sin(T - M) \quad (12)$$

[0038] The axial magnetic field measurement and the axial acceleration component (measured by the B_z magnetometer and the A_z accelerometer) may also be averaged as described above for the transverse measurements (e.g., over the same time interval). In embodiments utilizing a near-bit sensor sub (as depicted on FIG. 2) the axial magnetometer measurements may be contaminated by remanent and induced magnetic interference from nearby ferromagnetic drilling tool components. Such magnetic interference may be removed, for example, as described in U.S. Patent Publication 2013/0069655 (which is incorporated by reference in its entirety herein).

[0039] Based on the foregoing discussion, the three-dimensional magnetic field measured while rotating may be transformed from a tool based x / y / z coordinate system to a rotation invariant high side / right side / axial coordinate system. Alternatively, the three-dimensional magnetic field measured while rotating may be expressed as the magnitude of the transverse component B_{xy} , the toolface offset angle ($T - M$), and the magnitude of the axial component B_z . The three components of the rotation invariant magnetic field vector (e.g., BHS, BRS, and B_z) may be computed downhole as described above and transmitted to the surface using conventional telemetry techniques (e.g., via mud pulse or mud siren telemetry techniques). It may also be advantageous to transmit either the axial accelerometer measurement A_z or the borehole inclination Inc , which may be computed from the axial accelerometer measurement, for example, as follows:

$$Inc = \cos^{-1}\left(\frac{A_z}{G}\right) \quad (13)$$

[0040] where G represents the local gravitational field of the Earth which may be determined from an external source or from the tri-axial accelerometer array during times in which the sensor sub is not rotating.

[0041] In certain embodiments the measured transverse magnetic field components may be perturbed by rotation of the drill string which can produce eddy currents in the electrically conductive collar. Such phenomenon has been disclosed, for example, in U.S. Patent 5,012,412. In order to compensate for the effect of rotation induced eddy currents, it may also be desirable to transmit to the rotary speed (the rotation rate) of the sensor sub to the surface. The rotary speed rpm may be found, for example, as follows:

$$rpm = \frac{60s}{(2\pi N)} \sum_{i=1}^N [\text{mod}(M_i - M_{i-1} + \pi, 2\pi) - \pi] \quad (14)$$

[0042] where the summation is over N samples acquired at s per second (e.g., 3000 samples acquired at 100 samples per second) and M_i represents the magnetic tool face of the i^{th} sample.

[0043] Since the error in the direction of the transverse magnetic component caused by the conductive collar is approximately proportional to rotary speed, it may be represented by a fixed time delay between the accelerometer and magnetometer measurements. The effect may therefore be corrected by shifting the acquisition times for one set of sensors (either the accelerometers or magnetometers). This may be accomplished, for example, through the use of appropriate filters which delay the accelerometer signals with respect to the magnetometer signals. The methodologies disclosed in U.S. Patent 7,650,269 and U.S. Patent Publications 2007/0203651 and 2010/0250207 may also optionally be employed to address any transverse magnetic field perturbations due to eddy currents in the drill collar.

[0044] The magnetic field components measured downhole represent the sum of the local Earth's magnetic field and the field from the target (as well as any magnetic interference from the drill string – which may be removed as described above). In order to obtain the target field from which magnetic ranging calculations are made, it may be necessary to remove the Earth's field components from the measured field. This may be represented mathematically, for example, as follows:

$$\vec{B}_T = \vec{B}_m - \vec{B}_e \quad (15)$$

[0045] where \vec{B}_T represents the target magnetic field vector, \vec{B}_m represents the measured magnetic field vector, and \vec{B}_e represents the Earth's magnetic field vector. It will be understood that computing the target field vector may require that the measured

magnetic field vector and the Earth's magnetic field vector be transformed into the same coordinate system (e.g., the rotation invariant system described above).

[0046] The magnetic field of the Earth (including both magnitude and direction components) is typically known, for example, from previous geological survey data or a geomagnetic model. However, for some applications it may be advantageous to measure the magnetic field in real time on site at a location substantially free from magnetic interference, e.g., at the surface of the well or in a previously drilled well. Measurement of the magnetic field in real time is generally advantageous in that it accounts for time dependent variations in the Earth's magnetic field, e.g., as caused by solar winds. However, at certain sites, such as an offshore drilling rig, measurement of the Earth's magnetic field in real time may not be practical. In such instances, it may be preferable to utilize previous geological survey data in combination with suitable interpolation and/or mathematical modeling (i.e., computer modeling) routines. Those of ordinary skill in the art will readily be able to transform the Earth's field to the above described high side / right side / axial reference frame, for example, using measured borehole inclination and borehole azimuth values.

MAGNETIC RANGING TO A DC TARGET

[0047] The disclosed magnetic ranging embodiments may be utilized with a magnetic target including substantially any suitable DC magnetization. For example, the target well may include a magnetized casing string. The casing string may be intentionally magnetized so as to impart a known magnetic pattern to the string, for example, as disclosed in U.S. Patents 7,538,650, 7,656,161, and 8,026,722, each of which is incorporated by reference herein in its entirety. In one embodiment commonly used in

SAGD operations, the casing string may be magnetized such that each tubular in a premagnetized region of the casing includes a single pair of magnetically opposing poles (NN or SS) located at the approximate midpoint of the tubular. In this embodiment, the pairs of opposing poles are spaced at intervals about equal to the length of the tubulars, while the period of the magnetic field pattern (e.g., the distance from one a NN pair of opposing poles to the next) is about twice the length of the tubular.

[0048] When ranging to a target including premagnetized casing (also referred to as remanent magnetism), the magnetic field of the Earth \vec{B}_e may be subtracted, for example, as described above with respect to Equation 15. Alternatively, periodic variations in the measured magnetic field along the length (axis) of the drilling well may be used to separate the Earth's field from the target field. FIG. 6 depicts a plot of radial B_r and axial B_z magnetic field components versus measured depth for an example target well having a casing string premagnetized as described above. The components B_r and B_z are equivalent to the measured values of B_{xy} and B_z when the drilling well is approximately parallel to the target well (e.g., within about 10 degrees of parallel).

[0049] In embodiments in which the drilling well is a sufficient distance from the target well (e.g., greater than about one third of the axial distance between adjacent NN and SS opposing magnetic poles) the axial component B_z displays a single maximum or minimum between adjacent NN and SS poles. The maxima and minima of the axial component B_z correspond to the midpoints between the NN and SS poles where the target produces essentially no transverse magnetic field. Thus the values of BHS and BRS at these points may be taken to define the transverse component of the Earth's field. Conversely, maxima and minima of the transverse components BHS and BRS correspond to points opposite the NN and SS poles where the target produces essentially no axial

magnetic field. Thus the value of the axial component B_z at these points may be taken to define the axial component of the Earth's field.

[0050] In embodiments in which the drilling well is closer to the target well (e.g., less than about one third of the axial distance between adjacent NN and SS opposing magnetic poles), the axial component B_z may display multiple maxima and/or minima between adjacent NN and SS poles (e.g., two maxima and one minimum or two minima and one maximum. In such embodiments, the single maximum or single minimum about which the axial component is symmetrical corresponds to the midpoints between the NN and SS poles where the target produces essentially no transverse magnetic field. Thus the values of BHS and BRS at these points may be taken to define the transverse component of the Earth's field.

[0051] Upon removing the Earth's magnetic field, the distance to the target wellbore may be computed from the target magnetic field vector and the known pole strengths imparted to the target well. For example, the magnitude of the transverse component of the target magnetic field may be processed in combination with an empirical or theoretical model of the magnetic field about the target to compute the distance. Moreover, the high side and right side components of the target magnetic field may be processed to compute the distance and/or direction to the target well. U.S. Patent 7,617,049, which is incorporated by reference herein in its entirety, discloses other suitable methods for computing the distance and/or direction between a drilling well and a target well using magnetic ranging measurements.

[0052] The direction in the transverse plane to the target well may alternatively and/or additionally be obtained via plotting the high side and right side components BHS and BRS of the measured magnetic field. FIG. 7 depicts a plot of the high side BHS versus

right side *BRS* components of the measured magnetic field. The slope of the plot represents the tool face to target (TFT) direction (the direction to the target well in the transverse plane). The TFT may be determined in this way prior to removing the Earth's magnetic field from the measured magnetic field. FIG. 7 also depicts the maxima and minima of the transverse magnetic field component (the locations of the NN and SS poles). Moreover, the midpoint of the plot represents the transverse component of the Earth's magnetic field.

[0053] The casing string may include a residual remanent magnetism imparted during a magnetic particle inspection of the threaded ends of the casing tubulars. Magnetic ranging to such residual remanent magnetism is commonly referred to in the art as passive ranging. Such passive ranging can be challenging as the residual remanent magnetism tends to be highly localized at the ends of the casing tubulars, and consequently at the casing joints within the target wellbore. Moreover, the magnetic field strengths of the poles can be weak and unknown; therefore resulting in a magnetic field pattern that also tends to be unknown. Notwithstanding, magnetic ranging to target wells including residual remanent magnetism may be required, for example, when attempting to intercept the target well with a relief well, particularly when a close approach is used in a non-conductive formation such as salt, which tends to prevent the use of active ranging techniques.

[0054] Owing to the relatively low magnitude of the target magnetic field, passive ranging is generally utilized at close distances (e.g., within five meters or less of the target). At close distances, each pole may present a signature such as that depicted on FIG. 8 (which is a plot of the radial and axial components of the measured magnetic field versus axial position along the target well). The axial distance δz between opposing

peaks (maxima and minima) of the axial component may be used to estimate the distance to the target. For example, the target magnetic field may be approximated to be emanating from a monopole located at the casing joint (this may be a reasonable assumption since the residual remanent magnetism tends to be highly localized at the ends of the casing tubulars). The axial component of the target field B_{zt} may then be expressed mathematically, for example, as follows:

$$B_{zt} = \frac{P}{4\pi} \frac{z-z_0}{[d^2+(z-z_0)^2]^{1.5}} \quad (16)$$

[0055] where P represents the magnetic pole strength, d represents the radial distance to the target, z represents the axial position of the magnetic field sensor, and z_0 represents the axial position of the magnetic source (e.g., the joint between adjacent casing tubulars). Equation 16 may be differentiated with respect to the axial direction, for example, as follows:

$$\frac{dB_{zt}}{dz} = \frac{P}{4\pi} \frac{d^2-2(z-z_0)^2}{[d^2+(z-z_0)^2]^{2.5}} \quad (17)$$

[0056] The axial positions of the maximum and minimum may be obtained by setting Equation 17 to zero which yields $d^2 = 2(z - z_0)^2$. Assuming from FIG. 8 that $\delta z = 2(z - z_0)$ yields the following expression for the distance between the drilling well and the target well:

$$d = \sqrt{2}(z - z_0) = \delta z / \sqrt{2} \quad (18)$$

[0057] It will be understood that the methodology described above with respect to Equations 16-18 and FIG. 8 does not necessarily require the Earth's magnetic field to be removed from the magnetic field measurements. The direction in the transverse plane to the target well may be obtained via plotting the high side and right side components BHS and BRS of the measured magnetic field as described above with respect to FIG. 7. Such

processing may also be performed without removing the Earth's magnetic field from the measured magnetic field.

[0058] The target magnetic field may also be obtained by removing the Earth's magnetic field \vec{B}_e , for example, as describe above with respect to Equation 15. The target magnetic field may then be processed to compute the distance and/or the direction (e.g., the TFT) to the target well, for example, using the one or more of the techniques disclosed in U.S. Patent 6,985,814, which is incorporated by reference herein in its entirety.

[0059] The target well may alternatively and/or additionally include a direct current (DC) electromagnetic source deployed therein. The electromagnetic source, such as a solenoid, may be moved along the axis of the target during the drilling operation and may further be controlled during drilling, for example, via switching the source on or off, varying its intensity, or reversing its polarity.

[0060] The target magnetic field may be found, for example, from the difference between measurements taken with the source excited in two different states such as two opposing polarities (e.g., positively and negatively directed current in the solenoid). The three components of the target magnetic field vector (B_{HS} , B_{RS} , and B_z of the target) may be resolved into distance and direction by inversion of models or maps of the field around the target.

[0061] The Earth's field may be found from a measurement taken with the source switched off, or from the average of two measurements in which the source was excited with equal amplitude in two opposing polarities. Measurement of the Earth's field components in this way may be used to ascertain the attitude of the receiver by the use of standard relationships well known in magnetic wellbore surveying.

MAGNETIC RANGING TO AN AC TARGET

[0062] FIG. 9 depicts a flow chart of another disclosed method embodiment 120. A sensor sub including a magnetic field sensor (such as a tri-axial magnetometer set) is rotated in a drilling wellbore at 122 in sensory range of AC magnetic flux emanating from a target wellbore (note that the sensor sub may optionally, but does not necessarily, include accelerometers). Magnetic sensor measurements are acquired at 124 while rotating in 122 to obtain a magnetic field vector. The measured magnetic field vector is processed at 126 to compute at least one of (i) the amplitude of the transverse component of the AC magnetic flux emanating from the target wellbore and (ii) the angle between the transverse component of the AC magnetic flux emanating from the target wellbore and the transverse component of the Earth's magnetic field. The computed quantity (or quantities) may then be further processed at 128 to compute at least one of a distance and a direction from the drilling well to the target well.

[0063] The disclosed magnetic ranging embodiments may be utilized with a magnetic target including substantially any suitable AC magnetization. In such operations the target well may include an electromagnet powered by an alternating current (AC) power source. The magnetic field about an AC target B_T may be expressed mathematically, for example, as follows:

$$B_T = B_{Ta} \sin(\omega t + \phi) \quad (19)$$

[0064] where B_{Ta} represents the amplitude of the magnetic field, ω represents the known frequency, and ϕ represents an arbitrary phase. When in sensory range of the target, the axial (z-axis) magnetic field B_z may be expressed as follows:

$$B_z = B_{ez} + B_{Tz} \quad (20)$$

[0065] where B_{ez} represents the axial component of the Earth's field and B_{Tz} represents the axial component of the target AC field. It will be understood from Equation 20 that the mean value (the DC value) of B_z is equal to B_{ez} and that the periodic variations from the mean may be used to compute the amplitude and phase of B_{Tz} . When magnetic field measurements are acquired over an interval of several cycles (preferably over an integer number of cycles – which may be readily achieved since the source frequency is known), the mean value of a set of measured B_z measurements represents the axial component of the Earth's field. Thus, subtracting the mean value from each individual B_z measurement gives the corresponding B_{Tz} . These operations may be expressed mathematically, for example, as follows:

$$B_{zm} = \frac{\sum B_z}{N} = B_{ez} \quad (21)$$

$$B_{Tz} = B_z - B_{zm} \quad (22)$$

[0066] where B_{zm} represents the mean value of a set of B_z measurements. The standard deviation of the set of B_z measurements represents the root mean square (rms) amplitude of B_{Tz} . The amplitude B_{za} of B_z may thus be found by multiplying the root mean square value by the square root of two and the phase information $\sin(\omega t + \phi)$ may be found by dividing B_{Tz} by B_{za} . These operations may be expressed mathematically, for example, as follows

$$B_{Tzrms} = \sigma(B_z) \quad (23)$$

$$B_{za} = \sqrt{2} B_{Tzrms} \quad (24)$$

$$\sin(\omega t + \phi) = \frac{B_{Tz}}{B_{za}} \quad (25)$$

[0067] where B_{Tzrms} represents the root mean square amplitude of B_z and $\sigma(\cdot)$ represents the standard deviation. While Equations 19, 24 and 25 may imply that the

target field B_T is sinusoidal, the disclosed embodiments are expressly not limited in this regard. In practice the target field may deviate from a sine wave, as nonlinearity and hysteresis of ferromagnetic materials in the solenoid core and target casing may distort the waveform of the magnetic field (even when the input AC current is perfectly sinusoidal). The deviation of the magnetic field from a sine wave may be modeled or measured and suitable corrections made, if necessary.

[0068] FIG. 10 depicts the transverse (xy) magnetic field vectors. Note that the transverse alternating magnetic field \vec{B}_{xy} measured by the rotating x- and y-axis magnetic field sensors is the vector sum the transverse components of the Earth's magnetic field vector \vec{B}_{exy} and the target well's magnetic field vector \vec{B}_{Txy} . The target field oscillates between positive and negative maxima $\vec{B}_{Txy}(\phi)$ and $\vec{B}_{Txy}(\phi + \pi)$ at a frequency ω . As such the measured field also oscillates at a frequency ω (e.g., between $\vec{B}_{xy}(\phi)$ and $\vec{B}_{xy}(\phi + \pi)$ as indicated). The aforementioned vector sum of the transverse components may be expressed mathematically, for example, as follows:

$$\vec{B}_{xy}(\phi) = \vec{B}_{exy} + \vec{B}_{Txy}(\phi) \quad (26)$$

[0069] With continued reference to FIG. 10, the magnitude of the transverse component of the measured magnetic field B_{xy} may be expressed mathematically, for example, as follows (using the law of cosines):

$$B_{xy} = \sqrt{(B_{exy}^2 + B_{Txy}^2 - 2B_{exy}B_{Txy} \cos \theta)} \quad (27)$$

[0070] where B_{exy} represents the magnitude of the transverse component of the Earth's field, B_{Txy} represents the magnitude of the transverse component of the target field, and θ represents the angle between the transverse components of the Earth's magnetic field

vector and the target magnetic field vector. The direction of the transverse component of the measured magnetic field vector B_{xy} diverges from the transverse component Earth's magnetic field vector B_{exy} by the angle α where (using the law of sines):

$$\sin \alpha = \frac{B_{Txy} \cdot \sin \theta}{B_{xy}} \quad (28)$$

[0071] It will thus be understood that both the amplitude and direction of the measured transverse component oscillate with the target field, for example, as follows:

$$B_{Txy} = B_{Txya} \sin(\omega t + \phi) \quad (29)$$

[0072] where B_{Txya} represents the amplitude of the transverse magnetic field from the target and where at any time t the corresponding value of $\sin(\omega t + \phi)$ may be obtained from the axial measurement (even when the magnetic field is non-sinusoidal). The magnitude of the transverse component of the measured magnetic field can be computed from the x- and y-axis magnetometer measurements (e.g., $B_{xy}^2 = B_x^2 + B_y^2$). Combining Equations 27 and 29 enables the magnitude of the transverse component of the measured magnetic field to be expressed as a quadratic function of the phase $\sin(\omega t + \phi)$, for example, as follows:

$$B_{xy}^2 = B_{Txya}^2 \sin^2(\omega t + \phi) - 2 B_{xye} B_{Txya} \cos \theta \sin(\omega t + \phi) + B_{xye}^2 \quad (30)$$

[0073] Since $\sin(\omega t + \phi)$ is known at any instant in time from the axial magnetic field measurements (Equation 25), and since corresponding values of B_{xy} are measured, a standard least-squares fit may be applied to determine the quadratic coefficients B_{Txya}^2 , $2B_{xye}B_{Txya} \cos \theta$, and B_{xye}^2 , from which B_{Txya} , B_{exy} , and θ may be determined. These parameters may then be used to obtain the distance and direction to the target well as described in more detail below.

[0074] The coefficients in a quadratic equation $y = a \cdot x^2 + b \cdot x + c$ may be found, for example, as follows when x and y are known:

$$\begin{bmatrix} a \\ b \\ c \end{bmatrix} = \begin{bmatrix} \Sigma x^4 & \Sigma x^3 & \Sigma x^2 \\ \Sigma x^3 & \Sigma x^2 & \Sigma x \\ \Sigma x^2 & \Sigma x & N \end{bmatrix}^{-1} \times \begin{bmatrix} \Sigma x^2 y \\ \Sigma xy \\ \Sigma y \end{bmatrix} \quad (31)$$

[0075] where $y = B_{xy}^2$, $x = \sin(\omega t + \phi)$, and $\Sigma(\cdot)$ indicates a sum over a predetermined number of measurements. For example, measurements may be acquired at 10 millisecond intervals for 30 seconds to obtain 3000 accelerometer and magnetometer measurements. In an embodiment in which the AC frequency is 10 Hz these measurements span 300 cycles.

[0076] It will be understood that the foregoing discussion has assumed that the AC magnetic field emanating from the target is substantially sinusoidal. However, the disclosed embodiments are not limited in this regard. In practice, when ranging to an AC solenoid, the received magnetic field may be non-sinusoidal. While the solenoid may be driven by a sinusoidal current, nonlinear behavior of ferromagnetic materials in the solenoid core and/or in the casing may cause the emitted AC magnetic field to be non-sinusoidal. In particular, the magnetic field may contain a third harmonic corresponding to a depression of the peak values resulting from material nonlinearity as magnetic saturation is approached.

[0077] A non-sinusoidal magnetic field may result in biased ranging results unless compensation is made. The waveform of the target magnetic field can be determined from the measured axial component, or from measurements of transverse components during intervals of non-rotation of the magnetic sensors. Corrections for harmonics (such as the above described third harmonic) may then be made by modeling their effect or by experiments conducted at the surface. Alternatively, the solenoid may be driven by a

non-sinusoidal current whose waveform is adjusted to produce a sinusoidal magnetic field at the receiver. The waveform may be determined by modeling, by experiments conducted at the surface, or by feedback from real-time measurements of the received magnetic waveforms. The disclosed embodiments are not limited in this regard.

[0078] For example, a method for magnetic ranging may include deploying a magnetic field sensor in sensory range of magnetic flux emanating from a ferromagnetic casing string having an AC magnetic source deployed therein. The casing may be deployed at the surface or in a target well. Magnetic field measurements may be processed to compute an amplitude of at least one higher order harmonic of the AC magnetic field. The AC magnetic source may then be energized with a non-sinusoidal input electrical current to reduce (or eliminate) the amplitude of the higher order harmonic.

[0079] The above described magnetic ranging technique tends to be effective when the magnitude of B_{xy} is a strong function of the target field; i.e., when the angle θ in FIG. 10 is small (e.g., less than about 45 degrees). This may be the case when drilling twin well pairs for SAGD applications in northern latitudes (where the magnetic dip angle is high). However, when the angle between these components is large (e.g., greater than about 45 degrees), the magnitude of B_{xy} is less dependent on the target field and thus it may be beneficial to alternatively and/or additionally examine the oscillating direction α . The direction α may be observed as a regular variation in apparent rotary speed calculated using x- and y- axis magnetometers.

[0080] FIG. 11 depicts a flow chart of yet another disclosed method embodiment 140. A sensor sub including a magnetic field sensor (such as a tri-axial magnetometer set) is rotated in a drilling wellbore at 142 in sensory range of AC magnetic flux emanating from a target wellbore (note that the sensor sub may optionally, but does not necessarily

include accelerometers). Magnetic sensor measurements are acquired at 144 while rotating in 142 to obtain a magnetic field vector. The measured magnetic field vector is processed at 146 to compute a difference between an instantaneous rotation rate and an average rotation rate of the sensor sub. The computed difference is processed at 148 to compute a direction from the drilling well to the target well. The difference may be optionally further processed at 150 to compute a distance to the target well.

[0081] At each instant (i.e., at each magnetometer measurement interval – such as 10 millisecond), an apparent magnetic toolface may be computed, for example, as described above with respect to FIG. 2 ($M = \tan^{-1}(B_x/B_y)$). The instantaneous rotary speed rpm_t may be computed from the difference between successive toolface values, for example, as follows:

$$rpm_t = \frac{60s}{(2\pi)} [\text{mod}(M_t - M_{t-1} + \pi, 2\pi) - \pi] \quad (32)$$

[0082] where s represents the magnetometer sample rate (measurement interval). It will be understood that the magnetic toolface M is measured with respect to the transverse component of the measured magnetic field (i.e., \vec{B}_{xy}). As described above with respect to FIG. 10, the direction of \vec{B}_{xy} is offset from the transverse component of the Earth's magnetic field \vec{B}_{exy} by the angle α which varies at frequency ω . Thus, the calculated instantaneous rotary speed is directly affected by the rate of change of the reference direction, which may be expressed mathematically, for example, as follows:

$$rpm_t = rpm_{avg} - \frac{60s}{(2\pi)} \cdot \frac{\partial \alpha}{\partial t} \quad (33)$$

[0083] where rpm_{avg} represents the average rotary speed determined, for example, via Equation 14 and $\partial \alpha / \partial t$ represents the rate of change of the angle α which may be

evaluated by applying the law of sines to the diagram on FIG. 10, for example, as follows:

$$\frac{\sin \alpha}{B_{Txy}} = \frac{\sin(\theta + \alpha)}{B_{exy}} \quad (34)$$

[0084] from which it follows that:

$$\tan \alpha = \frac{B_{Txy} \sin \theta}{B_{exy} - B_{Txy} \cos \theta} \quad (35)$$

[0085] Differentiating Equation 35 yields:

$$\frac{\partial \alpha}{\partial t} = \frac{\partial \alpha}{\partial B_{Txy}} \frac{\partial B_{Txy}}{\partial t} = \frac{B_{exy} B_{Txy} a \cdot \omega \cos(\omega t + \phi) \sin \theta}{(B_{exy}^2 + B_{Txy}^2 - 2B_{exy} B_{Txy} \cos \theta)} \quad (36)$$

[0086] From Equation 33 the deviation of the measured rotary speed from the average rotary speed Δrpm may be given as follows:

$$\Delta rpm = -\frac{60}{(2\pi)} \cdot \frac{\partial \alpha}{\partial t} \quad (37)$$

[0087] Substituting Equation 36 into Equation 37 yields:

$$\Delta rpm = -\frac{60}{(2\pi)} \cdot \frac{B_{exy} B_{Txy} a \cdot \omega \cos(\omega t + \phi) \sin \theta}{B_{exy}^2 + B_{Txy}^2 - 2B_{exy} B_{Txy} \cos \theta} \quad (38)$$

[0088] In many magnetic ranging operations to an AC target, it may be assumed that the Earth's field B_{exy} is much larger than the target field B_{Txya} such that Equation 37 may be simplified, for example, as follows:

$$\Delta rpm \approx -\frac{60}{(2\pi)} \cdot \frac{B_{Txya} \cdot \sin \theta}{B_{exy}} \omega \cos(\omega t + \phi) \quad (39)$$

[0089] Note that in Equation 39 the deviation (or variation) in the measured rotary speed Δrpm is sinusoidal (proportional to $\cos(\omega t + \phi)$) at the AC excitation frequency ω with an amplitude equal to $B_{Txya} \cdot \sin \theta / B_{exy}$. The amplitude is proportional B_{Txya} and may thus be related to the distance from the drilling well to the target well (e.g., using

one or more of the above described methods). Moreover, the Earth's field B_{exy} may be known from other measurements.

[0090] In many ranging operations employing an AC target, it may be advantageous to employ both of the above described methodologies (the first based on the magnitude of B_{xy} described with respect to Equations 27-30 and the second based on the oscillating direction described with respect to Equations 31-38). For example, the first methodology may be employed to obtain values of B_{Txya} and θ while the second methodology may be employed to obtain the sign (positive or negative) of $\sin\theta$ which indicates whether the target is to the right or left of the drilling well. Alternatively, both methodologies may be employed simultaneously to provide a more robust solution for B_{Txya} and θ (i.e., a solution having reduced noise).

[0091] The three components of the AC target magnetic field (B_{Txya} , θ , and B_{za} of the target) may be resolved into distance and direction by inversion of models or maps of the field around the target. For example, the amplitude of the transverse component of the target field B_{Txya} may be resolved into distance using an empirical or theoretical model or map of the target field and the angle θ between the Earth's field and the target field may be resolved into a toolface to target direction, for example, as follows:

$$TFT = \theta + (T - M) \quad (40)$$

[0092] where TFT represents the toolface to target direction in the transverse plane and $(T - M)$ represents the above described toolface offset that may be measured, for example, using Equation 9 at times when the AC target is not energized.

[0093] It will be understood that while not shown in FIGS. 1 and 2, downhole measurement tools suitable for use with the disclosed embodiments generally include at

least one electronic controller. Such a controller may include signal processing circuitry including a digital processor (a microprocessor), an analog to digital converter, and processor readable memory. The controller may also include processor-readable or computer-readable program code embodying logic, including instructions for computing various parameters as described above, for example, with respect to the disclosed mathematical equations. One skilled in the art will also readily recognize some of the above mentioned equations may also be solved using hardware mechanisms (e.g., including analog or digital circuits).

[0094] A suitable controller may include a timer including, for example, an incrementing counter, a decrementing time-out counter, or a real-time clock. The controller may further include multiple data storage devices, various sensors, other controllable components, a power supply, and the like. The controller may also optionally communicate with other instruments in the drill string, such as telemetry systems that communicate with the surface or an EM (electro-magnetic) shorthop that enables the two-way communication across a downhole motor. It will be appreciated that the controller is not necessarily located in the sensor sub (e.g., sub 60), but may be disposed elsewhere in the drill string in electronic communication therewith. Moreover, one skilled in the art will readily recognize that the multiple functions described above may be distributed among a number of electronic devices (controllers).

[0095] Although magnetic ranging while rotating and certain advantages thereof have been described in detail, it should be understood that various changes, substitutions and alternations can be made herein without departing from the spirit and scope of the disclosure as defined by the appended claims.

CLAIMS

What is claimed is:

1. A method for magnetic ranging comprising:
 - (a) rotating a downhole drilling tool in a drilling well in sensory range of magnetic flux emanating from a target well, the downhole tool including a magnetometer set and an accelerometer set rotatably coupled to the tool;
 - (b) causing the magnetometer set and the accelerometer set to acquire corresponding magnetometer measurements and accelerometer measurements while rotating in (a);
 - (c) transforming the magnetometer measurements acquired in (b) to a rotation independent reference frame to obtain rotation invariant measurements;
 - (d) processing the rotation invariant measurements to compute at least one of a distance and a direction from the drilling well to the target well.

2. The method of claim 1, wherein the magnetometer set comprises a tri-axial set of magnetometers and the accelerometer set comprises a tri-axial set of accelerometers.

3. The method of claim 1, wherein the rotation independent reference frame comprises an axial component, a high side component, and a right side component of the magnetometer measurements acquired in (b).

4. The method of claim 3, wherein the high side component BHS and the right side component BRS are obtained using the following equations:

$$BHS = B_{xy} \cdot \cos(T - M)$$

$$BRS = B_{xy} \cdot \sin(T - M)$$

wherein B_{xy} represents a magnitude of a transverse component of the magnetometer measurements acquired in (b) and $(T - M)$ represents a toolface offset of the transverse component of the magnetometer measurements acquired in (b).

5. The method of claim 1, wherein the rotation independent reference frame comprises an axial component, a magnitude of a transverse component, and a toolface offset of the transverse component of the magnetometer measurements acquired in (b).

6. The method of claim 5, wherein:

the magnitude of the transverse component B_{xy} is computed using at least one of the following equations:

$$B_{xy} = \sqrt{(B_x^2 + B_y^2)}$$

$$B_{xy} = \sqrt{2 \cdot \sigma(B_x) \cdot \sigma(B_y)}$$

and the toolface offset of the transverse component $(T - M)$ is computed using the following equation:

$$(T - M) = \tan^{-1} \left[\frac{(B_x \cdot A_y - B_y \cdot A_x)}{(-B_x \cdot A_x - B_y \cdot A_y)} \right]$$

wherein A_x and A_y represent transverse accelerometer measurements acquired in (b), B_x and B_y represent transverse magnetometer measurements acquired in (b), and

$\sigma(B_x)$ and $\sigma(B_y)$ represent standard deviations of corresponding sets of B_x and B_y measurements.

7. The method of claim 1, wherein the rotation invariant measurements are transmitted to a surface location and the processing in (d) is performed at the surface location.

8. A method for magnetic ranging comprising:

(a) rotating a downhole drilling tool in a drilling well in sensory range of magnetic flux emanating from a target well having a magnetized casing string, the downhole tool including a magnetometer set and an accelerometer set rotatably coupled to the tool;

(b) causing the magnetometer set and the accelerometer set to acquire corresponding magnetometer measurements and accelerometer measurements while rotating in (a);

(c) transforming the magnetometer measurements acquired in (b) to a rotation independent reference frame to obtain rotation invariant measurements;

(d) processing the rotation invariant measurements to compute at least one of a distance and a direction from the drilling well to the target well.

9. The method of claim 8, wherein the magnetized casing string comprises an alternating pattern of magnetically opposing north-north (NN) poles and magnetically opposing south-south (SS) poles spaced apart along an axis of the target well.

10. The method of claim 9, wherein (d) comprises (i) acquiring a model that relates the rotation invariant measurements to a distance from the drilling well to the target well and (ii) processing the rotation invariant measurements in combination with the model acquired in (i) to determine the distance from the drilling well to the target well.

11. The method of claim 9, wherein the processing in (d) comprises (i) subtracting a magnetic field of the Earth from the rotation invariant measurements obtained in (c) to obtain a target magnetic field and (ii) processing target magnetic field to compute at least one of the distance and the direction from the drilling well to the target well.

12. The method of claim 11, wherein (ii) comprises processing high side and right side components of the target magnetic field to compute the distance and the direction from the drilling well to the target well.

13. The method of claim 11, wherein:

a transverse component of the magnetic field of the Earth is obtained at a location of maximum or minimum axial magnetic field; and

an axial component of the magnetic field of the Earth is obtained at a location of maximum or minimum transverse magnetic field.

14. The method of claim 9, wherein the processing in (d) comprises (i) processing a high side component and a right side component of the rotation invariant

measurements to compute a slope and (ii) relating the slope to the direction from the drilling well to the target well.

15. The method of claim 8, wherein the target well comprises ferromagnetic casing having residual remanent magnetism at casing joints therein.

16. The method of claim 15, wherein the processing in (d) comprises (i) processing the magnetometer measurements acquired in (b) to obtain an axial separation between an adjacent maximum and minimum of an axial component of the magnetometer measurements and (ii) processing the axial separation to compute the distance from the drilling well to the target well.

17. The method of claim 16, wherein the distance from the drilling well to the target well is computed using the following equation:

$$d = \delta z / \sqrt{2}$$

wherein d represents the distance from the drilling well to the target well and δz represents the axial separation.

18. The method of claim 15, wherein the processing in (d) comprises (i) processing a high side component and a right side component of the rotation invariant measurements to compute a slope and (ii) relating the slope to the direction from the drilling well to the target well.

19. The method of claim 15, wherein the processing in (d) comprises (i) subtracting a magnetic field of the Earth from the rotation invariant measurements obtained in (c) to obtain a target magnetic field and (ii) processing target magnetic field to compute at least one of the distance and the direction from the drilling well to the target well.

20. A method for magnetic ranging comprising:

(a) rotating a downhole drilling tool in a drilling well in sensory range of magnetic flux emanating from a target well having an electromagnet deployed therein, the downhole tool including a magnetometer set and an accelerometer set rotatably coupled to the tool;

(b) causing the magnetometer set and the accelerometer set to acquire corresponding magnetometer measurements and accelerometer measurements while rotating in (a);

(c) transforming the magnetometer measurements acquired in (b) to a rotation independent reference frame to obtain rotation invariant measurements;

(d) processing the rotation invariant measurements to compute at least one of a distance and a direction from the drilling well to the target well.

21. The method of claim 20, wherein (d) comprises (i) acquiring a model that relates the rotation invariant measurements to a distance from the drilling well to the target well and (ii) processing the rotation invariant measurements in combination with the model acquired in (i) to determine the distance from the drilling well to the target well.

22. The method of claim 20, wherein the processing in (d) comprises (i) subtracting a magnetic field of the Earth from the rotation invariant measurements obtained in (c) to obtain a target magnetic field and (ii) processing the target magnetic field to compute at least one of the distance and the direction from the drilling well to the target well.

23. The method of claim 22, wherein the magnetic field of the Earth is measured in (b) when the electromagnet is de-energized.

24. The method of claim 20, wherein:

(b) and (c) in combination further comprise obtaining a first set of rotation invariant measurements when the electromagnet is energized with a first polarity and a second set of rotation invariant measurements when the electromagnet is energized with a second opposing polarity; and

(d) comprises (i) processing a difference between the first and second sets of rotation invariant measurements to compute a target magnetic field and (ii) processing the target magnetic field to compute at least one of the distance and the direction from the drilling well to the target well.




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8





FIG. 9

6/6

FIG. 10



140




FIG. 11

INTERNATIONAL SEARCH REPORT

International application No.
PCT/US2015/037875**A. CLASSIFICATION OF SUBJECT MATTER****E21B 47/09(2006.01)i, G01V 3/18(2006.01)i, G01V 3/38(2006.01)i**

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

E21B 47/09; G06G 7/48; G01V 3/00; E21B 10/00; G01V 3/26; G01V 3/10; E21B 47/022; G01V 3/18; G01V 3/38

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Korean utility models and applications for utility models

Japanese utility models and applications for utility models

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

eKOMPASS(KIPO internal) & Keywords:

magnetic ranging, while rotating, magnetometer, accelerometer, distance, drilling well, target well

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	WO 2012-134468 A1 (HALLIBURTON ENERGY SERVICES, INC. et al.) 04 October 2012 See page 2, line 22 - page 5, line 8; and figures 1-2.	1-24
A	WO 2013-101587 A1 (SCHLUMBERGER CANADA LIMITED et al.) 04 July 2013 See paragraphs [0001], [0008]-[0012], [0039]-[0040]; and figure 6.	1-24
A	US 2013-0069655 A1 (MCELHINNEY et al.) 21 March 2013 See paragraphs [0002], [0008]-[0012], [0035]; and figure 4.	1-24
A	US 2006-0106587 A1 (RODNEY, PAUL F.) 18 May 2006 See paragraphs [0001], [0015]-[0019], [0052]-[0066]; and figure 4.	1-24
A	US 2014-0111210 A1 (FANG et al.) 24 April 2014 See paragraphs [0003], [0009]-[0011], [0046]; and figure 6.	1-24

 Further documents are listed in the continuation of Box C. See patent family annex.

* Special categories of cited documents:

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier application or patent but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

08 September 2015 (08.09.2015)

Date of mailing of the international search report

09 September 2015 (09.09.2015)

Name and mailing address of the ISA/KR

International Application Division
Korean Intellectual Property Office
189 Cheongsu-ro, Seo-gu, Daejeon Metropolitan City, 35208,
Republic of Korea

Facsimile No. +82-42-472-7140

Authorized officer

LEE, Jong Kyung

Telephone No. +82-42-481-3360



INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No.

PCT/US2015/037875

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO 2012-134468 A1	04/10/2012	EP 2691797 A1 US 2014-0035586 A1	05/02/2014 06/02/2014
WO 2013-101587 A1	04/07/2013	CA 2862256 A1 US 2013-0173164 A1	04/07/2013 04/07/2013
US 2013-0069655 A1	21/03/2013	CA 2782921 A1 GB 2492666 A GB 2492666 B MX 2012008366 A US 8947094 B2	18/01/2013 09/01/2013 18/03/2015 26/08/2013 03/02/2015
US 2006-0106587 A1	18/05/2006	US 2010-0250207 A1 US 7650269 B2 US 8170851 B2	30/09/2010 19/01/2010 01/05/2012
US 2014-0111210 A1	24/04/2014	WO 2014-093096 A1	19/06/2014