



- (51) **International Patent Classification:**
H04N 19/30 (2014.01) *H04N 19/70* (2014.01)
- (21) **International Application Number:**
PCT/JP2014/003721
- (22) **International Filing Date:**
14 July 2014 (14.07.2014)
- (25) **Filing Language:** English
- (26) **Publication Language:** English
- (30) **Priority Data:**
61/846,056 14 July 2013 (14.07.2013) US
61/847,462 17 July 2013 (17.07.2013) US
- (71) **Applicant:** SHARP KABUSHIKI KAISHA [JP/JP]; 22-22, Nagaike-cho, Abeno-ku, Osaka-shi, Osaka, 5458522 (JP).
- (72) **Inventors:** DESHPANDE, Sachin G.. MISRA, Kiran.
- (74) **Agent:** HARA KENZO WORLD PATENT & TRADE-MARK; Daiwa Minamimorimachi Building, 2-6, Tenjin-

bashi 2-chome Kita, Kita-ku, Osaka-shi, Osaka, 5300041 (JP).

- (81) **Designated States** (*unless otherwise indicated, for every kind of national protection available*): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LT, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.
- (84) **Designated States** (*unless otherwise indicated, for every kind of regional protection available*): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV,

[Continued on next page]

(54) **Title:** TILE ALIGNMENT SIGNALING AND CONFORMANCE CONSTRAINTS

(57) **Abstract:** This invention introduces a variant in a video parameter set extension syntax element which allows more flexible signaling regarding tile alignment between each layer with respect to the layers it directly depends on.

vps_extension() {	Descriptor
while(1byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avo_base_layer_flag	u(1)
splitting_flag	u(1)
for(i = 0; NumScalabilityTypes = 0; i < 16; i++) {	
scalability_mask[i]	u(1)
NumScalabilityTypes += scalability_mask[i]	
}	
for(j = 0; j < (NumScalabilityTypes - splitting_flag); j++)	
dimension_id_len_minus1[j]	u(3)
vps_nuh_layer_id_present_flag	u(1)
for(i = 1; i <= vps_max_layers_minus1; i++) {	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
if(!splitting_flag)	
for(j = 0; j < NumScalabilityTypes; j++)	
dimension_id[i][j]	u(v)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++)	
direct_dependency_flag[i][j]	u(1)
for(i = 0; i < vps_max_layers_minus1; i++)	
max_tid_ref_plus1[i]	u(3)
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++)	
reflayer_file_boundaries_aligned_flag[i][j]	u(1)
.....	

FIG. 56



MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK,
SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ,
GW, KM, ML, MR, NE, SN, TD, TG).

— *as to the applicant's entitlement to claim the priority of
the earlier application (Rule 4.17(iii))*

Declarations under Rule 4.17:

— *as to applicant's entitlement to apply for and be granted
a patent (Rule 4.17(ii))*

Published:

— *with international search report (Art. 21(3))*

Description

Title of Invention: TILE ALIGNMENT SIGNALING AND CONFORMANCE CONSTRAINTS

Technical Field

[0001] The present disclosure relates generally to electronic devices.

Background Art

[0002] Electronic devices have become smaller and more powerful in order to meet consumer needs and to improve portability and convenience. Consumers have become dependent upon electronic devices and have come to expect increased functionality. Some examples of electronic devices include desktop computers, laptop computers, cellular phones, smart phones, media players, integrated circuits, etc.

[0003] Some electronic devices are used for processing and displaying digital media. For example, portable electronic devices now allow for digital media to be consumed at almost any location where a consumer may be. Furthermore, some electronic devices may provide download or streaming of digital media content for the use and enjoyment of a consumer.

Summary of Invention

Technical Problem

[0004] The increasing popularity of digital media has presented several problems. For example, efficiently representing high-quality digital media for storage, transmittal and rapid playback presents several challenges. As can be observed from this discussion, systems and methods that represent digital media efficiently with improved performance may be beneficial.

Solution to Problem

[0005] According to the present invention, there is provided a method for decoding video comprising: (a) decoding a plurality of frames of said video, wherein each of said frames belong to a different one of a plurality of layers and have at least one of (1) a same temporal time in a corresponding decoded said video and (2) a different temporal time in a corresponding decoded said video, (b) receiving a video parameter set extension syntax providing information used for said decoding of said layers, wherein said information includes a tile boundary aligned flag for direct reference layers of said different layers.

[0006] The foregoing and other objectives, features, and advantages of the invention will be more readily understood upon consideration of the following detailed description of the invention, taken in conjunction with the accompanying drawings.

Brief Description of Drawings

- [0007] [fig.1A]Figure 1A is a block diagram illustrating an example of one or more electronic devices in which systems and methods for sending a message and buffering a bitstream may be implemented;
- [fig.1B]Figure 1B is another block diagram illustrating an example of one or more electronic devices in which systems and methods for sending a message and buffering a bitstream may be implemented;
- [fig.2]Figure 2 is a flow diagram illustrating one configuration of a method for sending a message;
- [fig.3]Figure 3 is a flow diagram illustrating one configuration of a method for determining one or more removal delays for decoding units in an access unit;
- [fig.4]Figure 4 is a flow diagram illustrating one configuration of a method for buffering a bitstream;
- [fig.5]Figure 5 is a flow diagram illustrating one configuration of a method for determining one or more removal delays for decoding units in an access unit;
- [fig.6A]Figure 6A is a block diagram illustrating one configuration of an encoder 604 on an electronic device;
- [fig.6B]Figure 6B is another block diagram illustrating one configuration of an encoder 604 on an electronic device;
- [fig.7A]Figure 7A is a block diagram illustrating one configuration of a decoder on an electronic device;
- [fig.7B]Figure 7B is another block diagram illustrating one configuration of a decoder on an electronic device;
- [fig.8]Figure 8 illustrates various components that may be utilized in a transmitting electronic device;
- [fig.9]Figure 9 is a block diagram illustrating various components that may be utilized in a receiving electronic device;
- [fig.10]Figure 10 is a block diagram illustrating one configuration of an electronic device in which systems and methods for sending a message may be implemented; and
- [fig.11]Figure 11 is a block diagram illustrating one configuration of an electronic device in which systems and methods for buffering a bitstream may be implemented.
- [fig.12]Figure 12 is a block diagram illustrating one configuration of a method for operation of a decoded picture buffer.
- [fig.13]FIGS. 13A-13C illustrates different NAL Unit header syntax.
- [fig.14]FIG. 14 illustrates a general NAL Unit syntax.
- [fig.15]FIG. 15 illustrates an existing video parameter set.
- [fig.16]FIG. 16 illustrates existing scalability types.

[fig.17]FIG. 17 illustrates an exemplary video parameter set.

[fig.18]FIG. 18 illustrates an exemplary scalability map syntax.

[fig.19]FIG. 19 illustrates an exemplary video parameter set.

[fig.20]FIG. 20 illustrates an existing video parameter set.

[fig.21]FIG. 21 illustrates an existing dimension type, dimension id syntax.

[fig.22]FIG. 22 illustrates an exemplary video parameter set.

[fig.23]FIG. 23 illustrates an exemplary scalability map syntax.

[fig.24]FIG. 24 illustrates an exemplary video parameter set.

[fig.25]FIG. 25 illustrates an exemplary video parameter set.

[fig.26]FIG. 26 illustrates an exemplary video parameter set.

[fig.27]FIG. 27 illustrates an exemplary scalability mask syntax.

[fig.28]FIG. 28 illustrates an exemplary video parameter set extension syntax.

[fig.29]FIG. 29 illustrates an exemplary video parameter set extension syntax.

[fig.30]FIG. 30 illustrates an exemplary video parameter set extension syntax.

[fig.31]FIG. 31 illustrates an exemplary video parameter set extension syntax.

[fig.32]FIG. 32 illustrates an exemplary video parameter set extension syntax.

[fig.33]FIG. 33 illustrates an exemplary video parameter set extension syntax.

[fig.34A]FIG. 34A illustrates an exemplary video parameter extension syntax.

[fig.34B]FIG. 34B illustrates an exemplary video parameter extension syntax.

[fig.35A]FIG. 35A illustrates an exemplary op_dpb_info_parameters(j) syntax.

[fig.35B]FIG. 35B illustrates an exemplary op_dpb_info_parameters(j) syntax.

[fig.36]FIG. 36 illustrates another exemplary video parameter extension syntax.

[fig.37]FIG. 37 illustrates another exemplary oop_dpb_info_parameters(j) syntax.

[fig.38]FIG. 38 illustrates another exemplary oop_dpb_info_parameters(j) syntax.

[fig.39]FIG. 39 illustrates an exemplary num_dpb_info_parameters syntax.

[fig.40]FIG. 40 illustrates another exemplary oop_dpb_info_parameters(j) syntax.

[fig.41]FIG. 41 illustrates another exemplary num_dpb_info_parameters syntax.

[fig.42]FIG. 42 illustrates another exemplary num_dpb_info_parameters syntax.

[fig.43]FIG. 43 illustrates another exemplary video parameter extension syntax and layer_dpb_info(i).

[fig.44]FIG. 44 illustrates an exemplary oop_dpb_info_parameters and layer_dpb_info(i) syntax.

[fig.45]FIG. 45 illustrates a base layer and enhancement layers.

[fig.46]FIG. 46 illustrates an exemplary picture having multiple slices.

[fig.47]FIG. 47 illustrates another exemplary picture having multiple slices

[fig.48]FIG. 48 illustrates a picture with column and row boundaries.

[fig.49]FIG. 49 illustrates a picture with slices.

[fig.50]FIG. 50 illustrates an accuess unit with a base layer, enhancement layers, and

tiles.

[fig.51A]FIG. 51A illustrate an exemplary SPS syntax.

[fig.51B]FIG. 51B illustrate an exemplary SPS syntax.

[fig.52A]FIG. 52A illustrate an exemplary vui syntax.

[fig.52B]FIG. 52B illustrate an exemplary vui syntax.

[fig.53]FIG. 53 illustrates an exemplary PPS syntax.

[fig.54A]FIG. 54A illustrate an exemplary VPS syntax.

[fig.54B]FIG. 54B illustrate an exemplary VPS syntax.

[fig.55]FIG. 55 illustrates an exemplary VPS extension syntax.

[fig.56]FIG. 56 illustrates an exemplary VPS extension syntax.

[fig.57]FIG. 57 illustrates an exemplary VPS extension syntax.

[fig.58]FIG. 58 illustrates an exemplary VPS extension syntax.

[fig.59]FIG. 59 illustrates an exemplary VPS extension syntax.

[fig.60]FIG. 60 illustrates an exemplary vui syntax.

[fig.61]FIG. 61 illustrates an exemplary vui syntax.

[fig.62]FIG. 62 illustrates an exemplary vui syntax.

[fig.63]FIG. 63 illustrates a replayer_tile_boundaries_aligned_flag operation.

[fig.64]FIG. 64 illustrates another replayer_tile_boundaries_aligned_flag operation.

Description of Embodiments

[0008] An electronic device for sending a message is described. The electronic device includes a processor and instructions stored in memory that is in electronic communication with the processor. The electronic device determines, when a Coded Picture Buffer (CPB) supports operation on a sub-picture level, whether to include a common decoding unit CPB removal delay parameter in a picture timing Supplemental Enhancement Information (SEI) message. The electronic device also generates, when the common decoding unit CPB removal delay parameter is to be included in the picture timing SEI message (or some other SEI message or some other parameter set e.g. picture parameter set or sequence parameter set or video parameter set or adaptation parameter set), the common decoding unit CPB removal delay parameter, wherein the common decoding unit CPB removal delay parameter is applicable to all decoding units in an access unit from the CPB. The electronic device also generates, when the common decoding unit CPB removal delay parameter is not to be included in the picture timing SEI message, a separate decoding unit CPB removal delay parameter for each decoding unit in the access unit. The electronic device also sends the picture timing SEI message with the common decoding unit CPB removal delay parameter or the decoding unit CPB removal delay parameters.

[0009] The common decoding unit CPB removal delay parameter may specify an amount of

sub-picture clock ticks to wait after removal from the CPB of an immediately preceding decoding unit before removing from the CPB a current decoding unit in the access unit associated with the picture timing SEI message.

- [0010] Furthermore, when a decoding unit is a first decoding unit in an access unit, the common decoding unit CPB removal delay parameter may specify an amount of sub-picture clock ticks to wait after removal from the CPB of a last decoding unit in an access unit associated with a most recent buffering period SEI message in a preceding access unit before removing from the CPB the first decoding unit in the access unit associated with the picture timing SEI message.
- [0011] In contrast, when the decoding unit is a non-first decoding unit in an access unit, the common decoding unit CPB removal delay parameter may specify an amount of sub-picture clock ticks to wait after removal from the CPB of a preceding decoding unit in the access unit associated with the picture timing SEI message before removing from the CPB a current decoding unit in the access unit associated with the picture timing SEI message.
- [0012] The decoding unit CPB removal delay parameters may specify an amount of sub-picture clock ticks to wait after removal from the CPB of the last decoding unit before removing from the CPB an i-th decoding unit in the access unit associated with the picture timing SEI message.
- [0013] The electronic device may calculate the decoding unit CPB removal delay parameters according to a remainder of a modulo $2^{(\text{cpb_removal_delay_length_minus1} + 1)}$ counter where $\text{cpb_removal_delay_length_minus1} + 1$ is a length of a common decoding unit CPB removal delay parameter.
- [0014] The electronic device may also generate, when the CPB supports operation on an access unit level, a picture timing SEI message including a CPB removal delay parameter that specifies how many clock ticks to wait after removal from the CPB of an access unit associated with a most recent buffering period SEI message in a preceding access unit before removing from the CPB the access unit data associated with the picture timing SEI message.
- [0015] The electronic device may also determine whether the CPB supports operation on a sub-picture level or an access unit level. This may include determining a picture timing flag that indicates whether a Coded Picture Buffer (CPB) provides parameters supporting operation on a sub-picture level based on a value of the picture timing flag. The picture timing flag may be included in the picture timing SEI message.
- [0016] Determining whether to include a common decoding unit CPB removal delay parameter may include setting a common decoding unit CPB removal delay flag to 1 when the common decoding unit CPB removal delay parameter is to be included in the picture timing SEI message. It may also include setting the common decoding unit

CPB removal delay flag to 0 when the common decoding unit CPB removal delay parameter is not to be included in the picture timing SEI message. The common decoding unit CPB removal delay flag may be included in the picture timing SEI message.

- [0017] The electronic device may also generate, when the CPB supports operation on a sub-picture level, separate network abstraction layer (NAL) units related parameters that indicate an amount, offset by one, of NAL units for each decoding unit in an access unit. Alternatively, or in addition to, the electronic device may generate a common NAL parameter that indicates an amount, offset by one, of NAL units common to each decoding unit in an access unit.
- [0018] An electronic device for buffering a bitstream is also described. The electronic device includes a processor and instructions stored in memory that is in electronic communication with the processor. The electronic device determines that a CPB signals parameters on a sub-picture level for an access unit. The electronic device also determines, when a received picture timing Supplemental Enhancement Information (SEI) message comprises the common decoding unit Coded Picture Buffer (CPB) removal delay flag, a common decoding unit CPB removal delay parameter applicable to all decoding units in the access unit. The electronic device also determines, when the picture timing SEI message does not comprise the common decoding unit CPB removal delay flag, a separate decoding unit CPB removal delay parameter for each decoding unit in the access unit. The electronic device also removes decoding units from the CPB using the common decoding unit CPB removal delay parameter or the separate decoding unit CPB removal delay parameters. The electronic device also decodes the decoding units in the access unit.
- [0019] In one configuration, the electronic device determines that a picture timing flag is set in the picture timing SEI message. The electronic device may also set a CPB removal delay parameter, *cpb_removal_delay*, according to

$$cpb_removal_delay = \frac{\left(\sum_{i=0}^{num_decoding_units_minus1} du_cpb_removal_delay[i] \right) * t_{c,sub}}{t_c}$$

where *du_cpb_removal_delay[i]* are the decoding unit CPB removal delay parameters, *t_c* is a clock tick, *t_{c,sub}* is a sub-picture clock tick, *num_decoding_units_minus1* is an amount of decoding units in the access unit offset by one, and *i* is an index.

- [0020] Alternatively, the electronic device may set a CPB removal delay parameter, *cpb_removal_delay*, and *du_cpb_removal_delay[num_decoding_units_minus1]* so as to satisfy the equation

$$-1 \leq [\text{cpb_removal_delay} * t_c - (\sum_{i=0}^{\text{num_decoding_units_minus1}} \text{du_cpb_removal_delay}[i]) * t_{c,\text{sub}}] \leq 1$$

where $\text{du_cpb_removal_delay}[i]$ are the decoding unit CPB removal delay parameters, t_c is a clock tick, $t_{c,\text{sub}}$ is a sub-picture clock tick, $\text{num_decoding_units_minus1}$ is an amount of decoding units in the access unit offset by one, and i is an index.

[0021] Alternatively, the electronic device may set a CPB removal delay parameter, cpb_removal_delay , and $\text{du_cpb_removal_delay}[\text{num_decoding_units_minus1}]$ according to $\text{cpb_removal_delay} * t_c =$

$\text{du_cpb_removal_delay}[\text{num_decoding_units_minus1}] * t_{c,\text{sub}}$ where

$\text{du_cpb_removal_delay}[\text{num_decoding_units_minus1}]$ is the decoding unit CPB removal delay parameter for the $\text{num_decoding_units_minus1}$ 'th decoding unit, t_c is a clock tick, $t_{c,\text{sub}}$ is a sub-picture clock tick, $\text{num_decoding_units_minus1}$ is an amount of decoding units in the access unit offset by one.

[0022] In one configuration, the electronic device determines that a picture timing flag is set in the picture timing SEI message. The electronic device may also set CPB removal delay parameters, cpb_removal_delay , and

$\text{du_cpb_removal_delay}[\text{num_decoding_units_minus1}]$ so as to satisfy the equation: $-1 \leq (\text{cpb_removal_delay} * t_c - \text{du_cpb_removal_delay}[\text{num_decoding_units_minus1}] * t_{c,\text{sub}}) \leq 1$ where $\text{du_cpb_removal_delay}[\text{num_decoding_units_minus1}]$ is the decoding unit CPB removal delay parameter for the $\text{num_decoding_units_minus1}$ 'th decoding unit, t_c is a clock tick, $t_{c,\text{sub}}$ is a sub-picture clock tick, $\text{num_decoding_units_minus1}$ is an amount of decoding units in the access unit offset by one.

[0023] A ClockDiff variable may be defined as $\text{ClockDiff} =$

$(\text{num_units_in_tick} - (\text{num_units_in_sub_tick} * (\text{num_decoding_units_minus1} + 1))) / \text{time_scale}$ where num_units_in_tick is number of time units of a clock operating at the frequency time_scale Hz that corresponds to one increment of a clock tick counter, $\text{num_units_in_sub_tick}$ is number of time units of a clock operating at the frequency time_scale Hz that corresponds to one increment of a sub-picture clock tick counter, $\text{num_decoding_units_minus1} + 1$ is an amount of decoding units in the access unit, and time_scale is the number of time units that pass in one second.

[0024] When a low delay hypothetical reference decoder (HRD) flag (e.g.,

$\text{low_delay_hrd_flag}$) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1, the CPB is operating at sub-picture level and ClockDiff is greater than zero, the removal time for decoding unit m , $t_r(m)$ is determined according to: $t_r(m) = t_{r,n}(m) + t_{c,\text{sub}} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c,\text{sub}}) + \text{ClockDiff}$ where $t_{r,n}(m)$ is the nominal removal time of the decoding unit m , $t_{c,\text{sub}}$ is a sub-picture clock tick, $\text{Ceil}()$ is a ceiling function and $t_{af}(m)$ is final arrival time of decoding unit m .

- [0025] When a low delay hypothetical reference decoder (HRD) flag (e.g., low_delay_hrd_flag) is set to 1, $t_{r,n}(n) < t_{af}(n)$, a picture timing flag is set to 1, the CPB is operating at an access unit level and ClockDiff is greater than zero, the removal time for access unit n, $t_r(n)$ is determined according to: $t_r(n) = t_{r,n}(n) + t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c) - \text{ClockDiff}$ where $t_{r,n}(n)$ is the nominal removal time of the access unit n, t_c is a clock tick, $\text{Ceil}()$ is a ceiling function and $t_{af}(n)$ is a final arrival time of access unit n.
- [0026] When a low delay hypothetical reference decoder (HRD) flag (e.g., low_delay_hrd_flag) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the last decoding unit m of access unit, $t_r(m)$ according to: $t_r(m) = t_{r,n}(m) + \max((t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub})), (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c)))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m, t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m, $t_{r,n}(n)$ is the nominal removal time of the access unit n, t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n.
- [0027] When a low delay hypothetical reference decoder (HRD) flag is set to 1, $t_{r,n}(n) < t_{af}(n)$, a picture timing flag is set to 1 and the CPB is operating at access unit level, the removal time for access unit n, $t_r(n)$ according to: $t_r(n) = t_{r,n}(n) + \max((t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub})), (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c)))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit n, t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m, $t_{r,n}(n)$ is the nominal removal time of the access unit n, t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n.
- [0028] When a low delay hypothetical reference decoder (HRD) flag (e.g., low_delay_hrd_flag) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the last decoding unit m of access unit, $t_r(m)$ according to: $t_r(m) = t_{r,n}(m) + \min((t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub})), (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c)))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m, t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m, $t_{r,n}(n)$ is the nominal removal time of the access unit n, t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n.
- [0029] When a low delay hypothetical reference decoder (HRD) flag is set to 1, $t_{r,n}(n) < t_{af}(n)$, a picture timing flag is set to 1 and the CPB is operating at access unit level, the removal time for access unit n, $t_r(n)$ according to: $t_r(n) = t_{r,n}(n) + \min((t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub})), (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c)))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit n, t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is

a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n .

[0030] When a low delay hypothetical reference decoder (HRD) flag (e.g., `low_delay_hrd_flag`) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the last decoding unit m of access unit, $t_r(m)$ according to: $t_r(m) = t_{r,n}(m) + (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n .

[0031] When a low delay hypothetical reference decoder (HRD) flag is set to 1, $t_{r,n}(n) < t_{af}(n)$, a picture timing flag is set to 1 and the CPB is operating at access unit level, the removal time for access unit n , $t_r(n)$ according to: $t_r(n) = t_{r,n}(n) + (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit n , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n .

[0032] When a low delay hypothetical reference decoder (HRD) flag (e.g., `low_delay_hrd_flag`) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for a decoding unit m which is not the last decoding unit is set as $t_r(m) = t_{af}(m)$, where $t_{af}(m)$ is a final arrival time of decoding unit m . When a low delay hypothetical reference decoder (HRD) flag (e.g., `low_delay_hrd_flag`) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for a decoding unit m which is the last decoding unit m of access unit, $t_r(m)$ according to: $t_r(m) = t_{r,n}(m) + (t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub}))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick, $t_{af}(n)$ is a final arrival time of access unit n , and $t_{af}(m)$ is a final arrival time of last decoding unit m in the access unit n .

[0033] When a low delay hypothetical reference decoder (HRD) flag (e.g., `low_delay_hrd_flag`) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for a decoding unit m which is not the last decoding unit is set as $t_r(m) = t_{af}(m)$, where $t_{af}(m)$ is a final arrival time of decoding unit m . When a low delay hypothetical reference decoder (HRD) flag (e.g., `low_delay_hrd_flag`) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing

flag is set to 1 and the CPB is operating at sub-picture level, the removal time for a decoding unit m which is the last decoding unit m of access unit, $t_r(m)$ according to: $t_r(m) = t_{r,n}(m) + (t_c * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_c))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick, $t_{af}(n)$ is a final arrival time of access unit n , and $t_{af}(m)$ is a final arrival time of last decoding unit m in the access unit n .

[0034] When a low delay hypothetical reference decoder (HRD) flag (e.g., low_delay_hrd_flag) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for a decoding unit m is set as $t_r(m) = t_{af}(m)$ where $t_{r,n}(m)$ is the nominal removal time of the decoding unit m , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick, $t_{af}(n)$ is a final arrival time of access unit n , and $t_{af}(m)$ is a final arrival time of decoding unit m in the access unit n .

[0035] When a low delay hypothetical reference decoder (HRD) flag is set to 1, $t_{r,n}(n) < t_{af}(n)$, a picture timing flag is set to 1 and the CPB is operating at access unit level, the removal time for access unit n , $t_r(n)$ according to: $t_r(n) = t_{af}(n)$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit n , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n .

[0036] Additionally in some cases a flag may be sent in part of the bitstream to signal which of the above alternative equations are used for deciding the removal time of the decoding units and removal time of the access unit. In one case the flag may be called du_au_cpb_alignment_mode_flag. If du_au_cpb_alignment_mode_flag is 1 then the equations above which align the operation of CPB which operates in sub-picture based mode with the CPB which operates in the access unit mode are used. If du_au_cpb_alignment_mode_flag is 0 then the equations above which do not align the operation of CPB which operates in sub-picture based mode with the CPB which operates in the access unit mode are used.

[0037] In once case the flag du_au_cpb_alignment_mode_flag may be signaled in the video usability information (VUI). In another case the flag du_au_cpb_alignment_mode_flag may be sent in picture timing SEI message. In yet another case the flag du_au_cpb_alignment_mode_flag may be sent in some other normative part of the bitstream. One example of modified syntax and semantics in accordance with the systems and methods disclosed herein is given in Table (0) as follows.

pic_timing(payloadSize) {
if(CpbDpbDelaysPresentFlag) {
cpb_removal_delay
dpb_output_delay
if(sub_pic_cpb_params_present_flag) {
num_decoding_units_minus1
du_au_cpb_alignment_mode_flag
for(i = 0; i <= num_decoding_units_minus1; i++) {
num_nalus_in_du_minus1[i]
du_cpb_removal_delay[i]
}
}
}
}

Table (0)

[0038] It should be noted that different symbols (names) than those used above for various variables may be used. For example $t_r(n)$ of access unit n may be called CpbRemovalTime(n), $t_r(m)$ of decoding unit n may be called CpbRemovalTime(m), t_{c_sub} may be called ClockSubTick, t_c may be called ClockTick, $t_{af}(n)$ of access unit m may be called FinalArrivalTime(n) of access unit n , $t_{af}(m)$ of decoding unit m may be called FinalArrivalTime(m), $t_{r,n}(n)$ may be called NominalRemovalTime(n) of the access unit n , $t_{r,n}(m)$ may be called NominalRemovalTime(m) of the decoding unit m .

[0039] A method for sending a message by an electronic device is also described. The method includes determining, when a Coded Picture Buffer (CPB) supports operation on a sub-picture level, whether to include a common decoding unit CPB removal delay parameter in a picture timing Supplemental Enhancement Information (SEI) message. The method also includes generating, when the common decoding unit CPB removal delay parameter is to be included in the picture timing SEI message, the common decoding unit CPB removal delay parameter, wherein the common decoding unit CPB removal delay parameter is applicable to all decoding units in an access unit from the CPB. The method also includes generating, when the common decoding unit CPB removal delay parameter is not to be included in the picture timing SEI message, a separate decoding unit CPB removal delay parameter for each decoding unit in the access unit. The method also includes sending the picture timing SEI message with the common decoding unit CPB removal delay parameter or the decoding unit CPB

removal delay parameters.

[0040] A method for buffering a bitstream by an electronic device is also described. The method includes determining that a CPB signals parameters on a sub-picture level for an access unit. The method also includes determining, when a received picture timing Supplemental Enhancement Information (SEI) message comprises the common decoding unit Coded Picture Buffer (CPB) removal delay flag, a common decoding unit CPB removal delay parameter applicable to all decoding units in the access unit. The method also includes determining, when the picture timing SEI message does not comprise the common decoding unit CPB removal delay flag, a separate decoding unit CPB removal delay parameter for each decoding unit in the access unit. The method also includes removing decoding units from the CPB using the common decoding unit CPB removal delay parameter or the separate decoding unit CPB removal delay parameters. The method also includes decoding the decoding units in the access unit.

[0041] The systems and methods disclosed herein describe electronic devices for sending a message and buffering a bitstream. For example, the systems and methods disclosed herein describe buffering for bitstreams starting with sub-picture parameters. In some configurations, the systems and methods disclosed herein may describe signaling sub-picture based Hypothetical Reference Decoder (HRD) parameters. For instance, the systems and methods disclosed herein describe modification to a picture timing Supplemental Enhancement Information (SEI) message. The systems and methods disclosed herein (e.g., the HRD modification) may result in more compact signaling of parameters when each sub-picture arrives and is removed from CPB at regular intervals.

[0042] Furthermore, when the sub-picture level CPB removal delay parameters are present, the Coded Picture Buffer (CPB) may operate at access unit level or sub-picture level. The present systems and methods may also impose a bitstream constraint so that the sub-picture level based CPB operation and the access unit level CPB operation result in the same timing of decoding unit removal. Specifically the timing of removal of last decoding unit in an access unit when operating in sub-picture mode and the timing of removal of access unit when operating in access unit mode will be the same.

[0043] It should be noted that although the term "hypothetical" is used in reference to an HRD, the HRD may be physically implemented. For example, "HRD" may be used to describe an implementation of an actual decoder. In some configurations, an HRD may be implemented in order to determine whether a bitstream conforms to High Efficiency Video Coding (HEVC) specifications. For instance, an HRD may be used to determine whether Type I bitstreams and Type II bitstreams conform to HEVC specifications. A Type I bitstream may contain only Video Coding Layer (VCL) Network Access Layer (NAL) units and filler data NAL units. A Type II bitstream may contain additional

other NAL units and syntax elements.

- [0044] Joint Collaborative Team on Video Coding (JCTVC) document JCTVC-I0333 includes sub-picture based HRD and supports picture timing SEI messages. This functionality has been incorporated into the High Efficiency Video Coding (HEVC) Committee Draft (JCTVC-I1003), incorporated by reference herein in its entirety. B. Bros, W-J. Han, J-R. Ohm, G.J. Sullivan, Wang, and T-. Wiegand, "High efficiency video coding (HEVC) text specification draft 10 (for DFIS & Last Call)," JCTVC-L1003_v34, Geneva, January 2013 is hereby incorporated by reference herein in its entirety. B. Bros, W-J. Han, J-R. Ohm, G.J. Sullivan, Wang, and T-. Wiegand, "High efficiency video coding (HEVC) text specification draft 10," JCTVC-L1003, Geneva, January 2013 is hereby incorporated by reference herein in its entirety.
- [0045] One example of modified syntax and semantics in accordance with the systems and methods disclosed herein is given in Table (1) as follows.

pic_timing(payloadSize) {
if(CpbDpbDelaysPresentFlag) {
cpb_removal_delay
dpb_output_delay
if(sub_pic_cpb_params_present_flag) {
num_decoding_units_minus1
common_du_cpb_removal_delay_flag
if(common_du_cpb_removal_delay_flag) {
common_du_cpb_removal_delay
}
for(i = 0; i <= num_decoding_units_minus1; i++) {
num_nalus_in_du_minus1[i]
if(!common_du_cpb_removal_delay_flag)
du_cpb_removal_delay[i]
}
}
}

Table (1)

- [0046] Examples regarding buffering period SEI message semantics in accordance with the systems and methods disclosed herein are given as follows. In particular, additional detail regarding the semantics of the modified syntax elements are given as follows.

When NalHrdBpPresentFlag or VclHrdBpPresentFlag are equal to 1, a buffering period SEI message can be associated with any access unit in the bitstream, and a buffering period SEI message may be associated with each IDR access unit, with each CRA access unit, and with each access unit associated with a recovery point SEI message. For some applications, the frequent presence of a buffering period SEI message may be desirable. A buffering period is specified as the set of access units between two instances of the buffering period SEI message in decoding order.

- [0047] 'seq_parameter_set_id' specifies the sequence parameter set that contains the sequence HRD attributes. The value of seq_parameter_set_id may be equal to the value of seq_parameter_set_id in the picture parameter set referenced by the primary coded picture associated with the buffering period SEI message. The value of seq_parameter_set_id may be in the range of 0 to 31, inclusive.
- [0048] 'initial_cpb_removal_delay'[SchedSelIdx] specifies the delay for the SchedSelIdx-th CPB between the time of arrival in the CPB of the first bit of the coded data associated with the access unit associated with the buffering period SEI message and the time of removal from the CPB of the coded data associated with the same access unit, for the first buffering period after HRD initialization. The syntax element has a length in bits given by initial_cpb_removal_delay_length_minus1 + 1. It is in units of a 90 kHz clock. initial_cpb_removal_delay[SchedSelIdx] may not be equal to 0 and may not exceed

$$90000 * (\text{CpbSize}[\text{SchedSelIdx}] \div \text{BitRate}[\text{SchedSelIdx}]),$$

the time-equivalent of the CPB size in 90 kHz clock units.

- [0049] 'initial_cpb_removal_delay_offset'[SchedSelIdx] is used for the SchedSelIdx-th CPB in combination with the cpb_removal_delay to specify the initial delivery time of coded access units to the CPB. initial_cpb_removal_delay_offset[SchedSelIdx] is in units of a 90 kHz clock. The initial_cpb_removal_delay_offset[SchedSelIdx] syntax element is a fixed length code whose length in bits is given by initial_cpb_removal_delay_length_minus1 + 1. This syntax element is not used by decoders and is needed only for the delivery scheduler (HSS) (e.g., as specified in Annex C of JCTVC-I1003).
- [0050] Over the entire coded video sequence, the sum of initial_cpb_removal_delay[SchedSelIdx] and initial_cpb_removal_delay_offset[SchedSelIdx] may be constant for each value of SchedSelIdx.
- [0051] 'initial_du_cpb_removal_delay'[SchedSelIdx] specifies the delay for the SchedSelIdx-th CPB between the time of arrival in the CPB of the first bit of the coded data associated with the first decoding unit in the access unit associated with the

buffering period SEI message and the time of removal from the CPB of the coded data associated with the same decoding unit, for the first buffering period after HRD initialisation. The syntax element has a length in bits given by $\text{initial_cpb_removal_delay_length_minus1} + 1$. It is in units of a 90 kHz clock. $\text{initial_du_cpb_removal_delay}[\text{SchedSelIdx}]$ may not be equal to 0 and may not exceed

$$90000 * (\text{CpbSize}[\text{SchedSelIdx}] \div \text{BitRate}[\text{SchedSelIdx}]),$$

the time-equivalent of the CPB size in 90 kHz clock units.

- [0052] 'initial_du_cpb_removal_delay_offset' [SchedSelIdx] is used for the SchedSelIdx-th CPB in combination with the `cpb_removal_delay` to specify the initial delivery time of decoding units to the CPB. `initial_cpb_removal_delay_offset` [SchedSelIdx] is in units of a 90 kHz clock. The `initial_du_cpb_removal_delay_offset` [SchedSelIdx] syntax element is a fixed length code whose length in bits is given by $\text{initial_cpb_removal_delay_length_minus1} + 1$. This syntax element is not used by decoders and is needed only for the delivery scheduler (HSS) (e.g., as specified in Annex C of JCTVC-I1003).
- [0053] Over the entire coded video sequence, the sum of `initial_du_cpb_removal_delay` [SchedSelIdx] and `initial_du_cpb_removal_delay_offset` [SchedSelIdx] may be constant for each value of SchedSelIdx.
- [0054] Examples regarding picture timing SEI message semantics in accordance with the systems and methods disclosed herein are given as follows. In particular, additional detail regarding the semantics of the modified syntax elements are given as follows.
- [0055] The syntax of the picture timing SEI message is dependent on the content of the sequence parameter set that is active for the coded picture associated with the picture timing SEI message. However, unless the picture timing SEI message of an Instantaneous Decoding Refresh (IDR) access unit is preceded by a buffering period SEI message within the same access unit, the activation of the associated sequence parameter set (and, for IDR pictures that are not the first picture in the bitstream, the determination that the coded picture is an IDR picture) does not occur until the decoding of the first coded slice Network Abstraction Layer (NAL) unit of the coded picture. Since the coded slice NAL unit of the coded picture follows the picture timing SEI message in NAL unit order, there may be cases in which it is necessary for a decoder to store the raw byte sequence payload (RBSP) containing the picture timing SEI message until determining the parameters of the sequence parameter that will be active for the coded picture, and then perform the parsing of the picture timing SEI message.
- [0056] The presence of picture timing SEI message in the bitstream is specified as follows.

If CpbDpbDelaysPresentFlag is equal to 1, one picture timing SEI message may be present in every access unit of the coded video sequence. Otherwise (CpbDpbDelaysPresentFlag is equal to 0), no picture timing SEI messages may be present in any access unit of the coded video sequence.

- [0057] 'cpb_removal_delay' specifies how many clock ticks (see subclause E.2.1 of JCTVC-I1003) to wait after removal from the CPB of the access unit associated with the most recent buffering period SEI message in a preceding access unit before removing from the buffer the access unit data associated with the picture timing SEI message. This value is also used to calculate an earliest possible time of arrival of access unit data into the CPB for the HSS, as specified in Annex C of JCTVC-I1003. The syntax element is a fixed length code whose length in bits is given by $\text{cpb_removal_delay_length_minus1} + 1$. The `cpb_removal_delay` is the remainder of a modulo $2^{(\text{cpb_removal_delay_length_minus1} + 1)}$ counter.
- [0058] The value of `cpb_removal_delay_length_minus1` that determines the length (in bits) of the syntax element `cpb_removal_delay` is the value of `cpb_removal_delay_length_minus1` coded in the sequence parameter set that is active for the primary coded picture associated with the picture timing SEI message, although `cpb_removal_delay` specifies a number of clock ticks relative to the removal time of the preceding access unit containing a buffering period SEI message, which may be an access unit of a different coded video sequence.
- [0059] 'dpb_output_delay' is used to compute the Decoded Picture Buffer (DPB) output time of the picture. It specifies how many clock ticks to wait after removal of the last decoding unit in an access unit from the CPB before the decoded picture is output from the DPB (see subclause C.2 of JCTVC-I1003).
- [0060] With respect to the DPB, a picture is not removed from the DPB at its output time when it is still marked as "used for short-term reference" or "used for long-term reference". Only one `dpb_output_delay` is specified for a decoded picture. The length of the syntax element `dpb_output_delay` is given in bits by $\text{dpb_output_delay_length_minus1} + 1$. When `max_dec_pic_buffering[ max_temporal_layers_minus1 ]` is equal to 0, `dpb_output_delay` may be equal to 0.
- [0061] The output time derived from the `dpb_output_delay` of any picture that is output from an output timing conforming decoder as specified in subclause C.2 of JCTVC-I1003 may precede the output time derived from the `dpb_output_delay` of all pictures in any subsequent coded video sequence in decoding order. The picture output order established by the values of this syntax element may be the same order as established by the values of `PicOrderCnt( )` as specified by subclause. For pictures that are not output by the "bumping" process of subclause because they precede, in decoding order, an IDR picture with `no_output_of_prior_pics_flag` equal to 1 or inferred to be equal to 1,

the output times derived from `dpb_output_delay` may be increasing with increasing value of `PicOrderCnt()` relative to all pictures within the same coded video sequence.

- [0062] `'num_decoding_units_minus1'` plus 1 specifies the number of decoding units in the access unit the picture timing SEI message is associated with. The value of `num_decoding_units_minus1` may be in the range of 0 to $\text{PicWidthInCtbs} * \text{PicHeightInCtbs} - 1$, inclusive.
- [0063] `'common_du_cpb_removal_delay_flag'` equal to 1 specifies that the syntax element `common_du_cpb_removal_delay` is present. `common_du_cpb_removal_delay_flag` equal to 0 specifies that the syntax element `common_du_cpb_removal_delay` is not present.
- [0064] `'common_du_cpb_removal_delay'` specifies information as follows: If a decoding unit is the first decoding unit in the access unit associated with the picture timing SEI message then `common_du_cpb_removal_delay` specifies how many sub-picture clock ticks (see subclause E.2.1 of JCTVC-I1003) to wait after removal from the CPB of the last decoding unit in the access unit associated with the most recent buffering period SEI message in a preceding access unit before removing from the CPB the first decoding unit in the access unit associated with the picture timing SEI message.
- [0065] Otherwise `common_du_cpb_removal_delay` specifies how many sub-picture clock ticks (see subclause E.2.1 of JCTVC-I1003) to wait after removal from the CPB of the preceding decoding unit in the access unit associated with the picture timing SEI message before removing from the CPB the current decoding unit in the access unit associated with the picture timing SEI message. This value is also used to calculate an earliest possible time of arrival of decoding unit data into the CPB for the HSS, as specified in Annex C. The syntax element is a fixed length code whose length in bits is given by $\text{cpb_removal_delay_length_minus1} + 1$. The `common_du_cpb_removal_delay` is the remainder of a modulo $2^{(\text{cpb_removal_delay_length_minus1} + 1)}$ counter.
- [0066] An alternate way of specifying `common_du_cpb_removal_delay` is as follows:
- [0067] `'common_du_cpb_removal_delay'` specifies how many sub-picture clock ticks (see subclause E.2.1 of JCTVC-I1003) to wait after removal from the CPB of the last decoding unit before removing from the CPB the current decoding unit in the access unit associated with the picture timing SEI message. This value is also used to calculate an earliest possible time of arrival of decoding unit data into the CPB for the HSS, as specified in Annex C. The syntax element is a fixed length code whose length in bits is given by $\text{cpb_removal_delay_length_minus1} + 1$. The `common_du_cpb_removal_delay` is the remainder of a modulo $2^{(\text{cpb_removal_delay_length_minus1} + 1)}$ counter.
- [0068] The value of `cpb_removal_delay_length_minus1` that determines the length (in bits)

of the syntax element `common_du_cpb_removal_delay` is the value of `cpb_removal_delay_length_minus1` coded in the sequence parameter set that is active for the coded picture associated with the picture timing SEI message, although `common_du_cpb_removal_delay` specifies a number of sub-picture clock ticks relative to the removal time of the first decoding unit in the preceding access unit containing a buffering period SEI message, which may be an access unit of a different coded video sequence.

[0069] `'num_nalus_in_du_minus1[ i ]'` plus 1 specifies the number of NAL units in the *i*-th decoding unit of the access unit the picture timing SEI message is associated with. The value of `num_nalus_in_du_minus1[ i ]` may be in the range of 0 to $\text{PicWidthInCtbs} * \text{PicHeightInCtbs} - 1$, inclusive.

[0070] The first decoding unit of the access unit consists of the first `num_nalus_in_du_minus1[ 0 ] + 1` consecutive NAL units in decoding order in the access unit. The *i*-th (with *i* greater than 0) decoding unit of the access unit consists of the `num_nalus_in_du_minus1[ i ] + 1` consecutive NAL units immediately following the last NAL unit in the previous decoding unit of the access unit, in decoding order. There may be at least one VCL NAL unit in each decoding unit. All non-VCL NAL units associated with a VCL NAL unit may be included in the same decoding unit.

[0071] `'du_cpb_removal_delay[ i ]'` specifies how many sub-picture clock ticks (see subclause E.2.1 of JCTVC-I1003) to wait after removal from the CPB of the first decoding unit in the access unit associated with the most recent buffering period SEI message in a preceding access unit before removing from the CPB the *i*-th decoding unit in the access unit associated with the picture timing SEI message. This value is also used to calculate an earliest possible time of arrival of decoding unit data into the CPB for the HSS (e.g., as specified in Annex C of JCTVC-I1003). The syntax element is a fixed length code whose length in bits is given by `cpb_removal_delay_length_minus1 + 1`. The `du_cpb_removal_delay[ i ]` is the remainder of a modulo $2^{(\text{cpb_removal_delay_length_minus1} + 1)}$ counter.

[0072] The value of `cpb_removal_delay_length_minus1` that determines the length (in bits) of the syntax element `du_cpb_removal_delay[ i ]` is the value of `cpb_removal_delay_length_minus1` coded in the sequence parameter set that is active for the coded picture associated with the picture timing SEI message, although `du_cpb_removal_delay[ i ]` specifies a number of sub-picture clock ticks relative to the removal time of the first decoding unit in the preceding access unit containing a buffering period SEI message, which may be an access unit of a different coded video sequence.

[0073] In one configuration, the timing of decoding unit removal and decoding of decoding units may be implemented as follows.

- [0074] If SubPicCpbFlag is equal to 0, the variable CpbRemovalDelay(m) is set to the value of cpb_removal_delay in the picture timing SEI message associated with the access unit that is decoding unit m , and the variable T_c is set to t_c . Otherwise if SubPicCpbFlag is equal to 1 and common_du_cpb_removal_delay_flag is 0 the variable CpbRemovalDelay(m) is set to the value of du_cpb_removal_delay[i] for decoding unit m (with m ranging from 0 to num_decoding_units_minus1) in the picture timing SEI message associated with the access unit that contains decoding unit m , and the variable T_c is set to t_{c_sub} .
- [0075] In some cases, Otherwise if SubPicCpbFlag is equal to 1 and common_du_cpb_removal_delay_flag is 0 the variable CpbRemovalDelay(m) is set to the value of $(m+1)*du_cpb_removal_delay[i]$ for decoding unit m (with m ranging from 0 to num_decoding_units_minus1) in the picture timing SEI message associated with the access unit that contains decoding unit m , and the variable T_c is set to t_{c_sub} .
- [0076] Otherwise if SubPicCpbFlag is equal to 1 and common_du_cpb_removal_delay_flag is 1 the variable CpbRemovalDelay(m) is set to the value of common_du_cpb_removal_delay for decoding unit m in the picture timing SEI message associated with the access unit that contains decoding unit m , and the variable T_c is set to t_{c_sub} .
- [0077] When a decoding unit m is the decoding unit with n equal to 0 (the first decoding unit of the access unit that initializes the HRD), the nominal removal time of the decoding unit from the CPB is specified by
- $$t_{r,n}(0) = \text{InitCpbRemovalDelay}[\text{SchedSelIdx}] \div 90000.$$
- [0078] When a decoding unit m is the first decoding unit of the first access unit of a buffering period that does not initialize the HRD, the nominal removal time of the decoding unit from the CPB is specified by $t_{r,n}(m) = t_{r,n}(m_b) + T_c * \text{CpbRemovalDelay}(m)$, where $t_{r,n}(m_b)$ is the nominal removal time of the first decoding unit of the previous buffering period.
- [0079] When a decoding unit m is the first decoding unit of a buffering period, m_b is set equal to m at the removal time $t_{r,n}(m)$ of the decoding unit m . The nominal removal time $t_{r,n}(m)$ of a decoding unit m that is not the first decoding unit of a buffering period is given by $t_{r,n}(m) = t_{r,n}(m_b) + T_c * \text{CpbRemovalDelay}(m)$, where $t_{r,n}(m_b)$ is the nominal removal time of the first decoding unit of the current buffering period.
- [0080] The removal time of decoding unit m is specified as follows. If low_delay_hrd_flag is equal to 0 or $t_{r,n}(m) \geq t_{af}(m)$, the removal time of decoding unit m is specified by $t_r(m) = t_{r,n}(m)$. Otherwise (low_delay_hrd_flag is equal to 1 and $t_{r,n}(m) < t_{af}(m)$), the removal time of decoding unit m is specified by

$$t_r(m) = t_{r,n}(m) + T_c * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) \div T_c).$$

The latter case (low_delay_hrd_flag is equal to 1 and $t_{r,n}(m) < t_{af}(m)$) indicates that the size of decoding unit m , $b(m)$, is so large that it prevents removal at the nominal removal time.

- [0081] In another case the removal time of decoding unit m is specified as follows. If low_delay_hrd_flag is equal to 0 or $t_{r,n}(m) \geq t_{af}(m)$, the removal time of decoding unit m is specified by $t_r(m) = t_{r,n}(m)$. Otherwise (low_delay_hrd_flag is equal to 1 and $t_{r,n}(m) < t_{af}(m)$), the removal time of decoding unit m which is not the last decoding unit in the access unit is specified by $t_r(m) = t_{af}(m)$, and the removal time of decoding unit m which is the last decoding unit in the access unit

$$t_r(m) = t_{r,n}(m) + T_c * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) \div T_c).$$

The latter case (low_delay_hrd_flag is equal to 1 and $t_{r,n}(m) < t_{af}(m)$) indicates that the size of decoding unit m , $b(m)$, is so large that it prevents removal at the nominal removal time.

- [0082] In another case the removal time of decoding unit m is specified as follows. If low_delay_hrd_flag is equal to 0 or $t_{r,n}(m) \geq t_{af}(m)$, the removal time of decoding unit m is specified by $t_r(m) = t_{r,n}(m)$. Otherwise (low_delay_hrd_flag is equal to 1 and $t_{r,n}(m) < t_{af}(m)$), the removal time of decoding unit m which is not the last decoding unit in the access unit is specified by $t_r(m) = t_{af}(m)$, and the removal time of decoding unit m which is the last decoding unit in the access unit

$$t_r(m) = t_{r,n}(m) + t_c * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) \div t_c).$$

The latter case (low_delay_hrd_flag is equal to 1 and $t_{r,n}(m) < t_{af}(m)$) indicates that the size of decoding unit m , $b(m)$, is so large that it prevents removal at the nominal removal time.

- [0083] In another case the removal time of decoding unit m is specified as follows. If low_delay_hrd_flag is equal to 0 or $t_{r,n}(m) \geq t_{af}(m)$, the removal time of decoding unit m is specified by $t_r(m) = t_{r,n}(m)$. Otherwise (low_delay_hrd_flag is equal to 1 and $t_{r,n}(m) < t_{af}(m)$), the removal time of decoding unit m is specified by $t_r(m) = t_{af}(m)$. The latter case (low_delay_hrd_flag is equal to 1 and $t_{r,n}(m) < t_{af}(m)$) indicates that the size of decoding unit m , $b(m)$, is so large that it prevents removal at the nominal removal time.

- [0084] When SubPicCpbFlag is equal to 1, the nominal CPB removal time of access unit n $t_{r,n}(n)$ is set to the nominal CPB removal time of the last decoding unit in access unit n , the CPB removal time of access unit n $t_r(n)$ is set to the CPB removal time of the last decoding unit in access unit n .

- [0085] When SubPicCpbFlag is equal to 0, each decoding unit is an access unit, hence the nominal CPB removal time and the CPB removal time of access unit n are the nominal CPB removal time and the CPB removal time of decoding unit n.
- [0086] At CPB removal time of decoding unit m, the decoding unit is instantaneously decoded.
- [0087] Another example of modified syntax and semantics for a picture timing SEI message in accordance with the systems and methods disclosed herein is given in Table (2) as follows. Modifications in accordance with the systems and methods disclosed herein are denoted in bold.

pic_timing(payloadSize) {
if(CpbDpbDelaysPresentFlag) {
cpb_removal_delay
dpb_output_delay
if(sub_pic_cpb_params_present_flag) {
num_decoding_units_minus1
common_du_cpb_removal_delay_flag
if(common_du_cpb_removal_delay_flag) {
common_num_nalus_in_du_minus1
common_du_cpb_removal_delay
}
for(i = 0; i <= num_decoding_units_minus1; i++) {
num_nalus_in_du_minus1[i]
if(!common_du_cpb_removal_delay_flag)
du_cpb_removal_delay[i]
}
}
}
}

Table (2)

- [0088] The illustrated example in Table (2) includes a syntax element `common_num_nalus_in_du_minus1`, which may be used to determine how much data should be removed from the CPB when removing a decoding unit. `common_num_nalus_in_du_minus1` plus 1 specifies the number of NAL units in each decoding unit of the access unit the picture timing SEI message is associated with. The value of `common_num_nalus_in_du_minus1` may be in the range of 0 to `PicWidthInCtbs * PicHeightInCtbs - 1`, inclusive.

- [0089] The first decoding unit of the access unit consists of the first $\text{common_num_nalus_in_du_minus1} + 1$ consecutive NAL units in decoding order in the access unit. The i -th (with i greater than 0) decoding unit of the access unit consists of the $\text{common_num_nalus_in_du_minus1} + 1$ consecutive NAL units immediately following the last NAL unit in the previous decoding unit of the access unit, in decoding order. There may be at least one VCL NAL unit in each decoding unit. All non-VCL NAL units associated with a VCL NAL unit may be included in the same decoding unit.
- [0090] Another example of modified syntax and semantics for a picture timing SEI message in accordance with the systems and methods disclosed herein is given in Table (3) as follows. Modifications in accordance with the systems and methods disclosed herein are denoted in bold.

pic_timing(payloadSize) {
if(CpbDpbDelaysPresentFlag) {
cpb_removal_delay
dpb_output_delay
if(sub_pic_cpb_params_present_flag) {
num_decoding_units_minus1
common_num_nalus_in_du_flag
if(common_num_nalus_in_du_flag) {
common_num_nalus_in_du_minus1
}
common_du_cpb_removal_delay_flag
if(common_du_cpb_removal_delay_flag) {
common_du_cpb_removal_delay
}
for(i = 0; i <= num_decoding_units_minus1; i++) {
if(!common_num_nalus_in_du_flag)
num_nalus_in_du_minus1[i]
if(!common_du_cpb_removal_delay_flag)
du_cpb_removal_delay[i]
}
}
}
}

Table (3)

- [0091] The illustrated example in Table (3) includes a syntax element 'common_num_nalus_in_du_flag' that, when equal to 1, specifies that the syntax element 'common_num_nalus_in_du_minus1' is present. 'common_num_nalus_in_du_flag' equal to 0 specifies that the syntax element 'common_num_nalus_in_du_minus1' is not present.
- [0092] In yet another embodiment flags common_du_cpb_removal_delay_flag common_num_nalus_in_du_minus1, may not be sent. Instead syntax elements common_num_nalus_in_du_minus1 and common_du_cpb_removal_delay could be sent every time. In this case a value of 0 (or some other) for these syntax elements could be used to indicate that these elements are not signaled.
- [0093] In addition to modifications to the syntax elements and semantics of the picture timing SEI message, the present systems and methods may also implement a bitstream constraint so that sub-picture based CPB operation and access unit level CPB operation result in the same timing of decoding unit removal.
- [0094] When sub_pic_cpb_params_present_flag equals to 1 that sub-picture level CPB removal delay parameters are present the CPB may operate at access unit level or sub-picture level. sub_pic_cpb_params_present_flag equal to 0 specifies that sub-picture level CPB removal delay parameters are not present and the CPB operates at access unit level. When sub_pic_cpb_params_present_flag is not present, its value is inferred to be equal to 0.
- [0095] To support the operation at both access unit level or sub-picture level, the following bitstream constraints may be used: If sub_pic_cpb_params_present_flag is 1 then it is requirement of bitstream conformance that the following constraint is obeyed when signaling the values for cpb_removal_delay and du_cpb_removal_delay[i] for all i:

$$\text{cpb_removal_delay} = \frac{\left(\sum_{i=0}^{\text{num_decoding_units_minus1}} \text{du_cpb_removal_delay}[i] \right) * t_{c,sub}}{t_c}$$

where du_cpb_removal_delay[i] are the decoding unit CPB removal delay parameters, t_c is a clock tick, $t_{c,sub}$ is sub-picture clock tick, num_decoding_units_minus1 is an amount of decoding units in the access unit offset by one, and i is an index. In some embodiments a tolerance parameter could be added to satisfy the above constraint.

- [0096] To support the operation at both access unit level or sub-picture level, the bitstream constraints as follows may be used: Let the variable $T_{du}(k)$ be defined as:

$$T_{du}(k) = T_{du}(k-1) + t_{c,sub} * \sum_{i=0}^{\text{num_decoding_units_minus1}_k} (\text{du_cpb_removal_delay_minus1}_k[i] + 1)$$

where $du_cpb_removal_delay_minus1_k[i]$ and $num_decoding_units_minus1_k$ are parameters for i 'th decoding unit of k 'th access unit (with $k=0$ for the access unit that initialized the HRD and $T_{du}(k)=0$ for $k<1$), and where $du_cpb_removal_delay_minus1_k[i]+1=du_cpb_removal_delay_minus1_k[i]$ is the decoding unit CPB removal delay parameter for the i 'th decoding unit of the k 'th access unit, and $num_decoding_units_minus1_k$ is the number of decoding units in the k 'th access unit, t_c is a clock tick, $t_{c,sub}$ is a sub-picture clock tick, and i and k are an indices. Then when the picture timing flag (e.g., $sub_pic_cpb_params_present_flag$) is set to 1, the following constraint may be true: $(au_cpb_removal_delay_minus1 + 1) * t_c == T_{du}(k)$, where $(au_cpb_removal_delay_minus1 + 1)=cpb_removal_delay$, the CPB removal delay. Thus in this case the CPB removal delay $(au_cpb_removal_delay_minus1 + 1)$ is set such that the operation of sub-picture based CPB operation and access unit based CPB operation result in the same timing of access unit removal and last decoding unit of the access unit removal.

[0097] To support the operation at both access unit level or sub-picture level, the following bitstream constraints may be used: If $sub_pic_cpb_params_present_flag$ is 1 then it is requirement of bitstream conformance that the following constraint is obeyed when signaling the values for $cpb_removal_delay$ and $du_cpb_removal_delay[i]$ for all i :

$$-1 \leq [cpb_removal_delay * t_c - (\sum_{i=0}^{num_decoding_units_minus1} du_cpb_removal_delay[i] * t_{c,sub})] \leq 1$$

where $du_cpb_removal_delay[i]$ are the decoding unit CPB removal delay parameters, t_c is a clock tick, $t_{c,sub}$ is sub-picture clock tick, $num_decoding_units_minus1$ is an amount of decoding units in the access unit offset by one, and i is an index.

[0098] To support the operation at both access unit level or sub-picture level, the following bitstream constraints may be used: If $sub_pic_cpb_params_present_flag$ is 1 then it is requirement of bitstream conformance that the following constraint is obeyed when signaling the values for $cpb_removal_delay$ and

$du_cpb_removal_delay[num_decoding_units_minus1]$: $cpb_removal_delay * t_c =$

$du_cpb_removal_delay[num_decoding_units_minus1] * t_{c,sub}$ where

$du_cpb_removal_delay[num_decoding_units_minus1]$ is the decoding unit CPB removal delay parameter for the $num_decoding_units_minus1$ 'th decoding unit, t_c is a clock tick, $t_{c,sub}$ is a sub-picture clock tick, $num_decoding_units_minus1$ is an amount of decoding units in the access unit offset by one. In some embodiments a tolerance parameter could be added to satisfy the above constraint.

[0099] To support the operation at both access unit level or sub-picture level, the following bitstream constraints may be used: If $sub_pic_cpb_params_present_flag$ is 1 then it is requirement of bitstream conformance that the following constraint is obeyed when

signaling the values for `cpb_removal_delay` and `du_cpb_removal_delay[i]` for all i :
 $1 \leq (cpb_removal_delay * t_c - du_cpb_removal_delay[num_decoding_units_minus1] * t_{c,sub}) \leq 1$ where `du_cpb_removal_delay[num_decoding_units_minus1]` is the decoding unit CPB removal delay parameter for the `num_decoding_units_minus1`'th decoding unit, t_c is a clock tick, $t_{c,sub}$ is a sub-picture clock tick, `num_decoding_units_minus1` is an amount of decoding units in the access unit offset by one.

[0100] Additionally, the present systems and methods may modify the timing of decoding unit removal. When sub-picture level CPB removal delay parameters are present, the removal time of decoding unit for "big pictures" (when `low_delay_hrd_flag` is 1 and $t_{r,n}(m) < t_{af}(m)$) may be changed to compensate for difference that can arise due to clock tick counter and sub-picture clock tick counter.

[0101] When `sub_pic_cpb_params_present_flag` equals to 1 then sub-picture level CPB removal delay parameters are present and the CPB may operate at access unit level or sub-picture level. `sub_pic_cpb_params_present_flag` equal to 0 specifies that sub-picture level CPB removal delay parameters are not present and the CPB operates at access unit level. When `sub_pic_cpb_params_present_flag` is not present, its value is inferred to be equal to 0.

[0102] Specifically, one example of timing of decoding unit removal and decoding of decoding unit implementation is as follows. The variable `SubPicCpbPreferredFlag` is either specified by external means, or when not specified by external means, set to 0. The variable `SubPicCpbFlag` is derived as follows: `SubPicCpbFlag = SubPicCpbPreferredFlag && sub_pic_cpb_params_present_flag`. If `SubPicCpbFlag` is equal to 0, the CPB operates at access unit level and each decoding unit is an access unit. Otherwise the CPB operates at sub-picture level and each decoding unit is a subset of an access unit.

[0103] If `SubPicCpbFlag` is equal to 0, the variable `CpbRemovalDelay(m)` is set to the value of `cpb_removal_delay` in the picture timing SEI message associated with the access unit that is decoding unit m , and the variable T_c is set to t_c . Otherwise the variable `CpbRemovalDelay(m)` is set to the value of `du_cpb_removal_delay[i]` for decoding unit m in the picture timing SEI message associated with the access unit that contains decoding unit m , and the variable T_c is set to $t_{c,sub}$.

[0104] When a decoding unit m is the decoding unit with n equal to 0 (the first decoding unit of the access unit that initializes the HRD), the nominal removal time of the decoding unit from the CPB is specified by

$$t_{r,n}(0) = \text{InitCpbRemovalDelay}[\text{SchedSelIdx}] \div 90000.$$

[0105] When a decoding unit m is the first decoding unit of the first access unit of a buffering period that does not initialize the HRD, the nominal removal time of the

decoding unit from the CPB is specified by $t_{r,n}(m) = t_{r,n}(m_b) + T_c * CpbRemovalDelay(m)$ where $t_{r,n}(m_b)$ is the nominal removal time of the first decoding unit of the previous buffering period.

- [0106] When a decoding unit m is the first decoding unit of a buffering period, m_b is set equal to m at the removal time $t_{r,n}(m)$ of the decoding unit m .
- [0107] The nominal removal time $t_{r,n}(m)$ of a decoding unit m that is not the first decoding unit of a buffering period is given by $t_{r,n}(m) = t_{r,n}(m_b) + T_c * CpbRemovalDelay(m)$ where $t_{r,n}(m_b)$ is the nominal removal time of the first decoding unit of the current buffering period.
- [0108] The removal time of decoding unit m is specified as follows. The variable `ClockDiff` is defined as `ClockDiff = (num_units_in_tick - (num_units_in_sub_tick * (num_decoding_units_minus1 + 1))) / time_scale`. In some case it may be requirement of a bitstream conformance that the parameters `num_units_in_tick`, `num_units_in_sub_tick`, `num_decoding_units_minus1` are signaled such that following equation is satisfied.

$$(num_units_in_tick - (num_units_in_sub_tick * (num_decoding_units_minus1 + 1))) \geq 0$$
- [0109] In some other case it may be requirement of a bitstream conformance that the parameters `num_units_in_tick`, `num_units_in_sub_tick`, `num_decoding_units_minus1` may be signaled such that following equation is satisfied.

$$(num_units_in_tick - (num_units_in_sub_tick * (num_decoding_units_minus1 + 1))) \leq 0$$
If `low_delay_hrd_flag` is equal to 0 or $t_{r,n}(m) \geq t_{af}(m)$, the removal time of decoding unit m is specified by $t_r(m) = t_{r,n}(m)$.
- [0110] Otherwise (`low_delay_hrd_flag` is equal to 1 and $t_{r,n}(m) < t_{af}(m)$), and when `sub_pic_cpb_params_present_flag` equals to 1 and the CPB is operating at sub-picture level, and if `ClockDiff` is greater than zero the removal time of decoding unit m when it is the last decoding unit of the access unit n is specified by $t_r(m) = t_{r,n}(m) + T_c * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / T_c) + \text{ClockDiff}$.
- [0111] Otherwise (`low_delay_hrd_flag` is equal to 1 and $t_{r,n}(m) < t_{af}(m)$), and when `sub_pic_cpb_params_present_flag` equals to 1 and the CPB is operating at access unit level and if `ClockDiff` is less than zero the removal time of access unit n is specified by $t_r(m) = t_{r,n}(m) + T_c * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / T_c) - \text{ClockDiff}$.
- [0112] Otherwise (`low_delay_hrd_flag` is equal to 1 and $t_{r,n}(m) < t_{af}(m)$), the removal time of decoding unit m is specified by $t_r(m) = t_{r,n}(m) + T_c * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / T_c)$. The latter case (`low_delay_hrd_flag` is equal to 1 and $t_{r,n}(m) < t_{af}(m)$) indicates that the size of decoding unit m , $b(m)$, is so large that it prevents removal at the nominal removal time.
- [0113] Otherwise (`low_delay_hrd_flag` is equal to 1 and $t_{r,n}(m) < t_{af}(m)$) and when a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal

time for the last decoding unit m of access unit, $t_r(m)$ according to: $t_r(m) = t_{r,n}(m) + \min((t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub})), (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c)))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n .

[0114] Otherwise ($\text{low_delay_hrd_flag}$ is equal to 1 and $t_{r,n}(n) < t_{af}(n)$) and when a picture timing flag is set to 1 and the CPB is operating at access unit level, the removal time for access unit n , $t_r(n)$ according to: $t_r(n) = t_{r,n}(n) + \min((t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub})), (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c)))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit n , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n .

[0115] Otherwise ($\text{low_delay_hrd_flag}$ is equal to 1 and $t_{r,n}(m) < t_{af}(m)$) and a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the last decoding unit m of access unit, $t_r(m)$ according to: $t_r(m) = t_{r,n}(m) + (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n .

[0116] Otherwise ($\text{low_delay_hrd_flag}$ is equal to 1 and $t_{r,n}(n) < t_{af}(n)$) and a picture timing flag is set to 1 and the CPB is operating at access unit level, the removal time for access unit n , $t_r(n)$ according to: $t_r(n) = t_{r,n}(n) + (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit n , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n .

[0117] Otherwise ($\text{low_delay_hrd_flag}$ is equal to 1 and $t_{r,n}(m) < t_{af}(m)$) and a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the decoding unit which is not the last decoding unit of the access unit is set as $t_r(m) = t_{af}(m)$, where $t_{af}(m)$ is a final arrival time of decoding unit m . And the removal time of the last decoding unit m of access unit, $t_r(m)$ is set according to: $t_r(m) = t_{r,n}(m) + (t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub}))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n and $t_{af}(m)$ is a final arrival time of the last decoding unit m in the access unit n .

- [0118] Otherwise (low_delay_hrd_flag is equal to 1 and $t_{r,n}(m) < t_{af}(m)$) and a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the decoding unit which is not the last decoding unit of the access unit is set as $t_r(m) = t_{af}(m)$, where $t_{af}(m)$ is a final arrival time of decoding unit m . And the removal time of the last decoding unit m of access unit, $t_r(m)$ is set according to: $t_r(m) = t_{r,n}(m) + (t_c * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_c))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n and $t_{af}(m)$ is a final arrival time of the last decoding unit m in the access unit n .
- [0119] Otherwise (low_delay_hrd_flag is equal to 1 and $t_{r,n}(m) < t_{af}(m)$) and a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the decoding unit is set as $t_r(m) = t_{af}(m)$ where $t_{r,n}(m)$ is the nominal removal time of the decoding unit m , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n and $t_{af}(m)$ is a final arrival time of the decoding unit m in the access unit n .
- [0120] Otherwise (low_delay_hrd_flag is equal to 1 and $t_{r,n}(n) < t_{af}(n)$) and a picture timing flag is set to 1 and the CPB is operating at access unit level, the removal time for access unit n , $t_r(n)$ according to: $t_r(n) = t_{af}(n)$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit n , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n .
- [0121] When SubPicCpbFlag is equal to 1, the nominal CPB removal time of access unit n $t_{r,n}(n)$ is set to the nominal CPB removal time of the last decoding unit in access unit n , the CPB removal time of access unit n $t_r(n)$ is set to the CPB removal time of the last decoding unit in access unit n .
- [0122] When SubPicCpbFlag is equal to 0, each decoding unit is an access unit, hence the nominal CPB removal time and the CPB removal time of access unit n are the nominal CPB removal time and the CPB removal time of decoding unit n . At CPB removal time of decoding unit m , the decoding unit is instantaneously decoded.
- [0123] As illustrated by the foregoing, the systems and methods disclosed herein provide syntax and semantics that modify a picture timing SEI message bitstreams carrying sub-picture based parameters. In some configurations, the systems and methods disclosed herein may be applied to HEVC specifications.
- [0124] For convenience, several definitions are given as follows, which may be applied to the systems and methods disclosed herein. A random access point may be any point in

a stream of data (e.g., bitstream) where decoding of the bitstream does not require access to any point in a bitstream preceding the random access point to decode a current picture and all pictures subsequent to said current picture in output order.

- [0125] A buffering period may be specified as a set of access units between two instances of the buffering period SEI message in decoding order. Supplemental Enhancement Information (SEI) may contain information that is not necessary to decode the samples of coded pictures from VCL NAL units. SEI messages may assist in procedures related to decoding, display or other purposes. Conforming decoders may not be required to process this information for output order conformance to HEVC specifications (Annex C of HEVC specifications (JCTVC-I1003) includes specifications for conformance, for example). Some SEI message information may be used to check bitstream conformance and for output timing decoder conformance.
- [0126] A buffering period SEI message may be an SEI message related to buffering period. A picture timing SEI message may be an SEI message related to CPB removal timing. These messages may define syntax and semantics which define bitstream arrival timing and coded picture removal timing.
- [0127] A Coded Picture Buffer (CPB) may be a first-in first-out buffer containing access units in decoding order specified in a hypothetical reference decoder (HRD). An access unit may be a set of Network Access Layer (NAL) units that are consecutive in decoding order and contain exactly one coded picture. In addition to the coded slice NAL units of the coded picture, the access unit may also contain other NAL units not containing slices of the coded picture. The decoding of an access unit always results in a decoded picture. A NAL unit may be a syntax structure containing an indication of the type of data to follow and bytes containing that data in the form of a raw byte sequence payload interspersed as necessary with emulation prevention bytes.
- [0128] As used herein, the term "common" generally refers to a syntax element or a variable that is applicable to more than one thing. For example, in the context of syntax elements in a picture timing SEI message, the term "common" may mean that the syntax element (e.g., `common_du_cpb_removal_delay`) is applicable to all decoding units in an access unit associated with the picture timing SEI message. Additionally, units of data are described in terms of "n" and "m" generally refer to access units and decoding units, respectively.
- [0129] Various configurations are now described with reference to the Figures, where like reference numbers may indicate functionally similar elements. The systems and methods as generally described and illustrated in the Figures herein could be arranged and designed in a wide variety of different configurations. Thus, the following more detailed description of several configurations, as represented in the Figures, is not intended to limit scope, as claimed, but is merely representative of the systems and

methods.

- [0130] Figure 1A is a block diagram illustrating an example of one or more electronic devices 102 in which systems and methods for sending a message and buffering a bitstream may be implemented. In this example, electronic device A 102a and electronic device B 102b are illustrated. However, it should be noted that one or more of the features and functionality described in relation to electronic device A 102a and electronic device B 102b may be combined into a single electronic device in some configurations.
- [0131] Electronic device A 102a includes an encoder 104. The encoder 104 includes a message generation module 108. Each of the elements included within electronic device A 102a (e.g., the encoder 104 and the message generation module 108) may be implemented in hardware, software or a combination of both.
- [0132] Electronic device A 102a may obtain one or more input pictures 106. In some configurations, the input picture(s) 106 may be captured on electronic device A 102a using an image sensor, may be retrieved from memory and/or may be received from another electronic device.
- [0133] The encoder 104 may encode the input picture(s) 106 to produce encoded data. For example, the encoder 104 may encode a series of input pictures 106 (e.g., video). In one configuration, the encoder 104 may be a HEVC encoder. The encoded data may be digital data (e.g., part of a bitstream 114). The encoder 104 may generate overhead signaling based on the input signal.
- [0134] The message generation module 108 may generate one or more messages. For example, the message generation module 108 may generate one or more SEI messages or other messages. For a CPB that supports operation on a sub-picture level, the electronic device 102 may send sub-picture parameters, (e.g., CPB removal delay parameter). Specifically, the electronic device 102 (e.g., the encoder 104) may determine whether to include a common decoding unit CPB removal delay parameter in a picture timing SEI message. For example, the electronic device may set a flag (e.g., `common_du_cpb_removal_delay_flag`) to one when the encoder 104 is including a common decoding unit CPB removal delay parameter (e.g., `common_du_cpb_removal_delay`) in the picture timing SEI message. When the common decoding unit CPB removal delay parameter is included, the electronic device may generate the common decoding unit CPB removal delay parameter that is applicable to all decoding units in an access unit. In other words, rather than including a decoding unit CPB removal delay parameter for each decoding unit in an access unit, a common parameter may apply to all decoding units in the access unit with which the picture timing SEI message is associated.
- [0135] In contrast, when the common decoding unit CPB removal delay parameter is not to

be included in the picture timing SEI message, the electronic device 102 may generate a separate decoding unit CPB removal delay for each decoding unit in the access unit with which the picture timing SEI message is associated. A message generation module 108 may perform one or more of the procedures described in connection with Figure 2 and Figure 3 below.

- [0136] In some configurations, electronic device A 102a may send the message to electronic device B 102b as part of the bitstream 114. In some configurations electronic device A 102a may send the message to electronic device B 102b by a separate transmission 110. For example, the separate transmission may not be part of the bitstream 114. For instance, a picture timing SEI message or other message may be sent using some out-of-band mechanism. It should be noted that, in some configurations, the other message may include one or more of the features of a picture timing SEI message described above. Furthermore, the other message, in one or more aspects, may be utilized similarly to the SEI message described above.
- [0137] The encoder 104 (and message generation module 108, for example) may produce a bitstream 114. The bitstream 114 may include encoded picture data based on the input picture(s) 106. In some configurations, the bitstream 114 may also include overhead data, such as a picture timing SEI message or other message, slice header(s), PPS(s), etc. As additional input pictures 106 are encoded, the bitstream 114 may include one or more encoded pictures. For instance, the bitstream 114 may include one or more encoded pictures with corresponding overhead data (e.g., a picture timing SEI message or other message).
- [0138] The bitstream 114 may be provided to a decoder 112. In one example, the bitstream 114 may be transmitted to electronic device B 102b using a wired or wireless link. In some cases, this may be done over a network, such as the Internet or a Local Area Network (LAN). As illustrated in Figure 1A, the decoder 112 may be implemented on electronic device B 102b separately from the encoder 104 on electronic device A 102a. However, it should be noted that the encoder 104 and decoder 112 may be implemented on the same electronic device in some configurations. In an implementation where the encoder 104 and decoder 112 are implemented on the same electronic device, for instance, the bitstream 114 may be provided over a bus to the decoder 112 or stored in memory for retrieval by the decoder 112.
- [0139] The decoder 112 may be implemented in hardware, software or a combination of both. In one configuration, the decoder 112 may be a HEVC decoder. The decoder 112 may receive (e.g., obtain) the bitstream 114. The decoder 112 may generate one or more decoded pictures 118 based on the bitstream 114. The decoded picture(s) 118 may be displayed, played back, stored in memory and/or transmitted to another device, etc.

- [0140] The decoder 112 may include a CPB 120. The CPB 120 may temporarily store encoded pictures. The CPB 120 may use parameters found in a picture timing SEI message to determine when to remove data. When the CPB 120 supports operation on a sub-picture level, individual decoding units may be removed rather than entire access units at one time. The decoder 112 may include a Decoded Picture Buffer (DPB) 122. Each decoded picture is placed in the DPB 122 for being referenced by the decoding process as well as for output and cropping. A decoded picture is removed from the DPB at the later of the DPB output time or the time that it becomes no longer needed for inter-prediction reference.
- [0141] The decoder 112 may receive a message (e.g., picture timing SEI message or other message). The decoder 112 may also determine whether the received message includes a common decoding unit CPB removal delay parameter (e.g., `common_du_cpb_removal_delay`). This may include identifying a flag (e.g., `common_du_cpb_removal_delay_flag`) that is set when the common parameter is present in the picture timing SEI message. If the common parameter is present, the decoder 112 may determine the common decoding unit CPB removal delay parameter applicable to all decoding units in the access unit. If the common parameter is not present, the decoder 112 may determine a separate decoding unit CPB removal delay parameter for each decoding unit in the access unit. The decoder 112 may also remove decoding units from the CPB 120 using either the common decoding unit CPB removal delay parameter or the separate decoding unit CPB removal delay parameters. The CPB 120 may perform one or more of the procedures described in connection with Figure 4 and Figure 5 below.
- [0142] The HRD described above may be one example of the decoder 112 illustrated in Figure 1A. Thus, an electronic device 102 may operate in accordance with the HRD and CPB 120 and DPB 122 described above, in some configurations.
- [0143] It should be noted that one or more of the elements or parts thereof included in the electronic device(s) 102 may be implemented in hardware. For example, one or more of these elements or parts thereof may be implemented as a chip, circuitry or hardware components, etc. It should also be noted that one or more of the functions or methods described herein may be implemented in and/or performed using hardware. For example, one or more of the methods described herein may be implemented in and/or realized using a chipset, an Application-Specific Integrated Circuit (ASIC), a Large-Scale Integrated circuit (LSI) or integrated circuit, etc.
- [0144] Figure 1B is a block diagram illustrating another example of an encoder 1908 and a decoder 1972. In this example, electronic device A 1902 and electronic device B 1970 are illustrated. However, it should be noted that the features and functionality described in relation to electronic device A 1902 and electronic device B 1970 may be

combined into a single electronic device in some configurations.

- [0145] Electronic device A 1902 includes the encoder 1908. The encoder 1908 may include a base layer encoder 1910 and an enhancement layer encoder 1920. The video encoder 1908 is suitable for scalable video coding and multi-view video coding, as described later. The encoder 1908 may be implemented in hardware, software or a combination of both. In one configuration, the encoder 1908 may be a high-efficiency video coding (HEVC) coder, including scalable and/or multi-view. Other coders may likewise be used. Electronic device A 1902 may obtain a source 1906. In some configurations, the source 1906 may be captured on electronic device A 1902 using an image sensor, retrieved from memory or received from another electronic device.
- [0146] The encoder 1908 may code the source 1906 to produce a base layer bitstream 1934 and an enhancement layer bitstream 1936. For example, the encoder 1908 may code a series of pictures (e.g., video) in the source 1906. In particular, for scalable video encoding for SNR scalability also known as quality scalability the same source 1906 may be provided to the base layer and the enhancement layer encoder. In particular, for scalable video encoding for spatial scalability a downsampled source may be used for the base layer encoder. In particular, for multi-view encoding a different view source may be used for the base layer encoder and the enhancement layer encoder. The encoder 1908 may be similar to the encoder 1782 described later in connection with Figure 6B.
- [0147] The bitstreams 1934, 1936 may include coded picture data based on the source 1906. In some configurations, the bitstreams 1934, 1936 may also include overhead data, such as slice header information, PPS information, etc. As additional pictures in the source 1906 are coded, the bitstreams 1934, 1936 may include one or more coded pictures.
- [0148] The bitstreams 1934, 1936 may be provided to the decoder 1972. The decoder 1972 may include a base layer decoder 1980 and an enhancement layer decoder 1990. The video decoder 1972 is suitable for scalable video decoding and multi-view video decoding. In one example, the bitstreams 1934, 1936 may be transmitted to electronic device B 1970 using a wired or wireless link. In some cases, this may be done over a network, such as the Internet or a Local Area Network (LAN). As illustrated in Figure 1B, the decoder 1972 may be implemented on electronic device B 1970 separately from the encoder 1908 on electronic device A 1902. However, it should be noted that the encoder 1908 and decoder 1972 may be implemented on the same electronic device in some configurations. In an implementation where the encoder 1908 and decoder 1972 are implemented on the same electronic device, for instance, the bitstreams 1934, 1936 may be provided over a bus to the decoder 1972 or stored in memory for retrieval by the decoder 1972. The decoder 1972 may provide a decoded base layer 1992 and

decoded enhancement layer picture(s) 1994 as output.

- [0149] The decoder 1972 may be implemented in hardware, software or a combination of both. In one configuration, the decoder 1972 may be a high-efficiency video coding (HEVC) decoder, including scalable and/or multi-view. Other decoders may likewise be used. The decoder 1972 may be similar to the decoder 1812 described later in connection with Figure 7B. Also, the base layer encoder and/or the enhancement layer encoder may each include a message generation module, such as that described in relation to Figure 1A. Also, the base layer decoder and/or the enhancement layer decoder may include a coded picture buffer and/or a decoded picture buffer, such as that described in relation to Figure 1A. In addition, the electronic devices of Figure 1B may operate in accordance with the functions of the electronic devices of Figure 1A, as applicable.
- [0150] Figure 2 is a flow diagram illustrating one configuration of a method 200 for sending a message. The method 200 may be performed by an encoder 104 or one of its sub-parts (e.g., a message generation module 108). The encoder 104 may determine 202 a picture timing flag (e.g., `sub_pic_cpb_params_present_flag`) that indicates whether a CPB 120 supports operation on a sub-picture level. For example, when the picture timing flag is set to 1, the CPB 120 may operate on an access unit level or a sub-picture level. It should be noted that even when the picture timing flag is set to 1, the decision about whether to actually operate at the sub-picture level is left to the decoder 112 itself.
- [0151] The encoder 104 may also determine 204 one or more removal delays for decoding units in an access unit. For example, the encoder 104 may determine a single common decoding unit CPB removal delay parameter (e.g., `common_du_cpb_removal_delay`) that is applicable to all decoding units in the access unit from the CPB 120. Alternatively, the encoder 104 may determine a separate decoding unit CPB removal delay (e.g., `du_cpb_removal_delay[i]`) for each decoding unit in the access unit.
- [0152] The encoder 104 may also determine 206 one or more NAL parameters that indicate an amount, offset by one, of NAL units in each decoding unit in the access point. For example, the encoder 104 may determine a single common NAL parameter (e.g., `common_num_nalus_in_du_minus1`) that is applicable to all decoding units in the access unit from the CPB 120. Alternatively, the encoder 104 may determine a separate decoding unit CPB removal delay (e.g., `num_nalus_in_du_minus1[i]`) for each decoding unit in the access unit.
- [0153] The encoder 104 may also send 208 a picture timing SEI message that includes the picture timing flag, the removal delays and the NAL parameters. The picture timing SEI message may also include other parameters (e.g., `cpb_removal_delay`, `dpb_output_delay`, etc). For example, the electronic device 102 may transmit the

message via one or more of wireless transmission, wired transmission, device bus, network, etc. For instance, electronic device A 102a may transmit the message to electronic device B 102b. The message may be part of the bitstream 114, for example. In some configurations, electronic device A 102a may send 208 the message to electronic device B 102b in a separate transmission 110 (that is not part of the bitstream 114). For instance, the message may be sent using some out-of-band mechanism. In some case the information indicated in 204, 206 may be sent in a SEI message different than picture timing SEI message. In yet another case the information indicated in 204, 206 may be sent in a parameter set e.g. video parameter set and/or sequence parameter set and/or picture parameter set and/or adaptation parameter set and/or slice header.

- [0154] Figure 3 is a flow diagram illustrating one configuration of a method 300 for determining one or more removal delays for decoding units in an access unit. In other words, the method 300 illustrated in Figure 3 may further illustrate step 204 in the method 200 illustrated in Figure 2. The method 300 may be performed by an encoder 104. The encoder 104 may determine 302 whether to include a common decoding unit CPB removal delay parameter (e.g., `common_du_cpb_removal_delay`). This may include determining whether a common decoding unit CPB removal delay flag (e.g., `common_du_cpb_removal_delay_flag`) is set. An encoder 104 may send this common parameter in case the decoding units are removed from the CPB at regular interval. This may be the case, for example, when each decoding unit corresponds to certain number of rows of the picture or has some other regular structure.
- [0155] For example, the common decoding unit CPB removal delay flag may be set to 1 when the common decoding unit CPB removal delay parameter is to be included in the picture timing SEI message and 0 when it is not to be included. If yes (e.g., flag is set to 1), the encoder 104 may determine 304 a common decoding unit CPB removal delay parameter (e.g., `common_du_cpb_removal_delay`) that is applicable to all decoding units in an access unit. If no (e.g., flag is set to 0), the encoder 104 may determine 306 separate decoding unit CPB removal delay parameters (e.g., `du_cpb_removal_delay[i]`) for each decoding unit in an access unit.
- [0156] If a common decoding unit CPB removal delay parameter is present in a picture timing SEI message, it may specify an amount of sub-picture clock ticks to wait after removal from the CPB 120 of an immediately preceding decoding unit before removing from the CPB 120 a current decoding unit in the access unit associated with the picture timing SEI message.
- [0157] For example, when a decoding unit is a first decoding unit in an access unit, the common decoding unit CPB 120 removal delay parameter may specify an amount of sub-picture clock ticks to wait after removal from the CPB 120 of a last decoding unit

in an access unit associated with a most recent buffering period SEI message in a preceding access unit before removing from the CPB 120 the first decoding unit in the access unit associated with the picture timing SEI message.

[0158] When the decoding unit is a non-first decoding unit in an access unit, the common decoding unit CPB removal delay parameter may specify an amount of sub-picture clock ticks to wait after removal from the CPB 120 of a preceding decoding unit in the access unit associated with the picture timing SEI message before removing from the CPB a current decoding unit in the access unit associated with the picture timing SEI message.

[0159] In contrast, when a common decoding unit CPB removal delay parameter (e.g., `common_du_cpb_removal_delay`) is not sent in a picture timing SEI message, separate decoding unit CPB removal delay parameters (e.g., `du_cpb_removal_delay[i]`) may be included in the picture timing SEI message for each decoding unit in an access unit. The decoding unit CPB removal delay parameters (e.g., `du_cpb_removal_delay[i]`) may specify an amount of sub-picture clock ticks to wait after removal from the CPB 120 of the last decoding unit before removing from the CPB 120 an i-th decoding unit in the access unit associated with the picture timing SEI message. The decoding unit CPB removal delay parameters may be calculated according to a remainder of a modulo $2^{(\text{cpb_removal_delay_length_minus1} + 1)}$ counter where `cpb_removal_delay_length_minus1 + 1` is a length of a common decoding unit CPB removal delay parameter.

[0160] Figure 4 is a flow diagram illustrating one configuration of a method 400 for buffering a bitstream. The method 400 may be performed by a decoder 112 in an electronic device 102 (e.g., electronic device B 102b), which may receive 402 a message (e.g., a picture timing SEI message or other message). For example, the electronic device 102 may receive 402 the message via one or more of wireless transmission, wired transmission, device bus, network, etc. For instance, electronic device B 102b may receive 402 the message from electronic device A 102a. The message may be part of the bitstream 114, for example. In another example, electronic device B 102b may receive the message from electronic device A 102a in a separate transmission 110 (that is not part of the bitstream 114, for example). For instance, the picture timing SEI message may be received using some out-of-band mechanism. In some configurations, the message may include one or more of a picture timing flag, one or more removal delays for decoding units in an access unit and one or more NAL parameters. Thus, receiving 402 the message may include receiving one or more of a picture timing flag, one or more removal delays for decoding units in an access unit and one or more NAL parameters.

[0161] The decoder 112 may determine 404 whether a CPB 120 operates on an access unit level or a sub-picture level. For example, a decoder 112 may decide to operate on sub-

picture basis if it wants to achieve low latency. Alternatively, the decision may be based on whether the decoder 112 has enough resources to support sub-picture based operation. If the CPB 120 operates on a sub-picture level, the decoder may determine 406 one or more removal delays for decoding units in an access unit. For example, the decoder 112 may determine a single common decoding unit CPB removal delay parameter (e.g., `common_du_cpb_removal_delay`) that is applicable to all decoding units in the access unit. Alternatively, the decoder 112 may determine a separate decoding unit CPB removal delay (e.g., `du_cpb_removal_delay[i]`) for each decoding unit in the access unit. In other words, the picture timing SEI message may include a common parameter applicable to all decoding units in an access unit or separate parameters for every decoding unit.

[0162] The decoder 112 may also remove 408 decoding units based on the removal delays for the decoding units, i.e., using either a common parameter applicable to all decoding units in an access unit or separate parameters for every decoding unit. The decoder 112 may also decode 410 the decoding units.

[0163] The decoder 112 may use a variable `ClockDiff` when determining a removal time for determined from various signaled parameters. Specifically, `ClockDiff` may be determined according to `ClockDiff =`

$$(\text{num_units_in_tick} - (\text{num_units_in_sub_tick} * (\text{num_decoding_units_minus1} + 1)) / \text{time_scale})$$
 where `num_units_in_tick` is number of time units of a clock operating at the frequency `time_scale` Hz that corresponds to one increment of a clock tick counter, `num_units_in_sub_tick` is number of time units of a clock operating at the frequency `time_scale` Hz that corresponds to one increment of a sub-picture clock tick counter, `num_decoding_units_minus1+1` is an amount of decoding units in the access unit, and `time_scale` is the number of time units that pass in one second.

[0164] When a low delay hypothetical reference decoder (HRD) flag (e.g., `low_delay_hrd_flag`) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1, the CPB is operating at sub-picture level and `ClockDiff` is greater than zero, the removal time for decoding unit `m`, $t_r(m)$ is determined according to: $t_r(m) = t_{r,n}(m) + t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub}) + \text{ClockDiff}$ where $t_{r,n}(m)$ is the nominal removal time of the decoding unit `m`, t_{c_sub} is a sub-picture clock tick, `Ceil()` is a ceiling function and $t_{af}(m)$ is final arrival time of decoding unit `m`.

[0165] When a low delay hypothetical reference decoder (HRD) flag (e.g., `low_delay_hrd_flag`) is set to 1, $t_{r,n}(n) < t_{af}(n)$, a picture timing flag is set to 1, the CPB is operating at an access unit level and `ClockDiff` is greater than zero, the removal time for access unit `n`, $t_r(n)$ is determined according to: $t_r(n) = t_{r,n}(n) + t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c) - \text{ClockDiff}$ where $t_{r,n}(n)$ is the nominal removal time of the access unit `n`, t_c is a clock tick, `Ceil()` is a ceiling function and $t_{af}(n)$ is a final arrival time of

access unit n.

- [0166] When a low delay hypothetical reference decoder (HRD) flag (e.g., low_delay_hrd_flag) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the last decoding unit m of access unit, $t_r(m)$ according to: $t_r(m) = t_{r,n}(m) + \max((t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub})), (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c)))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m, t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m, $t_{r,n}(n)$ is the nominal removal time of the access unit n, t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n.
- [0167] When a low delay hypothetical reference decoder (HRD) flag is set to 1, $t_{r,n}(n) < t_{af}(n)$, a picture timing flag is set to 1 and the CPB is operating at access unit level, the removal time for access unit n, $t_r(n)$ according to: $t_r(n) = t_{r,n}(n) + \max((t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub})), (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c)))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit n, t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m, $t_{r,n}(n)$ is the nominal removal time of the access unit n, t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n.
- [0168] When a low delay hypothetical reference decoder (HRD) flag (e.g., low_delay_hrd_flag) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the last decoding unit m of access unit, $t_r(m)$ according to: $t_r(m) = t_{r,n}(m) + \min((t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub})), (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c)))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m, t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m, $t_{r,n}(n)$ is the nominal removal time of the access unit n, t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n.
- [0169] When a low delay hypothetical reference decoder (HRD) flag is set to 1, $t_{r,n}(n) < t_{af}(n)$, a picture timing flag is set to 1 and the CPB is operating at access unit level, the removal time for access unit n, $t_r(n)$ according to: $t_r(n) = t_{r,n}(n) + \min((t_{c_sub} * \text{Ceil}((t_{af}(m) - t_{r,n}(m)) / t_{c_sub})), (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c)))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit n, t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m, $t_{r,n}(n)$ is the nominal removal time of the access unit n, t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n.
- [0170] When a low delay hypothetical reference decoder (HRD) flag (e.g., low_delay_hrd_flag) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the last decoding unit m of access unit, $t_r(m)$ according to: $t_r(m) = t_{r,n}(m) + (t_c * \text{Ceil}((t_{af}(n) - t_{r,n}(n)) / t_c))$

where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m , t_{c_sub} is sub-picture clock tick, $Ceil()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n .

[0171] When a low delay hypothetical reference decoder (HRD) flag is set to 1, $t_{r,n}(n) < t_{af}(n)$, a picture timing flag is set to 1 and the CPB is operating at access unit level, the removal time for access unit n , $t_r(n)$ according to: $t_r(n) = t_{r,n}(n) + (t_c * Ceil((t_{af}(n) - t_{r,n}(n)) / t_c))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit n , t_{c_sub} is sub-picture clock tick, $Ceil()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n .

[0172] When a low delay hypothetical reference decoder (HRD) flag (e.g., `low_delay_hrd_flag`) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the decoding unit which is not the last decoding unit of the access unit is set as $t_r(m) = t_{af}(m)$, where $t_{af}(m)$ is a final arrival time of decoding unit m . And the removal time for the last decoding unit m of access unit, $t_r(m)$ according to: $t_r(m) = t_{r,n}(m) + (t_{c_sub} * Ceil((t_{af}(m) - t_{r,n}(m)) / t_{c_sub}))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m , t_{c_sub} is sub-picture clock tick, $Ceil()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick, $t_{af}(n)$ is a final arrival time of access unit n and $t_{af}(m)$ is a final arrival time of the last decoding unit in the access unit n .

[0173] When a low delay hypothetical reference decoder (HRD) flag (e.g., `low_delay_hrd_flag`) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the decoding unit which is not the last decoding unit of the access unit is set as $t_r(m) = t_{af}(m)$, where $t_{af}(m)$ is a final arrival time of decoding unit m . And the removal time for the last decoding unit m of access unit, $t_r(m)$ according to: $t_r(m) = t_{r,n}(m) + (t_c * Ceil((t_{af}(m) - t_{r,n}(m)) / t_c))$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit m , t_{c_sub} is sub-picture clock tick, $Ceil()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick, $t_{af}(n)$ is a final arrival time of access unit n and $t_{af}(m)$ is a final arrival time of the last decoding unit in the access unit n .

[0174] When a low delay hypothetical reference decoder (HRD) flag (e.g., `low_delay_hrd_flag`) is set to 1, $t_{r,n}(m) < t_{af}(m)$, a picture timing flag is set to 1 and the CPB is operating at sub-picture level, the removal time for the decoding unit is set as $t_r(m) = t_{af}(m)$ where $t_{r,n}(m)$ is the nominal removal time of the decoding unit m , t_{c_sub} is sub-picture clock tick, $Ceil()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of

decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick, $t_{af}(n)$ is a final arrival time of access unit n and $t_{af}(m)$ is a final arrival time of the decoding unit in the access unit n .

- [0175] When a low delay hypothetical reference decoder (HRD) flag is set to 1, $t_{r,n}(n) < t_{af}(n)$, a picture timing flag is set to 1 and the CPB is operating at access unit level, the removal time for access unit n , $t_r(n)$ according to: $t_r(n) = t_{af}(n)$ where $t_{r,n}(m)$ is the nominal removal time of the last decoding unit n , t_{c_sub} is sub-picture clock tick, $\text{Ceil}()$ is a ceiling function, $t_{af}(m)$ is a final arrival time of last decoding unit m , $t_{r,n}(n)$ is the nominal removal time of the access unit n , t_c is clock tick and $t_{af}(n)$ is a final arrival time of access unit n .
- [0176] If the CPB operates on an access unit level, the decoder 112 may determine 412 a CPB removal delay parameter. This may be included in the received picture timing SEI message (e.g., `cpb_removal_delay`). The decoder 112 may also remove 414 an access unit based on the CPB removal delay parameter and decode 416 the access unit. In other words, the decoder 112 may decode whole access units at a time, rather than decoding units within the access unit.
- [0177] Figure 5 is a flow diagram illustrating one configuration of a method 500 for determining one or more removal delays for decoding units in an access unit. In other words, the method 500 illustrated in Figure 5 may further illustrate step 406 in the method 400 illustrated in Figure 4. The method 500 may be performed by a decoder 112. The decoder 112 may determine 502 whether a received picture timing SEI message includes a common decoding unit CPB removal delay parameter. This may include determining whether a common decoding unit CPB removal delay flag (e.g., `common_du_cpb_removal_delay_flag`) is set. If yes, the decoder 112 may determine 504 a common decoding unit CPB removal delay parameter (e.g., `common_du_cpb_removal_delay`) that is applicable to all decoding units in an access unit. If no, the decoder 112 may determine 506 separate decoding unit CPB removal delay parameters (e.g., `du_cpb_removal_delay[i]`) for each decoding unit in an access unit.
- [0178] In addition to modifying the picture timing SEI message semantics, the present systems and methods may also impose a bitstream constraint so that the operation of sub-picture based CPB operation and access unit based CPB operation result in the same timing of decoding unit removal. Specifically, when the picture timing flag (e.g., `sub_pic_cpb_params_present_flag`) is set to 1, the CPB removal delay may be set according to

$$\text{cpb_removal_delay} = \frac{\left(\sum_{i=0}^{\text{num_decoding_units_minus1}} \text{du_cpb_removal_delay}[i] \right) * t_{c,sub}}{t_c}$$

where $\text{du_cpb_removal_delay}[i]$ are the decoding unit CPB removal delay parameters, t_c is a clock tick, $t_{c,sub}$ is a sub-picture clock tick, $\text{num_decoding_units_minus1}$ is an amount of decoding units in the access unit offset by one, and i is an index.

[0179] Alternatively, the CPB removal delay may be set as described next: Let the variable $T_{du}(k)$ be defined as:

$$T_{du}(k) = T_{du}(k-1) + t_{c,sub} * \sum_{i=0}^{\text{num_decoding_units_minus1}_k} (\text{du_cpb_removal_delay_minus1}_k[i] + 1)$$

where $\text{du_cpb_removal_delay_minus1}_k[i]$ and $\text{num_decoding_units_minus1}_k$ are parameters for i 'th decoding unit of k 'th access unit (with $k=0$ for the access unit that initialized the HRD and $T_{du}(k)=0$ for $k<1$), and where $\text{du_cpb_removal_delay_minus1}_k[i] + 1 = \text{du_cpb_removal_delay_minus1}_k[i]$ is the decoding unit CPB removal delay parameter for the i 'th decoding unit of the k 'th access unit, and $\text{num_decoding_units_minus1}_k$ is the number of decoding units in the k 'th access unit, t_c is a clock tick, $t_{c,sub}$ is a sub-picture clock tick, and i and k are an indices. Then when the picture timing flag (e.g., $\text{sub_pic_cpb_params_present_flag}$) is set to 1, the following condition may be true:

[0180] $(\text{au_cpb_removal_delay_minus1} + 1) * t_c == T_{du}(k)$, where $(\text{au_cpb_removal_delay_minus1} + 1) = \text{cpb_removal_delay}$, the CPB removal delay. Thus in this case the CPB removal delay $(\text{au_cpb_removal_delay_minus1} + 1)$ is set such that the operation of sub-picture based CPB operation and access unit based CPB operation result in the same timing of access unit removal and last decoding unit of the access unit removal.

[0181] Alternatively, the CPB removal delay may be set according to

$$-1 \leq [\text{cpb_removal_delay} * t_c - \left(\sum_{i=0}^{\text{num_decoding_units_minus1}} \text{du_cpb_removal_delay}[i] \right) * t_{c,sub}] \leq 1$$

where $\text{du_cpb_removal_delay}[i]$ are the decoding unit CPB removal delay parameters, t_c is a clock tick, $t_{c,sub}$ is a sub-picture clock tick, $\text{num_decoding_units_minus1}$ is an amount of decoding units in the access unit offset by one, and i is an index.

[0182] Alternatively, cpb_removal_delay and $\text{du_cpb_removal_delay}[\text{num_decoding_units_minus1}]$ may be set according to:
 $\text{cpb_removal_delay} * t_c = \text{du_cpb_removal_delay}[\text{num_decoding_units_minus1}] * t_{c,sub}$
 where $\text{du_cpb_removal_delay}[\text{num_decoding_units_minus1}]$ is the decoding unit CPB

removal delay parameter for the num_decoding_units_minus1'th decoding unit, t_c is a clock tick, $t_{c,sub}$ is a sub-picture clock tick, num_decoding_units_minus1 is an amount of decoding units in the access unit offset by one.

[0183] In addition to modifying the picture timing SEI message semantics, the present systems and methods may also impose a bitstream constraint so that the operation of sub-picture based CPB operation and access unit based CPB operation result in the same timing of decoding unit removal. Specifically, when the picture timing flag (e.g., sub_pic_cpb_params_present_flag) is set to 1, the values for cpb_removal_delay and du_cpb_removal_delay[num_decoding_units_minus1] may be set so as to satisfy: $-1 \leq (cpb_removal_delay * t_c - du_cpb_removal_delay[num_decoding_units_minus1] * t_{c,sub}) \leq 1$ where du_cpb_removal_delay[num_decoding_units_minus1] is the decoding unit CPB removal delay parameter for the num_decoding_units_minus1'th decoding unit, t_c is a clock tick, $t_{c,sub}$ is a sub-picture clock tick, num_decoding_units_minus1 is an amount of decoding units in the access unit offset by one.

[0184] Figure 6A is a block diagram illustrating one configuration of an encoder 604 on an electronic device 602. It should be noted that one or more of the elements illustrated as included within the electronic device 602 may be implemented in hardware, software or a combination of both. For example, the electronic device 602 includes an encoder 604, which may be implemented in hardware, software or a combination of both. For instance, the encoder 604 may be implemented as a circuit, integrated circuit, application-specific integrated circuit (ASIC), processor in electronic communication with memory with executable instructions, firmware, field-programmable gate array (FPGA), etc., or a combination thereof. In some configurations, the encoder 604 may be a HEVC coder.

[0185] The electronic device 602 may include a source 622. The source 622 may provide picture or image data (e.g., video) as one or more input pictures 606 to the encoder 604. Examples of the source 622 may include image sensors, memory, communication interfaces, network interfaces, wireless receivers, ports, etc.

[0186] One or more input pictures 606 may be provided to an intra-frame prediction module and reconstruction buffer 624. An input picture 606 may also be provided to a motion estimation and motion compensation module 646 and to a subtraction module 628.

[0187] The intra-frame prediction module and reconstruction buffer 624 may generate intra mode information 640 and an intra-signal 626 based on one or more input pictures 606 and reconstructed data 660. The motion estimation and motion compensation module 646 may generate inter mode information 648 and an inter signal 644 based on one or more input pictures 606 and a reference picture 678 from decoded picture buffer 676. In some configurations, the decoded picture buffer 676 may include data from one or more reference pictures in the decoded picture buffer 676.

- [0188] The encoder 604 may select between the intra signal 626 and the inter signal 644 in accordance with a mode. The intra signal 626 may be used in order to exploit spatial characteristics within a picture in an intra-coding mode. The inter signal 644 may be used in order to exploit temporal characteristics between pictures in an inter coding mode. While in the intra coding mode, the intra signal 626 may be provided to the subtraction module 628 and the intra mode information 640 may be provided to an entropy coding module 642. While in the inter coding mode, the inter signal 644 may be provided to the subtraction module 628 and the inter mode information 648 may be provided to the entropy coding module 642.
- [0189] Either the intra signal 626 or the inter signal 644 (depending on the mode) is subtracted from an input picture 606 at the subtraction module 628 in order to produce a prediction residual 630. The prediction residual 630 is provided to a transformation module 632. The transformation module 632 may compress the prediction residual 630 to produce a transformed signal 634 that is provided to a quantization module 636. The quantization module 636 quantizes the transformed signal 634 to produce transformed and quantized coefficients (TQCs) 638.
- [0190] The TQCs 638 are provided to an entropy coding module 642 and an inverse quantization module 650. The inverse quantization module 650 performs inverse quantization on the TQCs 638 to produce an inverse quantized signal 652 that is provided to an inverse transformation module 654. The inverse transformation module 654 decompresses the inverse quantized signal 652 to produce a decompressed signal 656 that is provided to a reconstruction module 658.
- [0191] The reconstruction module 658 may produce reconstructed data 660 based on the decompressed signal 656. For example, the reconstruction module 658 may reconstruct (modified) pictures. The reconstructed data 660 may be provided to a deblocking filter 662 and to the intra prediction module and reconstruction buffer 624. The deblocking filter 662 may produce a filtered signal 664 based on the reconstructed data 660.
- [0192] The filtered signal 664 may be provided to a sample adaptive offset (SAO) module 666. The SAO module 666 may produce SAO information 668 that is provided to the entropy coding module 642 and an SAO signal 670 that is provided to an adaptive loop filter (ALF) 672. The ALF 672 produces an ALF signal 674 that is provided to the decoded picture buffer 676. The ALF signal 674 may include data from one or more pictures that may be used as reference pictures.
- [0193] The entropy coding module 642 may code the TQCs 638 to produce bitstream A 614a (e.g., encoded picture data). For example, the entropy coding module 642 may code the TQCs 638 using Context-Adaptive Variable Length Coding (CAVLC) or Context-Adaptive Binary Arithmetic Coding (CABAC). In particular, the entropy coding module 642 may code the TQCs 638 based on one or more of intra mode in-

formation 640, inter mode information 648 and SAO information 668. Bitstream A 614a (e.g., encoded picture data) may be provided to a message generation module 608. The message generation module 608 may be configured similarly to the message generation module 108 described in connection with Figure 1. Additionally or alternatively, the message generation module 608 may perform one or more of the procedures described in connection with Figure 2 and Figure 3.

[0194] For example, the message generation module 608 may generate a message (e.g., picture timing SEI message or other message) including sub-picture parameters. The sub-picture parameters may include one or more removal delays for decoding units (e.g., `common_du_cpb_removal_delay` or `du_cpb_removal_delay[i]`) and one or more NAL parameters (e.g., `common_num_nalus_in_du_minus1` or `num_nalus_in_du_minus1[i]`). In some configurations, the message may be inserted into bitstream A 614a to produce bitstream B 614b. Thus, the message may be generated after the entire bitstream A 614a is generated (e.g., after most of bitstream B 614b is generated), for example. In other configurations, the message may not be inserted into bitstream A 614a (in which case bitstream B 614b may be the same as bitstream A 614a), but may be provided in a separate transmission 610.

[0195] In some configurations, the electronic device 602 sends the bitstream 614 to another electronic device. For example, the bitstream 614 may be provided to a communication interface, network interface, wireless transmitter, port, etc. For instance, the bitstream 614 may be transmitted to another electronic device via LAN, the Internet, a cellular phone base station, etc. The bitstream 614 may additionally or alternatively be stored in memory or other component on the electronic device 602.

[0196] Figure 6B is a block diagram illustrating one configuration of a video encoder 1782 on an electronic device 1702. The video encoder 1782 may include an enhancement layer encoder 1706, a base layer encoder 1709, a resolution upscaling block 1770 and an output interface 1780. The video encoder of Figure 6B, for example, is suitable for scalable video coding and multi-view video coding, as described herein.

[0197] The enhancement layer encoder 1706 may include a video input 1781 that receives an input picture 1704. The output of the video input 1781 may be provided to an adder/subtractor 1783 that receives an output of a prediction selection 1750. The output of the adder/subtractor 1783 may be provided to a transform and quantize block 1752. The output of the transform and quantize block 1752 may be provided to an entropy encoding 1748 block and a scaling and inverse transform block 1772. After entropy encoding 1748 is performed, the output of the entropy encoding block 1748 may be provided to the output interface 1780. The output interface 1780 may output both the encoded base layer video bitstream 1707 and the encoded enhancement layer video bitstream 1710.

- [0198] The output of the scaling and inverse transform block 1772 may be provided to an adder 1779. The adder 1779 may also receive the output of the prediction selection 1750. The output of the adder 1779 may be provided to a deblocking block 1751. The output of the deblocking block 1751 may be provided to a reference buffer 1794. An output of the reference buffer 1794 may be provided to a motion compensation block 1754. The output of the motion compensation block 1754 may be provided to the prediction selection 1750. An output of the reference buffer 1794 may also be provided to an intra predictor 1756. The output of the intra predictor 1756 may be provided to the prediction selection 1750. The prediction selection 1750 may also receive an output of the resolution upscaling block 1770.
- [0199] The base layer encoder 1709 may include a video input 1762 that receives a downsampled input picture, or other image content suitable for combining with another image, or an alternative view input picture or the same input picture 1703 (i.e., the same as the input picture 1704 received by the enhancement layer encoder 1706). The output of the video input 1762 may be provided to an encoding prediction loop 1764. Entropy encoding 1766 may be provided on the output of the encoding prediction loop 1764. The output of the encoding prediction loop 1764 may also be provided to a reference buffer 1768. The reference buffer 1768 may provide feedback to the encoding prediction loop 1764. The output of the reference buffer 1768 may also be provided to the resolution upscaling block 1770. Once entropy encoding 1766 has been performed, the output may be provided to the output interface 1780. The encoded base layer video bitstream 1707 and/or the encoded enhancement layer video bitstream 1710 may be provided to one or more message generation modules, as desired.
- [0200] Figure 7A is a block diagram illustrating one configuration of a decoder 712 on an electronic device 702. The decoder 712 may be included in an electronic device 702. For example, the decoder 712 may be a HEVC decoder. The decoder 712 and one or more of the elements illustrated as included in the decoder 712 may be implemented in hardware, software or a combination of both. The decoder 712 may receive a bitstream 714 (e.g., one or more encoded pictures and overhead data included in the bitstream 714) for decoding. In some configurations, the received bitstream 714 may include received overhead data, such as a message (e.g., picture timing SEI message or other message), slice header, PPS, etc. In some configurations, the decoder 712 may additionally receive a separate transmission 710. The separate transmission 710 may include a message (e.g., a picture timing SEI message or other message). For example, a picture timing SEI message or other message may be received in a separate transmission 710 instead of in the bitstream 714. However, it should be noted that the separate transmission 710 may be optional and may not be utilized in some configurations.

- [0201] The decoder 712 includes a CPB 720. The CPB 720 may be configured similarly to the CPB 120 described in connection with Figure 1 above. Additionally or alternatively, the decoder 712 may perform one or more of the procedures described in connection with Figure 4 and Figure 5. For example, the decoder 712 may receive a message (e.g., picture timing SEI message or other message) with sub-picture parameters and remove and decode decoding units in an access unit based on the sub-picture parameters. It should be noted that one or more access units may be included in the bitstream and may include one or more of encoded picture data and overhead data.
- [0202] The Coded Picture Buffer (CPB) 720 may provide encoded picture data to an entropy decoding module 701. The encoded picture data may be entropy decoded by an entropy decoding module 701, thereby producing a motion information signal 703 and quantized, scaled and/or transformed coefficients 705.
- [0203] The motion information signal 703 may be combined with a portion of a reference frame signal 798 from a decoded picture buffer 709 at a motion compensation module 780, which may produce an inter-frame prediction signal 782. The quantized, descaled and/or transformed coefficients 705 may be inverse quantized, scaled and inverse transformed by an inverse module 707, thereby producing a decoded residual signal 784. The decoded residual signal 784 may be added to a prediction signal 792 to produce a combined signal 786. The prediction signal 792 may be a signal selected from either the inter-frame prediction signal 782 produced by the motion compensation module 780 or an intra-frame prediction signal 790 produced by an intra-frame prediction module 788. In some configurations, this signal selection may be based on (e.g., controlled by) the bitstream 714.
- [0204] The intra-frame prediction signal 790 may be predicted from previously decoded information from the combined signal 786 (in the current frame, for example). The combined signal 786 may also be filtered by a de-blocking filter 794. The resulting filtered signal 796 may be written to decoded picture buffer 709. The resulting filtered signal 796 may include a decoded picture. The decoded picture buffer 709 may provide a decoded picture which may be outputted 718. In some cases 709 may be considered as frame memory.
- [0205] Figure 7B is a block diagram illustrating one configuration of a video decoder 1812 on an electronic device 1802. The video decoder 1812 may include an enhancement layer decoder 1815 and a base layer decoder 1813. The video decoder 812 may also include an interface 1889 and resolution upscaling 1870. The video decoder of Figure 7B, for example, is suitable for scalable video coding and multi-view video encoded, as described herein.
- [0206] The interface 1889 may receive an encoded video stream 1885. The encoded video stream 1885 may consist of base layer encoded video stream and enhancement layer

encoded video stream. These two streams may be sent separately or together. The interface 1889 may provide some or all of the encoded video stream 1885 to an entropy decoding block 1886 in the base layer decoder 1813. The output of the entropy decoding block 1886 may be provided to a decoding prediction loop 1887. The output of the decoding prediction loop 1887 may be provided to a reference buffer 1888. The reference buffer may provide feedback to the decoding prediction loop 1887. The reference buffer 1888 may also output the decoded base layer video stream 1884.

[0207] The interface 1889 may also provide some or all of the encoded video stream 1885 to an entropy decoding block 1890 in the enhancement layer decoder 1815. The output of the entropy decoding block 1890 may be provided to an inverse quantization block 1891. The output of the inverse quantization block 1891 may be provided to an adder 1892. The adder 1892 may add the output of the inverse quantization block 1891 and the output of a prediction selection block 1895. The output of the adder 1892 may be provided to a deblocking block 1893. The output of the deblocking block 1893 may be provided to a reference buffer 1894. The reference buffer 1894 may output the decoded enhancement layer video stream 1882. The output of the reference buffer 1894 may also be provided to an intra predictor 1897. The enhancement layer decoder 1815 may include motion compensation 1896. The motion compensation 1896 may be performed after the resolution upscaling 1870. The prediction selection block 1895 may receive the output of the intra predictor 1897 and the output of the motion compensation 1896. Also, the decoder may include one or more coded picture buffers, as desired, such as together with the interface 1889.

[0208] Figure 8 illustrates various components that may be utilized in a transmitting electronic device 802. One or more of the electronic devices 102, 602, 702 described herein may be implemented in accordance with the transmitting electronic device 802 illustrated in Figure 8.

[0209] The transmitting electronic device 802 includes a processor 817 that controls operation of the electronic device 802. The processor 817 may also be referred to as a CPU. Memory 811, which may include both read-only memory (ROM), random access memory (RAM) or any type of device that may store information, provides instructions 813a (e.g., executable instructions) and data 815a to the processor 817. A portion of the memory 811 may also include non-volatile random access memory (NVRAM). The memory 811 may be in electronic communication with the processor 817.

[0210] Instructions 813b and data 815b may also reside in the processor 817. Instructions 813b and/or data 815b loaded into the processor 817 may also include instructions 813a and/or data 815a from memory 811 that were loaded for execution or processing by the processor 817. The instructions 813b may be executed by the processor 817 to implement the systems and methods disclosed herein. For example, the instructions

813b may be executable to perform one or more of the methods 200, 300, 400, 500 described above.

- [0211] The transmitting electronic device 802 may include one or more communication interfaces 819 for communicating with other electronic devices (e.g., receiving electronic device). The communication interfaces 819 may be based on wired communication technology, wireless communication technology, or both. Examples of a communication interface 819 include a serial port, a parallel port, a Universal Serial Bus (USB), an Ethernet adapter, an IEEE 1394 bus interface, a small computer system interface (SCSI) bus interface, an infrared (IR) communication port, a Bluetooth wireless communication adapter, a wireless transceiver in accordance with 3rd Generation Partnership Project (3GPP) specifications and so forth.
- [0212] The transmitting electronic device 802 may include one or more output devices 823 and one or more input devices 821. Examples of output devices 823 include a speaker, printer, etc. One type of output device that may be included in an electronic device 802 is a display device 825. Display devices 825 used with configurations disclosed herein may utilize any suitable image projection technology, such as a cathode ray tube (CRT), liquid crystal display (LCD), light-emitting diode (LED), gas plasma, electroluminescence or the like. A display controller 827 may be provided for converting data stored in the memory 811 into text, graphics, and/or moving images (as appropriate) shown on the display 825. Examples of input devices 821 include a keyboard, mouse, microphone, remote control device, button, joystick, trackball, touchpad, touchscreen, lightpen, etc.
- [0213] The various components of the transmitting electronic device 802 are coupled together by a bus system 829, which may include a power bus, a control signal bus and a status signal bus, in addition to a data bus. However, for the sake of clarity, the various buses are illustrated in Figure 8 as the bus system 829. The transmitting electronic device 802 illustrated in Figure 8 is a functional block diagram rather than a listing of specific components.
- [0214] Figure 9 is a block diagram illustrating various components that may be utilized in a receiving electronic device 902. One or more of the electronic devices 102, 602, 702 described herein may be implemented in accordance with the receiving electronic device 902 illustrated in Figure 9.
- [0215] The receiving electronic device 902 includes a processor 917 that controls operation of the electronic device 902. The processor 917 may also be referred to as a CPU. Memory 911, which may include both read-only memory (ROM), random access memory (RAM) or any type of device that may store information, provides instructions 913a (e.g., executable instructions) and data 915a to the processor 917. A portion of the memory 911 may also include non-volatile random access memory (NVRAM).

The memory 911 may be in electronic communication with the processor 917.

- [0216] Instructions 913b and data 915b may also reside in the processor 917. Instructions 913b and/or data 915b loaded into the processor 917 may also include instructions 913a and/or data 915a from memory 911 that were loaded for execution or processing by the processor 917. The instructions 913b may be executed by the processor 917 to implement the systems and methods disclosed herein. For example, the instructions 913b may be executable to perform one or more of the methods 200, 300, 400, 500 described above.
- [0217] The receiving electronic device 902 may include one or more communication interfaces 919 for communicating with other electronic devices (e.g., a transmitting electronic device). The communication interface 919 may be based on wired communication technology, wireless communication technology, or both. Examples of a communication interface 919 include a serial port, a parallel port, a Universal Serial Bus (USB), an Ethernet adapter, an IEEE 1394 bus interface, a small computer system interface (SCSI) bus interface, an infrared (IR) communication port, a Bluetooth wireless communication adapter, a wireless transceiver in accordance with 3rd Generation Partnership Project (3GPP) specifications and so forth.
- [0218] The receiving electronic device 902 may include one or more output devices 923 and one or more input devices 921. Examples of output devices 923 include a speaker, printer, etc. One type of output device that may be included in an electronic device 902 is a display device 925. Display devices 925 used with configurations disclosed herein may utilize any suitable image projection technology, such as a cathode ray tube (CRT), liquid crystal display (LCD), light-emitting diode (LED), gas plasma, electroluminescence or the like. A display controller 927 may be provided for converting data stored in the memory 911 into text, graphics, and/or moving images (as appropriate) shown on the display 925. Examples of input devices 921 include a keyboard, mouse, microphone, remote control device, button, joystick, trackball, touchpad, touchscreen, lightpen, etc.
- [0219] The various components of the receiving electronic device 902 are coupled together by a bus system 929, which may include a power bus, a control signal bus and a status signal bus, in addition to a data bus. However, for the sake of clarity, the various buses are illustrated in Figure 9 as the bus system 929. The receiving electronic device 902 illustrated in Figure 9 is a functional block diagram rather than a listing of specific components.
- [0220] Figure 10 is a block diagram illustrating one configuration of an electronic device 1002 in which systems and methods for sending a message may be implemented. The electronic device 1002 includes encoding means 1031 and transmitting means 1033. The encoding means 1031 and transmitting means 1033 may be configured to perform

one or more of the functions described in connection with one or more of Figure 1, Figure 2, Figure 3, Figure 6 and Figure 8 above. For example, the encoding means 1031 and transmitting means 1033 may generate a bitstream 1014. Figure 8 above illustrates one example of a concrete apparatus structure of Figure 10. Other various structures may be implemented to realize one or more of the functions of Figure 1, Figure 2, Figure 3, Figure 6 and Figure 8. For example, a DSP may be realized by software.

[0221] Figure 11 is a block diagram illustrating one configuration of an electronic device 1102 in which systems and methods for buffering a bitstream 1114 may be implemented. The electronic device 1102 may include receiving means 1135 and decoding means 1137. The receiving means 1135 and decoding means 1137 may be configured to perform one or more of the functions described in connection with one or more of Figure 1, Figure 4, Figure 5, Figure 7 and Figure 9 above. For example, the receiving means 1135 and decoding means 1137 may receive a bitstream 1114. Figure 9 above illustrates one example of a concrete apparatus structure of Figure 11. Other various structures may be implemented to realize one or more functions of Figure 1, Figure 4, Figure 5, Figure 7 and Figure 9. For example, a DSP may be realized by software.

[0222] Figure 12 is a flow diagram illustrating one configuration of a method 1200 for operation of decoded picture buffer (DPB). The method 1200 may be performed by an encoder 104 or one of its sub-parts (e.g., a decoded picture buffer module 676). The method 1200 may be performed by a decoder 112 in an electronic device 102 (e.g., electronic device B 102b). Additionally or alternatively the method 1200 may be performed by a decoder 712 or one of its sub-parts (e.g., a decoded picture buffer module 709). The decoder may parse first slice header of a picture 1202. The output and removal of pictures from DPB before decoding of the current picture (but after parsing the slice header of the first slice of the current picture) happens instantaneously when first decoding unit of the access unit containing the current picture is removed from the CPB and proceeds as follows.

[0223] - The decoding process for reference picture set (RPS) is invoked. Reference picture set is a set of reference pictures associated with a picture, consisting of all reference pictures that are prior to the associated picture in decoding order, that may be used for inter prediction of the associated picture or any picture following the associated picture in decoding order.

[0224] - The bitstream of the video may include a syntax structure that is placed into logical data packets generally referred to as Network Abstraction Layer (NAL) units. Each NAL unit includes a NAL unit header, such as a two-byte NAL unit header (e.g., 16 bits), to identify the purpose of the associated data payload. For example, each coded

slice (and/or picture) may be coded in one or more slice (and/or picture) NAL units. Other NAL units may be included for other categories of data, such as for example, supplemental enhancement information, coded slice of temporal sub-layer access (TSA) picture, coded slice of step-wise temporal sub-layer access (STSA) picture, coded slice a non-TSA, non-STSA trailing picture, coded slice of broken link access picture, coded slice of instantaneous decoded refresh picture, coded slice of clean random access picture, coded slice of decodable leading picture, coded slice of tagged for discard picture, video parameter set, sequence parameter set, picture parameter set, access unit delimiter, end of sequence, end of bitstream, filler data, and/or sequence enhancement information message. Table (4) illustrates one example of NAL unit codes and NAL unit type classes. Other NAL unit types may be included, as desired. It should also be understood that the NAL unit type values for the NAL units shown in the Table (4) may be reshuffled and reassigned. Also additional NAL unit types may be added. Also some NAL unit types may be removed.

- [0225] An intra random access point (IRAP) picture is a coded picture for which each video coding layer NAL unit has `nal_unit_type` in the range of `BLA_W_LP` to `RSV_IRAP_VCL23`, inclusive as shown in Table (4). An IRAP picture contains only Intra coded (I) slices. An instantaneous decoding refresh (IDR) picture is an IRAP picture for which each video coding layer NAL unit has `nal_unit_type` equal to `IDR_W_RADL` or `IDR_N_LP` as shown in Table (4). An instantaneous decoding referesh (IDR) picture contains only I slices, and may be the first picture in the bitstream in decoding order, or may appear later in the bitstream. Each IDR picture is the first picture of a coded video sequence (CVS) in decoding order. A broken link access (BLA) picture is an IRAP picture for which each video coding layer NAL unit has `nal_unit_type` equal to `BLA_W_LP`, `BLA_W_RADL`, or `BLA_N_LP` as shown in Table (4). A BLA picture contains only I slices, and may be the first picture in the bitstream in decoding order, or may appear later in the bitstream. Each BLA picture begins a new coded video sequence, and has the same effect on the decoding process as an IDR picture. However, a BLA picture contains syntax elements that specify a non-empty reference picture set.

nal_unit_type	Name of nal_unit_type	Content of NAL unit and raw byte sequence payload (RBSP) syntax structure	NAL unit type class
0 1	TRAIL_N TRAIL_R	Coded slice segment of a non-TSA, non-STSA trailing picture slice_segment_layer_rbsp()	Video Coding Layer (VCL)
2 3	TSA_N TSA_R	Coded slice segment of a temporal sub-layer access (TSA) picture slice_segment_layer_rbsp()	VCL
4 5	STSA_N STSA_R	Coded slice segment of an Step-wise Temporal sub-layer access (STSA) picture slice_segment_layer_rbsp()	VCL
6 7	RADL_N RADL_R	Coded slice segment of a random access decodable leading (RADL) picture slice_segment_layer_rbsp()	VCL
8 9	RASL_N RASL_R	Coded slice segment of a random access skipped leading (RASL) picture slice_segment_layer_rbsp()	VCL
10 12 14	RSV_VCL_N10 RSV_VCL_N12 RSV_VCL_N14	Reserved non-IRAP sub-layer non-reference VCL NAL unit types	VCL
11 13 15	RSV_VCL_R11 RSV_VCL_R13 RSV_VCL_R15	Reserved non-IRAP sub-layer reference VCL NAL unit types	VCL
16 17 18	BLA_W_LP BLA_W_RADL BLA_N_LP	Coded slice segment of a broken link access (BLA) picture slice_segment_layer_rbsp()	VCL
19 20	IDR_W_RADL IDR_N_LP	Coded slice segment of an instantaneous decoding refresh (IDR) picture slice_segment_layer_rbsp()	VCL
21	CRA_NUT	Coded slice segment of a clean random access (CRA) picture slice_segment_layer_rbsp()	VCL
22 23	RSV_IRAP_VCL22 RSV_IRAP_VCL23	Reserved IRAP VCL NAL unit types	VCL
24..31	RSV_VCL24.. RSV_VCL31	Reserved non-IRAP VCL NAL unit types	VCL
32	VPS_NUT	Video parameter set video_parameter_set_rbsp()	non-video coding layer (non-VCL)
33	SPS_NUT	Sequence parameter set seq_parameter_set_rbsp()	non-VCL
34	PPS_NUT	Picture parameter set pic_parameter_set_rbsp()	non-VCL
35	AUD_NUT	Access unit delimiter access_unit_delimiter_rbsp()	non-VCL
36	EOS_NUT	End of sequence end_of_seq_rbsp()	non-VCL
37	EOB_NUT	End of bitstream end_of_bitstream_rbsp()	non-VCL
38	FD_NUT	Filler data filler_data_rbsp()	non-VCL
39 40	PREFIX_SEI_NUT SUFFIX_SEI_NUT	Supplemental enhancement information sei_rbsp()	non-VCL
41..47	RSV_NVCL41.. RSV_NVCL47	Reserved	non-VCL
48..63	UNSPEC48.. UNSPEC63	Unspecified	non-VCL

Table (4)

[0226] Referring to Table (5), the NAL unit header syntax may include two bytes of data, namely, 16 bits. The first bit is a "forbidden_zero_bit" which is always set to zero at the start of a NAL unit. The next six bits is a "nal_unit_type" which specifies the type of raw byte sequence payloads ("RBSP") data structure contained in the NAL unit as shown in Table (4). The next 6 bits is a "nuh_layer_id" which specify the identifier of

the layer. In some cases these six bits may be specified as "nuh_reserved_zero_6bits" instead. The nuh_reserved_zero_6bits may be equal to 0 in the base specification of the standard. In a scalable video coding and/or syntax extensions nuh_layer_id may specify that this particular NAL unit belongs to the layer identified by the value of these 6 bits. The next syntax element is "nuh_temporal_id_plus1". The nuh_temporal_id_plus1 minus 1 may specify a temporal identifier for the NAL unit. The variable temporal identifier TemporalId may be specified as TemporalId = nuh_temporal_id_plus1 - 1. The temporal identifier TemporalId is used to identify a temporal sub-layer. The variable HighestTid identifies the highest temporal sub-layer to be decoded.

nal_unit_header() {	Descriptor
forbidden_zero_bit	f(1)
nal_unit_type	u(6)
nuh_layer_id	u(6)
nuh_temporal_id_plus1	u(3)
}	

Table (5)

- [0227] Table (6) shows an exemplary sequence parameter set (SPS) syntax structure.
- [0228] pic_width_in_luma_samples specifies the width of each decoded picture in units of luma samples. pic_width_in_luma_samples may not be equal to 0.
- [0229] pic_height_in_luma_samples specifies the height of each decoded picture in units of luma samples. pic_height_in_luma_samples may not be equal to 0.
- [0230] sps_max_sub_layers_minus1 plus 1 specifies the maximum number of temporal sub-layers that may be present in each CVS referring to the SPS. The value of sps_max_sub_layers_minus1 may be in the range of 0 to 6, inclusive.
- [0231] sps_sub_layer_ordering_info_present_flag equal to 1 specifies that sps_max_dec_pic_buffering_minus1[i], sps_max_num_reorder_pics[i], and sps_max_latency_increase_plus1[i] syntax elements are present for sps_max_sub_layers_minus1 + 1 sub-layers.
- sps_sub_layer_ordering_info_present_flag equal to 0 specifies that the values of sps_max_dec_pic_buffering_minus1[sps_max_sub_layers_minus1], sps_max_num_reorder_pics[sps_max_sub_layers_minus1], and sps_max_latency_increase_plus1[sps_max_sub_layers_minus1] apply to all sub-layers.

- [0232] `sps_max_dec_pic_buffering_minus1[ i ]` plus 1 specifies the maximum required size of the decoded picture buffer for the CVS in units of picture storage buffers when `HighestTid` is equal to `i`. The value of `sps_max_dec_pic_buffering_minus1[ i ]` may be in the range of 0 to `MaxDpbSize - 1`, inclusive where `MaxDpbSize` specifies the maximum decoded picture buffer size in units of picture storage buffers. When `i` is greater than 0, `sps_max_dec_pic_buffering_minus1[ i ]` may be greater than or equal to `sps_max_dec_pic_buffering_minus1[ i - 1 ]`. When `sps_max_dec_pic_buffering_minus1[ i ]` is not present for `i` in the range of 0 to `sps_max_sub_layers_minus1 - 1`, inclusive, due to `sps_sub_layer_ordering_info_present_flag` being equal to 0, it is inferred to be equal to `sps_max_dec_pic_buffering_minus1[ sps_max_sub_layers_minus1 ]`.
- [0233] `sps_max_num_reorder_pics[ i ]` indicates the maximum allowed number of pictures that can precede any picture in the CVS in decoding order and follow that picture in output order when `HighestTid` is equal to `i`. The value of `sps_max_num_reorder_pics[ i ]` may be in the range of 0 to `sps_max_dec_pic_buffering_minus1[ i ]`, inclusive. When `i` is greater than 0, `sps_max_num_reorder_pics[ i ]` may be greater than or equal to `sps_max_num_reorder_pics[ i - 1 ]`. When `sps_max_num_reorder_pics[ i ]` is not present for `i` in the range of 0 to `sps_max_sub_layers_minus1 - 1`, inclusive, due to `sps_sub_layer_ordering_info_present_flag` being equal to 0, it is inferred to be equal to `sps_max_num_reorder_pics[ sps_max_sub_layers_minus1 ]`.
- [0234] `sps_max_latency_increase_plus1[ i ]` not equal to 0 is used to compute the value of `SpsMaxLatencyPictures[ i ]`, which specifies the maximum number of pictures that can precede any picture in the CVS in output order and follow that picture in decoding order when `HighestTid` is equal to `i`.
- [0235] When `sps_max_latency_increase_plus1[ i ]` is not equal to 0, the value of `SpsMaxLatencyPictures[ i ]` is specified as follows:
- [0236]
$$\text{SpsMaxLatencyPictures}[i] = \text{sps_max_num_reorder_pics}[i] + \text{sps_max_latency_increase_plus1}[i] - 1$$
- [0237] When `sps_max_latency_increase_plus1[ i ]` is equal to 0, no corresponding limit is expressed.
- [0238] The value of `sps_max_latency_increase_plus1[ i ]` may be in the range of 0 to $2^{32} - 2$, inclusive. When `sps_max_latency_increase_plus1[ i ]` is not present for `i` in the range of 0 to `sps_max_sub_layers_minus1 - 1`, inclusive, due to `sps_sub_layer_ordering_info_present_flag` being equal to 0, it is inferred to be equal to `sps_max_latency_increase_plus1[ sps_max_sub_layers_minus1 ]`.

seq_parameter_set_rbsp() {
...
sps_max_sub_layers_minus1
...
pic_width_in_luma_samples
pic_height_in_luma_samples
...
for(i = (sps_sub_layer_ordering_info_present_flag ? 0 :
sps_max_sub_layers_minus1);
i <= sps_max_sub_layers_minus1; i++) {
sps_max_dec_pic_buffering_minus1[i]
sps_max_num_reorder_pics[i]
sps_max_latency_increase_plus1[i]
}
...
}

Table (6)

[0239] When the current picture is an IRAP picture, the following applies:

- If the current picture is an IDR picture, a BLA picture, the first picture in the bitstream in decoding order, or the first picture that follows an end of sequence NAL unit in decoding order, a variable NoRaslOutputFlag is set equal to 1.
- Otherwise, if some external means is available to set a variable HandleCraAsBlaFlag to a value for the current picture, the variable HandleCraAsBlaFlag is set equal to the value provided by that external means and the variable NoRaslOutputFlag is set equal to HandleCraAsBlaFlag.
- Otherwise, the variable HandleCraAsBlaFlag is set equal to 0 and the variable NoRaslOutputFlag is set equal to 0.

[0240] If the current picture is an IRAP picture with NoRaslOutputFlag equal to 1 that is not picture 0, the following ordered steps are applied:

1. The variable NoOutputOfPriorPicsFlag is derived for the decoder under test as follows:

- If the current picture is a CRA picture, NoOutputOfPriorPicsFlag is set equal to 1 (regardless of the value of no_output_of_prior_pics_flag).
- Otherwise, if the value of pic_width_in_luma_samples, pic_height_in_luma_samples, or sps_max_dec_pic_buffering_minus1[HighestTid] derived from the active SPS is different from the value of pic_width_in_luma_samples, pic_height_in_luma_samples, or sps_max_dec_pic_buffering_minus1[HighestTid], respectively, derived from the SPS active for the preceding picture, NoOutputOfPriorPicsFlag may (but should not) be set to 1 by the decoder under test, regardless of the value of no_output_of_prior_pics_flag.
- Otherwise, NoOutputOfPriorPicsFlag is set equal to no_output_of_prior_pics_flag.

2. The value of NoOutputOfPriorPicsFlag derived for the decoder under test is applied for the HRD as follows:

- If NoOutputOfPriorPicsFlag is equal to 1, all picture storage buffers in the DPB are emptied without output of the pictures they contain, and the DPB fullness is set equal to 0.
- Otherwise (NoOutputOfPriorPicsFlag is equal to 0), all picture storage buffers containing a picture that is marked as "not needed for output" and "unused for reference" are emptied (without output), and all non-empty picture storage buffers in the DPB are emptied by repeatedly invoking the "bumping" process 1204, and the DPB fullness is set equal to 0.

– Otherwise (the current picture is not an IRAP picture with NoRaslOutputFlag equal to 1), all picture storage buffers containing a picture which are marked as "not needed for output" and "unused for reference" are emptied (without output). For each picture storage buffer that is emptied, the DPB fullness is decremented by one. When one or more of the following conditions are true, the "bumping" process 1204 is invoked repeatedly while further decrementing the DPB fullness by one for each additional picture storage buffer that is emptied, until none of the following conditions are true:

1. The number of pictures with that particular nuh_layer_id value in the DPB that are marked as "needed for output" is greater than sps_max_num_reorder_pics[HighestTid] from the active sequence parameter set (when that particular nuh_layer_id value is equal to 0) or from the active layer sequence parameter set for that particular nuh_layer_id value.
2. If sps_max_latency_increase_plus1[HighestTid] from the active sequence parameter set (when that particular nuh_layer_id value is equal to 0) or from the active layer sequence parameter set for that particular nuh_layer_id value is not equal to 0 and there is at least one picture with that particular nuh_layer_id value in the DPB that is marked as "needed for output" for which the associated variable PicLatencyCount is greater than or equal to SpsMaxLatencyPictures[HighestTid] for that particular nuh_layer_id value.
3. The number of pictures with that particular nuh_layer_id value in the DPB is greater than or equal to sps_max_dec_pic_buffering[HighestTid] + 1 from the active sequence parameter set (when that particular nuh_layer_id value is equal to 0) or from the active layer sequence parameter set for that particular nuh_layer_id value.

[0241] Picture decoding process in the block 1206 (picture decoding and marking) happens instantaneously when the last decoding unit of access unit containing the current picture is removed from the CPB.

[0242] For each picture with nuh_layer_id value equal to current picture's nuh_layer_id value in the DPB that is marked as "needed for output", the associated variable PicLa-

tencyCount is set equal to PicLatencyCount + 1.

[0243] The current picture is considered as decoded after the last decoding unit of the picture is decoded. The current decoded picture is stored in an empty picture storage buffer in the DPB, and the following applies:

- If the current decoded picture has PicOutputFlag equal to 1, it is marked as "needed for output" and its associated variable PicLatencyCount is set equal to 0.
- Otherwise (the current decoded picture has PicOutputFlag equal to 0), it is marked as "not needed for output".

[0244] The current decoded picture is marked as "used for short-term reference".

[0245] When one or more of the following conditions are true, the additional "bumping" process 1208 is invoked repeatedly until none of the following conditions are true:

- The number of pictures with nuh_layer_id value equal to current picture's nuh_layer_id value in the DPB that are marked as "needed for output" is greater than sps_max_num_reorder_pics[HighestTid] from the active sequence parameter set (when the current picture's nuh_layer_id value is equal to 0) or from the active layer sequence parameter set for the current picture's nuh_layer_id value.

- sps_max_latency_increase_plus1[HighestTid] from the active sequence parameter set (when the current picture's nuh_layer_id value is equal to 0) or from the active layer sequence parameter set for the current picture's nuh_layer_id value is not equal to 0 and there is at least one picture with that particular nuh_layer_id value in the DPB that is marked as "needed for output" for which the associated variable PicLatencyCount is greater than or equal to SpsMaxLatencyPictures[HighestTid] for that particular nuh_layer_id value.

[0246] The "bumping" process 1204 and additional bumping process 1208 are identical in terms of the steps and consists of the following ordered steps: The pictures that are first for output is selected as the ones having the smallest value of picture order count (PicOrderCntVal) of all pictures in the DPB marked as "needed for output". A picture order count is a variable that is associated with each picture, uniquely identifies the associated picture among all pictures in the CVS, and, when the associated picture is to be output from the decoded picture buffer, indicates the position of the associated picture in output order relative to the output order positions of the other pictures in the same CVS that are to be output from the decoded picture buffer.

- These pictures are cropped, using the conformance cropping window specified in the active sequence parameter set for the picture with `nuh_layer_id` equal to 0 or in the active layer sequence parameter set for a `nuh_layer_id` value equal to that of the picture, the cropped pictures are output in ascending order of `nuh_layer_id`, and the pictures are marked as "not needed for output".
- Each picture storage buffer that contains a picture marked as "unused for reference" and that included one of the pictures that was cropped and output is emptied.

- [0247] Referring to FIG. 13A, as previously described the NAL unit header syntax may include two bytes of data, namely, 16 bits. The first bit is a "forbidden_zero_bit" which is always set to zero at the start of a NAL unit. The next six bits is a "nal_unit_type" which specifies the type of raw byte sequence payloads ("RBSP") data structure contained in the NAL unit. The next 6 bits is a "nuh_reserved_zero_6bits". The `nuh_reserved_zero_6bits` may be equal to 0 in the base specification of the standard. Other values of `nuh_reserved_zero_6bits` may be specified as desired. Decoders may ignore (i.e., remove from the bitstream and discard) all NAL units with values of `nuh_reserved_zero_6bits` not equal to 0 when handling a stream based on the base specification of the standard. In a scalable or other extension `nuh_reserved_zero_6bits` may specify other values, to signal scalable video coding and/or syntax extensions. In some cases syntax element `nuh_reserved_zero_6bits` may be called `reserved_zero_6bits`. In some cases the syntax element `nuh_reserved_zero_6bits` may be called as `layer_id_plus1` or `layer_id`, as illustrated in FIG. 13B and FIG. 13C. In this case the element `layer_id` will be `layer_id_plus1` minus 1. In this case it may be used to signal information related to layer of scalable coded video. The next syntax element is "nuh_temporal_id_plus1". `nuh_temporal_id_plus1` minus 1 may specify a temporal identifier for the NAL unit. The variable temporal identifier `TemporalId` may be specified as $\text{TemporalId} = \text{nuh_temporal_id_plus1} - 1$.
- [0248] Referring to FIG. 14, a general NAL unit syntax structure is illustrated. The NAL unit header two byte syntax of FIG. 13 is included in the reference to `nal_unit_header()` of FIG. 14. The remainder of the NAL unit syntax primarily relates to the RBSP.
- [0249] One existing technique for using the "nuh_reserved_zero_6bits" is to signal scalable video coding information by partitioning the 6 bits of the `nuh_reserved_zero_6bits` into distinct bit fields, namely, one or more of a dependency ID, a quality ID, a view ID, and a depth flag, each of which refers to the identification of a different layer of the scalable coded video. Accordingly, the 6 bits indicate what layer of the scalable encoding technique this particular NAL unit belongs to. Then in a data payload, such as a video parameter set ("VPS") extension syntax ("scalability_type") as illustrated in

FIG. 15, the information about the layer is defined. The VPS extension syntax of FIG. 15 includes 4 bits for scalability type (syntax element `scalability_type`) which specifies the scalability types in use in the coded video sequence and the dimensions signaled through `layer_id_plus1` (or `layer_id`) in the NAL unit header. When the scalability type is equal to 0, the coded video sequence conforms to the base specification, thus `layer_id_plus1` of all NAL units is equal to 0 and there are no NAL units belonging to an enhancement layer or view. Higher values of the scalability type are interpreted as illustrated in FIG. 16.

- [0250] The `layer_id_dim_len[ i ]` specifies the length, in bits, of the *i*-th scalability dimension ID. The sum of the values `layer_id_dim_len[ i ]` for all *i* values in the range of 0 to 7 is less than or equal to 6. The `vps_extension_byte_alignment_reserved_zero_bit` is zero. The `vps_layer_id[ i ]` specifies the value of `layer_id` of the *i*-th layer to which the following layer dependency information applies. The `num_direct_ref_layers[ i ]` specifies the number of layers the *i*-th layer directly depends on. The `ref_layer_id[ i ][ j ]` identifies the *j*-th layer the *i*-th layer directly depends on.
- [0251] In this manner, the existing technique signals the scalability identifiers in the NAL unit and in the video parameter set to allocate the bits among the scalability types listed in FIG. 16. Then for each scalability type, FIG. 16 defines how many dimensions are supported. For example, scalability type 1 has 2 dimensions (i.e., spatial and quality). For each of the dimensions, the `layer_id_dim_len[i]` defines the number of bits allocated to each of these two dimensions, where the total sum of all the values of `layer_id_dim_len[i]` is less than or equal to 6, which is the number of bits in the `nuh_reserved_zero_6bits` of the NAL unit header. Thus, in combination the technique identifies which types of scalability is in use and how the 6 bits of the NAL unit header are allocated among the scalability.
- [0252] While such a fixed combination of different scalability dimensions, as illustrated in FIG. 16, is suitable for many applications there are desirable combinations which are not included. Referring to FIG. 17, a modified video parameter set extension syntax specifies a scalability type for each bit in the `nuh_reserved_zero_6bits` syntax element. The `vps_extension_byte_alignment_reserved_zero_bit` is set to 0. The `max_num_layers_minus1_bits` indicates the total number of bits used for the syntax element in the first two bytes of the NAL unit header in FIG. 13 referred to as `layer_id_plus1` or `nuh_reserved_zero_6bits`. The `scalability_map[i]` specifies the scalability type for each bit in the `layer_id_plus1` syntax element. In some case the `layer_id_plus1` syntax element may be instead called `nuh_reserved_zero_6bits` or `rserved_zero_6bits` syntax element. The scalability map for all the bits of the syntax element `layer_id_plus1` together specifies the scalability in use in the coded video

sequence. The actual value of the identifier for each of the scalability types is signaled through those corresponding bits in the `layer_id_plus1` (`nuh_reserved_zero_6bits`) field in the NAL unit header. When `scalability_map[i]` is equal to 0 for all values of `i`, the coded video sequence conforms to the base specification, thus `layer_id_plus1` value of NAL units is equal to 0 and there are no NAL units belonging to an enhancement layer or view. The `vps_layer_id[ i ]` specifies the value of `layer_id` of the `i`-th layer to which the following layer dependency information applies. The `num_direct_ref_layers[ i ]` specifies the number of layers the `i`-th layer directly depends on. The `ref_layer_id[ i ][ j ]` identifies the `j`-th layer the `i`-th layer directly depends on.

- [0253] Higher values of `scalability_map[i]` are interpreted as shown in FIG. 18. The scalability map `[i]` includes the scalability dimensions of (0) none; (1) spatial; (2) quality; (3) depth; (4) multiview; (5) unspecified; (6) reserved; and (7) reserved.
- [0254] Therefore each bit in the NAL unit header is interpreted based on the 3 bits in the video parameter set of what is the scalability dimension (e.g., none, spatial, quality, depth, multiview, unspecified, reserved). For example, to signal that all the bits in `layer_id_plus1` correspond to spatial scalability, the `scalability_map` values in the VPS may be coded as 001 001 001 001 001 001 for the 6 bits of the NAL unit header. Also for example, to signal that 3 bits in `layer_id_plus1` correspond to spatial scalability and 3 bits correspond to quality scalability, the `scalability_map` values in the VPS may be coded as 001 001 001 010 010 010 for the 6 bits of the NAL Unit header.
- [0255] Referring to FIG. 19, another embodiment includes the video parameter set signaling the number of scalability dimensions in the 6 bits of the NAL unit header using the `num_scalability_dimensions_minus1`. The `num_scalability_dimensions_minus1` plus 1 indicates the number of scalability dimensions signaled through the `layer_id_plus1`; `nuh_reserved_zero_6bits`; and/or `reserved_zero_6bits` syntax elements. The `scalability_map[i]` has the same semantics as described above in relation to FIG. 17. The `num_bits_for_scalability_map[i]` specifies the length in bits for the `i`'th scalability dimension. The sum of all of the `num_bits_for_scalability_map[i]` for `i=0,...num_scalability_dimensions_minus1` is equal to six (or otherwise equal to the number of bits used for `layer_id_plus1`; `vps_reserved_zero_6bits`; `max_num_layers_minus1`; `reserved_zero_6bits`; `nuh_reserved_zero_6bits` syntax elements).
- [0256] With respect to FIG. 17 and FIG. 19 other variations may be used, if desired. In one embodiment for example, the `scalability_map[i]` may be signaled with `u(4)` (or `u(n)` with `n>3` or `n<3`). In this case the higher values of `scalability_map[i]` may be specified as reserved for bitstreams conforming to a particular profile of the video technique. For example, scalability map values 6...15 may be specified as 'reserved' when signaling `scalability_map[i]` with `u(4)`. In another embodiment for example, `scalability_map[i]`

maybe signaled with $ue(v)$ or some other coding scheme. In another embodiment for example, a restriction may be specified such that the $scalability_map[i]$ values are arranged in monotonic non decreasing (or non-increasing) order. This results in various scalability dimension fields in the $layer_id_plus1$ field in NAL unit header being contiguous.

[0257] Another existing technique for signaling the scalable video coding using the "layer_id_plus1" or "nuh_reserved_zero_6bits" syntax element is to map the $layer_id_plus1$ in the NAL unit header to a layer identification by signaling a general lookup table in the video parameter set. Referring to FIG. 20, the existing technique includes a video parameter set that specifies the number of dimension types and dimension identifications for the i -th layer of the lookup table. In particular, the $vps_extension_byte_alignment_reserved_zero_bit$ is zero. The $num_dimensions_minus1[i]$ plus 1 specifies the number of dimension types ($dimension_type[i][j]$) and dimension identifiers ($dimension_id[i][j]$) for the i -th layer. The $dimension_type[i][j]$ specifies the j -th scalability dimension type of the i -th layer, which has $layer_id$ or $layer_id_plus1$ equal to i , as specified in FIG. 31. As illustrated in FIG. 21, the dimensions that are identified include of (0) view order idx; (1) depth flag; (2) dependency ID; (3) quality ID; (4)-(15) reserved. The $dimension_id[i][j]$ specifies the identifier of the j -th scalability dimension type of the i -th layer, which when not present is inferred to be 0. The $num_direct_ref_layers[i]$ specifies the number of layers the i -th layer directly depends on. The $ref_layer_id[i][j]$ identifies the j -th layer the i -th layer directly depends on. Unfortunately, the proposed embodiment illustrated in FIG. 20 results in an unwieldy large lookup table.

[0258] Referring to FIG. 22, a modified video parameter set extension includes a scalability mask that is used in combination with a scalability dimension. The $scalability_mask$ signals a pattern of 0 and 1 bits with each bit corresponding to one scalability dimension as indicated by the scalability map syntax of FIG. 23. A value of 1 for a particular scalability dimension indicates that this scalability dimension is present in this layer (i 'th layer). A value of 0 for a particular scalability dimension indicates that this scalability dimension is not present in this layer (i 'th layer). For example, a set of bits of 00100000 refers to quality scalability. The actual identifier value of the particular scalability dimension that is present is indicated by the $scalability_id[j]$ value signaled. The values of $num_scalability_types[i]$ is equal to the sum of number of bits in the $scalability_mask$ having value of 1. Thus

$$num_scalability_types[i] = \sum_{k=0}^7 scalability_mask[i](k).$$

The $scalability_id[j]$ indicates the j -th scalability dimension's identifier value for the

type of scalability values that are signaled by the scalability_mask value.

[0259] Referring to FIG. 24, a modification of FIG. 22, includes the scalability mask being signaled outside the loop. This results in one common mask for each layer identification. Referring to FIG. 25, in this modification a corresponding exemplary video parameter set may include the scalable identification with the scalability mask not being included. In this case the syntax element scalable_id[j] has same interpretation as the syntax element scalability_id[j] in FIG. 22.

[0260] Referring to FIG. 26 a modification of FIG. 22 includes the scalability mask (scalability_mask) being signaled outside the loop. This results in one common mask for each layer identification. The scalability_mask signals a pattern of 0 and 1 bits with each bit corresponding to one scalability dimension as indicated by the scalability map syntax of FIG. 27. A value of 1 for a particular scalability dimension indicates that this scalability dimension is present in this layer (i'th layer). A value of 0 for a particular scalability dimension indicates that this scalability dimension is not present in this layer (i'th layer). For example, a set of bits of 00100000 refers to quality scalability. The actual identifier value of the particular scalability dimension that is present is indicated by the scalability_id[j] value signaled. The values of num_scalability_types[i] is equal to the sum of number of bits in the scalability_mask having value of 1. Thus

$$\text{NumScalabilityTypes}[i] = \sum_{k=0}^{15} \text{scalability_mask}(k).$$

In this case the scalability_id[j] variable may instead be called dimension_id[i][j] variable. dimension_id[i][j] specifies the scalability identifier of the j-th scalability dimension of the i-th layer. Then a variable ScalabilityId[i][j] is derived as follows.

```

for( i = 1; i <= vps_max_layers_minus1; i++ ) {
    for(k=0, j=0; k<=15; k++) {
        if(scalability_mask(k)==1)
            ScalabilityId [i][k]=dimension_id[i][j++]
        else
            ScalabilityId [i][k]=0;
    }
}

```

Where the ScalabilityId [i][k] signals dimension ID for the corresponding scalability type as follows.

k	ScalabilityId [i][k]
0	DependencyId[i][k]
1	QualityId[i][k]
2	depthFlag[i][k]
3	ViewId[i][k]
4-15	Reserved

Where DependencyId[i][1] is the dependency ID for the spatial scalability dimension for the i-th layer, QualityId[i][2] is the quality ID for the quality scalability dimension for the i-th layer, depthFlag[i][3] is the depth flag / depth ID for the depth scalability dimension for the i-th layer, and ViewId[i][4] is the view ID for the multiview scalability dimension for the i-th layer.

[0261] Also in FIG. 26 `avc_base_codec_flag` equal to 1 specifies that the base layer conforms to Rec. ITU-T H.264 | ISO/IEC 14496-10, and `avc_base_codec_flag` equal to 1 specifies to HEVC. `vps_nuh_layer_id_presnet_flag` indicates if `layer_id_in_nuh[i]` variable which signals the value of `layer_id` in NAL unit header is signaled.

[0262] In another embodiment one or more of the syntax elements `scalability_mask[i]`, `scalability_mask`, `scalability_id[j]` may be signaled using different number of bits than `u(8)`. For example they could be signaled with `u(16)` (or `u(n)` with $n > 8$ or $n < 8$). In another embodiment one or more of these syntax element could be signaled with `ue(v)`. In another embodiment the `scalability_mask` may be signaled in the NAL unit header in `layer_id_plus1`; `vps_reserved_zero_6bits`; `max_num_layers_minus1`; `reserved_zero_6bits`; and/or `nuh_reserved_zero_6bits` syntax elements. In some embodiments the system may do this only for VPS NAL units, or only for non-VPS NAL units, or for all NAL units. In yet another embodiment `scalability_mask` may be signaled per picture anywhere in the bitstream. For example it may be signaled in slice header, picture parameter set, video parameter set, or any other parameter set or any other normative part of the bitstream.

[0263] It should be noted that FIGS. 13, 15, 18, 20, 21, 22, 23 and corresponding description refer to 6 bits since the syntax element `nuh_reserved_zero_6bits` or `layer_id_plus1` in NAL unit header of FIG. 13 has 6 bits. However all the above description can be suitably modified if that syntax element used a different number of bits than 6 bits. For example if that syntax element (`nuh_reserved_zero_6bits` or `layer_id_plus1`) instead used 9 bits then in FIG. 17 the value of `max_num_layer_minus1` bits will be 9 and the `scalability_map[i]` will be signaled for each of the 9 bits instead of 6 bits.

[0264] Referring to FIG 24 a modification of FIG 22 provides syntax for signaling layer dependency information. New syntax element `layer_dependency_information_pattern` is defined. `layer_dependency_information_pattern` signals a pattern of 0 and 1 bits with

the length equal to $vps_max_layers_minus1$. A value of 0 for i'th bit indicates that the layer with layer_id (i+1) is an independent layer. A value of 1 for i'th bit indicates that the layer with layer_id (i+1) is a dependent layer which depends on one or more of other layers.

- [0265] The values of NumDepLayers is equal to the sum of number of bits in the layer_dependency_information_pattern having value of 1. Thus .

$$NumDepLayers = \sum_{k=0}^{vps_max_layer_minus1-1} layer_dependency_information_pattern(k) .$$

- [0266] Referring to FIG. 29 a modification of FIG. 26 provides syntax for signaling layer dependency information. New syntax element layer_dependency_flag[i] is defined. layer_dependency_flag[i] signals if a layer depends on other layers . A value of 0 for the flag indicates that the layer with layer_id i is an independent layer. A value of 1 for i'th bit indicates that the layer with layer_id i is a dependent layer.

- [0267] Referring to FIG. 30 a modification of FIG. 26 provides syntax for signaling layer dependency information. New syntax element layer_dependency_map[i] is defined. layer_dependency_map[i] signals a pattern of 0 and 1 bits with the length equal to $vps_max_layers_minus1$. A value of 0 for k'th bit of layer_dependency_map[i] indicates that the layer i does not depend on layer with layer_id (k+1). A value of 1 for k'th bit of layer_dependency_map[i] indicates that the layer i depends on layer with layer_id (k+1).

- [0268] Referring to FIG. 31 a modification of FIG. 26 provides syntax for signaling layer dependency information. New syntax element layer_dependency_information_pattern is defined. layer_dependency_information_pattern signals a pattern of 0 and 1 bits with the length equal to $vps_max_layers_minus1$. A value of 0 for i'th bit indicates that the layer with layer_id (i+1) is an independent layer. A value of 1 for i'th bit indicates that the layer with layer_id (i+1) is a dependent layer which depends on one or more of other layers. The values of NumDepLayers is equal to the sum of number of bits in the layer_dependency_information_pattern having value of 1. Thus

$$NumDepLayers = \sum_{k=0}^{vps_max_layer_minus1-1} layer_dependency_information_pattern(k) .$$

layer_dependency_map[i] signals a pattern of 0 and 1 bits with the length equal to $vps_max_layers_minus1$. A value of 0 for k'th bit of layer_dependency_map[i] indicates that the layer i does not depend on layer with layer_id (k+1). A value of 1 for k'th bit of layer_dependency_map[i] indicates that the layer i depends on layer with layer_id (k+1).

- [0269] Referring to FIG. 32 a modification of FIG. 26 provides syntax for signaling layer dependency information. FIG 28 is a variant syntax based on syntax in FIG 27. New

syntax element `layer_dependency_information_pattern` is defined.

- [0270] `layer_dependency_information_pattern` signals a pattern of 0 and 1 bits with the length equal to `vps_max_layers_minus1`. A value of 0 for *i*'th bit indicates that the layer with `layer_id` (*i*+1) is an independent layer. A value of 1 for *i*'th bit indicates that the layer with `layer_id` (*i*+1) is a dependent layer which depends on one or more of other layers.

- [0271] The values of `NumDepLayers` is equal to the sum of number of bits in the `layer_dependency_information_pattern` having value of 1. Thus

$$\text{NumDepLayers} = \sum_{k=0}^{\text{vps_max_layer_minus1}-1} \text{layer_dependency_information_pattern}(k) .$$

Syntax elements `num_direct_ref_layers[i]` and `ref_layer_id[i][j]` are signaled only when `layer_dependency_information_pattern(i)` has a value of 1. Where `layer_depndency_information_pattern(i)` is the *i*'th bit of the syntax element `layer_dependency_pattern`.

- [0272] Referring to FIG. 33 a modification of FIG. 26 provides syntax for signaling layer dependency information. FIG 29 is a variant syntax based on syntax in FIG. 31. New syntax element `layer_dependency_information_pattern` is defined.

- [0273] `layer_dependency_information_pattern` signals a pattern of 0 and 1 bits with the length equal to `vps_max_layers_minus1`. A value of 0 for *i*'th bit indicates that the layer with `layer_id` (*i*+1) is an independent layer. A value of 1 for *i*'th bit indicates that the layer with `layer_id` (*i*+1) is a dependent layer which depends on one or more of other layers.

- [0274] The values of `NumDepLayers` is equal to the sum of number of bits in the `layer_dependency_information_pattern` having value of 1. Thus

$$\text{NumDepLayers} = \sum_{k=0}^{\text{vps_max_layer_minus1}-1} \text{layer_dependency_information_pattern}(k) .$$

`layer_dependency_map[i]` signals a pattern of 0 and 1 bits with the length equal to `vps_max_layers_minus1`. A value of 0 for *k*'th bit of `layer_dependency_map[i]` indicates that the layer *i* does not depend on layer with `layer_id` (*k*+1). A value of 1 for *k*'th bit of `layer_dependency_map[i]` indicates that the layer *i* depends on layer with `layer_id` (*k*+1). Syntax elements `layer_dependency_map[i]` is signaled only when `layer_dependency_information_pattern(i)` has a value of 1. Where `layer_depndency_information_pattern(i)` is the *i*'th bit of the syntax element `layer_dependency_pattern`.

- [0275] In another embodiment `layer_dependency_information_pattern` syntax element may be signaled as a set of 1 bit flag values. In this case a total of `vps_max_layers_minus1`

1 bit values will be signaled as:

```
for( i = 1; i <= vps_max_layers_minus1 ; i++ )
{
    layer_dependency_information_pattern_flags[i];
}
```

[0276] In another embodiment `layer_dependency_map[i]` syntax element may be signaled as a set of 1 bit flag values. In this case a total of `vps_max_layers_minus1` 1 bit values will be signaled as:

```
for( j = 1; j <= vps_max_layers_minus1 ; j++ )
{
    layer_dependency_map_values[i][j];
}
```

[0277] In another embodiment one or more of the syntax elements `layer_dependency_information_pattern`, `layer_dependency_map` may be signaled using a known fixed number of bits instead of `u(v)`. For example they could be signaled using `u(64)`.

[0278] In another embodiment one or more of or more of the syntax elements `layer_dependency_information_pattern`, `layer_dependency_map` may be signaled with `ue(v)` or some other coding scheme.

[0279] In another embodiment the names of various syntax elements and their semantics may be altered by adding a plus1 or plus2 or by subtracting a minus1 or a minus2 compared to the described syntax and semantics.

[0280] In yet another embodiment various syntax elements such as `layer_dependency_information_pattern`, `layer_dependency_map`, `layer_dependency_flag[i]` etc. may be signaled per picture anywhere in the bitstream. For example it may be signaled in slice header, pps/ sps/ vps/ aps or any other parameter set or other normative part of the bitstream.

[0281] As previously described, scalable video coding is a technique of encoding a video bitstream that also contains one or more subset bitstreams. A subset video bitstream may be derived by dropping packets from the larger video to reduce the bandwidth required for the subset bitstream. The subset bitstream may represent a lower spatial resolution (smaller screen), lower temporal resolution (lower frame rate), or lower quality video signal. For example, a video bitstream may include 5 subset bitstreams, where each of the subset bitstreams adds additional content to a base bitstream. Hannuksela, et al., "Test Model for Scalable Extensions of High Efficiency Video

Coding (HEVC)" JCTVC-L0453, Shanghai, October 2012, is hereby incorporated by reference herein in its entirety. Chen, et al., "SHVC Draft Text 1," JCTVC-L1008, Geneva, March, 2013, is hereby incorporated by reference herein in its entirety.

[0282] As previously described, multi-view video coding is a technique of encoding a video bitstream that also contains one or more other bitstreams representative of alternative views. For example, the multiple views may be a pair of views for stereoscopic video. For example, the multiple views may represent multiple views of the same scene from different viewpoints. The multiple views generally contain a large amount of inter-view statistical dependencies, since the images are of the same scene from different viewpoints. Therefore, combined temporal and inter-view prediction may achieve efficient multi-view encoding. For example, a frame may be efficiently predicted not only from temporally related frames, but also from the frames of neighboring viewpoints. Hannuksela, et al., "Common specification text for scalable and multi-view extensions," JCTVC-L0452, Geneva, January 2013, is hereby incorporated by reference herein in its entirety. Tech, et. al. "MV-HEVC Draft Text 3 (ISO/IEC 23008-2:201x/PDAM2)," JCT3V-C1004_d3, Geneva, January 2013, is hereby incorporated by reference herein in its entirety.

[0283] Chen, et al., "SHVC Draft Text 1," JCTVC-L1008, Geneva, January 2013; Hannuksela, et al. "Test Model for Scalable Extensions of High Efficiency Video Coding (HEVC)," JCTVC-L0453-spec-text, Shanghai, October 2012; and Hannuksela, "Draft Text for Multiview Extension of High Efficiency Video Coding (HEVC)," JCTVC-L0452-spec-text-r1, Shanghai, October 2012; each of which is incorporated by reference herein in its entirety, each have an output order decoded picture buffer (DPB) which operates based on using `sps_max_num_reorder_pics[HighestTid]`, `sps_max_latency_increase_plus1[HighestTid]` and `sps_max_dec_pic_buffering[HighestTid]` syntax elements for the output and removal of pictures 0 from the DPB. This information is signaled in the video parameter set for the base layer, which provides buffering information for the video content including the enhancement layers, if any.

[0284] It was determined that signaling the output order decoded picture buffer (DPB) based on using `sps_max_num_reorder_pics[HighestTid]`, `sps_max_latency_increase_plus1[HighestTid]` and `sps_max_dec_pic_buffering[HighestTid]` syntax elements for the output and removal of pictures from the DPB does not account for the buffer characteristics that may result from scalable video coding, such as when different numbers of enhancement layers are used which tends to vary after the content has been encoded based upon the user's viewing preferences, and the multi-view enhancement layers which tends to vary after the content has been encoded based upon the user's viewing preferences. Also it was

determined that signaling the output order decoded picture buffer (DPB) based on using `sps_max_num_reorder_pics[HighestTid]`, `sps_max_latency_increase_plus1[HighestTid]` and `sps_max_dec_pic_buffering[HighestTid]` syntax elements for the output and removal of pictures from the DPB may not be optimal in terms of the memory usage of the DPB when decoder operates at a certain operation point and/ or is outputting selected output layer set. To accommodate such differences in the viewing preferences, the output order decoded picture buffer (DPB) may further and/or alternatively be based upon such syntax elements being included together with the video parameter set extension (VPS extension) to provide syntax elements for one or more of the enhancement layers. In this manner the syntax elements may be selected to be especially suitable for the particular operation point or output layer set, which tends to correspond to the user's viewing preferences.

- [0285] The DPB buffering related parameters, `vps_max_dec_pic_buffering_minus1`, `vps_max_num_reorder_pics`, `vps_max_latency_increase_plus1` may be signaled for sub-layers for the CVS for one or more operation points and/or for output layer sets in VPS extension. Similarly, the system may define the operation and bumping process for the output order DPB to use the above signalled DPB buffering parameters from the VPS extension if they are signalled for the operation point under test or for the selected output layer set. Otherwise the corresponding SPS level parameters from the active SPS (when `currLayerId` which corresponds to `nuh_layer_id` of the current picture is equal to 0) or from the active layer SPS depending upon the `layer_id` of the current layer are used.
- [0286] Referring to FIG. 34A, an exemplary modified `vps_extension` is illustrated. The modified `vps` extension includes new syntax, namely, `num_op_dpb_info_parameters` and `operation_point_layer_set_idx[i]`. This modified `vps` extension may be defined in terms of the operation point which is a bitstream created from another bitstream by operation of a sub-bitstream extraction process with the another bitstream, a target highest TemporalId, and a target layer identifier list as inputs.
- [0287] `num_output_layer_sets` specifies the number of layer sets for which output layers are specified with `output_layer_set_index[ i ]` and `output_layer_flag[ lsIdx ][ j ]`. When not present, the value of `num_output_layer_sets` is inferred to be equal to 0. A layer set describing output layers is an output layer set.
- [0288] `output_layer_set_idx[ i ]` specifies the index `lsIdx` of the layer set for which `output_layer_flag[ lsIdx ][ j ]` is present.
- [0289] `output_layer_flag[ lsIdx ][ j ]` equal to 1 specifies that the layer with `nuh_layer_id` equal to `j` is a target output layer of the `lsIdx`-th layer set. A value of `output_layer_flag[ lsIdx ][ j ]` equal to 0 specifies that the layer with `nuh_layer_id` equal to `j` is not a target

output layer of the $lsIdx$ -th layer set.

- [0290] The `num_op_dpb_info_parameters` specifies the number of `op_dpb_parameters()` syntax structures present in the VPS extension RBSP, defined in terms of the operation point. The `num_op_dpb_info_parameters` decoders is in the range of 0 to `vps_num_layer_sets_minus1`, inclusive.
- [0291] The `operation_point_layer_set_idx[i]` specifies the index, into the list of layer sets defined by operation points to which the i th `op_dpb_info_parameters()` syntax structure in the VPS extension applies. The value of `operation_point_layer_set_idx[i]` may be in the range of 0 to `vps_num_layer_sets_minus1`, inclusive. For bitstream conformance the `operation_point_layer_set_idx[i]` is not equal to `operation_point_layer_set_idx[j]` for any j not equal to i .
- [0292] Referring to FIG. 35A, the `op_dpb_info_parameters` specifies `vps_max_sub_layers_minus1[j]`, `vps_sub_layer_ordering_info_present_flag[j]`, `vps_max_dec_pic_buffering_minus1[j][k]`, `vps_max_num_reorder_pics[j][k]`, and `vps_max_latency_increase_plus1[j][k]`.
- [0293] The `vps_max_sub_layers_minus1[j]` plus 1 indicates how many sub layers are included. The `vps_max_sub_layers_minus1[j]` plus 1 specifies the maximum number of temporal sub-layers that may be present in the CVS for layer with `nuh_layer_id` equal to j . The value of `vps_max_sub_layers_minus1[j]` is in the range of 0 to 6, inclusive.
- [0294] The `vps_sub_layer_ordering_info_present_flag[j]` indicates whether the syntax is for one set including all layers or for each individual layer. The `vps_sub_layer_ordering_info_present_flag[j]` equal to 1 specifies that `vps_max_dec_pic_buffering_minus1[j][k]`, `vps_max_num_reorder_pics[j][k]`, and `vps_max_latency_increase_plus1[j][k]` are present for layer with `nuh_layer_id` equal to j for `vps_max_sub_layers_minus1[j] + 1` sub-layers. The `vps_sub_layer_ordering_info_present_flag[j]` equal to 0 specifies that the values of `vps_max_dec_pic_buffering_minus1[j][vps_max_sub_layers_minus1[j]]`, `vps_max_num_reorder_pics[j][vps_max_sub_layers_minus1[j]]`, and `vps_max_latency_increase_plus1[j][vps_max_sub_layers_minus1[j]]` apply to all sub-layers for layer with `nuh_layer_id` equal to j .
- [0295] The `vps_max_dec_pic_buffering_minus1[j][k]` plus 1 specifies the maximum required size of the decoded picture buffer for the CVS for layer with `nuh_layer_id` equal to j in units of picture storage buffers when `HighestTid` is equal to k . The value of `vps_max_dec_pic_buffering_minus1[j][k]` may be in the range of 0 to `MaxDpbSize - 1` (as specified in subclause A.4), inclusive. When k is greater than 0, `vps_max_dec_pic_buffering_minus1[j][k]` may be greater than or equal to `vps_max_dec_pic_buffering_minus1[j][k - 1]`. When

vps_max_dec_pic_buffering_minus1[j][k] is not present for k in the range of 0 to vps_max_sub_layers_minus1[j] - 1, inclusive, due to vps_sub_layer_ordering_info_present_flag[j] being equal to 0, it is inferred to be equal to vps_max_dec_pic_buffering_minus1[j][vps_max_sub_layers_minus1[j]].

[0296] The vps_max_num_reorder_pics[j][k] indicates the maximum allowed number of pictures that can precede any picture in the CVS for layer with nuh_layer_id equal to j in decoding order and follow that picture in output order when HighestTid is equal to k. The value of vps_max_num_reorder_pics[j][k] may be in the range of 0 to vps_max_dec_pic_buffering_minus1[j][k], inclusive. When k is greater than 0, vps_max_num_reorder_pics[j][k] is greater than or equal to vps_max_num_reorder_pics[j][k - 1]. When vps_max_num_reorder_pics[j][k] is not present for k in the range of 0 to vps_max_sub_layers_minus1[j] - 1, inclusive, due to vps_sub_layer_ordering_info_present_flag[j] being equal to 0, it is inferred to be equal to vps_max_num_reorder_pics[j][vps_max_sub_layers_minus1[j]].

[0297] The vps_max_latency_increase_plus1[j][k] not equal to 0 is used to compute the value of VpsMaxLatencyPictures[j][k], which specifies the maximum number of pictures that can precede any picture in the CVS for layer with nuh_layer_id equal to j in output order and follow that picture in decoding order when HighestTid is equal to k.

[0298] When vps_max_latency_increase_plus1[j][k] is not equal to 0, the value of VpsMaxLatencyPictures[j][k] may be specified as follows:

$$\begin{aligned} \text{VpsMaxLatencyPictures}[\text{id}][j][k] = \\ \text{vps_max_num_reorder_pics}[\text{id}][j][k] + \\ \text{vps_max_latency_increase_plus1}[\text{id}][j][k] - 1 \end{aligned}$$

[0299] When vps_max_latency_increase_plus1[j][k] is equal to 0, no corresponding limit is expressed.

[0300] The value of vps_max_latency_increase_plus1[j][k] is in the range of 0 to $2^{32} - 2$, inclusive. When vps_max_latency_increase_plus1[j][k] is not present for k in the range of 0 to vps_max_sub_layers_minus1[j] - 1, inclusive, due to vps_sub_layer_ordering_info_present_flag[j] being equal to 0, it is inferred to be equal to vps_max_latency_increase_plus1[j][vps_max_sub_layers_minus1[j]].

[0301] The 'vps_max_sub_layers_minus1'[id][j] plus 1 specifies the maximum number of temporal sub-layers that may be present in the CVS for layer with nuh_layer_id equal to j for the operation point associated with index id. The value of vps_max_sub_layers_minus1[id][j] may be in the range of 0 to 6, inclusive.

[0302] The 'vps_sub_layer_ordering_info_present_flag'[id][j] equal to 1 specifies that vps_max_dec_pic_buffering_minus1[id][j][k], vps_max_num_reorder_pics[id][j][k],

$[[k]]$, and $vps_max_latency_increase_plus1[id][j][k]$ are present for layer with nuh_layer_id equal to j for the operation point associated with index id for $vps_max_sub_layers_minus1[id][j] + 1$ sub-layers.

$vps_sub_layer_ordering_info_present_flag[id][j]$ equal to 0 specifies that the values of $vps_max_dec_pic_buffering_minus1[id][j][vps_max_sub_layers_minus1[id][j]]$, $vps_max_num_reorder_pics[id][j][vps_max_sub_layers_minus1[id][j]]$, and $vps_max_latency_increase_plus1[id][j][vps_max_sub_layers_minus1[id][j]]$ apply to all sub-layers for layer with nuh_layer_id equal to j for the operation point associated with index id .

[0303] The ' $vps_max_dec_pic_buffering_minus1[id][j][k]$ ' plus 1 specifies the maximum required size of the decoded picture buffer for the CVS for layer with nuh_layer_id equal to j for the operation point associated with index id in units of picture storage buffers when HighestTid is equal to k . The value of $vps_max_dec_pic_buffering_minus1[id][j][k]$ may be in the range of 0 to $MaxDpbSize - 1$ (as specified in subclause A.4), inclusive. When k is greater than 0, $vps_max_dec_pic_buffering_minus1[id][j][k]$ may be greater than or equal to $vps_max_dec_pic_buffering_minus1[id][j][k - 1]$. When $vps_max_dec_pic_buffering_minus1[id][j][k]$ is not present for k in the range of 0 to $vps_max_sub_layers_minus1[id][j] - 1$, inclusive, due to $vps_sub_layer_ordering_info_present_flag[id][j]$ being equal to 0, it is inferred to be equal to $vps_max_dec_pic_buffering_minus1[id][j][vps_max_sub_layers_minus1[id][j]]$.

[0304] The ' $vps_max_num_reorder_pics[id][j][k]$ ' indicates the maximum allowed number of pictures that can precede any picture in the CVS for layer with nuh_layer_id equal to j for the operation point associated with index id in decoding order and follow that picture in output order when HighestTid is equal to k . The value of $vps_max_num_reorder_pics[id][j][k]$ may be in the range of 0 to $vps_max_dec_pic_buffering_minus1[id][j][k]$, inclusive. When k is greater than 0, $vps_max_num_reorder_pics[id][j][k]$ may be greater than or equal to $vps_max_num_reorder_pics[id][j][k - 1]$. When $vps_max_num_reorder_pics[id][j][k]$ is not present for k in the range of 0 to $vps_max_sub_layers_minus1[id][j] - 1$, inclusive, due to $vps_sub_layer_ordering_info_present_flag[id][j]$ being equal to 0, it is inferred to be equal to $vps_max_num_reorder_pics[id][j][vps_max_sub_layers_minus1[id][j]]$.

[0305] The ' $vps_max_latency_increase_plus1[id][j][k]$ ' not equal to 0 is used to compute the value of $VpsMaxLatencyPictures[id][j][k]$, which specifies the maximum number of pictures that can precede any picture in the CVS for layer with nuh_layer_id equal to j for the operation point associated with index id in output order

and follow that picture in decoding order when HighestTid is equal to k.

- [0306] When `vps_max_latency_increase_plus1[ id ][ j ][ k ]` is not equal to 0, the value of `VpsMaxLatencyPictures[ id ][ j ][ k ]` is specified as follows:

$$\begin{aligned} \text{VpsMaxLatencyPictures}[id][j][k] = \\ \text{vps_max_num_reorder_pics}[id][j][k] + \\ \text{vps_max_latency_increase_plus1}[id][j][k] - 1 \end{aligned}$$

- [0307] When `vps_max_latency_increase_plus1[ id ][ j ][ k ]` is equal to 0, no corresponding limit is expressed.
- [0308] The value of `vps_max_latency_increase_plus1[ id ][ j ][ k ]` may be in the range of 0 to $2^{32} - 2$, inclusive. When `vps_max_latency_increase_plus1[ id ][ j ][ k ]` is not present for k in the range of 0 to `vps_max_sub_layers_minus1[ id ][ j ] - 1`, inclusive, due to `vps_sub_layer_ordering_info_present_flag[ id ][ j ]` being equal to 0, it is inferred to be equal to `vps_max_latency_increase_plus1[ id ][ j ][ vps_max_sub_layers_minus1[ id ][ j ] ]`.
- [0309] Referring to FIG. 35 B, the `op_dpb_info_parameters` may be further modified as shown to `op_dpb_info_parameters(id,j)`. In this case the syntax of VPS extension may be as illustrated in FIG. 34B. The hypothetical reference decoder (HRD) is used to check bitstream and decoder conformance. Two types of bitstreams or bitstream subsets are subject to HRD conformance checking for the Joint Collaborative Team on Video Coding (JCT-VC). The first type, called a Type I bitstream, is a NAL unit stream containing only the VCL NAL units and NAL units with `nal_unit_type` equal to `FD_NUT` (filler data NAL units) for all access units in the bitstream. The second type, called a Type II bitstream, contains, in addition to the VCL NAL units and filler data NAL units for all access units in the bitstream, at least one of (a) additional non-VCL NAL units other than filler data NAL units, and (b) all `leading_zero_8bits`, `zero_byte`, `start_code_prefix_one_3bytes`, and `trailing_zero_8bits` syntax elements that form a byte stream from the NAL unit stream.
- [0310] The syntax elements of non-VCL NAL units (or their default values for some of the syntax elements), required for the HRD, are specified in the semantic subclauses of clause 7, Annexes D and E.
- [0311] Two types of HRD parameter sets (NAL HRD parameters and VCL HRD parameters) are used. The HRD parameter sets are signalled through the `hrd_parameters( )` syntax structure, which may be part of the SPS syntax structure or the VPS syntax structure.
- [0312] Multiple tests may be needed for checking the conformance of a bitstream, which is referred to as the bitstream under test. For each test, the following steps apply in the order listed:

(1) An operation point under test, denoted as TargetOp, is selected. The layer identifier list OpLayerIdList of TargetOp consists of the list of nuh_layer_id values, in increasing order of nuh_layer_id values, present in the bitstream subset associated with TargetOp, which is a subset of the nuh_layer_id values present in the bitstream under test. The OpTid of TargetOp is equal to the highest TemporalId present in the bitstream subset associated with TargetOp.

(2) TargetDecLayerIdList is set equal to OpLayerIdList of TargetOp, HighestTid is set equal to OpTid of TargetOp, and the sub-bitstream extraction process as specified in clause 10 is invoked with the bitstream under test, HighestTid, and TargetDecLayerIdList as inputs, and the output is assigned to BitstreamToDecode.

(3) The hrd_parameters() syntax structure and the sub_layer_hrd_parameters() syntax structure applicable to TargetOp are selected. If TargetDecLayerIdList contains all nuh_layer_id values present in the bitstream under test, the hrd_parameters() syntax structure in the active SPS (or provided through an external means not specified in this Specification) is selected. Otherwise, the hrd_parameters() syntax structure in the active VPS (or provided through some external means not specified in this Specification) that applies to TargetOp is selected. Within the selected hrd_parameters() syntax structure, if BitstreamToDecode is a Type I bitstream, the sub_layer_hrd_parameters(HighestTid) syntax structure that immediately follows the condition "if(vcl_hrd_parameters_present_flag)" is selected and the variable NalHrdModeFlag is set equal to 0; otherwise (BitstreamToDecode is a Type II bitstream), the sub_layer_hrd_parameters(HighestTid) syntax structure that immediately follows either the condition "if(vcl_hrd_parameters_present_flag)" (in this case the variable NalHrdModeFlag is set equal to 0) or the condition "if(nal_hrd_parameters_present_flag)" (in this case the variable NalHrdModeFlag is set equal to 1) is selected. When BitstreamToDecode is a Type II bitstream and NalHrdModeFlag is equal to 0, all non-VCL NAL units except filler data NAL units, and all leading_zero_8bits, zero_byte, start_code_prefix_one_3bytes, and trailing_zero_8bits syntax elements that form a byte stream from the NAL unit stream (as specified in Annex B), when present, are discarded from BitstreamToDecode, and the remaining bitstream is assigned to BitstreamToDecode.

[0313] In another case Multiple tests may be needed for checking the conformance of a bitstream, which is referred to as the bitstream under test. For each test, the following steps apply in the order listed:

(1) An output layer set under test, denoted as TargetOpLs is selected. The operation point referred in TargetOpLs by output_layer_set_idx[] identifies the operation point under test. The output layer identifier list OpLayerIdList of TargetOpLs consists of the list of nuh_layer_id values, in increasing order of nuh_layer_id values, present in the bitstream subset associated with TargetOp and TargetOpLs, which is a subset of the nuh_layer_id values present in the bitstream under test. The OpTid of TargetOp is equal to the highest TemporalId present in the bitstream subset associated with TargetOp.

(2) TargetDecLayerIdList is set equal to target decoded layer identifier list targetDLayerIdList for the selected output layer set TargetOpLs, HighestTid is set equal to OpTid of TargetOp, and the sub-bitstream extraction process as specified in clause 10 is invoked with the bitstream under test, HighestTid, and TargetDecLayerIdList as inputs, and the output is assigned to BitstreamToDecode.

(3) The hrd_parameters() syntax structure and the sub_layer_hrd_parameters() syntax structure applicable to TargetOp are selected. If TargetDecLayerIdList contains all nuh_layer_id values present in the bitstream under test, the hrd_parameters() syntax structure in the active SPS (or provided through an external means not specified in this Specification) is selected. Otherwise, the hrd_parameters() syntax structure in the active VPS (or provided through some external means not specified in this Specification) that applies to TargetOp is selected. Within the selected hrd_parameters() syntax structure, if BitstreamToDecode is a Type I bitstream, the sub_layer_hrd_parameters(HighestTid) syntax structure that immediately follows the condition "if(vcl_hrd_parameters_present_flag)" is selected and the variable NalHrdModeFlag is set equal to 0; otherwise (BitstreamToDecode is a Type II bitstream), the sub_layer_hrd_parameters(HighestTid) syntax structure that immediately follows either the condition "if(vcl_hrd_parameters_present_flag)" (in this case the variable NalHrdModeFlag is set equal to 0) or the condition "if(nal_hrd_parameters_present_flag)" (in this case the variable NalHrdModeFlag is set equal to 1) is selected. When BitstreamToDecode is a Type II bitstream and NalHrdModeFlag is equal to 0, all non-VCL NAL units except filler data NAL units, and all leading_zero_8bits, zero_byte, start_code_prefix_one_3bytes, and trailing_zero_8bits syntax elements that form a byte stream from the NAL unit stream (as specified in Annex B), when present, are discarded from BitstreamToDecode, and the remaining bitstream is assigned to BitstreamToDecode.

[0314] A conforming decoder may fulfil all requirements specified in this subclause.

(1) A decoder claiming conformance to a specific profile, tier and level may be able to successfully decode all bitstreams that conform to the bitstream conformance requirements specified in subclause C.4, in the manner specified in Annex A, provided that all VPSs, SPSs and PPSs referred to in the VCL NAL units, and appropriate buffering period and picture timing SEI messages are conveyed to the decoder, in a timely manner, either in the bitstream (by non-VCL NAL units), or by external means not specified in this Specification.

(2) When a bitstream contains syntax elements that have values that are specified as reserved and it is specified that decoders may ignore values of the syntax elements or NAL units containing the syntax elements having the reserved values, and the bitstream is otherwise conforming to this Specification, a conforming decoder may decode the bitstream in the same manner as it would decode a conforming bitstream and may ignore the syntax elements or the NAL units containing the syntax elements having the reserved values as specified.

- [0315] There are two types of conformance of a decoder: output timing conformance and output order conformance.
- [0316] To check conformance of a decoder, test bitstreams conforming to the claimed profile, tier and level, as specified in subclause C.4 are delivered by a hypothetical stream scheduler (HSS) both to the HRD and to the decoder under test (DUT). All cropped decoded pictures output by the HRD may also be output by the DUT, each cropped decoded picture output by the DUT may be a picture with PicOutputFlag equal to 1, and, for each such cropped decoded picture output by the DUT, the values of all samples that are output may be equal to the values of the samples produced by the specified decoding process.
- [0317] For output timing decoder conformance, the HSS operates as described above, with delivery schedules selected only from the subset of values of SchedSelIdx for which the bit rate and CPB size are restricted as specified in Annex A for the specified profile, tier and level, or with "interpolated" delivery schedules as specified below for which the bit rate and CPB size are restricted as specified in Annex A. The same delivery schedule is used for both the HRD and the DUT.
- [0318] When the HRD parameters and the buffering period SEI messages are present with $\text{cpb_cnt_minus1}[\text{HighestTid}]$ greater than 0, the decoder may be capable of decoding the bitstream as delivered from the HSS operating using an "interpolated" delivery schedule specified as having peak bit rate r , CPB size $c(r)$, and initial CPB removal delay

$$(f(r) \div r)$$

as follows:

$$\alpha = (r - \text{BitRate}[\text{SchedSelIdx} - 1]) / (\text{BitRate}[\text{SchedSelIdx}] - \text{BitRate}[\text{SchedSelIdx} - 1]), \quad (\text{C-22})$$

$$c(r) = \alpha * \text{CpbSize}[\text{SchedSelIdx}] + (1 - \alpha) * \text{CpbSize}[\text{SchedSelIdx} - 1], \quad (\text{C-23})$$

$$f(r) = \alpha * \text{InitCpbRemovalDelay}[\text{SchedSelIdx}] * \text{BitRate}[\text{SchedSelIdx}] + (1 - \alpha) * \text{InitCpbRemovalDelay}[\text{SchedSelIdx} - 1] * \text{BitRate}[\text{SchedSelIdx} - 1] \quad (\text{C-24})$$

- [0319] for any SchedSelIdx > 0 and r such that BitRate[SchedSelIdx - 1] <= r <= BitRate[SchedSelIdx] such that r and c(r) are within the limits as specified in Annex A for the maximum bit rate and buffer size for the specified profile, tier and level. The InitCpbRemovalDelay[SchedSelIdx] can be different from one buffering period to another and have to be re-calculated.
- [0320] For output timing decoder conformance, an HRD as described above is used and the timing (relative to the delivery time of the first bit) of picture output is the same for both the HRD and the DUT up to a fixed delay.
- [0321] For output order decoder conformance, the following applies:

(1) The HSS delivers the bitstream BitstreamToDecode to the DUT "by demand" from the DUT, meaning that the HSS delivers bits (in decoding order) only when the DUT requires more bits to proceed with its processing. This means that for this test, the coded picture buffer of the DUT could be as small as the size of the largest decoding unit.

(2) A modified HRD as described below is used, and the HSS delivers the bitstream to the HRD by one of the schedules specified in the bitstream BitstreamToDecode such that the bit rate and CPB size are restricted as specified in Annex A. The order of pictures output may be the same for both the HRD and the DUT.

(3) The HRD CPB size is given by $CpbSize[SchedSelIdx]$ as specified in subclause E.2.3, where SchedSelIdx and the HRD parameters are selected as specified in subclause C.1. The DPB size is given by $sps_max_dec_pic_buffering_minus1[HighestTid] + 1$ from the active SPS (when nuh_layer_id for the current decoded picture is equal to 0) or from the active layer SPS for the value of nuh_layer_id of the current decoded picture. In some cases, if operation point DPB information parameters $op_dpb_info_parameters()$ are present for the selected output layer set, The DPB size is given by $vps_max_dec_pic_buffering_minus1[HighestTid]$ when $currLayerId$ is equal to 0 or is set to $vps_max_dec_pic_buffering_minus1[CurrLayerId][HighestTid]$ for the $currLayerId$ for the operation point under test when $currLayerId$ is greater than 0, where $currLayerId$ is the nuh_layer_id of the current decoded picture. Otherwise if operation point DPB information parameters $op_dpb_info_parameters()$ are not present for the operation point under test, the DPB Size is given by $sps_max_dec_pic_buffering_minus1[HighestTid] + 1$ from the active SPS (when nuh_layer_id for the current decoded picture is equal to 0) or from the active layer SPS for the value of nuh_layer_id of the current decoded picture.

In some cases, if output layer sets DPB information parameters $oop_dpb_info_parameters()$ are present for the selected output layer set, The DPB size is given by $vps_max_dec_pic_buffering_minus1[HighestTid]$ when $currLayerId$ is equal to 0 or is set to $vps_max_dec_pic_buffering_minus1[CurrLayerId][HighestTid]$ for the $currLayerId$ for the selected output layer set, where $currLayerId$ is the nuh_layer_id of the current decoded picture. Otherwise if output layer sets DPB information parameters $oop_dpb_info_parameters()$ are not present for the selected output layer set, the DPB Size is given by $sps_max_dec_pic_buffering_minus1[HighestTid] + 1$ from the active SPS (when nuh_layer_id for the current decoded picture is equal to 0) or from the active layer SPS for the value of nuh_layer_id of the current decoded picture.

[0322] The removal time from the CPB for the HRD is the final bit arrival time and decoding is immediate. The operation of the DPB of this HRD is as described in subclauses C.5.2 through C.5.2.3.

[0323] The decoded picture buffer contains picture storage buffers. The number of picture storage buffers for nuh_layer_id equal to 0 is derived from the active SPS. The number

of picture storage buffers for each non-zero `nuh_layer_id` value is derived from the active layer SPS for that non-zero `nuh_layer_id` value. Each of the picture storage buffers contains a decoded picture that is marked as "used for reference" or is held for future output. The process for output and removal of pictures from the DPB as specified in subclause F.13.5.2.2 is invoked, followed by the invocation of the process for picture decoding, marking, additional bumping, and storage as specified in subclause F.13.5.2.3. The "bumping" process is specified in subclause F.13.5.2.4 and is invoked as specified in subclauses F.13.5.2.2 and F.13.5.2.3.

[0324] The output and removal of pictures from the DPB before the decoding of the current picture (but after parsing the slice header of the first slice of the current picture) happens instantaneously when the first decoding unit of the access unit containing the current picture is removed from the CPB and proceeds as follows.

[0325] The decoding process for RPS as specified in subclause 8.3.2 is invoked.

(1) If the current picture is an IRAP picture with NoRaslOutputFlag equal to 1 and with nuh_layer_id equal to 0 that is not picture 0, the following ordered steps are applied:

(A) The variable NoOutputOfPriorPicsFlag is derived for the decoder under test as follows:

(i) If the current picture is a CRA picture, NoOutputOfPriorPicsFlag is set equal to 1 (regardless of the value of no_output_of_prior_pics_flag).

(ii) Otherwise, if the value of pic_width_in_luma_samples, pic_height_in_luma_samples, or sps_max_dec_pic_buffering_minus1[HighestTid] derived from the active SPS is different from the value of pic_width_in_luma_samples, pic_height_in_luma_samples, or sps_max_dec_pic_buffering_minus1[HighestTid], respectively, derived from the SPS active for the preceding picture, NoOutputOfPriorPicsFlag may (but should not) be set to 1 by the decoder under test, regardless of the value of no_output_of_prior_pics_flag. Although setting NoOutputOfPriorPicsFlag equal to no_output_of_prior_pics_flag is preferred under these conditions, the decoder under test is allowed to set NoOutputOfPriorPicsFlag to 1 in this case.

(iii) Otherwise, NoOutputOfPriorPicsFlag is set equal to no_output_of_prior_pics_flag.

(B) The value of NoOutputOfPriorPicsFlag derived for the decoder under test is applied for the HRD as follows:

(i) If NoOutputOfPriorPicsFlag is equal to 1, all picture storage buffers in the DPB are emptied without output of the pictures they contain, and the DPB fullness is set equal to 0.

(ii) Otherwise (NoOutputOfPriorPicsFlag is equal to 0), all picture storage buffers containing a picture that is marked as "not needed for output" and "unused for reference" are emptied (without output), and all non-empty picture storage buffers in the DPB are emptied by repeatedly invoking the "bumping" process specified in subclause F.13.5.2.4, and the DPB fullness is set equal to 0.

(iii) Otherwise (the current picture is not an IRAP picture with NoRaslOutputFlag equal to 1 and with nuh_layer_id equal to 0), all picture storage buffers containing a picture which are marked as "not needed for output" and "unused for reference" are emptied (without output). For each picture storage buffer that is emptied, the DPB fullness is decremented by one. The variable currLayerId is set equal to nuh_layer_id of the current decoded picture.

[0326] The variables

MaxNumReorderPics[TargetOp][currLayerId][HighestTid],

MaxLatencyIncreasePlus1[TargetOp][currLayerId][HighestTid],

MaxLatencyPictures[TargetOp][currLayerId][HighestTid],

MaxDecPicBufferingMinus1[TargetOp][currLayerId][HighestTid] are derived

as follows based on the current operation point under test:

(1) If operation point DPB information parameters `op_dpb_info_parameters()` are present for the operation point under test `TargetOp`, `MaxNumReorderPics[ TargetOp ][ currLayerId ][ HighestTid ]` is set to `vps_max_num_reorder_pics[ HighestTid ]` when `currLayerId` is equal to 0 or is set to `vps_max_num_reorder_pics[ TargetOp ][ CurrLayerId ][ HighestTid ]` for the `currLayerId` for the operation point under test when `currLayerId` is greater than 0. Otherwise if operation point DPB information parameters `op_dpb_info_parameters()` are not present for the operation point under test `MaxNumReorderPics[ TargetOp ][ currLayerId ][ HighestTid ]` is set to `sps_max_num_reorder_pics[ HighestTid ]` from the active SPS (when `currLayerId` is equal to 0) or from the active layer SPS for the value of `currLayerId`.

(2) If operation point DPB information parameters `op_dpb_info_parameters()` are present for the operation point under test `TargetOp`, `MaxLatencyIncreasePlus1[ TargetOp ][ currLayerId ][ HighestTid ]` is set to `vps_max_latency_increase_plus1[ HighestTid ]` when `currLayerId` is equal to 0 or is set to `vps_max_latency_increase_plus1[ TargetOp ][ CurrLayerId ][ HighestTid ]` for the `currLayerId` for the operation point under test when `currLayerId` is greater than 0. If operation point DPB information parameters `op_dpb_info_parameters()` are present for the operation point under test, `MaxLatencyPictures[ TargetOp ][ currLayerId ][ HighestTid ]` is set to `VpsMaxLatencyPictures[ HighestTid ]` when `currLayerId` is equal to 0 or is set to `VpsMaxLatencyPictures[ TargetOp ][ CurrLayerId ][ HighestTid ]` for the `currLayerId` for the operation point under test when `currLayerId` is greater than 0. Otherwise if operation point DPB information parameters `op_dpb_info_parameters()` are not present for the operation point under test, `MaxLatencyIncreasePlus1[ TargetOp ][ currLayerId ][ HighestTid ]` is set to `sps_max_latency_increase_plus1[ HighestTid ]` of the active SPS (when `currLayerId` is equal to 0) or the active layer SPS for the value of `currLayerId` and `MaxLatencyPictures[ TargetOp ][ currLayerId ][ HighestTid ]` is set to `SpsMaxLatencyPictures[ HighestTid ]` derived from the active SPS (when `currLayerId` is equal to 0) or from the active layer SPS for the value of `currLayerId`.

(3) If operation point DPB information parameters `op_dpb_info_parameters()` are present for the selected operation point under test `TargetOp`, `MaxDecPicBufferingMinus1[ TargetOp ][ currLayerId ][ HighestTid ]` is set to `vps_max_dec_pic_buffering_minus1[ HighestTid ]` when `currLayerId` is equal to 0 or is set to `vps_max_dec_pic_buffering_minus1[ TargetOp ][ CurrLayerId ][ HighestTid ]` for the `currLayerId` for the operation point under test when `currLayerId` is greater than 0. Otherwise if operation point DPB information parameters `op_dpb_info_parameters()` are not present for the operation point under test, `MaxDecPicBufferingMinus1[ TargetOp ][ currLayerId ][ HighestTid ]` is set to `sps_max_dec_pic_buffering_minus1[ HighestTid ]` from the active SPS (when `currLayerId` is equal to 0) or from the active layer SPS for the value of `currLayerId`.

[0327] When one or more of the following conditions are true, the "bumping" process specified in subclause F.13.5.2.4 is invoked repeatedly while further decrementing the DPB fullness by one for each additional picture storage buffer that is emptied, until none of the following conditions are true:

(1) The number of pictures with `nuh_layer_id` equal to `currLayerId` in the DPB that are marked as "needed for output" is greater than `MaxNumReorderPics[ TargetOp ][ CurrLayerId ][ HighestTid ]`.

(2) If `MaxLatencyIncreasePlus1[ TargetOp ][ CurrLayerId ][ HighestTid ]` is not equal to 0 and there is at least one picture with `nuh_layer_id` equal to `currLayerId` in the DPB that is marked as "needed for output" for which the associated variable `PicLatencyCount[ currLayerId ]` is greater than or equal to `MaxLatencyPictures[ TargetOp ][ CurrLayerId ][ HighestTid ]`.

(3) The number of pictures with `nuh_layer_id` equal to `currLayerId` in the DPB is greater than or equal to `MaxDecPicBuffering[ TargetOp ][ CurrLayerId ][ HighestTid ]`.

[0328] The processes specified in this subclause happen instantaneously when the last decoding unit of access unit `n` containing the current picture is removed from the CPB.

[0329] The variable `currLayerId` is set equal to `nuh_layer_id` of the current decoded picture.

[0330] For each picture in the DPB that is marked as "needed for output" and that has a `nuh_layer_id` value equal to `currLayerId`, the associated variable `PicLatencyCount[ currLayerId ]` is set equal to `PicLatencyCount[ currLayerId ] + 1`.

[0331] The current picture is considered as decoded after the last decoding unit of the picture is decoded. The current decoded picture is stored in an empty picture storage buffer in the DPB, and the following applies:

(A) If the current decoded picture has `PicOutputFlag` equal to 1, it is marked as "needed for output" and its associated variable `PicLatencyCount[ currLayerId ]` is set equal to 0.

(B) Otherwise (the current decoded picture has `PicOutputFlag` equal to 0), it is marked as "not needed for output".

[0332] The current decoded picture is marked as "used for short-term reference".

[0333] When one or more of the following conditions are true, the "bumping" process specified in subclause F.13.5.2.4 is invoked repeatedly until none of the following conditions are true.

(A) The number of pictures with `nuh_layer_id` equal to `currLayerId` in the DPB that are marked as "needed for output" is greater than `MaxNumReorderPics[ TargetOp ][ CurrLayerId ][ HighestTid ]`.

(B) `MaxLatencyIncreasePlus1[ TargetOp ][ CurrLayerId ][ HighestTid ]` is not equal to 0 and there is at least one picture with `nuh_layer_id` equal to `currLayerId` in the DPB that is marked as "needed for output" for which the associated variable `PicLatencyCount[ currLayerId ]` is greater than or equal to `MaxLatencyPictures[ TargetOp ][ CurrLayerId ][ HighestTid ]`.

[0334] In other case The variables
`MaxNumReorderPics[ currLayerId ][ HighestTid ]`,
`MaxLatencyIncreasePlus1[ currLayerId ][ HighestTid ]`,
`MaxLatencyPictures[ currLayerId ][ HighestTid ]`,
`MaxDecPicBufferingMinus1[ currLayerId ][ HighestTid ]` may be derived as follows:

(1) If operation point DPB information parameters `op_dpb_info_parameters()` are present for the operation point under test, `MaxNumReorderPics[ currLayerId ][ HighestTid ]` is set to `vps_max_num_reorder_pics[ HighestTid ]` when `currLayerId` is equal to 0 or is set to `vps_max_num_reorder_pics[ CurrLayerId ][ HighestTid ]` for the `currLayerId` for the operation point under test when `currLayerId` is greater than 0. Otherwise if operation point DPB information parameters `op_dpb_info_parameters()` are not present for the operation point under test `MaxNumReorderPics[ currLayerId ][ HighestTid ]` is set to `sps_max_num_reorder_pics[ HighestTid ]` from the active SPS (when `currLayerId` is equal to 0) or from the active layer SPS for the value of `currLayerId`.

(2) If operation point DPB information parameters `op_dpb_info_parameters()` are present for the operation point under test, `MaxLatencyIncreasePlus1[ currLayerId ][ HighestTid ]` is set to `vps_max_latency_increase_plus1[ HighestTid ]` when `currLayerId` is equal to 0 or is set to `vps_max_latency_increase_plus1[ CurrLayerId ][ HighestTid ]` for the `currLayerId` for the operation point under test when `currLayerId` is greater than 0. If operation point DPB information parameters `op_dpb_info_parameters()` are present for the operation point under test, `MaxLatencyPictures[ currLayerId ][ HighestTid ]` is set to `VpsMaxLatencyPictures[ HighestTid ]` when `currLayerId` is equal to 0 or is set to `VpsMaxLatencyPictures[ CurrLayerId ][ HighestTid ]` for the `currLayerId` for the operation point under test when `currLayerId` is greater than 0. Otherwise if operation point DPB information parameters `op_dpb_info_parameters()` are not present for the operation point under test, `MaxLatencyIncreasePlus1[ currLayerId ][ HighestTid ]` is set to `sps_max_latency_increase_plus1[ HighestTid ]` of the active SPS (when `currLayerId` is equal to 0) or the active layer SPS for the value of `currLayerId` and `MaxLatencyPictures[ currLayerId ][ HighestTid ]` is set to `SpsMaxLatencyPictures[ HighestTid ]` derived from the active SPS (when `currLayerId` is equal to 0) or from the active layer SPS for the value of `currLayerId`.

(3) If operation point DPB information parameters `op_dpb_info_parameters()` are present for the selected operation point under test, `MaxDecPicBufferingMinus1[ currLayerId ][ HighestTid ]` is set to `vps_max_dec_pic_buffering_minus1[ HighestTid ]` when `currLayerId` is equal to 0 or is set to `vps_max_dec_pic_buffering_minus1[ CurrLayerId ][ HighestTid ]` for the `currLayerId` for the operation point under test when `currLayerId` is greater than 0. Otherwise if operation point DPB information parameters `op_dpb_info_parameters()` are not present for the operation point under test, `MaxDecPicBufferingMinus1[ currLayerId ][ HighestTid ]` is set to `sps_max_dec_pic_buffering_minus1[ HighestTid ]` from the active SPS (when `currLayerId` is equal to 0) or from the active layer SPS for the value of `currLayerId`.

[0335] When one or more of the following conditions are true, the "bumping" process specified in subclause F.13.5.2.4 is invoked repeatedly while further decrementing the DPB fullness by one for each additional picture storage buffer that is emptied, until none of the following conditions are true:

(1) The number of pictures with `nuh_layer_id` equal to `currLayerId` in the DPB that are marked as "needed for output" is greater than `MaxNumReorderPics[CurrLayerId][HighestTid]`.

(2) If `MaxLatencyIncreasePlus1[CurrLayerId][HighestTid]` is not equal to 0 and there is at least one picture with `nuh_layer_id` equal to `currLayerId` in the DPB that is marked as "needed for output" for which the associated variable `PicLatencyCount[ currLayerId ]` is greater than or equal to `MaxLatencyPictures[CurrLayerId][HighestTid]`.

(3) The number of pictures with `nuh_layer_id` equal to `currLayerId` in the DPB is greater than or equal to `MaxDecPicBuffering[CurrLayerId][HighestTid]`.

[0336] The processes specified in this subclause happen instantaneously when the last decoding unit of access unit *n* containing the current picture is removed from the CPB.

[0337] The variable `currLayerId` is set equal to `nuh_layer_id` of the current decoded picture.

[0338] For each picture in the DPB that is marked as "needed for output" and that has a `nuh_layer_id` value equal to `currLayerId`, the associated variable `PicLatencyCount[ currLayerId ]` is set equal to `PicLatencyCount[ currLayerId ] + 1`.

[0339] The current picture is considered as decoded after the last decoding unit of the picture is decoded. The current decoded picture is stored in an empty picture storage buffer in the DPB, and the following applies:

(A) If the current decoded picture has `PicOutputFlag` equal to 1, it is marked as "needed for output" and its associated variable `PicLatencyCount[ currLayerId ]` is set equal to 0.

(B) Otherwise (the current decoded picture has `PicOutputFlag` equal to 0), it is marked as "not needed for output".

[0340] The current decoded picture is marked as "used for short-term reference".

[0341] When one or more of the following conditions are true, the "bumping" process specified in subclause F.13.5.2.4 is invoked repeatedly until none of the following conditions are true.

(A) The number of pictures with `nuh_layer_id` equal to `currLayerId` in the DPB that are marked as "needed for output" is greater than `MaxNumReorderPics[CurrLayerId][HighestTid]`.

(B) `MaxLatencyIncreasePlus1[CurrLayerId][HighestTid]` is not equal to 0 and there is at least one picture with `nuh_layer_id` equal to `currLayerId` in the DPB that is marked as "needed for output" for which the associated variable `PicLatencyCount[ currLayerId ]` is greater than or equal to `MaxLatencyPictures[CurrLayerId][HighestTid]`.

[0342] The "bumping" process consists of the following ordered steps:

(A) The pictures that are first for output are selected as the ones having the smallest value of `PicOrderCntVal` of all pictures in the DPB marked as "needed for output".

(B) These pictures are cropped, using the conformance cropping window specified in the active SPS for the picture with `nuh_layer_id` equal to 0 or in the active layer SPS for a `nuh_layer_id` value equal to that of the picture, the cropped pictures are output in ascending order of `nuh_layer_id`, and the pictures are marked as "not needed for output".

(C) Each picture storage buffer that contains a picture marked as "unused for reference" and that included one of the pictures that was cropped and output is emptied.

[0343] The VPS Extension may have additional modifications, if desired.

[0344] Referring to FIG. 36, an additional modification may include the DPB parameters being sent in the VPS extension for output layer sets instead of for operation points, where the `oops_dpb_info_parameters(j)` are illustrated in FIG. 37.

[0345] The `num_dpb_info_parameters` specifies the number of `oop_dpb_parameters( )` syntax structures present in the VPS extension RBSP. `num_dpb_info_parameters` decoders may be in the range of 0 to `num_output_layer_sets`, inclusive.

[0346] The `output_point_layer_set_idx[ i ]` specifies the index, into the list of target output layer sets to which the *i*th `oop_dpb_info_parameters( )` syntax structure in the VPS extension applies.

[0347] The value of `output_point_layer_set_idx[ i ]` should be in the range of 0 to `num_output_layer_sets`, inclusive. It is requirement of bitstream conformance that `output_point_layer_set_idx[ i ]` may not be equal to `output_point_layer_set_idx[ j ]` for any *j* not equal to *i*.

[0348] Referring to FIG. 38, the `oop_dpb_info_paremters(c)` may be further modified, where the syntax in the VPS extension may be as illustrated in FIG. 39.

[0349] Referring to FIG. 40, the oop_dpb_info_paremters(c) may be further modified, where the syntax in the VPS extension may be as illustrated in FIG.41 or FIG. 42.

[0350] An exemplary alternative for the syntax in VPS extension is that

for(j = 0; j <= vps_max_layer_id; j++)
oop_dpb_info_parameters(j)

[0351] may be changed to

for(j = 0; j <= vps_max_layers_minus1; j++)
oop_dpb_info_parameters(j)

[0352] The vps_max_layer_id specifies the maximum allowed value of nuh_layer_id of all NAL units in the CVS. The vps_max_layers_minus1, specifies the maximum number of layers that may be present in the CVS, wherein a layer may e.g. be a spatial scalable layer, a quality scalable layer, a texture view or a depth view.

[0353] Another exemplary alternative for the syntax in VPS extension is that

for(j = 0; j <= vps_max_layer_id; j++)
oop_dpb_info_parameters(j)

[0354] may be changed to

for(j = 0; j < numOutputLayers; j++)
oop_dpb_info_parameters(j)

[0355] where numOutputLayers for the selected output layer set index oplIdx is derived as:

```

for(k=0, numOutputLayers=0; k<=vps_max_layer_id; k++)
    if(output_layer_flag[opLsIdx][k])
        targetOpLayerIdList
[numOutputLayers++]=layer_id_in_nuh[k].

```

[0356] Another exemplary alternative for the syntax in VPS extension is that

for(j = 0; j <= vps_max_layer_id; j++)
oop_dpb_info_parameters(j)

[0357] may be changed to

for(j = 0; j < numDecodedLayers; j++)
oop_dpb_info_parameters(j)

[0358] where numOutputLayers for the selected oplIdx is derived as:

```

        for(k=0, numOutputLayers=0; k<=vps_max_layer_id; k++)
            if(output_layer_flag[opLsIdx][k])
                targetOpLayerIdList
[numOutputLayers++] = layer_id_in_nuh[k].

```

[0359] Then a target decoded layer identifier list targetDLayerIdList and numDecodedLayers for the selected opLsIdx is derived as:

```

        for(m=0, numDecodedLayers=0; m< numOutputLayers; m++) {
            for(n=0; n<NumDirectRefLayers[LayerIdInVps[targetOpLayerIdList[
m]]]; n++) {
                rLid=RefLayerId[LayerIdInVps[targetOpLayerIdList[m]]][n]
                if(rLid not included in targetDLayerIdList[0,...,
numDecodedLayers])
                    targetDLayerIdList[numDecodedLayers++] = rLid;
            }
        }

```

[0360] In one embodiment an additional flag maybe signalled to indicate if oop_dpb_information_parameters are signalled for the particular layer as follows:

for(j = 0; j <= vps_max_layer_id; j++) {	
vps_layer_info_present_flag[j]	u(1)
if(vps_layer_info_present_flag)	
oop_dpb_info_parameters(j)	
}	

[0361] The vps_layer_info_present_flag[j] equal to 1 specifies that oop_dpb_info_parameters are present for the j'th layer for the particular output layer set. vps_layer_info_present_flag[j] equal to 0 specifies that oop_dpb_info_parameters are not present for the j'th layer for the particular output layer set.

[0362] In another embodiment num_dpb_info_parameters decoders may be in the range of 0 to 1024, inclusive. In yet another embodiment a different fixed number could be used in place of 1024.

[0363] In an alternative embodiment output_point_layer_set_idx[i] is in the range of 0 to 1023, inclusive.

[0364] Referring to FIG. 43, another modified VPS extension and layer_dpb_info(i) may be used if the DPB parameters are sent in the VPS extension for each layer independently of output layer sets and operation points.

[0365] Referring to FIG. 44, a modified layer_dpb_info(i) may be used where the syntax

element `vps_max_sub_layer_minus1` signaled from VPS is used for all the layers and is not separately signalled in `oop_dpb_info_parameters(id)` / `op_dpb_info_parameters(id)`.

- [0366] In another embodiment one or more of the syntax elements may be signaled using a known fixed number of bits instead of `u(v)` instead of `ue(v)`. For example they could be signaled using `u(8)` or `u(16)` or `u(32)` or `u(64)`, etc.
- [0367] In another embodiment one or more of these syntax element could be signaled with `ue(v)` or some other coding scheme instead of fixed number of bits such as `u(v)` coding.
- [0368] In another embodiment the names of various syntax elements and their semantics may be altered by adding a plus1 or plus2 or by subtracting a minus1 or a minus2 compared to the described syntax and semantics.
- [0369] In yet another embodiment various syntax elements may be signaled per picture anywhere in the bitstream. For example they may be signaled in slice segment header, `pps/` `sps/` `vps/` or any other parameter set or other normative part of the bitstream.
- [0370] In yet another embodiments all the concepts defined in this invention related to output layer sets could be applied to output operation points [2,3] and/ or to operation points [1].
- [0371] As previously described, sequence parameter sets ("SPS") may be used to carry data valid for an entire video sequence. Accordingly, the SPS is a syntax structure containing syntax elements that apply to zero or more entire coded video sequences as determined by the content of a syntax element found in the PPS referred to by a syntax element, such as that found in each slice segment header. Also as previously described, picture parameter sets ("PPS") carry data valid on a picture by picture basis. Accordingly, the PPS is a syntax structure containing syntax elements that apply to zero or more entire coded pictures as determined by a syntax element, such as that found in each slice segment header. By way of example, the base layer may be a 1080p encoded video sequence while the enhancement layer(s) provides a 4K encoded video sequence.
- [0372] Referring to FIG. 45, when coding scalable high efficiency coding ("SVHC") the base layer may include one or more SPS and may also include one or more PPS. Also, each enhancement layer may include one or more SPS and may also include one or more PPS. In FIG. 45 SPS+ indicates one or more SPS and PPS+ indicates one or more PPS being signaled for a particular base or enhancement layer. In this manner, for a video bitstream having both a base layer and one or more enhancement layers, the collective number of SPS and PPS data sets becomes significant together with the required bandwidth to transmit such data, which tends to be limited in many applications. With such bandwidth limitations, it is desirable to limit the data that needs to be transmitted, and locate the data in the bitstream in an effective manner. Each layer may have one SPS and/or PPS that is activate at any particular time, and may

select a different active SPS and/or PPS, as desired.

[0373] An input picture may comprise a plurality of coded tree blocks (e.g., generally referred to herein as blocks) may be partitioned into one or several slices. The values of the samples in the area of the picture that a slice represents may be properly decoded without the use of data from other slices provided that the reference pictures used at the encoder and the decoder are the same and that de-blocking filtering does not use information across slice boundaries. Therefore, entropy decoding and block reconstruction for a slice does not depend on other slices. In particular, the entropy coding state may be reset at the start of each slice. The data in other slices may be marked as unavailable when defining neighborhood availability for both entropy decoding and reconstruction. The slices may be entropy decoded and reconstructed in parallel. No intra prediction and motion-vector prediction is preferably allowed across the boundary of a slice. In contrast, de-blocking filtering may use information across slice boundaries.

[0374] FIG. 46 illustrates an exemplary video picture 2090 comprising eleven blocks in the horizontal direction and nine blocks in the vertical direction (nine exemplary blocks labeled 2091-2099). FIG. 46 illustrates three exemplary slices: a first slice denoted "SLICE #0" 2080, a second slice denoted "SLICE #1" 2081 and a third slice denoted "SLICE #2" 2082. The decoder may decode and reconstruct the three slices 2080, 2081, 2082 in parallel. Each of the slices may be transmitted in scan line order in a sequential manner. At the beginning of the decoding/reconstruction process for each slice, context models are initialized or reset and blocks in other slices are marked as unavailable for both entropy decoding and block reconstruction. The context model generally represents the state of the entropy encoder and/or decoder. Thus, for a block, for example, the block labeled 2093, in "SLICE #1," blocks (for example, blocks labeled 2091 and 2092) in "SLICE #0" may not be used for context model selection or reconstruction. Whereas, for a block, for example, the block labeled 2095, in "SLICE #1," other blocks (for example, blocks labeled 2093 and 2094) in "SLICE #1" may be used for context model selection or reconstruction. Therefore, entropy decoding and block reconstruction proceeds serially within a slice. Unless slices are defined using a flexible block ordering (FMO), blocks within a slice are processed in the order of a raster scan.

[0375] Flexible block ordering defines a slice group to modify how a picture is partitioned into slices. The blocks in a slice group are defined by a block-to-slice-group map, which is signaled by the content of the picture parameter set and additional information in the slice headers. The block-to-slice-group map consists of a slice-group identification number for each block in the picture. The slice-group identification number specifies to which slice group the associated block belongs. Each slice group may be partitioned into one or more slices, wherein a slice is a sequence of blocks within the

same slice group that is processed in the order of a raster scan within the set of blocks of a particular slice group. Entropy decoding and block reconstruction proceeds serially within a slice group.

- [0376] FIG. 47 depicts an exemplary block allocation into three slice groups: a first slice group denoted "SLICE GROUP #0" 2083, a second slice group denoted "SLICE GROUP #1" 2084 and a third slice group denoted "SLICE GROUP #2" 2085. These slice groups 2083, 2084, 2085 may be associated with two foreground regions and a background region, respectively, in the picture 2090.
- [0377] The arrangement of slices, as illustrated in FIG. 47, may be limited to defining each slice between a pair of blocks in the image scan order, also known as raster scan or a raster scan order. This arrangement of scan order slices is computationally efficient but does not tend to lend itself to the highly efficient parallel encoding and decoding. Moreover, this scan order definition of slices also does not tend to group smaller localized regions of the image together that are likely to have common characteristics highly suitable for coding efficiency. The arrangement of slices 2083, 2084, 2085, as illustrated in FIG. 47, is highly flexible in its arrangement but does not tend to lend itself to high efficient parallel encoding or decoding. Moreover, this highly flexible definition of slices is computationally complex to implement in a decoder.
- [0378] Referring to FIG. 48, a tile technique divides an image into a set of rectangular (inclusive of square) regions. The blocks (alternatively referred to as largest coding units or coded treeblocks in some systems) within each of the tiles are encoded and decoded in a raster scan order. The arrangement of tiles are likewise encoded and decoded in a raster scan order. Accordingly, there may be any suitable number of column boundaries (e.g., 0 or more) and there may be any suitable number of row boundaries (e.g., 0 or more). Thus, the frame may define one or more slices, such as the one slice illustrated in FIG. 48. In some embodiments, blocks located in different tiles are not available for intra-prediction, motion compensation, entropy coding context selection or other processes that rely on neighboring block information.
- [0379] Referring to FIG. 49, the tile technique is shown dividing an image into a set of three rectangular columns. The blocks (alternatively referred to as largest coding units or coded treeblocks in some systems) within each of the tiles are encoded and decoded in a raster scan order. The tiles are likewise encoded and decoded in a raster scan order. One or more slices may be defined in the scan order of the tiles. Each of the slices are independently decodable. For example, slice 1 may be defined as including blocks 1-9, slice 2 may be defined as including blocks 10-28, and slice 3 may be defined as including blocks 29-126 which spans three tiles. The use of tiles facilitates coding efficiency by processing data in more localized regions of a frame.
- [0380] Referring to FIG. 50, the base layer and the enhancement layers may each include

tiles which each collectively form a picture or a portion thereof. The coded pictures including tiles from the base layer and one or more enhancement layers may collectively form an access unit. The access unit may be defined as a set of NAL units that are associated with each other according to a specified classification rule, are consecutive in decoding order, and/or contain the VCL NAL units of all coded pictures associated with the same output time (picture order count or otherwise) and their associated non-VCL NAL units. The VCL NAL is the video coding layer of the network abstraction layer. Similarly, the coded picture may be defined as a coded representation of a picture comprising VCL NAL units with a particular value of `nuh_layer_id` within an access unit and containing all coding tree units of the picture. Additional descriptions are described in B. Bros, W.-J. Han, J.-R. Ohm, G. J. Sullivan, and T. Wiegand, "High efficiency video coding (HEVC) text specification draft 10," JCTVC-L1003, Geneva, January 2013; J. Chen, J. Boyce, Y. Ye, M.M. Hannuksela, "SHVC Draft Text 2," JCTVC-M1008, Incheon, May 2013; G. Tech, K. Wegner, Y. Chen, M. Hannuksela, J. Boyce, "MV-HEVC Draft Text 4 (ISO/IEC 23008-2:201x/PDAM2)," JCTVC-D1004, Incheon, May 2013; and K. Suhling, R. Skupin, G. Tech, T. Schierl, K. Rapaka, W. Pu, X. Li, J. Chen, Y.-K. Wang, M. Karczewicz, K. Ugur, M. M. Hannuksela, "Tile Boundary Alignment and Inter-layer Prediction Constraint for SHVC and MV-HEVC," JCTVC-M0464, Incheon, April 2013, each of which is incorporated by reference herein in its entirety.

[0381] $x \ll y$ represents the arithmetic left shift of a two's complement integer representation of x by y binary digits. This function is defined only for non-negative integer values of y . Bits shifted into the least significant bits as a result of the left shift have a value equal to 0.

[0382] $x \gg y$ represents the arithmetic right shift of a two's complement integer representation of x by y binary digits. This function is defined only for non-negative integer values of y . Bits shifted into the MSBs as a result of the right shift have a value equal to the MSB of x prior to the shift operation.

[0383] $\text{Ceil}(x)$ represents the smallest integer greater than or equal to x .

[0384] $+$ represents addition.

[0385] $-$ represents subtraction.

[0386] $\div$

is used to denote division in mathematical equations where no truncation or rounding is intended.

[0387] x/y is used to denote division in mathematical equations where no truncation or rounding is intended.

[0388] $>$ represents greater than.

[0389] $\geq$ represents greater than equal to.

- [0390] < represents less than.
- [0391] <= represents less than equal to.
- [0392] == represents equal to
- [0393] != represents not equal to.
- [0394] = represents assignment operator.
- [0395] * represents multiplication, including matrix multiplication.
- [0396] x && y represents boolean logical "and" of x and y.
- [0397] x || y represents boolean logical "or" of x and y.
- [0398] A coding tree block is an NxN block of samples for some value of N such that the division of a component into coding tree blocks is a partitioning.
- [0399] The array size for each luma coding tree block in both width and height is CtbSizeY in units of samples.
- [0400] The variable PicWidthInCtbsY is derived as follows
- $$\text{PicWidthInCtbsY} = \text{Ceil}(\text{pic_width_in_luma_samples} \div \text{CtbSizeY})$$
- [0401] The variable PicHeightInCtbsY is derived as follows
- $$\text{PicHeightInCtbsY} = \text{Ceil}(\text{pic_height_in_luma_samples} \div \text{CtbSizeY})$$
- [0402] The variable PicSizeInCtbsY is derived as follows $\text{PicSizeInCtbsY} = \text{PicWidthInCtbsY} * \text{PicHeightInCtbsY}$
- [0403] The num_tile_columns_minus1 plus 1 specifies the number of tile columns partitioning the picture. num_tile_columns_minus1 shall be in the range of 0 to PicWidthInCtbsY - 1, inclusive. When not present, the value of num_tile_columns_minus1 is inferred to be equal to 0.
- [0404] The num_tile_rows_minus1 plus 1 specifies the number of tile rows partitioning the picture. num_tile_rows_minus1 shall be in the range of 0 to PicHeightInCtbsY - 1, inclusive. When not present, the value of num_tile_rows_minus1 is inferred to be equal to 0.
- [0405] When tiles_enabled_flag is equal to 1, num_tile_columns_minus1 and num_tile_rows_minus1 shall not be both equal to 0.
- [0406] The uniform_spacing_flag equal to 1 specifies that tile column boundaries and likewise tile row boundaries are distributed uniformly across the picture. uniform_spacing_flag equal to 0 specifies that tile column boundaries and likewise tile row boundaries are not distributed uniformly across the picture but signalled explicitly using the syntax elements column_width_minus1[i] and row_height_minus1[i]. When not present, the value of uniform_spacing_flag is inferred to be equal to 1.
- [0407] The column_width_minus1[i] plus 1 specifies the width of the i-th tile column in units of coding tree blocks.

- [0408] The `row_height_minus1[ i ]` plus 1 specifies the height of the *i*-th tile row in units of coding tree blocks.
- [0409] The `loop_filter_across_tiles_enabled_flag` equal to 1 specifies that in-loop filtering operations may be performed across tile boundaries in pictures referring to the PPS. `loop_filter_across_tiles_enabled_flag` equal to 0 specifies that in-loop filtering operations are not performed across tile boundaries in pictures referring to the PPS. The in-loop filtering operations include the deblocking filter and sample adaptive offset filter operations. When not present, the value of `loop_filter_across_tiles_enabled_flag` is inferred to be equal to 1.
- [0410] The list `rowHeight[ j ]` for *j* ranging from 0 to `num_tile_rows_minus1`, inclusive, specifies the height of the *j*-th tile row in units of CTBs.
- [0411] The list `colWidth[ i ]` for *i* ranging from 0 to `num_tile_columns_minus1`, inclusive, specifies the width of the *i*-th tile column in units of CTBs.
- [0412] The variables `PicWidthInSamplesL` and `PicHeightInSamplesL` are set equal to `pic_width_in_luma_samples` and `pic_height_in_luma_samples`, respectively.
- [0413] The variable `CtbAddrInRs`, specifying a coding tree block address in coding tree block raster scan of a picture.
- [0414] The list `CtbAddrRsToTs[ ctbAddrRs ]` for `ctbAddrRs` ranging from 0 to `PicSizeInCtbsY - 1`, inclusive, specifying the conversion from a CTB address in CTB raster scan of a picture to a CTB address in tile scan.
- [0415] The list `TileId[ ctbAddrTs ]` for `ctbAddrTs` ranging from 0 to `PicSizeInCtbsY - 1`, inclusive, specifying the conversion from a CTB address in tile scan to a tile identifier.
- [0416] The `scaled_ref_layer_left_offset[ i ]` specifies the horizontal offset between the upper-left luma sample of the resampled *i*-th direct reference layer picture used for inter-layer prediction and the upper-left luma sample of the current picture in units of two luma samples. When not present, the value of `scaled_ref_layer_left_offset[ i ]` is inferred to be equal to 0.
- [0417] The `scaled_ref_layer_top_offset[ i ]` specifies the vertical offset between the upper-left luma sample of the resampled *i*-th direct reference layer picture used for inter-layer prediction and the upper-left luma sample of the current picture in units of two luma samples. When not present, the value of `scaled_ref_layer_top_offset[ i ]` is inferred to be equal to 0.
- [0418] The `scaled_ref_layer_right_offset[ i ]` specifies the horizontal offset between the bottom-right luma sample of the resampled *i*-th direct reference layer picture used for inter-layer prediction and the bottom-right luma sample of the current picture in units of two luma samples. When not present, the value of `scaled_ref_layer_right_offset[ i ]` is inferred to be equal to 0.
- [0419] The `scaled_ref_layer_bottom_offset[ i ]` specifies the vertical offset between the

bottom-right luma sample of the resampled i-th direct reference layer picture used for inter-layer prediction and the bottom-right luma sample of the current picture in units of two luma samples. When not present, the value of scaled_ref_layer_bottom_offset[i] is inferred to be equal to 0.

[0420] The variables ScaledRefLayerLeftOffset, ScaledRefLayerTopOffset, ScaledRefLayerRightOffset and ScaledRefLayerBottomOffset are derived as follows:

$$\text{ScaledRefLayerLeftOffset} = \text{scaled_ref_layer_left_offset}[\text{dRIdx}] \ll 1$$

$$\text{ScaledRefLayerTopOffset} = \text{scaled_ref_layer_top_offset}[\text{dRIdx}] \ll 1$$

$$\text{ScaledRefLayerRightOffset} = \text{scaled_ref_layer_right_offset}[\text{dRIdx}] \ll 1$$

$$\text{ScaledRefLayerBottomOffset} = \text{scaled_ref_layer_bottom_offset}[\text{dRIdx}] \ll 1$$

where dRIdx corresponds to a direct reference layer index.

[0421] The variables RefLayerPicWidthInSamplesL and RefLayerPicHeightInSamplesL are set equal to the width and height of the decoded reference layer picture in units of luma samples, respectively.

[0422] The variables ScaledRefLayerPicWidthInSamplesL and ScaledRefLayerPicHeightInSamplesL are derived as follows:

$$\text{ScaledRefLayerPicWidthInSamplesL} = \text{PicWidthInSamplesL} -$$

$$\text{ScaledRefLayerLeftOffset} - \text{ScaledRefLayerRightOffset}$$

$$\text{ScaledRefLayerPicHeightInSamplesL} = \text{PicHeightInSamplesL} -$$

$$\text{ScaledRefLayerTopOffset} - \text{ScaledRefLayerBottomOffset}$$

[0423] The variables ScaleFactorX and ScaleFactorY are derived as follows:

$$\text{ScaleFactorX} = ((\text{RefLayerPicWidthInSamplesL} \ll 16) + (\text{ScaledRefLayerPicWidthInSamplesL} \gg 1)) /$$

$$\text{ScaledRefLayerPicWidthInSamplesL}$$

$$\text{ScaleFactorY} = ((\text{RefLayerPicHeightInSamplesL} \ll 16) + (\text{ScaledRefLayerPicHeightInSamplesL} \gg 1)) /$$

$$\text{ScaledRefLayerPicHeightInSamplesL}$$

[0424] The array size for each luma coding tree block in both width and height for the reference layer is CtbSizeYRL in units of samples.

[0425] pic_width_in_luma_samples_RL specifies the width of each reference layer decoded picture in units of luma samples. pic_width_in_luma_samples_RL may not be equal to 0.

[0426] pic_height_in_luma_samples_RL specifies the height of each reference layer decoded picture in units of luma samples. pic_height_in_luma_samples_RL may not

be equal to 0.

[0427] The variable PicWidthInCtbsYRL is derived as follows

$$\text{PicWidthInCtbsYRL} = \text{Ceil}(\text{pic_width_in_luma_samples_RL} \div \text{CtbSizeYRL})$$

[0428] The variable PicHeightInCtbsYRL is derived as follows

$$\text{PicHeightInCtbsYRL} = \text{Ceil}(\text{pic_height_in_luma_samples_RL} \div \text{CtbSizeYRL})$$

[0429] The variable PicSizeInCtbsYRL is derived as follows $\text{PicSizeInCtbsYRL} = \text{PicWidthInCtbsYRL} * \text{PicHeightInCtbsYRL}$

[0430] num_tile_columns_minus1_RL plus 1 specifies the number of tile columns partitioning the reference layer picture. num_tile_columns_minus1_RL shall be in the range of 0 to PicWidthInCtbsYRL - 1, inclusive. When not present, the value of num_tile_columns_minus1_RL is inferred to be equal to 0.

[0431] num_tile_rows_minus1_RL plus 1 specifies the number of tile rows partitioning the reference layer picture. num_tile_rows_minus1_RL shall be in the range of 0 to PicHeightInCtbsYRL - 1, inclusive. When not present, the value of num_tile_rows_minus1_RL is inferred to be equal to 0.

[0432] The list rowHeightRL[j] for j ranging from 0 to num_tile_rows_minus1_RL, inclusive, specifies the height of the j-th tile row in units of CTBs for the corresponding reference layer picture.

[0433] The list colWidthRL[i] for i ranging from 0 to num_tile_columns_minus1_RL, inclusive, specifies the width of the i-th tile column in units of CTBs for the corresponding reference layer picture.

[0434] column_width_minus1_RL[i] plus 1 specifies the width of the i-th tile column in units of coding tree blocks for the corresponding reference layer picture.

[0435] ColumnWidthMinus1RL[i] plus 1 specifies the width of the i-th tile column in units of coding tree blocks for the corresponding reference layer picture.

[0436] row_height_minus1_RL[i] plus 1 specifies the height of the i-th tile row in units of coding tree blocks for the corresponding reference layer picture.

[0437] RowHeightMinus1RL[i] plus 1 specifies the height of the i-th tile row in units of coding tree blocks for the corresponding reference layer picture,

[0438] The variable CtbAddrInRsRL, specifying a coding tree block address in coding tree block raster scan of the corresponding reference layer picture.

[0439] The list CtbAddrRsToTsRL[ctbAddrRs] for ctbAddrRs ranging from 0 to PicSizeInCtbsYRL - 1, inclusive, specifying the conversion from a CTB address in CTB raster scan of a corresponding reference layer picture to a CTB address in tile scan.

[0440] The list TileIdRL[ctbAddrTs] for ctbAddrTs ranging from 0 to PicSizeInCtbsYRL - 1, inclusive, specifying the conversion from a CTB address in tile scan of a corre-

sponding reference layer picture to a tile identifier.

- [0441] `layer_id_in_nuh[ i ]` specifies the value of the `nuh_layer_id` syntax element in VCL NAL units of the *i*-th layer. In an embodiment *i* ranges from 0 to `vps_max_layers_minus1`, inclusive. In an embodiment when not present, the value of `layer_id_in_nuh[ i ]` is inferred to be equal to *i*.
- [0442] The list value `NumDirectRefLayer[ layer_id_in_nuh[ i ] ]` equals to the number of direct reference layers for target layer with `nuh_layer_id layer_id_in_nuh[ i ]`.
- [0443] The array value `DirectRefLayerIdx[ layer_id_in_nuh[ i ] ][ layer_id_in_nuh[ j ] ]` equals to the direct reference layer index for a target layer with `nuh_layer_id layer_id_in_nuh[ i ]` and a reference layer with `nuh_layer_id layer_id_in_nuh[ j ]`.
- [0444] The array value `RefLayerId[ layer_id_in_nuh[ i ] ][ j ]` equals to the `nuh_layer_id` of a reference layer corresponding to target layer with `nuh_layer_id layer_id_in_nuh[ i ]` and reference layer with direct reference layer index *j*.
- [0445] The variable `RefPicLayerId[ i ]`, corresponds to the `nuh_layer_id` of the *i*-th picture that may be used by the current picture for inter-layer prediction.
- [0446] Referring also to FIG. 51A and FIG. 51B, the SPS syntax includes a `vui_parameters_present_flag` which signals the existence of `vui` (video usability information) information in a `vui_parameters( )` syntax. Referring to FIG. 52A and FIG. 52B, the `vui_parameters()` syntax includes a `tile_boundaries_aligned_flag` that is signalled. The `tile_boundaries_aligned_flag` indicates whether the tiles for coded pictures of one or more layers are aligned with one another. One technique of defining the alignment relationship is the `tile_boundaries_aligned_flag` equal to 1 indicates that, when any two samples of one picture in an access unit belong to one tile, the collocated samples, if any, in another picture in the same access unit belong to one tile, and when any two samples of one picture in an access unit belong to different tiles, the collocated samples in another picture in the same access unit may belong to different tiles. The `tile_boundaries_aligned_flag` equal to 0 indicates that such a restriction may or may not apply. For example, if the `tile_boundaries_aligned_flag` is equal to one then two samples in a single tile of the base layer are similarly two corresponding samples in a single tile of an enhancement layer of the same access unit. For example, if the `tile_boundaries_aligned_flag` is equal to one then two samples in two different tiles of the base layer are similarly two corresponding samples in two different tiles of an enhancement layer of the same access unit.
- [0447] Another technique of defining the alignment relationship is the `tile_boundaries_aligned_flag` equal to 1 indicates that all tile boundaries of the corresponding base layer picture have corresponding tile boundaries in the given enhancement layer and there exist no additional tile boundaries in the enhancement layer. That means, for any two enhancement layer picture samples that lie within the same

enhancement layer tile, the collocated base layer samples may also lie within the same reference layer tile and for any two reference layer picture samples that lie within the same reference layer tile, the collocated enhancement layer samples may also lie within the same enhancement layer tile. `tile_boundaries_aligned_flag` equal to 0 indicates that there is no restriction on the tile configuration between corresponding enhancement layer and the given reference layer.

[0448] When the bitstream has the `tile_boundaries_aligned_flag` equal to one then one or more of a set of constraints may be selected and defined by the system in some manner, so that consistent signaling is maintained across the different layers of the video, which reduces the likelihood of a bitstream that provides an undesirable rendered output. One way of implementing this is detailed below.

[0449] First, if `tile_boundaries_aligned_flag` is equal to 1 and `tiles_fixed_structure_flag` is equal to 1 for one picture in an access unit then `tiles_fixed_structure_flag` may be set to 1 in the `vui_parameters()` of the active SPS of the layer of other picture(s) in the same access unit. In general, the `tiles_fixed_structure_flag` equal to 1 indicates that each picture parameter set that is active in the coded video sequence has the same value of the syntax elements `num_tile_columns_minus1`, `num_tile_rows_minus1`, `uniform_spacing_flag`, `column_width_minus1[i]`, `row_height_minus1[i]` and `loop_filter_across_tiles_enabled_flag`, when present. `tiles_fixed_structure_flag` equal to 0 indicates that tiles syntax elements in different picture parameter sets may or may not have the same value. When the `tiles_fixed_structure_flag` syntax element is not present, it is inferred to be equal to 0. Thus the signalling of `tiles_fixed_structure_flag` equal to 1 is a guarantee to a decoder that each picture in the CVS has the same number of tiles distributed in the same way which might be useful for workload allocation in the case of multi-threaded decoding.

[0450] Second, if `tile_boundaries_aligned_flag` is equal to 1 then `num_tile_columns_minus1` may be equal for each PPS that is active for picture(s) in the same access unit. In general, the `num_tile_columns_minus1` plus 1 specifies the number of tile columns partitioning the picture.

[0451] Third, if `tile_boundaries_aligned_flag` is equal to 1 then `num_tile_rows_minus1` may be equal for each PPS that is active for picture(s) in the same access unit. In general, the `num_tile_rows_minus1` plus 1 specifies the number of tile rows partitioning the picture.

[0452] Fourth, define

$$\text{CtbSizeYRatio} = \text{CtbSizeY} \div \text{CtbSizeYRL}.$$

[0453] If `tile_boundaries_aligned_flag` is equal to 1 then for the corresponding reference

layer(s):

$$\begin{aligned} \text{rowHeight}[0] &= (\text{ScaledRefLayerTopOffset} + \\ & ((\text{CtbSizeYRL} * \text{rowHeightRL}[0]) \div \text{ScaleFactorY})) / \\ & \text{CtbSizeY} \text{ and } \text{colWidth}[0] = (\text{ScaledRefLayerLeftOffset} + \\ & ((\text{CtbSizeYRL} * \text{colWidthRL}[0]) \div \text{ScaleFactorX})) / \\ & \text{CtbSizeY} \end{aligned}$$

$$\begin{aligned} \text{rowHeight}[\text{num_tile_row_minus_1}] &= \\ & (\text{ScaledRefLayerBottomOffset} + ((\text{CtbSizeYRL} * \\ & \text{rowHeightRL}[\text{num_tile_row_minus_1}]) \div \text{ScaleFactorY})) / \\ & \text{CtbSizeY} \text{ and } \text{colWidth}[\text{num_tile_columns_minus1}] = \\ & (\text{ScaledRefLayerRightOffset} + ((\text{CtbSizeYRL} * \\ & \text{colWidthRL}[\text{num_tile_columns_minus1}]) \div \text{ScaleFactorX})) / \\ & \text{CtbSizeY} \end{aligned}$$

$\text{rowHeight}[i] = \text{rowHeightRL}[i] / (\text{ScaleFactorY} * \text{CtbSizeYRatio})$ where i not equal to 0 or
 $\text{num_tile_row_minus_1}$ and ranges from 1 to
 $(\text{num_tile_row_minus_1}-1)$ inclusive.

$\text{colWidth}[j] = \text{colWidthRL}[j] / (\text{ScaleFactorX} * \text{CtbSizeYRatio})$ where j not equal to 0 or
 $\text{num_tile_columns_minus1}$ and ranges from 1 to
 $(\text{num_tile_columns_minus1}-1)$ inclusive.

[0454] Alternatively, If `tile_boundaries_aligned_flag` is equal to 1 then for the corresponding reference layer(s):

$$\begin{aligned} \text{row_height_minus1}[0] &= (\text{ScaledRefLayerTopOffset} + \\ & ((\text{CtbSizeYRL} * \text{rowHeightRL}[0]) \div \text{ScaleFactorY})) / \\ & \text{CtbSizeY} - 1 \text{ and } \text{column_width_minus1}[0] = \\ & (\text{ScaledRefLayerLeftOffset} + ((\text{CtbSizeYRL} * \\ & \text{colWidthRL}[0]) \div \text{ScaleFactorX})) / \text{CtbSizeY} - 1. \end{aligned}$$

$\text{row_height_minus1}[i] = \text{rowHeightRL}[i] /$
 $(\text{ScaleFactorY} * \text{CtbSizeYRatio}) - 1$ where i not equal to 0
or $\text{num_tile_row_minus_1}$ and ranges from 1 to
 $(\text{num_tile_row_minus_1}-1)$ inclusive

$\text{column_width_minus1}[j] = \text{colWidthRL}[j] /$
 $(\text{ScaleFactorX} * \text{CtbSizeYRatio}) - 1$ where j not equal to 0
or $\text{num_tile_columns_minus1}$ and ranges from 1 to
 $(\text{num_tile_columns_minus1}-1)$ inclusive.

[0455] Alternatively, If `tile_boundaries_aligned_flag` is equal to 1 then for the corresponding reference layer(s):

$$\begin{aligned} \text{row_height_minus1}[0] &= (\text{ScaledRefLayerTopOffset} + \\ & ((\text{CtbSizeYRL} * (\text{row_height_minus1_RL}[0] + 1)) \div \\ & \text{ScaleFactorY})) / \text{CtbSizeY} - 1 \text{ and} \\ \text{column_width_minus1}[0] &= (\text{ScaledRefLayerLeftOffset} + \\ & ((\text{CtbSizeYRL} * (\text{column_width_minus1_RL}[0] + 1)) \div \\ & \text{ScaleFactorX})) / \text{CtbSizeY} - 1. \end{aligned}$$

$$\begin{aligned} \text{row_height_minus1}[i] &= (\text{row_height_minus1_RL}[i] + \\ & 1) / (\text{ScaleFactorY} * \text{CtbSizeYRatio}) - 1 \text{ where } i \text{ not equal to} \\ & 0 \text{ or } \text{num_tile_row_minus_1} \text{ and ranges from } 1 \text{ to} \\ & (\text{num_tile_row_minus_1} - 1) \text{ inclusive} \end{aligned}$$

$$\begin{aligned} \text{column_width_minus1}[j] &= \\ & (\text{column_width_minus1_RL}[j] + 1) / (\text{ScaleFactorX} * \\ & \text{CtbSizeYRatio}) - 1 \text{ where } j \text{ not equal to } 0 \text{ or} \\ & \text{num_tile_columns_minus1} \text{ and ranges from } 1 \text{ to} \\ & (\text{num_tile_columns_minus1} - 1) \text{ inclusive} \end{aligned}$$

[0456] Alternatively, If `tile_boundaries_aligned_flag` is equal to 1 then for each reference layer with layer identifier `RefLayerId[ nuh_layer_id ][ k ]` for `k` ranging from 0 to `NumDirectRefLayer[ nuh_layer_id ] - 1`:

$$\begin{aligned} \text{row_height_minus1}[0] &\text{ shall be equal to} \\ & (\text{ScaledRefLayerTopOffset} + ((\text{CtbSizeYRL} * \\ & (\text{RowHeightMinus1RI}[0] + 1)) \div \text{ScaleFactorY})) / \text{CtbSizeY} \\ &- 1 \text{ and } \text{column_width_minus1}[0] \text{ shall be equal to} \\ & (\text{ScaledRefLayerLeftOffset} + ((\text{CtbSizeYRL} * \\ & (\text{ColumnWidthMinus1RI}[0] + 1)) \div \text{ScaleFactorX})) / \\ &\text{CtbSizeY} - 1. \end{aligned}$$

$$\begin{aligned} \text{row_height_minus1}[i] &\text{ shall be equal to} \\ & (\text{RowHeightMinus1RI}[i] + 1) / (\text{ScaleFactorY} * \\ &\text{CtbSizeYRatio}) - 1 \text{ where for each } i \text{ from } 1 \text{ to} \\ & (\text{num_tile_row_minus_1} - 1) \text{ inclusive} \end{aligned}$$

$$\begin{aligned} \text{column_width_minus1}[j] &\text{ shall be equal to} \\ & (\text{ColumnWidthMinus1RI}[j] + 1) / (\text{ScaleFactorX} * \\ &\text{CtbSizeYRatio}) - 1 \text{ for each } i \text{ from } 1 \text{ to} \\ & (\text{num_tile_columns_minus1} - 1) \text{ inclusive} \end{aligned}$$

[0457] Alternatively, If `tile_boundaries_aligned_flag` is equal to 1 then for each reference

layer with layer identifier $\text{RefLayerId}[\text{currLayerId}][k]$ for k ranging from 0 to $\text{NumDirectRefLayer}[\text{currLayerId}] - 1$, where currLayerId is the nuh_layer_id of the current picture:

$\text{row_height_minus1}[0]$ shall be equal to

$$\left(\text{ScaledRefLayerTopOffset} + \left(\left(\text{CtbSizeYRL} * (\text{RowHeightMinus1Rl}[0] + 1) \right) \div \text{ScaleFactorY} \right) \right) / \text{CtbSizeY} - 1$$
and $\text{column_width_minus1}[0]$ shall be equal to

$$\left(\text{ScaledRefLayerLeftOffset} + \left(\left(\text{CtbSizeYRL} * (\text{ColumnWidthMinus1Rl}[0] + 1) \right) \div \text{ScaleFactorX} \right) \right) / \text{CtbSizeY} - 1.$$

$\text{row_height_minus1}[i]$ shall be equal to

$$(\text{RowHeightMinus1Rl}[i] + 1) / (\text{ScaleFactorY} * \text{CtbSizeYRatio}) - 1$$
where for each i from 1 to $(\text{num_tile_row_minus1}-1)$ inclusive
 $\text{column_width_minus1}[j]$ shall be equal to

$$(\text{ColumnWidthMinus1Rl}[j] + 1) / (\text{ScaleFactorX} * \text{CtbSizeYRatio}) - 1$$
for each j from 1 to $(\text{num_tile_columns_minus1}-1)$ inclusive

[0458] The values of variables $\text{ScaledRefLayerLeftOffset}$, ScaleFactorX , $\text{ScaledRefLayerTopOffset}$, ScaleFactorY are derived using information from picture with nuh_layer_id equal to $\text{RefLayerId}[\text{currLayerId}][k]$ and index $\text{DirectRefLayerIdx}[\text{currLayerId}][\text{RefLayerId}[\text{currLayerId}][k]]$ as input.

[0459] In one embodiment CtbSizeYRatio may be constrained as follows

$\text{CtbSizeYRatio} \in \{8, 4, 2, 1, 1/2, 1/4, 1/8\}.$

[0460] Moreover, the row and column calculations may be modified, as desired, and also may be modified based upon the particular characteristics of the reference layer and the current layer (e.g., may have a different number, size of tiles, etc.).

[0461] Fifth, if the $\text{tile_boundaries_aligned_flag}$ is equal to 1 and then $\text{uniform_spacing_flag}$ may be equal to $\text{uniform_spacing_flag}$ for each PPS that is active for pictures in the same access unit.

[0462] In some cases it is desirable that among the different layers (e.g., base layer and/or enhancement layers) the tile only uses sample prediction (e.g., up scaling) and motion mapping (e.g., motion vectors, mode information, motion field) from co-located tiles in another layer, so that consistent signaling is maintained across the different layers of the video, which reduces the likelihood of a bitstream that provides an undesirable rendered output. It also allows parallel decoding of tiles across layers without having to

wait for entire picture belonging to a reference layer to be decoded. One way of implementing this is detailed below.

[0463] First, in one embodiment, this co-located tiles restriction may be based on the `tile_boundaries_aligned_flag` or on another flag such as `inter_layer_pred_tile_dec_constraint_flag` equal to 1 indicates that within the CVS that CTBs belonging to i-th tile do not use either the sample value or the motion information from CTBs that belong to any tile besides i-th tile within the reference layer, for i ranging from 0 to $(\text{num_tile_row_minus_1}+1)*(\text{num_tile_columns_minus_1}+1)-1$, inclusive. The `inter_layer_pred_tile_dec_constraint_flag` equal to 0 indicates that within the CVS that CTBs belonging to i-th tile may use either the sample value or the motion information from CTBs that belong to any tile within the reference layer, for i ranging from 0 to $(\text{num_tile_row_minus_1}+1)*(\text{num_tile_columns_minus_1}+1)-1$, inclusive. When `tile_boundaries_aligned_flag` equal to 0 then `inter_layer_pred_tile_dec_constraint_flag` may be 0. When `inter_layer_pred_tile_dec_constraint_flag` is not present then it is inferred to be equal to 0. In another embodiment `inter_layer_pred_tile_dec_constraint_flag` specifies whether inter-layer prediction at tile boundaries is constrained in the CVS.

- If `inter_layer_pred_tile_dec_constraint_flag` is equal to 1, the following applies:
 - When the decoding process of a block of a picture uses inter-layer prediction, the coded picture shall be constrained such that the inter-layer prediction only depends on data elements of the inter-layer reference picture that can be derived from the collocated reference layer tile of the block.
 - The syntax element `loop_filter_across_tiles_enabled_flag` of all inter-layer reference pictures used by the current picture shall be equal to 0.
- Otherwise, (`inter_layer_pred_tile_dec_constraint_flag` is equal to 0), no constraints are signalled by this flag.

[0464] When not present the `inter_layer_pred_tile_dec_constraint_flag` is inferred to be equal to 0.

[0465] In some embodiments `inter_layer_pred_tile_dec_constraint_flag` may be called `inter_layer_pred_tile_constraint_flag`.

[0466] First, in another embodiment, the constraints defined by the semantics of `inter_layer_pred_tile_dec_constraint_flag` may be indicated using past data signalled in the bistream e.g. `tile_boundaries_aligned_flag`, profile, level. This may be implemented by the loop filter not being permitted to operate across tile boundaries but permitted to operate within tile boundaries. In particular, If `inter_layer_pred_tile_dec_constraint_flag` is equal to 1 then `loop_filter_across_tiles_enabled_flag` may be 0 for active PPS of each reference layer of each picture in the same access unit. In particular, if `inter_layer_pred_tile_dec_constraint_flag` is equal to 1 then

pps_loop_filter_across_slices_enabled_flag may be 0 for active PPS of each reference layer of each picture in the same access unit.

- [0467] In yet another alternative embodiment, if the inter_layer_pred_tile_dec_constraint_flag is equal to 1 then reference layer sample values affected by loop filtering (SAO or deblocking) shall not be used (a) in the inter prediction decoding process (e.g. for SNR scalability) or (b) within the inter-layer up-sampling process (e.g. when spatial scalability factor is not 1).
- [0468] In yet another embodiment, if the inter_layer_pred_tile_dec_constraint_flag is equal to 1 then motion mapping process between the current layer and reference layer is modified so that the decoding process for a tile does not use motion information from a non-located tile in the reference layer. An example modification is listed as pseudo-code below:

```

If ( xP >= tilePredPreventOffset && yP >= tilePredPreventOffset ) {
    CtbAddrInRs = ( ( yP - tilePredPreventOffset ) / CtbSizeY ) *
    PicWidthInCtbsY + ( ( xP - tilePredPreventOffset ) / CtbSizeY )
    TileIdx = TileIdx[ CtbAddrRsToTs[ CtbAddrInRs ] ]
    CtbAddrInRsRL = ( yRL / CtbSizeYRL ) * PicWidthInCtbsYRL + ( xRL /
    CtbSizeYRL )

    TileIdxRL = TileIdxRL[ CtbAddrRsToTsRL[ CtbAddrInRsRL ] ]
}

If ( xRL < 0 ) || ( xRL >= RefLayerPicWidthInSamplesL ) || ( yRL < 0 ) || ( yRL >=
RefLayerPicHeightInSamplesL ) || ( inter_layer_pred_tile_dec_constraint_flag
&& ( xP >= 8 && yP >= 8 ) && TileIdxRL != TileIdx ) , predMode[ xP ][ yP ] is set to
MODE_INTRA

```

- [0469] The variables xP and yP represent luma sample location under consideration within the current layer picture. The variables xRL and yRL represent the corresponding luma sample location within the reference layer picture. The variables predMode[xP][yP] corresponds to the prediction mode of the resampled picture for luma location (xP, yP). The variable tilePredPreventOffset may be derived based on past data signalled within the bitstream. In an example, tilePredPreventOffset is set to the value 8. MODE_INTRA corresponds to intra prediction mode.

- [0470] When the bitstream has the tile_boundaries_aligned_flag equal to one then one or more of a set of constraints of an enhancement layer may be selected and defined by the system by reference to the base layer, so that consistent signaling is maintained across the different layers of the video, which reduces the likelihood of a bitstream that

provides an undesirable rendered output.

- [0471] This selection of desirable constraints to ensure that consistent signaling is maintained across the different enhancement layers, it is desirable not to expressly signal `num_tile_columns_minus1`, `num_tile_rows_minus1`, `uniform_spacing_flag`, `column_width_minus1[i]`, and/or `row_height_minus1[i]` syntax elements when `nuh_layer_id > 0` and `tile_boundaries_aligned_flag` is equal to 1, so that such data may be copied and inferred, as needed.
- [0472] Referring to FIG. 53, a picture parameter set (e.g., `pic_parameter_set_rbsp()`) may be modified to consider whether it is an enhancement layer and the setting of the `tile_boundaries_aligned_flag` to determine whether to use other signaled syntax from the base layer, namely, "`if(!nuh_layer_id>0 && tile_boundaries_aligned_flag)`" and its associated syntax. This may be expressed, for example as follows, when `nuh_layer_id > 0 && tile_boundaries_aligned_flag` for the SPS corresponding to `pps_seq_parameter_set_id` is 1, `num_tile_columns_minus1`, `num_tile_rows_minus1`, `uniform_spacing_flag`, `column_width_minus1[i]`, `row_height_minus1[i]` are not signaled. The corresponding values from the active PPS of reference layer are used for inference of the values of these PPS syntax elements for the current layer. They may be derived as follows:
- [0473] First, the values for `num_tile_columns_minus1`, `num_tile_rows_minus1`, and/or `uniform_spacing_flag` for the current layer PPS are respectively set equal to the value for `num_tile_columns_minus1`, `num_tile_rows_minus1`, and/or `uniform_spacing_flag` syntax element from the active PPS of the layer with `nuh_layer_id` equal to 0.
- [0474] Second,
- the value of `column_width_minus1[ 0 ]` is set equal to the value

$$(\text{ScaledRefLayerLeftOffset} + (\text{CtbSizeYRL} * (\text{column_width_minus1_RL}[0] + 1)) \div \text{ScaleFactorX}) / \text{CtbSizeY} - 1$$
for syntax element from the active PPS of the layer with `nuh_layer_id` equal to 0.
- [0475] Third, the values of `column_width_minus1[ i ]` for ($i=1, \dots, \text{num_tile_columns_minus1}-1$) for the current layer PPS are respectively set equal to the value $(\text{column_width_minus1_RL}[i] + 1) / (\text{ScaleFactorX} * \text{CtbSizeYRatio}) - 1$ for syntax element from the active PPS of the layer with `nuh_layer_id` equal to 0.
- [0476] Fourth,
- the value of `row_height_minus1[ 0 ]` is set equal to the value

$$(\text{ScaledRefLayerTopOffset} + (\text{CtbSizeYRL} * (\text{row_height_minus1_RL}[0] + 1)) \div \text{ScaleFactorY}) / \text{CtbSizeY} - 1$$
for syntax element from the active PPS of the layer with `nuh_layer_id` equal to 0.

- [0477] Fifth, the values of `row_height_minus1[ i ]` for $(i=1, \dots, \text{num_tile_rows_minus1}-1)$ for the current layer PPS are respectively set equal to the value $(\text{row_height_minus1_RL}[i] + 1) / (\text{ScaleFactorY} * \text{CtbSizeYRatio}) - 1$ for syntax element from the active PPS of the layer with `nuh_layer_id` equal to 0.
- [0478] For each of these syntax elements first through fifth, all constraints, if any, that apply to the value of the corresponding reference layer PPS syntax element also apply. In some embodiments reference layer may be base layer. The active PPS maybe PPS of layer with `nuh_layer_id` equal to 0 in the access unit of the current picture. In some embodiments instead of setting values equal to those from the active PPS of the layer with `nuh_layer_id` equal to 0, the values may instead be set equal to those from the active PPS of a different referenc layer, i.e. layer with `nuh_layer_id` different than 0.
- [0479] In yet another embodiment, the tile syntax elements may be derived as follows:
- [0480] First, the values for `num_tile_columns_minus1`, `num_tile_rows_minus1`, and/or `uniform_spacing_flag` for the current layer PPS are respectively set equal to the value for `num_tile_columns_minus1`, `num_tile_rows_minus1`, and/or `uniform_spacing_flag` syntax element from the active PPS of the layer with `nuh_layer_id` equal to 0.
- [0481] Second, a variable `dRIIdx0` is set equal to `DirectRefLayerIdx[ currLayerId ][ RefLayerId[currLayerId][0] ]` where `currLayerId` is the `nuh_layer_id` of the current picture.
- [0482] Third, the values of `ScaledRefLayerLeftOffset`, `ScaleFactorX`, `ScaledRefLayerTopOffset`, `ScaleFactorY` are derived using information from picture with `nuh_layer_id` equal to `RefLayerId[currLayerId][0]` and index `dRIIdx0` as input.
- [0483] Fourth, the list `ColumnWidthMinus1dRI0[i]` is respectively set equal to `column_width_minus1[i]` for each $i=0, \dots, \text{num_tile_columns_minus1}-1$ and the list `RowHeightMinus1dRI0[i]` is respectively set equal to `row_height_minus1[i]` for each $i=0, \dots, \text{num_tile_rows_minus1}-1$ values from active PPS of layer with `nuh_layer_id` equal to `RefLayerId[currLayerId][0]`.
- [0484] Fifth,
- the value of `column_width_minus1[ 0 ]` is set equal to the value $(\text{ScaledRefLayerLeftOffset} + (\text{CtbSizeYRL} * (\text{ColumnWidthMinus1dRI0}[0] + 1)) \div \text{ScaleFactorX}) / \text{CtbSizeY} - 1$ for syntax element from the active PPS of the layer with `nuh_layer_id` equal to `RefLayerId[currLayerId][0]`.
- [0485] Sixth, the values of `column_width_minus1[ i ]` for $(i=1, \dots, \text{num_tile_columns_minus1}-1)$ for the current layer PPS are respectively set equal to the value $(\text{ColumnWidthMinus1dRI0}[i] + 1) / (\text{ScaleFactorX} * \text{CtbSizeYRatio}) - 1$ for syntax element from the active PPS of the layer with `nuh_layer_id` equal to `RefLayerId[currLayerId][0]`.

[0486] Seventh,

the value of $\text{row_height_minus1}[0]$ is set equal to the value
 $(\text{ScaledRefLayerTopOffset} + (\text{CtbSizeYRL} * (\text{RowHeightMinus1dRI0}[0] + 1))) \div \text{ScaleFactorY} / \text{CtbSizeY} - 1$ for syntax element from the active PPS of the layer with nuh_layer_id equal to $\text{RefLayerId}[\text{currLayerId}][0]$.

[0487] Eighth, the values of $\text{row_height_minus1}[i]$ for $(i=1, \dots, \text{num_tile_rows_minus1}-1)$ for the current layer PPS are respectively set equal to the value
 $(\text{RowHeightMinus1dRI0}[i] + 1) / (\text{ScaleFactorY} * \text{CtbSizeYRatio}) - 1$ for syntax element from the active PPS of the layer with nuh_layer_id equal to $\text{RefLayerId}[\text{currLayerId}][0]$.

[0488] In yet another embodiment, the tile syntax elements may be derived as follows:

[0489] First, the values for $\text{num_tile_columns_minus1}$, $\text{num_tile_rows_minus1}$, and/or $\text{uniform_spacing_flag}$ for the current layer PPS are respectively set equal to the value for $\text{num_tile_columns_minus1}$, $\text{num_tile_rows_minus1}$, and/or $\text{uniform_spacing_flag}$ syntax element from the active PPS of the layer with nuh_layer_id equal to 0.

[0490] Second, a variable dRIIdx1 is set equal to $\text{DirectRefLayerIdx}[\text{currLayerId}][\text{RefLayerId}[\text{currLayerId}][0]]$ where currLayerId is the nuh_layer_id of the current picture.

[0491] Third, the values of $\text{ScaledRefLayerLeftOffset}$, ScaleFactorX , $\text{ScaledRefLayerTopOffset}$, ScaleFactorY are derived using information from a reference layer picture, say rPic1 , in the DPB within the same access unit as the current picture and with nuh_layer_id equal to rPic1 . and index dRIIdx1 as input.

[0492] Fourth, the list $\text{ColumnWidthMinus1dRI1}[i]$ is respectively set equal to $\text{column_width_minus1}[i]$ for each $i=0, \dots, \text{num_tile_columns_minus1}-1$ and the list $\text{RowHeightMinus1dRI1}[i]$ is respectively set equal to $\text{row_height_minus1}[i]$ for each $i=0, \dots, \text{num_tile_rows_minus1}-1$ values from active PPS of rPic1 .

[0493] Fifth,

the value of $\text{column_width_minus1}[0]$ is set equal to the value
 $(\text{ScaledRefLayerLeftOffset} + (\text{CtbSizeYRL} * (\text{ColumnWidthMinus1dRI1}[0] + 1))) \div \text{ScaleFactorX} / \text{CtbSizeY} - 1$ for syntax element from the active PPS of rPic1 .

[0494] Sixth, the values of $\text{column_width_minus1}[i]$ for $(i=1, \dots, \text{num_tile_columns_minus1}-1)$ for the current layer PPS are respectively set equal to the value
 $(\text{ColumnWidthMinus1dRI1}[i] + 1) / (\text{ScaleFactorX} * \text{CtbSizeYRatio}) - 1$ for syntax element from the active PPS of rPic1 .

[0495] Seventh,

the value of `row_height_minus1[ 0 ]` is set equal to the value

$$(\text{ScaledRefLayerTopOffset} + (\text{CtbSizeYRL} * (\text{RowHeightMinus1dRl1}[0] + 1))) \div \text{ScaleFactorY}) / \text{CtbSizeY} - 1$$
 for syntax element from the active PPS of `rlPic1`.

[0496] Eighth, the values of `row_height_minus1[ i ]` for ($i=1, \dots, \text{num_tile_rows_minus1}-1$) for the current layer PPS are respectively set equal to the value ($\text{RowHeightMinus1dRl1}[i] + 1$) / ($\text{ScaleFactorY} * \text{CtbSizeYRatio}$) - 1 for syntax element from the active PPS of `rlPic1`.

[0497] In yet another embodiment, the tile syntax elements may be derived as follows:

[0498] First, the values for `num_tile_columns_minus1`, `num_tile_rows_minus1`, and/or `uniform_spacing_flag` for the current layer PPS are respectively set equal to the value for `num_tile_columns_minus1`, `num_tile_rows_minus1`, and/or `uniform_spacing_flag` syntax element from the active PPS of the layer with `nuh_layer_id` equal to 0.

[0499] Second, a variable `dRIIdx2` is set equal to `DirectRefLayerIdx[ currLayerId ][ RlPicNuhLid ]` where `currLayerId` is the `nuh_layer_id` of the current picture and `RlPicNuhLid` is `nuh_layer_id` of a reference layer picture for the current picture.

[0500] Third, the values of `ScaledRefLayerLeftOffset`, `ScaleFactorX`, `ScaledRefLayerTopOffset`, `ScaleFactorY` are derived using information from picture with `nuh_layer_id` equal to `RlPicNuhLid` and index `dRIIdx2` as input.

[0501] Fourth, the list `ColumnWidthMinus1dRl2[i]` is respectively set equal to `column_width_minus1[i]` for each $i=0, \dots, \text{num_tile_columns_minus1}-1$ and the list `RowHeightMinus1dRl2[i]` is respectively set equal to `row_height_minus1[i]` for each $i=0, \dots, \text{num_tile_rows_minus1}-1$ values from active PPS of layer with `nuh_layer_id` equal to `RlPicNuhLid`.

[0502] Fifth,

the value of `column_width_minus1[ 0 ]` is set equal to the value

$$(\text{ScaledRefLayerLeftOffset} + (\text{CtbSizeYRL} * (\text{ColumnWidthMinus1dRl2}[0] + 1))) \div \text{ScaleFactorX}) / \text{CtbSizeY} - 1$$
 for syntax element from the active PPS of the layer with `nuh_layer_id` equal to `RlPicNuhLid`.

[0503] Sixth, the values of `column_width_minus1[ i ]` for ($i=1, \dots, \text{num_tile_columns_minus1}-1$) for the current layer PPS are respectively set equal to the value $(\text{ColumnWidthMinus1dRl2}[i] + 1) / (\text{ScaleFactorX} * \text{CtbSizeYRatio}) - 1$ for syntax element from the active PPS of the layer with `nuh_layer_id` equal to `RlPicNuhLid`.

[0504] Seventh,

the value of row_height_minus1[0] is set equal to the value

$$(\text{ScaledRefLayerTopOffset} + (\text{CtbSizeYRL} * (\text{RowHeightMinus1dRI2}[0] + 1)))$$

$$\div \text{ScaleFactorY}) / \text{CtbSizeY} - 1$$
 for syntax element from the active PPS of the layer with nuh_layer_id equal to RIPicNuhLId.

[0505] Eighth, the values of row_height_minus1[i] for (i=1,..., num_tile_rows_minus1-1) for the current layer PPS are respectively set equal to the value ($\text{RowHeightMinus1dRI2}[i] + 1) / (\text{ScaleFactorY} * \text{CtbSizeYRatio}) - 1$ for syntax element from the active PPS of the layer with nuh_layer_id equal to RIPicNuhLId.

[0506] In yet another embodiment, the tile syntax elements may be derived as follows:

The values for num_tile_columns_minus1, num_tile_rows_minus1, uniform_spacing_flag for the current layer PPS are respectively set equal to the value for num_tile_columns_minus1 and num_tile_rows_minus1, uniform_spacing_flag syntax element from the active PPS of the layer with nuh_layer_id equal to 0.

[0507] The values for column_width_minus1[i], row_height_minus1[i] are derived as follows:

ScaledRefLayerLeftOffset, ScaleFactorX, ScaledRefLayerTopOffset, ScaleFactorY are calculated using information from picture with nuh_layer_id equal to RefLayerId[currLayerId][0] and index DirectRefLayerIdx[currLayerId][RefLayerId[currLayerId][0]] as input. Where currLayerId is the nuh_layer_id of the current picture. ColumnWidthMinus1RI3[i] is respectively set equal to column_width_minus1[i] for each $i=0, \dots, \text{num_tile_columns_minus1}-1$ and RowHeightMinus1RI3[i] is respectively set equal to row_height_minus1[i] for each $i=0, \dots, \text{num_tile_rows_minus1}-1$ values from active PPS of layer with nuh_layer_id equal to RefLayerId[currLayerId][0]. CtbSizeYRatio is set equal to $\text{CtbSizeY} \div \text{CtbSizeYRL}$ where CtbSizeYRL is the array size of each luma coding tree block in both width and height for the layer with nuh_layer_id equal to RefLayerId[currLayerId][0].

The value of column_width_minus1[0] is set equal to the value $(\text{ScaledRefLayerLeftOffset} + (\text{CtbSizeYRL} * (\text{ColumnWidthMinus1RI3}[0] + 1)) \div \text{ScaleFactorX}) / \text{CtbSizeY} - 1$.

The values of column_width_minus1[i] for $(i=1, \dots, \text{num_tile_columns_minus1}-1)$ are respectively set equal to the value $(\text{ColumnWidthMinus1RI3}[i] + 1) / (\text{ScaleFactorX} * \text{CtbSizeYRatio}) - 1$.

The value of row_height_minus1[0] is set equal to the value $(\text{ScaledRefLayerTopOffset} + (\text{CtbSizeYRL} * (\text{RowHeightMinus1RI3}[0] + 1)) \div \text{ScaleFactorY}) / \text{CtbSizeY} - 1$.

The values of row_height_minus1[i] for $(i=1, \dots, \text{num_tile_rows_minus1}-1)$ are respectively set equal to the value $(\text{RowHeightMinus1RI3}[i] + 1) / (\text{ScaleFactorY} * \text{CtbSizeYRatio}) - 1$.

[0508] In an additional embodiment, the values for loop_filter_across_tiles_enabled_flag and/or pps_loop_filter_across_slices_enabled_flag for the current layer PPS are respectively set equal to the value for loop_filter_across_tiles_enabled_flag and/or pps_loop_filter_across_slices_enabled_flag syntax element from the active PPS of the layer with nuh_layer_id equal to 0. In this case those syntax elements are also not signaled when nuh_layer_id > 0 && tile_boundaries_aligned_flag for the SPS corresponding to pps_seq_parameter_set_id is 1.

[0509] The tile_boundaries_aligned_flag is a flag that is applicable to all layers within an access unit. The tile_boundaries_aligned_flag may be included within the SPS syntax as being part of the vui_parameters syntax, but the SPS syntax is included within each of the layers and thus the tile_boundaries_aligned_flag is signaled multiple times for the same access unit. To reduce the bandwidth of the system, together with simpli-

fication of the signaling for the `tile_boundaries_aligned_flag`, it is desirable to include the `tile_boundaries_aligned_flag` within the VPS syntax which is applicable to all layers of the access unit rather than the SPS syntax which is included for each layer of the access unit.

- [0510] Referring to FIG. 54A and FIG. 54B, an exemplary VPS syntax includes a `vps_extension_flag` and if flagged signals a `vps_extension()`. Referring to FIG. 55, an exemplary `vps_extension()` may include the `tile_boundaries_aligned_vps_flag`. The `tile_boundaries_aligned_vps_flag` may be defined, for example, as equal to 1 indicates that, when any two samples of one picture in an access unit belong to one tile, the collocated samples, if any, in another picture in the same access unit belong to one tile, and when any two samples of one picture in an access unit belong to different tiles, the collocated samples in another picture in the same access unit may belong to different tiles. `tile_boundaries_aligned_flag` equal to 0 indicates that such a restriction may or may not apply.
- [0511] In another embodiment, the `tile_boundaries_aligned_flag` may be signaled within the vps extension syntax as being applicable to particular ones of the extension layers, which is applicable to the selected layers of the access unit rather than the SPS syntax which is included for each layer of the access unit.
- [0512] Referring to FIG. 56, thus for each of the enhancement layers (e.g., $i=1; i \leq \text{vps_max_layers_minus1}; i++$) and for each syntax within each of the enhancement layers (e.g., $j=0; j < i; j++$) the syntax may signal how the tile is aligned (e.g., `reflayer_tile_boundaries_aligned_flag[ i ][ j ]`).
- [0513] For example, the `reflayer_tile_boundaries_aligned_flag[ i ][ j ]` may be defined as, equal to 1 indicates that, when any two samples of a picture belonging to the layer i , belong to one tile, the collocated samples, if any, in another picture belonging to the layer j belong to one tile, and when any two samples of a picture belonging to the layer i , belong to different tiles, the collocated samples in another picture belonging to the layer j may belong to different tiles. `reflayer_tile_boundaries_aligned_vps_flag[ i ][ j ]` equal to 0 indicates that such a restriction may or may not apply for pictures belonging to layer i and layer j . When `reflayer_tile_boundaries_aligned_vps_flag[ i ][ j ]` is not present it is inferred to be equal to 0.
- [0514] For example, the `reflayer_tile_boundaries_aligned_flag[ i ][ j ]` may be defined as, equal to 1 indicates that, when any two samples of a picture in an access unit belonging to the layer i , belong to one tile, the collocated samples, if any, in another picture in the same access unit belonging to the layer j belong to one tile, and when any two samples of a picture belonging to the layer i , belong to different tiles, the collocated samples in another picture belonging to the layer j may belong to different tiles. The `reflayer_tile_boundaries_aligned_vps_flag[ i ][ j ]` equal to 0 indicates that such a re-

striction may or may not apply for pictures belonging to layer i and layer j . When `reflayer_tile_boundaries_aligned_vps_flag[ i ][ j ]` is not present it is inferred to be equal to 0.

[0515] For example, the `reflayer_tile_boundaries_aligned_flag[ i ][ j ]` may be defined as, equal to 1 indicates that, when any two samples of a picture belonging to the layer i belong to one tile, the collocated samples, if any, in another picture belonging to the layer j which may be a direct reference layer for layer i , belong to one tile, and when any two samples of a picture belonging to the layer i , belong to different tiles, the collocated samples in another picture belonging to the layer j may belong to different tiles. The `reflayer_tile_boundaries_aligned_vps_flag[ i ][ j ]` equal to 0 indicates that such a restriction may or may not apply for pictures belonging to layer i and layer j . When `reflayer_tile_boundaries_aligned_vps_flag[ i ][ j ]` is not present it is inferred to be equal to 0.

[0516] For example, the `reflayer_tile_boundaries_aligned_flag[ i ][ j ]` may be defined as, equal to 1 indicates that, when any two samples of a picture in an access unit belonging to the layer i , belong to one tile, the collocated samples, if any, in another picture in the same access unit belonging to the layer j which may be a direct reference layer for layer i , belong to one tile, and when any two samples of a picture belonging to the layer i , belong to different tiles, the collocated samples in another picture belonging to the layer j may belong to different tiles. `reflayer_tile_boundaries_aligned_vps_flag[ i ][ j ]` equal to 0 indicates that such a restriction may or may not apply for pictures belonging to layer i and layer j . When `reflayer_tile_boundaries_aligned_vps_flag[ i ][ j ]` is not present it is inferred to be equal to 0.

[0517] In another embodiment, the `tile_boundaries_aligned_flag` may be signaled within the vps extension syntax as being applicable to particular ones of the extension layers, which is applicable to the selected layers of the access unit based upon their dependency rather than the SPS syntax which is included for each layer of the access unit.

[0518] Referring to FIG. 57, thus for each of the enhancement layers (e.g., $i=1$; $i<vps_max_layers_minus1$; $i++$) and for each syntax within each of the enhancement layers (e.g., $j=0$; $j<i$; $j++$) for which they depend (e.g., `direct_dependency_flag[ i ][ j ]` equal to 1) the syntax may signal how the tile is aligned (e.g., `reflayer_tile_boundaries_aligned_flag[ i ][ j ]`).

[0519] Referring to FIG. 58, a modified structure with similar functionality to FIG. 56, is illustrated.

[0520] Referring to FIG. 59, a further modified structure with similar functionality to FIG. 57 is illustrated. In some embodiments in FIG. 57 and FIG. 59 `reflayer_tile_boundaries_aligned_flag[i][j]` for the case when

direct_dependency_flag[i][j] is 0 is inferred to be equal to 0.

[0521] The tile boundaries alignment signalling in VPS as shown in FIG. 55, FIG. 56, FIG. 57, FIG. 58, or FIG. 59 can be sent in addition to the current signalling of tile_boundaries_aligned_flag in SPS in FIG. 52B. In this case the information in SPS can update / over-ride the information signalled in VPS.

[0522] In some embodiments instead of signaling reflower_tile_boundaries_aligned_flag[i][j] in VPS it may be signaled in SPS. In one embodiment this signaling may be inside vui_parameters. FIG. 60 shows a syntax variant for this which is similar to syntax variant in FIG. 56 but is in SPS in vui_parameters instead. In FIG. 60 reflower_tile_boundaries_aligned_flag[i][j] has semantics similar to reflower_tile_boundaries_aligned_flag[i][j] of FIG. 56 in this case.

[0523] FIG. 61 shows a syntax variant for this which is similar to syntax variant in FIG. 57 but is in SPS in vui_parameters instead. In FIG. 61 reflower_tile_boundaries_aligned_flag[i][j] has semantics similar to reflower_tile_boundaries_aligned_flag[i][j] of FIG. 57. In this case, FIG. 61 shows a syntax variant where ref_layer_tile_boundaries_aligned_flag[j] is signaled in SPS in vui_parameters instead. ref_layer_tile_boundaries_aligned_vps_flag[j] equal to 1 indicates that, when any two samples of a picture with nuh_layer_id, belong to one tile, the collocated samples, if any, in another picture belonging to layer with nuh_layer_id equal to RefLayerId[nuh_layer_id][j] belong to one tile, and when any two samples of a picture with nuh_layer_id, belong to different tiles, the collocated samples in another picture belonging to the layer with nuh_layer_id equal to RefLayerId[nuh_layer_id][j] shall belong to different tiles. ref_layer_tile_boundaries_aligned_vps_flag[j] equal to 0 indicates that such a restriction may or may not apply for pictures with nuh_layer_id. When ref_layer_tile_boundaries_aligned_vps_flag[j] is not present it is inferred to be equal to 0.

[0524] Further syntax variants are shown in FIG. 62 and FIG. 63 for carrying reflower_tile_boundaries_aligned_flag[i][j]. In yet another embodiment the syntax variants in FIG. 62 and / or FIG. 63 may be carried anywhere in the normative part of the bitstream such as picture parameter set, slice segment header, any other parameter set, etc. or in non-normative part of the bitstream.

[0525] In another embodiment one or more of the syntax elements may be signaled using a known fixed number of bits instead of u(v) instead of ue(v). For example they could be signaled using u(8) or u(16) or u(32) or u(64), etc.

[0526] In another embodiment one or more of these syntax element could be signaled with ue(v) or some other coding scheme instead of fixed number of bits such as u(v) coding.

[0527] In another embodiment the names of various syntax elements and their semantics may be altered by adding a plus1 or plus2 or by subtracting a minus1 or a minus2

compared to the described syntax and semantics.

[0528] In yet another embodiment various syntax elements may be signaled per picture anywhere in the bitstream. For example they may be signaled in slice segment header, pps/ sps/ vps/ or any other parameter set or other normative part of the bitstream.

[0529] The term "computer-readable medium" refers to any available medium that can be accessed by a computer or a processor. The term "computer-readable medium," as used herein, may denote a computer- and/or processor-readable medium that is non-transitory and tangible. By way of example, and not limitation, a computer-readable or processor-readable medium may comprise RAM, ROM, EEPROM, CD-ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other medium that can be used to carry or store desired program code in the form of instructions or data structures and that can be accessed by a computer or processor. Disk and disc, as used herein, includes compact disc (CD), laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray (registered trademark) disc where disks usually reproduce data magnetically, while discs reproduce data optically with lasers.

[0530] It should be noted that one or more of the methods described herein may be implemented in and/or performed using hardware. For example, one or more of the methods or approaches described herein may be implemented in and/or realized using a chipset, an ASIC, a large-scale integrated circuit (LSI) or integrated circuit, etc.

[0531] Each of the methods disclosed herein comprises one or more steps or actions for achieving the described method. The method steps and/or actions may be interchanged with one another and/or combined into a single step without departing from the scope of the claims. In other words, unless a specific order of steps or actions is required for proper operation of the method that is being described, the order and/or use of specific steps and/or actions may be modified without departing from the scope of the claims.

[0532] It is to be understood that the claims are not limited to the precise configuration and components illustrated above. Various modifications, changes and variations may be made in the arrangement, operation and details of the systems, methods, and apparatus described herein without departing from the scope of the claims.

Claims

- [Claim 1] A method for decoding video comprising:
- (a) decoding a plurality of frames of said video, wherein each of said frames belong to a different one of a plurality of layers and have at least one of (1) a same temporal time in a corresponding decoded said video and (2) a different temporal time in a corresponding decoded said video,
 - (b) receiving a video parameter set extension syntax providing information used for said decoding of said layers, wherein said information includes a tile boundary aligned flag for direct reference layers of said different layers.
- [Claim 2] The method of claim 1 wherein each of said frames of said video that includes at least one slice and at least one tile, wherein each of said at least one slice is characterized that it is decoded independently of the other said at least one slice, wherein each of said at least one slice is characterized that it is decoded independently of the other said at least one slice, wherein each of said at least one tile is characterized that it is a rectangular region of said frame and having a plurality of coding units that are decoded by said decoding arranged in a raster scan order within a region of said frame, wherein said frame includes a plurality of said tiles that are not overlapping with one another; wherein said at least one tile of said frame are collectively arranged in a raster scan order of said frame;
- [Claim 3] The method of claim 1 or 2 wherein said tile boundaries aligned flag equal to 1 indicates that, when any two samples of said frame of one of said layers specified by said video parameter set extension syntax belong to one of said plurality of tiles, the two samples, when both present in said frame of a direct reference layer of said frame of said one of said layers, belong to one tile.
- [Claim 4] The method of claim 1 or 2 wherein said any two samples of said frame of said one of said layers specified by said video parameter set extension syntax belong to different said tiles, the two samples, when both present in said frame of said direct reference layer of said frame of said one of said layers belong to different tiles.
- [Claim 5] The method of claim 4 wherein tile boundaries aligned flag equal to 0

indicates that such restrictions may or may not apply.

[Claim 6] The method of claim 1 or 2 wherein for each of said layers and for each syntax within each of said layers for which each of said layers have a direct dependency said video parameter set extension syntax indicates how at least one of said tiles are aligned.

[Claim 7] The method of claim 1 wherein said tile boundary aligned flag is not signaled for layers that are not a direct reference layers of said different layers.

[Claim 8] The method of claim 7 wherein said tile boundary aligned flag is inferred to be 0 when it is said not signaled.

[Fig. 1A]




FIG. 1A

[Fig. 1B]




FIG. 1B

[Fig. 2]




FIG. 2

[Fig. 3]




FIG. 3

[Fig. 4]




FIG. 4

[Fig. 5]




FIG. 5

[Fig. 6A]




FIG. 6A

[Fig. 6B]




FIG. 6B

[Fig. 7A]





FIG. 7A

[Fig. 7B]



[Fig. 8]




FIG. 8

[Fig. 9]




FIG. 9

[Fig. 10]




FIG. 10

[Fig. 11]




FIG. 11

[Fig. 12]




FIG. 12

[Fig. 13A]

nal_unit_header() {	Descriptor
forbidden_zero_bit	f(1)
nal_unit_type	u(6)
nuh_reserved_zero_6bits	u(6)
nuh_temporal_id_plus1	u(3)
}	

NAL UNIT HEADER SYNTAX

FIG. 13A

[Fig. 13B]

nal_unit_header() {	Descriptor
forbidden_zero_bit	f(1)
nal_unit_type	u(6)
layer_id_plus1	u(6)
nuh_temporal_id_plus1	u(3)
}	

NAL UNIT HEADER SYNTAX

FIG. 13B

[Fig. 13C]

nal_unit_header() {	Descriptor
forbidden_zero_bit	f(1)
nal_unit_type	u(6)
layer_id	u(6)
nuh_temporal_id_plus1	u(3)
}	

NAL UNIT HEADER SYNTAX

FIG. 13C

[Fig. 14]

nal_unit(NumBytesInNALunit) {	Descriptor
nal_unit_header()	
NumBytesInRBSP = 0	
for(i = 2; i < NumBytesInNALunit; i++) {	
if(i + 2 < NumBytesInNALunit && next_bits(24) == 0x000003) {	
rbsp_byte[NumBytesInRBSP++]	b(8)
rbsp_byte[NumBytesInRBSP++]	b(8)
i += 2	
emulation_prevention_three_byte /* equal to 0x03 */	f(8)
} else	
rbsp_byte[NumBytesInRBSP++]	b(8)
}	
}	

GENERAL NAL UNIT SYNTAX

FIG. 14

[Fig. 15]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_zero_bit	u(1)
// scalability type and layer_id partitioning method	
scalability_type	u(4)
for(i = 0; i < MaxDim(scalability_type); i++)	
layer_id_dim_len[i]	u(3)
// layer specific information	
for(i = 0; i <= max_num_layers_minus1; i++) {	
vps_layer_id[i]	u(6)
// layer dependency	
num_direct_ref_layers[i]	u(6)
for(j = 0; j < num_direct_ref_layers[i]; j++)	
ref_layer_id[i][j]	u(6)
}	
}	

Existing video parameter set extension syntax

FIG. 15

[Fig. 16]

scalability type	MaxDim(scalability type)	Scalability dimensions
0	1	none (base HRVC)
1	2	spatial and quality
2	3	spatial, quality, unspecified
3	4	spatial, quality, unspecified, unspecified
4	2	multiview and depth
5	3	multiview, depth, unspecified
6	4	multiview, depth, unspecified, unspecified
7	4	multiview, spatial, quality and depth
8	5	multiview, spatial, quality, depth, unspecified
9	6	multiview, spatial, quality, depth, unspecified, unspecified
10...15	reserved	reserved

Existing Scalability Types

FIG. 16

[Fig. 17]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_zero_bit	u(1)
// Scalability map and layer_id_plus1 mapping method	
for (i=0; i<=max_num_layers_minus1_bits; i++) {	
scalability_map[i]	u(3)
}	
// layer specific information	
for(i = 0; i <= max_num_layers_minus1; i++) {	
vps_layer_id[i]	u(6)
// layer dependency	
num_direct_ref_layers[i]	u(6)
for(j = 0; j < num_direct_ref_layers[i]; j++)	
ref_layer_id[i][j]	u(6)
}	
}	

Video parameter set extension syntax

FIG. 17

[Fig. 18]

Scalability_map[i]	Scalability dimension
0	none (base HEVC)
1	spatial
2	quality
3	depth
4	multiview
5	unspecified
6, 7	reserved

Scalability Map Syntax

FIG. 18

[Fig. 19]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_zero_bit	u(1)
// scalability map and layer_id plus1 mapping method	
num_scalability_dimensions_minus1	u(3)
for(i=0; i<=num_scalability_dimensions_minus1; i++) {	
scalability_map[i]	u(3)
num_bits_for_scalability_map[i]	u(3)
}	
// layer specific information	
for(i=0; i <= max_num_layers_minus1; i++) {	
vps_layer_id[i]	u(6)
// layer dependency	
num_direct_ref_layers[i]	u(6)
for(j=0; j < num_direct_ref_layers[i]; j++)	
ref_layer_id[i][j]	u(6)
}	
}	

Video parameter set extension syntax

FIG. 19

[Fig. 20]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_zero_bit	u(1)
// layer specific information	
for(i=1; i <= vps_max_layers_minus1; i++) {	
// mapping of layer ID to scalability dimension IDs	
num_dimensions_minus1[i]	u(4)
for(j=0; j <= num_dimensions_minus1; j++) {	
dimension_type[i][j]	u(4)
dimension_id[i][j]	u(8)
}	
// layer dependency	
num_direct_ref_layers[i]	u(6)
for(j=0; j < num_direct_ref_layers[i]; j++)	
ref_layer_id[i][j]	u(6)
}	
}	

Existing video parameter set extension syntax

FIG. 20

[Fig. 21]

dimension_type[i][j]	dimension_id[i][j]
0	view order idx
1	depth flag
2	dependency ID
3	quality ID
4..15	reserved

Existing Dimension Type, Dimension ID Syntax

FIG. 21

[Fig. 22]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_zero_bit	u(1)
// layer specific information	
for(i = 1; i <= max_num_layers_minus1; i++) {	
// mask signalling scalability types that are present for this layer ID	
scalability_mask	u(8)
for(j = 0; j <= num_scalability_types[i]; j++) {	
scalability_id[j]	u(8)
}	
// layer dependency	
num_direct_ref_layers[i]	u(6)
for(j = 0; j < num_direct_ref_layers[i]; j++)	
ref_layer_id[i][j]	u(6)
}	
}	

Video parameter set extension syntax

FIG. 22

[Fig. 23]

scalability_mask_bit[k]	Scalability dimension
0	spatial
1	quality
2	depth
3	multiview
4-15	Reserved

Scalability Map Syntax

FIG. 23

[Fig. 24]

video_parameter_set_rbsp() {	Descriptor
video_parameter_set_id	u(4)
vps_temporal_id_nesting_flag	u(1)
reserved_zero_2bits	u(2)
max_num_layers_minus1 // reserved_zero_6bits	u(6)
vps_max_sub_layers_minus1	u(3)
profile_level(1, vps_max_sub_layers_minus1)	
next_essential_info_byte_offset // reserved_zero_12bits	u(12)
for(i = 0; i <= vps_max_sub_layers_minus1; i++) {	
vps_max_dec_pic_buffering[i]	ue(v)
vps_max_num_reorder_pics[i]	ue(v)
vps_max_latency_increase[i]	ue(v)
}	
num_hrd_parameters	ue(v)
for(i = 0; i < num_hrd_parameters; i++) {	
if(i > 0)	
op_point(i)	
hrd_parameters(i == 0, vps_max_sub_layers_minus1)	
}	
bit_equal_to_one	u(1)
scalability_mask	u(8)
for(i = 0; i <= max_num_layers_minus1; i++) {	
vps_extension_data()	
}	
vps_extension_flag	u(1)
if(vps_extension_flag)	
while(more_rbsp_data())	
vps_extension_data_flag	u(1)
rbsp_trailing_bits()	
}	
}	

Video parameter set extension syntax

FIG. 24

[Fig. 25]

vps_extension_data() {	Descriptor
vps_extension_type	u(2)
layer_id	u(6)
layer_max_sub_layers_minus1	u(3)
new_profile_level_flag	u(1)
if (new_profile_level_flag == 0) {	
profile_reference_layer_id	u(6)
}	
else {	
profile_level(1, layer_max_sub_layers_minus1)	
}	
for(j = 0; j <= num_scalability_types; j++) {	
scalable_id[j]	u(8)
}	
num_reference_layers	u(6)
for(n = 0; n < num_reference_layers; n++)	
direct_coding_dependency_layer_id_plus1[n]	u(6)
}	

Video parameter set extension syntax

FIG. 25

[Fig. 26]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_codec_flag	u(1)
scalability_mask	u(16)
for(i = 0; i < NumScalabilityTypes; i++) {	
dimension_id_for_minus1[i]	u(3)
}	
vps_nuh_layer_id_present_flag	u(1)
// layer specific information	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
// mapping of layer ID to scalability dimension IDs	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
for(j = 0; j < NumScalabilityTypes; j++)	
dimension_id[i][j]	u(4)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
profile_tier_level(1, vps_max_sub_layers_minus1)	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
// layer dependency	
num_direct_ref_layers[i]	u(6)
for(j = 0; j < num_direct_ref_layers[i]; j++)	
ref_layer_id[i][j]	u(6)
}	
}	

Video Parameter Set Extension Syntax

FIG. 26

[Fig. 27]

scalability_mask's k'th bit	Scalability dimension
0	spatial
1	quality
2	depth
3	multiview
4-15	Reserved

Scalability_mask Syntax

FIG. 27

[Fig. 28]

vps_extension() {	Descriptor
while(lbyte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_codec_flag	u(1)
scalability_mask	u(16)
for(i = 0; i < NumScalabilityTypes; i++) {	
dimension_id_len_minus1[i]	u(3)
}	
vps_nuh_layer_id_present_flag	u(1)
// layer specific information	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
// mapping of layer ID to scalability dimension IDs	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
for(j = 0; j <= num_dimensions_minus1; j++)	
dimension_id[i][j]	u(v)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
profile_tier_level(1, vps_max_sub_layers_minus1)	
layer_dependency_information_pattern	u(v)
for(i = 1; i <= NumDepLayers; i++) {	
// layer dependency information signaling	
num_direct_ref_layers[i]	u(6)
for(j = 0; j < num_direct_ref_layers[i]; j++)	
ref_layer_id[i][j]	u(6)
}	
}	

Video Parameter Set Extension Syntax

FIG. 28

[Fig. 29]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_codec_flag	u(1)
scalability_mask	u(16)
for(i = 0; i < NumScalabilityTypes; i++) {	
dimension_id_len_minus1[i]	u(3)
}	
vps_nuh_layer_id_present_flag	u(1)
// layer specific information	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
// mapping of layer ID to scalability dimension IDs	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
for(j = 0; j <= num_dimensions_minus1; j++)	
dimension_id[i][j]	u(v)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
profile_tier_level(1, vps_max_sub_layers_minus1)	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
// layer dependency information signaling	
layer_dependency_flag[i]	u(1)
if(layer_dependency_flag[i]) {	
num_direct_ref_layers[i]	u(6)
for(j = 0; j < num_direct_ref_layers[i]; j++)	
ref_layer_id[i][j]	u(6)
}	
}	
}	

Video Parameter Set Extension Syntax

FIG. 29

[Fig. 30]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_codec_flag	u(1)
scalability_mask	u(16)
for(i = 0; i < NumScalabilityTypes; i++) {	
dimension_id_len_minus1[i]	u(3)
}	
vps_nuh_layer_id_present_flag	u(1)
// layer specific information	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
// mapping of layer ID to scalability dimension IDs	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
for(j = 0; j <= num_dimensions_minus1; j++)	
dimension_id[i][j]	u(v)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
profile_tier_level(1, vps_max_sub_layers_minus1)	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
// layer dependency information signaling	
layer_dependency_map[i]	u(v)
}	
}	

Video Parameter Set Extension Syntax

FIG. 30

[Fig. 31]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_codec_flag	u(1)
scalability_mask	u(16)
for(i = 0; i < NumScalabilityTypes; i++) {	
dimension_id_len_minus1[i]	u(3)
}	
vps_nuh_layer_id_present_flag	u(1)
// layer specific information	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
// mapping of layer ID to scalability dimension IDs	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
for(j = 0; j <= num_dimensions_minus1; j++)	
dimension_id[i][j]	u(v)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
profile_tier_level(i, vps_max_sub_layers_minus1)	
layer_dependency_information_pattern	u(v)
for(i = 1; i <= NumDepLayers; i++)	
layer_dependency_map[i]	u(v)
}	

Video Parameter Set Extension Syntax

FIG. 31

[Fig. 32]

vps_extension() {	Descriptor
while(lbyte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_codec_flag	u(1)
scalability_mask	u(16)
for(i = 0; i < NumScalabilityTypes; i++) {	
dimension_id_len_minus1[i]	u(3)
}	
vps_nuh_layer_id_present_flag	u(1)
// layer specific information	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
// mapping of layer ID to scalability dimension IDs	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
for(j = 0; j <= num_dimensions_minus1; j++)	
dimension_id[i][j]	u(v)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
profile_tier_level(1, vps_max_sub_layers_minus1)	
layer_dependency_information_pattern	u(v)
for(i = 1; i <= vps_max_layers_minus1; i++) {	
if(layer_dependency_information_pattern(i)) {	
// layer dependency information signaling	
num_direct_ref_layers[i]	u(6)
for(j = 0; j < num_direct_ref_layers[i]; j++)	
ref_layer_id[i][j]	u(6)
}	
}	
}	
}	

Video Parameter Set Extension Syntax

FIG. 32

[Fig. 33]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
ave_base_codec_flag	u(1)
scalability_mask	u(16)
for(i = 0; i < NumScalabilityTypes; i++) {	
dimension_id_len_minus1[i]	u(3)
}	
vps_nuh_layer_id_present_flag	u(1)
// layer specific information	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
// mapping of layer ID to scalability dimension IDs	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
for(j = 0; j <= num_dimensions_minus1; j++)	
dimension_id[i][j]	u(v)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
profile_tier_level(1, vps_max_sub_layers_minus1)	
layer_dependency_information_pattern	u(v)
for(i = 1; i <= vps_max_layers_minus1; i++) {	
if(layer_dependency_information_pattern[i]) {	
layer_dependency_map[i]	u(v)
}	
}	

Video Parameter Set Extension Syntax

FIG. 33

[Fig. 34A]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_layer_flag	u(1)
splitting_flag	u(1)
for(i = 0; NumScalabilityTypes = 0; i < 16; i++) {	
scalability_mask[i]	u(1)
NumScalabilityTypes += scalability_mask[i]	
}	
for(j = 0; j < NumScalabilityTypes; j++)	
dimension_id_len_minus1[j]	u(3)
...	
num_output_layer_sets	ue(v)
for(i = 0; i < num_output_layer_sets; i++) {	
output_layer_set_idx[i]	ue(v)
lsIdx = output_layer_set_idx[i]	
for(j = 0; j <= vps_max_layer_id; j++)	
if(layer_id_included_flag[lsIdx][j])	
output_layer_flag[lsIdx][j]	u(1)
}	
num_op_dpb_info_parameters	ue(v)
for(i = 0; i < num_op_dpb_info_parameters; i++) {	
operation_point_layer_set_idx[i]	ue(v)
for(j = 0; j <= vps_max_layer_id; j++)	
op_dpb_info_parameters(j)	
}	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
for(j = 0; j < i; j++)	
direct_dependency_flag[i][j]	u(1)
}	

FIG. 34A

[Fig. 34B]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_layer_flag	u(1)
splitting_flag	u(1)
for(i = 0, NumScalabilityTypes = 0; i < 16; i++) {	
scalability_mask[i]	u(1)
NumScalabilityTypes += scalability_mask[i]	
}	
for(j = 0; j < NumScalabilityTypes; j++)	
dimension_id_len_minus1[j]	u(3)
...	
num_output_layer_sets	ue(v)
for(i = 0; i < num_output_layer_sets; i++) {	
output_layer_set_idx[i]	ue(v)
lsIdx = output_layer_set_idx[i]	
for(j = 0 ; j <= vps_max_layer_id; j++)	
if(layer_id_included_flag[lsIdx][j])	
output_layer_flag[lsIdx][j]	u(1)
}	
num_op_dpb_info_parameters	ue(v)
for(i = 0; i < num_op_dpb_info_parameters; i++) {	
operation_point_layer_set_idx[i]	ue(v)
for(j = 0; j <= vps_max_layer_id; j++)	
op_dpb_info_parameters(i, j)	
}	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
for(j = 0; j < i; j++)	
direct_dependency_flag[i][j]	u(1)
}	

FIG. 34B

[Fig. 35A]

op_dpb_info_parameters(j) {	
vps_max_sub_layers_minus1[j]	u(3)
vps_sub_layer_ordering_info_present_flag[j]	u(1)
for(k = (vps_sub_layer_ordering_info_present_flag[j] ? 0 : vps_max_sub_layers_minus1[j]); k <= vps_max_sub_layers_minus1[j]; k++) {	
vps_max_dec_pic_buffering_minus1[j][k]	ue(v)
vps_max_num_reorder_pics[j][k]	ue(v)
vps_max_latency_increase_plus1[j][k]	ue(v)
}	
}	

FIG. 35A

[Fig. 35B]

op_dpb_info_parameters(id, j) {	
vps_max_sub_layers_minus1[id][j]	u(3)
vps_sub_layer_ordering_info_present_flag[id][j]	u(1)
for(k = (vps_sub_layer_ordering_info_present_flag[id][j] ? 0 : vps_max_sub_layers_minus1[id][j]); k <= vps_max_sub_layers_minus1[id][j]; k++) {	
vps_max_dec_pic_buffering_minus1[id][j][k]	ue(v)
vps_max_num_reorder_pics[id][j][k]	ue(v)
vps_max_latency_increase_plus1[id][j][k]	ue(v)
}	
}	

FIG. 35B

[Fig. 36]

vps_extension() {	Descriptor
while(lbyte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_layer_flag	u(1)
splitting_flag	u(1)
for(i = 0, NumScalabilityTypes = 0; i < 16; i++) {	
scalability_mask[i]	u(1)
NumScalabilityTypes += scalability_mask[i]	
}	
for(j = 0; j < NumScalabilityTypes; j++)	
dimension_id_len_minus1[j]	u(3)
...	
num_output_layer_sets	ue(v)
for(i = 0; i < num_output_layer_sets; i++) {	
output_layer_set_idx[i]	ue(v)
lsIdx = output_layer_set_idx[i]	
for(j = 0; j <= vps_max_layer_id; j++)	
if(layer_id_included_flag[lsIdx][j])	
output_layer_flag[lsIdx][j]	u(1)
}	
num_dpb_info_parameters	ue(v)
for(i = 0; i < num_dpb_info_parameters; i++) {	
output_point_layer_set_idx[i]	ue(v)
oplsIdx = output_point_layer_set_idx[i]	
for(j = 0; j <= vps_max_layer_id; j++)	
oop_dpb_info_parameters(j)	
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++)	
direct_dependency_flag[i][j]	u(1)
}	

FIG. 36

[Fig. 37]

oop_dpb_info_parameters(j) {	
vps_max_sub_layers_minus1[j]	u(3)
vps_sub_layer_ordering_info_present_flag[j]	u(1)
for(k = (vps_sub_layer_ordering_info_present_flag[j] ? 0 : vps_max_sub_layers_minus1[j]); k <= vps_max_sub_layers_minus1[j]; k++) {	
vps_max_dec_pic_buffering_minus1[j][k]	ue(v)
vps_max_num_reorder_pics[j][k]	ue(v)
vps_max_latency_increase_plus1[j][k]	ue(v)
}	
}	

FIG. 37

[Fig. 38]

oop_dpb_info_parameters() {	
vps_max_sub_layers_minus1	u(3)
vps_sub_layer_ordering_info_present_flag	u(1)
for(k = (vps_sub_layer_ordering_info_present_flag ? 0 : vps_max_sub_layers_minus1); k <= vps_max_sub_layers_minus1; k++) {	
vps_max_dec_pic_buffering_minus1[k]	ue(v)
vps_max_num_reorder_pics[k]	ue(v)
vps_max_latency_increase_plus1[k]	ue(v)
}	
}	

FIG. 38

[Fig. 39]

num_dpb_info_parameters	ue(v)
for(i = 0; i < num_dpb_info_parameters; i++) {	
output_point_layer_set_idx[i]	ue(v)
oplsIdx=output_point_layer_set_idx[i]	
for(j = 0; j <= vps_max_layer_id; j++)	
oop_dpb_info_parameters()	
}	

FIG. 39

[Fig. 40]

oop_dpb_info_parameters(id, j) {	
vps_max_sub_layers_minus1[id][j]	u(3)
vps_sub_layer_ordering_info_present_flag[id][j]	u(1)
for(k = (vps_sub_layer_ordering_info_present_flag[id][j] ? 0 : vps_max_sub_layers_minus1[id][j]); k <= vps_max_sub_layers_minus1[id][j]; k++) {	
vps_max_dec_pic_buffering_minus1[id][j][k]	ue(v)
vps_max_num_reorder_pics[id][j][k]	ue(v)
vps_max_latency_increase_plus1[id][j][k]	ue(v)
}	
}	

FIG. 40

[Fig. 41]

num_dpb_info_parameters	ue(v)
for(i = 0; i < num_dpb_info_parameters; i++) {	
output_point_layer_set_idx[i]	ue(v)
oplsIdx=output_point_layer_set_idx[i]	
for(j = 0; j <= vps_max_layer_id; j++)	
oop_dpb_info_parameters(oplsIdx, j)	
}	

FIG. 41

[Fig. 42]

num_dpb_info_parameters	ue(v)
for(i = 0; i < num_dpb_info_parameters; i++) {	
output_point_layer_set_idx[i]	ue(v)
oplsIdx=output_point_layer_set_idx[i]	
for(j = 0; j <= vps_max_layer_id; j++)	
oop_dpb_info_parameters(i, j)	
}	

FIG. 42

[Fig. 43]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_layer_flag	u(1)
splitting_flag	u(1)
for(i = 0, NumScalabilityTypes = 0; i < 16; i++) {	
scalability_mask[i]	u(1)
NumScalabilityTypes += scalability_mask[i]	
}	
for(j = 0; j < NumScalabilityTypes; j++)	
dimension_id_len_minus1[j]	u(3)
...	
for(i = 1; i <= vps_max_layers_minus1; i++) {	
for(j = 0; j < i; j++)	
direct_dependency_flag[i][j]	u(1)
for(i = 1; i <= vps_max_layers_minus1; i++) {	
layer_dpb_info(i)	
}	
}	
}	

layer_dpb_info(i) {	
vps_max_sub_layers_minus1[i]	u(3)
vps_sub_layer_ordering_info_present_flag[i]	u(1)
for(k = (vps_sub_layer_ordering_info_present_flag[i] ? 0 : vps_max_sub_layers_minus1[i]);	
k <= vps_max_sub_layers_minus1[i]; k++) {	
vps_max_dec_pic_buffering_minus1[i][k]	ue(v)
vps_max_num_reorder_pics[i][k]	ue(v)
vps_max_latency_increase_plus1[i][k]	ue(v)
}	
}	
}	

FIG. 43

[Fig. 44]

oop_dpb_info_parameters(id) / op_dpb_info_parameters(id) / layer_dpb_info(id) {	
vps_sub_layer_ordering_info_present_flag[id]	u(1)
for(i = (vps_sub_layer_ordering_info_present_flag ? 0 : vps_max_sub_layers_minus1);	
i <= vps_max_sub_layers_minus1; i++) {	
vps_max_dec_pic_buffering_minus1[id][i]	ue(v)
vps_max_num_reorder_pics[id][i]	ue(v)
vps_max_latency_increase_plus1[id][i]	ue(v)
}	
}	
}	

FIG. 44

[Fig. 45]

BASE LAYER

SPS+

PPS+

ENHANCEMENT LAYER 0

SPS+

PPS+

ENHANCEMENT LAYER 1

SPS+

PPS+


ENHANCEMENT LAYER 2

SPS+

PPS+


FIG. 45

[Fig. 46]



PRIOR ART
FIG. 46

[Fig. 47]



PRIOR ART
FIG. 47

[Fig. 48]




Diagram illustrating a 10x10 grid structure with row and column boundaries. The grid is divided into four 5x5 quadrants by thick lines. The top-left quadrant contains numbers 1 through 21. The top-right quadrant contains numbers 22 through 42. The bottom-left quadrant contains numbers 43 through 63. The bottom-right quadrant contains numbers 64 through 84. The grid is labeled with 'COLUMN BOUNDARIES' and 'ROW BOUNDARIES' with arrows indicating the boundaries.

1	2	3	4	5	16	17	18	19	20	21	34	35	36
6	7	8	9	10	22	23	24	25	26	27	37	38	39
11	12	13	14	15	28	29	30	31	32	33	40	41	42
43	44	45	46	47	63	64	65	66	67	68	87	88	89
48	49	50	51	52	69	70	71	72	73	74	90	91	92
53	54	55	56	57	75	76	77	78	79	80	93	94	95
58	59	60	61	62	81	82	83	84	85	86	96	97	98
99	100	101	102	103	109	110	111	112	113	114	121	122	123
104	105	106	107	108	115	116	117	118	119	120	124	125	126

FIG. 48

[Fig. 49]

1	2	3	4	37	38	39	40	41	42	43	100	101	102
5	6	7	8	44	45	46	47	48	49	50	103	104	105
9	10	11	12	51	52	53	54	55	56	57	106	107	108
13	14	15	16	58	59	60	61	62	63	64	109	110	111
17	18	19	20	65	66	67	68	69	70	71	112	113	114
21	22	23	24	72	73	74	75	76	77	78	115	116	117
25	26	27	28	79	80	81	82	83	84	85	118	119	120
29	30	31	32	86	87	88	89	90	91	92	121	122	123
33	34	35	36	93	94	95	96	97	98	99	124	125	126

SLICE 1

SLICE 2

SLICE 3

COLUMN BOUNDARIES

FIG. 49

[Fig. 50]




FIG. 50

[Fig. 51A]

seq_parameter_set_rbsp() {	Descriptor
sps_video_parameter_set_id	u(4)
if(nuh_layer_id == 0) {	
sps_max_sub_layers_minus1	u(3)
sps_temporal_id_nesting_flag	u(1)
profile_tier_level(1, sps_max_sub_layers_minus1)	
}	
sps_seq_parameter_set_id	ue(v)
chroma_format_idc	ue(v)
if(chroma_format_idc == 3)	
separate_colour_plane_flag	u(1)
pic_width_in_luma_samples	ue(v)
pic_height_in_luma_samples	ue(v)
conformance_window_flag	u(1)
if(conformance_window_flag) {	
conf_win_left_offset	ue(v)
conf_win_right_offset	ue(v)
conf_win_top_offset	ue(v)
conf_win_bottom_offset	ue(v)
}	
bit_depth_luma_minus8	ue(v)
bit_depth_chroma_minus8	ue(v)
log2_max_pic_order_cnt_lsb_minus4	ue(v)
sps_sub_layer_ordering_info_present_flag	u(1)
for(i = (sps_sub_layer_ordering_info_present_flag ? 0 : sps_max_sub_layers_minus1);	
i <= sps_max_sub_layers_minus1; i++) {	
sps_max_dec_pic_buffering_minus1[i]	ue(v)
sps_max_num_reorder_pics[i]	ue(v)
sps_max_latency_increase_plus1[i]	ue(v)
}	
log2_min_luma_coding_block_size_minus3	ue(v)
log2_diff_max_min_luma_coding_block_size	ue(v)
log2_min_transform_block_size_minus2	ue(v)
log2_diff_max_min_transform_block_size	ue(v)
max_transform_hierarchy_depth_inter	ue(v)
max_transform_hierarchy_depth_intra	ue(v)
scaling_list_enabled_flag	u(1)
if(scaling_list_enabled_flag) {	
sps_scaling_list_data_present_flag	u(1)

FIG. 51A

[Fig. 51B]

if(sps_scaling_list_data_present_flag)	
scaling_list_data()	
}	
amp_enabled_flag	u(1)
sample_adaptive_offset_enabled_flag	u(1)
pcm_enabled_flag	u(1)
if(pcm_enabled_flag) {	
pcm_sample_bit_depth_luma_minus1	u(4)
pcm_sample_bit_depth_chroma_minus1	u(4)
log2_min_pcm_luma_coding_block_size_minus3	ue(v)
log2_diff_max_min_pcm_luma_coding_block_size	ue(v)
pcm_loop_filter_disabled_flag	u(1)
}	
num_short_term_ref_pic_sets	ue(v)
for(i = 0; i < num_short_term_ref_pic_sets; i++)	
short_term_ref_pic_set(i)	
long_term_ref_pics_present_flag	u(1)
if(long_term_ref_pics_present_flag) {	
num_long_term_ref_pics_sps	ue(v)
for(i = 0; i < num_long_term_ref_pics_sps; i++) {	
lt_ref_pic_poc_lsb_sps[i]	u(v)
used_by_curr_pic_lt_sps_flag[i]	u(1)
}	
}	
sps_temporal_mvp_enabled_flag	u(1)
strong_intra_smoothing_enabled_flag	u(1)
vui_parameters_present_flag	u(1)
if(vui_parameters_present_flag)	
vui_parameters()	
sps_extension_flag	u(1)
if(sps_extension_flag) {	
sps_extension()	
sps_extension2_flag	u(1)
if(sps_extension2_flag)	
while(more_rbsp_data())	
sps_extension_data_flag	u(1)
}	
rbsp_trailing_bits()	
}	

FIG. 51B

[Fig. 52A]

vui_parameters() {	Descriptor
aspect_ratio_info_present_flag	u(1)
if(aspect_ratio_info_present_flag) {	
aspect_ratio_idc	u(8)
if(aspect_ratio_idc == EXTENDED_SAR) {	
sar_width	u(16)
sar_height	u(16)
}	
}	
overscan_info_present_flag	u(1)
if(overscan_info_present_flag)	
overscan_appropriate_flag	u(1)
video_signal_type_present_flag	u(1)
if(video_signal_type_present_flag) {	
video_format	u(3)
video_full_range_flag	u(1)
colour_description_present_flag	u(1)
if(colour_description_present_flag) {	
colour_primaries	u(8)
transfer_characteristics	u(8)
matrix_coeffs	u(8)
}	
}	
chroma_loc_info_present_flag	u(1)
if(chroma_loc_info_present_flag) {	
chroma_sample_loc_type_top_field	ue(v)
chroma_sample_loc_type_bottom_field	ue(v)
}	
neutral_chroma_indication_flag	u(1)
field_seq_flag	u(1)
frame_field_info_present_flag	u(1)
default_display_window_flag	u(1)
if(default_display_window_flag) {	
def_disp_win_left_offset	ue(v)
def_disp_win_right_offset	ue(v)
def_disp_win_top_offset	ue(v)
def_disp_win_bottom_offset	ue(v)

FIG. 52A

[Fig. 52B]

}	
vui_timing_info_present_flag	u(1)
if(vui_timing_info_present_flag) {	
vui_num_units_in_tick	u(32)
vui_time_scale	u(32)
vui_poc_proportional_to_timing_flag	u(1)
if(vui_poc_proportional_to_timing_flag)	
vui_num_ticks_poc_diff_one_minus1	ue(v)
vui_hrd_parameters_present_flag	u(1)
if(vui_hrd_parameters_present_flag)	
hrd_parameters(1, sps_max_sub_layers_minus1)	
}	
bitstream_restriction_flag	u(1)
if(bitstream_restriction_flag) {	
tiles_fixed_structure_flag	u(1)
if(nuh_layer_id > 0)	
tile_boundaries_aligned_flag	u(1)
motion_vectors_over_pic_boundaries_flag	u(1)
restricted_ref_pic_lists_flag	u(1)
min_spatial_segmentation_idc	ue(v)
max_bytes_per_pic_denom	ue(v)
max_bits_per_min_cu_denom	ue(v)
log2_max_mv_length_horizontal	ue(v)
log2_max_mv_length_vertical	ue(v)
}	
}	

FIG. 52B

[Fig. 53]

pic_parameter_set_rbsp() {	Descriptor
pps_pic_parameter_set_id	ue(v)
pps_seq_parameter_set_id	ue(v)
dependent_slice_segments_enabled_flag	u(1)
...	
tiles_enabled_flag	u(1)
entropy_coding_sync_enabled_flag	u(1)
if(tiles_enabled_flag) {	
if (!(nuh_layer_id > 0 && tile_boundaries_aligned_flag)) {	
num_tile_columns_minus1	ue(v)
num_tile_rows_minus1	ue(v)
uniform_spacing_flag	u(1)
if(!uniform_spacing_flag) {	
for(i = 0; i < num_tile_columns_minus1; i++)	
column_width_minus1[i]	ue(v)
for(i = 0; i < num_tile_rows_minus1; i++)	
row_height_minus1[i]	ue(v)
}	
}	
loop_filter_across_tiles_enabled_flag	u(1)
}	
pps_loop_filter_across_slices_enabled_flag	u(1)
deblocking_filter_control_present_flag	u(1)
...	
pps_extension_flag	u(1)
if(pps_extension_flag)	
while(more_rbsp_data())	
pps_extension_data_flag	u(1)
rbsp_trailing_bits()	
}	

FIG. 53

[Fig. 54A]

video_parameter_set_rbsp() {	Descriptor
vps_video_parameter_set_id	u(4)
vps_reserved_three_2bits	u(2)
vps_max_layers_minus1	u(6)
vps_max_sub_layers_minus1	u(3)
vps_temporal_id_nesting_flag	u(1)
vps_extension_offset // vps_reserved_0xffff_16bits	u(16)
profile_tier_level(1, vps_max_sub_layers_minus1)	
vps_sub_layer_ordering_info_present_flag	u(1)
for(i = (vps_sub_layer_ordering_info_present_flag ? 0 : vps_max_sub_layers_minus1); i <= vps_max_sub_layers_minus1; i++) {	
vps_max_dec_pic_buffering_minus1[i]	ue(v)
vps_max_num_reorder_pics[i]	ue(v)
vps_max_latency_increase_plus1[i]	ue(v)
}	
vps_max_layer_id	u(6)
vps_num_layer_sets_minus1	ue(v)
for(i = 1; i <= vps_num_layer_sets_minus1; i++)	
for(j = 0; j <= vps_max_layer_id; j++)	
layer_id_included_flag[i][j]	u(1)
vps_timing_info_present_flag	u(1)
if(vps_timing_info_present_flag) {	
vps_num_units_in_tick	u(32)
vps_time_scale	u(32)
vps_poc_proportional_to_timing_flag	u(1)
if(vps_poc_proportional_to_timing_flag)	
vps_num_ticks_poc_diff_one_minus1	ue(v)
vps_num_hrd_parameters	ue(v)
for(i = 0; i < vps_num_hrd_parameters; i++) {	
hrd_layer_set_idx[i]	ue(v)
if(i > 0)	
cprms_present_flag[i]	u(1)
hrd_parameters(cprms_present_flag[i], vps_max_sub_layers_minus1)	
}	

FIG. 54A

[Fig. 54B]

}	
vps_extension_flag	u(1)
if(vps_extension_flag) {	
vps_extension()	
vps_extension2_flag	u(1)
if(vps_extension2_flag)	
while(more_rbsp_data())	
vps_extension_data_flag	u(1)
}	
rbsp_trailing_bits()	
}	

FIG. 54B

[Fig. 55]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_layer_flag	u(1)
splitting_flag	u(1)
for(i = 0; NumScalabilityTypes = 0; i < 16; i++) {	
scalability_mask[i]	u(1)
NumScalabilityTypes += scalability_mask[i]	
}	
for(j = 0; j < (NumScalabilityTypes - splitting_flag); j++)	
dimension_id_len_minus1[j]	u(3)
vps_nuh_layer_id_present_flag	u(1)
for(i = 1; i <= vps_max_layers_minus1; i++) {	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
if(!splitting_flag)	
for(j = 0; j < NumScalabilityTypes; j++)	
dimension_id[i][j]	u(v)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++)	
direct_dependency_flag[i][j]	u(1)
for(i = 0; i < vps_max_layers_minus1; i++)	
max_tid_il_ref_pics_plus1[i]	u(3)
tile_boundaries_aligned_vps_flag	u(1)
.....	

FIG. 55

[Fig. 56]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_layer_flag	u(1)
splitting_flag	u(1)
for(i = 0, NumScalabilityTypes = 0; i < 16; i++) {	
scalability_mask[i]	u(1)
NumScalabilityTypes += scalability_mask[i]	
}	
for(j = 0; j < (NumScalabilityTypes - splitting_flag); j++)	
dimension_id_len_minus1[j]	u(3)
vps_nuh_layer_id_present_flag	u(1)
for(i = 1; i <= vps_max_layers_minus1; i++) {	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
if(!splitting_flag)	
for(j = 0; j < NumScalabilityTypes; j++)	
dimension_id[i][j]	u(v)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++)	
direct_dependency_flag[i][j]	u(1)
for(i = 0; i < vps_max_layers_minus1; i++)	
max_tid_il_ref_pics_plus1[i]	u(3)
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++)	
reflayer_tile_boundaries_aligned_flag[i][j]	u(1)
.....	

FIG. 56

[Fig. 57]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_layer_flag	u(1)
splitting_flag	u(1)
for(i = 0, NumScalabilityTypes = 0; i < 16; i++) {	
scalability_mask[i]	u(1)
NumScalabilityTypes += scalability_mask[i]	
}	
for(j = 0; j < (NumScalabilityTypes - splitting_flag); j++)	
dimension_id_len_minus1[j]	u(3)
vps_nuh_layer_id_present_flag	u(1)
for(i = 1; i <= vps_max_layers_minus1; i++) {	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
if(!splitting_flag)	
for(j = 0; j < NumScalabilityTypes; j++)	
dimension_id[i][j]	u(v)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++)	
direct_dependency_flag[i][j]	u(1)
for(i = 0; i < vps_max_layers_minus1; i++)	
max_tid_il_ref_pics_plus1[i]	u(3)
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++)	
if(direct_dependency_flag[i][j])	
reflayer_tile_boundaries_aligned_flag[i][j]	u(1)
.....	

FIG. 57

[Fig. 58]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_layer_flag	u(1)
splitting_flag	u(1)
for(i = 0, NumScalabilityTypes = 0; i < 16; i++) {	
scalability_mask[i]	u(1)
NumScalabilityTypes += scalability_mask[i]	
}	
for(j = 0; j < (NumScalabilityTypes - splitting_flag); j++)	
dimension_id_len_minus1[j]	u(3)
vps_nuh_layer_id_present_flag	u(1)
for(i = 1; i <= vps_max_layers_minus1; i++) {	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
if(!splitting_flag)	
for(j = 0; j < NumScalabilityTypes; j++)	
dimension_id[i][j]	u(v)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++) {	
direct_dependency_flag[i][j]	u(1)
reflayer_tile_boundaries_aligned_flag[i][j]	u(1)
}	
for(i = 0; i < vps_max_layers_minus1; i++)	
max_tid_il_ref_pics_plus1[i]	u(3)
.....	

FIG. 58

[Fig. 59]

vps_extension() {	Descriptor
while(!byte_aligned())	
vps_extension_byte_alignment_reserved_one_bit	u(1)
avc_base_layer_flag	u(1)
splitting_flag	u(1)
for(i = 0, NumScalabilityTypes = 0; i < 16; i++) {	
scalability_mask[i]	u(1)
NumScalabilityTypes += scalability_mask[i]	
}	
for(j = 0; j < (NumScalabilityTypes - splitting_flag); j++)	
dimension_id_len_minus1[j]	u(3)
vps_nuh_layer_id_present_flag	u(1)
for(i = 1; i <= vps_max_layers_minus1; i++) {	
if(vps_nuh_layer_id_present_flag)	
layer_id_in_nuh[i]	u(6)
if(!splitting_flag)	
for(j = 0; j < NumScalabilityTypes; j++)	
dimension_id[i][j]	u(v)
}	
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++) {	
direct_dependency_flag[i][j]	u(1)
if(direct_dependency_flag[i][j])	
reflayer_tile_boundaries_aligned_flag[i][j]	u(1)
}	
for(i = 0; i < vps_max_layers_minus1; i++)	
max_tid_il_ref_pics_plus1[i]	u(3)
.....	

FIG. 59

[Fig. 60]

vui_parameters() {	Descriptor
aspect_ratio_info_present_flag	u(1)
...	
bitstream_restriction_flag	u(1)
if(bitstream_restriction_flag) {	
tiles_fixed_structure_flag	u(1)
if (nuh_layer_id > 0) {	
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++)	
reflayer_tile_boundaries_aligned_flag[i][j]	u(1)
}	
motion_vectors_over_pic_boundaries_flag	u(1)
restricted_ref_pic_lists_flag	u(1)
min_spatial_segmentation_idc	ue(v)
max_bytes_per_pic_denom	ue(v)
max_bits_per_min_cu_denom	ue(v)
log2_max_mv_length_horizontal	ue(v)
log2_max_mv_length_vertical	ue(v)
}	
}	

FIG. 60: VUI parameters syntax

[Fig. 61]

vui_parameters() {	Descriptor
aspect_ratio_info_present_flag	u(1)
...	
bitstream_restriction_flag	u(1)
if(bitstream_restriction_flag) {	
tiles_fixed_structure_flag	u(1)
if (nuh_layer_id > 0) {	
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++)	
if(direct_dependency_flag[i][j])	
reflayer_tile_boundaries_aligned_flag[i][j]	u(1)
}	
motion_vectors_over_pic_boundaries_flag	u(1)
restricted_ref_pic_lists_flag	u(1)
min_spatial_segmentation_idc	ue(v)
max_bytes_per_pic_denom	ue(v)
max_bits_per_min_cu_denom	ue(v)
log2_max_mv_length_horizontal	ue(v)
log2_max_mv_length_vertical	ue(v)
}	
}	

FIG. 61: VUI parameters syntax

[Fig. 62]

vui_parameters() {	Descriptor
aspect_ratio_info_present_flag	u(1)
...	
bitstream_restriction_flag	u(1)
if(bitstream_restriction_flag) {	
tiles_fixed_structure_flag	u(1)
if (nuh_layer_id > 0) {	
for(j = 0; j < NumDirectRefLayers[nuh_layer_id]; j++)	
ref_layer_tile_boundaries_aligned_flag[j]	u(1)
}	
motion_vectors_over_pic_boundaries_flag	u(1)
restricted_ref_pic_lists_flag	u(1)
min_spatial_segmentation_idc	ue(v)
max_bytes_per_pic_denom	ue(v)
max_bits_per_min_cu_denom	ue(v)
log2_max_mv_length_horizontal	ue(v)
log2_max_mv_length_vertical	ue(v)
}	
}	

FIG. 62: VUI parameters syntax

[Fig. 63]

if (nuh_layer_id > 0) {	
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++)	
reflayer_tile_boundaries_aligned_flag[i][j]	u(1)
}	

FIG. 63

[Fig. 64]

if (nuh_layer_id > 0) {	
for(i = 1; i <= vps_max_layers_minus1; i++)	
for(j = 0; j < i; j++)	
if(direct_dependency_flag[i][j])	
reflayer_tile_boundaries_aligned_flag[i][j]	u(1)
}	

FIG. 64

INTERNATIONAL SEARCH REPORT

International application No.

PCT/JP2014/003721

A. CLASSIFICATION OF SUBJECT MATTER			
Int.Cl. H04N19/30 (2014.01) i, H04N19/70 (2014.01) i			
According to International Patent Classification (IPC) or to both national classification and IPC			
B. FIELDS SEARCHED			
Minimum documentation searched (classification system followed by classification symbols)			
Int.Cl. H04N19/30, H04N19/70			
Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched			
Published examined utility model applications of Japan 1922-1996 Published unexamined utility model applications of Japan 1971-2014 Registered utility model specifications of Japan 1996-2014 Published registered utility model applications of Japan 1994-2014			
Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)			
C. DOCUMENTS CONSIDERED TO BE RELEVANT			
Category*	Citation of document, with indication, where appropriate, of the relevant passages		Relevant to claim No.
P, X	Deshpande, S., et al, On Tile Alignment, Joint Collaborative Team on Video Coding (JCT-VC) of ITU-T SG 16 WP 3 and ISO/IEC JTC1/SC29/WG11 JCTVC-N0199, 2013.07.16		1-8
A	Suhring, K., et al, Tile boundary alignment and inter-layer prediction constraints for SHVC and MV-HEVC, Joint Collaborative Team on Video Coding (JCT-VC) of ITU-T SG 16 WP 3 and ISO/IEC JTC1/SC29/WG11 JCTVC-M0464, 2013.04.25		1-8
A	Chen, J., et al, SHVC Working Draft 2, Joint Collaborative Team on Video Coding (JCT-VC) of ITU-T SG16 WP3 and ISO/IEC JTC1/SC29/WG11 JCTVC-M1008_v3, 2013.06.14, P.7-8, 17-18		1-8
☐ Further documents are listed in the continuation of Box C. ☐ See patent family annex.			
* Special categories of cited documents: "A" document defining the general state of the art which is not considered to be of particular relevance "E" earlier application or patent but published on or after the international filing date "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified) "O" document referring to an oral disclosure, use, exhibition or other means "P" document published prior to the international filing date but later than the priority date claimed "T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art "&" document member of the same patent family			
Date of the actual completion of the international search		Date of mailing of the international search report	
01.09.2014		09.09.2014	
Name and mailing address of the ISA/JP		Authorized officer	
Japan Patent Office		Hiroshi Kawasaki	
3-4-3, Kasumigaseki, Chiyoda-ku, Tokyo 100-8915, Japan		Telephone No. +81-3-3581-1101 Ext. 3541	