



(86) Date de dépôt PCT/PCT Filing Date: 2013/06/21
(87) Date publication PCT/PCT Publication Date: 2014/12/24
(45) Date de délivrance/Issue Date: 2017/08/08
(85) Entrée phase nationale/National Entry: 2015/12/17
(86) N° demande PCT/PCT Application No.: CN 2013/077631
(87) N° publication PCT/PCT Publication No.: 2014/201684

(51) Cl.Int./Int.Cl. *H04J 14/00* (2006.01)
(72) Inventeurs/Inventors:
WANG, CHAO, CN;
ZHANG, CHUNHUI, CN;
ZHANG, LEWEI, CN
(73) Propriétaire/Owner:
HUAWEI TECHNOLOGIES CO., LTD., CN
(74) Agent: SMART & BIGGAR

(54) Titre : PROCEDE ET APPAREIL DE COMMUNICATION OPTIQUE
(54) Title: OPTICAL COMMUNICATIONS METHOD AND APPARATUS

100

A local communications node determines at least two local input areas from the input optical modulator array, so that each input optical modulator in the at least two local input areas is configured to receive a foreign signal light and the foreign signal light is a signal light that comes from a transmitter-side foreign communications node and needs to be sent to a receiver-side foreign communications node


S110

The local communications node determines at least two local output areas from the output optical modulator array, so that each output optical modulator in the at least two local output areas is configured to send the foreign signal light, where the at least two local input areas correspond to the at least two local output areas in a one-to-one mapping manner, and each input optical modulator in a local input area is capable of transmitting the signal light to each output optical modulator in a corresponding local output area

S120

(57) **Abrégé/Abstract:**

An optical communications method and an optical communications apparatus are provided, where the method is executed on a communications node that includes an input optical modulator array and an output optical modulator array, where the input optical modulator array includes N input optical modulators, where N is greater than the number of input optical modulators capable of covering a same output optical modulator, and the method includes: determining at least two local input areas from the input optical modulator array, so that each input optical modulator in each local input area is used to receive a foreign signal light; and determining at least two local output areas from the output optical modulator array, where each output optical modulator in each local output area is used to send the foreign signal light, the at least two local input areas correspond to the at least two local output areas in a one-to-one mapping manner, and each input optical modulator in a local input area is capable of transmitting the signal light to each output optical modulator in a corresponding local output area.



ABSTRACT

An optical communications method and an optical communications apparatus are provided, where the method is executed on a communications node that includes an input optical modulator array and an output optical modulator array, where the input
5 optical modulator array includes N input optical modulators, where M is greater than the number of output optical modulators that can be covered by one input optical modulator and N is greater than the number of input optical modulators capable of covering a same output optical modulator, and the method includes: determining at least two local input areas from the input optical modulator array, so that each input
10 optical modulator in each local input area is used to receive a foreign signal light; and determining at least two local output areas from the output optical modulator array, where each output optical modulator in each local output area is used to send the foreign signal light, the at least two local input areas correspond to the at least two local output areas in a one-to-one mapping manner, and each input optical modulator
15 in a local input area is capable of transmitting the signal light to each output optical modulator in a corresponding local output area.

52663-170

OPTICAL COMMUNICATIONS METHOD AND APPARATUS

TECHNICAL FIELD

[0001] The present invention relates to the communications field, and in particular, relates to an optical communications apparatus and method.

5

BACKGROUND

[0002] With rapid growth of video and cloud services, operators pay special attention to flexibility of optical network construction and reduction of costs in optical network construction, operation, and maintenance. A network node requires cross-connections in more direction dimensions (or, in other words, transmission paths). By using a reconfigurable optical add/drop multiplexer (ROADM, Reconfigurable Optical Add/Drop Multiplexer), an operator can perform dimension switching remotely and automatically instead of replacing a fiber connection manually by visiting a site in traditional practices, which meets a requirement for dynamic connections on a network. To meet efficiency and flexibility requirements of a high-speed optical communications network, the ROADM serving as a network cross-connection core needs to develop continuously.

[0003] At present, the ROADM switches a direction dimension primarily by using an optical cross connect (OXC, Optical Cross Connect). One OXC includes multiple input optical modulators and multiple output optical modulators. Each input optical modulator corresponds to one beam of input signal light, and each output optical modulator corresponds to one beam of output signal light. A cross-connect capability (that is, the number of output optical modulators that can be covered by one input optical modulator, or, in other words, the number of input optical modulators capable of covering one output optical modulator) of the optical modulator, which serves as a core component of the OXC, determines a direction dimension to which the OXC can switch, or, in other words, determines the number of input optical modulators and output optical modulators

52663-170

included in the OXC.

[0004] Therefore, the ROADM in the prior art may be unable to meet currently growing network requirements and user requirements due to the limited cross-connect capability of the optical modulator.

5

SUMMARY

[0005] Embodiments of the present invention provide an optical communications method and apparatus, which can enable the number of switchable dimensions to be greater than a cross-connect capability of a single optical modulator, and meet network requirements and user requirements on condition that a structure of the single optical
10 modulator is not changed.

[0006] According to a first aspect, an optical communications method is provided, where the method is executed on a communications node that includes an input optical modulator array and an output optical modulator array, where the input optical modulator array includes N input optical modulators and the N input optical modulators are
15 configured to receive a signal light, and the output optical modulator array includes M output optical modulators and the M output optical modulators are configured to send the signal light, where M is greater than the number of output optical modulators that can be covered by one input optical modulator and/or N is greater than the number of input optical modulators capable of covering a same output optical modulator, and the method
20 includes: determining, by a local communications node, at least two local input areas from the input optical modulator array, so that each input optical modulator in the at least two local input areas is used to receive a foreign signal light and the foreign signal light is a signal light that comes from a transmitter-side foreign communications node and needs to be sent to a receiver-side foreign communications node; and determining, by the local
25 communications node, at least two local output areas from the output optical modulator array, so that each output optical modulator in the at least two local output areas is used to send the foreign signal light, where the at least two local input areas correspond to the at least two local output areas in a one-to-one mapping manner, and each input optical modulator in a local input area is capable of transmitting the signal light to each output

52663-170

optical modulator in a corresponding local output area.

[0007] With reference to the first aspect, in a first implementation manner of the first aspect, the number of output optical modulators included in the at least two local output areas is greater than the number of output optical modulators that can be covered by one
5 input optical modulator.

[0008] With reference to the first aspect and the foregoing implementation manner, in a second implementation manner of the first aspect, the number of input optical modulators included in the at least two local input areas is greater than the number of input optical modulators capable of covering the same output optical modulator.

10 **[0009]** With reference to the first aspect and the foregoing implementation manner, in a third implementation manner of the first aspect, the method further includes: when a first input optical modulator included in a first local input area of the at least two local input areas receives a first foreign signal light from a first transmitter-side foreign communications node, performing, by the local communications node, control to cause
15 the first input optical modulator to transmit the first foreign signal light to a first output optical modulator included in a first local output area of the at least two local output areas, so that the first output optical modulator transmits the first foreign signal light to a first receiver-side foreign communications node, where the first local output area corresponds to the first local input area, the first transmitter-side foreign communications node is a previous-hop communications node of the local communications node in a transmission path of the first foreign signal light, the first input optical modulator corresponds to the first transmitter-side foreign communications node and a wavelength of the first foreign signal light, the first receiver-side foreign communications node is a next-hop communications node of the local communications node in the transmission
20 path of the first foreign signal light, and the first output optical modulator corresponds to the first receiver-side foreign communications node and the wavelength of the first foreign signal light.

[0010] With reference to the first aspect and the foregoing implementation manner, in a fourth implementation manner of the first aspect, the determining, by a local communications node, at least two local input areas from the input optical modulator
30

52663-170

array, includes: determining, by the local communications node, the at least two local input areas from the input optical modulator array according to the number of dimensions of the transmitter-side foreign communications node and the number of wavelengths of the foreign signal light.

5 [0011] With reference to the first aspect and the foregoing implementation manner, in a fifth implementation manner of the first aspect, the determining, by the local communications node, at least two local output areas from the output optical modulator array, includes: determining, by the local communications node, the at least two local
10 dimensions of the receiver-side foreign communications node and the number of wavelengths of the foreign signal light.

[0012] With reference to the first aspect and the foregoing implementation manner, in a sixth implementation manner of the first aspect, the method further includes: determining, by the local communications node, a global input area from the input optical
15 modulator array, so that each input optical modulator in the global input area is used to receive an uplink local signal light, where the uplink local signal light is a signal light from the local communications node, and each input optical modulator in the global input area is capable of transmitting the signal light to all output optical modulators in the optical modulator array.

20 [0013] With reference to the first aspect and the foregoing implementation manner, in a seventh implementation manner of the first aspect, the determining, by the local communications node, a global input area from the input optical modulator array, includes: determining, by the local communications node, the global input area from the input optical modulator array according to the number of channels used by the uplink
25 local signal light.

[0014] With reference to the first aspect and the foregoing implementation manner, in an eighth implementation manner of the first aspect, the determining, by the local communications node, at least two local output areas from the output optical modulator array, includes: determining, by the local communications node, the at least two local
30 output areas from the output optical modulator array, so that each output optical

52663-170

modulator in the at least two local output areas is used to send the uplink local signal light.

[0015] With reference to the first aspect and the foregoing implementation manner, in a ninth implementation manner of the first aspect, the method further includes: when a first uplink local signal light needs to be sent, performing, by the local communications node, control to cause the second input optical modulator to transmit the first uplink local signal light to a second output optical modulator in the output optical modulator array, so that the second output optical modulator transmits the first uplink local signal light to a second receiver-side foreign communications node, where the second input optical modulator corresponds to a channel used by the first uplink local signal light, the second receiver-side foreign communications node is a next-hop communications node of the local communications node in a transmission path of the first uplink local signal light, and the second output optical modulator corresponds to the second receiver-side foreign communications node and a wavelength of the first uplink local signal light.

[0016] With reference to the first aspect and the foregoing implementation manner, in a tenth implementation manner of the first aspect, the determining, by the local communications node, at least two local output areas from the output optical modulator array, includes: determining, by the local communications node, the at least two local output areas from the output optical modulator array according to the number of wavelengths of the foreign signal light, the number of wavelengths of the uplink local signal light, and the number of dimensions of the receiver-side foreign communications node.

[0017] With reference to the first aspect and the foregoing implementation manner, in an eleventh implementation manner of the first aspect, the method further includes: obtaining, by the local communications node, a first piece of communication status information, where the first piece of communication status information is used to indicate that at least one of the following parameters needs to be changed: the number of wavelengths of the foreign signal light, the number of channels used by the uplink local signal light or the number of dimensions of the transmitter-side foreign communications node; and changing the at least two local input areas and the global input area according

52663-170

to the first piece of communication status information.

[0018] With reference to the first aspect and the foregoing implementation manner, in a twelfth implementation manner of the first aspect, the method further includes: determining, by the local communications node, a global output area from the output
5 optical modulator array, so that each output optical modulator in the global output area is used to send a downlink local signal light, where the downlink local signal light is a signal light that needs to be sent to the local communications node, and each output optical modulator in the global output area is capable of receiving the signal light transmitted by all input optical modulators in the optical modulator array.

[0019] With reference to the first aspect and the foregoing implementation manner, in a thirteenth implementation manner of the first aspect, the determining, by the local
10 communications node, a global output area from the output optical modulator array, includes: determining, by the local communications node, the global output area from the output optical modulator array according to the number of channels used by the downlink
15 local signal light.

[0020] With reference to the first aspect and the foregoing implementation manner, in a fourteenth implementation manner of the first aspect, the determining, by a local
communications node, at least two local input areas from the input optical modulator array, includes: determining, by the local communications node, the at least two local
20 input areas from the input optical modulator array, so that each input optical modulator in the at least two local input areas is used to receive the downlink local signal light.

[0021] With reference to the first aspect and the foregoing implementation manner, in a fifteenth implementation manner of the first aspect, the method further includes: when a
third input optical modulator in the input optical modulator array receives a first
25 downlink local signal light from a second transmitter-side foreign communications node, performing, by the local communications node, control to cause the third input optical modulator to transmit the first downlink local signal light to a third output optical modulator in the global output area; and obtaining the first downlink local signal light from the third output optical modulator, where the second transmitter-side foreign
30 communications node is a previous-hop communications node of the local

52663-170

communications node in a transmission path of the first downlink local signal light, and the third input optical modulator corresponds to the second transmitter-side foreign communications node and a wavelength of the first downlink local signal light, and the third output optical modulator corresponds to a channel used by the first downlink local signal light.

[0022] With reference to the first aspect and the foregoing implementation manner, in a sixteenth implementation manner of the first aspect, the determining, by a local communications node, at least two local input areas from the input optical modulator array, includes: determining, by the local communications node, the at least two local input areas from the input optical modulator array according to the number of wavelengths of the foreign signal light, the number of wavelengths of the downlink local signal light, and the number of dimensions of the transmitter-side foreign communications node.

[0023] With reference to the first aspect and the foregoing implementation manner, in a seventeenth implementation manner of the first aspect, the method further includes: obtaining, by the local communications node, a second piece of communication status information, where the second piece of communication status information is used to indicate that at least one of the following parameters needs to be changed: the number of wavelengths of the foreign signal light, the number of channels used by the uplink local signal light or the number of dimensions of the receiver-side foreign communications node; and changing the at least two local output areas and the global output area according to the second piece of communication status information.

[0024] According to a second aspect, an optical communications apparatus is provided, where the apparatus includes: an input optical modulator array and an output optical modulator array, where the input optical modulator array includes N input optical modulators and the N input optical modulators are configured to receive a signal light, and the output optical modulator array includes M output optical modulators and the M output optical modulators are configured to send the signal light, where M is greater than the number of output optical modulators that can be covered by one input optical modulator and/or N is greater than the number of input optical modulators capable of

52663-170

covering a same output optical modulator; a controller, configured to determine at least two local input areas from the input optical modulator array, so that each input optical modulator in the at least two local input areas is used to receive a foreign signal light and the foreign signal light is a signal light that comes from a transmitter-side foreign communications node and needs to be sent to a receiver-side foreign communications node; and configured to determine at least two local output areas from the output optical modulator array, so that each output optical modulator in the at least two local output areas is used to send the foreign signal light, where the at least two local input areas correspond to the at least two local output areas in a one-to-one mapping manner, and each input optical modulator in a local input area is capable of transmitting the signal light to each output optical modulator in a corresponding local output area.

[0025] With reference to the second aspect, in a first implementation manner of the second aspect, the number of output optical modulators included in the at least two local output areas is greater than the number of output optical modulators that can be covered by one input optical modulator.

[0026] With reference to the second aspect and the foregoing implementation manner, in a second implementation manner of the second aspect, the number of input optical modulators included in the at least two local input areas is greater than the number of input optical modulators capable of covering the same output optical modulator.

[0027] With reference to the second aspect and the foregoing implementation manner, in a third implementation manner of the second aspect, the controller is further configured to: when a first input optical modulator included in a first local input area of the at least two local input areas receives a first foreign signal light from a first transmitter-side foreign communications node, perform control to cause the first input optical modulator to transmit the first foreign signal light to a first output optical modulator included in a first local output area of the at least two local output areas, so that the first output optical modulator transmits the first foreign signal light to a first receiver-side foreign communications node, where the first local output area corresponds to the first local input area, the first transmitter-side foreign communications node is a previous-hop communications node of the local communications node in a transmission

52663-170

path of the first foreign signal light, the first input optical modulator corresponds to the first transmitter-side foreign communications node and a wavelength of the first foreign signal light, the first receiver-side foreign communications node is a next-hop communications node of the local communications node in the transmission path of the first foreign signal light, and the first output optical modulator corresponds to the first receiver-side foreign communications node and the wavelength of the first foreign signal light.

[0028] With reference to the second aspect and the foregoing implementation manner, in a fourth implementation manner of the second aspect, the controller is specifically configured to determine the at least two local input areas from the input optical modulator array according to the number of dimensions of the transmitter-side foreign communications node and the number of wavelengths of the foreign signal light.

[0029] With reference to the second aspect and the foregoing implementation manner, in a fifth implementation manner of the second aspect, the controller is specifically configured to determine the at least two local output areas from the output optical modulator array according to the number of dimensions of the receiver-side foreign communications node and the number of wavelengths of the foreign signal light.

[0030] With reference to the second aspect and the foregoing implementation manner, in a sixth implementation manner of the second aspect, the controller is further configured to determine a global input area from the input optical modulator array, so that each input optical modulator in the global input area is used to receive an uplink local signal light, where the uplink local signal light is a signal light from the local communications node, and each input optical modulator in the global input area is capable of transmitting the signal light to all output optical modulators in the optical modulator array.

[0031] With reference to the second aspect and the foregoing implementation manner, in a seventh implementation manner of the second aspect, the controller is specifically configured to determine the global input area from the input optical modulator array according to the number of channels used by the uplink local signal light.

[0032] With reference to the second aspect and the foregoing implementation manner,

52663-170

in an eighth implementation manner of the second aspect, the controller is specifically configured to determine the at least two local output areas from the output optical modulator array, so that each output optical modulator in the at least two local output areas is used to send the uplink local signal light.

5 [0033] With reference to the second aspect and the foregoing implementation manner, in a ninth implementation manner of the second aspect, the controller is specifically configured to: when a first uplink local signal light needs to be sent, perform control to cause a second input optical modulator to transmit the first uplink local signal light to a second output optical modulator in the output optical modulator array, so that the second
10 output optical modulator transmits the first uplink local signal light to a second receiver-side foreign communications node, where the second input optical modulator corresponds to a channel used by the first uplink local signal light, the second receiver-side foreign communications node is a next-hop communications node of the local communications node in a transmission path of the first uplink local signal light, and the second output
15 optical modulator corresponds to the second receiver-side foreign communications node and a wavelength of the first uplink local signal light.

[0034] With reference to the second aspect and the foregoing implementation manner, in a tenth implementation manner of the second aspect, the controller is specifically configured to determine the at least two local output areas from the output optical
20 modulator array according to the number of wavelengths of the foreign signal light, the number of wavelengths of the uplink local signal light, and the number of dimensions of the receiver-side foreign communications node.

[0035] With reference to the second aspect and the foregoing implementation manner, in an eleventh implementation manner of the second aspect, the controller is further
25 configured to obtain, by the local communications node, a first piece of communication status information, where the first piece of communication status information is used to indicate that at least one of the following parameters needs to be changed: the number of wavelengths of the foreign signal light, the number of channels used by the uplink local signal light or the number of dimensions of the transmitter-side foreign communications
30 node; and configured to change the at least two local input areas and the global input area

52663-170

according to the first piece of communication status information.

[0036] With reference to the second aspect and the foregoing implementation manner, in a twelfth implementation manner of the second aspect, the controller is further configured to determine a global output area from the output optical modulator array, so that each output optical modulator in the global output area is used to send a downlink local signal light, where the downlink local signal light is a signal light that needs to be sent to the local communications node, and each output optical modulator in the global output area is capable of receiving the signal light transmitted by all input optical modulators in the optical modulator array.

[0037] With reference to the second aspect and the foregoing implementation manner, in a thirteenth implementation manner of the second aspect, the controller is specifically configured to determine the global output area from the output optical modulator array according to the number of channels used by the downlink local signal light.

[0038] With reference to the second aspect and the foregoing implementation manner, in a fourteenth implementation manner of the second aspect, the controller is specifically configured to determine the at least two local input areas from the input optical modulator array, so that each input optical modulator in the at least two local input areas is used to receive the downlink local signal light.

[0039] With reference to the second aspect and the foregoing implementation manner, in a fifteenth implementation manner of the second aspect, the controller is specifically configured to: when a third input optical modulator in the input optical modulator array receives a first downlink local signal light from a second transmitter-side foreign communications node, perform control to cause the third input optical modulator to transmit the first downlink local signal light to a third output optical modulator in the global output area; and obtain the first downlink local signal light from the third output optical modulator, where the second transmitter-side foreign communications node is a previous-hop communications node of the local communications node in a transmission path of the first downlink local signal light, and the third input optical modulator corresponds to the second transmitter-side foreign communications node and a wavelength of the first downlink local signal light, and the third output optical modulator

52663-170

corresponds to a channel used by the first downlink local signal light.

[0040] With reference to the second aspect and the foregoing implementation manner, in a sixteenth implementation manner of the second aspect, the controller is specifically configured to determine the at least two local input areas from the input optical modulator array according to the number of wavelengths of the foreign signal light, the number of wavelengths of the downlink local signal light, and the number of dimensions of the transmitter-side foreign communications node.

[0041] With reference to the second aspect and the foregoing implementation manner, in a seventeenth implementation manner of the second aspect, the controller is further configured to obtain a second piece of communication status information, where the second piece of communication status information is used to indicate that at least one of the following parameters needs to be changed: the number of wavelengths of the foreign signal light, the number of channels used by the uplink local signal light or the number of dimensions of the receiver-side foreign communications node; and configured to change the at least two local output areas and the global output area according to the second piece of communication status information.

[0042] In the optical communications method and apparatus according to the embodiments of the present invention, by enabling an input optical modulator array to include at least two local input areas, enabling an output optical modulator array to include at least two local output areas, enabling each local input area to correspond to each local output area in a one-to-one mapping manner, and enabling each input optical modulator in a local input area to transmit a signal light to each output optical modulator in a corresponding local output area, switchable dimensions in each local input area and each local output area correspond to a cross-connect capability of the optical modulator, and therefore the overall number of switchable dimensions of the apparatus is greater than the cross-connect capability of a single optical modulator, and network requirements and user requirements are met on condition that a structure of the single optical modulator is not changed.

52663-170

BRIEF DESCRIPTION OF DRAWINGS

[0043] To describe the technical solutions in the embodiments of the present invention more clearly, the following briefly introduces the accompanying drawings required for describing the embodiments. Apparently, the accompanying drawings in the following description show merely some embodiments of the present invention, and a person of ordinary skill in the art may still derive other drawings from these accompanying drawings without creative efforts.

[0044] FIG. 1 is a schematic flowchart of an optical communications method according to an embodiment of the present invention;

10 [0045] FIG. 2 is a schematic diagram of a system structure of an ROADM, provided by an embodiment of the present invention, to which an optical communications method is applicable;

15 [0046] FIG. 3 is a schematic diagram of a configuration structure of an input optical modulator array and an output optical modulator array according to an embodiment of the present invention;

[0047] FIG. 4 is a schematic diagram of a configuration structure of an input optical modulator array and an output optical modulator array according to another embodiment of the present invention;

20 [0048] FIG. 5 is a schematic diagram of a configuration structure of an input optical modulator array and an output optical modulator array according to still another embodiment of the present invention;

25 [0049] FIG. 6a is a schematic diagram of a division manner for local input areas according to an embodiment of the present invention; and FIG. 6b is a schematic diagram of a division manner for local output areas according to an embodiment of the present invention;

[0050] FIG. 7 is a schematic diagram of a cross-connect capability of an optical modulator according to an embodiment of the present invention;

30 [0051] FIG. 8a is a schematic diagram of a division manner for a global input area according to an embodiment of the present invention; and FIG. 8b is a schematic diagram of a division manner for a global output area according to an embodiment of the present

52663-170

invention;

[0052] FIG. 9 is a schematic diagram of relationships between each local input area and a global input area and each input port, and relationships between each local output area and a global output area and each output port according to an embodiment of the present invention;

[0053] FIG. 10 is a schematic structural diagram of an optical communications apparatus according to an embodiment of the present invention; and

[0054] FIG. 11 is a schematic structural diagram of an optical communications device according to an embodiment of the present invention.

DESCRIPTION OF EMBODIMENTS

[0055] The following clearly describes the technical solutions in the embodiments of the present invention with reference to the accompanying drawings in the embodiments of the present invention. Apparently, the described embodiments are a part rather than all of the embodiments of the present invention. All other embodiments obtained by a person of ordinary skill in the art based on the embodiments of the present invention without creative efforts shall fall within the protection scope of the present invention.

[0056] The technical solution of the present invention is applicable to various communications systems that can use signal light to transmit data, for example, a Global System for Mobile Communications (GSM, Global System of Mobile communication), a Code Division Multiple Access (CDMA, Code Division Multiple Access) system, Wideband Code Division Multiple Access (WCDMA, Wideband Code Division Multiple Access), General Packet Radio Service (GPRS, General Packet Radio Service), and Long Term Evolution (LTE, Long Term Evolution).

[0057] FIG. 1 is a schematic flowchart of an optical communications method 100 according to an embodiment of the present invention. The method 100 is executed on a communications node that includes an input optical modulator array and an output optical modulator array, where the input optical modulator array includes N input optical modulators and the N input optical modulators are configured to receive a signal light, and the output optical modulator array includes M output optical modulators and the M

52663-170

output optical modulators are configured to send the signal light, where M is greater than the number of output optical modulators that can be covered by one input optical modulator and/or N is greater than the number of input optical modulators capable of covering a same output optical modulator. As shown in FIG. 1, the method 100 includes

5 the following steps:

[0058] S110. A local communications node determines at least two local input areas from the input optical modulator array, so that each input optical modulator in the at least two local input areas is used to receive a foreign signal light and the foreign signal light is a signal light that comes from a transmitter-side foreign communications node and needs

10 to be sent to a receiver-side foreign communications node.

[0059] S120. The local communications node determines at least two local output areas from the output optical modulator array, so that each output optical modulator in the at least two local output areas is used to send the foreign signal light, where the at least two local input areas correspond to the at least two local output areas in a one-to-one

15 mapping manner, and each input optical modulator in a local input area is capable of transmitting the signal light to each output optical modulator in a corresponding local output area.

[0060] Specifically, the optical communications method 100 in this embodiment of the present invention is applicable to various apparatuses and devices that use multiple

20 input optical modulators and input optical modulators to switch a direction dimension (or, in other words, a transmission path) of a signal light. A reconfigurable optical add/drop multiplexer (ROADM, Reconfigurable Optical Add/Drop Multiplexer) may be used as an example of the apparatuses and devices. Unless otherwise specified, in the following description, a process in which the optical communications method 100 according to the

25 embodiments of the present invention is applied to the ROADM is used as an example.

[0061] The following describes a structure of the ROADM first.

[0062] FIG. 2 is a schematic diagram of a system structure of an ROADM, provided by an embodiment of the present invention, to which an optical communications method is applicable. As shown in FIG. 2, an ROADM 200 may include an optical cross connect

30 (OXC, Optical Cross Connect) 210, an add/drop wavelength module 220, a controller

52663-170

230, multiple multiplexers 240, and multiple demultiplexers 250, where the OXC 210, the add/drop wavelength module 220, the multiplexers 240, and the demultiplexers 250 may be connected by fiber jumper.

[0063] The multiplexer 240 is configured to multiplex multiple signals (of different wavelengths) from the OXC 210 into a wavelength division multiplexing (WDM, Wavelength Division Multiplexing) signal, and output the signal to a next-hop node (an example of the receiver-side foreign communications node) of the ROADM.

[0064] It should be noted that, in this embodiment of the present invention, a value obtained by multiplying the number of dimensions (or, in other words, direction dimensions) of the receiver-side foreign communications node by the number of wavelengths of the signal light is the same as the number of the multiplexers 240. That is, one multiplexer 240 is configured to transmit a signal light of one wavelength in one dimension. Here the dimensions of the receiver-side foreign communications node specifically refer to the number of a type of nodes under a preset rule (or, in other words, the number of fibers connected to the ROADM), where the nodes can connect to the ROADM for communication, and the preset rule may be area-specific, for example, specific to a city level, a province level, or a country level; or may be entity-specific, for example, a receiver-side foreign communications node is a dimension or a group of receiver-side foreign communications nodes is a dimension.

[0065] It should be understood that the dimension sorting manners listed above are merely exemplary, and the present invention is not specially limited thereto, and all other sorting manners capable of differentiating communications nodes shall fall within the protection scope of the present invention.

[0066] The demultiplexer 250 demultiplexes a WDM signal from a previous-hop node (a transmitter-side foreign communications node) into multiple signals (of different wavelengths), and outputs the signals to the OXC 210.

[0067] Similarly, a value obtained by multiplying the number of dimensions (or, in other words, direction dimensions) of the transmitter-side foreign communications node by the number of wavelengths of the signal light is the same as the number of the demultiplexers 250. That is, one demultiplexer 250 is configured to receive the signal

52663-170

light of one wavelength in one dimension. Here the dimensions of the transmitter-side foreign communications node specifically refer to the number of a type of nodes under a preset rule, where the nodes can connect to the ROADM for communication.

[0068] It should be noted that, in this embodiment of the present invention, a basis
5 (the preset rule) for sorting dimensions of the transmitter-side foreign communications node may be the same as or different from that for sorting dimensions of the receiver-side foreign communications node, which is not specially limited by the present invention. Therefore, the number of multiplexers 240 may be the same as or different from the number of demultiplexers 250, which is not specially limited by the present invention.

[0069] In addition, in this embodiment of the present invention, the multiplexers 240
10 and the demultiplexers 250 are connected to fibers, and one fiber is generally connected to one multiplexer or demultiplexer. Therefore, the dimensions of the foreign communications node may be determined according to the number of fibers connected to the ROADM. For example, the number of dimensions of the receiver-side foreign
15 communications node may be the same as the number of input fibers connected to the ROADM.

[0070] The add/drop wavelength module 220 includes multiple transmitters and multiple receivers.

[0071] The number of the transmitters may be greater than or equal to the number of
20 channels (or, in other words, paths) used by an add-wavelength signal light that needs to be processed by the ROADM apparatus. Here the add-wavelength signal light (that is, uplink local signal light) refers to a signal light sent (by a transmitter) from a local node, where the uplink local signal light may be a signal light sent to a foreign communications node or a signal light sent to a local communications node, which is not specially limited
25 by the present invention. It should be noted that, in this embodiment of the present invention, the channels used by the uplink local signal light may be set arbitrarily. For example, the number of channels used by the uplink local signal light may be the same as the number of wavelengths of the uplink local signal light. That is, one transmitter is configured only to send the uplink local signal lights of one wavelength. Alternatively, a
30 time division multiplexing manner may be used so that one transmitter sends the uplink

52663-170

local signal lights of one wavelength in one time segment but sends the uplink local signal lights of another wavelength in another time segment.

[0072] The number of the receivers may be greater than or equal to the number of channels (or, in other words, paths) used by a drop-wavelength signal light that needs to be processed by the ROADM. Here the drop-wavelength signal light (that is, a downlink local signal light) refers to a signal light that is received (by a receiver) and needs to be sent to a local node, where the downlink local signal light may be a signal light sent by a foreign communications node or a signal light sent by a local communications node, which is not specially limited by the present invention. It should be noted that, in this embodiment of the present invention, the channels used by the downlink local signal light may be set arbitrarily. For example, the number of channels used by the downlink local signal light may be the same as the number of wavelengths of the downlink local signal light. That is, one receiver is configured only to receive the downlink local signal lights of one wavelength. Alternatively, a time division multiplexing manner may be used so that one receiver receives the downlink local signal lights of one wavelength in one time segment but receives the downlink local signal lights of another wavelength in another time segment.

[0073] In this embodiment of the present invention, the transmitter and the receiver may be devices separated from each other, or integrated into a same device, which is not specially limited by the present invention. In addition, some transmitters may be short-circuited to some receivers by using jumpers, so as to implement wavelength conversion for local nodes.

[0074] The OXC 210 may include an input fiber array 211, an input microlens array 212, an input spatial optical modulator array (an example of the input optical modulator array) 213, a mirror 214, an output spatial optical modulator array (an example of the output optical modulator array) 215, an output microlens array 216, and an output fiber array 217.

[0075] The input fiber array 211 is configured to receive the signal light (from the demultiplexer 250 or the transmitter of the add/drop wavelength module 220). In this embodiment of the present invention, the signal light is provided with multiple

52663-170

dimensions (from different demultiplexers 250 or transmitters) and has different wavelengths. Therefore, the input fiber array 211 has multiple input fiber units, and the number of input fiber units included in the input fiber array 211 is equal to a sum of the number of transmitters of the add/drop wavelength module 220 and a product of
5 multiplying the number of demultiplexers 250 by the number of output wavelengths of a demultiplexer. That is, one input fiber unit is configured only to receive the signal light of one wavelength in one dimension.

[0076] The input microlens array 212 is configured to couple and output the signal light, which is output from the input fiber array 211, to the input spatial optical modulator
10 array 213. Similarly, the input microlens array 212 has multiple input microlens units, and the input microlens units correspond to the input fiber units in a one-to-one mapping manner.

[0077] The input spatial optical modulator array 213 has multiple input spatial optical modulators (or, in other words, input spatial optical modulator units), and the input
15 microlens units correspond to the input spatial optical modulators in a one-to-one mapping manner. The input spatial optical modulator array 213 is configured to receive a signal light (from the input microlens array 212), and adjust the input spatial optical modulator (an example of the input optical modulator) of the received signal light according to a control command (from the controller 230, whose functions will be
20 detailed later), so as to output the signal light to the mirror 214 and a specified output spatial optical modulator (an example of the output optical modulator) in the output spatial optical modulator array 215.

[0078] The mirror 214 is configured to output the signal light (for example, by reflecting) to the output spatial optical modulator array 215. In addition, in this
25 embodiment of the present invention, the mirror 214 may further perform Fourier transformation on an optical signal.

[0079] In this embodiment of the present invention, the receiver-side foreign communications node for the signal light has multiple dimensions, or, in other words, the signal light is sent to different multiplexers 250 or receivers. Therefore, the output spatial
30 optical modulator array 215 has multiple output spatial optical modulators (or, in other

52663-170

words, output spatial optical modulator units), and one output spatial optical modulator is configured only to receive and send a signal light of a specified wavelength in one dimension. In addition, the output spatial optical modulator array 215 is configured to: according to a control command (from the controller 230), enable the specified output
5 spatial optical modulator to receive the signal light (from a specified input spatial optical modulator in the input spatial optical modulator array 213), adjust a reflection angle of the signal light, and output the signal light to the microlens array 216.

[0080] The output microlens array 216 is configured to couple and output the signal light to the output fiber array 217. Similarly, the output microlens array 216 has multiple
10 output microlens units, and the output microlens units correspond to the output spatial optical modulators in a one-to-one mapping manner.

[0081] The output fiber array 217 is configured to receive the signal light from the output microlens array 216, and output the signal light to the multiplexer 240 or the receiver. Similarly, the output fiber array 217 has multiple output fiber units, and the
15 output fiber units correspond to the output microlens units in a one-to-one mapping manner.

[0082] That is, in this embodiment of the present invention, the input fiber units, the input microlens units, and the input spatial optical modulators correspond to one another in a one-to-one mapping manner. The output fiber units, the output microlens units, and
20 the output spatial optical modulators correspond to one another in a one-to-one mapping manner.

[0083] Integration of the fiber array and the microlens array in this embodiment is also referred to as a collimator lens array.

[0084] In this embodiment of the present invention, a demultiplexer or transmitter, an
25 input fiber unit, and an input microlens unit may form an input port in the present invention. Here, it should be noted that a demultiplexer or transmitter may generate signal lights of multiple wavelengths, and therefore the demultiplexers or transmitters corresponding to different input ports may be the same. However, the input fiber unit and the input microlens unit corresponding to one input port are different from those
30 corresponding to another input port.

52663-170

[0085] In addition, a multiplexer or receiver, an output fiber unit, and an output microlens unit may form an output port in the present invention. Here, it should be noted that a multiplexer or receiver may receive signal lights of multiple wavelengths, and therefore the multiplexers or receivers corresponding to different output ports may be the same. However, the output fiber unit and the output microlens unit corresponding to one output port are different from those corresponding to another output port.

[0086] It should be understood that the input port and the output port listed above (or, in other words, structures of the input optical modulator array and the output optical modulator array in the ROADM) are merely exemplary, and the present invention is not limited thereto. Other structures shall fall within the protection scope of the present invention provided that a signal light input by a previous-hop communications node (an example of the transmitter-side foreign communications node) can be transmitted to a specified input optical modulator in the input optical modulator array, and enable the input optical modulator to transmit the signal light to a specified output optical modulator in the output optical modulator array, and enable the output optical modulator to transmit the signal light to a next-hop communications node (an example of the receiver-side foreign communications node).

[0087] In this embodiment of the present invention, spatial configuration positions of the input fiber array 211, the input microlens array 212, the mirror 214, the output microlens array 216, and the output fiber array 217 in the ROADM may change properly according to a configuration structure of the input spatial optical modulator array 213 and the output spatial optical modulator array 215.

[0088] For example, FIG. 3 is a schematic diagram of a configuration structure of an input optical modulator array and an output optical modulator array according to an embodiment of the present invention. As shown in FIG. 3, in this embodiment of the present invention, the input spatial optical modulator array 213 and the output spatial optical modulator array 215 may be configured on a same plane, and the input collimator lens array and the output collimator lens array may be located on both sides of the ROADM.

[0089] For another example, FIG. 4 is a schematic diagram of a configuration

52663-170

structure of an input optical modulator array and an output optical modulator array according to another embodiment of the present invention. As shown in FIG. 4, according to actual optical path design requirements, the mirror 214 may not be used, but the input spatial optical modulator array 213 is deployed opposite to the output spatial optical modulator array 215, so that the input spatial optical modulator array 213 can output a signal light to the output spatial optical modulator array 215 directly.

[0090] For another example, FIG. 5 is a schematic diagram of a configuration structure of an input optical modulator array and an output optical modulator array according to still another embodiment of the present invention. As shown in FIG. 5, the mirror 214 may be used so that hardware configuration is interchangeable between an input side and an output side. That is, the input collimator lens array and the output collimator lens array are located on the same side of the ROADM, and an emergent direction of the signal light of the input collimator lens array is parallel to an incident direction of the signal light of the output collimator lens array.

[0091] In addition, due to reversibility of an optical path, in this embodiment of the present invention, the output port of the OXC may also implement functions of an input port, and the corresponding input port may also implement functions of the output port. Further, the input optical modulator array and the output optical modulator array may also implement functions of each other.

[0092] In this embodiment of the present invention, a structure of an input optical modulator (a unit that forms the input optical modulator array) may be the same as or similar to that of an output optical modulator (a unit that forms the output optical modulator array). The following describes an implementation manner of functions by using the input optical modulator as an example.

[0093] For example, in this embodiment of the present invention, the input optical modulator may be implemented by using a micro-electro-mechanical system (MEMS, Micro-Electro-Mechanical System) technology. The MEMS technology is a technology of highly integrating a micro-electro-mechanical apparatus and a control circuit in a tiny space on a silicon-based or non-silicon-based material to form a mechatronics device or system, where a geometric size or an operation size of the micro-electro-mechanical

52663-170

apparatus is of only a micron, submicron or even nanometer magnitude. The optical modulator implemented by using the MEMS technology uses an electrostatic force or another control force to cause mechanical motion of a micromirror, so that a beam that hits the micromirror deflects to any direction. In a case in which the optical modulator of the present invention is implemented by using the MEMS technology, the controller may use a control instruction to control a micromechanical structure and drive the optical modulator (microlens) to rotate, so as to deflect the optical path and switch dimensions (or, in other words, transmission paths) of the signal light.

[0094] For another example, in this embodiment of the present invention, the input optical modulator may be implemented by using a liquid crystal on silicon (LCoS, Liquid Crystal On Silicon) technology. The LCoS technology achieves a purpose of separating lights by adjusting reflection angles of lights of different wavelengths according to principles of liquid crystal grating. Because no removable part exists, the LCoS technology is rather reliable. The LCoS technology changes the reflection angles by means of refractive index change control of a liquid crystal unit, which facilitates expansion and upgrade. Different channels correspond to different areas of a spatial optical modulator (liquid crystal) array. By adjusting a phase of a flare, a transmission direction of a light is changed, so as to achieve purposes of switching ports and adjusting attenuation.

[0095] For another example, in this embodiment of the present invention, the input optical modulator may be implemented by using a liquid crystal (LC, liquid crystal) technology. In the optical modulator implemented by using the LC technology, after an incident light passes through a birefringent crystal, the incident light is divided into two lights of polarization states. After one light passes through a half-wave plate, the polarization states of the two lights are the same, and then the light hits the spatial optical modulator (liquid crystal module). By adjusting a voltage of the birefringent crystal, an arrangement structure of the liquid crystals (angles of internal molecules of the crystals) is changed, and therefore the refractive index of the crystal is changed, and a light source is output as lights from different angles. After the light passes through each layer of a liquid crystal, two directions are available for selection. After the light passes through

52663-170

multiple layers of liquid crystals, multiple optical paths are available for selection.

[0096] For another example, in this embodiment of the present invention, the input optical modulator may be implemented by using a digital light processing (DLP, Digital Light Processing) technology. An internal structure of the optical modulator implemented
5 by using the DLP technology is similar to the internal structure of the optical modulator implemented by using the MEMS technology, and light energy is switched by deflecting the microlens. A difference is that the signal light corresponds to multiple mirrors for reflection. Therefore, multiple microlenses on the spatial optical modulator array need to be coordinated to vibrate, so as to reflect the signal light from the same destination. By
10 using a rotation angle of a mirror array, a reflection direction of the light changes, and a purpose of switching channels is achieved.

[0097] It should be understood that the implementation manners of the optical modulators (including the input optical modulator and the output optical modulator) listed above are merely exemplary, and the present invention is not limited thereto, and
15 all other methods and structures capable of deflecting a spatial transmission path of a signal light to multiple directions shall fall within the protection scope of the present invention.

[0098] In this embodiment of the present invention, the input optical modulator and the input optical modulator may be controlled by the controller 230 to switch the spatial
20 transmission path of the signal light.

[0099] Specifically, in this embodiment of the present invention, a fixed mapping relationship exists between input optical modulators and output optical modulators. That is, for a signal light (mainly foreign signal light), it is appropriate that only one transmission path exists (a next-hop communications node is specified by the system).
25 That is, a source of the light (a previous-hop communications node) may control an input optical modulator to which the signal light is cast (for example, a rotation angle of the input optical modulator), so as to switch the signal light to a specified output optical modulator (corresponding to the next-hop communications node specified by the system).

[0100] Alternatively, in this embodiment of the present invention, the controller may
30 also extract data carried in the signal light, and parse the data to obtain a destination

52663-170

address. According to the destination address, the controller controls the input optical modulator to which the signal light is cast (for example, the rotation angle of the input optical modulator), so as to switch the signal light to an output optical modulator corresponding to the destination address (or, in other words, the next-hop
5 communications node).

[0101] It should be understood that the abovementioned control performed by the controller 230 on the input optical modulator and the input optical modulator in switching the spatial transmission path of the signal light is merely exemplary, and the present invention is not limited thereto. All other control methods capable of accurately
10 transmitting the signal light to the next-hop communications node fall within the protection scope of the present invention. For example, the controller 230 may control only the input optical modulator (such as the rotation angle), or may control both the input optical modulator (such as the rotation angle) and the output optical modulator (such as the rotation angle).

[0102] It should be noted that, in this embodiment of the present invention, the controller 230 may be independent of the OXC 210, and connected to the OXC 210 for communication by using a communications protocol and a communications cable, and may perform control according to a signaling message. Alternatively, the controller 230 may be embedded into the OXC 210, and serve as a microprocessor to control the OXC
20 210.

[0103] In addition, in the prior art, to ensure that the signal light is accurately transmitted to the next-hop communications node, one input optical modulator in the input optical modulator array needs to be capable of covering all output optical modulators in the output optical modulator array (or, in other words, one input optical
25 modulator in the input optical modulator array needs to be capable of transmitting the signal light to all output optical modulators in the modulator array). Therefore, a cross-connect capability of a single optical modulator restricts a size of the optical modulator array, and further restricts a communication capability of the communications node, which cannot meet network requirements and user requirements.

[0104] In a case in which an optical communications method 100 of the present

52663-170

invention is used, one input optical modulator does not need to cover all output optical modulators in the output optical modulator array, but needs only to cover the output optical modulators in a corresponding local output area (which will be detailed later). Therefore, a size of the input optical modulator array and a size of the output optical modulator array can be set according to network requirements and user requirements. That is, in this embodiment of the present invention, the number (M) of input optical modulators included in an input optical modulator array is greater than the number of input optical modulators capable of covering one output optical modulator, and the number (N) of output optical modulators included in an output optical modulator array is greater than the number of output optical modulators that can be covered by one input optical modulator.

[0105] It should be noted that, in this embodiment of the present invention, the cross-connect capability of the optical modulator (the number of input optical modulators capable of covering one output optical modulator, or the number of output optical modulators that can be covered by one input optical modulator) depends on the technology for implementing the optical modulators and an arrangement manner of the optical modulators in the optical modulator array (for example, an arrangement interval between one another). On condition that the optical modulators have the same cross-connect capability, the technical effects of the present invention are noticeable against the prior art.

[0106] The following describes a specific procedure of the optical communications method 100.

[0107] In this embodiment of the present invention, a communications node may have only a transit (or, in other words, transparent transmission) function. That is, the communications node is configured only to send all received signal light to other communications nodes rather than to serve as a destination receiver side of data carried on any received signal light or to generate and send the signal light to other communications nodes proactively, or, in other words, the communications node is equipped with only a multiplexer and a demultiplexer, but is not equipped with a receiver or a transmitter (that is, scenario 1), or the communications node not only has the transit

52663-170

function but may also serve as a source communications node or a destination communications node of the signal light (that is, scenario 2). The following describes actions taken in the foregoing two scenarios.

[0108] Scenario 1:

5 **[0109]** Generally, in an ROADM, the number of demultiplexers is the same as the number of multiplexers, that is, the number of dimensions of the transmitter-side foreign communications node is the same as the number of dimensions of the receiver-side foreign communications node, or, in other words, the number of input ports is the same as the number of output ports; in addition, the structure of the input optical modulator is the
10 same as that of the output optical modulator, or, in other words, the cross-connect capability of the input optical modulator (the number of output optical modulators that can be covered by one input optical modulator) is the same as the cross-connect capability of the output optical modulator (the number of input optical modulators capable of covering the same output optical modulator).

15 **[0110]** The following describes actions taken in this scenario.

[0111] The controller 230 may divide an input spatial optical modulator array 213 into multiple non-overlapped local input areas according to a preset rule (a first preset rule).

[0112] The controller 230 may divide an output spatial optical modulator array 215
20 into multiple non-overlapped local output areas according to a preset rule (a second preset rule).

[0113] The local input areas correspond to the local output areas in a one-to-one mapping manner. That is, the input optical modulators in a local input area are configured only to transmit a signal light to the output optical modulators in a corresponding local
25 output area. Here, "non-overlapped" means that one input optical modulator belongs to only one local input area, and one output optical modulator belongs to only one local output area.

[0114] Optionally, the number of output optical modulators included in the at least two local output areas is greater than the number of output optical modulators that can be
30 covered by one input optical modulator.

52663-170

[0115] In addition, the number of input optical modulators included in the at least two local input areas is greater than the number of input optical modulators capable of covering the same output optical modulator.

[0116] Optionally, the determining, by the local communications node, at least two
5 local input areas from the input optical modulator array, includes:

determining, by the local communications node, the at least two local input areas from the input optical modulator array according to the number of dimensions of the transmitter-side foreign communications node and the number of wavelengths of the foreign signal light.

10 **[0117]** In addition, the determining, by the local communications node, at least two local output areas from the output optical modulator array, includes:

determining, by the local communications node, the at least two local output areas from the output optical modulator array according to the number of dimensions of the receiver-side foreign communications node and the number of wavelengths of the
15 foreign signal light.

[0118] Specifically, in this embodiment of the present invention, the number and a range of local input areas and local input areas (or, in other words, the number of optical modulators included) may be determined according to the cross-connect capability of an optical modulator, the number of dimensions of the foreign communications node, and
20 the number of wavelengths of the signal light.

[0119] For example, if the number of wavelengths used by the signal light (foreign signal light) is 4 (that is, there are 4 wavelengths that are different from one another) and the number of dimensions of the foreign communications node (receiver-side foreign communications node and transmitter-side foreign communications node) is 4 (that is, 4
25 demultiplexers are arranged); then in theory, the local communications node may receive 4×4 signal lights, and 4×4 input optical modulators are required to receive all the signal lights. Similarly, the local communications node may need to send 4×4 signal lights, and 4×4 output optical modulators are required to send all the signal lights.

[0120] In this case, if the cross-connect capability of one optical modulator
30 (specifically, an output optical modulator) is 2×2, which means that one output optical

52663-170

modulator is only capable of receiving the signal lights (2×2 signal lights) transmitted by 2×2 input optical modulators in a specified range and that one input optical modulator is only capable of transmitting the signal lights (2×2 signal lights) to 2×2 output optical modulators in a specified range; then in the prior art, in order to ensure accuracy and reliability of transmission, a size of the input optical modulators can only be 2×2 , and a size of the output optical modulators can only be 2×2 , which cannot meet network requirements.

[0121] By contrast, in this embodiment of the present invention, a size of the input optical modulator array may be set to 4×4 , and the input optical modulator array may be divided into 4 local input areas, each of which includes 2×2 input optical modulators.

[0122] In addition, correspondingly, the output optical modulator array is also divided into 4 local output areas, each of which includes 2×2 output optical modulators.

[0123] Generally, the cross-connect capability of the optical modulator is greater than the number of wavelengths of the signal light or the number of dimensions of the communications node. Therefore, in this embodiment of the present invention, the following division manner may be used:

[0124] Manner 1

[0125] Each optical modulator in a local area (local output area or local input area) can be enabled to transmit signal lights of a same wavelength in different dimensions.

[0126] For example, signal lights of wavelength a are transmitted in dimensions (4 dimensions) between a local output area a (including 4 output optical modulators) and a local input area a (including 4 input optical modulators); signal lights of wavelength b are transmitted in dimensions (4 dimensions) between a local output area b (including 4 output optical modulators) and a local input area b (including 4 input optical modulators); signal lights of wavelength c are transmitted in dimensions (4 dimensions) between a local output area c (including 4 output optical modulators) and a local input area c (including 4 input optical modulators); and signal lights of wavelength d are transmitted in dimensions (4 dimensions) between a local output area d (including 4 output optical modulators) and a local input area d (including 4 input optical modulators).

[0127] The foregoing manner 1 may be intuitively expressed as a port matching

52663-170

manner described in Table 1.

Table 1

Area	Port
Local input/output area a	Wavelengths 1–4 on demultiplexer 1 or wavelengths 1–4 on multiplexer 1
Local input/output area b	Wavelengths 1–4 on demultiplexer 2 or wavelengths 1–4 on multiplexer 2
Local input/output area c	Wavelengths 1–4 on demultiplexer 3 or wavelengths 1–4 on multiplexer 3
Local input/output area d	Wavelengths 1–4 on demultiplexer 4 or wavelengths 1–4 on multiplexer 4

[0128] Manner 2

5 **[0129]** Each optical modulator in a local area (local output area or local input area) can be enabled to transmit signal lights of different wavelengths in a same dimension.

[0130] For example, signal lights of wavelengths (4 wavelengths) are transmitted in a dimension a between the local output area a (including 4 output optical modulators) and the local input area a (including 4 input optical modulators); signal lights of wavelengths
 10 (4 wavelengths) are transmitted in a dimension b between the local output area b (including 4 output optical modulators) and the local input area b (including 4 input optical modulators); signal lights of wavelengths (4 wavelengths) are transmitted in a dimension c between the local output area c (including 4 output optical modulators) and the local input area c (including 4 input optical modulators); and signal lights of
 15 wavelengths (4 wavelengths) are transmitted in a dimension d between the local output area d (including 4 output optical modulators) and the local input area d (including 4 input optical modulators).

[0131] The foregoing manner 2 may be intuitively expressed as a port matching manner described in Table 2.

52663-170

Table 2

Area	Port
Local input/output area a	Wavelength 1 on demultiplexers 1–4 or wavelength 1 on multiplexers 1–4
Local input/output area b	Wavelength 2 on demultiplexers 1–4 or wavelength 2 on multiplexers 1–4
Local input/output area c	Wavelength 3 on demultiplexers 1–4 or wavelength 3 on multiplexers 1–4
Local input/output area d	Wavelength 4 on demultiplexers 1–4 or wavelength 4 on multiplexers 1–4

[0132] It should be understood that the division method listed above is merely exemplary, and the present invention is not limited thereto. For example, the port matching manner for the local input area may be the same as or different from that for the corresponding local output area. For example, the local input area may use the port matching manner described in Table 1 but the local output area may use the port matching manner described in Table 2.

[0133] In addition, if the cross-connect capability of the optical modulator is smaller than the number of wavelengths of the signal light or the number of dimensions of the communications node, it is also possible to cause one local area to match only ports of some dimensions and some wavelengths.

[0134] FIG. 6a is a schematic diagram of the foregoing division manner, and FIG. 6b is a schematic diagram of a division manner for a local output area according to an embodiment of the present invention.

[0135] As shown in FIG. 6a, the input spatial optical modulator array 213 may be divided into four local input areas, and the output spatial optical modulator array 215 may be divided into four local output areas, where the local input area a corresponds to the local output area a, the local input area b corresponds to the local output area b, the local input area c corresponds to the local output area c, and the local input area d corresponds to the local output area d.

[0136] In addition, in this embodiment of the present invention, the following

52663-170

scenarios are not excluded: in an ROADM, the number of demultiplexers is different from the number of multiplexers, that is, the number of dimensions of the transmitter-side foreign communications node is different from the number of dimensions of the receiver-side foreign communications node (or, in other words, the number of input ports is different from the number of output ports); and/or, the cross-connect capability of the input optical modulator (the number of output optical modulators that can be covered by one input optical modulator) is different from the cross-connect capability of the output optical modulator (the number of input optical modulators capable of covering one output optical modulator).

10 [0137] The following describes actions taken in this scenario.

[0138] The controller 230 may divide an input spatial optical modulator array 213 into multiple non-overlapped local input areas according to a preset rule (a first preset rule).

15 [0139] The controller 230 may divide an output spatial optical modulator array 215 into multiple non-overlapped local output areas according to a preset rule (a second preset rule).

[0140] The local input areas correspond to the local output areas in a one-to-one mapping manner. That is, the input optical modulators in a local input area are configured only to transmit a signal light to the output optical modulators in a corresponding local output area. Here, "non-overlapped" means that one input optical modulator belongs to only one local input area, and one output optical modulator belongs to only one local output area.

25 [0141] Optionally, the first preset rule and the second preset rule are determined according to a first value or a second value, whichever is larger, and according to a third value or a fourth value, whichever is larger, where the first value is a product of the number of dimensions of the transmitter-side foreign communications node and the number of wavelengths of the foreign signal light, the second value is a product of the number of dimensions of the receiver-side foreign communications node and the number of wavelengths of the foreign signal light, the third value is the number of output optical modulators that can be covered by one input optical modulator, and the fourth value is the

30

52663-170

number of input optical modulators capable of covering one output optical modulator.

[0142] Specifically, in this embodiment of the present invention, the number of local input areas needs to be the same as the number of local output areas as a result of division. Therefore, in order to ensure transmission reliability, the number and the range of local input areas and local input areas (or, in other words, the number of optical modulators included) may be determined according to the cross-connect capability of an input optical modulator or the cross-connect capability of an output optical modulator, whichever is smaller, and according to the number of optical modulators required by the input optical modulator array or the number of optical modulators required by the output optical modulator array, whichever is greater.

[0143] For example, if the number of wavelengths used by the input signal light (an example of the foreign signal light) is 4 (that is, there are 4 wavelengths that are different from one another) and the number of dimensions of the transmitter-side foreign communications node is 4 (that is, 4 demultiplexers are arranged); then in theory, the local communications node may receive 4×4 signal lights, and 4×4 input optical modulators are required to receive all signal lights.

[0144] If the number of wavelengths used by the output signal light (another example of the foreign signal light) is 8 (that is, there are 8 wavelengths that are different from one another) and the number of dimensions of the receiver-side foreign communications node is 8 (that is, 8 multiplexers are arranged); then in theory, the local communications node may need to send 8×8 signal lights, and 8×8 output optical modulators are required to receive all signal lights.

[0145] If the cross-connect capability of one output optical modulator is 4×4 , that is, one output optical modulator is only capable of receiving the signal lights (4×4 signal lights) transmitted by 4×4 input optical modulators in a specified range, and, if the cross-connect capability of one input optical modulator is 2×2 , that is, one input optical modulator is only capable of transmitting the signal lights (2×2 signal lights) to 2×2 output optical modulators in a specified range; then in order to ensure transmission reliability, the output optical modulator array and the input optical modulator array need to be divided into $8 \times 8/2 \times 2 = 16$ areas.

52663-170

[0146] In this case, each local input area of the input optical modulator array includes 2×2 optical modulators. For reasons described above, the local communications node requires 4×4 input optical modulators to receive all signal lights, that is, requires only $4 \times 4/2 \times 2 = 4$ local areas to receive all the signal lights. Therefore, in the input optical modulator array, it is possible that all input optical modulators in the 4 areas match the same input port but match different output ports.

[0147] Each local input area of the output optical modulator array includes 2×2 optical modulators. Because the local communications node may receive 4×4 signal lights but need to send 8×8 signal lights, it is possible that in the input optical modulator array, all input optical modulators in the 4 areas match exactly the same input port but match different output ports.

[0148] The specific port matching manner is the same as or similar to the manner described in Table 1 or Table 2, which, for avoiding repetition, is not described herein any further.

[0149] Optionally, in this embodiment of the present invention, a position of a local input area in the input optical modulator array is consistent with a position of a corresponding local output area in the output optical modulator array.

[0150] Specifically, in this embodiment of the present invention, because structures of all optical modulators are consistent, to facilitate transmission of the signal light, the position (relative position) of a local input area in the input optical modulator array may be consistent with the position (relative position) of a corresponding local output area in the output optical modulator array. For example, if a local input area is located in an upper left corner of the input optical modulator array, the corresponding local output area is also located in the upper left corner of the output optical modulator array. Therefore, when the input optical modulator in each local input area transmits a signal light to the output optical modulator in the corresponding local output area, all required adjustments (for example, a microlens deflection angle of the optical modulator) fall within the same range, which facilitates configuration and improves practicality of the optical communications method 100 in this embodiment of the present invention.

[0151] Optionally, in this embodiment of the present invention, ranges of the at least

52663-170

two local input areas in the input optical modulator array are consistent, and ranges of the at least two local output areas in the output optical modulator array are consistent.

[0152] Specifically, in this embodiment of the present invention, in order that each output optical modulator in the local output area is capable of receiving a signal light
5 transmitted by all input optical modulators in the corresponding local input area, the number of the input optical modulators in the local input area should be smaller than or equal to the cross-connect capability of the output optical modulator. Therefore, the number of input optical modulators in each local input area may be configured according to the number of input ports and the cross-connect capability of the output optical
10 modulator. That is, all local input areas may include the same number of input optical modulators or different numbers of input optical modulators.

[0153] However, if the ranges of the local input areas in the input optical modulator array are consistent (or, in other words, all local input areas include the same number of input optical modulators), when a fault occurs in a local input area, the local input area
15 can be replaced by a normal local input area by changing a matched port, which further improves practicality and reliability of the optical communications method 100 in this embodiment of the present invention. Similarly, the ranges of the local output areas in the output optical modulator array may be consistent.

[0154] The following describes actions of a local communications node in receiving a
20 signal light sent by a previous-hop communications node and sending the signal light to a next-hop communications node.

[0155] Optionally, the method further includes:

when a first input optical modulator included in a first local input area of the at least two local input areas receives a first foreign signal light from a first transmitter-side foreign communications node, performing, by the local communications node,
25 control to cause the first input optical modulator to transmit the first foreign signal light to a first output optical modulator included in a first local output area of the at least two local output areas, so that the first output optical modulator transmits the first foreign signal light to a first receiver-side foreign communications node, where the first local
30 output area corresponds to the first local input area, the first transmitter-side foreign

52663-170

communications node is a previous-hop communications node of the local communications node in a transmission path of the first foreign signal light, the first input optical modulator corresponds to the first transmitter-side foreign communications node and a wavelength of the first foreign signal light, the first receiver-side foreign communications node is a next-hop communications node of the local communications node in the transmission path of the first foreign signal light, and the first output optical modulator corresponds to the first receiver-side foreign communications node and the wavelength of the first foreign signal light.

[0156] Specifically, in this embodiment of the present invention, each demultiplexer is connected to a fiber, and therefore when a demultiplexer A receives a signal light from a corresponding fiber A, the signal light may be sent directly (by using an input fiber unit A and an input microlens unit A) to a corresponding input optical modulator A (an example of the first input optical modulator). Here, it should be noted that, in this embodiment of the present invention, the local input area in which the input optical modulator A is located corresponds to a wavelength of the signal light and a dimension (such as a direction of a transmission path) of a previous-hop node.

[0157] In this case, the controller may, for example, parse data carried in the signal light to obtain a destination communications node of the signal light, and then determine the next-hop communications node of the signal light and an output optical modulator B (an example of the first output optical modulator) corresponding to the next-hop communications node. Here, it should be noted that, in this embodiment of the present invention, the local input area in which the input optical modulator A is located corresponds to the local output area of the output optical modulator B.

[0158] Subsequently, the controller may adjust angles of the input optical modulator A and the output optical modulator B (such as an angle of a microlens), and transmit the signal light to the output optical modulator B.

[0159] The output optical modulator B transmits the signal light (by using an output microlens unit B and an output fiber unit B) to a corresponding multiplexer B, so that the signal light can be sent to the next-hop communications node by using the fiber B.

[0160] Scenario 2:

52663-170

[0161] First, the following describes actions of the communications node serving as a source communications node of the signal light (that is, the local communications node is equipped with a transmitter).

[0162] Optionally, the method 100 further includes:

5 [0163] The method further includes:

determining, by the local communications node, a global input area from the input optical modulator array, so that each input optical modulator in the global input area is used to receive an uplink local signal light, where the uplink local signal light is a signal light from the local communications node, and each input optical modulator in the
10 global input area is capable of transmitting the signal light to all output optical modulators in the optical modulator array.

[0164] Specifically, in this embodiment of the present invention, when the local communications node serves as a source communications node of the signal light, the signal light needs to be transmitted to each output port. Therefore, the input optical
15 modulator (that is, the optical modulator in the global input area) intended for transmitting the signal light (the uplink local signal light) needs to be capable of covering the entire output optical modulator array, and a port that matches the input optical modulator needs to be allocated to the transmitter.

[0165] Optionally, in this embodiment of the present invention, the global input area
20 is located at a center of the input optical modulator array.

[0166] Specifically, because all optical modulators have a same structure, the input optical modulator located at the center of the input optical modulator array can cover the largest number of output optical modulators. Therefore, in this embodiment of the present invention, the global input area may be arranged at the center of the input optical
25 modulator array.

[0167] Optionally, the determining, by the local communications node, a global input area from the input optical modulator array, includes:

determining, by the local communications node, the global input area from the input optical modulator array according to the number of channels used by the uplink
30 local signal light.

52663-170

[0168] Specifically, in this embodiment of the present invention, the number of the input optical modulators included in the global input area may be determined according to the number of channels (or, in other words, paths) configured for the local communications node to send a signal light, so that one input optical modulator in the global input area obtains the signal light by using only one channel. In addition, in this embodiment of the present invention, a time division multiplexing manner may be used so that one channel can send signal lights of different wavelengths at different times. Therefore, the number of channels may be smaller than or equal to the number of wavelengths of the signal lights sent by the local communications node.

[0169] The determining, by the local communications node, at least two local output areas from the output optical modulator array, includes:

determining, by the local communications node, the at least two local output areas from the output optical modulator array, so that each output optical modulator in the at least two local output areas is configured to send the uplink local signal light.

[0170] Specifically, in this embodiment of the present invention, because the local communications node needs to send a signal light to the foreign communications node, each output optical modulator in the determined local output area is further configured to receive the signal light from the global input area, and similarly, the output port corresponding to each output optical modulator is also configured to send the signal light from the global input area.

[0171] It is assumed that the cross-connect capability of the input optical modulator is $X \times Y$, that is, the input optical modulator is capable of covering 2^X output optical modulators in the output optical modulator array in a horizontal direction and covering 2^Y output optical modulators in the output optical modulator array in a vertical direction.

For example, as shown in FIG. 7, the input optical modulator (for example, position thereof) corresponding to the output optical modulator located at the center of the output optical modulator array (hereinafter referred to as a central output optical modulator) is capable of covering $\pm X$ output optical modulators centered on the central output optical modulator in the horizontal direction and covering $\pm Y$ spatial optical modulator units centered on the central output optical modulator in the vertical direction, where, it should

52663-170

be noted that " $\pm$ " in " $\pm X$ " and " $\pm Y$ " refers to two opposite directions.

[0172] As shown in FIG. 8a, if a size of the global input area is $M \times N$ (that is, including $M \times N$ input optical modulators, where $M \leq X$, $N \leq Y$), in order that each input optical modulator in the global input area covers all output optical modulators in the output optical modulator array, a maximum size of the output optical modulator array may be $(2X - M) \times (2Y - N)$.

[0173] The determining, by the local communications node, at least two local output areas from the output optical modulator array, includes:

determining, by the local communications node, the at least two local output areas from the output optical modulator array according to the number of wavelengths of the foreign signal light, the number of wavelengths of the uplink local signal light, and the number of dimensions of the receiver-side foreign communications node.

[0174] Specifically, after the maximum size of the entire output optical modulator array is determined, the output optical modulator array may be divided into local output areas. Because the output optical modulator array also needs to transmit a signal light from the global input area, the actual size of the output optical modulator array needs to take into account the number of wavelengths of the signal light from the global input area. It should be noted that because the global input area is located at the center of the input optical modulator array, the output optical modulator array may, for example, be divided equally into four local output areas with the same range. The manner of matching local input areas and ports may be the same as or similar to the matching manner described in scenario 1, which, for avoiding repetition, is not described herein any further.

[0175] It should be understood that the division manner of the local output areas listed above is merely exemplary, and the present invention is not limited thereto, and other division manners are appropriate as long as the range and the size of each local output area satisfy the cross-connect capability of the input optical modulator in the corresponding local input area.

[0176] The following describes actions of a local communications node in sending a local signal light to a next-hop communications node.

52663-170

[0177] Optionally, the method further includes:

when a first uplink local signal light needs to be sent, performing, by the local communications node, control to cause the second input optical modulator to transmit the first uplink local signal light to a second output optical modulator in the output optical modulator array, so that the second output optical modulator transmits the first uplink local signal light to a second receiver-side foreign communications node, where the second input optical modulator corresponds to a channel used by the first uplink local signal light, the second receiver-side foreign communications node is a next-hop communications node of the local communications node in a transmission path of the first uplink local signal light, and the second output optical modulator corresponds to the second receiver-side foreign communications node and a wavelength of the first uplink local signal light.

[0178] Specifically, in this embodiment of the present invention, data that needs to be sent may be encapsulated to generate a signal light. The process thereof may be the same as or similar to the prior art, and, for avoiding repetition, is not described herein any further.

[0179] Subsequently, the signal light may be sent by a transmitter over a specified channel, and therefore an input optical modulator C (an example of the second input optical modulator, located in the global input area) corresponding to the channel receives the signal light.

[0180] In this case, the controller may, for example, parse data carried in the signal light to obtain a destination communications node of the signal light, and then determine the next-hop communications node of the signal light and an output optical modulator D (an example of the second output optical modulator) corresponding to the next-hop communications node.

[0181] Subsequently, the controller may adjust angles of the input optical modulator C and the output optical modulator D (such as an angle of a microlens), and transmit the signal light to the output optical modulator D.

[0182] The output optical modulator D transmits the signal light (by using an output microlens unit D and an output fiber unit D) to a corresponding multiplexer D, so that the

52663-170

signal light can be sent to the next-hop communications node by using the fiber D.

[0183] Optionally, the method further includes:

obtaining, by the local communications node, a first piece of communication status information, where the first piece of communication status information is used to indicate that at least one of the following parameters needs to be changed: the number of wavelengths of the foreign signal light, the number of channels used by the uplink local signal light or the number of dimensions of the transmitter-side foreign communications node; and

changing the at least two local input areas and the global input area according to the first piece of communication status information.

[0184] Specifically, in this embodiment of the present invention, the global input area is capable of covering all output optical modulators in the output optical modulator array. Therefore, the global input area and the local input areas may be adjusted according to a current communication state (an example of the first piece of communication status information). For example, if the number of dimensions of the transmitter-side foreign communications node (a previous-hop communications node) or the number of wavelengths of the foreign signal light increases, a part or all of the input optical modulators in the global input area may be allocated to one or more local input areas.

[0185] For example, if the cross-connect capability of both the input optical modulator and the output optical modulator is 12×12 , a maximum size of the input optical modulator array is 24×24 when the global input area is set. When the input optical modulator array is divided initially, for example, if the transmitter-side foreign communications node has 4 dimensions, the number of wavelengths of the signal light is 49, and 100 channels are configured for the local communications node; then the input optical modulator array is divided into four local input areas of a 14×14 size and a global input area of a 10×10 size. For example, when the number of wavelengths of the signal light changes from 49 to 64 and only 64 channels need to be configured for the local communications node, the global input area may be reduced to 8×8 , and the input optical modulator array is re-divided into four local input areas of a 16×16 size.

[0186] It should be understood that the change manner listed above is merely

52663-170

exemplary, and the present invention is not limited thereto. For example, if the local input area includes an input optical modulator capable of covering all output optical modulators in the output optical modulator array, the input optical modulator may also be allocated to the global input area when the number of channels used by the local communications
5 node increases.

[0187] According to the optical communications method in this embodiment of the present invention, because a global input area capable of covering the entire output optical modulator array is set, the range of each local input area can be adjusted flexibly according to the network status, user requirements and the like. That is, in a case in which
10 the number of dimensions of the foreign communications node or the number of wavelengths used by the signal light changes, the change can be handled flexibly, which significantly improves practicality of the optical communications method of the present invention.

[0188] The following describes actions of the communications node serving as a
15 destination communications node of the signal light (that is, the local communications node is equipped with a receiver).

[0189] Optionally, the method 100 further includes:

determining, by the local communications node, a global output area from the output optical modulator array, so that each output optical modulator in the global output
20 area is used to send a downlink local signal light, where the downlink local signal light is signal light that needs to be sent to the local communications node, and each output optical modulator in the global output area is capable of receiving the signal light transmitted by all input optical modulators in the optical modulator array.

[0190] Specifically, in this embodiment of the present invention, when the local
25 communications node serves as a destination communications node of the signal light, the signal light from each input port needs to be transmitted to the receiver. Therefore, the output optical modulator (that is, the optical modulator in a global output area) intended for transmitting the signal light (the downlink local signal light) needs to be capable of covering the entire input optical modulator array, and a port that matches the output
30 optical modulator needs to be allocated to the receiver.

52663-170

[0191] Optionally, in this embodiment of the present invention, the global output area is located at a center of the output optical modulator array.

[0192] Specifically, because all optical modulators have a same consistent structure, the output optical modulator located at the center of the output optical modulator array
 5 can cover the largest number of input optical modulators. Therefore, in this embodiment of the present invention, the global output area may be arranged at the center of the output optical modulator array.

[0193] Optionally, the determining, by the local communications node, a global output area from the output optical modulator array, includes:

10 determining, by the local communications node, the global output area from the output optical modulator array according to the number of channels used by the downlink local signal light.

[0194] Specifically, in this embodiment of the present invention, the number of the output optical modulators included in the global output area may be determined
 15 according to the number of channels (or, in other words, paths) configured for the local communications node to receive a signal light, so that one output optical modulator in the global output area sends the signal light by using only one channel. In addition, in this embodiment of the present invention, a time division multiplexing manner may be used so that one channel can send signal lights of different wavelengths at different times.
 20 Therefore, the number of channels may be smaller than or equal to the number of wavelengths of the signal light sent to the local communications node.

[0195] Optionally, the determining, by the local communications node, at least two local input areas from the input optical modulator array, includes:

25 determining, by the local communications node, the at least two local input areas from the input optical modulator array, so that each input optical modulator in the at least two local input areas is configured to receive the downlink local signal light.

[0196] Specifically, in this embodiment of the present invention, because the local communications node needs to receive a signal light sent by the foreign communications node, each input optical modulator in the determined local input area is further
 30 configured to send the signal light to the global output area, and similarly, the input port

52663-170

corresponding to each input optical modulator is also configured to send the signal light to the global output area.

[0197] It is assumed that the cross-connect capability of the output optical modulator is $X' \times Y'$, that is, the output optical modulator is capable of covering $2X'$ output optical modulators in the output optical modulator array in a horizontal direction and covering $2Y'$ output optical modulators in the output optical modulator array in a vertical direction. For example, as shown in FIG. 7, the output optical modulator (for example, position thereof) corresponding to the output optical modulator located at the center of the output optical modulator array (hereinafter referred to as a central output optical modulator) is capable of covering $\pm X'$ output optical modulators centered on the central output optical modulator in the horizontal direction and covering $\pm Y'$ spatial optical modulator units centered on the central output optical modulator in the vertical direction, where, it should be noted that " $\pm$ " in " $\pm X'$ " and " $\pm Y'$ " refers to two opposite directions.

[0198] As shown in FIG. 8b, if a size of the global output area is $M' \times N'$ (that is, including $M' \times N'$ output optical modulators, where $M' \leq X'$, $N' \leq Y'$), in order that each output optical modulator in the global output area covers all output optical modulators in the output optical modulator array, a maximum size of the output optical modulator array may be $(2X' - M') \times (2Y' - N')$.

[0199] Optionally, the determining, by the local communications node, at least two local input areas from the input optical modulator array, includes:

determining, by the local communications node, the at least two local input areas from the input optical modulator array according to the number of wavelengths of the foreign signal light, the number of wavelengths of the downlink local signal light, and the number of dimensions of the transmitter-side foreign communications node.

[0200] Specifically, after the maximum size of the entire output optical modulator array is determined, the output optical modulator array may be divided into local output areas. Because the input optical modulator array transmits a signal light to the global output area, the actual size of the input optical modulator array needs to take into account the number of wavelengths of signal light from the global output area. It should be noted that because the global output area is located at the center of the output optical modulator

52663-170

array, the input optical modulator array may, for example, be divided equally into four local input areas with the same range. The manner of matching local input areas and ports may be the same as or similar to the matching manner described in scenario 1, which, for avoiding repetition, is not described herein any further.

5 [0201] It should be understood that the division manner of the local input areas listed above is merely exemplary, and the present invention is not limited thereto, and other division manners are appropriate as long as the range and the size of each local input area satisfy the cross-connect capability of the output optical modulator in the corresponding local output area.

10 [0202] FIG. 9 is a schematic diagram of relationships between each local input area and a global input area and each input port, and relationships between each local output area and a global output area and each output port according to an embodiment of the present invention. As shown in FIG. 9, in this embodiment of the present invention, the global input area may be allocated to each transmitter in an add/drop wavelength module,
15 local input areas may be allocated to demultiplexers respectively, the global input area may be allocated to each receiver in the add/drop wavelength module, and local output areas may be allocated to multiplexers respectively. It should be noted that in FIG. 9, a dotted arrow indicates a transmission path of signal light in an ROADM.

[0203] The following describes actions of a local communications node to receive a
20 signal light sent by a previous-hop communications node.

[0204] Optionally, the method further includes:

when a third input optical modulator in the input optical modulator array receives a first downlink local signal light from a second transmitter-side foreign communications node, performing, by the local communications node, control to enable
25 the third input optical modulator to transmit the first downlink local signal light to a third output optical modulator in the global output area; and obtaining the first downlink local signal light from the third output optical modulator, where the second transmitter-side foreign communications node is a previous-hop communications node of the local communications node in a transmission path of the first downlink local signal light, and
30 the third input optical modulator corresponds to the second transmitter-side foreign

52663-170

communications node and a wavelength of the first downlink local signal light, and the third output optical modulator corresponds to a channel used by the first downlink local signal light.

[0205] Specifically, in this embodiment of the present invention, each demultiplexer
 5 is connected to each fiber, and therefore, when a demultiplexer E receives signal light from the corresponding fiber E, the signal light may be sent directly (by using an input fiber unit E and an input microlens unit E) to the corresponding input optical modulator E (an example of the third input optical modulator). Here, it should be noted that, in this
 10 embodiment of the present invention, the local input area in which the input optical modulator E is located corresponds to a wavelength of the signal light and a dimension (such as a direction of a transmission path) of a previous-hop node.

[0206] In this case, the controller may, for example, parse data carried in the signal light to know that the signal light needs to be sent to a local node, and, according to a wavelength of the signal light, determine a channel for transmitting the signal light, and
 15 further determine an output optical modulator F (an example of the third output optical modulator) in the global output area to which the signal light needs to be sent.

[0207] Subsequently, the controller may adjust angles of the input optical modulator E and the output optical modulator F (such as an angle of a microlens), and transmit the signal light to the output optical modulator F.

[0208] The output optical modulator F transmits the signal light (by using an output microlens unit F and an output fiber unit F) to a corresponding receiver, and the receiver may decapsulate the signal light and obtain desired data. The process thereof may be the same as or similar to the prior art, and, for avoiding repetition, is not described herein any further.

[0209] Optionally, the method further includes:

the determining, by the local communications node, at least two local input areas from the input optical modulator array, includes:

determining, by the local communications node, the at least two local input areas from the input optical modulator array according to the number of wavelengths of
 30 the foreign signal light, the number of wavelengths of the downlink local signal light, and

52663-170

the number of dimensions of the transmitter-side foreign communications node.

[0210] Specifically, in this embodiment of the present invention, the global output area is capable of covering all input optical modulators in the input optical modulator array. Therefore, the global output area and the local output areas may be adjusted according to a current communication state (an example of the second piece of communication status information). For example, if the number of dimensions of the receiver-side foreign communications node (a next-hop communications node) or the number of wavelengths of the foreign signal light increases, a part or all of the output optical modulators in the global output area may be allocated to one or more local output areas.

[0211] For example, if the cross-connect capability of both the input optical modulator and the output optical modulator is 12×12 , a maximum size of the output optical modulator array is 24×24 when the global output area is set. When the output optical modulator array is divided initially, for example, if the receiver-side foreign communications node has 4 dimensions, the number of wavelengths of the signal light is 49, and 100 channels are configured for the local communications node; then the output optical modulator array is divided into four local output areas of a 14×14 size and a global output area of a 10×10 size. For example, when the number of wavelengths of the signal light changes from 49 to 64 and only 64 channels need to be configured for the local communications node, the global output area may be reduced to 8×8 , and the output optical modulator array is re-divided into four local output areas of a 16×16 size.

[0212] It should be understood that the change manner listed above is merely exemplary, and the present invention is not limited thereto. For example, if the local output area includes an output optical modulator capable of covering all output optical modulators in the output optical modulator array, the output optical modulator may also be allocated to the global output area when the number of channels used by the local communications node increases.

[0213] According to the optical communications method in this embodiment of the present invention, because a global output area capable of covering the entire input optical modulator array is set, the range of each local output area can be adjusted flexibly

52663-170

according to the network status, user requirements and the like. That is, in a case in which the number of dimensions of the foreign communications node or the number of wavelengths used by the signal light changes, the change can be handled flexibly, which significantly improves practicality of the optical communications method of the present invention.

[0214] The foregoing has detailed the optical communications method according to the embodiments of the present invention with reference to FIG. 1 to FIG. 9. The following describes in detail an optical communications apparatus according to an embodiment of the present invention with reference to FIG. 10.

[0215] FIG. 10 is a schematic block diagram of an optical communications apparatus 300 according to an embodiment of the present invention. As shown in FIG. 10, the apparatus 300 includes:

an input optical modulator array 310 and an output optical modulator array 320, where the input optical modulator array 310 includes N input optical modulators and the N input optical modulators are configured to receive a signal light, and the output optical modulator array 320 includes M output optical modulators and the M output optical modulators are configured to send the signal light, where M is greater than the number of output optical modulators that can be covered by one input optical modulator and/or N is greater than the number of input optical modulators capable of covering a same output optical modulator; and

a controller 330, configured to determine at least two local input areas from the input optical modulator array 310, so that each input optical modulator in the at least two local input areas is configured to receive foreign signal light and the foreign signal light is signal light that comes from a transmitter-side foreign communications node and needs to be sent to a receiver-side foreign communications node; and

configured to determine at least two local output areas from the output optical modulator array 320, so that each output optical modulator in the at least two local output areas is configured to send the foreign signal light, where the at least two local input areas correspond to the at least two local output areas in a one-to-one mapping manner, and each input optical modulator in a local input area is capable of transmitting the signal

52663-170

light to each output optical modulator in a corresponding local output area.

[0216] Optionally, the number of output optical modulators included in the at least two local output areas is greater than the number of output optical modulators that can be covered by one input optical modulator.

5 **[0217]** Optionally, the number of input optical modulators included in the at least two local input areas is greater than the number of input optical modulators capable of covering the same output optical modulator.

[0218] Optionally, the controller 330 is further configured to: when a first input optical modulator included in a first local input area of the at least two local input areas
10 receives a first foreign signal light from a first transmitter-side foreign communications node, perform control to cause the first input optical modulator to transmit the first foreign signal light to a first output optical modulator included in a first local output area of the at least two local output areas, so that the first output optical modulator transmits the first foreign signal light to a first receiver-side foreign communications node, where
15 the first local output area corresponds to the first local input area, the first transmitter-side foreign communications node is a previous-hop communications node of the local communications node in a transmission path of the first foreign signal light, the first input optical modulator corresponds to the first transmitter-side foreign communications node and a wavelength of the first foreign signal light, the first receiver-side foreign
20 communications node is a next-hop communications node of the local communications node in the transmission path of the first foreign signal light, and the first output optical modulator corresponds to the first receiver-side foreign communications node and the wavelength of the first foreign signal light.

[0219] Optionally, the controller 330 is specifically configured to determine at least
25 two local input areas from the input optical modulator array 310 according to the number of dimensions of the transmitter-side foreign communications node and the number of wavelengths of the foreign signal light.

[0220] Optionally, the controller 330 is specifically configured to determine at least
30 two local output areas from the output optical modulator array 320 according to the number of dimensions of the receiver-side foreign communications node and the number

52663-170

of wavelengths of the foreign signal light.

[0221] Optionally, the controller 330 is further configured to determine a global input area from the input optical modulator array 310, so that each input optical modulator in the global input area is used to receive an uplink local signal light, where the uplink local signal light is signal light from the local communications node, and each input optical modulator in the global input area is capable of transmitting the signal light to all output optical modulators in the optical modulator array.

[0222] Optionally, the controller 330 is specifically configured to determine the global input area from the input optical modulator array 310 according to the number of channels used by the uplink local signal light.

[0223] Optionally, the controller 330 is specifically configured to determine at least two local output areas from the output optical modulator array 320, so that each output optical modulator in the at least two local output areas is configured to send the uplink local signal light.

[0224] Optionally, the controller 330 is specifically configured to: when a first uplink local signal light needs to be sent, perform control to cause the second input optical modulator to transmit the first uplink local signal light to a second output optical modulator in the output optical modulator array 320, so that the second output optical modulator transmits the first uplink local signal light to a second receiver-side foreign communications node, where the second input optical modulator corresponds to a channel used by the first uplink local signal light, the second receiver-side foreign communications node is a next-hop communications node of the local communications node in a transmission path of the first uplink local signal light, and the second output optical modulator corresponds to the second receiver-side foreign communications node and a wavelength of the first uplink local signal light.

[0225] Optionally, the controller 330 is specifically configured to determine at least two local output areas from the output optical modulator array 320 according to the number of wavelengths of the foreign signal light, the number of wavelengths of the uplink local signal light, and the number of dimensions of the receiver-side foreign communications node.

52663-170

[0226] Optionally, the controller 330 is further configured to obtain, by the local communications node, a first piece of communication status information, where the first piece of communication status information is used to indicate that at least one of the following parameters needs to be changed: the number of wavelengths of the foreign signal light, the number of channels used by the uplink local signal light or the number of dimensions of the transmitter-side foreign communications node; and

configured to change the at least two local input areas and the global input area according to the first piece of communication status information.

[0227] Optionally, the controller 330 is further configured to determine a global output area from the output optical modulator array 320, so that each output optical modulator in the global output area is used to send a downlink local signal light, where the downlink local signal light is signal light that needs to be sent to the local communications node, and each output optical modulator in the global output area is capable of receiving the signal light transmitted by all input optical modulators in the optical modulator array.

[0228] Optionally, the controller 330 is specifically configured to determine the global output area from the output optical modulator array 320 according to the number of channels used by the downlink local signal light.

[0229] Optionally, the controller 330 is specifically configured to determine at least two local input areas from the input optical modulator array 310, so that each input optical modulator in the at least two local input areas is configured to receive the downlink local signal light.

[0230] Optionally, the controller 330 is specifically configured to: when a third input optical modulator in the input optical modulator array 310 receives a first downlink local signal light from a second transmitter-side foreign communications node, perform control to cause the third input optical modulator to transmit the first downlink local signal light to a third output optical modulator in the global output area; and obtain the first downlink local signal light from the third output optical modulator, where the second transmitter-side foreign communications node is a previous-hop communications node of the local communications node in a transmission path of the first downlink local signal light, and

52663-170

the third input optical modulator corresponds to the second transmitter-side foreign communications node and a wavelength of the first downlink local signal light, and the third output optical modulator corresponds to a channel used by the first downlink local signal light.

5 [0231] Optionally, the controller 330 is specifically configured to determine at least two local input areas from the input optical modulator array 310 according to the number of wavelengths of the foreign signal light, the number of wavelengths of the downlink local signal light, and the number of dimensions of the transmitter-side foreign communications node.

10 [0232] Optionally, the controller 330 is further configured to obtain a second piece of communication status information, where the second piece of communication status information is used to indicate that at least one of the following parameters needs to be changed: the number of wavelengths of the foreign signal light, the number of channels used by the uplink local signal light or the number of dimensions of the receiver-side
15 foreign communications node; and

configured to change the at least two local output areas and the global output area according to the second piece of communication status information.

[0233] The optical communications apparatus 300 (specifically, the controller 350) according to the embodiments of the present invention may correspond to an execution
20 body of the method 100 according to the embodiments of the present invention, and units, that is, modules, in the apparatus 300 and the foregoing and other operations and/or functions are intended for implementing the corresponding procedure in the method 100 in FIG. 1, which, for brevity, is not repeated herein any further.

[0234] According to the optical communications apparatus in this embodiment of the
25 present invention, because a global output area capable of covering the entire input optical modulator array is set, the range of each local output area can be adjusted flexibly according to the network status, user requirements and the like. That is, in a case in which the number of dimensions of the foreign communications node or the number of wavelengths used by the signal light changes, the change can be handled flexibly, which
30 significantly improves practicality of the optical communications method of the present

52663-170

invention.

[0235] The foregoing has detailed the optical communications method according to the embodiments of the present invention with reference to FIG. 1 to FIG. 9. The following describes in detail an optical communications device according to an
 5 embodiment of the present invention with reference to FIG. 11.

[0236] FIG. 11 is a schematic block diagram of an optical communications device 400 according to an embodiment of the present invention. As shown in FIG. 11, the device 400 includes:

an input optical modulator array 410 and an output optical modulator array
 10 420, where the input optical modulator array 410 includes N input optical modulators and the N input optical modulators are configured to receive a signal light, and the output optical modulator array 420 includes M output optical modulators and the M output optical modulators are configured to send the signal light, where M is greater than the number of output optical modulators that can be covered by one input optical modulator
 15 and/or N is greater than the number of input optical modulators capable of covering a same output optical modulator;

a bus 430 connected to the input optical modulator array 410 and the output optical modulator array 420;

a processor 440 connected to the bus; and

20 a memory 450 connected to the bus.

[0237] The processor 440 uses the bus 430 and invokes a program stored in the memory 450 to determine at least two local input areas from the input optical modulator array 410, so that each input optical modulator in the at least two local input areas is configured to receive a foreign signal light and the foreign signal light is a signal light
 25 that comes from a transmitter-side foreign communications node and needs to be sent to a receiver-side foreign communications node.

[0238] The processor 440 is configured to determine at least two local output areas from the output optical modulator array 420, so that each output optical modulator in the at least two local output areas is configured to send the foreign signal light, where the at
 30 least two local input areas correspond to the at least two local output areas in a one-to-one

52663-170

mapping manner, and each input optical modulator in a local input area is capable of transmitting the signal light to each output optical modulator in a corresponding local output area.

[0239] Optionally, the number of output optical modulators included in the at least two local output areas is greater than the number of output optical modulators that can be covered by one input optical modulator.

[0240] Optionally, the number of input optical modulators included in the at least two local input areas is greater than the number of input optical modulators capable of covering the same output optical modulator.

[0241] Optionally, the processor 440 is further configured to: when a first input optical modulator included in a first local input area of the at least two local input areas receives a first foreign signal light from a first transmitter-side foreign communications node, perform control to cause the first input optical modulator to transmit the first foreign signal light to a first output optical modulator included in a first local output area of the at least two local output areas, so that the first output optical modulator transmits the first foreign signal light to a first receiver-side foreign communications node, where the first local output area corresponds to the first local input area, the first transmitter-side foreign communications node is a previous-hop communications node of the local communications node in a transmission path of the first foreign signal light, the first input optical modulator corresponds to the first transmitter-side foreign communications node and a wavelength of the first foreign signal light, the first receiver-side foreign communications node is a next-hop communications node of the local communications node in the transmission path of the first foreign signal light, and the first output optical modulator corresponds to the first receiver-side foreign communications node and the wavelength of the first foreign signal light.

[0242] Optionally, the processor 440 is specifically configured to determine at least two local input areas from the input optical modulator array 410 according to the number of dimensions of the transmitter-side foreign communications node and the number of wavelengths of the foreign signal light.

[0243] Optionally, the processor 440 is specifically configured to determine at least

52663-170

two local output areas from the output optical modulator array 420 according to the number of dimensions of the receiver-side foreign communications node and the number of wavelengths of the foreign signal light.

[0244] Optionally, the processor 440 is further configured to determine a global input area from the input optical modulator array 410, so that each input optical modulator in the global input area is used to receive an uplink local signal light, where the uplink local signal light is a signal light from the local communications node, and each input optical modulator in the global input area is capable of transmitting the signal light to all output optical modulators in the optical modulator array.

[0245] Optionally, the processor 440 is specifically configured to determine the global input area from the input optical modulator array 410 according to the number of channels used by the uplink local signal light.

[0246] Optionally, the processor 440 is specifically configured to determine at least two local output areas from the output optical modulator array 420, so that each output optical modulator in the at least two local output areas is configured to send the uplink local signal light.

[0247] Optionally, the processor 440 is specifically configured to: when a first uplink local signal light needs to be sent, perform control to cause the second input optical modulator to transmit the first uplink local signal light to a second output optical modulator in the output optical modulator array 420, so that the second output optical modulator transmits the first uplink local signal light to a second receiver-side foreign communications node, where the second input optical modulator corresponds to a channel used by the first uplink local signal light, the second receiver-side foreign communications node is a next-hop communications node of the local communications node in a transmission path of the first uplink local signal light, and the second output optical modulator corresponds to the second receiver-side foreign communications node and a wavelength of the first uplink local signal light.

[0248] Optionally, the processor 440 is specifically configured to determine at least two local output areas from the output optical modulator array 420 according to the number of wavelengths of the foreign signal light, the number of wavelengths of the

52663-170

uplink local signal light, and the number of dimensions of the receiver-side foreign communications node.

[0249] Optionally, the processor 440 is further configured to obtain, by the local communications node, a first piece of communication status information, where the first
5 piece of communication status information is used to indicate that at least one of the following parameters needs to be changed: the number of wavelengths of the foreign signal light, the number of channels used by the uplink local signal light or the number of dimensions of the transmitter-side foreign communications node; and

configured to change the at least two local input areas and the global input
10 area according to the first piece of communication status information.

[0250] Optionally, the processor 440 is further configured to determine a global output area from the output optical modulator array 420, so that each output optical modulator in the global output area is used to send a downlink local signal light, where the downlink local signal light is a signal light that needs to be sent to the local
15 communications node, and each output optical modulator in the global output area is capable of receiving the signal light transmitted by all input optical modulators in the optical modulator array.

[0251] Optionally, the processor 440 is specifically configured to determine the global output area from the output optical modulator array 420 according to the number
20 of channels used by the downlink local signal light.

[0252] Optionally, the processor 440 is specifically configured to determine at least two local input areas from the input optical modulator array 410, so that each input optical modulator in the at least two local input areas is configured to receive the downlink local signal light.

25 [0253] Optionally, the processor 440 is specifically configured to: when a third input optical modulator in the input optical modulator array 410 receives a first downlink local signal light from a second transmitter-side foreign communications node, perform control to cause the third input optical modulator to transmit the first downlink local signal light to a third output optical modulator in the global output area; and obtain the first downlink
30 local signal light from the third output optical modulator, where the second transmitter-

52663-170

side foreign communications node is a previous-hop communications node of the local communications node in a transmission path of the first downlink local signal light, and the third input optical modulator corresponds to the second transmitter-side foreign communications node and a wavelength of the first downlink local signal light, and the
 5 third output optical modulator corresponds to a channel used by the first downlink local signal light.

[0254] Optionally, the processor 440 is specifically configured to determine at least two local input areas from the input optical modulator array 410 according to the number of wavelengths of the foreign signal light, the number of wavelengths of the downlink
 10 local signal light, and the number of dimensions of the transmitter-side foreign communications node.

[0255] Optionally, the processor 440 is further configured to obtain a second piece of communication status information, where the second piece of communication status information is used to indicate that at least one of the following parameters needs to be
 15 changed: the number of wavelengths of the foreign signal light, the number of channels used by the uplink local signal light or the number of dimensions of the receiver-side foreign communications node; and

configured to change the at least two local output areas and the global output area according to the second piece of communication status information.

[0256] In this embodiment of the present invention, the processor may also be referred to as a CPU. The memory may include a read-only memory and a random access memory, and provides instructions and data to the processor. A part of the memory may also include a non-volatile random access memory (NVRAM). In a specific application, a data transmission device may be embedded into, or itself may be, a standard Ethernet
 25 communications device such as a personal computer, and all modules of the data transmission device are coupled together by using a bus system, where the bus system includes not only a data bus, but also includes a power supply bus, a control bus, and a state signal bus.

[0257] The processor can implement or execute the steps and logic block diagrams
 30 disclosed in the method embodiments of the present invention. The general processor

52663-170

may be a micro processor or the processor may also be any conventional processor, decoder, or the like. The steps of the method disclosed in the embodiments of the present invention may be executed by a hardware processor directly, or by a combination of hardware and software modules in a decoding processor. The software modules may be
5 located in a random access memory, a flash memory, a read-only memory, a programmable read-only memory, an electrically erasable programmable memory, a register, or any other storage medium that is mature in the art. The storage medium is located in the memory. A decoding unit or a processing unit reads information from the memory, and executes the steps of the foregoing methods by using hardware thereof.

10 **[0258]** It should be understood that, in the embodiments of the present invention, the processor may be a central processing unit (Central Processing Unit, "CPU" for short), and the processor may also be another general processor, a digital signal processor (DSP), an application-specific integrated circuit (ASIC), a field-programmable gate array (FPGA), or another programmable logic device, independent gate or transistor logic
15 device, independent hardware component, and so on. The general processor may be a microprocessor or the processor may also be any conventional processor and so on.

[0259] During the implementation, all steps of the foregoing method may be completed by an integrated logic circuit of hardware or instructions in software forms in the processor. The steps of the method disclosed in the embodiments of the present
20 invention may be executed by a hardware processor directly, or by a combination of hardware and software modules in the processor. The software modules may be located in a random access memory, a flash memory, a read-only memory, a programmable read-only memory, an electrically erasable programmable memory, a register, or any other storage medium that is mature in the art. The storage medium is located in the memory.
25 The processor reads information from the memory, and executes the steps of the foregoing method in combination with hardware of the processor. To avoid repetition, details are not described herein again.

[0260] The optical communications device 400 (specifically, the processor 460) according to the embodiments of the present invention may correspond to an execution
30 body of the method 100 according to the embodiments of the present invention, and units,

52663-170

that is, modules, in the device 300 and the foregoing and other operations and/or functions are intended for implementing the corresponding procedure in the method 100 in FIG. 1, which, for brevity, is not repeated herein any further.

[0261] According to the optical communications device in this embodiment of the present invention, because a global output area capable of covering the entire input optical modulator array is set, the range of each local output area can be adjusted flexibly according to the network status, user requirements and the like. That is, in a case in which the number of dimensions of the foreign communications node or the number of wavelengths used by the signal light changes, the change can be handled flexibly, which significantly improves practicality of the optical communications method of the present invention.

[0262] It should be understood that the term "and/or" in this specification is only to describe an association relationship of associated objects, and represents that three relationships may exist, for example, A and/or B may represent the following three cases: A exists separately, both A and B exist, and B exists separately. In addition, the character "/" in this specification usually represents that the former and latter objects associated are in an "or" relationship.

[0263] It should be understood that in the embodiments of the present invention, the sequence numbers in each process do not represent an execution sequence; the execution sequence of each process should be determined by the function and internal logic of the process, and shall not be construed as a limitation on the implementation processes of the embodiments of the present invention.

[0264] A person of ordinary skill in the art may be aware that, in combination with the examples described in the embodiments disclosed in this specification, units and algorithm steps may be implemented by electronic hardware or a combination of computer software and electronic hardware. Whether the functions are performed by hardware or software depends on particular applications and design constraint conditions of the technical solutions. A person skilled in the art may use different methods to implement the described functions for each particular application, but it should not be considered that the implementation goes beyond the scope of the present invention.

52663-170

[0265] It may be clearly understood by a person skilled in the art that, for the purpose of convenient and brief description, for a detailed working process of the foregoing system, apparatus, and unit, reference may be made to a corresponding process in the foregoing method embodiments, and details are not described herein again.

5 [0266] In the several embodiments provided in the present application, it should be understood that the disclosed system, apparatus, and method may be implemented in other manners. For example, the described apparatus embodiment is merely exemplary. For example, the unit division is merely logical function division and may be other division in actual implementation. For example, multiple units or components may be
10 combined or integrated into another system, or some features may be ignored or not performed. In addition, the displayed or discussed mutual couplings or direct couplings or communication connections may be implemented through some interfaces. The indirect couplings or communication connections between the apparatuses or units may be implemented in electronic, mechanical, or other forms.

15 [0267] The units described as separate parts may or may not be physically separate, and parts displayed as units may or may not be physical units, may be located in one position, or may be distributed on multiple network units. A part or all of the units may be selected according to actual needs to achieve the objectives of the solutions of the embodiments.

20 [0268] In addition, functional units in the embodiments of the present invention may be integrated into one processing unit, or each of the units may exist alone physically, or two or more units are integrated into one unit.

[0269] When the functions are implemented in a form of a software functional unit and sold or used as an independent product, the functions may be stored in a computer-readable storage medium. Based on such an understanding, the technical solutions of the
25 present invention essentially, or the part contributing to the prior art, or a part of the technical solutions may be implemented in a form of a software product. The software product is stored in a storage medium, and includes several instructions for instructing a computer device (which may be a personal computer, a server, a network device, or the
30 like) to perform all or a part of the steps of the methods described in the embodiments of

52663-170

the present invention. The foregoing storage medium includes: any medium that can store program code, such as a USB flash drive, a removable hard disk, a read-only memory (ROM, Read-Only Memory), a random access memory (RAM, Random Access Memory), a magnetic disk, or an optical disc.

- 5 **[0270]** The foregoing descriptions are merely specific embodiments of the present invention, but are not intended to limit the protection scope of the present invention. Any variation or replacement readily figured out by a person skilled in the art within the technical scope disclosed in the present invention shall fall within the protection scope of the present invention. Therefore, the protection scope of the present invention shall be
- 10 subject to the protection scope of the claims.

52663-170

CLAIMS:

1. An optical communications method, wherein the method is executed on a communications node that comprises an input optical modulator array and an output optical modulator array, wherein the input optical modulator array comprises N input
 5 optical modulators and the N input optical modulators are configured to receive a signal light, and the output optical modulator array comprises M output optical modulators and the M output optical modulators are configured to send the signal light, wherein M is greater than the number of output optical modulators that can be covered by one input optical modulator and/or N is greater than the number of input optical modulators capable
 10 of covering a same output optical modulator, and the method comprises:

determining, by a local communications node, at least two local input areas from the input optical modulator array, wherein the at least two local input areas are used to receive a foreign signal light and the foreign signal light is a signal light that comes from a transmitter-side foreign communications node and needs to be sent to a
 15 receiver-side foreign communications node; and

determining, by the local communications node, at least two local output areas from the output optical modulator array, wherein the at least two local output areas are used to send the foreign signal light, the at least two local input areas correspond to the at least two local output areas in a one-to-one mapping manner, and each input optical
 20 modulator in a local input area is capable of transmitting a signal light to each output optical modulator in a corresponding local output area.

2. The method according to claim 1, wherein the number of output optical modulators comprised in the at least two local output areas is greater than the number of output optical modulators that can be covered by one input optical modulator.

25 3. The method according to claim 1 or 2, wherein the number of input optical modulators comprised in the at least two local input areas is greater than the number of input optical modulators capable of covering the same output optical modulator.

52663-170

4. The method according to claim 1 or 2, wherein the method further comprises:

when a first input optical modulator comprised in a first local input area of the at least two local input areas receives a first foreign signal light from a first
 5 transmitter-side foreign communications node, performing, by the local communications node, control to cause the first input optical modulator to transmit the first foreign signal light to a first output optical modulator comprised in a first local output area of the at least two local output areas, so that the first output optical modulator transmits the first foreign signal light to a first receiver-side foreign communications node, wherein the first
 10 local output area corresponds to the first local input area, the first transmitter-side foreign communications node is a previous-hop communications node of the local communications node in a transmission path of the first foreign signal light, the first input optical modulator corresponds to the first transmitter-side foreign communications node and a wavelength of the first foreign signal light, the first receiver-side foreign
 15 communications node is a next-hop communications node of the local communications node in the transmission path of the first foreign signal light, and the first output optical modulator corresponds to the first receiver-side foreign communications node and the wavelength of the first foreign signal light.

5. The method according to claim 1 or 2, wherein the determining, by a local
 20 communications node, at least two local input areas from the input optical modulator array, comprises:

determining, by a local communications node, the at least two local input areas from the input optical modulator array according to the number of dimensions of the transmitter-side foreign communications node and the number of wavelengths of the
 25 foreign signal light.

6. The method according to claim 1 or 2, wherein the determining, by a local communications node, at least two local output areas from the output optical modulator array, comprises:

52663-170

determining, by a local communications node, the at least two local output areas from the output optical modulator array according to the number of dimensions of the receiver-side foreign communications node and the number of wavelengths of the foreign signal light.

- 5 7. The method according to claim 1 or 2, wherein the method further comprises:

10 determining, by the local communications node, a global input area from the input optical modulator array, so that each input optical modulator in the global input area is used to receive an uplink local signal light, wherein the uplink local signal light is a signal light from the local communications node, and each input optical modulator in the global input area is capable of transmitting the signal light to all output optical modulators in the optical modulator array.

- 15 8. The method according to claim 7, wherein the determining, by the local communications node, a global input area from the input optical modulator array, comprises:

determining, by the local communications node, the global input area from the input optical modulator array according to the number of channels used by the uplink local signal light.

- 20 9. The method according to claim 7 or 8, wherein the determining, by a local communications node, at least two local output areas from the output optical modulator array, comprises:

25 determining, by the local communications node, the at least two local output areas from the output optical modulator array, so that each output optical modulator in the at least two local output areas is used to send the uplink local signal light.

10. The method according to claim 9, wherein the method further comprises:

52663-170

when a first uplink local signal light needs to be sent, performing, by the local communications node, control to cause a second input optical modulator to transmit the first uplink local signal light to a second output optical modulator in the output optical modulator array, so that the second output optical modulator transmits the first uplink

5 local signal light to a second receiver-side foreign communications node, wherein the second input optical modulator corresponds to a channel used by the first uplink local signal light, the second receiver-side foreign communications node is a next-hop communications node of the local communications node in a transmission path of the first uplink local signal light, and the second output optical modulator corresponds to the

10 second receiver-side foreign communications node and a wavelength of the first uplink local signal light.

11. The method according to claim 9 or 10, wherein the determining, by a local communications node, at least two local output areas from the output optical modulator array, comprises:

15 determining, by the local communications node, the at least two local output areas from the output optical modulator array according to the number of wavelengths of the foreign signal light, the number of wavelengths of the uplink local signal light, and the number of dimensions of the receiver-side foreign communications node.

20 12. The method according to claim 7 or 8, wherein the method further comprises:

obtaining, by the local communications node, a first piece of communication status information, wherein the first piece of communication status information is used to indicate that at least one of the following parameters needs to be

25 changed: the number of wavelengths of the foreign signal light, the number of channels used by the uplink local signal light or the number of dimensions of the transmitter-side foreign communications node; and

52663-170

changing the at least two local input areas and the global input area according to the first piece of communication status information.

13. The method according to claim 1 or 2, wherein the method further comprises:

5 determining, by the local communications node, a global output area from the output optical modulator array, so that each output optical modulator in the global output area is used to send a downlink local signal light, wherein the downlink local signal light is a signal light that needs to be sent to the local communications node, and each output optical modulator in the global output area is capable of receiving the signal
10 light transmitted by all input optical modulators in the optical modulator array.

14. The method according to claim 13, wherein the determining, by the local communications node, a global output area from the output optical modulator array, comprises:

determining, by the local communications node, the global output area
15 from the output optical modulator array according to the number of channels used by the downlink local signal light.

15. The method according to claim 13 or 14, wherein the determining, by a local communications node, at least two local input areas from the input optical modulator array, comprises:

20 determining, by the local communications node, the at least two local input areas from the input optical modulator array, so that each input optical modulator in the at least two local input areas is used to receive the downlink local signal light.

16. The method according to claim 15, wherein the method further comprises:

when a third input optical modulator in the input optical modulator array
25 receives a first downlink local signal light from a second transmitter-side foreign communications node, performing, by the local communications node, control to cause

52663-170

the third input optical modulator to transmit the first downlink local signal light to a third output optical modulator in the global output area; and obtaining the first downlink local signal light from the third output optical modulator, wherein the second transmitter-side foreign communications node is a previous-hop communications node of the local communications node in a transmission path of the first downlink local signal light, and the third input optical modulator corresponds to the second transmitter-side foreign communications node and a wavelength of the first downlink local signal light, and the third output optical modulator corresponds to a channel used by the first downlink local signal light.

10 17. The method according to claim 15 or 16, wherein the determining, by a local communications node, at least two local input areas from the input optical modulator array, comprises:

15 determining, by the local communications node, the at least two local input areas from the input optical modulator array according to the number of wavelengths of the foreign signal light, the number of wavelengths of the downlink local signal light, and the number of dimensions of the transmitter-side foreign communications node.

18. The method according to claim 13 or 14, wherein the method further comprises:

20 obtaining, by the local communications node, a second piece of communication status information, wherein the second piece of communication status information is used to indicate that at least one of the following parameters needs to be changed: the number of wavelengths of the foreign signal light, the number of channels used by the uplink local signal light or the number of dimensions of the receiver-side foreign communications node; and

25

changing the at least two local output areas and the global output area according to the second piece of communication status information.

52663-170

19. An optical communications apparatus, wherein the apparatus comprises:

an input optical modulator array and an output optical modulator array,
wherein the input optical modulator array comprises N input optical modulators and the
N input optical modulators are configured to receive a signal light, and the output optical
5 modulator array comprises M output optical modulators and the M output optical
modulators are configured to send the signal light, wherein M is greater than the number
of output optical modulators that can be covered by one input optical modulator and/or N
is greater than the number of input optical modulators capable of covering a same output
optical modulator;

10 a controller, configured to determine at least two local input areas from the
input optical modulator array, wherein the at least two local input areas are used to
receive a foreign signal light and the foreign signal light is a signal light that comes from
a transmitter-side foreign communications node and needs to be sent to a receiver-side
foreign communications node; and

15 configured to determine at least two local output areas from the output
optical modulator array, wherein the at least two local output areas are used to send the
foreign signal light, the at least two local input areas correspond to the at least two local
output areas in a one-to-one mapping manner, and each input optical modulator in a local
input area is capable of transmitting the signal light to each output optical modulator in a
20 corresponding local output area.

20. The apparatus according to claim 19, wherein the number of output optical
modulators comprised in the at least two local output areas is greater than the number of
output optical modulators that can be covered by one input optical modulator.

21. The apparatus according to claim 19 or 20, wherein the number of input
25 optical modulators comprised in the at least two local input areas is greater than the
number of input optical modulators capable of covering the same output optical
modulator.

52663-170

22. The apparatus according to claim 19 or 20, wherein the controller is further configured to: when a first input optical modulator comprised in a first local input area of the at least two local input areas receives a first foreign signal light from a first transmitter-side foreign communications node, perform control to cause the first input
5 optical modulator to transmit the first foreign signal light to a first output optical modulator comprised in a first local output area of the at least two local output areas, so that the first output optical modulator transmits the first foreign signal light to a first receiver-side foreign communications node, wherein the first local output area corresponds to the first local input area, the first transmitter-side foreign communications
10 node is a previous-hop communications node of the local communications node in a transmission path of the first foreign signal light, the first input optical modulator corresponds to the first transmitter-side foreign communications node and a wavelength of the first foreign signal light, the first receiver-side foreign communications node is a next-hop communications node of the local communications node in the transmission
15 path of the first foreign signal light, and the first output optical modulator corresponds to the first receiver-side foreign communications node and the wavelength of the first foreign signal light.

23. The apparatus according to claim 19 or 20, wherein the controller is specifically configured to determine the at least two local input areas from the input
20 optical modulator array according to the number of dimensions of the transmitter-side foreign communications node and the number of wavelengths of the foreign signal light.

24. The apparatus according to claim 19 or 20, wherein the controller is specifically configured to determine the at least two local output areas from the output
optical modulator array according to the number of dimensions of the receiver-side
25 foreign communications node and the number of wavelengths of the foreign signal light.

25. The apparatus according to claim 19 or 20, wherein the controller is further configured to determine a global input area from the input optical modulator array, so that each input optical modulator in the global input area is used to receive an uplink local signal light, wherein the uplink local signal light is a signal light from the

52663-170

local communications node, and each input optical modulator in the global input area is capable of transmitting the signal light to all output optical modulators in the optical modulator array.

26. The apparatus according to claim 25, wherein the controller is specifically
5 configured to determine the global input area from the input optical modulator array according to the number of channels used by the uplink local signal light.

27. The apparatus according to claim 25 or 26, wherein the controller is
specifically configured to determine the at least two local output areas from the output
optical modulator array, so that each output optical modulator in the at least two local
10 output areas is used to send the uplink local signal light.

28. The apparatus according to claim 27, wherein the controller is specifically
configured to: when a first uplink local signal light needs to be sent, perform control to
cause a second input optical modulator to transmit the first uplink local signal light to a
second output optical modulator in the output optical modulator array, so that the second
15 output optical modulator transmits the first uplink local signal light to a second receiver-
side foreign communications node, wherein the second input optical modulator
corresponds to a channel used by the first uplink local signal light, the second receiver-
side foreign communications node is a next-hop communications node of the local
communications node in a transmission path of the first uplink local signal light, and the
20 second output optical modulator corresponds to the second receiver-side foreign
communications node and a wavelength of the first uplink local signal light.

29. The apparatus according to claim 27 or 28, wherein the controller is
specifically configured to determine the at least two local output areas from the output
optical modulator array according to the number of wavelengths of the foreign signal
25 light, the number of wavelengths of the uplink local signal light, and the number of
dimensions of the receiver-side foreign communications node.

30. The apparatus according to claim 25 or 26, wherein the controller is

52663-170

further configured to obtain, by the local communications node, a first piece of communication status information, wherein the first piece of communication status information is used to indicate that at least one of the following parameters needs to be changed: the number of wavelengths of the foreign signal light, the number of channels
 5 used by the uplink local signal light or the number of dimensions of the transmitter-side foreign communications node; and

configured to change the at least two local input areas and the global input area according to the first piece of communication status information.

31. The apparatus according to claim 19 or 20, wherein the controller is
 10 further configured to determine a global output area from the output optical modulator array, so that each output optical modulator in the global output area is used to send a downlink local signal light, wherein the downlink local signal light is a signal light that needs to be sent to the local communications node, and each output optical modulator in the global output area is capable of receiving the signal light transmitted by all input
 15 optical modulators in the optical modulator array.

32. The apparatus according to claim 31, wherein the controller is specifically configured to determine the global output area from the output optical modulator array according to the number of channels used by the downlink local signal light.

33. The apparatus according to claim 31 or 32, wherein the controller is
 20 specifically configured to determine the at least two local input areas from the input optical modulator array, so that each input optical modulator in the at least two local input areas is used to receive the downlink local signal light.

34. The apparatus according to claim 33, wherein the controller is specifically configured to: when a third input optical modulator in the input optical modulator array
 25 receives a first downlink local signal light from a second transmitter-side foreign communications node, perform control to cause the third input optical modulator to transmit the first downlink local signal light to a third output optical modulator in the

52663-170

global output area; and obtain the first downlink local signal light from the third output optical modulator, wherein the second transmitter-side foreign communications node is a previous-hop communications node of the local communications node in a transmission path of the first downlink local signal light, and the third input optical modulator
 5 corresponds to the second transmitter-side foreign communications node and a wavelength of the first downlink local signal light, and the third output optical modulator corresponds to a channel used by the first downlink local signal light.

35. The apparatus according to claim 33 or 34, wherein the controller is specifically configured to determine the at least two local input areas from the input
 10 optical modulator array according to the number of wavelengths of the foreign signal light, the number of wavelengths of the downlink local signal light, and the number of dimensions of the transmitter-side foreign communications node.

36. The apparatus according to claim 31 or 32, wherein the controller is further configured to obtain a second piece of communication status information, wherein
 15 the second piece of communication status information is used to indicate that at least one of the following parameters needs to be changed: the number of wavelengths of the foreign signal light, the number of channels used by the uplink local signal light or the number of dimensions of the receiver-side foreign communications node; and

configured to change the at least two local output areas and the global
 20 output area according to the second piece of communication status information.

1/8


100

FIG. 1

2/8




FIG. 2




FIG. 3

3/8




FIG. 4




FIG. 5

4/8




FIG. 6a




FIG. 6b




FIG. 7

6/8




FIG. 8a




FIG. 8b




FIG. 9

8/8


300

FIG. 10


400

FIG. 11

A local communications node determines at least two local input areas from the input optical modulator array, so that each input optical modulator in the at least two local input areas is configured to receive a foreign signal light and the foreign signal light is a signal light that comes from a transmitter-side foreign communications node and needs to be sent to a receiver-side foreign communications node

S110



The local communications node determines at least two local output areas from the output optical modulator array, so that each output optical modulator in the at least two local output areas is configured to send the foreign signal light, where the at least two local input areas correspond to the at least two local output areas in a one-to-one mapping manner, and each input optical modulator in a local input area is capable of transmitting the signal light to each output optical modulator in a corresponding local output area

S120