




(86) Date de dépôt PCT/PCT Filing Date: 2014/07/09	(51) Cl.Int./Int.Cl. <i>H04W 36/00</i> (2009.01), <i>H04W 80/10</i> (2009.01)
(87) Date publication PCT/PCT Publication Date: 2015/03/19	
(45) Date de délivrance/Issue Date: 2018/06/05	(72) Inventeurs/Inventors: ISLAM, MUHAMMAD KHALEDUL, CA; WIRTANEN, JEFFREY WILLIAM, CA
(85) Entrée phase nationale/National Entry: 2016/03/08	
(86) N° demande PCT/PCT Application No.: CA 2014/000554	(73) Propriétaire/Owner: BLACKBERRY LIMITED, CA
(87) N° publication PCT/PCT Publication No.: 2015/035494	
(30) Priorité/Priority: 2013/09/11 (US14/024,144)	(74) Agent: MOFFAT & CO.

(54) Titre : PROCEDE ET APPAREIL D'ETABLISSEMENT D'UN APPEL PAR COMMUTATION DE CIRCUIT PENDANT UN REPLI PAR COMMUTATION DE CIRCUIT
(54) Title: METHOD AND APPARATUS FOR SETUP OF A CIRCUIT SWITCHED CALL DURING CIRCUIT SWITCHED FALLBACK



(57) Abrégé/Abstract:
A method, at a user equipment ('UE'), the method: sending a request to a first network for Circuit Switched Fallback ('CSFB'); receiving, responsive to the request, redirection information; acquiring a second network based on the redirection information; initiating establishment of Circuit Switched ('CS') voice radio bearers with the second network; waiting for a predetermined event to occur; after the predetermined event has occurred, establishing a Packet Switched ('PS') connection with the second network. Further, a method, at a network element, the method receiving a request for Circuit Switched Fallback ('CSFB') from a user equipment ('UE'); sending, to the UE, redirection information; receiving a Routing Area Update ('RAU') message from the UE; waiting for a predetermined event to occur; upon the predetermined event occurring, responding to the RAU message.

Abstract

A method, at a user equipment ('UE'), the method: sending a request to a first network for Circuit Switched Fallback ('CSFB'); receiving, responsive to the request, redirection information; acquiring a second network based on the redirection information; initiating establishment of Circuit Switched ('CS') voice radio bearers with the second network; waiting for a predetermined event to occur; after the predetermined event has occurred, establishing a Packet Switched ('PS') connection with the second network. Further, a method, at a network element, the method receiving a request for Circuit Switched Fallback ('CSFB') from a user equipment ('UE'); sending, to the UE, redirection information; receiving a Routing Area Update ('RAU') message from the UE; waiting for a predetermined event to occur; upon the predetermined event occurring, responding to the RAU message.

WO 2015/035494

PCT/CA2014/000554

IN THE UNITED STATES PATENT OFFICE

Title:

**METHOD AND APPARATUS FOR SETUP OF A CIRCUIT SWITCHED CALL
DURING CIRCUIT SWITCHED FALLBACK**

Inventors

**Muhammad Khaledul ISLAM
Jeffrey William WIRTANEN**

Assignee:

BlackBerry Limited

METHOD AND APPARATUS FOR SETUP OF A CIRCUIT SWITCHED CALL DURING CIRCUIT SWITCHED FALLBACK

FIELD OF THE DISCLOSURE

[0001] The present disclosure relates to the setup of a circuit-switched call on a mobile communication network and in particular relates to the setup of a circuit switched call during circuit switched fallback (CSFB).

BACKGROUND

[0002] The Third Generation Partnership Project (3GPP) defines a long-term evolution (LTE) architecture, which provides high data rate, low latency, packet optimization and improved system capacity and coverage. In an LTE system, an evolved universal terrestrial radio access network (E-UTRAN) includes a plurality of evolved Node-Bs (eNBs) and communicates with a plurality of mobile stations, also referred to as user equipments (UEs).

[0003] An LTE network supports only packet-switched (PS) services. However fallback is specified for circuit switched (CS) services as well. CSFB defines a mechanism for using a legacy CS network (e.g. Universal Mobile Telecommunications System Terrestrial Radio Access Network (UTRAN) or a GSM EDGE Radio Access Network (GERAN)) to provide voice and traditional CS-domain services (e.g. voice call, a CS short message service (SMS), Unstructured Supplementary Service Data (USSD), among others).

[0004] With CSFB, when there is an incoming CS call for a UE operating in LTE mode, the LTE network pages the device. The device responds with a special service request message to the network, and the network signals the device to move (fall back) to GERAN/UTRAN cell by providing redirection information for the UE to acquire a UTRAN/GERAN cell. Similarly for outgoing CS calls, the same special service request

is used to move the device to GERAN/UTRAN to place the outgoing call. The UE then attempts to acquire a GERAN or UTRAN cell based on the received redirection information and then attempts to establish a connection.

[0005] The UE then attempts to establish CS service and may attempt to move packet switched services from E-UTRAN to GERAN or UTRAN if applicable. In particular, to maintain data connectivity, an always-on UE is required to perform a Routing Area Update (RAU) procedure to transfer the PS data context from E-UTRAN to UTRAN/GERAN. In addition, there may have been a data session in progress when the CSFB call was initiated, which would trigger the UE to perform an RAU procedure and then initiate a packet data call in parallel with the establishment of the CS call.

[0006] The overall call setup time for a CSFB call is significantly longer compared to a CS voice call that is initiated while the UE is already in GERAN/UTRAN. Further, additional delays are caused if PS domain signaling activities take place while the CS domain is being setup.

BRIEF DESCRIPTION OF THE DRAWINGS

[0007] The present disclosure will be better understood with reference to the drawings, in which:

Figure 1 is a diagram of an example network architecture.

Figure 2 is a flow chart of a process according to at least one embodiment of the present disclosure.

Figure 3 is a flow chart of a process according to a further embodiment of the present disclosure.

Figure 4 is a flow chart of a process according to a further embodiment of the present disclosure.

Figure 5 is a flow chart of a process at a network side according a further embodiment of the present disclosure.

Figure 6 is a bar chart of the observed call setup times of legacy CS calls, CSFB prior art calls and CSFB calls in accordance with at least one embodiment of the present disclosure.

Figure 7 is a block diagram of an example user equipment.

Figure 8 is a block diagram of an example simplified network element.

DETAILED DESCRIPTION

[0008] The present disclosure provides a method, at a user equipment ('UE'), comprising: sending a request to a first network for Circuit Switched Fallback ('CSFB'); receiving, responsive to the request, redirection information; acquiring a second network based on the redirection information; initiating establishment of Circuit Switched ('CS') voice radio bearers with the second network; waiting for a predetermined event to occur; after the predetermined event has occurred, establishing a Packet Switched ('PS') connection with the second network.

[0009] The present disclosure further provides a user equipment comprising: a processor; a communications subsystem; wherein the user equipment is configured: send a request to a first network for Circuit Switched Fallback ('CSFB'); receive, responsive to the request, redirection information; acquire a second network based on the redirection information; initiate establishment of Circuit Switched ('CS') voice radio bearers with the second network; wait for a predetermined event to occur; after the predetermined event has occurred, establishing a Packet Switched ('PS') connection with the second network.

[0010] The present disclosure further provides a method, at a network element, comprising: receiving a request for Circuit Switched Fallback ('CSFB') from a user equipment ('UE'); sending, to the UE, redirection information; receiving a Routing Area Update ('RAU') message from the UE; waiting for a predetermined event to occur; upon the predetermined event occurring, responding to the RAU message.

[0011] The present disclosure further provides a network element, comprising: a processor; a communications subsystem; wherein the network element is configured to: receive a request for Circuit Switched Fallback ('CSFB') from a user equipment ('UE'); send, to the UE, redirection information; receive a Routing Area Update ('RAU') message from the UE; wait for a predetermined event to occur; upon the predetermined event occurring, respond to the RAU message.

[0012] The overall call setup time for a CSFB call is significantly longer compared to a CS voice call that is initiated while the UE is already camping on GERAN/UTRAN. One major contributor to the increase in call setup time is the acquisition of GERAN/UTRAN, and subsequent synchronization with GERAN/UTRAN which is needed before UE can exchange any signaling message with GERAN/UTRAN.

[0013] Further, additional delays may be caused by PS domain signaling activities that happen during the CS domain setup. In addition to the signaling messages that are exchanged to set up CS call, if the UE initiates an RAU procedure, the network in response initiates a PS domain security procedure which prevents or delays the signaling radio bearers to be used for signaling of CS domain activities until the PS domain security procedure is completed.

[0014] In addition, the network may also initiate the General Packet Radio Service (GPRS) Mobility Management (GMM) authentication and ciphering process for PS domain which delays the CSFB call setup further.

[0015] As a result of all these procedures, the establishment of voice radio bearers for the CS domain is significantly delayed compared to a legacy CS voice call in GERAN/UTRAN. As used herein, the CS voice radio bearers are the radio resources that are setup by the network to transport CS voice over wireless network and can be for either second or third generation networks. The end-to-end call setup delay is particularly long and noticeable by the user if a call is made from one LTE device to another LTE device when both devices are on an LTE network and both undergo the CSFB procedures including PS domain transfer when CS voice call is being setup. This

delay in call setup adversely impacts user experience; in addition, such increase in call setup time is highly undesirable if the voice call is an emergency call or an emergency callback call from the Public Safety Answering Point (PSAP).

[0016] Circuit switched fallback is provided for in the 3GPP LTE Technical Specification (TS) 23.272, “Third Generation Partnership Project; Technical Specification Group Services and System Aspects; Circuit Switched (CS) Fallback in Evolved Packet System (EPS); Stage 2”; v. 11.5.0, June 2013. CSFB can be used to fall back to either second generation GERAN networks or third generation UTRAN networks. In particular the system architecture is provided in Figure 4.2-1 of the 3GPP TS 23.272 specification and is reproduced herein with regard to **Figure 1**.

[0017] Reference is now made to **Figure 1**, which illustrates one embodiment of a mobile communication system that includes a GERAN/UTRAN network, as well as an LTE network.

[0018] In particular, a UE **110** is a multi-mode UE capable of communicating with both an LTE network as well as a GERAN/UTRAN network. As seen in **Figure 1**, UE **110** communicates with either or both of a UTRAN **120** or a GERAN **122** for circuit switched services. UE **110** further communicates with an E-UTRAN **130** for the LTE network.

[0019] Both UTRAN **120** and GERAN **122** communicate with a serving general packet radio service (GPRS) support node (SGSN) **140** for packet switched services and with MSC server **160** for circuit switched services.

[0020] The E-UTRAN communicates with mobility management entity (MME) **150**.

[0021] In the CSFB system, mobile switching center (MSC) server **160** further communicates with MME **150**.

[0022] During normal operation, UE 110 will camp on the LTE system. If a mobile terminated call is received then MSC server 160 will notify MME 150, which will then send a page to UE 110 through E-UTRAN 130 to transition to UTRAN 120 or GERAN 122. The UE 110 will then transition for the duration of the circuit switched call. At the end of the circuit switch call the UE then transitions back to the LTE network.

[0023] Packet switched services may either be suspended for the duration of the circuit switched call or may be transferred to SGSN 140, where the UE 110 will continue to receive packet data, although at a lower speed than from the LTE network.

[0024] For a mobile originated call, the UE 110 may transition to UTRAN 120 or GERAN 122 for the duration of the call.

[0025] Typical non-access stratum/radio resource control (NAS/RRC) signaling for a mobile-terminated CS voice call setup between a UE camped on a UTRAN cell and a UMTS network is shown with regards to **Table 1** below. The messages shown in *italics* are optional messages that UMTS network may initiate for authentication purposes.

UE	←	Network	Paging
UE	→	Network	rrcConnectionRequest (terminatingConversationalCall)
UE	←	Network	rrcConnectionSetup
UE	→	Network	rrcConnectionSetupComplete
UE	→	Network	initialDirectTransfer (NAS RR PAGING_RESPONSE)
UE	←	Network	<i>downlinkDirectTransfer (NAS MM AUTHENTICATION_REQUEST)</i>
UE	→	Network	<i>uplinkDirectTransfer (AUTHENTICATION_RESPONSE)</i>
UE	←	Network	securityModeCommand (CS domain)
UE	→	Network	securityModeComplete
UE	←	Network	downlinkDirectTransfer (NAS MM IDENTITY_REQUEST)
UE	→	Network	uplinkDirectTransfer (NAS MM IDENTITY_RESPONSE)
UE	←	Network	downlinkDirectTransfer (NAS CC SETUP)
UE	→	Network	uplinkDirectTransfer (NAS CC CALL_CONFIRMED)
UE	←	Network	radioBearerSetup (CS domain RAB)
UE	→	Network	radioBearerSetupComplete
UE	→	Network	uplinkDirectTransfer (NAS CC ALERT)

TABLE 1: CS Voice Call for UE camped on UTRAN Cell

[0026] Conversely, **Table 2** shows the NAS/RRC signaling during a mobile-terminated CS voice call setup, between a UE initially connected to an LTE network and the networks comprising the LTE network that receives CS voice call request and the UMTS network that handles the CS voice call. The bold messages are for the PS domain. In this example, the UE fallbacks to UTRAN for CS voice call. Fallback to GERAN comprises similar steps.

LTE to UMTS CSFB Voice Call			
UE	←	Network	Paging
UE	→	Network	EPS MM Extended service request (MT CSFB)
UE	→	Network	rrcConnectionRequest (mt-Access)
UE	←	Network	rrcConnectionSetup
UE	→	Network	rrcConnectionSetupComplete
UE	←	Network	securityModeCommand
UE	→	Network	securityModeCommandComplete
UE	←	Network	ueCapabilityEnquiry
UE	→	Network	ueCapabilityInformation
UE	←	Network	rrcConnectionReconfiguration
UE	→	Network	rrcConnectionReconfigurationComplete
UE	←	Network	rrcConnectionRelease (redirectedCarrierInfo ultra-FDD)
UE acquires a UTRAN cell			
UE	→	Network	rrcConnectionRequest (terminatingConversationalCall)
UE	←	Network	rrcConnectionSetup
UE	→	Network	rrcConnectionSetupComplete
UE	→	Network	initialDirectTransfer (NAS RR PAGING_RESPONSE)
UE	→	Network	initialDirectTransfer (GMM_ROUTING_AREA_UPDATE_REQUEST)
UE	←	Network	downlinkDirectTransfer (NAS MM AUTHENTICATION_REQUEST)
UE	←	Network	downlinkDirectTransfer (GMM_AUTHENTICATION_AND_CYPHERING_REQUEST)
UE	→	Network	uplinkDirectTransfer (AUTHENTICATION_RESPONSE)
UE	→	Network	uplinkDirectTransfer (GMM_AUTHENTICATION_AND_CYPHERING_RESPONSE)
UE	←	Network	securityModeCommand (CS domain)
UE	→	Network	securityModeComplete
UE	←	Network	securityModeCommand (PS domain)
UE	→	Network	securityModeComplete
UE	←	Network	downlinkDirectTransfer (GMM_ROUTING_AREA_UPDATE_ACCEPT)
UE	→	Network	uplinkDirectTransfer (ROUTING_AREA_UPDATE_COMPLETE)

UE	←	Network	downlinkDirectTransfer (NAS MM IDENTITY_REQUEST)
UE	→	Network	uplinkDirectTransfer (NAS MM IDENTITY_RESPONSE)
UE	←	Network	downlinkDirectTransfer (NAS GMM GMM_INFORMATION)
UE	←	Network	downlinkDirectTransfer (NAS CC SETUP)
UE	→	Network	uplinkDirectTransfer (NAS CC CALL_CONFIRMED)
UE	←	Network	signallingConnectionRelease (PS domain)
UE	←	Network	radioBearerSetup (CS domain RAB)
UE	→	Network	radioBearerSetupComplete
UE	→	Network	uplinkDirectTransfer (NAS CC ALERT)

TABLE 2: LTE to CSFB Voice Call

[0027] As seen in **Table 2** above, the UE is connected to the LTE network prior to acquiring the UTRAN cell, after which the UE is connected to the UMTS network.

[0028] Since the UE must first acquire the UTRAN cell, CS call setup with CSFB has more latency. For example, one set of real world test results, where the tests were performed on live-air commercial networks to compare the call setup latency of a CSFB call compared to a CS voice call, are shown with regards to **Table 3** below. The tests were performed simultaneously so that any loading or other artifacts of the network affected each call in a similar manner. The results in **Table 3** are merely examples, but show the call setup time for CSFB calls is significantly longer than for regular CS voice calls.

Source to Destination Type	Network	Type of Call	Median Call Setup Time (ms)		
			Total	Breakdown of Total	
				LTE Ext Service Request to UMTS RRC Connection Request (LTE→UMTS)	UMTS RRC Connection Request to UMTS Radio Bearer Setup for CS domain messages
Land to Mobile Call	Network 1	Legacy CS voice call in UTRAN	1268.5	N/A	1268.5
		CSFB LTE to UTRAN	2528	1002	1526
	Network 2,	Legacy CS voice call in UTRAN	1545	N/A	1545

	location 1	CSFB LTE to UTRAN	3406.5	988.5	2418
	Network 2,	Legacy CS voice call in UTRAN	1691.5	N/A	1691.5
	location 2	CSFB LTE to UTRAN	3541	816	2725
Mobile to Mobile Call	Network 2,	Legacy CS voice call in UTRAN	3749	N/A	3749
	location 2	CSFB LTE to UTRAN	6770	920	5850

TABLE 3: Comparison between Call Setup Latencies

[0029] Accordingly, the embodiments described below provide solutions to reduce the CSFB call setup delay. Specifically, embodiments of the present disclosure provide for the reduction in the CSFB delay by delaying PS domain signaling activities until after the voice radio bearer for the CS domain is established.

[0030] According to at least one embodiment, the PS domain signaling activities are suspended until the CS domain voice radio bearer for the voice call is setup. According to at least one further embodiment, the PS domain signaling activities are delayed for a certain duration.

[0031] According to at least one embodiment, these solutions may be triggered on the mobile device, regardless of whether there is an ongoing active PS data session in LTE at the time of the CSFB call. In an at least another embodiment, these solutions may be triggered only when there is no active PS data session in LTE or pending PS data session or request in UMTS for a PS data session. At the time of CSFB call in LTE, the Non Access Stratum (NAS) layer on the UE can implicitly determine that the UE has no active PS data session if the Evolved Packet System Mobility Management (EMM) entity is in idle mode (EMM-IDLE mode). The NAS layer on the UE may also check the status of a follow-on bit in an RAU request to check if there is any pending data or not.

[0032] Notably, the above solutions may delay the transfer of the PS data context from LTE to UTRAN by a small margin but reduce the latency for CS voice call setup which is more important from users' perspective.

[0033] Reference is now made to **Figure 2**, which provides a flow chart of a method according to at least one embodiment of the present disclosure.

[0034] The method of **Figure 2** starts at block **200**, and proceeds to block **210** in which a CSFB call request is sent from the UE to the LTE network. For example, the request may be based on a page from the network for a mobile terminated call, as seen in **Table 2** above, or may be for a mobile originated call.

[0035] The process next proceeds to block **220**, in which the UE receives redirection information from the network in response to the CSFB call request. For example, from **Table 2** above, the redirection information may be in the form of a `rrcConnectionRelease (redirectedCarrierInfo ultra-FDD)` message.

[0036] Based on the received redirection information, the UE attempts to acquire and then connect to a UTRAN cell to establish circuit switched service, as shown at block **230**.

[0037] The UE then waits until the circuit switched voice radio bearers are established, and checks that the circuit switched voice radio bearers are established at block **240**. Once the circuit switched voice radio bearers are established, the process proceeds block **250** in which UE initiates the procedure to transfer the PS domain to UTRAN by sending the `GMM_ROUTING_AREA_UPDATE_REQUEST` to the UTRAN.

[0038] The process then proceeds to block **260** and ends.

[0039] **Table 4** below shows example signaling for a mobile-terminated voice call between a UE and a network when the above solution is implemented.

LTE to UMTS CSFB Voice Call

UE	←	Network	Paging
UE	→	Network	EPS MM Extended service request (MT CSFB)
UE	→	Network	rrcConnectionRequest (mt-Access)
UE	←	Network	rrcConnectionSetup
UE	→	Network	rrcConnectionSetupComplete
UE	←	Network	securityModeCommand
UE	→	Network	securityModeCommandComplete
UE	←	Network	ueCapabilityEnquiry
UE	→	Network	ueCapabilityInformation
UE	←	Network	rrcConnectionReconfiguration
UE	→	Network	rrcConnectionReconfigurationComplete
UE	←	Network	rrcConnectionRelease (redirectedCarrierInfo ultra-FDD)
UE acquires a UTRAN cell			
UE	→	Network	rrcConnectionRequest (terminatingConversationalCall)
UE	←	Network	rrcConnectionSetup
UE	→	Network	rrcConnectionSetupComplete
UE	→	Network	initialDirectTransfer (NAS RR PAGING_RESPONSE)
UE	←	Network	<i>downlinkDirectTransfer (NAS MM AUTHENTICATION_REQUEST)</i>
UE	→	Network	<i>uplinkDirectTransfer (AUTHENTICATION_RESPONSE)</i>
UE	←	Network	securityModeCommand (CS domain)
UE	→	Network	securityModeComplete
UE	←	Network	downlinkDirectTransfer (NAS MM IDENTITY_REQUEST)
UE	→	Network	uplinkDirectTransfer (NAS MM IDENTITY_RESPONSE)
UE	←	Network	downlinkDirectTransfer (NAS CC SETUP)
UE	→	Network	uplinkDirectTransfer (NAS CC CALL_CONFIRMED)
UE	←	Network	radioBearerSetup (CS domain RAB)
UE	→	Network	radioBearerSetupComplete
UE	→	Network	initialDirectTransfer (GMM_ROUTING_AREA_UPDATE_REQUEST)
UE	→	Network	uplinkDirectTransfer (NAS CC ALERT)
UE	←	Network	radioBearerReconfiguration
UE	→	Network	radioBearerReconfigurationComplete
UE	←	Network	<i>downlinkDirectTransfer (GMM_AUTHENTICATION_AND_CYPHERING_REQUEST)</i>
UE	→	Network	<i>uplinkDirectTransfer (GMM_AUTHENTICATION_AND_CYPHERING_RESPONSE)</i>
UE	←	Network	securityModeCommand (PS domain)
UE	→	Network	securityModeComplete
UE	←	Network	downlinkDirectTransfer (GMM_ROUTING_AREA_UPDATE_ACCEPT)
UE	→	Network	uplinkDirectTransfer (ROUTING_AREA_UPDATE_COMPLETE)
UE	←	Network	downlinkDirectTransfer (NAS GMM GMM_INFORMATION)
UE	←	Network	signallingConnectionRelease (PS domain)

TABLE 4: LET to UMTS CSFB Voice Call (modified)

[0040] As seen in **Table 4** above, the PS establishment does not start until after the UE sends a radioBearerSetupComplete message for the CS domain RAB to the network.

[0041] Another embodiment of the present disclosure is illustrated with respect to **Figure 3**. In particular, in order not to increase PS bearer establishment during a CSFB call when there is an ongoing active PS data session on LTE network, a check may be made to determine whether to perform the CS voice radio bearer establishment in parallel with the PS bearer establishment, or whether the CS voice radio bearer establishment may occur first.

[0042] In particular, the method of **Figure 3** starts at block **300** and proceeds to block **310** in which the UE determines whether a PS data session is ongoing. In at least one embodiment, the UE also determines whether there are pending requests for a PS data session. In other embodiments, the determination at block **310** may simply be that the UE is in LTE active. Other examples are possible.

[0043] From block **310** the process proceeds to block **320** in which the UE then requests a CSFB call from the network. As with the embodiment of **Figure 2**, the request may be based on a page for a mobile terminated call or may be based on a mobile originated call.

[0044] The process then proceeds to block **330**, in which the UE receives redirection information from the network in response to the request for a CSFB call.

[0045] The process then proceeds to block **335** in which a check is made whether a PS data session was ongoing or if there were pending requests for a PS data session, as determined at block **310**. If there was an ongoing PS data session, or if there was a pending request for a PS data session, the process proceeds from block **335** to block **340** where circuit and packet switched bearers are established in parallel, for example using signaling similar to that of **Table 2** above. The process then proceeds to block **350** and ends.

[0046] Conversely, from block **335**, if there was no PS data session, or if there was no pending request for a PS data session, the method proceeds to block **360** to establish the CS voice radio bearers, and then to block **370** to wait until it is determined that the circuit switched bearers are established. Once the circuit switched voice radio bearers are established, the process proceeds to block **390** in which the packet switched bearers are established. From block **390** the process proceeds to block **350** and ends. The process of block **360** and **390** may, for example, use the signaling of **Table 4** above.

[0047] In at least some embodiments, the process of block **310**, namely determining whether a PS data session is ongoing, could be performed at block **330** instead.

[0048] In a further embodiment, rather than wait and check for CS voice radio bearers being (or in addition to this process), a delay may be introduced after CS voice radio bearer establishment is initiated. The further embodiment is illustrated with respect to **Figure 4**.

[0049] The process of **Figure 4** starts at block **400** and proceeds to block **410** in which the UE makes a CSFB call request to the network. As indicated above for the embodiments of **Figures 2** and **3**, the request may be made based on the receipt of a page for a mobile terminated call or based on a mobile originated call. From **Tables 2** and **4**, the mobile terminated version of the signaling may be a EPS MM Extended service request (MT CSFB) message.

[0050] From block **410** the process proceeds to block **420**, in which the UE receives redirection information from the network in response to the request for a CSFB call. For example, from **Table 4** the redirection information may be in the form of message `rrcConnectionRelease (redirectedCarrierInfo ultra-FDD)`.

[0051] The process then proceeds to block **430**, in which the UE acquires the UTRAN cell and establishes circuit switched voice radio bearers. Such CS voice radio bearer establishment may be in the form of a `radioBearerSetup (CS domain RAB)` message.

[0052] The process then proceeds to block **440**, where the UE waits a predetermined amount of time. The predetermined amount of time maybe preset, for example at the time the UE is manufactured or by a carrier when a device is deployed, or may be configured by the network, or by other means known in the art. The timer for the predetermined wait time is reset if the CS voice radio bearer is established prior to its expiry.

[0053] After the predetermined amount of time has elapsed, the process proceeds to block **450**, in which the procedure to transfer PS domain is initiated, for example, using the GMM_ROUTING_AREA_UPDATE_REQUEST. From block 450 the process proceeds to block **460** and ends.

[0054] In some cases, the processes of **Figure 3** and **Figure 4** may be combined. Specifically, if a PS data session is ongoing, or if there is a pending request for a PS data session at the time of the CSFB call, the UE may skip waiting for a predetermined amount of time and proceed immediately to establishing packet switched bearers.

[0055] Furthermore, the predetermined amount of time could be set to a length which is longer than the expected time required for establishing circuit switched voice radio bearers. Specifically, if for some reason the UE is unable to establish circuit switched voice radio bearers and the UE is prevented from establishing packet switched bearers until the circuit switched voice radio bearers are established, the UE may become inoperable. Accordingly, in some embodiments, the method waits for the first one of the establishment of circuit switched voice radio bearers or the expiration of a predetermined time period to establish packet switched bearers. In a further embodiment, the predetermined time period is longer than an expected or an average time required to establish circuit switched voice radio bearers.

[0056] In a further embodiment, the delaying procedure is performed on the network side instead of on the UE side. Reference is now made to **Figure 5**.

[0057] The process of **Figure 5** starts at block **500** and proceeds to block **510** in which the network element receives a CSFB call request from the UE.

[0058] The process then proceeds to block **520** in which the network element responds to the CSFB request with redirection information. From **Table 4**, the response may be a redirectedCarrierInfo ultra-FDD message.

[0059] The process then proceeds to block **530**, where the network element receives a Routing Area Update message from the UE. In at least some embodiments, the network element examines the follow-on bit in the Routing Area Update message to determine whether the UE is in an active PS data session or a PS data session is about to start.

[0060] If the network element determines that the UE is in an active data session, as shown by block **535**, the network element may proceed directly from block **530** to block **550** and respond to the Routing Area Update message, after which the method ends at block **560**.

[0061] Otherwise, if the network element determines that the UE is not in an active data session, or if the network element does not perform the check of block **535**, the network element waits until the UE has established its circuit switched voice radio bearers as shown at block **540**.

[0062] Once the network element determines that the UE has established circuit switched voice radio bearers, the network element may respond to the Routing Area Update message at block **550**, after which the process ends at block **560**.

[0063] Therefore, the above embodiments provide for the delay, at least in some cases, of the establishment of PS radio bearers to reduce the call setup latency of a CSFB call.

[0064] Practical results demonstrate a relative improvement for CSFB voice call setup times, attributed to the above embodiments, shown in **Table 5** below. **Table 5** further shows the increase in the time required to transfer the PS domain.

Source to Destination Type	Network	Type of Call	LTE Ext Service Request to UMTS RRC Connection Request (LTE→UMTS)	UMTS RRC Connection Request to UMTS Radio Bearer Setup for CS domain messages	Median time of PS data session transfer (ms)
					UMTS RRC Connection Request → RAU Accept message
Land to Mobile Call	Network 1	Legacy CS	N/A	1268.5	N/A
		CSFB	1000	1526	
		CSFB (modified)	929	1396	
	Network 2	Legacy CS	N/A	1545	N/A
		CSFB	988.5	2418	2346
		CSFB (modified)	1071.5	1720	3694
	Network 3	Legacy CS	N/A	1691.5	N/A
		CSFB	1080	2661	1986
		CSFB (modified)	860	1746	3815.5
Mobile to Mobile Call	Network 3	Legacy CS	N/A	3749	N/A
		CSFB	920	5850	2296
		CSFB (modified)	954	4296	6357.5

Table 5: Example Call Setup Time Comparison

[0065] In **Table 5**, a “legacy CS” is a call originated on a UTRAN cell. The “CSFB” is the time using existing CSFB procedures and “CSFB (modified)” uses the embodiment of **Figure 2** above. From the table the modified CSFB procedure of **Figure 2** provides a reduction in the call setup time.

[0066] Further results are illustrated in **Figure 6**, which compares the time required to establish a legacy CS voice call, a prior art CSFB voice call, and a CSFB voice call in accordance with the present disclosure. The label T1 stands for the time interval between the CSFB request from the UE when the UE is on an LTE network and the UMTS RRC Connection Request after the UE has acquired a UMTS network. The label T2 stands for the time interval between the UMTS RRC Connection Request and the UMTS CS voice radio bearer setup. The label Total stands for the total of T1 and T2.

[0067] The above embodiments may be implemented by any UE. One exemplary device is described below with regard to **Figure 7**.

[0068] UE **700** is typically a two-way wireless communication device having voice and/or data communication capabilities. UE **700** generally has the capability to communicate with other computer systems on the Internet. Depending on the exact functionality provided, the UE may be referred to as a data messaging device, a two-way pager, a wireless e-mail device, a cellular telephone with data messaging capabilities, a wireless Internet appliance, a wireless device, a mobile device, or a data communication device, as examples.

[0069] Where UE **700** is enabled for two-way communication, it may incorporate a communication subsystem **711**, including both a receiver **712** and a transmitter **714**, as well as associated components such as one or more antenna elements **716** and **718**, local oscillators (LOs) **713**, and a processing module such as a digital signal processor (DSP) **720**. As will be apparent to those skilled in the field of communications, the particular design of the communication subsystem **711** will be dependent upon the communication network in which the device is intended to operate. The radio frequency front end of communication subsystem **711** can be for any of the embodiments described above.

[0070] Network access requirements will also vary depending upon the type of network **719**. In some networks network access is associated with a subscriber or user of UE **700**. A UE may require a removable user identity module (RUIM) or a subscriber identity module (SIM) or a universal subscriber identity module (USIM) in order to operate on a network. The SIM/USIM/RUIM interface **744** is normally similar to a card-slot into which a SIM/RUIM card can be inserted and ejected. The SIM/USIM/RUIM card can have memory and hold many key configurations **751**, and other information **753** such as identification, and subscriber related information.

[0071] When required network registration or activation procedures have been completed, UE **700** may send and receive communication signals over the network **719**.

As illustrated in **Figure 7**, network **719** can consist of multiple base stations communicating with the UE. Further, as described above, a multi-mode UE may communicate with base stations of different networks **719**, for example a WCDMA and an LTE network.

[0072] Signals received by antenna **716** through communication network **719** are input to receiver **712**, which may perform such common receiver functions as signal amplification, frequency down conversion, filtering, channel selection and the like. A/D conversion of a received signal allows more complex communication functions such as demodulation and decoding to be performed in the DSP **720**. In a similar manner, signals to be transmitted are processed, including modulation and encoding for example, by DSP **720** and input to transmitter **714** for digital to analog conversion, frequency up conversion, filtering, amplification and transmission over the communication network **719** via antenna **718**. DSP **720** not only processes communication signals, but also provides for receiver and transmitter control. For example, the gains applied to communication signals in receiver **712** and transmitter **714** may be adaptively controlled through automatic gain control algorithms implemented in DSP **720**.

[0073] UE **700** generally includes a processor **738** which controls the overall operation of the device. Communication functions, including data and voice communications, are performed through communication subsystem **711**. Processor **738** also interacts with further device subsystems such as the display **722**, flash memory **724**, random access memory (RAM) **726**, auxiliary input/output (I/O) subsystems **728**, serial port **730**, one or more keyboards or keypads **732**, speaker **734**, microphone **736**, other communication subsystem **740** such as a short-range communications subsystem and any other device subsystems generally designated as **742**. Serial port **730** could include a USB port or other port known to those in the art.

[0074] Some of the subsystems shown in **Figure 7** perform communication-related functions, whereas other subsystems may provide “resident” or on-device functions. Notably, some subsystems, such as keyboard **732** and display **722**, for example, may

be used for both communication-related functions, such as entering a text message for transmission over a communication network, and device-resident functions such as a calculator or task list.

[0075] Operating system software used by the processor **738** may be stored in a persistent store such as flash memory **724**, which may instead be a read-only memory (ROM) or similar storage element (not shown). Those skilled in the art will appreciate that the operating system, specific device applications, or parts thereof, may be temporarily loaded into a volatile memory such as RAM **726**. Received communication signals may also be stored in RAM **726**.

[0076] As shown, flash memory **724** can be segregated into different areas for both computer programs **758** and program data storage **750**, **752**, **754** and **756**. These different storage types indicate that each program can allocate a portion of flash memory **724** for their own data storage requirements. Processor **738**, in addition to its operating system functions, may enable execution of software applications on the UE. A predetermined set of applications that control basic operations, including at least data and voice communication applications for example, will normally be installed on UE **700** during manufacturing. Other applications could be installed subsequently or dynamically.

[0077] Applications and software may be stored on any computer readable storage medium. The computer readable storage medium may be a tangible or intransitory/non-transitory medium such as optical (e.g., CD, DVD, etc.), magnetic (e.g., tape) or other memory known in the art.

[0078] One software application may be a personal information manager (PIM) application having the ability to organize and manage data items relating to the user of the UE such as, but not limited to, e-mail, calendar events, voice mails, appointments, and task items. Naturally, one or more memory stores would be available on the UE to facilitate storage of PIM data items. Such PIM application may have the ability to send and receive data items, via the wireless network **719**. Further applications may also be

loaded onto the UE **700** through the network **719**, an auxiliary I/O subsystem **728**, serial port **730**, short-range communications subsystem **740** or any other suitable subsystem **742**, and installed by a user in the RAM **726** or a non-volatile store (not shown) for execution by the processor **738**. Such flexibility in application installation increases the functionality of the device and may provide enhanced on-device functions, communication-related functions, or both. For example, secure communication applications may enable electronic commerce functions and other such financial transactions to be performed using the UE **700**.

[0079] In a data communication mode, a received signal such as a text message or web page download will be processed by the communication subsystem **711** and input to the processor **738**, which may further process the received signal for output to the display **722**, or alternatively to an auxiliary I/O device **728**.

[0080] A user of UE **700** may also compose data items such as email messages for example, using the keyboard **732**, which may be a complete alphanumeric keyboard or telephone-type keypad, or a virtual keyboard, among others, in conjunction with the display **722** and possibly an auxiliary I/O device **728**. Such composed items may then be transmitted over a communication network through the communication subsystem **711**.

[0081] For voice communications, overall operation of UE **700** is similar, except that received signals would typically be output to a speaker **734** and signals for transmission would be generated by a microphone **736**. Alternative voice or audio I/O subsystems, such as a voice message recording subsystem, may also be implemented on UE **700**. Although voice or audio signal output is generally accomplished primarily through the speaker **734**, display **722** may also be used to provide an indication of the identity of a calling party, the duration of a voice call, or other voice call related information for example.

[0082] Serial port **730** in **Figure 7** may be implemented in a personal digital assistant (PDA)-type UE for which synchronization with a user's desktop computer (not shown)

may be desirable, but is an optional device component. Such a port **730** would enable a user to set preferences through an external device or software application and would extend the capabilities of UE **700** by providing for information or software downloads to UE **700** other than through a wireless communication network. The alternate download path may for example be used to load an encryption key onto the device through a direct and thus reliable and trusted connection to thereby enable secure device communication. As will be appreciated by those skilled in the art, serial port **730** can further be used to connect the UE to a computer to act as a modem or for charging purposes.

[0083] Other communications subsystems **740**, such as a short-range communications subsystem, is a further optional component which may provide for communication between UE **700** and different systems or devices, which need not necessarily be similar devices. For example, the subsystem **740** may include an infrared device and associated circuits and components or a Bluetooth™ communication module to provide for communication with similarly enabled systems and devices. Subsystem **740** may further include non-cellular communications such as WiFi or WiMAX, or near field communications (NFC).

[0084] Further, the network elements in the embodiments above can be any network element, or part of any network element, including various network servers. Reference is now made to **Figure 8**, which shows a generalized network element.

[0085] In **Figure 8**, network element **810** includes a processor **820** and a communications subsystem **830**, where the processor **820** and communications subsystem **830** cooperate to perform the methods of the embodiments described above.

[0086] Processor **820** is configured to execute programmable logic, which may be stored, along with data, on network element **810**, and shown in the example of **Figure 8** as memory **840**. Memory **840** can be any tangible storage medium.

[0087] Alternatively, or in addition to memory **840**, network element **810** may access data or programmable logic from an external storage medium, for example through communications subsystem **830**.

[0088] Communications subsystem **830** allows network element **810** to communicate with other network elements or to UEs.

[0089] Communications between the various elements of network element **810** may be through an internal bus **850** in one embodiment. However, other forms of communication are possible.

[0090] The embodiments described herein are examples of structures, systems or methods having elements corresponding to elements of the techniques of this application. This written description may enable those skilled in the art to make and use embodiments having alternative elements that likewise correspond to the elements of the techniques of this application. The intended scope of the techniques of this application thus includes other structures, systems or methods that do not differ from the techniques of this application as described herein, and further includes other structures, systems or methods with insubstantial differences from the techniques of this application as described herein.

Claims:

1. A method, at a user equipment ('UE'), comprising:
 - establishing connection to a first network, wherein transmission of a Routing Area Update ('RAU') message initiates a transfer of the connection from the first network to a second network;
 - 5 sending a request to the first network for Circuit Switched Fallback ('CSFB');
 - receiving, responsive to the request, redirection information to the second network;
 - 10 acquiring the second network based on the redirection information;
 - initiating establishment of Circuit Switched ('CS') voice radio bearers with the second network;
 - determining that the UE has no active Packet Switched ('PS') connection;
 - if there is no active PS connection, waiting for a predetermined event to occur following the initiating and before transmitting the RAU message;
 - 15 and
 - after the predetermined event has occurred, establishing the connection with the second network by transmitting the RAU message.
- 20 2. The method of claim 1, wherein the predetermined event is one of the CS voice radio bearers being established and the expiration of a timer.
3. The method of claim 1, wherein the predetermined event is the first of the CS voice radio bearers being established and the expiration of a timer.
- 25 4. The method of claim 1, wherein the UE waits for the predetermined event to occur if the UE did not have a pending data session request on the second network.
5. The method of claim 1, wherein the UE waits for the predetermined event to occur if
- 30 the UE did not have a pending data transmission on the second network.

6. The method of claim 2, wherein the CS voice radio bearers are determined to be established when the UE sends a radioBearerSetupComplete message for the CS domain.
- 5 7. The method of claim 2, wherein an initial value of the timer is configured based on a message from the first network or from the second network.
8. The method of claim 3, wherein an initial value of the timer is greater than an expected time required for the establishment of CS voice radio bearers.
- 10 9. The method of claim 2, wherein the timer is started upon initiating establishment of the CS voice radio bearers.
10. A user equipment comprising:
- 15 a processor;
- a communications subsystem;
- wherein the user equipment is configured:
- establish a connection to a first network, wherein transmission of a Routing Area Update ('RAU') message initiates a transfer of the
- 20 connection from the first network to a second network;
- send a request to the first network for Circuit Switched Fallback ('CSFB');
- receive, responsive to the request, redirection information to the second network;
- 25 acquire the second network based on the redirection information;
- initiate establishment of Circuit Switched ('CS') voice radio bearers with the second network;
- determine that the UE has no active Packet Switched ('PS') connection;
- if there is no active PS connection, wait for a predetermined event to occur
- 30 following the initiate and before transmitting the RAU;

after the predetermined event has occurred, establishing a Packet Switched ('PS') connection with the second network by transmitting the RAU message.

5 11. The user equipment of claim 10, wherein the predetermined event is one of the CS voice radio bearers being established and the expiration of a timer.

12. The user equipment of claim 10, wherein the predetermined event is the first one of the CS voice radio bearers being established and the expiration of a timer.

10 13. The user equipment of claim 10, wherein the UE waits for the predetermined event to occur if the UE did not have a pending data session request on the second network

15 14. The user equipment of claim 10, wherein the UE waits for the predetermined event to occur if the UE did not have a pending data transmission on the second network.

15. The user equipment of claim 10, wherein the CS voice radio bearers are determined to be established when the UE sends a radioBearerSetupComplete message for the
20 CS domain.

16. The user equipment of claim 11, wherein an initial value of the timer is configured based on a message from the first network or from the second network.

25 17. The user equipment of claim 12, wherein an initial value of the timer is greater than an expected time required for the establishment of CS voice radio bearers.

18. The user equipment of claim 11, wherein the timer is started upon initiating the establishment of CS voice radio bearers.

30 19. A method, at a network element, comprising:

receiving a request for Circuit Switched Fallback ('CSFB') from a user
equipment ('UE'), the UE having a connection to a first network;
sending, to the UE, redirection information for transfer of the connection to
a second network;
5 receiving a Routing Area Update ('RAU') message from the UE to initiate
the transfer of the connection to the second network;
determining that the UE has no active Packet Switched ('PS') connection;
if there is no active PS connection waiting for a predetermined event to
occur following the sending and before responding to the RAU; and
10 upon the predetermined event occurring, responding to the RAU
message.

20. The method of claim 19, wherein the predetermined event is one of the UE
establishing CS voice radio bearers and the expiration of a timer.

15

21. The method of claim 19, wherein the predetermined event is the first one of the UE
establishing CS voice radio bearers and the expiration of a timer.

22. The method of claim 19, wherein the network element waits for the predetermined
20 event to occur if the UE did not have a pending data session request on a second
network.

23. The method of claim 22, wherein the network element determines that the UE did
not have a pending data session request on a second network if an Evolved Packet
25 System Mobility Management ('EMM') entity is in idle mode.

24. The method of claim 22, wherein said determining whether the UE did not have an
ongoing data session on the first network or did not have a pending data session
request on the second network is based on a 'follow-on' bit in the RAU message.

30

25. The method of claim 19, wherein the CS voice radio bearers are determined to be established upon receiving, at the network element, a radioBearerSetupComplete message for the CS domain from the UE.

5 26. A network element, comprising:

a processor;

a communications subsystem;

wherein the network element is configured to:

receive a request for Circuit Switched Fallback ('CSFB') from a user

10 equipment ('UE'), the UE having a connection to a first network;

send, to the UE, redirection information for transfer of the connection to a second network;

receive a Routing Area Update ('RAU') message from the UE to initiate the transfer to the second network;

15 determine that the UE has no active Packet Switched ('PS') connection;

if there is no active PS connection, wait for a predetermined event to occur following the send and before responding to the RAU; and

upon the predetermined event occurring, respond to the RAU message.

20 27. The network element of claim 26, wherein the predetermined event is one of the UE establishing CS voice radio bearers and the expiration of a timer.

28. The network element of claim 26, wherein the predetermined event is the first one of the UE establishing CS voice radio bearers and the expiration of a timer.

25

29. The network element of claim 26, wherein the network element is configured to wait for the predetermined event to occur if the did not have a pending data session request on a second network.

30

30. The network element of claim 29, wherein the network element determines that the UE did not have a pending data session request on a second network if an Evolved Packet System Mobility Management ('EMM') entity is in idle mode.

31. The network element of claim 29, wherein said determining whether the UE did not have a pending data session request on the second network is based on a 'follow-on' bit in the RAU message.

5

32. The network element of claim 26, wherein the CS voice radio bearers are determined to be established upon receiving, at the network element, a radioBearerSetupComplete message for the CS domain from the UE.




FIG. 1
(prior art)

2/8





FIG. 2

**FIG. 3**

4/8





FIG. 4

5/8

**FIG. 5**

6/8



FIG. 6





FIG. 7

8/8

**FIG. 8**

