

(19) AUSTRALIAN PATENT OFFICE

(54) Title
A method and device for performing communication in digital subscriber line technology

(51)⁶ International Patent Classification(s)
H04B 1/38 (2006.01) 20060101AFI2007102
H04B 1/38 5BHCN
PCT/CN2007/000196

(21) Application No: 2007240059 (22) Application Date: 2007 .01 .18

(87) WIPO No: W007/118388

(30) Priority Data

(31) Number	(32) Date	(33) Country
200610072439.0	2006 .04 .13	CN

(43) Publication Date : 2007 .10 .25

(71) Applicant(s)
HUAWEI TECHNOLOGIES CO., LTD.

(72) Inventor(s)
Shi, Qingquan

(74) Agent/Attorney
Griffith Hack, Level 19 109 St Georges Terrace, Perth, WA, 6000

(56) Related Art
US 6567473
CN 1716989
US 2002/0137467
CN 1613190

(12) 按照专利合作条约所公布的国际申请

(19) 世界知识产权组织
国际局



(43) 国际公布日
2007年10月25日 (25.10.2007)

PCT


(10) 国际公布号
WO 2007/118388 A1

- (51) 国际专利分类号:
H04B 1/38 (2006.01)
- (21) 国际申请号: PCT/CN2007/000196
- (22) 国际申请日: 2007年1月18日 (18.01.2007)
- (25) 申请语言: 中文
- (26) 公布语言: 中文
- (30) 优先权:
200610072439.0
2006年4月13日 (13.04.2006) (CN)
- (71) 申请人 (对除美国外的所有指定国): 华为技术有限公司 (HUAWEI TECHNOLOGIES CO., LTD.)
[CN/CN]: 中国广东省深圳市龙岗区坂田华为总部办公楼, Guangdong 518129 (CN).
- (72) 发明人: 及
- (75) 发明人/申请人 (仅对美国): 石清泉 (SHI, Qingquan)
- (74) 代理人: 北京同达信恒知识产权代理有限公司 (BEIJING TONGDAXINHENG INTELLECTUAL PROPERTY AGENCY LTD.); 中国北京市西城区裕民路18号北环中心A座2002, Beijing 100029 (CN).
- (81) 指定国 (除另有指明, 要求每一种可提供的国家保护): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BW, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LT, LU, LV, LY, MA, MD, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RS, RU, SC, SD, SE, SG, SK, SL, SM, SV, SY, TH, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

[见续页]

(54) Title: A METHOD AND DEVICE FOR PERFORMING COMMUNICATION IN DIGITAL SUBSCRIBER LINE TECHNOLOGY

(54) 发明名称: 一种在数字用户线技术中进行通信的方法和装置



(57) Abstract: A method and transmitter receiver sets are used to perform communication in digital subscriber line technology. The method includes the following steps of: acquiring communication performance parameter; the first transmitter receiver set and the second transmitter receiver set using the predetermined communication standard to perform communication when the communication performance parameter is equal to the predetermined value or greater than the predetermined value, the predetermined communication standard is respectively set in the first transmitter receiver set and the second transmitter receiver set. The bit table and the gain table predetermined are respectively stored in the first transmitter receiver set and the second transmitter receiver set. The method can rapidly switch to the bit table and the gain table predetermined using simple message or enquiry answer mechanism when great wideband noise exists. The method has no need of interchanging the bit table and the gain table.

(57) 摘要:

一种在数字用户线技术中进行通信的收发装置和方法。方法包括下述步骤: 获得通信性能参数; 当通信性能参数达到或超过预定值时, 第一收发装置和第二收发装置采用预定的通信规则进行通信, 所述的预定的通信规则分别设置在第一收发装置和第二收发装置中。将预先确定的比特表、增益表分别保存在第一收发装置和第二收发装置中。当出现很大的宽带噪声时, 利用简单的消息或询问-应答机制, 可向预先确定的比特表、增益表快速切换。该方法不需要交换比特表、增益表。

WO 2007/118388 A1



(84) 指定国 (除另有指明, 要求每一种可提供的地区保护): ARIPO (BW, GH, GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), 欧亚 (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), 欧洲 (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LI, LU, LV, MC, NL, PL, PT, RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG)。

本国际公布:

— 包括国际检索报告。

所引用双字母代码及其它缩写符号, 请参考刊登在每期PCT公报期刊起始的“代码及缩写符号简要说明”。

A METHOD AND DEVICE FOR PERFORMING COMMUNICATION IN
DIGITAL SUBSCRIBER LINE TECHNOLOGY

Field of the invention

5 The present invention relates to a communication technique, especially to a method and a device for performing communication in digital subscriber line technology.

Background of the Invention

After several years of development, ADSL (asymmetric digital subscriber line)
10 technology has developed from the first generation to ADSL2 (second generation ADSL), ADSL2+ (ADSL2 with downlink bandwidth being extended) and more recent VDSL2 (second generation very high rate digital subscriber line). The frequency band being used is increasing gradually, and the bandwidth is also increasing gradually. The ADSL and ADSL2 employ a frequency spectrum below 1.1 MHz in downlink and are
15 able to provide a maximum downlink rate of 8 Mbps, the ADSL2+ extends the downlink bandwidth to 2.2 MHz and is able to provide a maximum downlink rate of 24 Mbps, and the VDSL2 can even employ a frequency spectrum up to 30 MHz and is able to provide a maximum access rate of 100 Mbit/s which is symmetrical in uplink and downlink. The above digital subscriber line technologies are totally called as
20 xDSL.

Because the transmission medium for the xDSL is an unshielded twisted-pair, and electromagnetic coupling exists between different twisted-pairs, the signal transmitted on a twisted-pair may be transmitted to another twisted-pair through electromagnetic
25 coupling to form a crosstalk. To reduce such a crosstalk, the twisted-pairs adopt different pitches, and the xDSL adopts differential signal transmission and reception, to counteract the common mode interference signal as far as possible by using the symmetry of twisted-pairs. However, in reality, the symmetry of twisted-pairs is relative and the crosstalk still exists. In addition, the interference signal in the ambient
30 environment may also be coupled to the twisted-pairs, because the symmetry of twisted-pairs is limited and the interference signal can be converted into a differential mode signal to cause interference.

The crosstalk between pairs may greatly affect the service. For example, when a pair 1 is trained, its adjacent lines have no service, and a higher activate rate can be achieved with respect to a given signal to noise ratio margin. Hereafter, the adjacent lines also
5 start to training, and signals emitted from these lines cause a crosstalk signal on the pair 1, which may result in a noise increase that may reach to ten and more dBs. At this time, the originally set signal to noise ratio margin of the pair 1 (generally of 6 dB) cannot ensure the operation at the original bit error rate and rate by the lines. At this
10 time, the better case may result in an increased bit error rate, and the worse case may result in link break and re-training, causing a service interruption. This problem can be more serious in case of VDSL2. Because the VDSL2 means a higher frequency and a shorter line, and the remote crosstalk increases with the frequency and decreases with the increase of distance, the crosstalk has a greater influence. The ADSL2+ defines a fast training mode. Although the fast re-training may recover the connection within a
15 minimum duration of 3 seconds, an influence to the service cannot be completely avoided. Moreover, some services such as voice over IP may require to re-connect due to problems such as link drop, and therefore, keeping a good communication connection quality (for example, no link drop) may be very important to service quality and user experience.

20

In the prior art, there are three kinds of solutions to solve the crosstalk caused by changing the adjacent line from unusable still state (in the silent state, there is no signal in the line) to normal use. The above three kinds of technical solutions will be
25 respectively described in the following.

Solution one, by increasing the target Signal to Noise Ratio (SNR) margin of the pair 1, a larger signal to noise ratio margin is reserved when training the pair 1, so that when the crosstalk suddenly increases, the communication can still keep the target bit
30 error rate as long as the increase does not reach to or exceed the target signal to noise ratio margin, and there is an enough margin to avoid the re-training. This solution has the benefits of simplicity and practicability, but also the deficiency that increasing the

signal to noise ratio margin may a reduced rate that can be achieved on the pair 1. Moreover, because the crosstalk noise is generally not flat, that is to say, noise power spectrum densities at different frequency points are different, and the signal to noise ratio margin is a flat value such that substantially equal values are reserved as margins
5 for signal to noise ratios of all the sub-channels, in view of a fact that the crosstalk is serious only in some frequency ranges, a too higher signal to noise ratio will waste the transmission capacity in the frequency bands where the crosstalk influence is very small.

- 10 Solution two is a seamless rate adaptation (SRA) solution. When the signal to noise ratio of the line reduces due to the crosstalk, the SRA solution ensure the signal to noise ratio margin by reducing the number of bits modulated on the sub-carriers being affected, so that the bit error rate is not higher that the target value. According to this solution the bit allocating can be adjusted automatically according to the noise
15 distribution, so as to avoid the problem of solution one. However, because it is necessary in the SRA solution to calculate and update bit tables and gain tables for the sub-carriers (bit allocation tables and gain adjustment tables for the sub-carriers in case of multiple carrier communication. See ADSL or VDSL standard of ITU-T), the amount of the data is very large. Limited by transmission capability of the channel for
20 transmitting the overhead, the solution has a lower response speed. However, the crosstalk from the adjacent lines suddenly increases at the moment of entering the training, and therefore the re-training may be performed due to consecutive failures, before completing the adjustment to the transceiver. Further, it is necessary in the SRA solution to transmit a lot of data (bit and gain table) between the receiving device and
25 the transmitting device. However, the signal to noise ratio of the channel has reduced, and the process of updating the bit and gain tables may fail due to errors.

Solution three, in the ITU-T G.993.2 standard (also called VDSL2), a concept of virtual noise (VN) is introduced, which is a noise obtained by shaping as required.

- 30 Figure 1 shows a relation between the virtual noise and the actual noise, where the dashed line represents a virtual noise variation curve and the solid line represents a noise variation curve. If such a virtual noise is used to calculate the signal to noise ratio

and the bit load of each of the sub-carriers is calculated, a VN based line rate can be obtained. By setting an appropriate VN not lower than the maximal possible crosstalk noise in a basic bundled unit of the cable (for example, in case of VDSL, for a basic unit of 25 pairs, the VN is setting as not lower than the crosstalk generated when 24 pairs of lines are activated at the same time), the pair 1 will not suffer a re-training even if these pairs are trained after the pair 1 reaches the showtime (a term for special use in the standard, also called operating state). Moreover, because of adopting a shaped noise, enough margins are only reserved on the required sub-channels to avoiding the waste due to simply setting a flat target signal to noise ratio margin. However, this solution is still a conservative solution because of the following reason. For security, it is required to design the VN according to the maximal possible crosstalk noise, for example, the worst case of 1%. However, the crosstalk is not so bad actually in many cases, or is in the worst case only during a very short period, so that the solution always running in this conservative mode can still making the waste of channel capacity.

Summary of the Invention

An object of the present invention is to provide a method and system for performing communication in digital subscriber line technology.

In accordance with a first aspect of the present invention, there is provided a communication method for a digital subscriber line, comprising:

obtaining, by a first transceiver, a communication performance parameter according to received signals;

transmitting, by the first transceiver, a switch request message to a second transceiver when the communication performance parameter reaches or exceeds a predetermined value;

sending, by the first transceiver, an experiential bit table calculating parameter to the second transceiver through information interaction; and

upon receiving the switch request message, switching to a bit table calculated based on the experiential bit table calculating parameter, and instructing the first

transceiver to execute a synchronous switch through synchronization symbols, by the second transceiver.

In accordance with a second aspect of the present invention, there is provided a
5 transceiver for a digital subscriber line, comprising:

a receiving module, configured to receive a signal from a peer transceiver;

a monitor module, configured to obtain a communication performance parameter based on the received signal; and

10 a processing module, configured to generate a switch request message when the communication performance parameter reaches or exceeds a predetermined value, transmit the switch request message and experiential bit table calculating parameter to the peer transceiver through a transmitting module, wait for a synchronization signal from the peer transceiver; and initiate a switch unit upon receiving the synchronization signal from the peer transceiver;

15 the switch unit configured to switch to a bit table calculated based on the experiential bit table calculating parameter;

the transmitting module configured to transmit signals and the switch request message to the peer transceiver.

20 In accordance with a third aspect of the present invention, there is provided a transceiver system in digital subscriber line technology, comprising a first transceiver and a second transceiver communicating through a subscriber line, wherein,

the first transceiver is configured to receive signals from the second transceiver; obtain a communication performance parameter according to the received signals;

25 generate a switch request message when the communication performance parameter reaches or exceeds a predetermined value; transmit the switch request message to the second transceiver and wait for a synchronization signal from the second transceiver; transmit experiential bit table calculating parameter to the second transceiver; and switch to a bit table calculated based on the experiential bit table calculating parameter
30 upon receiving the synchronization signal from the second transceiver; and

6a

the second transceiver is configured to receive the switch request message from the first transceiver; switch to a bit table calculated based on the experiential bit table calculating parameter upon receiving the switch request message; and instruct the first transceiver to execute a synchronous switch through synchronization symbols.

5

According to the embodiments of the present invention, a bit table and a gain table are determined in advance and the determined bit table and gain table are respectively saved in the first transceiver and the second transceiver, or a calculation rule that can be understood and used by the first transceiver and the second transceiver is

10

determined in advance. When a large wideband noise (for example, crosstalk) presents, a fast switch from the currently used bit table and gain table to the bit table and gain table determined in advance is performed by using a simple message or query-response mechanism, or a new bit table and gain table are calculated by using the currently used bit table and gain table according to the rule determined in advance and a fast switch to

15

the new bit table and gain table is performed. Because it is not necessary to exchange the bit table and gain table between the first transceiver and the second transceiver, the solutions according to the embodiments of the present invention have the advantages of fast switch speed and high reliability. When the above wideband noise decreases (for example, the user of a crosstalk source turns off the modem), the SNRM may be calculated according to the current channel, and the frequency spectrum utilization may be increased by increasing the rate through the SRA.

20

Brief Description of the Drawings

Figure 1 shows an example about the relation between the virtual noise the actual noise;

25

Figure 2 shows a schematic diagram of a receiving system according to an embodiment of the present invention;

5 Figure 3 shows a schematic diagram of the relation between the line noise, the signal to noise ratio margin and the line rate according to one embodiment of the present invention;

10 Figure 4 shows a schematic diagram of a query message and a response message according to one embodiment of the present invention;

Figure 5 shows a query-response process between the first transceiver and the second transceiver according to one embodiment of the present invention;

15 Figure 6 is a schematic diagram showing the case where a failure occurs in the query-response process between the first transceiver and the second transceiver according to one embodiment of the present invention; and

20 Figure 7 shows a schematic diagram of performing a bit table switch by using the query-response process between the first transceiver and the second transceiver according to one embodiment of the present invention.

Detailed Description of the Embodiments

25 For ease in understanding and implementing the present invention by those skilled in the art, the embodiment of the present invention will be described in connection with the accompanying drawings.

30 As shown in figure 2, one embodiment of the present invention discloses a transceiver system in the digital subscriber line technology, including: a first transceiver configured to acquire a communication performance parameter; and a second transceiver configured to acquire a communication performance parameter. When the communication performance parameter reaches or exceeds a predetermined value, the

first transceiver communicates with a second transceiver according to a predetermined communication rule which is provided in the first transceiver, or based on the parameters in a bit table and a gain table calculated according to the actual noise. When the communication performance parameter reaches or exceeds a predetermined value, the second transceiver communicates with the first transceiver according to a predetermined communication rule which is provided in the second transceiver, or based on the parameters in a bit table and a gain table calculated according to the actual noise.

The configuration and the function of the first transceiver are the same as that of the second transceiver. One of them may be arranged at the office side, and another of them may be arranged at the subscriber side. The transceivers includes: a receiving module configured to receive a signal and a message from the peer transceiver; a monitor module configured to obtain a communication performance parameter from the acquiring, the communication performance parameter including signal to noise ratio, signal to noise ratio margin and bit error rate; a processing module configured to perform the switch of the predetermined communication rule according to the communication performance parameter from the monitor module and generate a switch message, and perform the switch for the predetermined communication rule according to the switch message, the predetermined communication rule including the bit table and/or the gain table; a transmitting module configured to transmit a signal and the switch message generated by the processing module to the peer transceiver.

The processing module includes: a storage unit configured to store the bit tables and the gain tables respectively according to the two communication rules and the bit tables and the gain tables calculated according to the actual noise, and some configuration parameters such as switch threshold for triggering the bit tables and the gain tables (bi & gi) defined according to the bit error rate or the signal to noise ratio margin; a judgment unit configured to judge whether the communication performance parameter reaches or exceeds the predetermined value, and if the communication performance parameter reaches or exceeds the predetermined value, generate a switch message and transmitting the switch message to the peer end through the transmitting module, wait

for a synchronization signal from the peer end, and initiate a switch unit if the synchronization signal is obtained from the peer end within a predetermined time; the switch unit configured to switch to the predetermined bit table and the predetermined gain table.

5

The transceivers also includes: a seamless rate adaptor configured to calculate a bit table and a gain table according to the actual noise, and take them as a new communication rule to increase the rate when the noise decreases. The receiving module is also configured to receive the bit table and the gain table transmitted from the peer end and the transmitting module is also configured to transmit the bit table and the gain table to the peer end.

10

The embodiments of the present invention also disclose a method of performing communication in the digital subscriber line technology, including: obtaining a communication performance parameter; judging whether the communication performance parameter reaches or exceeds the predetermined value, if the communication performance parameter reaches or exceeds the predetermined value, notifying the peer transceiver through a message and making the transceivers of both ends to using parameters in the predetermined bit table and the predetermined gain table to perform the communication, and if the communication performance parameter does not reach or exceed the predetermined value, making them to use parameters in the bit table and the gain table calculated according to the actual noise to perform the communication.

15

20

To obtain the communication performance parameters, the monitor module continues to monitor the signal received by the receiving module, and obtains the communication performance parameters such as signal to noise ratio, signal to noise ratio margin and bit error rate from the received signal, so as to notify the peer transceiver when one or more of these parameters reach or exceed predetermined values. Therefore, the transceivers of both ends adopt parameters in the predetermined bit table and the predetermined gain table to perform the communication.

25

30

Upon obtaining the communication performance parameter, the judgment module judges whether the communication performance parameter reaches or exceeds the predetermined value. If the communication performance parameter reaches or exceeds the predetermined value, the peer transceiver is notified through a message and the transceivers of both ends are instructed to use parameters in the predetermined bit table and the predetermined gain table to perform the communication. If the communication performance parameter does not reach or exceed the predetermined value, the transceivers of both ends are instructed to use parameters in the bit table and the gain table calculated according to the actual noise to perform the communication.

To judge whether the communication performance parameter reaches or exceeds the predetermined value, a virtual noise or experiential bit table calculating parameter, a signal to noise ratio margin threshold and/or a bit error rate threshold may be pre-set in the first transceiver (assuming that the first transceiver is arranged at the office side) before the training. The experiential bit table calculating parameter is a bit number reduced from the bit number calculated according to the actual noise to provide the bit number of the signal to noise ratio margin on each tone (sub-frequency band), then the virtual noise or experiential bit table calculating parameter, the signal to noise ratio margin threshold and/or the bit error rate threshold as set are saved in the storage module of the first transceiver. In order to send the virtual noise or experiential bit table calculating parameter, the signal to noise ratio margin threshold and/or the bit error rate threshold to the second transceiver (assuming that the second transceiver are arranged at the subscriber side) through information interaction in the training process, and the second transceiver saves the virtual noise or experiential bit table calculating parameter, the signal to noise ratio margin threshold and/or the bit error rate threshold in the storage module. In the training, the processing module of the second transceiver calculates two sets of signal to noise ratio table, bit table and gain table respectively based on the preset virtual noise or experiential bit table calculating parameter and the actual noise: SNR_{vi} , B_{vi} and G_{vi} , and SNR_{ri} , b_{ri} and G_{ri} , and saves the SNR_{vi} , B_{vi} and G_{vi} , and the SNR_{ri} , b_{ri} and G_{ri} in the local storage module and transmits them to the first transceiver through information interaction, in order to save them in the storage module of the first transceiver. Then the first transceiver and the second

transceiver implement the connection based on the SNR_{ri}, b_{ri} and G_{ri} calculated according to the actual noise.

5 The process of judging whether the communication performance parameter reaches or exceeds the predetermined value is described as follows. The first transceiver and/or the second transceiver compare the monitored signal to noise ratio, signal to noise ratio margin and bit error rate with the preset thresholds stored in their storage modules. Taking the monitoring of the signal to noise ratio margin as an example, when it is found that the signal to noise ratio margins of multiple sub-carriers (according to the power distribution of the crosstalk, there are many consecutive sub-carriers in most cases), for example, 10 sub-carriers, are lower than the preset thresholds, which indicates a case where the training of an adjacent pair causes a sudden increase of the crosstalk, the transceiver generates a switch request message and transmits the switch request message to the peer transceiver. Upon receiving the switch request message, 10 the peer transceiver switches to the bit table and the gain table calculated based on the virtual noise or experiential bit table calculating parameter, and then returns a confirmation message and a synchronization message (it is also possible to only return a confirmation message and a synchronization message). Upon receiving the confirmation message and the synchronization message, the transceiver switches to the bit table and the gain table 15 calculated based on the virtual noise. Thus, the first transceiver and the second transceiver can perform the communication by using the bit table and the gain table calculated from the virtual noise.

25 The predetermined bit table and the predetermined gain table may be obtained according to the preset virtual noise or may be an experiential bit table.

30 The virtual noise may be the noise in case of the worst line crosstalk. Thus, in the training, in addition to obtaining a signal to noise ratio table SNR_{ri}, a bit table B_{ri} and a gain table G_{ri} according to the actual noise on the U-interface (an interface between the xDSL transceiver and the external twisted-pair), the first transceiver and the second transceiver also calculate another corresponding data (SNR_{vi}, B_{vi} and G_{vi}) according to the preset virtual noise or experiential bit table calculating parameter. The signal to

noise ratio table SNR_{ri} , the bit table B_{ri} and the gain table G_{ri} respectively represent the signal to noise ratio, the number of carried bits and the relative gain adjustment coefficient of each sub-carrier. (SNR_{vi} , B_{vi} and G_{vi}) are respectively saved in the storage modules of the first transceiver and the second transceiver. When the
5 transceiver detects that the signal to noise ratio SNR_{ri} and/or the signal to noise ratio margin $SNRM_{i}$ and/or the bit error rate BER reach or exceed a preset value due to the crosstalk generated by training the adjacent pair, the transceiver transmits a switch request message to the peer end transceiver, so that the peer end transceiver switches to the B_{vi} and the G_{vi} calculated according to the saved virtual noise or experiential bit
10 table calculating parameter, and the synchronous switch between the first transceiver and the second transceiver is implemented through the switch synchronization signal.

The experiential bit table may be obtained by experience, for example, according to experiential distribution of the crosstalk. By subtracting a corresponding bit number
15 from the actual noise-based bit gain table B_{ri} & G_{ri} obtained according to the training result (the increase of signal to noise ratio margin caused by the subtracted bit number should be greater than or equal to the decrease of signal to noise ratio margin caused by the crosstalk), it is necessary to design the virtual noise and transmit it the peer end, thereby further simplifying the operations.

20 Because the bit load and gain adjustment table calculated according to the virtual noise is a very conservative solution, although the signal to noise ratio margin and the bit error rate meet the requirement (usually reach or exceed the requirement), the resultant rate is lower than the value in case of actual noise. The line rate may be increased step-
25 by-step according to the actual SNR_{ri} . Accordingly, a fast decreasing rate may be obtained to accommodate the sudden increase of noise, and to slowly increase the rate to accommodate the dynamic rate adjustment process with the noise being reduced. Because the line parameters in this fast switch process are calculated in advance, and saved in the first transceiver and the second transceiver, the switch can be implemented
30 only through a simple message and a synchronization message when it is necessary to perform the switch. This is much faster and more reliable than the original SRA or BS, because the SRA or BS needs to transmit the updated bit table and gain table. In case

of SRA or BS, a failure may occur in transmitting the bit table and the gain table due to the bit errors in the transmission process, if the channel is poor. The solution according to the embodiment of the present invention will not cause this problem, and when the line crosstalk noise decreases, the signal to noise ratio increases and the bit error rate decreases, so that a large amount of data required by the SRA can be transmitted.

When entering the showtime, the signal to noise ratio table SNR_{ri} , the bit table B_{ri} and the gain table G_{ri} calculated according to the actual noise may act as transmission parameters, to achieve a higher transmission rate.

Figure 3 shows a diagram of the relation between the line noise, the signal to noise ratio margin and the line rate. As shown in figure 3, the abscissa axis represents time, and the relation between the line noise, the signal to noise ratio margin and the line rate are shown by the ordinate. At time a, because the adjacent pair starts the training to greatly increase the line noise and sharply reduce the SNRM, according to the embodiment of the present invention, the switch to a predetermined bit gain table is performed to reduce the rate. During the period from time b to time c, when the training of the adjacent pair completes, the adjacent pair enters a power control phase and the crosstalk decreases, i.e., the line noise decreases, so that the SNRM increases.

Thus, according to the embodiment of the present invention, the rate may be adjusted through the SRA to increase the line rate. During the period from time d to time e, when the subscriber of the adjacent pair turns off the modem, the crosstalk greatly decreases, i.e., the line noise greatly decreases, so that the SNRM increases. Thus, according to the embodiment of the present invention, the rate may be adjusted through the SRA to increase the line rate.

To implement the embodiments of the present invention, a switch message is also defined. In the standard for VDSL2 (ITU-T G.993.2), an eoc (embedded overhead channel) message for an OLR command is defined. The command type field is $(0000001)_2$, subscript 2 represents binary, and other fields are defined in the following tables.

Name	Length (octets)	Octet number	Content
Request Type 1	$5 + 4 \times N_f$ ($N_f \leq 128$)	2	04_{16} (NOTE)
		3 to 4	2 octets for the number of sub-carriers N_f to be modified
		5 to $4 + 4 \times N_f$	$4 \times N_f$ octets describing the sub-carrier parameter field for each sub-carrier
		$5 + 4 \times N_f$	1 octet for SC
Request Type 2	For further study	2	05_{16} (NOTE)
		All others	Reserved by the ITU-T
Request Type 3	For further study	2	06_{16} (NOTE)
		All others	Reserved by the ITU-T
NOTE – All other values for octet number 2 are reserved by the ITU-T			

Table 11-7/G.993.2 – Reason codes for OLR responses

Reason	Octet value	Applicable to Defer Type 1	Applicable to Reject Type 2	Applicable to Reject Type 3
Busy	01_{16}	X	X	X
Invalid parameters	02_{16}	X	X	X

- 5 According to the above table, Type 1 has been used, and according to the embodiment of the present invention, Type 2 or Type 3 may be used. The length of the fields is set to 2 octets, and the contents of the second octets are respectively (as shown in the table): 05_{16} , 06_{16} , where subscript 16 represents hex. Another message Type 4 may be defined, whose length is 2 octets, the content of the second octet being 07_{16} . Therefore,
- 10 the definitions in the current standard are not affected. As such, the format of the response message corresponding to the switch message is as shown in the following table.

Name	Length (octets)	Octet number	Content
Defer Type 1 Request	3	2	81 ₁₆ (NOTE)
		3	1 octet for reason code (Table 11-7)
Reject Type 2 Request	3	2	82 ₁₆ (NOTE)
		3	1 octet for reason code (Table 11-7)
Reject Type 3 Request	3	2	83 ₁₆ (NOTE)
		3	1 octet for reason code (Table 11-7)
IACK	3	2	8B ₁₆ (NOTE)
		3	1 octet for SC

NOTE – All other values for octet number 2 are reserved by the ITU-T

Therefore, if the existing Type 2 or Type 3 is directly adopted, corresponding message fields are modified. The length of a message for granting the switch is 2 octets, where the second octet is 72₁₆ or 73₁₆ (corresponding to the message type). The length of a message for rejecting the switch is 3 octets, where the second octet is 82₁₆ or 83₁₆ (corresponding to the message type), and the third octet is the cause for rejecting (alternatively, if the cause is not needed, the length is 2 octets). The length in case of newly defined Type 4, a response Type 4 is defined and the length of a message for granting the switch is 2 octets, where the second octet is 73₁₆, and the length of a message for rejecting the switch is 3 octets, where the second octet is 83₁₆, and the third octet is the cause for rejecting (alternatively, if the cause is not needed, the length is 2 octets). The synchronization signal is based on the signal defined in G.993.2, i.e., the synchronization signal is represented by switches between all-0 and all-1 of synchronization symbols.

15

In the above method, the messages have more capacity, and thus are able to facilitate the communication between two parties. To increase the switch speed, a switch request message Type 2 or Type 3 or Type 4 may be transmitted without acknowledgement,

and then the transceiver executes the switch action upon receiving this message, and instructs the receiving end through synchronization symbols to execute the synchronous switch. If rejected, the synchronization message is not transmitted. Thus, the transmission and parsing process of the message content is avoided, thereby
5 increasing the switch speed and reducing the error probability.

According to the above embodiment, two sets of parameters are calculated in advance in the training, where one set is a bit table and gain table obtained according to the current channel parameter (for example, channel noise), and another set is a
10 conservative bit table and gain table obtained according to the virtual noise or experiential bit table calculating parameter. These two sets of parameters are saved in the first transceiver and the second transceiver at the same time. When the training is completed, the transceiver uses the bit table and the gain table obtained according to the current channel parameter, called current bit table and gain table, and this bit table
15 and gain table is dynamically adjusted with the change in the channel (for example, bit swapping). When a very large wide band noise (for example, crosstalk) presents, a fast switch from the current bit table and gain table to the bit table and gain table corresponding to the virtual noise is performed by using a simple message. Because it is not necessary to exchange the bit table and gain table and only a simple message is
20 exchanged, compared with the bit exchange, the solutions according to the embodiments of the present invention have the advantages of fast switch speed and high reliability. When the above wideband noise decreases (for example, the user of a crosstalk source turns off the modem), the SNRM may be calculated according to the current channel parameter, and the frequency spectrum utilization may be increased by
25 increasing the rate through the SRA.

In addition, because the switch speed in the solutions according to the embodiment of the present invention is fast, link drops may be avoided by responding to the feature of sudden increasing of the crosstalk. In case of SRA, failures are likely to occur because
30 of response speed and errors in the parameter exchange process, thereby causing the re-training and interrupting the service.

To obtain the communication performance parameter, the following query-response mode may be adopted. Specifically, the line quality is determined according to the result of query-response. The method of obtaining the line quality through the query-response mode is described as follows.

5

As shown in figure 4, a query message and a response message are constructed. Figure 4 (a) shows the query message, and figure 4 (b) shows the response message. It is assumed that the first transceiver transmits the query message to the second transceiver.

10

When the counter in the query message received by the second transceiver is X (X falls within the range of 0 - 255), the message is responded immediately, and the counter octet in the responded response message should be X+ 1. If an overflow occurs, the value of the counter octet is set to zero. When the first transceiver receives the response message and the content of the counter octet is valid, a query message is transmitted after a time interval (T), and the content of the counter octet is that of the valid counter octet received from the second transceiver. The further course is similar to the above. Figure 5 shows a query-response process between the first transceiver and the second transceiver.

20

As shown in figure 6, when the second transceiver does not correctly receive the query message from the first transceiver, the second transceiver does not respond. When the first transceiver does not correctly receive the response message from the receiving end, the first transceiver will continually re-transmit the query message identical to the previous one at a prescribed time point.

25

To record the result of query-response, a register may be provided in the first transceiver and the second transceiver, the bits of which respectively record receiving status of n consecutive messages. To facilitate the description, the registers in the first transceiver and the first transceiver are represented respectively with TM and RM.

30

After initialization or after a bit table entry switch, the initial values of the TM and the RM should be zero.

- For the first transceiver, within the current time frame, the first transceiver writes '1' in the current bit of the TM if no valid response message is received within the prescribed time interval, and writes '0' if a valid response message is received within the prescribed time interval. Then, the first transceiver receives the response message within the next time frame, determines the next bit of the TM as the current bit, and writes '1' in the current bit of the TM if no valid response message is received within the prescribed time interval, and writes '0' if a valid response message is received within the prescribed time interval.
- For the second transceiver, within the current time frame, the second transceiver writes '1' in the current bit of the RM if no valid query message is received within the prescribed time interval, and writes '0' if a valid query message is received within the prescribed time interval; then, the second transceiver receives the query message within the next time frame, determines the next bit of the RM as the current bit, and writes '1' in the current bit of the RM if no valid query message is received within the prescribed time interval, and writes '0' if a valid query message is received within the prescribed time interval.
- In the first transceiver, when a predetermined number (i.e., switch threshold) of bits in the TM register are set to '1', a decision is made to perform the switch at a time agreed on between the first transceiver and the second transceiver, for example, to perform the switch of bit table and gain table at the tenth symbol of the next synchronization frame. To ensure the synchronous switch, keep transmitting invalid data after the switch is decided, so that the second transceiver reaches the switch condition as soon as possible, and thus the switch of bit table and gain table is performed at the tenth symbol of the next synchronization frame. Thus, without the need to transmit the switch message between the first transceiver and the second transceiver, the synchronous switch of bit table may be implemented, to cope with various problems such as link drop caused by sudden increase of the line noise (for example, crosstalk). The same mechanism is adapted for the second transceiver in order to perform the switch of bit table.

Figure 7 shows a case of query-response where the TM and the RM have 5 bits and the switch threshold is 3. As shown in figure 7, the solid line represents that the present message transmission is correct, and the dashed line represents that the present message transmission is wrong. In the first time frame, the first transceiver transmits a query message having a counter octet of 001 to the second transceiver, and upon receiving the query message; the second transceiver returns a response message having a counter octet of 002 to the first transceiver. At this time, the bits in the TM and the RM of the first transceiver and the second transceiver do not change, i.e., all are 0. In the second time frame, the TM and the RM respectively shift by one bit circularly in a forward direction, the first transceiver transmits a query message having a counter octet of 002 to the second transceiver, and not receiving the query message, the second transceiver still returns a response message having a counter octet of 002 to the first transceiver. At this time, the current bit (the last one bit as shown in the figure) in the TM and the RM of the first transceiver and the second transceiver are all set to 1. In the third time frame, the TM and the RM respectively shift by one bit circularly in a forward direction, the first transceiver transmits a query message having a counter octet of 002 to the second transceiver, and upon receiving the query message, the second transceiver's receiving is correct, the current bit in the RM of the second transceiver keeps to 0, and then the second transceiver returns a response message having a counter octet of 003 to the first transceiver. Because the first transceiver does not receive the response message within the prescribed time interval, the current bit in the TM of the first transceiver is set to 1. Similar to these, when reaching to the 7th time frame, the number of '1's (switch threshold) in the TM of the first transceiver reaches to 3, and from the 8th time frame, the first transceiver transmit a query message having a wrong counter octet to the second transceiver, so that the number of '1's in the RM of the second transceiver reaches to the switch threshold as soon as possible, in order to perform the switch of bit table at the tenth symbol of the next synchronization frame. Because it is not necessary to re-transmit the message between the first transceiver and the second transceiver, the synchronous switch of bit table can be implemented, and the solutions according to the embodiments of the present invention have the advantages of fast switch speed and high reliability. When the

above wideband noise decreases (for example, the user of a crosstalk source turns off the modem), the SNRM may be calculated according to the current channel parameter, and the frequency spectrum utilization can be increased by increasing the rate through the SRA, thus increasing the transmission speed.

5

When performing the switch of bit table, the switch of gain table may or may not be performed.

10

In summary, a bit table and gain table are determined in advance, and the determined bit table and gain table are respectively saved in the first transceiver and the second transceiver. When a very large wide band noise (for example, crosstalk) presents, a fast switch from the current bit table and gain table to the previously determined bit table and gain table is performed by using a simple message or a query-response mechanism. Because it is not necessary to exchange the bit table and gain table

15

between the first transceiver and the second transceiver, the solutions according to the embodiments of the present invention have the advantages of fast switch speed and high reliability. When the above wideband noise decreases (for example, the user of a crosstalk source turns off the modem), the SNRM may be calculated according to the current channel parameter, and the frequency spectrum utilization may be increased by

20

increasing the rate through the SRA.

Although the present invention has been described in connection with the embodiments, those skilled in the art know that, there can be many variations and changes to the present invention without departing from the spirit and substance of the present invention, and the scope of the present invention is defined by the appended claims.

25

In the claims which follow and in the preceding description of the invention, except where the context requires otherwise due to express language or necessary implication, the word "comprise" or variations such as "comprises" or "comprising" is used in an inclusive sense, i.e. to specify the presence of the stated features but not to preclude the presence or addition of further features in various embodiments of the invention.

30

It is to be understood that, if any prior art publication is referred to herein, such reference does not constitute an admission that the publication forms a part of the common general knowledge in the art, in Australia or any other country.

5

THE CLAIMS DEFINING THE INVENTION ARE AS FOLLOWS:

1. A communication method for a digital subscriber line, comprising:
obtaining, by a first transceiver, a communication performance parameter
5 according to received signals;
transmitting, by the first transceiver, a switch request message to a second
transceiver when the communication performance parameter reaches or exceeds a
predetermined value;
sending, by the first transceiver, an experiential bit table calculating parameter to
10 the second transceiver through information interaction; and
upon receiving the switch request message, switching to a bit table calculated
based on the experiential bit table calculating parameter, and instructing the first
transceiver to execute a synchronous switch through synchronization symbols, by the
second transceiver.
15
2. The method according to claim 1, wherein the communication performance
parameter comprises at least one of a signal to noise ratio, a signal to noise ratio
margin and a bit error rate.
- 20 3. The method according to claim 1, wherein the switch request message is an
embedded overhead channel, EOC, message.
4. The method according to claim 1, wherein the experiential bit table calculating
parameter is a bit number reduced from the bit number calculated according to the
25 actual noise to provide the bit number of the signal to noise ratio margin on each sub-
frequency band.
5. The method according to claim 1, wherein when the communication
performance parameter reaches or exceeds a predetermined value, the method further
30 comprises: when the second transceiver receives the switch request message from the
first transceiver, transmitting, by the second transceiver, a response message to the first

transceiver through an embedded overhead channel, wherein the content of the response message comprises granting the switch.

5 6. The method according to claim 1, wherein the method further comprises adopting synchronization symbols to perform the synchronous switch of the first transceiver and the second transceiver, wherein the synchronous switch is performed by a transition from all-0 to all-1 of the information carried by the synchronization symbols, or by a reverse transition.

10 7. The method according to claim 1, further comprising:
adjusting the line rate through a seamless rate adaptation, SRA, solution after switching to the bit table calculated based on the experiential bit table calculating parameter.

15 8. A transceiver for a digital subscriber line, comprising:
a receiving module, configured to receive a signal from a peer transceiver;
a monitor module, configured to obtain a communication performance parameter based on the received signal; and
20 a processing module, configured to generate a switch request message when the communication performance parameter reaches or exceeds a predetermined value, transmit the switch request message and experiential bit table calculating parameter to the peer transceiver through a transmitting module, wait for a synchronization signal from the peer transceiver; and initiate a switch unit upon receiving the synchronization signal from the peer transceiver;
25 the switch unit configured to switch to a bit table calculated based on the experiential bit table calculating parameter;
the transmitting module configured to transmit signals and the switch request message to the peer transceiver.

9. The transceiver according to claim 8, wherein the communication performance parameter comprises at least one of a signal to noise ratio, a signal to noise ratio margin and a bit error rate.

5 10. The transceiver according to claim 8, wherein the transceiver further comprises a seamless rate adaptor, configured to calculate a bit table and a gain table according to a current actual noise.

10 11. The transceiver according to claim 8, wherein the experiential bit table calculating parameter is a bit number reduced from the bit number calculated according to the actual noise to provide the bit number of the signal to noise ratio margin on each sub-frequency band.

15 12. The transceiver according to claim 8, wherein the switch request message is an embedded overhead channel message.

13. A transceiver system in digital subscriber line technology, comprising a first transceiver and a second transceiver communicating through a subscriber line, wherein,

20 the first transceiver is configured to receive signals from the second transceiver; obtain a communication performance parameter according to the received signals; generate a switch request message when the communication performance parameter reaches or exceeds a predetermined value; transmit the switch request message to the second transceiver and wait for a synchronization signal from the second transceiver; 25 transmit experiential bit table calculating parameter to the second transceiver; and switch to a bit table calculated based on the experiential bit table calculating parameter upon receiving the synchronization signal from the second transceiver; and

the second transceiver is configured to receive the switch request message from the first transceiver; switch to a bit table calculated based on the experiential bit table 30 calculating parameter upon receiving the switch request message; and instruct the first transceiver to execute a synchronous switch through synchronization symbols.

14. The transceiver system according to claim 13, wherein the communication performance parameter comprises at least one of a signal to noise ratio, a signal to noise ratio margin and a bit error rate.

5

15. A communication method for a digital subscriber line substantially as hereinbefore described with reference to, and as shown in, the accompanying drawings.

10

16. A transceiver for a digital subscriber line substantially as hereinbefore described with reference to, and as shown in, the accompanying drawings.

15

17. A transceiver system in digital subscriber line technology substantially as hereinbefore described with reference to, and as shown in, the accompanying drawings.




FIG. 1




FIG. 2




FIG 3




FIG 4




FIG. 5




FIG. 6




FIG. 7