



(51) International Patent Classification:

H03F 1/02 (2006.01) *H03F 3/68* (2006.01)
H03F 1/07 (2006.01)

(21) International Application Number:

PCT/US2016/017916

(22) International Filing Date:

13 February 2016 (13.02.2016)

(25) Filing Language:

English

(26) Publication Language:

English

(30) Priority Data:

62/116,453 15 February 2015 (15.02.2015) US

(71) Applicant: **SKYWORKS SOLUTIONS, INC.** [US/US];
20 Sylvan Road, Woburn, Massachusetts 01801 (US).

(72) Inventor: **LEHTOLA, Philip John**; 5000 Hunt Road, Cedar Rapids, Iowa 52411 (US).

(74) Agent: **CHANG, James W.**; Fernando Hale & Chang LLP, 4199 Campus Drive, Suite 550, #115, Irvine, California 92612 (US).

(81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

(84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, KM, ML, MR, NE, SN, TD, TG).

Declarations under Rule 4.17:

— as to applicant's entitlement to apply for and be granted a patent (Rule 4.17(ii))

[Continued on next page]

(54) Title: DOHERTY POWER AMPLIFIER HAVING REDUCED SIZE




FIG. 7

(57) Abstract: Doherty power amplifier having reduced size. In some embodiments, a power amplification system can include a supply system configured to provide a high-voltage supply signal, and a Doherty power amplifier configured to receive the high-voltage supply signal and amplify a radio-frequency (RF) signal. The power amplification system can further include an output path configured to receive and route the amplified RF signal to a filter. The output path can be substantially free of an impedance transformation circuit.



Published:

— with international search report (Art. 21(3))

— before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments (Rule 48.2(h))

DOHERTY POWER AMPLIFIER HAVING REDUCED SIZE

CROSS-REFERENCE TO RELATED APPLICATION(S)

[0001] This application claims priority to U.S. Provisional Application No. 62/116,453 filed February 15, 2015, entitled DOHERTY POWER AMPLIFIER HAVING REDUCED SIZE, the disclosure of which is hereby expressly incorporated by reference herein in its entirety.

BACKGROUND

Field

[0002] The present disclosure relates to power amplifiers for radio-frequency (RF) applications.

Description of the Related Art

[0003] In many radio-frequency (RF) applications, an RF signal to be transmitted is typically amplified by a power amplifier. Such a power amplifier can be implemented in a number of ways, including, for example, a Doherty power amplifier.

SUMMARY

[0004] According to some implementations, the present disclosure relates to a power amplification system that includes a supply system configured to provide a high-voltage (HV) supply signal, and a Doherty power amplifier (PA) configured to receive the HV supply signal and amplify a radio-frequency (RF) signal. The power amplification system further includes an output path configured to receive and route the amplified RF signal to a filter. The output path is substantially free of an impedance transformation circuit.

[0005] In some embodiments, the supply system can include a boost DC/DC converter configured to generate the HV supply signal based on a battery voltage V_{batt} . The HV supply signal can be selected such that impedances of the Doherty PA and the filter match sufficiently to allow the output path to be substantially free of the impedance transformation circuit. The impedance of the Doherty PA can have a value of, for example, approximately 50 Ohms.

[0006] In some embodiments, the Doherty PA can include a heterojunction bipolar transistor (HBT). The HBT can be a gallium arsenide (GaAs) device. The HV supply signal can be provided to a collector of the HBT as V_{cc}.

[0007] In some embodiments, the filter can be a transmit (Tx) filter configured to operate in a corresponding Tx frequency band. The Tx filter can be part of a duplexer configured to operate in the Tx frequency band and a corresponding receive (Rx) frequency band.

[0008] In some embodiments, the power amplification system can further include one or more additional Doherty PAs, with each configured to receive the HV supply signal and amplify an RF signal. The power amplification system can further include an output path configured to receive and route the amplified RF signal for each of the one or more additional Doherty PAs to a corresponding filter. The additional output path can be substantially free of an impedance transformation circuit.

[0009] In some embodiments, each filter can have associated with it a corresponding Doherty PA. The power amplification system can be substantially free of a band selection switch between the Doherty PAs and the filters. The power amplification system can have a lower loss than another power amplifier system having similar band handling capability but in which the PAs are operated in low voltage.

[0010] In some teachings, the present disclosure relates to a radio-frequency (RF) module that includes a packaging substrate configured to receive a plurality of components, and a power amplification system implemented on the packaging substrate. The power amplification system includes a supply system configured to provide a high-voltage (HV) supply signal, and a Doherty power amplifier (PA) configured to receive the HV supply signal and amplify an RF signal. The power amplification system further includes an output path configured to receive and route the amplified RF signal to a filter. The output path is substantially free of an impedance transformation circuit.

[0011] In some embodiments, the RF module can be a front-end module (FEM). In some embodiments, the power amplification system can be substantially free of a band selection switch between the Doherty PA and the filter. The power amplification system can have a lower loss than another power

amplifier system having similar band handling capability but in which a Doherty PA is operated in low voltage. The RF module can have an area that is significantly less than another RF module having an amplification system with an impedance transformation circuit and a band selection switch.

[0012] In accordance with a number of implementations, the present disclosure relates to a wireless device having a transceiver configured to generate a radio-frequency (RF) signal, and a front-end module (FEM) in communication with the transceiver. The FEM includes a packaging substrate configured to receive a plurality of components, and a power amplification system implemented on the packaging substrate. The power amplification system includes a supply system configured to provide a high-voltage (HV) supply signal, and a Doherty power amplifier (PA) configured to receive the HV supply signal and amplify a radio-frequency (RF) signal. The power amplification system further includes an output path configured to receive and route the amplified RF signal to a filter. The output path is substantially free of an impedance transformation circuit. The wireless device further includes an antenna in communication with the FEM and configured to transmit the amplified RF signal.

[0013] For purposes of summarizing the disclosure, certain aspects, advantages and novel features of the inventions have been described herein. It is to be understood that not necessarily all such advantages may be achieved in accordance with any particular embodiment of the invention. Thus, the invention may be embodied or carried out in a manner that achieves or optimizes one advantage or group of advantages as taught herein without necessarily achieving other advantages as may be taught or suggested herein.

BRIEF DESCRIPTION OF THE DRAWINGS

[0014] Figure 1 shows a wireless system or architecture that includes an amplification system.

[0015] Figure 2 shows that the amplification system of Figure 1 can include a radio-frequency (RF) amplifier assembly having one or more power amplifiers (PAs).

[0016] Figures 3A-3E show examples of how the PA of Figure 2 can be configured.

[0017] Figure 4 shows that in some embodiments, the amplification system of Figure 2 can be implemented as a high-voltage (HV) power amplification system.

[0018] Figure 5 shows that in some embodiments, the HV power amplification system of Figure 4 can be configured as a Doherty power amplification system.

[0019] Figure 6 shows an example of a traditional Doherty power amplification system.

[0020] Figure 7 shows an example of a Doherty power amplification system having one or more features as described herein.

[0021] Figure 8 shows an HV Doherty power amplification system that can be a more specific example of the HV Doherty power amplification system of Figure 7.

[0022] Figure 9 shows an HV Doherty amplification system that can be a more specific example of the HV Doherty amplification system of Figure 8.

[0023] Figure 10 shows plots of AMAM vs output power, PAE vs output power, ratio of peak power and carrier power vs input power, and collector current vs output power, as Class C bias point is swept, for the HV Doherty amplification system of Figure 9.

[0024] Figure 11 shows gain, output power, emitter follower bias, and collector current characteristics for Class AB and Class C bias configurations associated with the HV Doherty amplification system of Figure 9.

[0025] Figure 12 shows AMAM, PAE, and AMPM characteristics for the HV Doherty amplification system of Figure 9, as well as for a single ended amplification system.

[0026] Figure 13 shows examples of battery level efficiency as a function of average output power for a Buck ET amplification system, a boost average power tracking (APT) amplification system, a Buck APT amplification system, and a boost Doherty amplification system having one or more features as described herein.

[0027] Figure 14 shows that in some embodiments, some or all of an HV Doherty power amplification system having one or more features as described herein can be implemented in a module.

[0028] Figure 15 depicts an example wireless device having one or more advantageous features described herein.

DETAILED DESCRIPTION OF SOME EMBODIMENTS

[0029] The headings provided herein, if any, are for convenience only and do not necessarily affect the scope or meaning of the claimed invention.

Introduction:

[0030] Referring to Figure 1, one or more features of the present disclosure generally relate to a wireless system or architecture 50 having an amplification system 52. In some embodiments, the amplification system 52 can be implemented as one or more devices, and such device(s) can be utilized in the wireless system/architecture 50. In some embodiments, the wireless system/architecture 50 can be implemented in, for example, a portable wireless device. Examples of such a wireless device are described herein.

[0031] Figure 2 shows that the amplification system 52 of Figure 1 typically includes a radio-frequency (RF) amplifier assembly 54 having one or more power amplifiers (PAs). In the example of Figure 2, three PAs 60a-60c are depicted as forming the RF amplifier assembly 54. It will be understood that other numbers of PA(s) can also be implemented. It will also be understood that one or more features of the present disclosure can also be implemented in RF amplifier assemblies having other types of RF amplifiers.

[0032] In some embodiments, the RF amplifier assembly 54 can be implemented on one or more semiconductor die, and such die can be included in a packaged module such as a power amplifier module (PAM) or a front-end module (FEM). Such a packaged module is typically mounted on a circuit board associated with, for example, a portable wireless device.

[0033] The PAs (e.g., 60a-60c) in the amplification system 52 are typically biased by a bias system 56. Further, supply voltages for the PAs are typically provided by a supply system 58. In some embodiments, either or both of the bias system 56 and the supply system 58 can be included in the foregoing packaged module having the RF amplifier assembly 54.

[0034] In some embodiments, the amplification system 52 can include a matching network 62. Such a matching network can be configured to provide input matching and/or output matching functionalities for the RF amplifier assembly 54.

[0035] For the purpose of description, it will be understood that each PA (60) of Figure 2 can be implemented in a number of ways. Figures 3A-3E show non-limiting examples of how such a PA can be configured. Figure 3A shows an example PA having an amplifying transistor 64, where an input RF signal (RF_in) is provided to a base of the transistor 64, and an amplified RF signal (RF_out) is output through a collector of the transistor 64.

[0036] Figure 3B shows an example PA having a plurality of amplifying transistors (e.g., 64a, 64b) arranged in stages. An input RF signal (RF_in) is provided to a base of the first transistor 64a, and an amplified RF signal from the first transistor 64a is output through its collector. The amplified RF signal from the first transistor 64a is provided to a base of the second transistor 64b, and an amplified RF signal from the second transistor 64b is output through its collector to thereby yield an output RF signal (RF_out) of the PA.

[0037] In some embodiments, the foregoing example PA configuration of Figure 3B can be depicted as two or more stages as shown in Figure 3C. The first stage 64a can be configured as, for example, a driver stage; and the second stage 64b can be configured as, for example, an output stage.

[0038] Figure 3D shows that in some embodiments, a PA can be configured as a Doherty PA. Such a Doherty PA can include amplifying transistors 64a, 64b configured to provide carrier amplification and peaking amplification of an input RF signal (RF_in) to yield an amplified output RF signal (RF_out). The input RF signal can be split into the carrier portion and the peaking portion by a splitter. The amplified carrier and peaking signals can be combined to yield the output RF signal by a combiner.

[0039] Figure 3E shows that in some embodiments, a PA can be implemented in a cascode configuration. An input RF signal (RF_in) can be provided to a base of the first amplifying transistor 64a operated as a common emitter device. The output of the first amplifying transistor 64a can be provided through its collector and be provided to an emitter of the second amplifying transistor 64b operated as a common base device. The output of the second

amplifying transistor 64b can be provided through its collector so as to yield an amplified output RF signal (RF_out) of the PA.

[0040] In the various examples of Figures 3A-3E, the amplifying transistors are described as bipolar junction transistors (BJTs) such as heterojunction bipolar transistors (HBTs). It will be understood that one or more features of the present disclosure can also be implemented in or with other types of transistors such as field-effect transistors (FETs).

[0041] Figure 4 shows that in some embodiments, the amplification system 52 of Figure 2 can be implemented as a high-voltage (HV) power amplification system 100. Such a system can include an HV power amplifier assembly 54 configured to include HV amplification operation of some or all of the PAs (e.g., 60a-60c). As described herein, such PAs can be biased by a bias system 56. In some embodiments, the foregoing HV amplification operation can be facilitated by an HV supply system 58. In some embodiments, an interface system 72 can be implemented to provide interface functionalities between the HV power amplifier assembly 54 and either or both of the bias system 56 and the HV supply system 58.

Examples Related to HV Systems:

[0042] Many wireless devices such as cellular handsets are configured to support multiple frequency bands; and such devices typically require complex power amplification architectures. However, such complexity in power amplification architectures can result in degradation of transmit efficiency as the number of supported bands increases. Such a degradation in efficiency is typically largely due to increased loss incurred by combining of multiple frequency bands while maintaining competitive size and cost targets.

[0043] Some wireless systems can include power amplifiers (PAs) configured in a Doherty configuration. Such a configuration typically includes separate amplification paths for carrier and peaking portions of an RF signal. Such a signal is split into the two amplification path, and the separately amplified carrier and peaking portions are combined to generate an amplified output signal.

[0044] Described herein are examples of systems, circuits, devices and methods that can provide advantageous features for Doherty PAs. Such advantageous features can include, for example, significantly reduce loss while

maintaining or improving competitive levels of size and/or cost. Figure 5 shows that in some embodiments, the HV power amplification system 100 of Figure 4 can be configured as a Doherty power amplification system. In some embodiments, such a Doherty power amplification system can include high-voltage operation capability.

[0045] Doherty power amplification architectures can offer significant advantages for transmit efficiency with moderated peak-average waveforms. However, physical implementation of such architectures typically involves increased passive component content to provide functionalities such as phase shifting and impedance transformation networks at the amplifier output.

[0046] As described herein, a Doherty power amplification architecture can utilize a boost converter to increase the amplifier supply voltage to a level that allows amplifier operation at, for example, a 50 ohm impedance without impedance transformation networks. Such an architecture can allow, for example, significant simplification and integration of passive component content with a system bill of materials (BOM) comparable to a single ended amplification configuration.

[0047] In the example of Figure 5, an HV Doherty power amplification system 100 can include a power amplifier assembly 104 having one or more PAs configured to amplify one or more RF signals (RF_In). Such amplified RF signal(s) can be routed to a duplexer assembly 108 having one or more duplexers, through a match component 106 having one or more matching circuits.

[0048] The duplexer(s) can allow duplexing of transmit (Tx) and receive (Rx) operations. The Tx portion of such duplexing operations is depicted as one or more amplified RF signals (RF_Out) being output from the duplexer assembly 108 for transmission through an antenna (not shown). In the example of Figure 5, the Rx portion is not shown; however, received signals from an antenna can be received by the duplexer assembly 108 and output to, for example, low-noise amplifiers (LNAs).

[0049] In the example of Figure 5, an HV supply system 102 is shown to provide one or more HV supply signals to the power amplifier assembly 104. More specific examples of how such HV signal(s) can be provided to corresponding PA(s) are described herein in greater detail.

[0050] In some embodiments, the HV Doherty power amplification system 100 of Figure 5 can utilize high-voltage capability of some PAs such as, for example, gallium arsenide (GaAs) heterojunction bipolar transistor (HBT) PAs. It will be understood that one or more features of the present disclosure can also be implemented with other types of PAs. For example, amplification systems utilizing CMOS devices with LDMOS multiple cascode stages, silicon bipolar devices, and GaN/HEMT devices can also benefit from operation in high-voltage regions.

[0051] With such HV operation of PAs, one or more lossy components can be eliminated from an amplification system. For example, PA output matching network(s) can be eliminated. In another example, PA supply efficiency can be increased. In yet another example, some passive components can be removed. Examples related to the foregoing are described herein in greater detail.

[0052] One or more of the foregoing features associated with HV operation can result in one or more die being implemented in smaller dimensions, thereby allowing greater flexibility in power amplification system designs. For example, a power amplification system can be implemented with an increased number of relatively small PAs, to thereby allow elimination of lossy components such as band switches. Examples related to such elimination of band switches are described herein in greater detail.

[0053] For the purpose of description, it will be understood that high-voltage (HV) can include voltage values that are higher than a battery voltage utilized in portable wireless devices. For example, an HV can be greater than 3.7V or 4.2V. In some situations, an HV can include voltage values that are greater than a battery voltage and at which portable wireless devices can operate more efficiently. In some situations, an HV can include voltage values that are greater than a battery voltage and less than a breakdown voltage associated with a given type of PA. In the example context of GaAs HBT, such a breakdown voltage can be in a range of 15V to 25V. Accordingly, an HV for GaAs HBT PA can be in a range of, for example, 3.7V to 25V, 4.2V to 20V, 5V to 15V, 6V to 14V, 7V to 13V, or 8V to 12V.

[0054] Figures 6 and 7 show a comparison between a traditional Doherty power amplification system 110 (Figure 6) and a high-voltage (HV)

Doherty power amplification system 100 (Figure 7) to demonstrate how some lossy components can be substantially eliminated in the HV Doherty power amplification system 100. For the purpose of comparison, it will be assumed that each power amplification system is configured to provide amplification for three frequency bands. However, it will be understood that more or less numbers of frequency bands can be utilized.

[0055] In the example of Figure 6, the traditional Doherty power amplification system 110 is shown to include a power amplifier assembly 114 having a broadband carrier amplification path 130 and a broadband peaking amplification path 132 capable of providing amplification for three frequency bands. In the example, each of the carrier and peaking amplification paths 130, 132 is shown to include two stages (e.g., a driver stage (130a or 132a) and an output stage (130b or 132b)); however, it will be understood that there may be other number of stage(s).

[0056] The foregoing amplification paths 130, 132 can receive an input RF signal through a common input node 126, and such an RF signal can be routed through, for example, a DC-block capacitance 128, and be split into the carrier amplification path 130 and the peaking amplification path 132. In some embodiments, each of the amplification stages 130a, 130b, 132a, 132b can include, for example, HBT or CMOS amplification transistors.

[0057] In the example of Figure 6, the collector of the output stage 130b is shown to be provided with a supply voltage VCC from a battery voltage source (V_{batt}) through a choke inductance 124.

[0058] When the power amplifier assembly is operated in the foregoing manner, impedance transformation typically needs to occur to match the impedance of the PAs with impedance associated with a downstream component. In the example of Figure 6, a band switch 138 (depicted as being part of a band switch system 118) that receives the output of the power amplifier assembly 114 is typically configured as a 50 Ω load. Accordingly, an impedance transformation to yield such an impedance load of 50 Ω needs to be implemented. In the example of Figure 6, such an impedance transformation is shown to be implemented by an output matching network (OMN) 136 which is depicted as being part of a load transform system 116.

[0059] In the example of Figure 6, the band switch 138 is depicted as having a single input from the output of the power amplifier assembly 114 (through the OMN 136), and three outputs corresponding to three example frequency bands. Three duplexers 142a-142c are shown to be provided for such three frequency bands.

[0060] Each of the three duplexers 142a-142c is shown to include TX and RX filters (e.g., bandpass filters). The TX filter is shown to be coupled to the band switch 138 to receive the amplified and switch-routed RF signal for transmission. Such an RF signal is shown to be filtered and routed to an antenna port (ANT) (144a, 144b or 144c). The RX filter is shown to receive an RX signal from the antenna port (ANT) (144a, 144b or 144c). Such an RX signal is shown to be filtered and routed to an RX component (e.g., an LNA) for further processing.

[0061] It is typically desirable to provide impedance matching between a given duplexer and a component that is upstream (in the TX case) or downstream (in the RX case). In the example of Figure 6, the band switch 138 is such an upstream component for the TX filter of the duplexer. Accordingly, matching circuits 140a-140c (depicted as being parts of a PI network 120) are shown to be implemented between the respective outputs of the band switch 138 and the respective duplexers 142a-142c. In some embodiments, each of such matching circuits 140a-140c can be implemented as, for example, a pi-matching circuit.

[0062] Table 1 lists example values of insertion loss and efficiency for the various components of the Doherty power amplification system 110 of Figure 6. It will be understood that the various values listed are approximate values.

Table 1

Component	Insertion loss	Efficiency
Power Amp. Assy. (114)	N/A	60% to 65% (PAE)
Load Transform (116)	0.5dB to 0.7dB	85% to 89%
Band Switch (118)	0.3dB to 0.5dB	89% to 93%
PI (120)	0.3dB	93%
Duplex (122)	2.0dB	63%

From Table 1, one can see that the Doherty power amplification system 110 of Figure 6 includes a significant number of loss contributors. Even if each component of the system 110 is assumed to operate at its upper limit of efficiency, the total efficiency of the ET power amplification system 110 is approximately 32% ($0.65 \times 0.89 \times 0.93 \times 0.93 \times 0.63$).

[0063] In the example of Figure 7, the HV Doherty power amplification system 100 is depicted as being configured to provide amplification for the same three frequency bands as in the Doherty power amplification system 110 of Figure 6. In a power amplifier assembly 104, three separate amplification paths can be implemented, such that each amplification path provides amplification for its respective frequency band(s). For example, the first amplification path is shown to include a first Doherty PA (167a and 168a) which receives an RF signal from an input node 162a through a DC-block capacitance 164a. The amplified RF signal is shown to be routed to a downstream component through a capacitance 170a. Similarly, the second amplification path is shown to include a second Doherty PA (167b and 168b) which receives an RF signal from an input node 162b through a DC-block capacitance 164b; and the amplified RF signal is shown to be routed to a downstream component through a capacitance 170b. Similarly, the third amplification path is shown to include a third Doherty PA (167c and 168c) which receives an RF signal from an input node 162c through a DC-block capacitance 164c; and the amplified RF signal is shown to be routed to a downstream component through a capacitance 170c.

[0064] In some embodiments, the Doherty PAs in the example of Figure 7 can include, for example, HBT PAs. It will be understood that one or more features of the present disclosure can also be implemented with other types of PAs. For example, PAs that can be operated to yield impedances that match or are close to downstream components (e.g., by HV operation and/or through other operating parameter(s)) can be utilized to yield one or more of the benefits as described herein.

[0065] In the example of Figure 7, each carrier PA (167a, 167b or 167c) can be provided with a supply voltage VCC from a boost DC/DC converter 160 through a choke inductance (166a, 166b or 166c). Similarly, each peaking PA (168a, 168b or 168c) can be provided with the supply voltage VCC from the boost DC/DC converter 160 through the choke inductance (166a, 166b or 166c).

The boost DC/DC converter 160 is depicted as being part of an HV system 102. The boost DC/DC converter 160 can be configured to supply such a range of VCC voltage values (e.g., about 1V to 10V), including HV ranges or values as described herein. The boost DC/DC converter 160 is shown to generate such a high VCC voltage based on a battery voltage V_{batt} .

[0066] When the Doherty PAs of the power amplifier assembly 104 are operated in the foregoing manner with high VCC voltage (e.g., at about 10V), impedance Z of each PA can be relatively high (e.g., about 40 Ω to 50 Ω); and thus, impedance transformation is not necessary to match with impedance associated with a downstream component and/or an upstream component. Accordingly, elimination or simplification of two impedance transformation networks can be realized. It is further noted that the Doherty PAs of the power amplifier assembly 104 can support very simple integration of, for example, a quarter-wave combining network.

[0067] In the example of Figure 7, each of the duplexers 174a-174c (depicted as being parts of a duplex assembly 108) that receives the output of the corresponding Doherty PA is typically configured as a 50 Ω load. Accordingly, and assuming that the impedance (Z) presented by the Doherty PA is about 50 Ω , an impedance transformation (such as the load transform system 116 in Figure 6) is not needed.

[0068] It is typically desirable to provide impedance matching between a given duplexer and a component that is upstream (in the TX case) or downstream (in the RX case). In the example of Figure 7, the Doherty PA is such an upstream component for the TX filter of the duplexer (174a, 174b or 174c). Accordingly, matching circuits 172a-172c (depicted as being parts of a PI network 106) can be implemented between the respective outputs of the Doherty PAs and the respective duplexers 174a-174c. In some embodiments, each of such matching circuits 172a-172c can be implemented as, for example, a pi-matching circuit.

[0069] In the example of Figure 7, the HV operation of the Doherty PAs can result in each of the Doherty PAs presenting an impedance Z that is similar to the impedance of the corresponding duplexer. Since impedance transformation is not needed in such a configuration, there is no need for an impedance transformer (116 in Figure 6).

[0070] It is also noted that operation of the Doherty PAs at the higher impedance can result in much lower current levels within the PAs. Such lower current levels can allow the Doherty PAs to be implemented in significantly reduced die size(s).

[0071] In some embodiments, either or both of the foregoing features (elimination of impedance transformer and reduced PA die size) can provide additional flexibility in power amplification architecture design. For example, space and/or cost savings provided by the foregoing can allow implementation of a relatively small Doherty PA for each frequency band, thereby removing the need for a band switch system (e.g., 118 in Figure 6). Accordingly, size, cost and/or complexity associated with the HV Doherty power amplification system 100 of Figure 7 can be maintained or reduced when compared to the Doherty power amplification system 110 of Figure 6, while significantly reducing the overall loss of the power amplification system 100.

[0072] Table 2 lists example values of insertion loss and efficiency for the various components of the HV Doherty power amplification system 100 of Figure 7. It will be understood that the various values listed are approximate values.

Table 2

Component	Insertion loss	Efficiency
HV (102)	N/A	93%
Power Amp. Assy. (104)	N/A	75% to 80% (PAE)
PI (106)	0.3dB	93%
Duplex (108)	2.0dB	63%

[0073] From Table 2, one can see that the HV Doherty power amplification system 100 of Figure 7 includes a number of loss contributors. However, when compared to the Doherty power amplification system 110 of Figure 6 and Table 1, two significant loss contributors (Load Transform (116) and Band Switch (118)) are absent in the HV Doherty power amplification system 100 of Figure 7. Elimination of such loss contributors is shown to remove about 1dB in the transmit path in the example of Figure 7 and Table 2.

[0074] Also referring to Table 2, if each component of the system 100 is assumed to operate at its upper limit of efficiency (as in the example of Table 1),

the total efficiency of the HV Doherty power amplification system 100 is approximately 44% ($0.93 \times 0.80 \times 0.93 \times 0.63$). Even if each component is assumed to operate at its lower limit of efficiency, the total efficiency of the HV Doherty power amplification system 100 is approximately 41% ($0.93 \times 0.75 \times 0.93 \times 0.63$). One can see that in either case, the total efficiency of the HV Doherty power amplification system 100 of Figure 7 is significantly higher than the total efficiency (approximately 32%) of the Doherty power amplification system 110 of Figure 6.

[0075] Referring to Figures 6 and 7, a number of features can be noted. It is noted that use of the DC/DC boost converter (160 in Figure 7) can allow elimination of one or more other power converters that may be utilized in a PA system. When operated to yield an HV supply voltage (e.g., 10VDC), 1 Watt ($(10V)^2/(2 \times 50\Omega)$) of RF power can be produced with no harmonic terminations. It is further noted that a PA driven as a 50 Ω load (e.g., Figure 7) results in a significantly lower loss per Ohm than a PA driven as a 3 Ω load (e.g., Figure 6).

[0076] Figure 8 shows an HV Doherty power amplification system 100 that can be a more specific example of the HV Doherty power amplification system 100 of Figure 7. In the example of Figure 8, a power amplifier assembly can include a carrier PA 167 and a peaking PA 168. Each of the carrier and peaking PAs is depicted as having a cascode configuration.

[0077] In the example of Figure 8, the carrier PA 167 can be operated with, for example, a Class AB bias; and the peaking PA 168 can be operated with, for example, a Class C bias. More particularly, the RF transistor of the carrier PA 167 is shown to be biased in a Class AB configuration; and the RF transistor of the peaking PA 168 is shown to be biased in a Class C configuration. The cascode transistor of each of the carrier and peaking PAs 167, 168 is shown to be biased by its respective cascode bias circuit.

[0078] In the example of Figure 8, an RF signal can be received at a common input port 162 (RFin), and such a signal can be split into the carrier amplification path and the peaking amplification path by an input splitter 202. The carrier portion is shown to be provided to the carrier PA 167, and the peaking portion is shown to be provided to the peaking PA 168 through an input inverter 204.

[0079] In the example of Figure 8, a supply voltage V_{cc} from a supply node 212 is shown to be provided to the collector of each cascode transistor of the carrier and peaking PAs 167, 168. More particularly, the collector of the cascode transistor of the carrier PA 167 is shown to be provided with V_{cc} through inductances indicated as Choke and L_{inv} . The collector of the cascode transistor of the peaking PA 168 is shown to be provided with V_{cc} through L_{inv} .

[0080] The collector of the cascode transistor of the carrier PA 167 is shown to be coupled to the emitter of the RF transistor of the carrier PA 167 through a corresponding capacitance C_{inv} . Similarly, the collector of the cascode transistor of the peaking PA 168 is shown to be coupled to the emitter of the RF transistor of the peaking PA 168 through a corresponding capacitance C_{inv} .

[0081] In the example of Figure 8, an assembly of the capacitances C_{inv} and the inductance L_{inv} can form an output J-inverter 210 having an impedance of, for example, approximately 100 Ω . The amplified outputs of the carrier and peaking PAs 167, 168 can be combined by the output J-inverter 210, and the combined output can be provided to an output node 214 through a capacitance 170.

[0082] As shown in Figure 8, the high impedance operation of the Doherty PAs can significantly simplify the Doherty amplification architecture, including the simplification of the combining network (e.g., the output J-inverter 210). In some embodiments, the carrier and peaking PAs 167, 168 can be implemented on a die. In some embodiments, the input splitter 202 and the input J-inverter 204 can also be implemented on the same die. In some embodiments, the inverter capacitances (C_{inv}) of the output J-inverter 210 can also be implemented on the same die. Accordingly, and assuming that the inverter inductance L_{inv} is implemented as an external passive device, only one such additional passive device is needed when compared to a single-ended power amplification design.

[0083] Figure 9 shows an HV Doherty amplification system that can be a more specific example of the HV Doherty amplification system of Figure 8. In Figure 9, reference numerals 202, 204, 207, 208 and 210 generally correspond to the same reference numerals of Figure 8. In the example of Figure 9, it will be understood that various values of circuit elements such as resistances,

capacitances and inductances can be selected to achieve desired functionalities for one or more frequencies.

[0084] Figures 10-12 show examples of performance characteristics of the HV Doherty amplification system of Figure 9. More particularly, Figure 10 shows plots of AMAM vs output power, PAE vs output power, ratio of peak power and carrier power vs input power, and collector current vs output power, as Class C bias point is swept.

[0085] Figure 11 shows gain, output power, emitter follower bias, and collector current characteristics for Class AB and Class C bias configurations.

[0086] Figure 12 shows AMAM, PAE, and AMPM characteristics for the HV Doherty amplification system, as well as for a single ended amplification system.

[0087] Figure 13 shows examples of battery level efficiency as a function of average output power for a Buck ET amplification system (A), a boost average power tracking (APT) amplification system (B), a Buck APT amplification system (C), and a boost Doherty amplification system (D) having one or more features as described herein. At an example output power of about 26dBm, one can see that the boost Doherty amplification system (D) has an efficiency level that is about 15% greater than both of the Buck ET (A) and boost APT (B) systems, and about 25% greater than the Buck APT system (C).

[0088] Figure 14 shows that in some embodiments, some or all of an HV Doherty power amplification system having one or more features as described herein can be implemented in a module. Such a module can be, for example, a front-end module (FEM). In the example of Figure 14, a module 300 can include a packaging substrate 302, and a number of components can be mounted on such a packaging substrate. For example, a front-end-power management integrated circuit (FE-PMIC) component 102, a power amplifier assembly 104, a match component 106, and a duplexer assembly 108 can be mounted and/or implemented on and/or within the packaging substrate 302. Other components such as a number of SMT devices 304 and an antenna switch module (ASM) 306 can also be mounted on the packaging substrate 302. Although all of the various components are depicted as being laid out on the packaging substrate 302, it will be understood that some component(s) can be implemented over other component(s).

[0089] In some implementations, a device and/or a circuit having one or more features described herein can be included in an RF device such as a wireless device. Such a device and/or a circuit can be implemented directly in the wireless device, in a modular form as described herein, or in some combination thereof. In some embodiments, such a wireless device can include, for example, a cellular phone, a smart-phone, a hand-held wireless device with or without phone functionality, a wireless tablet, etc.

[0090] Figure 15 depicts an example wireless device 400 having one or more advantageous features described herein. In the context of a module having one or more features as described herein, such a module can be generally depicted by a dashed box 300, and can be implemented as, for example, a front-end module (FEM).

[0091] Referring to Figure 15, power amplifiers (PAs) 420 can receive their respective RF signals from a transceiver 410 that can be configured and operated in known manners to generate RF signals to be amplified and transmitted, and to process received signals. The transceiver 410 is shown to interact with a baseband sub-system 408 that is configured to provide conversion between data and/or voice signals suitable for a user and RF signals suitable for the transceiver 410. The transceiver 410 can also be in communication with a power management component 406 that is configured to manage power for the operation of the wireless device 400. Such power management can also control operations of the baseband sub-system 408 and the module 300.

[0092] The baseband sub-system 408 is shown to be connected to a user interface 402 to facilitate various input and output of voice and/or data provided to and received from the user. The baseband sub-system 408 can also be connected to a memory 404 that is configured to store data and/or instructions to facilitate the operation of the wireless device, and/or to provide storage of information for the user.

[0093] In the example wireless device 400, outputs of the PAs 420 are shown to be matched (via respective match circuits 422) and routed to their respective duplexers 420. In some embodiments, the match circuit 422 can be the example matching circuits 172a-172c described herein in reference to Figure 7. As also described herein in reference to Figure 7, the outputs of the PAs 420 can be routed to their respective duplexers 424 without impedance

transformation (e.g., with load transformation 116 in Figure 6) when the PAs 420 are operated with HV supply. Such amplified and filtered signals can be routed to an antenna 416 through an antenna switch 414 for transmission. In some embodiments, the duplexers 420 can allow transmit and receive operations to be performed simultaneously using a common antenna (e.g., 416). In Figure 15, received signals are shown to be routed to "Rx" paths (not shown) that can include, for example, a low-noise amplifier (LNA).

[0094] A number of other wireless device configurations can utilize one or more features described herein. For example, a wireless device does not need to be a multi-band device. In another example, a wireless device can include additional antennas such as diversity antenna, and additional connectivity features such as Wi-Fi, Bluetooth, and GPS.

[0095] As described herein, one or more features of the present disclosure can provide a number of advantages when implemented in systems such as those involving the wireless device of Figure 15. For example, significant current drain reduction can be achieved through an elimination or reduction of output loss. In another example, lower bill of materials count can be realized for the power amplification system and/or the wireless device. In yet another example, independent optimization or desired configuration of each supported frequency band can be achieved due to, for example, separate PAs for their respective frequency bands. In yet another example, optimization or desired configuration of maximum or increased output power can be achieved through, for example, a boost supply voltage system. In yet another example, a number of different battery technologies can be utilized, since maximum or increased power is not necessarily limited by battery voltage.

[0096] One or more features of the present disclosure can be implemented with various cellular frequency bands as described herein. Examples of such bands are listed in Table 3. It will be understood that at least some of the bands can be divided into sub-bands. It will also be understood that one or more features of the present disclosure can be implemented with frequency ranges that do not have designations such as the examples of Table 3.

Table 3

Band	Mode	Tx Frequency Range (MHz)	Rx Frequency Range (MHz)
B1	FDD	1,920 – 1,980	2,110 – 2,170
B2	FDD	1,850 – 1,910	1,930 – 1,990
B3	FDD	1,710 – 1,785	1,805 – 1,880
B4	FDD	1,710 – 1,755	2,110 – 2,155
B5	FDD	824 – 849	869 – 894
B6	FDD	830 – 840	875 – 885
B7	FDD	2,500 – 2,570	2,620 – 2,690
B8	FDD	880 – 915	925 – 960
B9	FDD	1,749.9 – 1,784.9	1,844.9 – 1,879.9
B10	FDD	1,710 – 1,770	2,110 – 2,170
B11	FDD	1,427.9 – 1,447.9	1,475.9 – 1,495.9
B12	FDD	699 – 716	729 – 746
B13	FDD	777 – 787	746 – 756
B14	FDD	788 – 798	758 – 768
B15	FDD	1,900 – 1,920	2,600 – 2,620
B16	FDD	2,010 – 2,025	2,585 – 2,600
B17	FDD	704 – 716	734 – 746
B18	FDD	815 – 830	860 – 875
B19	FDD	830 – 845	875 – 890
B20	FDD	832 – 862	791 – 821
B21	FDD	1,447.9 – 1,462.9	1,495.9 – 1,510.9
B22	FDD	3,410 – 3,490	3,510 – 3,590
B23	FDD	2,000 – 2,020	2,180 – 2,200
B24	FDD	1,626.5 – 1,660.5	1,525 – 1,559
B25	FDD	1,850 – 1,915	1,930 – 1,995
B26	FDD	814 – 849	859 – 894
B27	FDD	807 – 824	852 – 869
B28	FDD	703 – 748	758 – 803
B29	FDD	N/A	716 – 728
B30	FDD	2,305 – 2,315	2,350 – 2,360
B31	FDD	452.5 – 457.5	462.5 – 467.5
B33	TDD	1,900 – 1,920	1,900 – 1,920
B34	TDD	2,010 – 2,025	2,010 – 2,025
B35	TDD	1,850 – 1,910	1,850 – 1,910
B36	TDD	1,930 – 1,990	1,930 – 1,990
B37	TDD	1,910 – 1,930	1,910 – 1,930
B38	TDD	2,570 – 2,620	2,570 – 2,620
B39	TDD	1,880 – 1,920	1,880 – 1,920
B40	TDD	2,300 – 2,400	2,300 – 2,400
B41	TDD	2,496 – 2,690	2,496 – 2,690
B42	TDD	3,400 – 3,600	3,400 – 3,600
B43	TDD	3,600 – 3,800	3,600 – 3,800
B44	TDD	703 – 803	703 – 803

[0097] Unless the context clearly requires otherwise, throughout the description and the claims, the words “comprise,” “comprising,” and the like are to be construed in an inclusive sense, as opposed to an exclusive or exhaustive sense; that is to say, in the sense of “including, but not limited to.” The word “coupled”, as generally used herein, refers to two or more elements that may be either directly connected, or connected by way of one or more intermediate

elements. Additionally, the words “herein,” “above,” “below,” and words of similar import, when used in this application, shall refer to this application as a whole and not to any particular portions of this application. Where the context permits, words in the above Description using the singular or plural number may also include the plural or singular number respectively. The word “or” in reference to a list of two or more items, that word covers all of the following interpretations of the word: any of the items in the list, all of the items in the list, and any combination of the items in the list.

[0098] The above detailed description of embodiments of the invention is not intended to be exhaustive or to limit the invention to the precise form disclosed above. While specific embodiments of, and examples for, the invention are described above for illustrative purposes, various equivalent modifications are possible within the scope of the invention, as those skilled in the relevant art will recognize. For example, while processes or blocks are presented in a given order, alternative embodiments may perform routines having steps, or employ systems having blocks, in a different order, and some processes or blocks may be deleted, moved, added, subdivided, combined, and/or modified. Each of these processes or blocks may be implemented in a variety of different ways. Also, while processes or blocks are at times shown as being performed in series, these processes or blocks may instead be performed in parallel, or may be performed at different times.

[0099] The teachings of the invention provided herein can be applied to other systems, not necessarily the system described above. The elements and acts of the various embodiments described above can be combined to provide further embodiments.

[0100] While some embodiments of the inventions have been described, these embodiments have been presented by way of example only, and are not intended to limit the scope of the disclosure. Indeed, the novel methods and systems described herein may be embodied in a variety of other forms; furthermore, various omissions, substitutions and changes in the form of the methods and systems described herein may be made without departing from the spirit of the disclosure. The accompanying claims and their equivalents are intended to cover such forms or modifications as would fall within the scope and spirit of the disclosure.

WHAT IS CLAIMED IS:

1. A power amplification system comprising:
a supply system configured to provide a high-voltage (HV) supply signal;
a Doherty power amplifier (PA) configured to receive the HV supply signal and amplify a radio-frequency (RF) signal; and
an output path configured to receive and route the amplified RF signal to a filter, the output path substantially free of an impedance transformation circuit.
2. The power amplification system of claim 1 wherein the supply system includes a boost DC/DC converter configured to generate the HV supply signal based on a battery voltage V_{batt} .
3. The power amplification system of claim 2 wherein the HV supply signal is selected such that impedances of the Doherty PA and the filter match sufficiently to allow the output path to be substantially free of the impedance transformation circuit.
4. The power amplification system of claim 3 wherein the impedance of the Doherty PA has a value of approximately 50 Ohms.
5. The power amplification system of claim 2 wherein the Doherty PA includes a heterojunction bipolar transistor (HBT).
6. The power amplification system of claim 5 wherein the HBT is a gallium arsenide (GaAs) device.
7. The power amplification system of claim 5 wherein the HV supply signal is provided to a collector of the HBT as V_{cc} .
8. The power amplification system of claim 2 wherein the filter is a transmit (Tx) filter configured to operate in a corresponding Tx frequency band.

9. The power amplification system of claim 8 wherein the Tx filter is part of a duplexer configured to operate in the Tx frequency band and a corresponding receive (Rx) frequency band.

10. The power amplification system of claim 2 further comprising one or more additional Doherty PAs, each configured to receive the HV supply signal and amplify an RF signal.

11. The power amplification system of claim 10 further comprising an output path configured to receive and route the amplified RF signal for each of the one or more additional Doherty PAs to a corresponding filter, the additional output path substantially free of an impedance transformation circuit.

12. The power amplification system of claim 11 wherein each filter has associated with it a corresponding Doherty PA.

13. The power amplification system of claim 12 wherein the power amplification system is substantially free of a band selection switch between the Doherty PAs and the filters.

14. The power amplification system of claim 13 wherein the power amplification system has a lower loss than another power amplifier system having similar band handling capability but in which the PAs are operated in low voltage.

15. A radio-frequency (RF) module comprising:

a packaging substrate configured to receive a plurality of components; and

a power amplification system implemented on the packaging substrate, the power amplification system including a supply system configured to provide a high-voltage (HV) supply signal, the power amplification system further including a Doherty power amplifier (PA) configured to receive the HV supply signal and amplify an RF signal, the power amplification system further including an output path configured to

receive and route the amplified RF signal to a filter, the output path substantially free of an impedance transformation circuit.

16. The RF module of claim 15 wherein the RF module is a front-end module (FEM).

17. The RF module of claim 15 wherein the power amplification system is substantially free of a band selection switch between the Doherty PA and the filter.

18. The RF module of claim 17 wherein the power amplification system has a lower loss than another power amplifier system having similar band handling capability but in which a Doherty PA is operated in low voltage.








19. The RF module of claim 17 wherein the RF module has an area that is significantly less than another RF module having an amplification system with an impedance transformation circuit and a band selection switch.

20. A wireless device comprising:


- a transceiver configured to generate a radio-frequency (RF) signal;
- a front-end module (FEM) in communication with the transceiver, the FEM including a packaging substrate configured to receive a plurality of components, the FEM further including a power amplification system implemented on the packaging substrate, the power amplification system including a supply system configured to provide a high-voltage (HV) supply signal, the power amplification system further including a Doherty power amplifier (PA) configured to receive the HV supply signal and amplify a radio-frequency (RF) signal, the power amplification system further including an output path configured to receive and route the amplified RF signal to a filter, the output path substantially free of an impedance transformation circuit; and

- an antenna in communication with the FEM, the antenna configured to transmit the amplified RF signal.


1/12

**FIG.1****FIG.2****FIG.3A****FIG.3B****FIG.3C****FIG.3D****FIG.3E**



2/12

**FIG.4**

3/12

**FIG.5**

4/12

**FIG. 6****FIG. 7**

5/12




FIG. 8




FIG. 9




FIG.10




FIG.11






FIG.12




A—78% BUCK ET B—87% BOOST APT C—97% BUCK APT REFERENCE D—87% BOOST DOHERTY

FIG.13

11/12

**FIG.14**

12/12

**FIG.15**

A. CLASSIFICATION OF SUBJECT MATTER**H03F 1/02(2006.01)i, H03F 1/07(2006.01)i, H03F 3/68(2006.01)i**

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

H03F 1/02; H03F 1/07; H03F 3/21; H03F 3/68; H03F 3/19; H03F 3/20

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Korean utility models and applications for utility models

Japanese utility models and applications for utility models

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

eKOMPASS(KIPO internal) & Keywords: power amplification system, high-voltage (HV) supply, Doherty power amplifier (PA), radio-frequency (RF) signal, output path, impedance transformation circuit**C. DOCUMENTS CONSIDERED TO BE RELEVANT**

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y	US 2010-0079210 A1 (KAZUHISA YAMAUCHI et al.) 01 April 2010 See abstract, paragraphs [0005], [0022]-[0024], claim 1 and figure 1.	1-20
Y	US 2010-0301947 A1 (TORU FUJIOKA et al.) 02 December 2010 See abstract, paragraphs [0141]-[0144], [0169]-[0170], [0204]-[0205], claim 1 and figures 7-8, 14, 29.	1-20
A	US 2014-0035677 A1 (HUAZHANG CHEN et al.) 06 February 2014 See paragraphs [0049]-[0053], claims 1, 6 and figure 3.	1-20
A	JP 2008-206106 A (FUJITSU LTD.) 04 September 2008 See paragraphs [0025]-[0049], claim 1 and figure 1.	1-20
A	US 2012-0299659 A1 (SANDEEP MODI SANKALP et al.) 29 November 2012 See paragraphs [0033]-[0037], claim 1 and figure 1.	1-20



Further documents are listed in the continuation of Box C.



See patent family annex.

* Special categories of cited documents:

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier application or patent but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

17 June 2016 (17.06.2016)

Date of mailing of the international search report

17 June 2016 (17.06.2016)

Name and mailing address of the ISA/KR

International Application Division

Korean Intellectual Property Office

189 Cheongsa-ro, Seo-gu, Daejeon, 35208, Republic of Korea

Facsimile No. +82-42-481-8578

Authorized officer

KIM, Sung Gon

Telephone No. +82-42-481-8746



INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No.

PCT/US2016/017916

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 2010-0079210 A1	01/04/2010	CN 101563840 A	21/10/2009
		CN 101563840 B	06/06/2012
		EP 2101409 A1	16/09/2009
		EP 2101409 A4	28/11/2012
		KR 10-1107888 B1	25/01/2012
		KR 10-2009-0086626 A	13/08/2009
		US 7893770 B2	22/02/2011
		WO 2008-075561 A1	26/06/2008
US 2010-0301947 A1	02/12/2010	CN 101098127 A	02/01/2008
		JP 2008-035487 A	14/02/2008
		US 2007-0298736 A1	27/12/2007
		US 7756494 B2	13/07/2010
US 2014-0035677 A1	06/02/2014	CN 102185568 A	14/09/2011
		EP 2538557 A1	26/12/2012
		EP 2538557 A4	02/10/2013
		US 8754709 B2	17/06/2014
		WO 2012-146002 A1	01/11/2012
JP 2008-206106 A	04/09/2008	JP 5217182 B2	19/06/2013
US 2012-0299659 A1	29/11/2012	US 8604881 B2	10/12/2013