



(51) International Patent Classification:
H02M 3/158 (2006.01)

(21) International Application Number:
PCT/EP2013/071023

(22) International Filing Date:
9 October 2013 (09.10.2013)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
12306265.5 12 October 2012 (12.10.2012) EP
61/727,439 16 November 2012 (16.11.2012) US

(71) Applicant: ST-ERICSSON SA [CH/CH]; 39 Chemin du
Champ-des-Filles, CH-1228 Plan-les-Ouates (CH).

(72) Inventor: BRANCA, Xavier; 12 rue Henri Debraye, F-
38000 Grenoble (FR).

(74) Agents: VERDURE, Stéphane et al.; CABINET
PLASSERAUD, 52 rue de la Victoire, F-75440 PARIS Ce-
dex 09 (FR).

(81) Designated States (unless otherwise indicated, for every
kind of national protection available): AE, AG, AL, AM,


AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY,
BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM,
DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT,
HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KN, KP, KR,
KZ, LA, LC, LK, LR, LS, LT, LU, LY, MA, MD, ME,
MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ,
OM, PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA,
SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM,
TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM,
ZW.

(84) Designated States (unless otherwise indicated, for every
kind of regional protection available): ARIPO (BW, GH,
GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, SZ, TZ,
UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ,
TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK,
EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV,
MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM,
TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW,
KM, ML, MR, NE, SN, TD, TG).

Published:

— with international search report (Art. 21(3))

(54) Title: INDEPENDENT OUTPUT CONTROL FOR SINGLE-INDUCTOR, BIPOLAR OUTPUTS, BUCK-BOOST CON-
VERTERS



(57) Abstract: A method of driving a power stage configured to provide both positive output voltage higher than a first potential to a positive output and negative output voltage to a negative output, the method comprising: - generating a first control signal; - generating a second control signal; - operating, the first control signal so as to initiate a charging phase, such that a first duty cycle of the first control signal is controlling an amount of energy to be accumulated; - operating, simultaneously, at the control signals so as to initiate an independent discharging phase of the accumulated energy, in a boost-type to the positive output or in a buck-type or boost-type to the negative output, such that a second and third duty cycles of the second and third control signals are controlling an amount of energy to be discharged.

Description**INDEPENDENT OUTPUT CONTROL FOR SINGLE-INDUCTOR, BIPOLAR
OUTPUTS, BUCK-BOOST CONVERTERS****Technical Field**

[0001] The proposed solution relates generally to Single Inductor Bipolar Output (SIBO) converters, and more especially to a method and an apparatus for controlling operation of such converters.

Background Art

[0002] Portable devices such as smartphones, tablets, console games or e-book readers, usually utilise multiple supply voltages to power up different internal modules.

[0003] Some applications require bipolar power supplies with different regulated voltages, meaning that both positive voltage and negative voltage are needed.

[0004] Audio module and display panel are some of examples compliant with the foregoing.

[0005] For instance, Active Matrix Organic Light Emitting Diodes (AMOLED) display panel, which is a good candidate for portable devices due to its high display quality (i.e. brightness, contrast, vividness and wide viewing angle) and low power consumption requires the supply of both a positive voltage of 4.6 V and a negative voltage ranging from -1.5 V to -7 V to operate properly.

[0006] A power converter such as a Single Inductor Bipolar Output (SIBO) converter may be used to provide such positive and a negative power supply.

[0007] A converter is proposed in document (1): **TEXAS INSTRUMENTS, TPS65136**. Single Inductor Multiple Output Regulator for AMOLED. <http://www.ti.com/lit/ds/symlink/tps65136.pdf> (849 KB). 07 Jul 2008.

[0008] However, the converter of document (1) is not able to operate properly with stability if the load current asymmetry between the negative output current and the positive output current is greater than 30%, meaning that the difference in current at each output needs to stay in close range.

- [0009] To summarize, the control of a SIBO- Boost converter adapted to generate required positive output voltage and negative output voltage is not adequately addressed by known techniques.
- [0010] A possible controller that might be used to solve the above problem is described in document (2) WO2012/032176 wherein it is disclosed a power stage that might be adapted to output a positive output voltage and a negative output voltage. While working satisfactorily, the solution described in document (2) may still be improved to better meet the ever increasing requirements of wireless applications.

Summary of invention

- [0011] As the input voltage (i.e. for instance the battery voltage) is most of the time lower than 4.5 V, it can be considered that the positive output voltage would, most of the time, be higher than the input voltage.
- [0012] Thus, only a Boost-type configuration of the SIBOBB is required for delivering the positive output voltage and Buck-Boost-type configuration of the SIBOBB is required for delivering the negative output voltage.
- [0013] A first aspect of the proposed solution relates to a method of driving a Single Inductor Bipolar Output Buck-Boost, SIBOBB, clocked by a clock signal having a given clock cycle period, the SIBOBB comprising an input for receiving a first potential, at least four power switches, and at least one positive output adapted to output a positive output voltage substantially higher than the first potential and at least one negative output adapted to output a negative output voltage. The method comprising the following steps performed during the clock cycle period: generating a first control signal based on, at least, the positive output voltage and a positive reference voltage; generating a second control signal based on, at least, the negative output voltage and a negative reference voltage; initiating a charging phase of charging the SIBOBB, based on a monitoring of the first control signal, during which an amount of energy to be accumulated by the SIBOBB is controlled by a first duty cycle of the first control signal; initiating a first discharging phase of discharging the energy accumulated in the SIBOBB to at least one of the positive output in a boost-type configuration of the SIBOBB and the negative output in a buck-type or

boost-type configuration of the SIBOBB, based on a simultaneous monitoring of the first control signal and the second control signal, during which first discharging phase, an amount of energy to be discharged by the SIBOBB is controlled by a second duty cycle of the second control signal; and, wherein, the charging phase is initiated before the first discharging phase.

[0014] A second aspect relates to an apparatus for driving a Single Inductor Bipolar Output Buck-Boost, SIBOBB, clocked by a clock signal having a given clock cycle period, the SIBOBB comprising an input for receiving a first potential and at least four power switches and at least one positive output adapted to output a positive output voltage substantially higher than the first potential and at least one negative output adapted to output a negative output voltage, the apparatus comprising:

- means for generating a first control signal configured to be based on, at least, the negative output voltage and a negative reference voltage;
 - means for generating a second control signal configured to be based on, at least, the positive output voltage and a positive reference voltage;
 - means for initiating a charging phase of the SIBOBB, configured to be based on a monitoring of the first control signal, during which an amount of energy to be accumulated by the SIBOBB is controlled by a first duty cycle of the first control signal;
 - means for initiating a first discharging phase of discharging the energy accumulated in the SIBOBB to at least one of the positive output in a boost-type configuration of the SIBOBB and the negative output in a buck-type or boost-type configuration of the SIBOBB, configured to be based on a simultaneous monitoring of the first control signal and the second control signal, during which first discharging phase, an amount of energy to be discharged by the SIBOBB is controlled by a second duty cycle of the second control signal; and,
- wherein, means for initiating the charging phase are activated before the activation of means for initiating the first discharging phase.

[0015] A third aspect relates to a display integrated circuit comprising:

- a display panel;

- a Single Inductor Bipolar Output Buck-Boost converter (SIBOBB);
- a processor; and,
- an apparatus as defined in the second aspect of the proposed solution, wherein the display panel and the apparatus are controlled by the processor, the display panel is powered by the SIBOBB and the SIBOBB is controlled by the apparatus.

[0016] A fourth aspect relates to wireless device comprising the display integrated circuit as defined in third aspect of the proposed solution.

[0017] Examples of such wireless devices comprising AMOLED display panels include, for instance, portable phones, smartphones, tablets, console games, e-book readers, portable audio and/or video players, etc.

[0018] Thus in a wireless device embodying the principles of such mechanism, weaknesses of prior art regarding SIBOBB regulation in order to enable independent boost-type conversion for the positive output and buck-type or boost-type conversion for the negative output during a clock cycle are overcome.

[0019] Also, with the proposed solution, full load current asymmetry between the negative output current and the positive output current may be supported with a single charge of the inductor of the SIBOBB.

[0020] In other words, embodiments offer proper solutions for cases as presented in the introduction.

[0021] In one embodiment, generating the first control signal is further based on the negative output voltage and generating the second control signal is further based on the positive output voltage.

[0022] In another embodiment, there is further provided the generating a third control signal based on, at least, the first control signal and the second control signal; initiating a second discharging phase of discharging the energy accumulated in the SIBOBB to the positive output in a boost-type configuration of the SIBOBB and to the negative output in a buck-type or boost-type configuration of the SIBOBB simultaneously, based on a monitoring of the first control signal, the second control signal and the third control signal simultaneously, during which second discharging phase, an amount of energy to be discharged by the SIBOBB is controlled by a

second duty cycle of the second control signal and a third duty cycle of the third control signal; and, wherein, the charging phase is initiated before the second discharging phase.

- [0023] In one other embodiment, the first discharging phase comprises discharging the accumulated energy in both the positive output and the negative output sequentially, the discharging of the accumulated energy to the positive output being initiated before the discharging of the accumulated energy to the negative output.
- [0024] In yet another embodiment, the first discharging phase comprises discharging the accumulated energy in both the positive output and the negative output sequentially, the discharging of the accumulated energy to the positive output being initiated after the discharging of the accumulated energy to the positive output.
- [0025] In still another embodiment, wherein the second discharging phase comprises discharging the accumulated energy in both the positive output and the negative output simultaneously, and wherein initiating the second discharging phase is performed before the first discharging phase.
- [0026] In yet another embodiment, the second discharging phase comprises discharging the accumulated energy in both the positive output and the negative output simultaneously, and wherein initiating the second discharging phase is performed after the first discharging phase.
- [0027] If desired, the first, second and third control signals are generated by a Pulse Width Modulation, PWM, modulator based on respective comparison signals, wherein at least some of the comparison signals are saw-tooth signals or triangular signals.
- [0028] In one embodiment, generating the first control signal is performed by inputting into the PWM modulator, the first comparison signal and a first error signal proportional to the voltage difference between the positive output voltage and the positive reference voltage.
- [0029] In another embodiment, generating the second control signal is performed by inputting into the PWM modulator, the second comparison signal and a second error signal proportional to the voltage difference between the negative output voltage and the negative reference voltage.

- [0030] In yet another embodiment, generating the first control signal is performed by inputting into the PWM modulator, the first comparison signal and a first error signal corresponding to a voltage difference between a sum reference voltage and a voltage sum of positive output voltage and negative output voltage.
- [0031] In still another embodiment, generating the second control signal is performed by inputting into the PWM modulator, the second comparison signal and a second error signal corresponding to a voltage difference between a difference reference voltage and a voltage difference between positive output voltage and the negative output voltage.
- [0032] In yet another embodiment, generating the third control signal is performed by inputting into the PWM modulator, a third error signal corresponding to a voltage difference between the first error signal and the second error signal.

Brief description of drawings

- [0033] A more complete understanding of the proposed solution may be obtained from a consideration of the following description in conjunction with the drawings, in which like reference numbers indicate the same or similar element, in FIG. 1 and FIGs. 6 to 14 in a first place and in FIGs. 2 to 5 in a second place and in which:
- [0034] FIG. 1 is a block diagram illustrating an embodiment of a SIBO -Boost converter.
- [0035] FIG. 2 is a schematic diagram representing a controlled switch according to one embodiment, included in a section of an electrical circuit of a power stage.
- [0036] FIG. 3 is a schematic diagram representing a controlled switch according to another embodiment, included in another section of the electrical circuit.
- [0037] FIG. 4 is a block diagram of an electrical circuit of a power stage according to one embodiment.
- [0038] FIG. 5 is a schematic diagram of a power supply according to one embodiment.
- [0039] FIG. 6 is a block diagram illustrating an embodiment of the proposed solution.

- [0040] FIG. 7A is a block diagram illustrating an embodiment of a phase of a conduction cycle according to the proposed solution.
- [0041] FIG. 7B is a block diagram illustrating an embodiment of another phase of a conduction cycle according to the proposed solution.
- [0042] FIG. 7C is a block diagram illustrating an embodiment of yet another phase of a conduction cycle according to the proposed solution.
- [0043] FIG. 7D is a block diagram illustrating an embodiment of still another phase of a conduction cycle according to the proposed solution.
- [0044] FIG. 8 is a block diagram illustrating an embodiment of a controller according to the proposed solution.
- [0045] FIG. 9 is a block diagram illustrating another embodiment of a controller according to the proposed solution.
- [0046] FIG. 10 is a table illustrating a truth table of a conduction cycle according to the proposed solution.
- [0047] FIG. 11 is a diagram illustrating an embodiment a conduction cycle according to the proposed solution.
- [0048] FIG. 12 is a diagram illustrating another embodiment a conduction cycle according to the proposed solution.
- [0049] FIG. 13 is a flow diagram illustrating an embodiment of the proposed solution.
- [0050] FIG. 14 is a block diagram illustrating yet another embodiment of a controller according to the proposed solution.
- [0051]

Description of embodiments

- [0052] FIG. 1 is a block diagram illustrating an embodiment of a SIBOBB 1000, wherein SIBOBB 1000 is clocked by a clock signal (not shown) having a clock cycle period and comprising four power switches 101, 102, 103, 104, one power inductor 106 and two capacitors 107, 108.
- [0053] SIBOBB 1000 is adapted to supply a positive output voltage V_{POS} and a negative output voltage V_{NEG} from an input voltage V_{BAT} .
- [0054] V_{REF} corresponds to a reference potential common to the entire SIBOBB 1000, commonly referred to as the ground with a value generally equal to 0 volts.

- [0055] A possible embodiment of SIBOBB 1000 is described, for instance, as a power stage in document (2) WO2012/032176.
- [0056] For the sake of clarity and completeness, it appears necessary to present the structure of the power stage of document (2) WO2012/032176 since essential elements therein might be manipulated to achieve the above objectives.
- [0057] Therefore, FIGs. 2 to 5 will be used to describe such power stage, and then, starting from the description of FIG. 6, the proposed solution to the above problem will be presented.
- [0058] One embodiment of a controlled switch 20, included in a section of an electrical circuit 5 of FIG. 4 of a power stage, is diagrammatically represented in FIG. 2. The switch 20 comprises a first coupling node 30 and a second coupling node 40. The switch 20 also comprises at least a first control input 50 and a second control input 60. The switch 20 is adapted to open or close an electrical circuit between the first coupling node 30 and the second coupling node 40, as a function of the control voltages received on the first input 50 and the second input 60. In the example in FIG. 2, the first coupling point 30 is coupled to a node D of the circuit 5, and the second coupling point 40 to a node S of the circuit 5. The voltage at the node S is equal to a voltage V_{NEG} .
- [0059] The switch 20 comprises cascode connected first transistor 21 and second transistor 22. The first and second transistors 21 and 22 may be metal-oxide-semiconductor (MOS) transistors, each comprising a gate, a drain, and a source. In the example in FIG. 2, the first and second transistors are N-channel MOS transistors, more commonly referred to as NMOS transistors.
- [0060] The first transistor 21 is conducting, meaning that it allows current to pass between its drain and its source, when the difference in potential V_{GS} between its gate and its source is greater than a first threshold V_{TH1} . Otherwise, meaning if $V_{GS} < V_{TH1}$, the first transistor 21 is blocked, that is to say non-conducting. The second transistor 22 is conducting, meaning that it allows current to pass between its drain and its source, when the difference in potential V_{GS} between its gate and its source is greater than a

second threshold V_{TH2} . Otherwise, meaning if $V_{GS} < V_{TH2}$, the second transistor 22 is non-conducting.

[0061] The first transistor 21 is placed in the switch 20 so that its gate is coupled to the first input 50, its drain is coupled to the first coupling node 30, and its source is coupled to the drain of the second transistor 22. The second transistor 22 is placed in the switch 20 so that its gate is coupled to the second input 60, its drain to the source of the first transistor 21, and its source to the second coupling node 40.

[0062] The switch 20 is adapted to be controlled by a first control voltage T_1 received on the first input 50, and by a second control voltage T_2 received on the second input 60. The value V_1 of the first control voltage T_1 is less than that of the voltage V_{BAT} and greater than that of the voltage V_{NEG} . The value V_1 of the first control voltage T_1 is substantially constant.

[0063] The second control voltage T_2 can substantially assume two values:

- a first value V_{21} which is substantially equal to the value V_1 of the first control voltage T_1
- a second value V_{22} which is less than the value V_1 of the first control voltage T_1 and equal to that of the voltage V_{NEG} .

[0064] The second transistor 22 is configured in the circuit so as to be:

- conducting when the second control voltage has a value substantially equal to the first value V_{21} ; and,
- non-conducting when the second control voltage has a value substantially equal to the second value V_{22} .

[0065] To close the switch 20, and therefore allow current to flow between the first and second coupling nodes, the control voltage T_2 is applied to the second input 60 while ensuring that the value of said control voltage is equal to the value V_{21} . The difference in potential V_{GS} between the gate and the source of the second transistor 22 is then equal to the difference between the value V_1 and the value of the voltage V_{NEG} , and this difference in potential V_{GS} is greater than the threshold V_{TH2} . Conversely, in order to open the switch 20 and therefore prevent current from flowing between the first and second coupling nodes, the control voltage T_2 is applied to the second input 60 while ensuring that the value of said control voltage is

equal to the value V_{22} . Whether the switch 20 is closed or open, the value of the first control voltage T_1 is maintained at the value V_1 . The difference in potential V_{GS} between the gate and the source of the second transistor 22 is then substantially zero and less than the threshold V_{TH2} .

[0066] In one embodiment, the circuit 5 is used to supply a positive voltage V_{POS} and a negative voltage V_{NEG} , from the voltage V_{BAT} . The switch 20 is then coupled to the circuit so that the first input 50 receives the reference voltage V_{REF} , and the second input 60 receives either the reference voltage V_{REF} or the negative voltage V_{NEG} , depending on whether the switch is to be closed or open.

[0067] As a non-limiting example, the voltage V_{BAT} is supplied by a battery, at a value substantially equal to 4.8V. The positive voltage V_{POS} and the negative voltage V_{NEG} can be symmetrical voltages or dissymmetrical voltages possibly comprised in a range of [1.5V; 4.8V] and [-1.5V; -4.8V] respectively. The values V_1 and V_{21} are equal to the reference voltage V_{REF} , which is 0V. The value V_{22} is equal to the negative voltage V_{NEG} , which is possibly comprised in the range [-1.5V; -4.8V]. When the switch 20 is open, the difference in potential between the first and second coupling nodes is therefore substantially equal to 9.6V. The voltage V_{GS} between the gate and the source of the first transistor 21 is then zero, because the current between the first and second coupling nodes is zero. As a result, the voltage at the drain of the second transistor 22 is equal to V_1 , which is 0V. The first and second transistors can therefore be designed and manufactured to support a maximum difference in potential of only 4.8V.

[0068] A controlled switch 100 according to another embodiment, and which may be included in a section of the electrical circuit 5, is represented in FIG. 3. The switch 100 comprises a first coupling node 130 and a second coupling node 140. The switch 100 also comprises at least a first control input 150 and a second control input 160. The switch 100 is adapted to open or close an electrical circuit between the first coupling node 130 and the second coupling node 140, as a function of the control voltages received in particular on the first input 150 and the second input 160. In the

example in FIG. 3, the first coupling point 130 is coupled to the node D, and the second coupling point 140 to the node T. The voltage at the node T is equal to the voltage V_{BAT} .

- [0069] The switch 100 as shown comprises cascode connected first transistor 110 and a second transistor 120. The first and second transistors are typically metal-oxide-semiconductor transistors, more commonly referred to as MOS transistors, each comprising a gate, a drain, and a source. More particularly, in the example in FIG. 3, the first and second transistors are P-channel MOS transistors or PMOS transistors.
- [0070] The first transistor 110 is conducting, meaning that it allows current to pass between its drain and its source, when the difference in potential V_{GS} between its gate and its source is less than a threshold V_{TH3} . Otherwise, meaning if $V_{GS} > V_{TH3}$, the first transistor 110 is non-conducting. The second transistor 120 is conducting, meaning it allows current to pass between its drain and its source, when the difference in potential V_{GS} between its gate and its source is less than a threshold V_{TH4} . Otherwise, meaning if $V_{GS} > V_{TH4}$, the second transistor 120 is non-conducting.
- [0071] The first transistor 110 is placed in the switch 100 so that its gate is coupled to the first input 150, its drain to the first coupling node 130, and its source to the drain of the second transistor 120. The second transistor 120 is placed in the switch 100 so that its gate is coupled to the second input 160, its drain to the source of the first transistor 110, and its source to the second coupling node 140.
- [0072] The switch 100 is adapted to be controlled by a first control voltage T_3 received on the first input 150, and by a second control voltage T_4 received on the second input 160. The value V_3 of the first control voltage T_3 is less than that of the voltage V_{BAT} and greater than that of the voltage V_{NEG} . The value V_3 of the first control voltage T_3 is substantially constant.
- [0073] The second control voltage T_4 can substantially assume two values:
- a first value V_{41} which is substantially equal to the value V_3 of the first control voltage T_3 ,
 - a second value V_{42} which is greater than the value V_3 of the first control voltage T_3 and equal to that of the voltage V_{BAT} .

- [0074] The second transistor 120 is configured in the circuit to be:
- conducting when the second control voltage has a value substantially equal to the first value V_{41} ,
 - non-conducting when the second control voltage has a value substantially equal to the second value V_{42} .
- [0075] Thus, to close the switch 100 and therefore allow current to flow between the first and second coupling nodes, it is sufficient to apply the control voltage T_4 to the second input 160 while ensuring that the value of said control voltage is equal to the value V_{41} . The difference in potential V_{GS} between the gate and the source of the second transistor is then equal to the difference between the value V_3 and the voltage V_{BAT} , and this difference in potential V_{GS} is less than the threshold V_{TH4} . Otherwise, to open the switch 100 and therefore prevent current from flowing between the first and the second coupling node, the control voltage T_4 is applied to the second input 160 while ensuring that the value of said control voltage is equal to the value V_{42} . The difference in potential V_{GS} between the gate and the source of the second transistor is then substantially zero and greater than the threshold V_{TH4} . Whether the switch 20 is open or closed, the value of the first control voltage T_3 is maintained at the value V_{41} .
- [0076] In one embodiment, the circuit 5 is used to supply the positive voltage V_{POS} and the negative voltage V_{NEG} , from the voltage V_{BAT} . The switch 100 is then coupled to the circuit so that the first input 150 is coupled to the reference potential of the circuit 45, and the second input 160 is coupled either to the voltage V_{BAT} or to the reference potential of the circuit 5, depending on whether the switch is to be closed or open.
- [0077] As a non-limiting example, the voltage V_{BAT} is for example supplied by a battery, and has a value substantially equal to 4.8V. The values V_3 and V_{41} are equal to that of the reference potential, which is 0V. The value V_{42} is equal to that of the voltage V_{BAT} , which is 4.8V. The maximum potential difference between the first and the second coupling node is therefore substantially equal to 4.8V. When the switch 100 is open, the voltage V_{GS} between the gate and the source of the first transistor is also zero, because the current between the first and second coupling node is zero.

As a result, the value of the voltage at the drain of the second transistor 120 is equal to the value V_3 , which is 0V. The first and second transistor can therefore be manufactured to support a maximum potential difference of only 4.8V, when the node D is at the negative voltage V_{NEG} .

- [0078] The switch 300 is a transistor which is typically a metal-oxide-semiconductor transistor, more commonly referred to as MOS, comprising a gate, a drain, a source, and a body diode. In the example in FIG 5, the transistor 300 is a N-channel MOS transistor, or NMOS transistor.
- [0079] The switch 300 is arranged so that its gate is coupled to the first input 350, its drain to the first coupling node 330, its source to the second coupling node 340, and the anode of the body diode to the first coupling node 330.
- [0080] The switch 300 is adapted to be controlled by a first control voltage T_7 received on the first input 350. To open the switch 300, so that no current can flow, the value V_7 of the first control voltage T_7 is equal to that of the reference voltage V_{REF} . To close the switch 300, so that current can flow, the value V_7 of the first control voltage T_7 is equal to that of the input voltage V_{BAT} .
- [0081] The switch 400 is a transistor which is typically a metal-oxide-semiconductor transistor, more commonly referred to as MOS, comprising a gate, a drain, a source, and a body diode. In the example in FIG 5, the transistor 400 is a P-channel MOS transistor, or PMOS transistor.
- [0082] The switch 400 is arranged so that its gate is coupled to the first input 450, its drain to the first coupling node 430, its source to the second coupling node 440, and the cathode of the body diode to the first coupling node 430.
- [0083] The switch 400 is adapted to be controlled by a first control voltage T_8 received on the first input 450. To open the switch 400, so that no current can flow, the value V_8 of the first control voltage T_8 is equal to that of the voltage V_{BAT} . To close the switch 400, so that current can flow, the value V_8 of the first control voltage T_8 is equal to that of the reference voltage V_{REF} .
- [0084] The circuit 5 comprising the previously described switches 20 and 100 can in particular be used in a power supply 600, as represented in FIGs 4 and

5. The power supply 600 is, for example, a voltage regulating device coupled to a voltage source supplying a voltage V_{BAT} , for example a storage cell such as a battery. The power supply 600 is, for example, contained in a portable device such as a mobile telephone, a portable audio and/or video player, or a laptop computer. The power supply 600 comprises a power stage implemented by the circuit 5, adapted to supply a positive voltage V_{POS} and a negative voltage V_{NEG} . The power stage is equipped with control inputs for receiving control voltages defining a control strategy for producing the negative voltage V_{NEG} and the positive voltage V_{POS} . The power supply comprises a control circuit coupled to the power stage outputs in order to compare over time the negative V_{NEG} and positive V_{POS} voltages to at least one reference voltage V_{REF} and to produce error signals V_{err1} , V_{err2} . The power supply comprises a driving circuit 500 coupled to the control circuit in order to receive the error signals V_{err1} , V_{err2} and to generate the control voltages, and to the power stage in order to supply the control voltages so generated.

[0085] FIG. 6 is a block diagram illustrating an embodiment of the proposed solution comprising the SIBOBB 1000, a controller (CTRL) 200, a driver (DRV) 3000, a processor (PROC) 4000, and a display module (DISP) 500 wherein DISP 500 and DRV 3000 are controlled by PROC 4000, DISP 500 is powered by SIBOBB 1000 and SIBOBB 1000 is controlled by DRV 3000.

[0086] All foregoing elements might be embodied, for instance, in a portable device such as a smartphone, a tablet, a console game or an e-book reader.

[0087] Referring to FIG. 6, the SIBOBB 1000 comprises four output pins 109, 110, 111, 112 and four input pins 113, 114, 115, 116.

[0088] Input pins 113, 114, 115 and 116 are adapted to receive driving commands DRV_2 , DRV_3 , DRV_1 and DRV_4 from DRV 3000, and used to command power switches 101, 102, 103 and 104, respectively.

[0089] DRV 3000 is configured to either turn on or turn off power switches 101, 102, 103 and 104 thanks to driving commands DRV_2 , DRV_3 , DRV_1 and

DRV₄, respectively based on one or more control commands CMD received from CTRL 2000.

- [0090] One should understand that, throughout the description, when a power switch 101, 102, 103 and 104, is said to be “turned on” it means that corresponding switch 101, 102, 103 and 104 is “closed” and conducting, such that current can flow through it.
- [0091] On the other hand, when a power switch 101, 102, 103 and 104, is said to be “turned off” it means that corresponding switch 101, 102, 103 and 104 is “open” and non-conducting, such that current can not flow through it.
- [0092] Referring again to FIG. 6, output pins 111 and 112 are adapted to provide positive output voltage V_{POS} substantially higher than the voltage V_{BAT} and negative output voltage V_{NEG} to DISP 500, respectively.
- [0093] DISP 500 is configured to display one or more images IMG, by supplying pixels (not shown) of DISP 500 with positive output voltage V_{POS} and negative output voltage V_{NEG} .
- [0094] For instance, DISP 500 might be a Liquid Crystal Display (LCD) panel, an Organic Light Emitting Diode (OLED) display panel or an AMOLED display panel.
- [0095] For instance, as well, the one or more images IMG are presented to DISP 500 by PROC 4000.
- [0096] Referring again to FIG. 6, output pins 109 and 110 are adapted to provide positive output voltage V_{POS} substantially higher than the voltage V_{BAT} and negative output voltage V_{NEG} to CTRL 2000, respectively.
- [0097] CTRL 2000 is configured to control operations modes performed by SIBOBB 1000.
- [0098] An operation mode is a particular task performed by SIBOBB 1000.
- [0099] For instance, in an embodiment, SIBOBB 1000 can be configured to perform the following tasks:
- charging the inductor 106 current,
 - discharging the inductor 106 current to a negative output 109, 111, or
 - discharging the inductor 106 current to a positive output 110, 112.
- [00100] These tasks can be arranged in a particular order depending on the requirements.

- [00101] In the rest of the description, a series of sequential tasks performed by SIBOBB 1000 would be called a conduction cycle.
- [00102] A conduction cycle is generally performed during a clock cycle period, whereby a clock cycle period is the time from a first clock signal to the end of a succession of clock signals.
- [00103] In order to apply particular conduction cycle, CTRL 2000 uses one or more control commands CMD sent to DRV 3000.
- [00104] Control commands CMD are based on, at least, positive output voltage V_{POS} , negative output voltage V_{NEG} , a first reference voltage V_{REF1} , and a second reference voltage V_{REF2} or a combination of the foregoing parameters.
- [00105] For instance, the first reference voltage might be a positive reference voltage or a sum reference voltage while the second reference voltage might be a negative reference voltage or a difference reference voltage.
- [00106] Both, the first reference voltage V_{REF1} and the second reference voltage V_{REF2} are received by CTRL 2000 from PROC 4000.
- [00107] PROC 4000 is configured to control the provided reference voltage V_{REF1} and reference voltage V_{REF2} to CTRL 2000 and is also configured to present one or more images IMG to DISP 500 so as to have them being displayed by DISP 500.
- [00108] In order to overcome the weakness of prior art regarding asymmetry in load current between negative output current and positive output current, as stated before, it is proposed, in one embodiment, a conduction cycle made of at least two phases.
- [00109] The two phases can be chosen from a group comprising embodiments of FIG. 7A (called thereafter charging phase or CHG), FIG. 7B (called thereafter positive discharging phase or DISCHG_{POS}), FIG. 7C (called thereafter negative discharging phase or DISCHG_{NEG}) and FIG. 7D (called thereafter simultaneous discharging phase or DISCHG_{SIMUL}).
- [00110] However, one should note that the first phase of the conduction cycle needs to be set to the embodiment of FIG. 7A CHG.

[00111] Therefore, at least eight different variants of the conduction cycle can be implemented, based on particular chaining of the different phases during a clock cycle period.

[00112] Namely, the conduction cycle can be arranged in any of the following configurations:

- CHG – DISCHG_{POS},
- CHG – DISCHG_{NEG},
- CHG – DISCHG_{POS} – DISCHG_{NEG},
- CHG – DISCHG_{NEG} – DISCHG_{POS},
- CHG – DISCHG_{SIMUL} – DISCHG_{POS},
- CHG – DISCHG_{SIMUL} – DISCHG_{NEG},
- CHG – DISCHG_{POS} – DISCHG_{SIMUL}, and
- CHG – DISCHG_{NEG} – DISCHG_{SIMUL}.

[00113] Therefore, one should understand that the discharging phase could be performed to only one output or both outputs.

[00114] In an embodiment wherein discharging phase occurs on both outputs, this could be done by discharging in a sequential fashion (i.e. one after the other).

[00115] Let's describe, the different phases of FIG. 7A, FIG. 7B, FIG. 7C and FIG. 7D.

[00116] Referring to FIG. 7A, FIG. 7B, FIG. 7C and FIG. 7D there is shown therein the SIBOBB 1000 wherein, for instance, power switches 102 and 103 might be implemented as Schottky diodes, if for instance low output power is required out of the SIBOBB 1000.

[00117] In fact, Schottky diodes have the main advantage of switching naturally. Therefore its use could permit to make the economy of charging a power MOSFET gate thus reducing the switching loss in the SIBOBB 1000. Furthermore, Schottky diodes have low drop (i.e. few hundred of millivolts) and thus they have not so large ohmic losses.

[00118] This choice is also simplifying the conduction cycle, since in this case only two power switches 101 and 104 need to be controlled.

[00119] Obviously others type of diodes may be used as well depending on required efficiency and transient responses.

- [00120] Referring to FIG. 7A, there is shown therein the power switches 102 and 103 which are turned off and the power switches 101 and 104 which are turned on.
- [00121] With such configuration, SIBOBB 1000 enters the charging phase CHG, wherein the inductor current is charged between V_{BAT} and V_{REF} .
- [00122] Referring to FIG. 7B, there is shown therein the power switches 101 and 103 which are turned on and the power switches 102 and 104 which are turned off.
- [00123] With such configuration, SIBOBB 1000 enters the positive discharging phase $DISCHG_{POS}$ wherein all or part of the inductor current is discharged to the positive output voltage V_{POS} , between V_{BAT} and V_{POS} .
- [00124] In this case, one should understand that this configuration assumes that V_{POS} is substantially higher than the voltage V_{BAT} .
- [00125] This is for instance the case for AMOLED display panels wherein the required positive voltage is 4.6 V while the battery voltage V_{BAT} supplying such screens are most of the time lower than 4.5 V.
- [00126] Referring to FIG. 7C, there is shown therein the power switches 102 and 104 which are turned on and the power switches 101 and 103 which are turned off.
- [00127] With such configuration, SIBOBB 1000 enters the negative discharging phase $DISCHG_{NEG}$ wherein all or part of the inductor current is discharged to the negative output voltage V_{NEG} , between V_{NEG} and V_{REF} .
- [00128] Referring to FIG. 7D, there is shown therein the power switches 101 and 104 which are turned off and the power switches 102 and 103 which are turned on.
- [00129] With such configuration, SIBOBB 1000 enters the discharging phase $DISCHG_{SIMUL}$, wherein all or part of the inductor current is discharged simultaneously to both the positive output voltage V_{POS} and the negative output voltage V_{NEG} , between V_{NEG} and V_{POS} .
- [00130] FIG. 8 is a block diagram illustrating an embodiment of CTRL 2000, wherein there is shown therein two difference units 201, 203, two error comparison units 202, 204 and a logic control unit LGC 205.

- [00131] Referring to FIG. 8, V_{POS} and V_{REF1} are received at the input of the difference unit 201 which is configured to generate an error signal ERR_1 from a difference between V_{POS} and V_{REF1} .
- [00132] Also, in FIG. 8, V_{NEG} and V_{REF2} are received at the input of the difference unit 203 which is configured to generate an error signal ERR_2 from a difference between V_{NEG} and V_{REF2} .
- [00133] Afterwards, ERR_1 is presented at the input of the comparison unit 202 along with a signal SIG_1 while ERR_2 is presented at the input of the comparison unit 204 along with a signal SIG_2 .
- [00134] One should understand that the implementation of comparison unit 202 might be different from the implementation of comparison unit 204, the implementation of the difference unit 201 might be different from the implementation of the difference unit 203 and the implementation of SIG_1 might be different from the implementation of SIG_2 .
- [00135] In an embodiment, the difference units 201, 203 are error amplifiers with proportional plus integral plus derivative (PID) control, the comparison units 202 and 204 are Pulse Width Modulation (PWM) modulators while signal SIG_1 and SIG_2 are, for instance, periodic ramp signals, which period equals the clock period such as saw-tooth signals or triangular signals.
- [00136] With such embodiment, the comparison unit 202 is configured to generate a PWM signal DC_1 based on ERR_1 and SIG_1 .
- [00137] This operation is performed, for instance, by having the PWM modulator 202 setting a logic high state to DC_1 when ERR_1 is below SIG_1 and setting a logic low state to DC_1 when ERR_1 exceeds SIG_1 .
- [00138] Also, with such embodiment, the comparison unit 204 is configured to generate a PWM signal DC_2 based on ERR_2 and SIG_2 .
- [00139] This operation is performed, for instance, by having the PWM modulator 204 setting a logic high state to DC_2 when ERR_2 is below SIG_2 and setting a logic low state to DC_2 when ERR_2 exceeds SIG_2 .
- [00140] In digital logic, logic high state would be a bit 1 and logic low state would be a bit 0 while in analog logic, logic high state would be a high voltage level and logic low state would be a low voltage level.

- [00141] Finally, DC_1 and DC_2 are presented at the input of LGC 205 which is configured to generate the one or more control commands CMD used to drive DRV 3000 as already explained in the foregoing, in order to apply a given conduction cycle.
- [00142] The choice of which configuration of the conduction cycle to be used depends on the different logic within which DC_1 and DC_2 are decoded, during the clock cycle period.
- [00143] Additionally, since DC_1 and DC_2 are based on the positive output voltage V_{POS} , and on the negative output voltage V_{NEG} , therefore the conduction cycle depends on the positive output voltage V_{POS} , and on the negative output voltage V_{NEG} .
- [00144] More generally, in the present application, DC_1 is used, alone, by LGC 205 to determine the amount of energy to be accumulated by SIBOBB 1000, namely by the current inductor 106, depending on the required positive output voltage V_{POS} , and on the negative output voltage V_{NEG} that need to be delivered by the SIBOBB 1000.
- [00145] On the other hand, DC_1 and DC_2 are used all together by LGC 205 to determine the amount of energy to be discharged to each output of SIBOBB 1000.
- [00146] FIG. 9 is a block diagram illustrating an embodiment of CTRL 2000, wherein there is shown therein three difference units 201, 203, 206, one summation unit 207, two error comparison units 202, 204 and a logic control unit (LGC) 205.
- [00147] Referring to FIG. 9, V_{POS} and V_{NEG} are received at the input of the difference unit 206 which is configured to generate a voltage DIFF from a difference between V_{POS} and V_{NEG} .
- [00148] Again in FIG. 9, V_{POS} and V_{NEG} are received at the input of the summation unit 207 which is configured to generate a voltage SUM from a sum of V_{POS} and V_{NEG} .
- [00149] Later in FIG. 9, SUM and V_{REF1} are received at the input of the difference unit 201 which is configured to generate an error signal ERR_1 from a difference between SUM and V_{REF1} .

- [00150] Also, in FIG. 9, DIFF and V_{REF2} are received at the input of the difference unit 203 which is configured to generate an error signal ERR_2 from a difference between DIFF and V_{REF2} .
- [00151] Then, ERR_1 is presented at the input of the comparison unit 202 along with a signal SIG_1 while ERR_2 is presented at the input of the comparison unit 204 along with a signal SIG_2 .
- [00152] One should understand that each of the implementation of comparison units 202, 204 might be different from each other, each of the implementation of the difference units 201, 203, 206 might be different from each other as well and each of the implementation of SIG_1 , SIG_2 might be different from each other.
- [00153] In an embodiment, the difference units 201, 203, 206 are error amplifiers with proportional plus integral plus derivative (PID) control, the comparison units 202 and 204 are Pulse Width Modulation (PWM) generators while signal SIG_1 and SIG_2 are a signal of a saw-tooth signal or a triangular signal.
- [00154] With such embodiment, the comparison unit 202 is configured to generate a PWM signal DC_1 based ERR_1 and SIG_1 .
- [00155] This operation is performed, for instance, by having the PWM modulator 202 setting a logic high state to DC_1 when ERR_1 is below SIG_1 and setting a logic low state to DC_1 when ERR_1 exceeds SIG_1 .
- [00156] Also, with such embodiment, the comparison unit 204 is configured to generate a PWM signal DC_2 based ERR_2 and SIG_2 .
- [00157] This operation is performed, for instance, by having the PWM modulator 204 setting a logic high state to DC_2 when ERR_2 is below SIG_2 and setting a logic low state to DC_2 when ERR_2 exceeds SIG_2 .
- [00158] In digital logic, logic high state would be a bit 1 and logic low state would be a bit 0 while in analog logic, logic high state would be a high voltage level and logic low state would be a low voltage level.
- [00159] Finally, DC_1 and DC_2 are presented at the input of LGC 205 which is configured to generate the one or more control commands CMD used to drive DRV 3000 as already explained in the foregoing, in order to apply a given conduction cycle.

- [00160] The choice of which configuration of the conduction cycle to be used depends on the different logic within which DC_1 and DC_2 are decoded, during the clock cycle period.
- [00161] Additionally, since DC_1 and DC_2 are based on the positive output voltage V_{POS} , and on the negative output voltage V_{NEG} , therefore the conduction cycle depends on the positive output voltage V_{POS} , and on the negative output voltage V_{NEG} .
- [00162] More generally, in the present application, DC_1 is used, alone, by LGC 205 to determine the amount of energy to be accumulated by SIBOBB 1000, namely by the current inductor 106, depending on the required positive output voltage V_{POS} , and on the negative output voltage V_{NEG} that need to be delivered by the SIBOBB 1000.
- [00163] On the other hand, DC_1 and DC_2 are used all together by LGC 205 to determine the amount of energy to be discharged to each output of SIBOBB 1000.
- [00164] One should understand, in other words, that the amount of energy to be accumulated or discharged, as explained in the foregoing embodiments of FIG. 8 and FIG. 9, depends on the duty cycle of the corresponding signals DC_1 and DC_2 wherein the duty cycle should be understood as being the amount of time during which DC_1 or DC_2 are in a logic high state, during the clock cycle period.
- [00165] The embodiment of the CTRL 2000 of FIG. 8 is mostly suitable for cases where there is a load current symmetry of negative output current and positive output current that is required at the output 109, 110, 111, 112 of SIBOBB 1000.
- [00166] In case where a total load current asymmetry of negative output current and positive output current is needed at the output 109, 110, 111, 112 of SIBOBB 1000, embodiment of the CTRL 2000 of FIG. 9 is a possible preferred solution.
- [00167] Hence, with the configuration of FIG. 9, weakness of state of the art regarding control of SIBO -Boost converters to deliver independent buck or boost to each input voltage is overcome.

- [00168] In fact, with this embodiment, depending on the duty cycles of DC_1 and/or DC_2 , one output 109, 110, 111, 112 of SIBOBB 1000 may signify that it does not need energy and that only the other output should be supplied. Thus, the conduction cycle could, for instance, comprise two phases corresponding, first to a charging phase followed by a discharging phase to an output 109, 110, 111, 112 of SIBOBB 1000.
- [00169] Another conduction cycle could, for instance, comprise three phases corresponding, first to a charging phase followed by a discharging phase to an output 109, 110, 111, 112 of SIBOBB 1000 and then another discharging phase to the other output 109, 110, 111, 112 of SIBOBB 1000.
- [00170] In this case, positive discharging phase $DISCHG_{POS}$ could be performed before negative discharging phase or $DISCHG_{NEG}$ or conversely, negative discharging phase $DISCHG_{NEG}$ could be performed before positive discharging phase or $DISCHG_{POS}$.
- [00171] The different logic state combinations of the conduction cycle can be summarised by the exemplary truth table 600 of FIG. 10, wherein digital logic is used.
- [00172] Possibly, truth table 600 is implemented within LGC 205.
- [00173] As it can be seen, when DC_1 is at a logic state corresponding to bit 0 (i.e. when ERR_1 exceeds SIG_1) and whatever the logic state of DC_2 , then SIBOBB 1000 would be instructed by CTRL 2000, through DRV 3000, to initiate the charging phase CHG.
- [00174] This is why it has been stated above that DC_1 , alone, might be used to determine the amount of energy to be accumulated by SIBOBB 1000.
- [00175] However, when DC_1 is at a logic state corresponding to bit 1 (i.e. when ERR_1 is below SIG_1) and DC_2 is at a logic state corresponding to bit 0 (i.e. when ERR_2 exceeds SIG_2) then SIBOBB 1000 would be instructed by CTRL 2000, through DRV 3000, to initiate the discharging phase $DISCHG_{POS}$.
- [00176] This is why it has been stated above that DC_1 and DC_2 are used to determine the amount of energy to be discharged to each output of SIBOBB 1000. As stated earlier, the amount of discharged energy to each output mainly depends on the duty cycle of DC_1 and DC_2 .

- [00177] Also, when DC_1 is at a logic state corresponding to bit 1 (i.e. when ERR_1 is below SIG_1) and DC_2 is at a logic state corresponding to bit 1 (i.e. when ERR_2 is below SIG_2) then SIBOBB 1000 would be instructed by CTRL 2000, through DRV 3000, to initiate the discharging phase $DISCHG_{NEG}$.
- [00178] This is why it has been stated above that DC_1 and DC_2 are used to determine the amount of energy to be discharged to each output of SIBOBB 1000.
- [00179] Again, as stated earlier, the amount of discharged energy to each output 109, 110, 111, 112 of SIBOBB 1000, mainly depends on the duty cycle of DC_1 and DC_2 .
- [00180] In order to fully understand the proposed solution, two exemplary embodiments of the proposed conduction cycle will be described in FIG. 11 and FIG. 12.
- [00181] Referring to FIG. 11 and FIG. 12, there is shown therein three timing diagrams A, B, C represented over two clock cycle periods.
- [00182] Timing diagram A shows the evolution of ERR_1 , ERR_2 , SIG_1 and SIG_2 .
- [00183] For the purpose of clarity and simplicity, SIG_1 and SIG_2 are considered alike and future references would be made to SIG_1 only as being a saw-tooth signal.
- [00184] Timing diagrams B and C show the evolution of DC_1 and DC_2 , respectively.
- [00185] Referring to FIG. 11, in the first clock cycle period, it can be seen that during CHG phase, both ERR_1 and ERR_2 exceed SIG_1 thus leading DC_1 and DC_2 being at the logic low state. In digital logic, this corresponds to configuration '00' as already described in FIG. 10.
- [00186] Later, it can be seen that during $DISCHG_{POS}$ phase, ERR_1 is below SIG_1 thus leading DC_1 being at the logic high state and ERR_2 exceeds SIG_1 thus leading DC_2 being at the logic low state.
- [00187] In digital logic, this corresponds to configuration '10' as already described in FIG. 10.
- [00188] Later again, it can be seen that during $DISCHG_{NEG}$ phase, ERR_1 is below SIG_1 thus leading DC_1 being at the logic high state and ERR_2 is below SIG_1 thus leading DC_2 being at the logic high state.

- [00189] In digital logic, this corresponds to configuration '11' as already described in FIG. 10.
- [00190] Referring to FIG. 11, in the second clock cycle period, it can be seen that during the first CHG phase, both ERR_1 and ERR_2 exceed SIG_1 thus leading DC_1 and DC_2 being at the logic low state.
- [00191] In digital logic, this corresponds to configuration '00' as already described in FIG. 10.
- [00192] Later, it can be seen that during the second CHG phase, ERR_2 is below SIG_1 thus leading DC_2 being at the logic high state and ERR_1 exceeds SIG_1 thus leading DC_1 being at the logic low state.
- [00193] In digital logic, this corresponds to configuration '01' as already described in FIG. 10.
- [00194] Later again, it can be seen that during $DISCHG_{NEG}$ phase, ERR_1 is below SIG_1 thus leading DC_1 being at the logic high state and ERR_2 is below SIG_1 thus leading DC_2 being at the logic high state.
- [00195] In digital logic, this corresponds to configuration '11' as already described in FIG. 10.
- [00196] Referring to FIG. 12, in the first clock cycle period, it can be seen that during CHG phase, both ERR_1 and ERR_2 exceed SIG_1 thus leading DC_1 and DC_2 being at the logic low state.
- [00197] In digital logic, this corresponds to configuration '00' as already described in FIG. 10.
- [00198] Later, it can be seen that during $DISCHG_{POS}$ phase, ERR_1 is below SIG_1 thus leading DC_1 being at the logic high state and ERR_2 exceeds SIG_1 thus leading DC_2 being at the logic low state.
- [00199] In digital logic, this corresponds to configuration '10' as already described in FIG. 10.
- [00200] Referring to FIG. 12, in the second clock cycle period, it can be seen that during the first CHG phase, both ERR_1 and ERR_2 exceed SIG_1 thus leading DC_1 and DC_2 being at the logic low state.
- [00201] In digital logic, this corresponds to configuration '00' as already described in FIG. 10.

- [00202] Later, it can be seen that during the second DISCHG_{NEG} phase, both ERR₁ and ERR₂ are below SIG₁ thus leading DC₁ and DC₂ being at the logic high state.
- [00203] In digital logic, this corresponds to configuration '11' as already described in FIG. 10.
- [00204] FIG. 13 is a flow diagram illustrating an embodiment of the proposed solution corresponding to the embodiment as already described above for FIG. 12.
- [00205] Referring to FIG. 13, in step S700, a first control signal DC₁ based on, at least, the negative output voltage, a negative reference voltage and a saw-tooth signal is generated as already described above.
- [00206] Then, in a step S701, a second control DC₂ signal based on, at least, the positive output voltage, positive reference voltage and a saw-tooth signal is generated as already described above.
- [00207] Later, in a step S702, the SIBOBB 1000 is operated, based on a given logic and the first control signal so as to initiate a charging phase CHG, such that a first duty cycle of the first control signal is controlling an amount of energy to be accumulated by the SIBOBB 1000 as already described above.
- [00208] Finally, in a step S703, the SIBOBB 1000 is operated, based on the given logic and the first control signal simultaneously with the second control signal so as to initiate an independent discharging phase DISCHG_{NEG}, DISCHG_{POS} of the accumulated energy, in a buck-type or boost-type, to at least an output of the SIBOBB 1000 such that a second duty cycle of the second control signal is controlling an amount of energy to be discharged by the SIBOBB 1000 as already described above.
- [00209] After that, the algorithm would stop.
- [00210] FIG. 14 is a block diagram illustrating an embodiment of CTRL 2000.
- [00211] With the embodiment of FIG. 14, the average current passing through the inductor 106 and the ohmic losses are optimised.
- [00212] In fact, for certain industry, such as the mobile phone industry, there are stringent requirements regarding the size of the components that could be

used, in order to produce low cost and small physical size devices in order to suit customers needs.

[00213] This is the case, for instance, for the inductor 106 that is used in the SIBOBB 1000 if the latter need to be placed as close a possible to the mobile phone screen.

[00214] One should know that the height of an inductor is proportional to the load current, thus it could be said that higher inductors can handle more currents than smaller ones.

[00215] In the SIBOBB 1000 the amount of current passing through the inductor 106, at a given moment in time, can be determined by the following formula:

$I_L = I_{OUT} \times V_{OUT}/V_{IN}$, wherein I_L is the amount of current in the inductor, I_{OUT} is the amount of current at the output of the SIBOBB 1000, V_{OUT} is the output voltage of the SIBOBB 1000 and V_{IN} is the input voltage of the SIBOBB 1000 such as V_{BAT} .

[00216] Therefore, one should understand that as V_{IN} is decreasing and V_{OUT} is increasing, depending on the application, high peak currents (e.g. 2 Amps) could be experienced in the inductor 106, thus reaching the current saturation of the inductor 106.

[00217] This situation could occur with conduction cycles feeding outputs 109, 110, 111, 112 of the SIBOBB 1000 in a sequential fashion.

[00218] However, as said above, high peak currents would require inductors high in size (e.g. 2 mm) while, for instance in the mobile phone industry, inductors with smaller height (e.g. <1 mm) are required.

[00219] This is not acceptable and it should be possible to deliver independent buck-type or boost-type bipolar voltages in a SIBOBB 1000 using small sized inductors.

[00220] This optimisation could be achieved by discharging the inductor, at some point, through the bipolar outputs of the SIBOBB 1000 in a simultaneous fashion instead of doing it in a sequential fashion.

[00221] Namely, this optimisation involves the use of conduction cycles made of at least three phases.

[00222] The three phases can be chosen from a group comprising a charging phase CHG, the positive discharging phase DISCHG_{POS}, the negative discharging phase DISCHG_{NEG} and the discharging phase DISCHG_{SIMUL} as already described above.

[00223] However, as stated earlier, one should note that the first phase of the conduction cycle needs to be set to the charging phase CHG and also that it is assumed that V_{POS} is substantially higher than the voltage V_{BAT} .

[00224] Therefore, in this embodiment of FIG. 14, at least four different configurations of the conduction cycle can be implemented, based on particular chaining of the different phases during a clock cycle period.

[00225] Namely, the conduction cycle can be arranged in any of the following configurations:

- CHG – DISCHG_{SIMUL} – DISCHG_{POS},
- CHG – DISCHG_{SIMUL} – DISCHG_{NEG},
- CHG – DISCHG_{POS} – DISCHG_{SIMUL}, and
- CHG – DISCHG_{NEG} – DISCHG_{SIMUL}.

[00226] For instance, conduction cycles “CHG – DISCHG_{POS} – DISCHG_{SIMUL}” or “CHG – DISCHG_{SIMUL} – DISCHG_{POS}” could be used to discharge more energy into the positive output 110, considering that it requires more energy than the negative output 109.

[00227] For instance, conduction cycle “CHG – DISCHG_{NEG} – DISCHG_{SIMUL}” or “CHG – DISCHG_{SIMUL} – DISCHG_{NEG}” could be used to discharge more energy into the negative output 109, considering that it requires more energy than the positive output 110.

[00228] Therefore, one should understand that discharging phase DISCHG_{SIMUL} is to be performed simultaneously on both outputs.

[00229] Referring to FIG. 14, there is shown therein four difference units 201, 203, 206, 212, one summation unit 207, three error comparison units 202, 204, 213 and a logic control unit (LGC) 205.

[00230] Referring to FIG. 14, V_{POS} and V_{NEG} are received at the input of the difference unit 206 which is configured to generate a voltage DIFF from a difference between V_{POS} and V_{NEG} .

- [00231] Again in FIG. 14, V_{POS} and V_{NEG} are received at the input of the summation unit 207 which is configured to generate a voltage SUM from a sum of V_{POS} and V_{NEG} .
- [00232] Later in FIG. 14, SUM and V_{REF1} are received at the input of the difference unit 201 which is configured to generate an error signal ERR_1 from a difference between SUM and V_{REF1} .
- [00233] Also, in FIG. 14, DIFF and V_{REF2} are received at the input of the difference unit 203 which is configured to generate an error signal ERR_2 from a difference between DIFF and V_{REF2} .
- [00234] Later, ERR_1 and ERR_2 are received at the input of the difference unit 212 which is configured to generate an error signal ERR_3 from a difference between ERR_1 and ERR_2 .
- [00235] Subsequently, ERR_1 is presented at the input of the comparison unit 202 along with a signal SIG_1 , ERR_2 is presented at the input of the comparison unit 204 along with a signal SIG_2 and ERR_3 is presented at the input of the comparison unit 213 along with a signal SIG_3 .
- [00236] One should understand that each of the implementation of comparison units 202, 204, 213 might be different from each other, each of the implementation of the difference units 201, 203, 206, 212 might be different from each other as well and each of the implementation of SIG_1 , SIG_2 , SIG_3 might be different from each other.
- [00237] In an embodiment, the difference units 201, 203, 206, 212 are error amplifiers with proportional plus integral plus derivative (PID) control, the comparison units 202, 204, 213 are Pulse Width Modulation (PWM) generators while signal SIG_1 , SIG_2 , SIG_3 are a signal of a saw-tooth signal or a triangular signal.
- [00238] With such embodiment, the comparison unit 202 is configured to generate a PWM signal DC_1 based on ERR_1 and SIG_1 .
- [00239] This operation is performed, for instance, by having the PWM modulator 202 setting a logic high state to DC_1 when ERR_1 is below SIG_1 and setting a logic low state to DC_1 when ERR_1 exceeds SIG_1 .
- [00240] Also, with such embodiment, the comparison unit 204 is configured to generate a PWM signal DC_2 based on ERR_2 and SIG_2 .

- [00241] This operation is performed, for instance, by having the PWM modulator 204 setting a logic high state to DC_2 when ERR_2 is below SIG_2 and setting a logic low state to DC_2 when ERR_2 exceeds SIG_2 .
- [00242] Again, with such embodiment, the comparison unit 213 is configured to generate a PWM signal DC_3 based on ERR_1 and ERR_2 .
- [00243] This operation is performed, for instance, by setting a logic high state to DC_3 when ERR_3 is below SIG_3 and setting a logic low state to DC_3 when ERR_3 exceeds SIG_3 .
- [00244] In digital logic, logic high state would be a bit 1 and logic low state would be a bit 0 while in analog logic, logic high state would be a high voltage level and logic low state would be a low voltage level.
- [00245] Finally, DC_1 , DC_2 and DC_3 are presented at the input of LGC 205 which is configured to generate the one or more control commands CMD used to drive DRV 3000 as already explained in the foregoing, in order to apply a given conduction cycle.
- [00246] The choice of which configuration of the conduction cycle to be used depends on the different logic within which DC_1 , DC_2 and DC_3 are, during the clock cycle period.
- [00247] Additionally, since DC_1 , DC_2 and DC_3 are based on the positive output voltage V_{POS} , and on the negative output voltage V_{NEG} , therefore the conduction cycle depends on the positive output voltage V_{POS} , and on the negative output voltage V_{NEG} .
- [00248] More generally, in the present application, DC_1 is used, alone, by LGC 205 to determine the amount of energy to be accumulated by SIBOBB 1000.
- [00249] On the other hand, DC_1 , DC_2 and DC_3 are used all together by LGC 205 to determine the amount of energy to be discharged to each output of SIBOBB 1000.
- [00250] This could be achieved by having DC_2 and DC_3 being symmetrical with respect to DC_1 , thus creating the two additional phases of the conduction cycle.
- [00251] In this case, at a given moment in time, DC_2 could be equal to DC_1 plus a given delta value while DC_3 would be equal to DC_1 minus the given delta value.

[00252] Another possibility is that, at a given moment in time, DC_3 could be equal to DC_1 plus a given delta value while DC_2 is equal to DC_1 minus the given delta value.

[00253] One should understand that the amount of energy to be accumulated or discharged, as explained in the foregoing embodiment of FIG. 14, depends on the duty cycle of the corresponding signals DC_1 , DC_2 and DC_3 wherein the duty cycle should be understood as being the amount of time during which DC_1 , DC_2 and DC_3 are in a logic high state, during the clock cycle period.

[00254] The proposed solution enables to optimise the amount of current that passes through the inductor 106 of the SIBOBB 1000, thus enabling the use of small sized conductors for implementation.

[00255] An apparatus embodying features of the proposed solution is also claimed.

[00256] A display integrated circuit comprising the apparatus is also claimed.

[00257] The latter may comprise also, for instance, a display panel, the SIBOBB 1000, a processor 4000.

[00258] A wireless device comprising the display integrated circuit is also claimed.

[00259] In the claims, the word “comprising” does not exclude other elements or steps, and the indefinite article “a” or “an” does not exclude a plurality. A single unit may fulfil the functions of several items recited in the claims.

[00260] For instance, reference voltages V_{REF1} , V_{REF2} might be stored inside the processor PROC 4000 or outside within a memory such as a register.

[00261] For instance also, DRV 3000 might be implemented inside CTRL 2000.

[00262] In the foregoing description, power switches 101, 102, 103 and 104 are respectively substantially equivalent to the power switches 100, 20, 400 and 300.

[00263] As explained as well earlier, CTRL 2000 might be implemented with digital logic, analog logic or mixed-signal logic without departing from the scope of the proposed solution.

[00264] The mere fact that different features are recited in mutually different dependent claims does not indicate that a combination of these features

cannot be advantageously used. Any reference signs in the claims should not be construed as limiting the scope of the proposed solution.

Reference documents list

[00265] Document (1): **TEXAS INSTRUMENTS, TPS65136**. Single Inductor Multiple Output Regulator for AMOLED.

<http://www.ti.com/lit/ds/symlink/tps65136.pdf> (849 KB). 07 Jul 2008.

[00266] Document (2): WO2012/032176.

Claims

1. A method of driving a Single Inductor Bipolar Output Buck-Boost (1000), SIBOBB, clocked by a clock signal having a given clock cycle period, the SIBOBB comprising an input for receiving a first potential (V_{BAT}), at least four power switches (101,102,103,104), and at least one positive output (110, 112) adapted to output a positive output voltage (V_{POS}) substantially higher than the first potential and at least one negative output (109, 111) adapted to output a negative output voltage (V_{NEG}), the method comprising the following steps performed during the clock cycle period:
 - generating a first control signal (DC_1) based on, at least, the positive output voltage and a positive reference voltage (V_{REF1});
 - generating a second control signal (DC_2) based on, at least, the negative output voltage and a negative reference voltage (V_{REF2});
 - initiating a charging phase (CHG) of charging the SIBOBB, based on a monitoring of the first control signal, during which an amount of energy to be accumulated by the SIBOBB is controlled by a first duty cycle of the first control signal;
 - initiating a first discharging phase ($DISCHG_{POS}$, $DISCHG_{NEG}$) of discharging the energy accumulated in the SIBOBB to at least one of the positive output in a boost-type configuration of the SIBOBB and the negative output in a buck-type or boost-type configuration of the SIBOBB, based on a simultaneous monitoring of the first control signal and the second control signal, during which first discharging phase, an amount of energy to be discharged by the SIBOBB is controlled by a second duty cycle of the second control signal; and, wherein, the charging phase is initiated before the first discharging phase.
2. The method of claim 1, wherein the SIBOBB comprising:
 - an electrical circuit, comprising:
 - at least a first control input (50), a second control input (60), a third control input (150), a fourth control input (160), a fifth control input (350), an sixth control input (450) and
 - at least a first switch (20) comprising a first terminal (30) and a second terminal (40), the first switch being adapted to be controlled:
 - by setting the first control input (50) to a first electrical control voltage

(T1), with the value (V1) of the first control voltage (T1) being less than that of the maximum value of the first potential (V_{BAT}) at the first terminal and greater than that of the value of a third potential (V_{NEG}) at the second terminal, and

- to close the first switch (20), by setting the second control input (60) to the first control voltage (T1), or,

- to open the first switch (20), by setting the second control input (60) to a second control voltage (T2) substantially equal to the third potential (V_{NEG}) of the second terminal,

- at least a second switch (100) comprising a third terminal (130) and a fourth terminal (140), the second switch being adapted to be controlled:

- by setting the third control input (150) to a third control voltage (T3), with the value (V3) of the third control voltage (T3) being less than a first minimum value of the first potential (V_{BAT}) at the fourth terminal and greater than the value of the third potential (V_{NEG}) at the third terminal, and

- to close the second switch (100), by setting the fourth control input (160) to the third control voltage (T3), or

- to open the second switch, by setting the fourth control input (160) to a fourth control voltage (T4) substantially equal to the maximum value of the of the first potential (V_{BAT}) of the fourth terminal (140),

- at least a third switch (300), comprising a fifth terminal (330) and a sixth terminal (340), the third switch being adapted to be controlled:

- to open the third switch, by setting the fifth control input (350) to the reference potential (V_{REF}), or

- to close the third switch, by setting the fifth control input (350) to the first potential (V_{BAT}), - at least a fourth switch (400), comprising a seventh terminal (430) and a eighth terminal (440), the fourth switch being adapted to be controlled:

- to close the fourth switch, by setting the sixth control input (450) to the reference potential (V_{REF}), or

- to open the fourth switch, by setting the sixth control input (450) to the second potential (V_{POS});

the difference between the first control voltage (T1) and the second control voltage (T2) being greater than both the value of the threshold voltage of a first

transistor and the value of the threshold voltage of a second transistor when the first switch is closed,

the difference between the third control voltage (T3) and the fourth control voltage (T4) being greater than both the value of the threshold voltage of a third transistor and the value of the threshold voltage of a fourth transistor when the second switch is closed,

the difference between a second potential (V_{POS}) and the reference potential (V_{REF}) being greater than the value of the fourth threshold voltage, and the difference between the third potential (V_{NEG}) and the reference potential (V_{REF}) being less than the value of the third threshold voltage,

the first switch (20) being adapted to be controlled by a potential received on the first control input and a potential received on the second control input, in a manner that controls the conversion of the first potential (V_{BAT}) into the second potential (V_{POS}) and into the third potential (V_{NEG}), the second terminal being coupled to a node of the circuit at the third potential (V_{NEG}) when the circuit is in operation,

the second switch (100) being adapted to be controlled by a potential received on the third control input and a potential received on the fourth control input, in a manner that controls the conversion of the first potential (V_{BAT}) into the second potential (V_{POS}) and into the third potential (V_{NEG}), the fourth terminal being coupled to a node of the circuit at the first potential (V_{BAT}) when the circuit is in operation,

the third switch (300) being adapted to be controlled by a potential received on the fifth control input, in a manner that controls the conversion of the first potential (V_{BAT}) into the second potential (V_{POS}) and into the third potential (V_{NEG}), the fifth terminal being coupled to a node of the circuit at the reference potential when the circuit is in operation,

the fourth switch (400) being adapted to be controlled by a potential received on the sixth control input, in a manner that controls the conversion of the first potential (V_{BAT}) into the second potential (V_{POS}) and into the third potential (V_{NEG}), the seventh terminal being coupled to a node of the circuit at the second potential (V_{POS}) when the circuit is in operation,

- Outputs for supplying the second potential (V_{POS}) and the third potential

(V_{NEG}), wherein, the reference potential is applied to the first control input of the first switch and/or a reference potential is applied to the third control input of the second switch.

3. The method of any one of claims 1 to 2, wherein generating the first control signal is further based on the negative output voltage and generating the second control signal is further based on the positive output voltage.
4. The method of any one of claims 1 to 3, wherein the first discharging phase comprises discharging the accumulated energy in both the positive output and the negative output sequentially, the discharging of the accumulated energy to the positive output being initiated before the discharging of the accumulated energy to the negative output.
5. The method of any one of claims 1 to 3, wherein the first discharging phase comprises discharging the accumulated energy in both the positive output and the negative output sequentially, the discharging of the accumulated energy to the positive output being initiated after the discharging of the accumulated energy to the negative output.
6. The method of any one of claims 1 to 5, further comprising:
 - generating a third control signal (DC_3) based on, at least, the first control signal and the second control signal;
 - initiating a second discharging phase ($DISCHG_{SIMUL}$) of discharging the energy accumulated in the SIBOBB to the positive output in a boost-type configuration of the SIBOBB and to the negative output in a buck-type or boost-type configuration of the SIBOBB simultaneously, based on a monitoring of the first control signal, the second control signal and the third control signal simultaneously, during which second discharging phase, an amount of energy to be discharged by the SIBOBB is controlled by a second duty cycle of the second control signal and a third duty cycle of the third control signal; and, wherein, the charging phase is initiated before the second discharging phase.
7. The method of claim 6, wherein the second discharging phase comprises discharging the accumulated energy in both the positive output and the negative output simultaneously, and wherein initiating the second discharging phase is performed before the first discharging phase.

8. The method of claim 6, wherein the second discharging phase comprises discharging the accumulated energy in both the positive output and the negative output simultaneously, and wherein initiating the second discharging phase is performed after the first discharging phase.
9. The method of any one of claims 1 to 8, wherein the first, second and third control signals (DC_1 , DC_2 , DC_3) are generated by a Pulse Width Modulation, PWM, modulator (202, 204, 213) based on respective comparison signals, wherein at least some of the comparison signals are saw-tooth signals or triangular signals.
10. The method of claim 9, wherein generating the first control signal is performed by inputting into the PWM modulator (202), the first comparison signal and a first error signal (ERR_1) proportional to the voltage difference between the positive output voltage and the positive reference voltage.
11. The method of any one of claims 9 to 10, wherein generating the second control signal is performed by inputting into the PWM modulator (204), the second comparison signal and a second error signal (ERR_2) proportional to the voltage difference between the negative output voltage and the negative reference voltage.
12. The method of claim 9, wherein generating the first control signal is performed by inputting into the PWM modulator (202), the first comparison signal and a first error signal (ERR_1) corresponding to a voltage difference between a sum reference voltage (V_{REF1}) and a voltage sum of positive output voltage and negative output voltage.
13. The method of any of one of claims 9 and 12, wherein generating the second control signal is performed by inputting into the PWM modulator (204), the second comparison signal and a second error signal (ERR_2) corresponding to a voltage difference between a difference reference voltage (V_{REF2}) and a voltage difference between positive output voltage and the negative output voltage.
14. The method of any of one of claims 9 and 12 to 13, wherein generating the third control signal is performed by inputting into the PWM modulator (213), a third error signal (ERR_3) corresponding to a voltage difference between the first error signal (ERR_1) and the second error signal (ERR_2).

15. An apparatus for driving a Single Inductor Bipolar Output Buck-Boost (1000), SIBOBB, clocked by a clock signal having a given clock cycle period, the SIBOBB comprising an input for receiving a first potential (V_{BAT}) and at least four power switches (101, 102, 103, 104) and at least one positive output (110, 112) adapted to output a positive output voltage (V_{POS}) substantially higher than the first potential and at least one negative output (109, 111) adapted to output a negative output voltage (V_{NEG}), the apparatus comprising:
- means for generating a first control signal (DC_1) configured to be based on, at least, the negative output voltage and a negative reference voltage (V_{REF2});
 - means for generating a second control signal (DC_2) configured to be based on, at least, the positive output voltage and a positive reference voltage (V_{REF1});
 - means for initiating a charging phase (CHG) of the SIBOBB, configured to be based on a monitoring of the first control signal, during which an amount of energy to be accumulated by the SIBOBB is controlled by a first duty cycle of the first control signal;
 - means for initiating a first discharging phase ($DISCHG_{POS}$, $DISCHG_{NEG}$) of discharging the energy accumulated in the SIBOBB to at least one of the positive output in a boost-type configuration of the SIBOBB and the negative output in a buck-type or boost-type configuration of the SIBOBB, configured to be based on a simultaneous monitoring of the first control signal and the second control signal, during which first discharging phase, an amount of energy to be discharged by the SIBOBB is controlled by a second duty cycle of the second control signal; and,
- wherein, means for initiating the charging phase are activated before the activation of means for initiating the first discharging phase.
16. The apparatus of claim 15, wherein the SIBOBB is a power stage comprising:
- an electrical circuit, comprising:
 - at least a first control input (50), a second control input (60), a third control input (150), a fourth control input (160), a fifth control input (350), an sixth control input (450) and
 - at least a first switch (20) comprising a first terminal (30) and a second terminal (40), the first switch being adapted to be controlled:

- by setting the first control input (50) to a first electrical control voltage (T1), with the value (V1) of the first control voltage (T1) being less than that of the maximum value of the first potential (V_{BAT}) at the first terminal and greater than that of the value of a third potential (V_{NEG}) at the second terminal, and
 - to close the first switch (20), by setting the second control input (60) to the first control voltage (T1), or,
 - to open the first switch (20), by setting the second control input (60) to a second control voltage (T2) substantially equal to the third potential (V_{NEG}) of the second terminal,
 - at least a second switch (100) comprising a third terminal (130) and a fourth terminal (140), the second switch being adapted to be controlled:
 - by setting the third control input (150) to a third control voltage (T3), with the value (V3) of the third control voltage (T3) being less than a first minimum value of the first potential (V_{BAT}) at the fourth terminal and greater than the value of the third potential (V_{NEG}) at the third terminal, and
 - to close the second switch (100), by setting the fourth control input (160) to the third control voltage (T3), or
 - to open the second switch, by setting the fourth control input (160) to a fourth control voltage (T4) substantially equal to the maximum value of the of the first potential (V_{BAT}) of the fourth terminal (140),
 - at least a third switch (300), comprising a fifth terminal (330) and a sixth terminal (340), the third switch being adapted to be controlled:
 - to open the third switch, by setting the fifth control input (350) to the reference potential (V_{REF}), or
 - to close the third switch, by setting the fifth control input (350) to the first potential (V_{BAT}),
 - at least a fourth switch (400), comprising a seventh terminal (430) and a eighth terminal (440), the fourth switch being adapted to be controlled:
 - to close the fourth switch, by setting the sixth control input (450) to the reference potential (V_{REF}), or
 - to open the fourth switch, by setting the sixth control input (450) to the second potential (V_{POS});
- the difference between the first control voltage (T1) and the second control

voltage (T2) being greater than both the value of the threshold voltage of a first transistor and the value of the threshold voltage of a second transistor when the first switch is closed,

the difference between the third control voltage (T3) and the fourth control voltage (T4) being greater than both the value of the threshold voltage of a third transistor and the value of the threshold voltage of a fourth transistor when the second switch is closed,

the difference between a second potential (V_{POS}) and the reference potential (V_{REF}) being greater than the value of the fourth threshold voltage, and the difference between the third potential (V_{NEG}) and the reference potential (V_{REF}) being less than the value of the third threshold voltage,

the first switch (20) being adapted to be controlled by a potential received on the first control input and a potential received on the second control input, in a manner that controls the conversion of the first potential (V_{BAT}) into the second potential (V_{POS}) and into the third potential (V_{NEG}), the second terminal being coupled to a node of the circuit at the third potential (V_{NEG}) when the circuit is in operation,

the second switch (100) being adapted to be controlled by a potential received on the third control input and a potential received on the fourth control input, in a manner that controls the conversion of the first potential (V_{BAT}) into the second potential (V_{POS}) and into the third potential (V_{NEG}), the fourth terminal being coupled to a node of the circuit at the first potential (V_{BAT}) when the circuit is in operation,

the third switch (300) being adapted to be controlled by a potential received on the fifth control input, in a manner that controls the conversion of the first potential (V_{BAT}) into the second potential (V_{POS}) and into the third potential (V_{NEG}), the fifth terminal being coupled to a node of the circuit at the reference potential when the circuit is in operation,

the fourth switch (400) being adapted to be controlled by a potential received on the sixth control input, in a manner that controls the conversion of the first potential (V_{BAT}) into the second potential (V_{POS}) and into the third potential (V_{NEG}), the seventh terminal being coupled to a node of the circuit at the second potential (V_{POS}) when the circuit is in operation,

- Outputs for supplying the second potential (V_{POS}) and the third potential (V_{NEG}), wherein, the reference potential is applied to the first control input of the first switch and/or a reference potential is applied to the third control input of the second switch.
17. The apparatus of any one of claims 15 to 16, wherein means for generating the first control signal are further configured to be based on the positive output voltage and means for generating the second control signal are further configured to be based on the negative output voltage.
18. The apparatus of any one of claims 15 to 17, wherein the first discharging phase comprises discharging the accumulated energy in both the positive output and the negative output sequentially, the activation of the means for discharging the accumulated energy to the positive output being performed before the activation of the means for discharging the accumulated energy to the negative output.
19. The apparatus of any one of claims 15 to 17, wherein the first discharging phase comprises discharging the accumulated energy in both the positive output and the negative output sequentially, the activation of the means for discharging the accumulated energy to the positive output being performed after the activation of the means for discharging the accumulated energy to the negative output.
20. The apparatus any one of claims 15 to 19, further comprising:
- means for generating a third control signal (DC_3) configured to be based on, at least, the first control signal and the second control signal;
 - means for initiating a second discharging phase ($DISCHG_{SIMUL}$) of discharging the energy accumulated in the SIBOBB to the positive output in a boost-type configuration of the SIBOBB and to the negative output in a buck-type or boost-type configuration of the SIBOBB simultaneously, configured to be based on a simultaneous monitoring of the first control signal, the second control signal and the third control signal, during which second discharging phase, an amount of energy to be discharged by the SIBOBB is controlled by a second duty cycle of the second control signal and a third duty cycle of the third control signal; and,

wherein, means for initiating the charging phase are activated before the activation of means for initiating the second discharging phase

21. The apparatus of claim 20, wherein the second discharging phase comprises discharging the accumulated energy in both the positive output and the negative output simultaneously, and wherein the activation of means for initiating the second discharging phase is performed before the activation of means for initiating the first discharging phase.
22. The apparatus of claim 20, wherein the second discharging phase comprises discharging the accumulated energy in both the positive output and the negative output simultaneously, and wherein the activation of means for initiating the second discharging phase is performed after the activation of means for initiating the first discharging phase.
23. The apparatus of any one of claims 15 to 22, wherein the first, second and third control signals (DC_1 , DC_2 , DC_3) are generated by a Pulse Width Modulation, PWM, modulator (202, 204, 213) based on respective comparison signals, wherein at least some of the comparison signals are saw-tooth signals or triangular signals.
24. A display integrated circuit comprising:
 - a display panel (600);
 - a Single Inductor Bipolar Output Buck-Boost converter, SIBOBB, (1000);
 - a processor (4000); and,
 - an apparatus as defined in any one of claims 15 to 23, wherein the display panel and the apparatus are controlled by the processor, the display panel is powered by the SIBOBB and the SIBOBB is controlled by the apparatus.
25. A wireless device comprising the display integrated circuit as defined in claim 24.

FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7A




FIG. 7B




FIG. 7C




FIG. 7D




FIG. 8




FIG. 9





FIG. 10

600

DC_1	DC_2	Phase
0	0	CHG
0	1	CHG
1	0	DISCHG _{POS}
1	1	DISCHG _{NEG}






**FIG. 13**

FIG. 14



INTERNATIONAL SEARCH REPORT

International application No
PCT/EP2013/071023

A. CLASSIFICATION OF SUBJECT MATTER INV. H02M3/158 ADD.		
According to International Patent Classification (IPC) or to both national classification and IPC		
B. FIELDS SEARCHED		
Minimum documentation searched (classification system followed by classification symbols) H02M		
Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched		
Electronic data base consulted during the international search (name of data base and, where practicable, search terms used) EPO-Internal, PAJ, WPI Data		
C. DOCUMENTS CONSIDERED TO BE RELEVANT		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X Y A A	US 2010/039080 A1 (SCHOENBAUER STEVE [US] ET AL) 18 February 2010 (2010-02-18) abstract; figures 1-5 paragraphs [0006] - [0008], [0014], [0015], [0017] - [0022] ----- US 2012/032664 A1 (COLEMAN CHARLES [US] ET AL) 9 February 2012 (2012-02-09) figures 2-9 paragraphs [0005], [0028] - [0032], [0038] - [0041] ----- US 2008/315850 A1 (NISHIDA JUNJI [JP]) 25 December 2008 (2008-12-25) figures 3,4,6 paragraphs [0005], [0015], [0016], [0026] - [0062], [0069] ----- -/-	1,3-15, 17-25 2,16 1,4,15, 18 1,3,5-9, 12-15, 17,19-25
☒ Further documents are listed in the continuation of Box C. ☒ See patent family annex.		
* Special categories of cited documents : "A" document defining the general state of the art which is not considered to be of particular relevance "E" earlier application or patent but published on or after the international filing date "L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified) "O" document referring to an oral disclosure, use, exhibition or other means "P" document published prior to the international filing date but later than the priority date claimed "T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention "X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone "Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art "&" document member of the same patent family		
Date of the actual completion of the international search 4 November 2013		Date of mailing of the international search report 13/11/2013
Name and mailing address of the ISA/ European Patent Office, P.B. 5818 Patentlaan 2 NL - 2280 HV Rijswijk Tel. (+31-70) 340-2040, Fax: (+31-70) 340-3016		Authorized officer Kail, Maximilian

INTERNATIONAL SEARCH REPORT

International application No

PCT/EP2013/071023

C(Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y	WO 2012/032176 A1 (ST ERICSSON SA [CH]; BRANCA XAVIER [FR]; CHESNEAU DAVID [FR]) 15 March 2012 (2012-03-15) cited in the application figures 1-6 pages 2,3,8 pages 16,17 claims 1-9	2,16
A	----- US 2012/235976 A1 (VAN LIER WILHELMUS JOHANNES ROBERTUS [US]) 20 September 2012 (2012-09-20) figures 10-18 paragraphs [0003], [0043], [0099] - [0110], [0124] - [0127] -----	1-25

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/EP2013/071023

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 2010039080 A1	18-02-2010	JP 2010045966 A US 2010039080 A1	25-02-2010 18-02-2010
US 2012032664 A1	09-02-2012	US 2012032664 A1 US 2012032708 A1 US 2012032728 A1	09-02-2012 09-02-2012 09-02-2012
US 2008315850 A1	25-12-2008	CN 101330253 A JP 5151266 B2 JP 2009005442 A US 2008315850 A1	24-12-2008 27-02-2013 08-01-2009 25-12-2008
WO 2012032176 A1	15-03-2012	CN 103098375 A EP 2614588 A1 WO 2012032176 A1	08-05-2013 17-07-2013 15-03-2012
US 2012235976 A1	20-09-2012	TW 201243812 A US 2012235976 A1 WO 2012128937 A1	01-11-2012 20-09-2012 27-09-2012