



(19) **United States**

(12) **Patent Application Publication**
Kikuchi et al.

(10) **Pub. No.: US 2006/0218473 A1**

(43) **Pub. Date: Sep. 28, 2006**

(54) **CODING APPARATUS AND DECODING APPARATUS FOR TRANSMISSION/STORAGE OF INFORMATION**

now Pat. No. 6,249,895, which is a division of application No. 08/720,067, filed on Sep. 27, 1996, now Pat. No. 5,862,153.

(75) Inventors: **Yoshihiro Kikuchi**, Yokohama-shi (JP); **Toshiaki Watanabe**, Yokohama-shi (JP); **Kenshi Dachiku**, Kawasaki-shi (JP); **Takeshi Chujoh**, Shibuya-Ku (JP); **Takeshi Nagai**, Higashi-Murayama-Shi (JP)

(30) **Foreign Application Priority Data**

Sep. 29, 1995 (JP)..... 276993/1995

Publication Classification

(51) **Int. Cl.**
H03M 13/00 (2006.01)
(52) **U.S. Cl.** **714/776**

Correspondence Address:
FINNEGAN, HENDERSON, FARABOW, GARRETT & DUNNER LLP
901 NEW YORK AVENUE, NW
WASHINGTON, DC 20001-4413 (US)

(57) **ABSTRACT**

An output coding apparatus includes a coder for coding an inputted bitstream to an error correction and/or detection code composed of information bits and check bits; and a bitstream assembling section for assembling an outputted bitstream by inserting a synchronization code at any one of a plurality of synchronization code insertion positions previously determined in the outputted bitstream, arranging the information bits at any desired positions of the bitstream, and by arranging the check bits at positions other than the synchronization code insertion positions in the bitstream. Therefore, when the coding apparatus is combined with a resynchronization method using both an error correction and/or detection code and a synchronization code, it is possible to solve a problem caused by pseudo-synchronization or synchronization-loss pull-out or step-out due to erroneous detection of the synchronization code.


(73) Assignee: **Kabushiki Kaisha Toshiba**, Kawasaki-shi (JP)

(21) Appl. No.: **11/418,202**

(22) Filed: **May 5, 2006**

Related U.S. Application Data

(60) Continuation of application No. 10/279,109, filed on Oct. 24, 2002, now Pat. No. 7,093,170, which is a division of application No. 09/580,430, filed on May 30, 2000, now Pat. No. 6,493,838, which is a division of application No. 09/148,164, filed on Sep. 4, 1998,






FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11

**CODING APPARATUS AND DECODING
APPARATUS FOR TRANSMISSION/STORAGE OF
INFORMATION**

BACKGROUND OF THE INVENTION

[0001] The present invention relates to a system for transmitting and/or storing information through a medium of high error rate such as radio transmission path, and more specifically to a coding and/or decoding apparatus for coding a bitstream obtained by a high efficiency compression coding to an error correction and/or detection code and for transmitting and/or storing the coded bitstream.

[0002] In a system for transmitting audio and/or video signals via radio transmission path after the signals have been compression-coded at a high efficiency to reduce the signal quantity as small as possible, for instance as with the case of radio TV telephone, portable information terminal, digital TV broadcasting system, etc., since the error rate of the transmission path is relatively high, it is important to transmit the obtained bitstream in as high a quality as possible.

[0003] When the bitstream is transmitted and/or stored via a medium of high error rate as described above, an error correction code such as BCH code, RS code, convolution code, etc. has been so far widely adopted as means for reducing the error rate. On the other hand, as means for detecting an error on the reception side, an error detecting code such as check sum, CRC, etc. are used. In these error correction and/or error detection methods, error is corrected and/or detected by adding excessive (redundant) bits to information to be transmitted and/or stored in accordance with a prescribed rule and further by checking whether the transmitted and/or stored bitstream abides by the same rule when decoded.

[0004] However, in the above-mentioned method such that the bitstream obtained by high efficiency compression coding is further coded to an error correction and/or detection code and then transmitted and/or stored, there exists a problem in that it is difficult to combine this method with a resynchronization method for recovering a synchronization when synchronization-loss occurred due to an erroneous bitstream word caused by the transmission and/or storage medium. Here, as the above-mentioned synchronization restoring method, there has been widely used such a method of inserting a unique word (referred to as synchronization code or start-code) decodable uniquely (unconditionally) and of resuming decoding operation, in case of synchronization-loss, from a time point when the synchronization code is detected again.

[0005] In order to form the synchronization code as a code word decodable unequivocally, it is necessary to construct the code word in combination with another code word in such a way that a bit pattern the same as that of the synchronization code will not appear. In the case of the general error correction and/or detection coding method, however, it is difficult to construct the code word in such a way that a specific bit pattern will not appear. On the other hand, when the bit pattern the same as the synchronization code appear, pseudo-synchronization may occur due to an erroneous detection of the synchronization code.

[0006] To overcome this problem, conventionally, the following method has been so far used: after the error

correction and/or detection coding has been executed, the presence of the bit pattern the same as that of the synchronization code is checked in the bitstream; when the same bit pattern exists, stuffing bits are inserted into the pattern in accordance with a prescribed rule; and the inserted stuffing bits are removed in accordance with the same prescribed rule by the decoding apparatus in order to prevent the pseudo-synchronization. In this method, however, when the bitstream having an error is transmitted and/or stored, since there exists a possibility that the stuffing bits are also inserted erroneously, there still exists another problem in that an additional synchronization-loss or pseudo-synchronization may occur.

[0007] Further, when the bitstream is coded for error correction and/or detection and further the synchronization code is inserted, in the conventional method, since many insertion bits must be added to the bitstream at the last portion of a synchronization block sandwiched between two synchronization codes in order to compensate for a remainder of the information bits to be coded for error correction and/or detection, there arises another problem in that the coding efficiency is lowered.

[0008] On the other hand, in order to increase the error correction and/or detection capability, although it may be considered to increase the redundancy of the information to be transmitted and/or stored, in this case, however, the number of necessary bits increases when the same quantity of the information is transmitted. Therefore, when the error correction and/or detection capability is simply increased, there arises another problem in that a transmission path of higher transmission rate is required or that the number of bits of information to be stored is increased. Further, when the transmission rate or the storage capacity is the same, the quantity of information to be transmitted and/or stored decreases with increasing redundancy. As a result, in the case where audio and video information are compression-coded at a high efficiency and then transmitted and/or stored, if the redundancy is simply increased to increase the error resistance, as far as the transmission and/or storage rate is the same, since the information must be compression-coded down to a lesser information quantity, there causes another problem in that the audio quality and picture quality both deteriorate.

[0009] To overcome the above-mentioned problems, as the method of obtaining a high error resistance in spite of a lesser redundancy, there exists a method referred to as hierarchical coding. In this method, the audio or picture information compression-coded at a high efficiency is classified according to the degree of error which deteriorates the audio quality or the picture quality; the error correction and/or detection code of a high redundancy and thereby a high error correction and/or detection capability is adopted for the information with more importance and a large error influence; and the error correction and/or detection coding of a low redundancy and thereby a low error correction and/or detection capability is adopted for the information with less importance and a small error influence. In this method, it is possible to increase the error resistance in spite of a relatively small averaged redundancy, as compared with when a correction and/or detection code is used uniformly for all the information in the same redundancy.

[0010] For instance, in the case of the coding method such that motion compensation prediction and the orthogonal

transform are combined with each other (which is widely adopted for compression-coding moving picture information at high efficiency); that is, in the case of the coding method such that the motion compensation prediction is executed for the inputted moving picture video signals, and the predicted residual is orthogonal-transformed (e.g., discrete cosine transform (DCT)), the error correction and/or detection code of strong error correction and/or detection capability is used for the motion vector information or low-order coefficients of the orthogonal transform coefficients of the prediction residual signals (because these information deteriorates picture quality largely in case an error occurs); and the error correction and/or detection code of weak error correction and/or detection capability is used for high-order coefficients of the orthogonal transform coefficients of the prediction residual signals (because these information exerts a relatively small influence upon the picture quality).

[0011] To realize the above-mentioned hierarchical coding, it is necessary to switch the error correction and/or detection codes of different error correction and/or detection capabilities midway in the outputted bitstream. As the method of switching the error correction and/or detection codings of different error correction and/or detection capabilities, there exists such a method that header information indicative of the sort of the error correction and/or detection code is added to the bitstream. **FIG. 1** shows an example of a bitstream in which the error correction and/or detection codes are switched by adding header information. In more detail, in this example, two sorts of the error correction and/or detection codes FEC1 and FEC2 are switched. In each of the headers **1101** to **1104**, header information indicative of the sort of the error correction and/or detection code and a number of code word is inserted. Therefore, the coding apparatus arranges the code word coded for error correction and/or detection after each header information, and the decoding apparatus decodes the header information; and the decoding apparatus decodes the header information and after that the error correction and/or detection code in accordance with the decoded header information.

[0012] However, in the above-mentioned method of switching the error correction and/or detection codes by adding the header information, however, there arises a problem in that the number of bits of the bitstream to be transmitted and/or stored increases due to the addition of the header information. In the case where audio or video signals are compression-coded, since some bits are used for the header information, the number of bits used for the compression-coding audio or video signals is inevitably reduced, with the result that the audio quality and/or the picture quality inevitably deteriorates.

[0013] As described above, when the error correction and/or detection coding is executed for a bitstream obtained by compression-coding moving picture signals, since any bit pattern is generated, in the case where the error correction and/or detection coding is combined with the synchronization method using the unique word as synchronization code, there exists a pseudo-synchronization due to erroneous detection of the synchronization code. Further, when the stuffing bits are inserted to prevent the pseudo-synchronization, there arises another problem in that the synchronization-loss and the pseudo-synchronization occur due to erroneous insertion of the stuffing bits.

[0014] Further, when the bitstream is coded for error correction and/or detection and further the synchronization code is inserted, in the conventional method, since a relatively large number of bits must be inserted to compensate for the remainder of the information bits to be coded for error correction and/or detection at the last portion of the synchronization block, there arises a problem in that the coding efficiency deteriorates.

[0015] Further, in the case of the coding and/or decoding apparatus in which the error correction and/or detection codes of different error correction and/or detection capabilities are switched by adding header information, since the number of bits to be transmitted and/or stored increases due to the addition of the header information, when audio or video signals are compression-coded at a high efficiency and then transmitted and/or stored, the information quantity used for audio or video information inevitably decreases, with the result there exists a problem in that the audio quality and the video quality both deteriorate.

SUMMARY OF THE INVENTION

[0016] With these problems in mind, therefore, it is the first object of the present invention to provide a coding and/or decoding apparatus, which can solve such a problem as pseudo-synchronization or synchronization-loss due to erroneous detection of the synchronization code, when combined with the resynchronization method which uses both the error correction and/or detection code and the synchronization code.

[0017] Further, the second object of the present invention is to provide a coding and/or decoding apparatus, which can increase the coding efficiency by reducing the number of bits inserted at the last portion of the synchronization block, when combined with the resynchronization method which uses both the error correction and/or detection code and the synchronization code.

[0018] Further, the third object of the present invention is to provide a coding and/or decoding apparatus, which can improve the information quality by reducing the number of bits of the bitstream to be transmitted and/or stored, without adding header information indicative of the sort of the error correction and/or detection code, in the case when bitstream obtained by compression-coding audio and video signals are coded by switching a plurality of sorts of error correction and/or detection codes and then transmitted and/or stored.

[0019] To achieve the above-mentioned object, the first aspect of the coding apparatus according to the present invention provides a coding apparatus, comprising: coding means for coding an inputted bitstream to an error correction and/or detection code composed of information bits and check bits; and bitstream assembling means for assembling an outputted bitstream by inserting a synchronization code at any one of a plurality of synchronization code insertion positions previously determined in the outputted bitstream, arranging the information bits at any desired positions of the bitstream, and by arranging the check bits at positions other than the synchronization code insertion positions in the bitstream.

[0020] Further, the first aspect of the present invention provides a decoding apparatus, comprising: synchronization code detecting means for detecting a synchronization code

from a bitstream coded to an error correction and/or detection code composed of information bits and check bits, at each of a plurality of previously determined synchronization code insertion positions thereof; bitstream disassembling means for disassembling the bitstream to extract the information bits of the error correction and/or detection code and the check bits of the error correction and/or detection code arranged at positions other than the synchronization code insertion positions; and decoding means for decoding the error correction and/or detection code on the basis of the information bits and the check bits extracted by said code disassembling means.

[0021] In the first aspect of the present invention, since the synchronization code is arranged at each of a plurality of predetermined synchronization code insertion positions in the output bitstream and further since the check bits of the error correction and/or detection code are arranged at positions other than the synchronization code insertion positions, even if the bit pattern the same as that of the synchronization code is included in the check bits, there exists no possibility that the synchronization code is detected erroneously. Therefore, it is unnecessary to use a specific error correction and/or detection code to prevent a specific bit pattern from being formed or to insert bits to protect the synchronization pattern after having been coded to the error correction and/or detection code. As a result, it is possible to increase not only the degree of freedom of selection of the usable error correction and/or detection codes but also to improve the resistance against error, because there exists no possibility that the new erroneous synchronization detection occurs due to mixture of the erroneous insertion bit.

[0022] Further, the second aspect of the present invention provides a coding apparatus, comprising: bitstream converting means for converting an inputted bitstream other than a synchronization code arranged at each of a plurality of synchronization code insertion positions previously determined in an outputted bitstream, in such a way that a Hamming distance from the synchronization code exceeds a predetermined value; coding means for coding the bitstream converted by said bitstream converting means to an error correction and/or detection code composed of information bits and check bits; and bitstream assembling means for assembling an outputted bitstream by inserting a synchronization code at any one of a plurality of the synchronization code insertion positions previously determined in the outputted bitstream, arranging the information bits at any desired positions of the bitstream, and by arranging the check bits at positions other than the synchronization code insertion positions in the bitstream.

[0023] Further, the second aspect of the present invention provides a decoding apparatus, comprising: synchronization code detecting means for detecting a synchronization code at each of previously determined synchronization code insertion positions, from a bitstream coded to an error correction and/or detection code composed of information bits and check bits and further including the inserted synchronization codes; bitstream disassembling means for disassembling the bitstream, to extract the information bits of the error correction and/or detection code and the check bits of the error correction and/or detection code arranged at positions other than the synchronization code insertion positions; decoding means for decoding the error correction and/or detection code on the basis of the information bits and the check bits

extracted by said code disassembling means; and bitstream converting means for converting the bitstream other than the synchronization code arranged at each of the synchronization code insertion positions, which is decoded by said decoding means and further converted in such a way that a Hamming distance from the synchronization code in the bitstream exceeds a predetermined value, to the original bitstream.

[0024] In the second aspect of the present invention, since the bit train arranged at the synchronization code insertion position is converted in such a way that the Hamming distance from the synchronization code exceeds a predetermined value and further since the bit train is reversely converted by the decoding processing, the bit pattern the same as that of the synchronization code will not be included in the bit train, so that it is possible to prevent the erroneous detection of the synchronization code. Further, when the bit train is converted in such a way that the Hamming distance between the synchronization code and the bitstream other than the synchronization code exceeds a predetermined value, even if an error is mixed with the bitstream, since the synchronization code can be discriminated from the bitstream other than the synchronization code, it is possible to reduce the possibility that the synchronization code is detected erroneously.

[0025] Further, since the above-mentioned conversion and/or reverse conversion processing is executed at the synchronization code insertion positions, it is possible to reduce the overhead, as compared with the prior art method such that the conversion and/or reverse conversion processing is executed all over the bitstream. In addition, in the case of the bitstream inputted to the coding apparatus, it is unnecessary to execute the conversion processing or to use a special code word, so that the bit pattern the same as that of the synchronization code can be prevented from being formed. In particular, in the case where a variable code length coding apparatus in which different code word tables are switched in use is connected to the input side of the coding apparatus according to the present invention, when the code word table is formed in such a way that the bit pattern the same as that of the synchronization code will not be formed by the variable length coding apparatus, there exists a problem in that the coding efficiency is inevitably reduced. In the present invention, however, since the coding apparatus and/or decoding apparatus as described above is used, it is possible to eliminate this problem.

[0026] Further, the third aspect of the present invention provides a coding apparatus, comprising: coding means for coding an inputted bitstream to an error correction and/or detection code; synchronization code inserting means for inserting synchronization codes into the inputted bitstream; deciding means for deciding the number of information bits to be coded to the error correction and/or detection code and arranged immediately before the synchronization code of the bitstream; and said coding means forming the error correction and/or detection code arranged immediately before the synchronization code as a degenerative code adaptively degenerated on the basis of the number of bits decided by said deciding means.

[0027] Further, the third aspect of the present invention provides a decoding apparatus, comprising: decoding means for decoding a bitstream coded to an error correction and/or

detection code and further including inserted synchronization codes; synchronization code detecting means for detecting the synchronization codes arranged in the bitstream; deciding means for deciding the number of information bits coded to the error correction and/or detection code and arranged immediately before the synchronization code detected by said synchronization code detecting means; and said decoding means decoding the bitstream by deciding whether the error correction and/or detection code arranged immediately before the synchronization code is a degenerative code or not on the basis of the number of the information bits decided by said deciding means.

[0028] In the third aspect of the present invention, since a degenerative code (whose number of bits is degenerated to a small number of bits required to code the information bits remaining at the last portion of the one synchronization period (block) is used for the error correction and/or detection code arranged immediately before the synchronization code, it is unnecessary to use many insertion bits to fill the remainder of the information bits at the last portion of the synchronization block, with the result that the coding efficiency can be increased.

[0029] Further, the fourth aspect of the present invention provides a coding apparatus, comprising: coding means for coding an inputted bitstream including a plurality of sorts of information to different error correction and/or detection codes; and switching means for switching the sorts of the error correction and/or detection codes according to the sort of the information included in the bitstream.

[0030] Further, the fourth aspect of the present invention provides a decoding apparatus, comprising: decoding means for decoding a bitstream coded to error correction and/or detection codes of different sorts according to information sort, to form original information; and means for deciding the sort of the error correction and/or detection code on the basis of the information sort formed by said decoding means, the decided sort being transmitted to said decoding means.

[0031] In the fourth aspect of the present invention, when the coding and/or decoding is executed by switching the error correction and/or detection codes according to the sort thereof, since the error correction and/or detection code is switched on the coding apparatus side according to the sort of information of the bitstream inputted to the coding apparatus, and since the error correction and/or detection code is switched on the decoding apparatus side by deciding the sort of the error correction and/or detection code on the basis of the decoded information (i.e., the same code as that used on the coding side), any header information indicative of the sort of the error correction and/or detection code is not required (being different from the prior art method), so that it is possible to eliminate the overhead due to the header information.

BRIEF DESCRIPTION OF THE DRAWINGS

[0032] FIG. 1 is an illustration showing an example of a bitstream obtained by the prior art error correction and/or detection code switch coding apparatus.

[0033] FIG. 2 is a block diagram showing an embodiment of the moving picture compression coding apparatus according to the present invention;

[0034] FIG. 3 is a diagram for assistance in explaining the multiplexing syntax adopted by a multiplexer of the moving picture compression coding apparatus shown in FIG. 2;

[0035] FIG. 4 is a block diagram showing an output coding apparatus of the moving picture compression coding apparatus shown in FIG. 2;

[0036] FIG. 5 is an illustration showing an example of an outputted bitstream outputted by the moving picture compression coding apparatus shown in FIG. 2;

[0037] FIG. 6 is an illustration showing an example of a synchronization code;

[0038] FIG. 7 is a block diagram showing the error correction and/or detection switching coder of the output coding apparatus shown in FIG. 4;

[0039] FIG. 8 is a block diagram showing the bitstream assembler of the output coding apparatus shown in FIG. 4;

[0040] FIG. 9 is a block diagram showing an embodiment of the moving picture compression decoding apparatus according to the present invention;

[0041] FIG. 10 is a block diagram showing an input decoding apparatus of the moving picture compression decoding apparatus shown in FIG. 9; and

[0042] FIG. 11 is a block diagram showing a bitstream disassembler of the input decoding apparatus shown in FIG. 10.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0043] Embodiments of the present invention will be described hereinbelow with reference to the attached drawings.

[0044] FIG. 2 is a block diagram showing an embodiment of the moving picture coding apparatus provided with an error correction and/or detection switching function according to the present invention, which is combined with a compression coding apparatus using motion compensation adaptive prediction and discrete cosine transform coding (one of orthogonal transform codings). Here, the coding method in which both the motion compensation adaptive prediction and discrete cosine transform coding are combined with each other is disclosed in detail by Document: by Hiroshi YASUDA, "International Standard of Multimedia Coding", published by Maruzen, June 1991, for instance. Therefore, only the operation thereof will be briefly explained hereinbelow. Further, as the error correction and/or detection code used in this embodiment, such a code as the BCH code in which the information bits are separated from the check bits is assumed to be used.

[0045] In FIG. 2, moving picture signals 131 to be coded are inputted in unit of frame. The inputted moving picture signals 131 are processed for motion compensation adaptive prediction in unit of small region (e.g., macro block). In more detail, a motion vector between inputted moving picture signals 131 and video signals already coded and locally decoded and further stored in a frame memory is detected by a motion compensation adaptive predictor 101. Further, predicted signals 132 are formed by compensation prediction on the basis of the detected motion vector. In this motion compensation predictor 101, a preferable prediction

mode to be used for coding is selected from both the motion compensation prediction coding and the intra-frame coding (the inputted moving picture signal **131** is coded as it is without forming any prediction signal), and the prediction signals corresponding to the selected mode are outputted.

[0046] The outputted prediction signals are inputted to a subtracter **103**, and prediction residual signals **133** obtained by subtracting the prediction signals **132** from the inputted moving picture signals **131** are outputted. The outputted prediction residual signals **133** are discrete-cosine transformed (DCTed) in unit of constant size block by a discrete cosine transform section **104**, so that DCT coefficients can be formed. The formed DCT coefficients are quantized by a quantizer **105**. The DCT coefficient signals quantized by the quantizer **105** are branched into two. One is variable-length coded by a first variable length coder **106**. Further, the other is dequantized by a dequantizer **107**, and further reversely discrete-cosine transformed by an inverse discrete cosine transform section **108**. The output of the inverse discrete cosine transform section **108** is added to a prediction signal **132** by an adder **109** to form local decoded signals. The formed local decoded signals are stored in a frame memory **102**.

[0047] On the other hand, the prediction mode and the motion vector information decided by the motion compensation adaptive predictor **101** are variable-length coded by a second variable length coder **110**. The variable length codes outputted by the first and the second variable length coders **106** and **110** are multiplexed by a multiplexer **111**.

[0048] From the multiplexer **111**, a bitstream **201** of the multiplexed variable length codes, an FEC sort ID (identification) signal **202** indicative of a sort of the corresponding error correction and/or detection code, and a synchronization code insertion request signal **203** for requesting an insertion of a synchronization code is outputted.

[0049] These signals of the bitstream **202**, the FEC sort ID signal **202**, and the synchronization code insertion request signal **203** are inputted to an output coding apparatus **200**. The output coding apparatus **200** codes the bitstream **201** by switching a plurality of error correction and/or detection codes of different sorts, to form a final output bitstream **205**. Here, the output coding apparatus **200** corresponds to the coding apparatus according to the present invention.

[0050] FIG. 3 shows a flow of signals multiplexed by the multiplexer **111**. Here, the multiplexing is executed in unit frame to be coded. First, the picture synchronization code **301** is multiplexed. When the picture synchronization code **301** is multiplexed, the synchronization code insertion request signal **203** is outputted from the multiplexer **111** to the coding apparatus **200**, so that the coding apparatus **200** can know that the multiplexed code word is a synchronization code. Successively, a picture header **302** indicative of one of various coding modes of the coded frame is multiplexed upon the bitstream **201**. Further, prediction mode information **303** indicative of the prediction mode of the motion compensation adaptive predictor MC at each region is multiplexed. Further, motion vector information **304** and the DCT coefficients (referred to as residual DCT coefficients) **305** of the prediction residual signals are multiplexed. Here, when the picture header **302**, the prediction mode information **303**, the motion vector information **304**, and the residual DCT coefficients **305** are multiplexed, the

FEC sort ID signal **202** indicative of the sort of the error correction and/or detection code is outputted in correspondence to each of the multiplexed signals.

[0051] Here, an error correction and/or detection code of high correction and/or detection capability is used for the picture header **302**, the prediction mode information **303** and the motion vector information **303**, because these information deteriorate picture quality largely when an error is mixed therewith. On the other hand, in the case of the residual DCT coefficients **305**, even if error is mixed therewith, since the picture quality can be prevented from being deteriorated largely by detecting the error and by setting the residual to zero, an error correction and/or detection code of high correction and/or detection capability is not used; that is, it is sufficient to detect only an error of the residual DCT coefficients **305**.

[0052] FIG. 4 is a block diagram showing the output coding apparatus **200** shown in FIG. 2. The output coding apparatus **200** is composed of a bit inserter **211**, an error correction and/or detection switching coder **212**, and a bitstream assembler **213**. Further, FIG. 5 shows an example of the output bitstream **205** formed by the output coding apparatus **200**. The bitstream **205** is composed of a picture synchronization code PSC, a picture header PH, prediction mode information MODE, motion vectors MV, error correction and/or detection code check bits CHK, residual DCT coefficients COEF, and stuffing (insertion) bits STUFF. The output bitstream **205** has the following features:

[0053] (1) The picture synchronization code PSC is inserted into any one of the synchronization code insertion positions as shown by arrows and arranged at constant intervals (for each sync_period bits). The length of the sync_period is determined larger than the maximum length of the synchronization code PSC and the maximum length of the check bit CHK. Further, the check bits CHK are arranged each being shifted so as to be arranged immediately before the synchronization code insertion position.

[0054] (2) The error correction and/or detection code arranged at the last portion of one frame (i.e., at the last portion of one synchronization period sandwiched between the two synchronization codes PSC) is a punctured code such that only the finally remaining information bits are coded. Further, in order to shift the position of the check bit CHK (e.g., the check bit CHK6 in the example shown in FIG. 5,) a necessary number of the stuffing bites STUFF are inserted.

[0055] (3) The FEC sort ID signal indicative of the sort and the number of the error correction and/or detection codes is not arranged in the output bitstream **205** shown in FIG. 5.

[0056] In the output bitstream **205** as shown in FIG. 5, since the positions of the check bits CHK are shifted as explained in item (1) above, the check bit CHK is not inserted at any of the synchronization code insertion positions shown by the arrows in FIG. 5, with the result that there exists no possibility that the pseudo-synchronization occurs by the check bits CHK. Further, in the case of the error correction and/or detection coding at the last of the frame, although many stuffing bits must be inserted at the last of the frame in the prior art method, since the punctured code is used for the last of the frame as explained by item

(2) above, it is possible to reduce the number of the insertion (stuffing) bits. In addition, since the header information indicative of the sort and the number of error correction and/or detection code is not included in the output bitstream 205 as explained by item (3) above, it is possible to reduce the code quantity for the header information.

[0057] The construction and the operation of the output coding apparatus 200 (shown in FIG. 4) for forming the output bitstream 205 will be described in more detail here-inbelow in relation between the bitstream 201 shown in FIG. 3 outputted by the multiplexer 111 and the output bitstream 205 shown in FIG. 5.

[0058] When the synchronization code 301 is multiplexed by the multiplexer 111, the synchronization code insertion request signal 203 is outputted as already explained. Here, the synchronization code 301 is composed of sync_0_len bits of "0", one bit of "1", and sync_nb_len bits of "xxxxx" indicative of the sort of the synchronization code 301, as shown in FIG. 6. In response to the synchronization code 301 and the synchronization code insertion request signal 203 outputted by the multiplexer 111, the output coding apparatus 200 outputs the synchronization code (PSC) of the output bitstream 205 from the bitstream assembler 213.

[0059] Here, as shown in FIG. 5, since the synchronization code 301 (PSC) can be inserted at only the synchronization code insertion positions arranged at sync_period intervals of the output bitstream 205, when the last position of the output bitstream 205 already formed is not arranged at the synchronization code insertion position, the stuffing bits STUFF (as described later) are inserted in such a way that the synchronization code 301 can be arranged at the synchronization code insertion position.

[0060] After the synchronization code 301 has been outputted to the output bitstream 205, the picture header 302, the prediction mode information 303, the motion vector information 304, and the residual DCT coefficients 305 are coded as follows: First, bits are inserted into the bitstream 201 outputted by the multiplexer 111 by the bit inserter 211 in order to prevent the generation of the pseudo-synchronization. In other words, when a bit pattern the same as that of the code word of the synchronization code 301 exists in the output bitstream 205, since the synchronization code 301 cannot be decoded unequivocally, bits are inserted according to the necessity. For instance, if the synchronization code 301 is a code word in which the sync_0_len bits of "0" are arranged continuously as shown in FIG. 6, it is possible to prevent the pseudo-synchronization by inserting "1" in such a way that "0" will not be continued beyond the sync_0_len bits in the bitstream, except at the synchronization code 301.

[0061] Here, since the synchronization code 301 is inserted at only the synchronization code insertion position as already explained, it is sufficient when the bit "1" is inserted at only the synchronization insertion positions, respectively for prevention of the pseudo-synchronization. Here, a count value 221 indicative of the total number of bits of the output bitstream 205 so far formed is outputted by the bitstream assembler 213, and further the bit inserter 211 decides as to whether further bit insertion is necessary or not on the basis of the count value 221 of the bit inserter 211. Here, when the count value 221, that is, the total bit number of the output bitstream 205 so far formed is denoted by

total_len, the number of "1" in the bitstream 201 is counted in a bit block (interval) of

$$0 < \text{total_len mod sync_period} \leq \text{sync_0_len}$$

[0062] where $A \bmod B$ denotes a remainder obtained when A is divided by B.

[0063] Here, if there exists no bit of "1" in this bit interval, one bit of "1" is inserted.

[0064] Further, in order to reduce the possibility that the synchronization code 301 is detected erroneously, bit are inserted as follows:

[0065] Here, in order to detect the synchronization code 301 even if an n-bit error is mixed with the synchronization code 301, it is necessary to decide the code word having a Hamming distance less than n from the true synchronization code, as the synchronization code, by use of an input decoding apparatus of the moving picture decoding apparatus (described later). In this case, however, if the above-mentioned decision is made by leaving the bitstream other than the synchronization code 301 as it is, since there exists the case where a bit pattern having a Hamming distance less than n exists in the bitstream other than the synchronization code 301, when existing at the synchronization code insertion position, this bit pattern is erroneously decided as the synchronization code 301.

[0066] To overcome this problem, the bit inserter 211 inserts bits into the bitstream 201 as follows: the bitstream other than the synchronization code arranged at each of the synchronization code insertion positions in the bitstream 201 is converted in such a way that the Hamming distance thereof from the synchronization code 301 becomes a value larger than $2^n + 1$. In more detail, the number (=n0) of "1" is counted in the bit block (interval) of

$$0 < \text{total_len mod sync_period} \leq \text{sync_0_len} - (2^n + 1)$$

[0067] Here, if n0 is less than $(2^n + 1)$, $\{(2^n + 1) - n0\}$ bits of "1" are inserted into the bitstream 201.

[0068] After the bits have been inserted by the bit inserter 211 as described above, the bitstream 222 is inputted to the error correction and/or detection code switching coder 212, together with the FEC sort ID signal 202 indicative of the sort of the error correction and/or detection code.

[0069] FIG. 7 is a block diagram showing the error correction and/or detection code switching coder 212 shown in FIG. 4. A latch circuit 603 is a circuit for latching the FEC sort ID signal 202, after the synchronization code has been outputted from the multiplexer 111 to the bitstream 201 and further the synchronization code insertion request signal 203 has been outputted. The latched signal 623 is supplied to an error correction and/or detection coder 604.

[0070] The error correction and/or detection coder 604 codes the bitstream 222 supplied by the bit inserter 211 for error correction and/or detection in accordance with the latched signal 623; that is, forms and outputs the information bits 631 and check bits 632, respectively. Further, after the error correction and/or detection coding for one block has been completed, the error correction and/or detection coder 604 outputs a latch command signal 625 for commanding the latch circuit 603 to latch the succeeding FEC sort ID signal 202. Therefore, on the basis of this latch command signal 625, the latch circuit 603 latches the succeeding FEC

sort ID signal 202 and supplies the latched signal to the error correction and/or detection coder 604 again.

[0071] By repeating the above-mentioned operation, the output coding apparatus 200 codes the bitstream 222 (to which bits have been already inserted by the bit inserter 211) for error correction and/or detection, by switching the error correction and/or detection codes by the error correction and/or detection switching coder 212 in accordance with the FEC sort ID signal 202 supplied by the multiplexer 111. Here, since the FEC sort ID signal 202 can be latched by the latch circuit 603 only when the error correction and/or detection coding of one block has been completed, the same error correction and/or detection code is kept applied until the FEC sort ID signal 202 is switched. For instance, in the case where the error correction and/or detection code of FEC1 is used for the picture header 302 and the code of FEC2 is used for the prediction mode information 303, if the number of bits of the picture header 302 is shorter than that of the one-block information of FEC1, the FEC1 code is kept used for the error correction and/or detection code of the succeeding prediction mode information 303 until reaching the bit number of FEC1 information.

[0072] FIG. 8 is a block diagram showing the bitstream assembler 213 shown in FIG. 4. The bitstream assembler 213 is composed of a counter 701 for counting the number of bits of the output bitstream 205, a buffer 702 for storing the check bits 632 and the number of bits thereof temporarily, a switch 703 for switching the output bitstream 205, and a switch controller 704 for controlling the switch 703. When the synchronization code request signal 203 is inputted to the bitstream assembler 213, the counter 701 is reset to a synchronization code length value sync_len, and counts up bits in sequence beginning from a bit just after the synchronization code until the succeeding synchronization code is inputted. Here, after the synchronization code has been inputted, the switch 703 is activated in such a way that the information bits 631 can be kept outputted until, the first check bit 632 is inputted. When the check bit 632 is inputted, the check bit 632 is stored in the buffer 702, and the number of bits (check bit number) 711 is outputted from the buffer 702 to the switch controller 704.

[0073] On the basis of the check bit number 711 and the count value 221 of the counter 701, the switch controller 704 controls the switch 703 to shift the check bit, that is, in such a way that the check bit 632 will not be outputted to the synchronization code insertion position, as already explained. For instance, when the count value 221 is denoted by bit_count and the check bit number 711 is denoted by check_len, if

$$\text{bit_count mod sync_period} < \text{sync_period} - \text{check_len}$$

information bits 631 are outputted, and if

$$\frac{\text{sync_period} - \text{check_len} \leq \text{total_bits}}{\text{sync_period} - \text{sync_period}} \quad \text{mod}$$

the check bits 713 stored in the buffer 702 are outputted. After that, the above-mentioned processing is repeated by inputting the information bits 631 and the check bits 632.

[0074] Here, as already explained, since the output coding apparatus 200 uses the punctured code at the last portion of each frame as the error correction and/or detection code and further shifts the check bit position for bit insertion, the operation is somewhat different from the ordinary operation.

In more detail, after having outputted the one-frame bitstream 201, the multiplexer 111 first outputs the synchronization code insertion request signal 203 for the succeeding frame. In correspondence thereto, the error correction and/or detection coder 604 of the error correction and/or detection switching coder 212 shown in FIG. 7 regards the insufficient portion of the information bits 631 of the error correction and/or detection code, as a bit pattern previously determined and outputted by an insertion (stuffing) bit generator 705, and forms the error correction and detection code by use of the redundant code. Here, the bit pattern can be composed of only bits of "1" or "0" or a repetition of a specific pattern as "010101 . . .".

[0075] After having outputted the last bit of the information bits 631, in the bitstream assembler 213 shown in FIG. 8, the switch 703 is switched from the bit generator 705 to the input side, to insert the insertion (stuffing) bit in such a way that the check bit 713 stored in the buffer 702 can be arranged just before the succeeding synchronization code. Here, when the count value 221 of the counter 701 obtained when the last information bit 631 of one frame has been outputted is denoted by total_len and the number of bits of the check bits 632 outputted lastly is denoted by last_check_len, the number of the insertion bits stuffing_len can be expressed as

$$\text{stuffing_len} = \text{sync_period} - \text{last_check_len} - (\text{total_len} \text{ mod } \text{sync_period}).$$

[0076] Further, when the degenerative code is not used, the insufficient portion (info_len - last_info_len) from the normal information bits info_len in the last information bits last_info_len are inserted. In addition, bits must be inserted in order to shift the check bits. As a result, as compared with when the redundant code is used, it is necessary to insert the following additional bits as

$$\frac{\text{info_len} - \text{last_info_len} + (\text{info_len} - \text{last_info_len}) \text{ mod } \text{sync_period}}$$

[0077] After having outputted the information bits 631 and the insertion bits to the output bitstream 205 through the switch 703, the bitstream assembler 213 is lastly switched to the check bits 731, and outputs the switched check bits 713 to the output bitstream 205.

[0078] The moving picture decoding apparatus according to the present invention will be described hereinbelow.

[0079] FIG. 9 is a block diagram showing the moving picture decoding apparatus which corresponds to the moving picture coding apparatus shown in FIG. 2. After having been passed through a transmission and/or storage system, the output bitstream 205 outputted by the moving picture coding apparatus shown in FIG. 2 is inputted to an input decoding apparatus 800 as an input bitstream 205'. In the present invention, the input decoding apparatus 800 corresponds to the output decoding apparatus 200 according to the present invention.

[0080] The input decoding apparatus 800, outputs a bitstream 801 obtained by decoding the error correction and/or detection code, a synchronization code detection signal 803, and an error detection signal 804, by switching the error correction and/or detection code on the basis of an FEC sort ID signal 802 indicative of the sort of the error correction and/or detection signal applied by the demultiplexer 811. That is, the demultiplexer 811 inputs the bitstream 801, the

synchronization code detection signal **803**, and the error detection signal **804**, and outputs a prediction residual signal **841** and a motion compensation adaptive prediction information code **842**, separately.

[0081] The prediction residual code **841** is inputted to the first variable length decoder **806**, and the motion compensation adaptive prediction information code **842** is inputted to a second variable length decoder **810**. Residual DCT coefficients **831** decoded by the first variable length decoder **806** are dequantized by a dequantizer **807**, inverse-DCTed by a inverse DCT section **808**, added to a motion compensation adaptive prediction signal **832** outputted by a motion compensation adaptive predictor **801** by an adder **809**, and then outputted as reconstructed picture signals **850**. The reproduced picture signals **850** are outputted from the decoding apparatus and further stored in a frame memory **820**. Further, the motion compensation adaptive prediction information decoded by the second variable length decoder **810** is inputted to a motion compensation adaptive predictor **801** to form motion compensation prediction signals **832**.

[0082] The above-mentioned processing is executed to reproduce moving picture in correspondence to the moving picture coding apparatus shown in **FIG. 2**. Therefore, the serial processing executed by the dequantizer **807**, the inverse DCT section **808**, the adder **800** and the frame memory **820** as shown in **FIG. 9** is basically the same as the serial processing executed by the dequantizer **107**, the inverse DCT section **108**, the adder **109'** and the frame memory **102** as shown in **FIG. 2**, although the realizing means are somewhat different from each other. Further, the processing of the first and second variable length decoders **806** and **810**, the demultiplexer **811** and the input decoding apparatus **800** are opposite to the processing of the first and second variable length decoders **106** and **110**, the multiplexer **111** and the output decoding apparatus **200**, respectively, excepting the case where an error injured the bitstream.

[0083] **FIG. 10** is a block diagram showing the input decoding apparatus **800** shown in **FIG. 9**. The input decoding apparatus **800** is composed of a synchronization detector **901** for detecting the synchronization code of the input bitstream **205'**, a counter **902** for counting the number of bits of the input bitstream **205'**, a bitstream disassembler **903** for disassembling the input bitstream **205'** into information bits **912** and check bits **913** and for outputting these bits separately, an error correction and/or detection decoder **904**, and an inserted stuffing bit remover **905**.

[0084] The synchronization detector **901** detects the synchronization code at only the synchronization code insertion position on the basis of the count value **911** outputted by the counter **902**. For instance, when the interval between the two synchronization code insertion positions is denoted by sync_period; the count value **911** is denoted by bit_count; and the length of the synchronization code is denoted by sync_len, the synchronization code is detected only when

$$0 < \text{bit_count} \bmod \text{sync_period} \leq \text{sync_len}$$

[0085] Here, it is also possible to detect the synchronization code under consideration of the presence of an error in the synchronization code.

[0086] Here, by the bit inserter **211** of the output coding apparatus **200** shown in **FIG. 4**, when the bitstream has been

converted by inserting bits in such a way that the Hamming distance thereof from the synchronization code becomes $2 * n + 1$ under consideration of an error less than n bits, even if the code having a Hamming distance less than n from the true synchronization code is decided as the synchronization code, as far as the erroneous bit is less than n bits, it is possible to prevent the synchronization code from being detected erroneously.

[0087] **FIG. 11** is a block diagram showing the bitstream disassembler **903** shown in **FIG. 10**. The input bitstream **205'** is switched to the information bits **1021** and the check bits **913** by a first switch **1002** controlled by a controller **1001** (described later). When the information bits **1021** are outputted from the first switch **1002**, the information bit length of the information bits **1021** are stored by a buffer **1004** via a second switch **1003**. A counter **1005** counts the number of the output bits from the second switch **1003**. The count value **1023** of the counter **1005** is compared with the information bit length **1024** outputted by an error correction and/or detection code (i.e., FEC) information output section **1007** by a comparator **1006**. When both match, the counter **1005** is reset, and the FEC sort ID signal **802** indicative of the sort of the error correction and/or detection code is latched by a latch circuit **1008**. Further, the information bits **912** are outputted from the buffer **1004**. Further, the output **914** of the latch circuit **1008** is inputted to the error correction and/or detection code information output circuit **1007** and further to the error correction and/or detection decoder **904** shown in **FIG. 10**.

[0088] As already explained, the check bits of the error correction and/or detection code are shifted in position so as to be formed between the information bits of the error correction and/or detection code arranged backward in the bitstream **205**. Therefore, the controller **1001** controls the switch **1002** in such a way that these position-shifted check bits can be separated from the information bits. After the information bits of the one-block error correction and/or detection code have been inputted, the count value **1023** matches the information bit length **1024** in the comparator **1006**. In response to this match signal, the controller **1001** receives the check bit length **1025** from the error correction and/or detection information output circuit **1007** to calculate the check bit position inserted between the information bits. Here, when the count value **911** indicative of the number of inputted bits of the bitstream **205'** (obtained when the comparator **1006** outputs the match signal) is denoted by bit_count; and the check bit length is denoted by check_len, the check bit start position check_start is

$$\text{check_start} = (\text{bit_count} / \text{sync_period} + 1) * \text{sync_period} - \text{check_len}$$

and the check bit end position check_end is

$$\text{check_end} = (\text{bit_count} / \text{sync_period} + 1) * \text{sync_period}$$

That is, the controller **1001** controls the switch **1002** so that the check bits **913** can be outputted when the count value **911** lies between check_start and check_end.

[0089] Further, since the error correction and/or detection coding is executed by the degenerative code at the last of one frame, a special processing is necessary. At the last of one frame, the synchronization detector **901** outputs a signal **803** indicative of that the synchronization code of the succeeding frame has been detected. In response to this signal, the controller **1001** calculates the position of the last error

correction and/or detection check bit in the frame and the number of insufficient information bits. Here, the assumption is made that the count value **911** of the number of bits of the bitstream **205'** inputted when the last error correction and/or detection code of one frame is started to be inputted is denoted by `pre_last_count`; the count value **911** at a time when the one-frame bitstream **205'** has been inputted is denoted by `total_count`; the count value **911** at the processing is denoted by `bit_count`; the check bit length of the last error correction and/or detection code of one frame is denoted by `last_check_len`; and the check bit length of the second-last error correction and/or detection code is denoted by `pre_last_check_len`. First, since the error correction code is a punctured code and further the bit is inserted, the overs and shorts of the information bits are calculated. Here, the number of information bits `last_info_len` of the last error correction and/or detection code of one frame included in the output bitstream **205** is

$$\text{last_info_len} = \text{total_count} - \text{last_check_len} - \text{pre_last_count} - \text{pre_last_check_len}$$

[0090] Then, when `last_info_len` is shorter than the information length `info_len` of the error correction code, the degenerative code is decided, so that the switch **1003** is switched so as to output the bit pattern from the insertion bit generator **1015** during the period between `last_info_len` and `info_len` of the count value **1023**, in order to supply the insufficient information bits due to the degenerative code. Here, the bit pattern outputted by the insertion bit generator **1015** is the same as that generated by the insertion bit generator **705** of the coder shown in **FIG. 8**.

[0091] On the other hand, when `last_info_len` is longer than `info_len`, this information bit length is decided as inserted bits, and the bit portion of the count value more than `info_len` is not outputted as the information bits **912**. On the other hand, the switch **1002** is so controlled that the output bitstream **205** is outputted as the check bits, when the bit count of the check bits is

$$\text{total_count} - \text{check_len} < \text{bit_count} \leq \text{total_count}$$

[0092] The error correction and/or detection decoder **904** inputs the information bits **912** and the check bits **913** outputted by the bitstream disassembler **903**, decodes the error correction and/or detection code on the basis of the FEC sort ID signal **914** indicative of the sort of the error correction and/or detection code latched by the latch circuit **1008** shown in **FIG. 11**, and outputs the error-corrected bitstream **915** and the error-detected signals **804**.

[0093] The error-corrected bitstream **915** is inputted to the insertion bit remover **905** to remove the insertion bits inserted by the bit inserter **211** of the output coding apparatus **200**, in order to prevent pseudo-synchronization signal from being generated. As already explained, since the bits are inserted at only the synchronization code insertion positions, the synchronization code insertion position can be decided on the basis of the count value **911** of the counter **902**.

[0094] For instance, when the synchronization code word is that as shown in **FIG. 6** and further when the bits are inserted by the bit inserter **211** at "0000 . . ." portion of the first `sync_len` bits in such a way that the Hamming distance from the synchronization code is more than $(2 * n + 1)$, the number ($=n0$) of "1" in $\{\text{sync_0_len} - (2 * n + 1)\}$ bits beginning from the synchronization code insertion position is

counted, when $n0$ is less than $2 * n + 1$, bits of $(2 * n + 1 - n0)$ are removed. Here, however, since the insertion bits are determined as "1", when the bit decided by the insertion bit remover **905** as the insertion bit is "0", this is regarded as that an error is mixed in the synchronization code insertion block. In this case, therefore, the error detection signal **804** is outputted.

[0095] As described above, the bitstream **801** decoded by the input decoding apparatus **800** is reverse multiplexed by the reverse multiplexer **811**. In this operation, the code word multiplexed as shown in **FIG. 3** is separated and then outputted. Further, this reverse multiplexer **811** operates in linkage with the first and second variable length decoders **806** and **810**, respectively.

[0096] In operation in **FIG. 9**, first when a synchronization code detection signal **803** is inputted from the output decoding apparatus **800**, the reverse multiplexer **811** is initialized for one-frame processing. Then, the reverse multiplexer **811** outputs the sort of the error correction and/or detection code corresponding to the picture header, as the FEC sort ID signal **802** indicative of the sort of the error correction and/or detection code, inputs the bitstream **801**, and decodes the picture header **302** to check whether there exists any error in the decoded picture header. When there exists no error, the reverse multiplexer **811** outputs the sort of the error correction and/or detection code corresponding to the prediction mode information **303** as the FEC sort ID signal **802**, inputs the bitstream **801**, multiplexes the prediction mode information, and then outputs the motion compensation adaptive prediction information code **842** to the second variable length decoder **810**.

[0097] When having decoded all the prediction mode information (the motion compensation adaptive prediction information code **842**), the second variable length decoder **810** outputs an end signal to the reverse multiplexer **811**. In response to this end signal, the reverse multiplexer **811** outputs the FEC sort ID signal indicative of the sort of the error correction and/or detection code corresponding to the motion vector information **304**, and starts the reverse multiplex processing of the motion vector information **304**. The reverse multiplexed motion vector information is outputted to the second variable length decoder **810** for decoding. After having decoded all the motion vector information, the second variable length decoder **810** outputs an end signal to the reverse multiplexer **811**. In response to this end signal the reverse multiplexer **811** outputs the FEC sort ID signal indicative of the sort of the error correction and/or detection code corresponding to the residual DCT coefficient **305**, reversely multiplexes the residual DCT coefficients **305**, and outputs the reversely multiplexed results to the first variable length decoder **806**. The first variable length decoder **806** decodes the residual DCT coefficients **305**.

[0098] As described above, the sort of the error correction and/or detection code is decided by the reverse multiplexer **811** in accordance with the multiplexing rule prescribed in the same way as with the case of the output coding apparatus **200**. Therefore, it is unnecessary to add the header information indicative of the sort of the error correction and/or detection code to the output bitstream **205**.

[0099] In the error correction and/or detection decoder **904** shown in **FIG. 10**, there exists the case where a mixture of an error with the inputted bitstream **205'** can be detected by

the error detection code. In addition, there exist the case where an erroneous bit insertion can be detected by the insertion bit remover **905**. In these error cases, the input decoding apparatus **800** outputs an error detection code **804**. Further, when a code word not stored in a variable length word table is detected in the variable length decoding processing, a mixture of an error is decided. Further, when the presence of a portion departing from the multiplexing rule is decided by the reverse multiplexer **811** during the reverse multiplexing processing, it is discriminated that an error is mixed. In these cases, in order to prevent the reproduced picture from being deteriorated largely, the input decoding apparatus **800** and the reverse multiplexer **811** execute the following processing:

[0100] (1) When an error is detected in the residual DCT coefficient, the residual at the corresponding portion is set to zero. In this case, when the intra-coding mode is selected as the prediction mode, the reproduced picture signals can be predicted on the basis of the already reproduced frame or the reproduced video signals in the surrounding area.

[0101] (2) When an error is detected in the prediction mode information and the motion vector, if it is possible to presume the prediction mode information or the motion vector information on the basis of the prediction mode information or the motion vector information existing in the surrounding area, these information can be used. If impossible, however, the reproduced picture signals are predicted on the basis of the reproduced picture signals in the already reproduced frame or existing in the surrounding area.

[0102] (3) When an error is detected in the picture header, since the picture quality deteriorates largely when decoded as it is, the reproduced picture of the preceding frame is used as it is, as the reproduced picture of the present frame.

[0103] In the above-mentioned processing in the items (1) to (3) above, when the error exerts a harmful influence upon the following code till the succeeding synchronization code, because the variable length coding is used, the similar processing as above is executed for the error-affected portion.

[0104] In the above-mentioned description, an example where the synchronization code detector **901** detects the synchronization code at only the synchronization code insertion positions (for each sync_period bits) has been explained. However, there exists the case where a bit is lost or an erroneous bit is inserted according to the transmission and/or storage medium. In this case, the synchronization code is detected at the position other than the synchronization code insertion position, and the position where the synchronization code can be detected is decided as the synchronization code insertion position.

[0105] Further, in the above description, although an example where the moving picture is high-efficiency compression-coded and then transmitted and/or stored has been explained by way of example, it is of course possible to apply the coding and decoding apparatus according to the present invention to the case where still picture or audio or other information are transmitted and/or stored. For instance, in the case where still picture signals are compression coded at a high efficiency by use of the orthogonal transform, it is preferable to switch the error correction and/or detection codes in such a way that the lower fre-

quency components of the transform coefficients can be protected from error more securely. For instance, in the method of coding audio signals by modeling voice with a sound source and a sound path filter, it is preferable that the error correction and/or detection codes are switched in such a way that the pitch period and the sound path filter can be protected from error more securely.

[0106] As described above, in the coding and decoding apparatus according to the present invention, since the synchronization code is inserted at only the synchronization code insertion position at regular intervals and further since the check bits of the error correction and/or detection code are shifted so as to be arranged at a position other than the synchronization code insertion position, even if the bit pattern the same as that of the synchronization code is formed in the check bits, the bit pattern the same as that of the synchronization code will not be formed at the synchronization code insertion position at which the synchronization code is detected, so that it is possible to perfectly eliminate the possibility that the synchronization is detected erroneously, from the principle standpoint.

[0107] Further, when the bits are inserted into the bitstream arranged at the synchronization code insertion position in such a way as not to form the pseudo-synchronization, it is possible to eliminate such a prior art difficulty that the code word must be constructed in such a way that the bit pattern the same as that of the synchronization bits will not be formed.

[0108] In addition, in the present invention, since the bits are inserted under consideration of erroneous synchronization code; that is, since the bit train arranged at the synchronization code insertion position is converted in such a way that the Hamming distance from the synchronization code exceeds a predetermined value and further reversely converted by the decoding apparatus, the bit pattern the same as that of the synchronization code will not be included in the bit train, so that it is possible to secure that an erroneous detection of the synchronization code can be prevented as far as the number of bits is less than a predetermined value. As a result, the possibility of the erroneous detection of the synchronization code can be reduced. Further, when the above-mentioned conversion is executed, even if an error is mixed with the bitstream, since it is possible to discriminate the synchronization code from the bitstream other than the synchronization code, it is possible to reduced the possibility that the synchronization code is detected erroneously.

[0109] Further, since the error correction and/or detection coding is executed after the code word has been converted by bit insertion, the bit insertion can be protected from the error occurrence. Therefore, as compared with the prior art method such that the bits are inserted after the error correction and/or detection coding has been completed, it is possible to reduce the possibility that the erroneous bit insertion occurs. In addition, since the bit insertion is executed only at the synchronization code insertion position, an increase of the code quantity due to the bit insertion can be reduced, as compared with the prior art case where the bits are inserted all over the bitstream, with the result that the coding efficiency can be increased.

[0110] Further, in the present invention, since the error correction and/or detection code immediately before the

synchronization code is formed as a degenerative code, it is possible to reduce the number of insertion bits for compensating for the remainder of the information bits immediately before the synchronization code, as compared with the prior art coding apparatus, with the result that the coding efficiency can be further increased.

[0111] Further, in the present invention, since the error correction and/or detection codes are switched in accordance with the multiplexing rule of the high efficiency compression coding apparatus for audio and video signals and according to the information sort of the inputted bitstream, and further since the error correction and/or detection codes are switched by deciding the sort of the error correction and/or detection code on the basis of the decoded information on the decoding apparatus side, it is unnecessary to add the header information indicative of the sort of the error correction and/or detection code and thereby the number of bits assigned to the audio or video high efficiency compression coding can be increased, with the result that it is possible to increase the quality of the audio and video information to that extent.

1.-8. (canceled)

9. A coding method, comprising:

 multiplexing a plurality of kinds of variable-length codes generated by compression coding of an input image signal to generate a multiplexed code string;

 assembling an output code string by using the multiplexed code string as an input; and

 inserting a synchronization code to one of a plurality of synchronization code inserting positions periodically predetermined in the output code string, and inserting a stuffing bit of 8 bits or less in the output code string.

10. A coding apparatus, comprising:

 a multiplexer configured to multiplex a plurality of kinds of variable-length codes generated by variable-length coding of an input image signal to generate a multiplexed code string; and

 a coding assembler configured to assemble an output code string by using the multiplexed code string as an input, the coding assembler inserting a synchronization code

to one of a plurality of synchronization code inserting positions periodically predetermined in the output code string, and inserting a stuffing bit of 8 bits or less in the output code string.

11. The coding apparatus according to claim 10, wherein the multiplexer multiplexes the variable-length codes in units of a frame of the image signal.

12. The coding apparatus according to claim 10, wherein the multiplexer multiplexes the variable-length codes in units of a partial area in a frame of the image signal.

13. The coding apparatus according to claim 10, wherein:

 the multiplexer multiplexes the variable-length codes in units of a frame of the image signal; and

 the coding assembler inserts the synchronization code to the synchronization code inserting position located just before or just after an end portion of each multiplexed portion in the multiplexed code string, the multiplexed portion being multiplexed in units of the frame.

14. The coding apparatus according to claim 10, wherein:

 the multiplexer multiplexes the variable-length code in units of a partial area in a frame of the image signal; and

 the coding assembler inserts the synchronization code to the synchronization code inserting position located just before or just after an end portion of each multiplexed portion in the multiplexed code string, the multiplexed portion being multiplexed in units of the partial area.

15. The coding apparatus according to claim 10, further comprising a code string converter which converts a code string except for the synchronization code located to the synchronization code inserting position in the output code string to set a Hamming distance from the synchronization code to be equal to or more than a predetermined value.

16. The coding apparatus according to claim 10, wherein the stuffing bit has a value in which a Hamming distance between the synchronization code and a portion there is equal to or more than a predetermined value.

17. The coding apparatus according to claim 16, wherein the code string assembler arranges the stuffing bit just before the synchronization code.

* * * * *