

(19) World Intellectual Property Organization  
International Bureau



(43) International Publication Date  
27 November 2008 (27.11.2008)

PCT

(10) International Publication Number  
**WO 2008/142402 A1**

(51) International Patent Classification:

A61N 1/05 (2006.01) A61N 1/34 (2006.01)

(21) International Application Number:

PCT/GB2008/001723

(22) International Filing Date: 20 May 2008 (20.05.2008)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:

0709834.6 22 May 2007 (22.05.2007) GB

(71) Applicant and

(72) Inventor: GILLBE, Ivor Stephen [GB/GB];  
'Greensleeves', Bridge Road, Leigh Woods, Bristol  
BS8 3PE (GB).

(74) Agents: CALDERBANK, Roger et al.; Mewburn Ellis  
LLP, York House, 23 Kingsway, London, Greater London  
WC2B 6HP (GB).

(81) Designated States (unless otherwise indicated, for every  
kind of national protection available): AE, AG, AL, AM,

AO, AT, AU, AZ, BA, BB, BG, BH, BR, BW, BY, BZ, CA,  
CH, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE,  
EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID,  
IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LA, LC,  
LK, LR, LS, LT, LU, LY, MA, MD, ME, MG, MK, MN,  
MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PG, PH,  
PL, PT, RO, RS, RU, SC, SD, SE, SG, SK, SL, SM, SV,  
SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN,  
ZA, ZM, ZW.


(84) Designated States (unless otherwise indicated, for every  
kind of regional protection available): ARIPO (BW, GH,  
GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM,  
ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM),  
European (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI,  
FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MT, NL,  
NO, PL, PT, RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG,  
CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Published:

- with international search report
- before the expiration of the time limit for amending the  
claims and to be republished in the event of receipt of  
amendments

(54) Title: ARRAY STIMULATOR

Figure 8



(57) Abstract: An array stimulator has a plurality of electrodes in an array (22), the electrodes forming a plurality of electrode pairs, and a signal generator (18) for generating signals to the electrodes so as to generate electrical pulse in a patient to which the stimulator has been applied either transcutaneously or by implantation. Those electrical pulses form a composite pulse in the patient which stimulates the nervous system of the patient. The composite pulse has a duration between 4 $\mu$ s and 1500 $\mu$ s and a maximum voltage between 2V and 50V when the stimulator is implanted, and 15V to 500V when applied transcutaneously. The electrical pulses themselves are significantly shorter duration than the composite pulse, so they stimulate the nervous system of the patient much less than the composite pulse or not at all.

## ARRAY STIMULATOR

## FIELD OF THE INVENTION

5 The present invention relates to an electrical device designed to produce currents that affect the behaviour of nerves and other excitable tissues lying at various distances from the electrodes and provides apparatus and methods for application of such device.

10

## BACKGROUND OF THE INVENTION

Electrical stimulation of nerves has been in use for therapeutic purposes for more than 40 years.

15

For example Melzack and Wall 1965 described how analgesia could be produced when A $\beta$  nerve fibres are stimulated at 100 Hz, a frequency that none of the other afferent fibres can follow faithfully. Wall 1986 produced these effects by applying the current through needles inserted into the patient's nerves. To avoid possible complications of inserting needles, he soon employed surface electrodes, leading to the term Transcutaneous Electrical Nerve Stimulation (TENS).

25

A typical TENS machine develops a pulse whose width can be varied from 50-250  $\mu$ s, employing a current whose amplitude can be increased from 0-50 mA, and whose frequency is in the range of 1 to 250 Hz. The pulse width is sufficiently long in duration to excite A $\beta$  fibres at low voltage causing a painless tingling and stimulation of interneurons releasing GABA. Johnson et al 1991 showed that 'high intensity stimulation', where the amplitude is increased sufficiently to recruit A $\delta$  fibres,

30

invokes release of met-enkephalin in the spinal cord which produces a more prolonged analgesic effect than that provided by the release of GABA produced by the more usual 'low intensity stimulation' of A $\beta$  fibres. Salar et al 1981 observed that opioids were released slowly into the cerebrospinal fluid when TENS is performed at frequencies of 40-60 Hz and at amplitudes of 40-80 mA, signals that readily recruit A $\delta$  fibres and whose firing is associated with sharp pain.

It is generally believed that TENS analgesia is caused mainly by cutaneous afferent fibre activation. However, Radkarishnan et al 2005 demonstrated that by differentially blocking cutaneous and deep tissue primary afferents, activation of large diameter primary afferents from deep somatic tissues, and not cutaneous afferent fibres, are pivotal in causing TENS analgesia.

A potential limitation of the effectiveness of TENS stimulation may therefore be that intensity of stimulation is limited by pain arising from activation of A $\delta$  and C-fibres lying immediately under the electrodes.

As tissue impedance is capacitive, impedance tends to fall as frequency is increased. In order to increase tissue penetration, signals may be provided at a frequency where the intervals between each electric signal are less than the refractory periods of fibres that require stimulation. In order to produce action potentials, such signals are modulated to provide low frequency stimulation either by interference or interruption.

The interference method of applying medium frequency currents is exemplified by Nemec US2622601 "Electrical Nerve Stimulator", Griffith US3096768 "Electrotherapy System" (Firmtron Inc) and many others. Two signal  
5 sources are each connected to a pair of electrodes. They can produce an amplitude modulated medium frequency signal in the tissues called interferential current, as follows. The first signal source uses a medium frequency carrier wave (typically 4.0 kHz) while the other operates  
10 at a slightly different frequency (typically 4.1 kHz). Their respective pairs of surface electrodes are arranged on the body in a manner that allows the two oscillating currents to intersect in deep tissues where interference is produced at a beat frequency in the low frequency  
15 range, typically at 100 Hz. This in turn is said to stimulate deeply placed A $\beta$  fibres to produce analgesia.

However, there has been controversy as to whether or not a beat frequency is required to cause action potentials.  
20 Palmer *et al* 1999 discovered that when there is no interference frequency, *i.e.* the patient is receiving currents from both signal generators at 4 kHz and this frequency is no longer subjected to amplitude modulation, sensation still occurs. Moreover, the threshold of  
25 sensation generated in this way at 4 kHz takes place at lower amplitude than that produced by low frequency signals at less than 100 Hz. Signals administered at a frequency higher than any individual fibre can respond to on a 1:1 basis will produce asynchronous volleys in a  
30 nerve trunk as a result of action potentials arising in any axons in the vicinity of the next signal that by coincidence are no longer refractory.

Another method of improving tissue penetration in transcutaneous stimulation devices is described in Carter and Siff US7130696 "Percutaneous electrode array" in which the electrode is constructed from an array of  
5 microscopic pins that are intended to penetrate the outer layers of the skin thereby overcoming the electrical impedance of these layers.

Macdonald and Coates US5776170 "Electrotherapeutic  
10 apparatus" (1995) explored the effects of applying electric signals whose pulse width is so brief, typically 4  $\mu$ s, that the voltage gated channels lying in excitable membranes of peripheral fibres that lie in the path of the current do not have time to respond to these signals  
15 sufficiently to reach membrane threshold and produce action potentials. This form of electrotherapy produces analgesic and mood altering effects provided that surface electrodes are placed over the spinal cord. Macdonald and Coates 1995 called this method TSE (Transcutaneous  
20 Spinal Electroanalgesia).

Littlewood et al. GB2414410 "Electrotherapy Apparatus" (Bioinduction Ltd, 2005) discusses the effects of employing short high power electrotherapy waveforms for  
25 therapeutic purposes and describes the relationship between pulse width and the generation of action potentials and shows that the current in the tissues may be controlled independently of the level of sensation perceived by the patient.

30

Although the TENS method is reasonably well accepted by patients, it tends to produce a rather short-lived, localized region of pain relief. This is perhaps because of the aforementioned limitation on stimulation intensity

caused by pain at the site of the electrodes and also because each electrode probably stimulates only those A $\beta$  fibres that lie in the immediate vicinity of the electrodes. Accordingly, in patients where there is pain  
5 in several areas of the body, there is a need to improve the method, to produce a more long-lasting and generalized form of pain relief.

In 1967 in order to activate more A $\beta$  fibres, electrodes  
10 were implanted by Professor Norman Shealy (Shealy et al 1967, 1971) in the spinal canal to stimulate the central nervous system, in particular the dorsal column (tracts through which the A $\beta$  fibres pass up and down the spinal cord). Now termed Spinal Cord Stimulation (SCS), a  
15 repetitive low frequency pulse is employed typically at a frequency of 100 Hz or less and a pulse width in excess of 50  $\mu$ s. When SCS is effective, a tingling sensation (paraesthesia) is perceived in the painful region of the body.

20 Since the invention of SCS by Shealy, many advances have been made in implanted devices for controlling chronic pain by means of electrical stimulation. The application of such devices has also been extended to include  
25 implanted deep brain stimulation, for pain relief and also to treat a range of conditions, for example Parkinson's disease.

Whereas transcutaneous stimulators tend to use only a few  
30 electrodes, often one or two pairs, implanted stimulators with four, eight or more pairs of electrodes are well known in the art. An early example, Timm and Bradley US3646940 "Implantable Electronic Stimulator Electrode and Method" (1969) described an apparatus for stimulation

of muscles which includes a plurality of electrodes wherein a timed sequence of stimulating pulses is applied to the electrodes such that secondary tissue stimulation (that caused by current flowing between nearby electrode  
5 pairs) is eliminated.

For convenience, multiple electrode contacts are often combined on a single carrier and these arrays of electrodes are widely used today in spinal cord  
10 stimulators. For example, Borkan Savino and Waltz "Multi-electrode catheter assembly for spinal cord stimulation" US4379462 (Neuromed Inc, 1980) describes a linear array of four electrodes spaced in-line along the exterior of a catheter electrode assembly. An advantage  
15 of this type of electrode is that it is easy to insert in into the epidural space by means of a needle. These electrodes are referred to today by the term "Percutaneous electrode" because of the introduction method used.

20 Today percutaneous electrodes with eight contacts are often employed and two may be inserted into the epidural space, connected to a sixteen output stimulator. The surgeon programs different combinations of electrodes via  
25 wireless telemetry to stimulate a particular region of tissue in order to produce the desired therapeutic result. An array of electrodes also provides a degree of protection against migration, as it may be possible to reconfigure the electrode combination to compensate for  
30 small movements in the implanted array, to continue to stimulate a particular target area of tissue without a surgical procedure.

Another typical lead configuration is described in Hull Cross and Langley "Method of using a spinal cord stimulation lead" US5417719 (Medtronic Inc, 1993). This describes a type of "paddle electrode" so called because  
5 of the shape of the end of the lead which contains an array of electrodes located on the lead paddle. Each electrode is independently selectable such that the spinal cord may be stimulated as required.

10 Recent developments have attempted to increase the ability of the surgeon and/or patient to stimulate a particular area of tissue. Gord "Programmable current output stimulus stage for implantable device" US6181969 (Advanced Bionics Inc, 1999) describes a programmable  
15 output current source for use within an implantable stimulator, wherein for example sixteen individual current sources may be employed to control the flow of current in an array of electrodes. Woods et al "Implantable generator having current steering means"  
20 US6909917 (Advanced Bionics Inc, 2003) describes a means of determining a desired electrode stimulation pattern by way of a directional programming technique that translates the movement for instance of a joystick into current levels on an array of electrodes. An objective  
25 of this technique is to provide fine control over the region of tissue that is stimulated, beyond that provided by the physical locations of the individual electrodes. A disadvantage is the complexity of the stimulator device, having sixteen current controlled outputs, and  
30 the relatively poor efficiency at mid range current output which is typical of a linear electronic design, thereby compromising battery life of the implant.



There also exists in the prior art the use of pulse width modulation as a technique which has been applied across many power electronic applications in order to improve efficiency. For example MacDonald "Pulsewidth Electrical Stimulation" US7054686 (Biophan Technologies Inc, 2002) describes an apparatus that employs a series of individual pulses to improve efficiency in (for example) cardiac pacing.

## 10 SUMMARY OF THE INVENTION

In order to generate action potentials in afferent fibres, a stimulator apparatus must produce a pulse or pulses of sufficient duration and amplitude. The required amplitude to cause an action potential varies depending on the electrode arrangement and also upon the quality of contact between the electrode and the tissues. The amplitude may be expressed in terms of voltage, current, charge or energy. Electrodes may be applied to the skin or implanted, but regardless of the contact method employed, the minimum amplitude of a pulse that will activate afferent nerves declines as pulse width is increased.

According to this invention, an apparatus consisting of a pulse generator connected to an array of electrodes is attachable to a patient's skin or implanted in the body so that it may be used to stimulate or otherwise affect the behaviour of a region of nerve or other excitable tissue. The electrodes of the electrode array, or a subset of the electrodes thereof, are excited for short durations in turn so that the current flowing from each electrode into its immediately adjacent tissue is of short duration. In the target region of tissue covered

by the array or subset thereof, these short duration "component pulses" sum in turn to form a longer duration (or higher amplitude) stimulus pulse referred to as the "composite pulse".

5

## Definitions

In this text, the following definitions apply:

10 Electrode - a conductive element that is used to apply electrical current to the tissues, applied either to the skin or implanted in the body.

Electrode array - a plurality of electrodes optionally  
15 including the conductive enclosure of an implanted device.

Electrode pair - the combination of one anode and one cathode (which may reverse in the case of a biphasic  
20 waveform) across which an electrical stimulus is applied. The anode and cathode are each formed from one or more electrodes from the array, in the case of more than one electrode forming either anode or cathode, these electrodes being electrically connected together.

25 Individual electrodes may be shared between anodes or cathodes in one or more electrode pairs, provided each combination is unique.

Pulse - a single departure from the zero volt or zero amp  
30 line, ideally with rapid rising and falling edges and preferably of approximately rectangular form.

Composite pulse - the desired form of pulse used for stimulating nerves or otherwise affecting the behaviour

of excitable tissues which is intended to be sub-divided into a number of sequential component parts before application to electrode pairs, typically of total duration between 4  $\mu$ s and 1500  $\mu$ s, or more preferably  
5 between 20  $\mu$ s and 1000  $\mu$ s.

Component pulse - a pulse which corresponds to a sub-division of the composite pulse, for application to a particular electrode pair, typically of maximum duration  
10 of 2  $\mu$ s, or 4  $\mu$ s, or 10  $\mu$ s, or 20  $\mu$ s, or 50  $\mu$ s. The sum of the width of all component pulses should be equal to the width of the composite pulse, although where component pulses are applied with spaces between them or overlapping, the total time taken to deliver all  
15 component pulses may not be the same as the composite pulse width.

Sub-component pulse - a further subdivision of the component pulse corresponding to a train of shorter  
20 pulses for application to a particular electrode pair, to be applied either in sequence or interleaved with sub-component pulses applied to other electrode pairs.

Modulation - reduction of the pulse width of a component  
25 or sub-component pulse expressed as a percentage of the time available for that pulse derived by division of the composite pulse into the appropriate component parts.

Duty cycle - the duration or pulse width of the component  
30 pulse (or sum of the sub-component pulse widths thereof) as a proportion of the pulse width of the composite pulse.

Waveform - a combination of one or more composite pulses, component pulses or sub-component pulse trains into a pattern normally consisting of forward and reverse elements which is intended to be repeated regularly.

5

Cycle - the combination of all waveforms applied to a particular array intended to be repeated regularly, typically at between 0.5 Hz and 2,000 Hz or 10,000 Hz.

10 In one aspect, the invention is an apparatus for applying electrical pulses to a patient, the apparatus comprising a plurality of electrodes arranged in an array, and a signal generator for generating signals to said electrodes so as to form said electrical pulses, the  
15 signal generator being arranged to generate said signals such that the signals are either sequentially transmitted to said successive electrode pairs in a cycle so the respective electrode pairs receive the corresponding signals at different times, or alternatively so that the  
20 signals are received by the electrode pairs such that they do not all start and end at the same point in time, further a composite pulse that is generatable by said electrodes due to said signals has a duration between 4  $\mu$ s and 1500  $\mu$ s, or more preferably between 20  $\mu$ s and  
25 1000  $\mu$ s, and a maximum voltage as follows:

a) for implanted devices a maximum voltage between 2 V and 50 V, or more preferably between 5V and 20V or even more preferably between 10 V and 15 V;

30

b) for transcutaneous devices a maximum voltage between 15V and 500V, or more preferably between 50V and 250V.

In a preferred embodiment, the composite pulse is generated by signals sequentially applied to the electrodes which are either single pulses or pulse trains with a minimum pulse width of 0.1 or 0.5  $\mu$ s and a maximum  
5 pulse width of 2  $\mu$ s, or 4  $\mu$ s, or 10  $\mu$ s, or 20  $\mu$ s, or 50  $\mu$ s. These pulse trains may thus be applied to pairs of electrodes either interleaved with trains applied to other pairs of electrodes in the array, or delivered sequentially.

10

In a second aspect, the invention provides an apparatus for applying electrical pulses to a patient, the apparatus comprising a plurality of electrodes arranged in an array and a signal generator, the signal generator  
15 incorporating a power supply and a controller arranged to generate or supply composite stimulus pulses which make up a desired stimulus waveform. The apparatus then has a converter arranged to convert composite stimulus pulse, using a network of high speed switching elements, into  
20 sequential component pulses directed to pairs of electrodes in the array in a sequence such that successive electrode pairs are arranged to generate the respective component pulses in a cycle. The composite stimulus pulse has duration of between 4  $\mu$ s and 1500  $\mu$ s,  
25 or more preferably between 20  $\mu$ s and 1000  $\mu$ s. The component pulses have a maximum pulse width of 2  $\mu$ s, or 4  $\mu$ s, or 10  $\mu$ s, or 20  $\mu$ s, or 50  $\mu$ s.

In a variation of the above, the composite stimulus pulse  
30 may be represented in the controller by a mathematical model or numerical analogue and the component pulses may be synthesized directly using a power supply and a network of high speed switching elements connected to electrodes in the array.

The component pulses may be delivered sequentially, so that at least one pair of electrodes is active at any time during the period of the composite stimulus pulse, or may have gaps of a few microseconds between them, preferably less than 20  $\mu$ s, but up to a maximum of 200  $\mu$ s, so that the sum of the component pulse widths is equal to the composite pulse width, but the total duration of the component pulses is equal to the composite pulse width plus the sum of the gaps between the component pulses.

In implanted stimulation apparatus, one or more electrode(s) in the array may optionally be provided by the enclosure of a stimulator device housing the signal generator and battery supply.

In a third aspect, the invention provides an apparatus for applying electrical pulses to a patient, the apparatus comprising a plurality of electrodes arranged in an array, a signal generator for generating signals to said electrodes (optionally an additional electrode provided by the signal generator enclosure), a controller arranged to control, represent or store a desired notional voltage, current, charge or energy distribution in a mathematical or empirically derived model of human or animal tissue in the region of the array, termed the "the notional stimulation field". The apparatus then has a transformation element arranged to reduce the notional stimulation field into a series of component pulses with respective duty cycles and/or amplitude so that they produce a desired notional stimulation field in a model of the flow of current between the electrodes, and a stimulator arranged to apply these component pulses to

the array of electrodes. The component pulses are either sequentially transmitted to said electrodes at different times such that successive electrode pairs are arranged to generate the respective component pulses in a cycle, or alternately so that they do not all start and end at the same point in time. These component pulses are produced by one or more signal generator devices. If the number of signal generators is less than electrodes in the array, a network of high speed switching elements is provided to direct the generator outputs to pairs of electrodes in the array. The mathematical model may be complex, including the various electrical characteristics of surrounding tissues, or may be simple, such as assuming a one or two dimensional homogeneous resistive medium. An empirical model may be expressed mathematically, or as a number of reference stimulation patterns which may be interpolated between, or as a series of look-up tables or rules.

The characteristics of the notional stimulation field may be controlled by the patient, surgeon, or other operator using an operator interface that provides control of the centre and optionally the coverage area of the desired field of stimulation.

In a variation of the above, the means of calculating the desired current, charge or energy distribution in a model of human or animal tissue is provided by a computer system separate from the signal generator unit and the parameters of the desired stimulus field and/or component waveforms are transmitted to the signal generator unit.

In a fourth aspect, the invention provides an apparatus for applying electrical pulses to a patient, the

apparatus comprising a plurality of electrodes arranged in an array and a signal generator for generating signals to said electrodes, the signals being short component pulses applied to pairs of electrodes such that the  
5 component pulses are generated by successive electrode pairs in a cycle; the amplitude and duration of the pulses being such that these pulses produce little or no activation of afferent fibres directly adjacent to one or more of the electrodes, but the sum of the pulses in a  
10 target region of tissue distant from one or more of the electrodes is sufficient to produce an action potential in fibres or some other physiological effect in excitable cells at this location.

15 This effect is arises when the combination of pulse width and amplitude of the component pulses is such that individually these pulses contain insufficient energy to activate voltage gated channels on nerve axons, but collectively the sum of the component pulses provide  
20 sufficient energy to meet the threshold level at which these channels are activated, thereby causing an action potential to be produced. The effect is particularly apparent with component pulses of duration of the order of 1  $\mu$ s to 4  $\mu$ s and composite pulses comprising 10 to 40  
25 component pulses such that their duration is 10  $\mu$ s to 160  $\mu$ s.

In a variation of the above, the component pulses may be of a duration and amplitude that in themselves cause an  
30 action potential in the tissues directly adjacent to the electrodes, but the sum of the component pulses is also sufficient to generate additional action potentials at locations distant from the electrodes.



In a fifth aspect, the invention provides an apparatus for applying electrical pulses to a patient, the apparatus comprising a plurality of electrodes arranged in an array and a signal generator for generating signals to said electrodes, the signals being short component pulses applied to pairs of electrodes, the relative pulse widths and polarity of the component pulses being varied with respect to each other and optionally the number of electrode pairs used are also varied to change the location and the coverage area of the region of the tissues that are stimulated.

In a sixth aspect, the invention provides an apparatus for applying electrical pulses to a patient, the apparatus comprising a plurality of electrodes arranged in an array and a signal generator for generating signals to said electrodes, the signals being short component pulses applied to pairs of electrodes, the component pulse widths on any given pair of electrodes, or individual electrodes with respect to the case or ground electrode of an implanted stimulator, being determined with respect to each other to normalise the sensation on each electrode such that the perceived stimulation at the amplitude limit or same programmed amplitude on each electrode pair is the same.

The above facilitates smooth changes in the location and the coverage area of the region of the tissues that are stimulated while minimising apparent changes in stimulation intensity due to differences in the tissues or contact resistance in the region of each electrode in the array. Determination of the relative pulse widths for the component pulses may be achieved by measuring the onset of sensation or other reference level of sensation

on each contact in turn with respect to the housing of the controller, or by measuring only a few electrodes and interpolating to provide an estimate for other electrodes.

5

Any of the first to sixth aspects discussed above may also provide a method of applying electrical pulses to a patient in which the pulses are applied via an electrode array on or in the patient.

10

Thus, for example, in the first aspect there may be provided a method in which signals are generated and sequentially transmitted to successive pairs of electrodes in an electrode array such that the signals are either sequentially transmitted to said successive electrode pairs in a cycle so the respective electrode pairs receive the corresponding signals at different times, or alternatively so that the signals are received by the electrode pairs such that they do not all start and end at the same point in time, thereby generating a composite pulse in the patient which has a duration between 4  $\mu$ s and 1500  $\mu$ s, or more preferably between 20  $\mu$ s and 1000  $\mu$ s, and a maximum voltage as follows:

25

a) for implanted devices a maximum voltage between 2 V and 50 V, or more preferably between 5V and 20V or even more preferably between 10 V and 15 V;

30

b) for transcutaneous devices a maximum voltage between 15V and 500V, or more preferably between 50V and 250V.

Similarly the second aspect may provide a method in which a composite pulse is converted into sequential component

pulses which are then directed to pairs of electrodes in the array in a sequence such that successive electrode pairs are arranged to generate the respective component pulses in a cycle. The composite stimulus pulse has  
5 duration of between 4  $\mu$ s and 1500  $\mu$ s, or more preferably between 20  $\mu$ s and 1000  $\mu$ s. The component pulses have a maximum pulse width of 2  $\mu$ s, or 4  $\mu$ s, or 10  $\mu$ s, or 20  $\mu$ s, or 50  $\mu$ s.

10 In the third aspect, a method may be provided in which a desired notional voltage, current, charge or energy distribution in a mathematical or empirically derived model of human or animal tissue in the region of the array, termed the "the notional stimulation field". The  
15 notional stimulation field is then reduced to a series of component pulses with respective duty cycles and/or amplitude so that they produce a desired notional stimulation field in the tissues or in a model of the flow of current between the electrodes, and these  
20 component pulses are then applied to the array of electrodes. The component pulses are either sequentially transmitted to said electrodes at different times such that successive electrode pairs are arranged to generate the respective component pulses in a cycle, or  
25 alternately so that they do not all start and end at the same point in time.

In the fourth aspect, a method may apply signals to a patient the signals being short component pulses applied  
30 to pairs of electrodes such that the component pulses are generated by successive electrode pairs in a cycle, the amplitude of the pulses being such that these pulses produce little or no activation of afferent fibres directly adjacent to one or more of the electrodes, but

the sum of the pulses in a target region of tissue distant from one or more of the electrodes is sufficient to produce an action potential in nerve fibres or some other physiological effect in excitable cells at this  
5 location.

Similarly, in the fifth aspect, the relative pulse widths and polarity of the component pulses is varied with respect to each other and optionally the number of  
10 electrode pairs used is varied to change the location and the coverage area of the region of the tissues that are stimulated.

Equally, in the sixth aspect the maximum component pulse widths on any given pair of electrodes, or individual  
15 electrodes with respect to the case or ground electrode of an implanted stimulator is determined with respect to each other to normalise the sensation on each electrode such that the perceived stimulation at the amplitude  
20 limit on each electrode pair is the same.

In any of the above aspects, the component pulses may be varied in time relative to each other such that they are separated by a few microseconds or overlap, save that  
25 they do not all start and end at the same point in time. Variation of the spacing between the component pulses changes the level and perceived location of afferent nerve activation for a given total charge delivered. The spacing may be optimised to provide the maximum level of  
30 perceived stimulation for minimum battery drain. The spacing may be a minimum of zero and a maximum of 20  $\mu$ s or 50  $\mu$ s or 200  $\mu$ s.

In any of the above aspects of the invention, the component pulses may be either:

5 a) Individual pulses, i.e. one component pulse applied to each pair of electrodes in respect of each composite pulse.

10 b) Trains of sub-component pulses, i.e. each component pulse is itself divided into trains of sub-component pulses with a space between each pulse, wherein the sum of the widths of each sub-component pulse in each train is equal to the pulse width of each equivalent component pulse, each train delivered to respective pairs of electrodes sequentially.

15 c) Trains of sub-component pulses, each component pulse divided into trains and these trains of pulses interleaved with other trains of pulses applied to other respective electrode pairs, so that the first sub-component pulse from the first train is applied to the first pair of electrodes, then the second  
20 sub-component pulse from the second train is applied to the second pair of electrodes and so on until the cycle is repeated and all sub-component pulses have been delivered.

25 The preferred arrangements are a) and c), the choice between the two determined by the length of the composite pulse and the desired maximum duration of any component or sub-component pulse, which is typically 2  $\mu$ s, or 4  $\mu$ s, or 10  $\mu$ s, or 20  $\mu$ s, or 50  $\mu$ s.

30

The relative duty cycle and/or amplitude of the component pulses may be determined and directed to the appropriate electrode pairs such that the desired stimulation field is produced. Additionally, each component or sub-

component pulse may be modulated by shortening the pulse by a percentage of the time slice allocated to the pulse in order to provide control over the effective amplitude of the pulse.

5

In another aspect of the invention, an implanted stimulator apparatus comprises a stimulator device and an electrode lead which contains embedded temperature sensors, preferably platinum resistance temperature devices or thermocouples. The stimulator device is provided with precision voltage and/or current measurement which is used to measure the temperature of the electrode array and/or leads, so that heating of the simulator apparatus or adjacent tissues due to induced currents caused by diagnostic imaging scanners, electrosurgical equipment etc. may be detected and the operator or surgeon may alter or terminate the procedure before unintentional tissue damage in the region of the implanted stimulator assembly occurs. The apparatus may also provide means for monitoring electro-magnetic interference induced on the implanted leads, so that action can be taken to minimise potential heating effects, for example in a magnetic resonance imaging scanner the patient can be oriented to minimise coupling between the scanner and the implanted stimulator leads. In leads which are not provided with embedded temperature sensors, the apparatus may additionally provide monitoring of the induced electro-magnetic interference in the leads so that electrode heating effects may be estimated. Additionally, the monitoring circuit that detects electro-magnetic interference on the leads may synchronise acquisition of temperature readings with periods of low interference, such as the periods during magnetic resonance imaging when the radio frequency

10

15

20

25

30

subsystem is not transmitting and gradient coils are static. The apparatus may also employ a two wire connection to a platinum resistance temperature device to detect changes rather than the absolute value of the electrode temperature. Note that this aspect, using embedded temperate sensors, may be used in combination with any or all of the first to sixth aspects discussed above.

- 10 The present invention addresses certain limitations or disadvantages of the prior art.

Applied to transcutaneous nerve stimulation, the relatively short duration of the component pulses immediately adjacent to each electrode allows higher currents to be applied to the skin without causing pain as a result of activating such cutaneous afferents as A $\delta$  and C-fibres.

- 20 Radkarishnan et al 2005 demonstrated that TENS signals only produce pain relief (in, for example, an acute arthritic knee) when deeply placed fibres are stimulated. When Radkarishnan injected local anaesthetic into the deep tissues pain relief from TENS was reduced. This might explain the differing reports of TENS in man, where perhaps TENS is only effective when patients are brave enough to use it at a high enough amplitude to penetrate deep tissues, an amplitude that many would say produces an unbearable amount of tingling. Because current density is attenuated the deeper the current penetrates into tissues, the problem with TENS is how can one employ surface electrodes in a conscious person and get sufficient current density to excite axons lying in deep tissues without first having a yet higher current density

in the superficial tissues - a current density often too painful to bear. The present invention offers a method of achieving high current density in deep tissues without causing painful stimulation of cutaneous afferents.

5

Applied to both transcutaneous and implanted stimulation, variation of the number of electrodes used in each array, the pairing of these electrodes and the component pulse width applied to each electrode allows the location and coverage area of the stimulation currents to be controlled and varied smoothly over an area of tissue covered by an electrode array. Preferably, the stimulation location and coverage area is controlled through a graphical interface and pointing device (for example a computer mouse, joystick, track ball or touch screen) which allows the surgeon or patient to control the electrode array in an intuitive manner, while the computer automatically decides the pairing and relative pulse widths etc. applied to the electrodes in the array.

20

The relatively short duration of the component pulses that are applied to each electrode also enables reduction in the effect of tissue capacitance, which causes the amplitude of a nerve stimulation pulse to decay in a few tens of microseconds. This droop arises with a voltage source as a droop in the current as the pulse is maintained, due to charging of capacitance in the tissues. By applying component pulses to an array of electrodes, the tissue capacitance in the tissue local to the electrodes is charged only by the individual component pulses. Potentially therefore, the invention allows the current flowing in deep tissues to be increased as compared with a device producing a single broad pulse.



Another advantage of the present invention is that the design of stimulators with many outputs may be simplified; this applies in particular to implanted  
5 stimulators. In the prior art, stimulators with multiple outputs are provided with an independent voltage or current source for each output, or alternatively with fewer voltage or current sources than the number of outputs, and a relatively low bandwidth means of  
10 multiplexing these sources to the outputs. In the former case, independent control of each output provides flexibility over the mapping of the notional stimulation field which may be provided by combining any number of available electrodes to produce the desired stimulation.  
15 However, the complexity of providing multiple outputs (typically sixteen or seventeen) is such that the voltage or current sources are typically constructed using analogue electronics in order to minimise space requirements, to satisfy the present trend towards  
20 smaller implants for ease of implantation. Analogue methods have the advantage that they can be implemented on chip and are therefore compact, but they have the disadvantage that they are inefficient, which wastes battery power. In the case where a few voltage or  
25 current sources are multiplexed onto many outputs, the few voltage or current sources may be constructed using switching electronics, such as switch-mode power supplies. This is efficient but bulky because external inductors or capacitors are required for each supply.  
30 This method has the disadvantage that the number of electrodes that can be controlled independently is limited by the number of current or voltage sources available.

In its simplest physical realization, the invention may require only a single current, voltage, charge or energy source to produce the desired composite pulse, which is then fed to a high speed switching network that breaks up  
5 the composite pulse into the component pulses that are applied to each electrode pair. The paths of the component pulses intersect in the tissues to reconstruct the composite pulse. The advantage of this method is that a single, efficient switching supply can be used,  
10 while providing independent control of the current or voltage applied to each electrode in the array. Such an apparatus may be made more efficient than the analogue current sources described in the prior art, thereby increasing battery life, which is particularly important  
15 in implanted devices. Such an arrangement also has the advantage of being very compact, as the single switching supply can be designed to operate directly from the power source or battery.

20 Ideally the bandwidth of the switching supply should be high enough to allow the amplitude of the component pulses to be controlled over the period of each pulse, which may be of the order of one microsecond. A high bandwidth current source, with minimal energy storage on  
25 the output side, or a means of either dissipating or regenerating into the battery excess energy stored on the output of the supply is desirable, but difficult to realise in practice due to the very high switching frequency required.

30 A simpler option is a fixed voltage supply, for instance fixed at the desired maximum output voltage of typically 15V in an implanted device, where the average voltage on each component pulse is varied by modulation of the

percentage of the time slice (i.e. the pulse width) allocated to each component pulse as a percentage of the total time available to each component pulse by control of the switching times on the switching network.

- 5 Feedback of current flowing during the application of the component pulse may be used to control this modulation, thereby controlling average current delivered during the pulse.
- 10 An improvement on the above is to provide a variable voltage supply, with relatively low bandwidth and consequently relatively low switching frequency, such that the voltage is essentially fixed during the period of the component pulse. The effective amplitude of each
- 15 component pulse is then adjusted by modulating the component pulse width as described above, either to achieve a desired average current level, voltage or charge per pulse.
- 20 A further variation is to employ a variable amplitude power supply, for example a voltage supply, and a sensor or sensors that measure the current and/or voltage for each component or sub-component pulse (either by averaging these throughout a pulse or by sampling them
- 25 one or more times), then feed back this data to modify the relative duty cycles of the component pulses so as to achieve the desired average current, voltage, charge or energy distribution among the respective electrode pairs and to modify the overall amplitude of the power supply
- 30 to achieve the desired average current, voltage, charge or energy in the composite pulse as a whole. The feedback loop may be implemented in the conventional way by applying correction to the respective duty cycles in real time, or on a cycle-by-cycle basis by applying

corrections to the next cycle on the basis of data from the previous cycle. The cycle-by-cycle method has the advantage that the corrections may be calculated using a relatively low performance microprocessor in the time  
5 between each cycle, whereas the real time method requires either analogue feedback or fast digital processors. The cycle-by-cycle feedback method is unable to compensate for variation in load impedance that occurs over the period of the stimulus pulse, but in practice impedance  
10 varies only relatively slowly so this is not a significant disadvantage.

A combination of the above schemes described in the preceding two paragraphs may be appropriate, particularly  
15 in the case where the apparatus has a power supply whose amplitude is variable within a restricted dynamic range. For example, in a voltage supply it may be convenient to vary the output voltage between the battery supply and the maximum output, but not down to zero voltage. If  
20 amplitude below the battery voltage is required, the component or sub-component pulses are pulse width modulated to reduce the effective amplitude of the applied pulses.

25 Another option is to provide a variable voltage power supply based on switching techniques, supplying an analogue current source which in turn feeds a switching matrix which directly synthesizes the component or sub-component pulses by connecting the appropriate electrode  
30 pairs in turn as required. The advantage of this approach is that the variable voltage source may be electrically efficient, providing only enough headroom voltage for the analogue current source to have good control. The combination of a switch mode variable

voltage supply with analogue current source is a good compromise between electrical efficiency and electronic complexity, while providing the high bandwidth and low noise that an analogue output stage may provide.

5

Other options include a fixed current supply with pulse width modulation of the switching matrix, or other combination of fixed or variable voltage, current, energy or charge control.

10

#### BRIEF DESCRIPTION OF THE DRAWINGS

Figure 1 shows an example of a typical bi-phasic square wave TENS waveform and the component waveforms A to E that are applied to each of the electrodes A to E in the linear array illustrated in figure 2.

15

Figure 2 shows a transcutaneous electrode array with five electrodes labelled A to E arranged in a linear array.

20

Figure 3 shows the current paths in tissues through a cross section of a notional homogenous limb wherein two linear electrode arrays according to figure 2 are applied transcutaneously on either side of the limb.

25

Figure 4 shows the relationship between peak pulse current at first onset of sensation and pulse width for a square wave pulse repeated at 100Hz applied transcutaneously via two square 50 mm x 50 mm electrodes placed mid forearm one on the anterior and the other on the posterior surface.

30

Figure 5 shows a voltage pulse applied transcutaneously, showing current droop during the pulse.

Figure 6 shows an example of a typical bi-phasic square wave pulse of 50  $\mu$ s duration and component waveforms A to E that consist of pulse trains of 2  $\mu$ s component pulses.

5

Figure 7 shows an example of a forward square wave composite pulse with a synthesized low amplitude recharge pulse and the resulting component waveforms.

10 Figure 8 shows an implanted stimulator and electrode assembly.

Figure 9a gives examples of typical implanted electrode lead configurations in the prior art, showing common  
15 electrode configurations at the distal end.

Figure 9b is a top sectional view of a typical stimulator connector arrangement with the lead inserted into the stimulator device.

20

Figure 10a shows an example of a focused stimulation field produced by a composite pulse using two cathodes and two anodes in a linear array and the basic component waveforms (the low amplitude recharge pulse or return  
25 pulse is omitted for clarity).

Figure 10b shows an alternative arrangement of the component pulses associated with the example in figure 10a comprising high frequency component waveforms,  
30 consisting of trains of sub-component pulses.

Figure 10c shows an alternative arrangement of above comprising component waveforms with extended inter-pulse spacing.

Figure 10d shows an alternative arrangement of above comprising high frequency component waveforms with extended inter-pulse spacing.

5

Figure 10e shows an alternative arrangement of above comprising overlapping component waveforms.

Figure 11 shows an example of a side by side array of sixteen contacts together with the basic component waveforms (the low amplitude recharge or recharge pulse is not shown).

Figure 12a shows an example of a focused stimulation field produced by a composite pulse using six electrodes (three electrode pairs) from an implanted array of sixteen contacts together with the associated component waveforms (the inter-pulse space not shown to scale).

Figure 12b shows alternate high frequency component waveforms (with the inter-pulse space not to scale) for the arrangement shown in figure 12a.

Figure 13 shows an implanted array similar to figure 12a with ten electrodes (five electrode pairs) activated to produce a more diffuse composite stimulation field than figure 12a.

Figure 14 shows a composite stimulation field centred over electrode E1 on the left side of the array.

Figure 15 shows a stimulation field generated by two groups of electrodes, group one: E1-E2, D1-F2, F1-D2, group two: F1-F2, E1-G2, G1-E2, activated in sequence.

Figure 16 shows an example layout of a touch screen from a computer based programming system for the stimulator apparatus.

5

Figure 17a shows a finite element model of current flows in a two dimensional homogeneous resistive medium, illustrating the voltage distribution.

10 Figure 17b shows current vectors associated with the voltage distribution in figure 17a.

Figure 18 shows a block diagram of the apparatus.

15 Figure 19 shows a paddle lead with embedded temperature sensing.

Figure 20a shows an overall arrangement of a percutaneous lead with embedded temperature sensor.

20

Figure 20b shows a section through the electrode contacts of the above percutaneous lead with embedded temperature sensor.

25 Figure 21 shows a two wire resistance temperature device interface.

#### DETAILED DESCRIPTION OF THE INVENTION

30 The invention can be illustrated by considering examples of its application to transcutaneous and implanted stimulators. The figures illustrating electrode arrays may be considered to be representative either of a clinical situation or of a corresponding mathematical



model of the tissues used to derive the appropriate component waveforms. The pulses in the figures can be considered to be representative of current, voltage, charge or energy, depending on the method of control used  
5 by the stimulator device.

Referring to figure 1, waveform 01 is a composite waveform required to affect the behaviour of excitable tissue in, for example, a transcutaneous nerve  
10 stimulation application. The waveform in this example consists of balanced forward and reverse composite pulses, the forward pulse of duration  $t_{fp}$  (which may typically be 50, 100, 500 or 1000  $\mu s$ ) and the reverse pulse of duration  $t_{rp}$ , with  $t_{fp} = t_{rp}$ , so that the net  
15 current flowing in the tissues is zero. Net zero current flow is preferable because it minimises ionic transport between the electrodes which can cause skin reactions. The forward and reverse pulses may be separated by an interpulse spacing  $t_{ip}$ , which may be zero. The composite  
20 waveform, 01, is broken into five component waveforms, labelled A to E. In this example, the resistance between any two pairs of electrodes is assumed to be equal and the desired amplitude of each component pulse of the component waveform is equal, consequently each component  
25 pulse is of equal duration. Each component waveform consists of a forward pulse of  $t_{cp}$   $\mu s$  duration, where  $t_{cp} = t_{fp}/5$ , followed  $t_{fp} + t_{ip}$   $\mu s$  later (measured between leading edges) by a reverse pulse of  $t_{cp}$   $\mu s$  duration. Each component waveform is identical except that it is  
30 delayed in time by  $t_{cp}$   $\mu s$  from the start of the previous component waveform. Adding component waveforms A through E together produces the original composite waveform, 01.

Figure 2 shows a linear electrode array consisting of five electrodes, 03, mounted in this example at 20mm pitch on an insulating backing sheet, 04. Each electrode in the array is labelled A to E, corresponding to the component waveforms in figure 1.

Figure 3 shows an example application of two linear electrode arrays labelled 06 and 07 of the type shown in figure 2. Each of the electrode arrays is positioned either side of a limb, 08, such that the component waveforms, A to E, are applied across electrode pairs A1-A2 etc. The respective current path through the tissues for each of the electrode pairs is illustrated approximately by the dotted lines shown, such as current path E1-E2, shown in bold.

It can be seen that the current paths of the component waveforms cross in the tissues in the area demarked by the shading. Afferent nerves or other excitable tissues in the shaded region will tend to be affected by a composite waveform similar in duration to the composite waveform, 01, in figure 1, whereas the afferent nerves or other excitable tissues in regions outside this shaded region will tend to be affected by the by individual component waveforms (02 in figure 1) for a correspondingly shorter duration.

The diagram is of course an idealised case assuming that the limb is homogeneous in cross-section; in a clinical situation the current will follow a path dictated by the relative conductivity of different tissues and bone etc. In both cases, the current path spreads out as it transits between the two electrode pairs, with its start and end point defined by the arrangement of the electrode

pairs. A crossing arrangement as shown provides a point of focus for the stimulating waveform in the deep tissues, whereas an alternative non-crossing arrangement (where each electrode pair is opposite each other

5 analogous to rungs on a ladder) provides a more distributed region of stimulation. It is also possible to vary the shape of the region of stimulation and the centre of this region by varying the relative duty cycle of the component waveforms and the pairing of electrodes.

10

The effect of pulse width on sensory threshold is illustrated by the graph in figure 4. This graph shows the variation of peak pulse current with pulse width at the threshold of sensation. The pulse current was

15 recorded between one pair of electrodes at the amplitude at which a test subject detects initial onset of sensation. The pulse was a square wave voltage pulse repeated at 100 Hz applied transcutaneously using two square 50 mm x 50 mm electrodes, placed mid forearm one

20 on the anterior and the other on the posterior surface. This example is for one subject, an adult male. It will be appreciated that the current will vary with subject and with the type and placement of the electrodes. In particular, implanted electrodes require much less

25 current to cause sensation because of the lack of skin resistance and the typical smaller size of the contact area, thereby providing higher current density at the electrode. Nevertheless, the general shape of the curve remains the same, an approximately exponential decline in

30 stimulus current as pulse width is increased.

For transcutaneous application, selection of appropriate component pulse widths and stimulation intensity, together with placement of the array electrodes so that

the currents in deep tissues tend to add, can generate action potentials in the deep tissues without activating the cutaneous afferents.

5 However, it is possible to activate the cutaneous afferents by a train of short pulses which individually do not have sufficient energy to generate an action potential, as they are individually of insufficient energy to activate voltage gated channels on the nerve,  
10 but they may do so by summation. Because of the close proximity of the electrode segments in the array, it may therefore be that the pulses from adjacent segments will add together. In the design of a transcutaneous stimulator which has the object of minimal activation of  
15 cutaneous afferents, the electrodes in figure 3 are activated in a sequence that ensures that no two adjacent segments are activated in turn. The labelling of the component waveforms in figure 1 and their corresponding electrodes in figures 2 and 3 is an example of such a  
20 sequence. It is also preferable that each segment in the array shown in figure 2 is separated by a few mm.

In this example, tissues directly beneath the electrode segments are subject to a pulse width that is no more  
25 than one fifth of the composite pulse duration. At particular stimulation intensity this may be insufficient to activate the cutaneous afferents. However, in deeper tissues, the applied signals tend to flow through the same tissues. The individual short pulses will add  
30 together in turn to reconstruct the longer pulse of the form of composite waveform, 01, in figure 1. This leads to an interesting effect whereby it is possible to stimulate a nerve innervating a region distant from the site of placement of the electrodes, without directly

stimulating the tissues directly under the electrode arrays.

Furthermore, in a system that includes balanced forward  
5 and reverse pulses as illustrated in figure 1, the  
spacing between the forward and reverse pulses (of a  
given amplitude and duration) affects stimulation  
intensity. Perceived stimulation intensity increases as  
the spacing increases from zero to about 20  $\mu$ s, stays  
10 relatively constant to about 200  $\mu$ s and decreases as the  
spacing is increased further still. This effect is most  
apparent for pulses of a few microseconds duration, such  
as typical component pulse durations of 1 to 20  $\mu$ s. In a  
system which has zero net current flow, but requires  
15 minimal activation of cutaneous fibres, it is preferable  
therefore that the reverse pulse is separated from the  
forward pulse in time, or alternately occurs immediately  
after the forward pulse. The latter is difficult to  
achieve because the reverse component pulse in must be  
20 separated from the forward pulse by at least the duration  
of the composite pulse (measured between leading edges).  
Consequently, in a typical system where the composite  
pulse repetition rate is 100 Hz, the spacing may  
preferably be such that the balancing reverse pulses  
25 occur half way between the forward pulses, i.e. 5,000  $\mu$ s  
after the leading edge of the forward pulse. An  
alternative approach is to provide the balancing reverse  
charge by means of a gradual reverse charge in between  
forward pulses. Because of the low mark-space ratio of a  
30 typical nerve stimulation waveform, this balancing  
reverse charge can be arranged to occur at an amplitude  
that is well below the level at which afferent fibres are  
activated.

In one application of the five electrode array described, two electrode arrays are placed directly over a painful region, for example an injured knee, and the stimulation intensity is increased until the patient determines it is at the maximum comfortable level. At the maximum comfortable level with a five electrode array, both cutaneous and deep afferents are typically firing. A comparison between the array device described herein and a standard TENS device with electrodes of equivalent area shows that users could not easily differentiate between sensations generated by cutaneous and deep afferents. Some subjects describe the array device to be "more penetrating", but the difference in sensation between the two devices is not marked. However, at equivalent maximum comfortable levels, the current flowing in the tissues from the array device is typically three times that of the standard TENS device. An advantage of this method is therefore that the pain threshold when measured in terms of current applied is increased - in this example three-fold.

Another advantage of the method is that capacitive effects in the tissues are reduced. These effects are illustrated in figure 5 for a short pulse of 2  $\mu$ s. Because of the capacitance of tissues, a square voltage pulse produces a current that droops during the pulse and on removal of the voltage produces a return current pulse. As the pulse width is extended to typical composite pulse lengths of 50 to 100  $\mu$ s, this effect produces a marked reduction in charge delivered during the pulse. Because the component pulses are shorter than the composite pulse, current in deeper tissues can be maintained at a higher level than a traditionally derived

broad duration pulse such as that produced by a TENS device in the prior art.

A further benefit in this regard is obtained by breaking the component pulses into in trains of sub-component pulses. This is illustrated in figure 6, wherein a desired composite waveform, 10, with equal forward and reverse pulses of 50  $\mu$ s duration with zero inter-pulse spacing is broken into five component waveforms, 12, A to E, each consisting of a train of 2  $\mu$ s sub-component pulses, 11, repeated at 10  $\mu$ s. Even though most figures in this text show the basic (i.e. single pulse) component waveforms for clarity, the higher frequency pulse train form is the preferred method for long composite pulse durations where the component pulses might exceed a desired maximum duration. In the preferred embodiment, the sub-component pulse trains are derived so that the minimum pulse width of any sub-component pulse is 0.1 to 0.5  $\mu$ s and the maximum is between 2 and 20  $\mu$ s.

The pulse train waveform might be expected to further reduce activation of cutaneous afferents in favour of deep afferents. This is indeed the case, but in practice this effect is not as marked as would be expected from inspection of the graph in figure 4 because of the aforementioned summation process that results in generation of an action potential from a series of very short pulses that might not themselves normally be expected to cause activation. However, the method does allow higher current to be applied to the skin without discomfort around the electrodes.

With a transcutaneous arrangement described above, there is an inevitable compromise between the number of

electrodes in the array, the complexity of the stimulator device and weight of the cable that connects each electrode array to the stimulator. One means of overcoming cabling weight is to construct a switching matrix on a flexible substrate on the back of the electrode array. This can operate using a two wire supply from the stimulator and multiplex the signal to the array on the basis either of time from start of the composite pulse, or using a three wire supply with a separate clock signal from the stimulator.

In previous examples, the composite pulse consists of balancing forward and reverse pulses of the same amplitude and duration. Although not an essential feature of this invention, it is preferable that the sum of forward and reverse charges is zero to prevent ionic transport between electrodes, although the shapes of the forward and reverse pulses do not have to be the same. Figure 7 illustrates such an example, in this case the forward pulse, 13, is the same as shown in figure 1, but zero net charge is provided by a gradual reverse recharge, 14, between forward pulses. Typically, the forward pulse accounts for 1% or less of the total cycle duration, so the reverse recharge can occur during the relatively long quiet period between forward pulses at well below the amplitude which activates nerves.

The reverse recharge pulse can be achieved by simply generating the desired forward pulse with a suitable signal generator, and coupling this to the tissues via a series capacitor, although the recharge should preferably be controlled so that it does not interfere with other component pulses, which introduces additional complexity.



Alternately and preferably, the reverse pulse can be generated explicitly by a signal generator with bipolar output, or a mono-polar signal generator with a suitable switching matrix on the output. Figure 7 illustrates an idealised current waveform in such a system, the desired composite stimulus pulse, 13, is balanced by a reverse recharge pulse with the same area under the curve, 14. The forward stimulus pulse would normally be negative going (i.e. the cathode). For clarity, the positive return recharge pulse shown in the drawing has five times the duration of the forward pulse and one fifth of the amplitude. However, in a practical implementation the return pulse would only be a single digit percentage of the amplitude of the forward pulse and consequently of longer duration, sometimes occupying most of the quiet period between forward pulses. Preferably, in apparatus without a series capacitor on the output, the output stage includes a circuit that integrates forward and reverse current flow on each electrode as a cross check that the net current flow is maintained at zero. The error from this integrator is fed back into the system to modify the duration of the return pulse on each channel.

Each forward component pulse, 16, is derived as described previously, based on the desired stimulus field (in this example all component pulses are of equal magnitude but this should not be construed as limiting). The reverse component recharge pulse, 17, is calculated to have the same net charge as the forward component pulse and delivered in turn as illustrated. The component waveforms, 15, may be delivered to the electrode array as previously described in figures 2 and 3, or if desired the anode may be comprised of one larger electrode, with the active array just at the cathode (i.e. that

delivering the negative going forward component pulses). This provides for a simplification of the electrode array and output electronics in the stimulator apparatus.

5 Figure 8 illustrates a typical configuration of an implanted stimulator. The implanted stimulator comprises the stimulator device, 18, which contains the electronics, battery, charging electronics and signal generator(s) contained within an enclosure, 19, which is  
10 typically a hermetically sealed titanium shell. On top of the device, a connector assembly provides connection to one or more leads, 21, (shown shortened in the drawing) which terminate in one or more electrode arrays, 22. The enclosure, 19, if made of conductive material  
15 may also be used as an electrode and optionally may form part of the available array of electrodes. A typical modern implanted stimulator will have provision for a number of electrode contacts, typically sixteen arranged as two sets of eight outputs. Applications of implanted  
20 stimulators include spinal cord stimulation, where the electrodes are implanted in the epidural space, and deep brain stimulation, where electrodes are implanted in the brain.

25 Examples of known implanted lead types for spinal cord stimulation are shown in figure 9a, each comprising a number of electrode contacts in an array. Lead types include the percutaneous lead, 23, which has a number of contacts in line, 24, spaced regularly or irregularly on  
30 a flexible lead. The percutaneous lead is so named because of its ease of implantation using a hollow needle introducer as a guide. Other types of lead include the paddle lead, 25, so named after its shape. This type of lead is more invasive to implant, but has the advantage

that it is less prone to migration once implanted. Many different types of paddle leads exist, including types with a multiplicity of electrodes arranged in a predefined array, 26, and types with two or more

5 individual paddles connected to a common lead, 27. In each case, the individual contacts have respective small diameter wires embedded in an insulating sleeve that provides electrical connection to a stimulator device.

One, two or more leads may be installed to cover a  
10 particular tissue or nerve area. To facilitate use of hollow needle introducers for percutaneous leads (figure 9a, 23), the diameter of the connector to the stimulator device should ideally be the same as the lead.

15 A typical stimulator connector arrangement is illustrated in figure 9b. The drawing shows the lead, 32, inserted into the stimulator device. A strain relief, 31, is provided to reduce flexing of the lead at the exit point from the stimulator. A series of spring loaded contacts,  
20 30, provide electrical connection between the electrodes and the stimulator outputs. A clamp, 29, is adjusted by a set-screw to secure the lead. The clamp may be used as an additional contact if required.

25 Whatever the target tissue area, implantation is an inexact science and therefore a multiplicity of contacts allows the neurosurgeon to span a particular area of tissue and experiment with different combinations of electrodes in the array to produce a desired therapeutic  
30 effect. Migration of the lead over time or changes in the contact impedance due to the accumulation of scar tissue around the implanted electrodes may necessitate reprogramming of the electrode combination over time. Furthermore, the electrode spacing may be physically

large when compared with the area of tissue to be stimulated, so a means of controlling excitation that provides variation of the point of stimulation to a finer resolution than the electrode pitch is preferred. The surgeon (or patient) should have control of a number of parameters in order to optimise the stimulation pattern, these include the amplitude of the applied stimulation (absolute current, voltage, charge, energy or a normalised value of these based on contact impedance or perceived sensation), the pulse width of the composite pulse, the repetition frequency of the pulse, the location of the centre of the area of stimulation and whether the stimulation pattern is tightly focused around the centre, or distributed more widely in the tissues.

In order to control the position of the centre of stimulation according to this invention, a composite waveform is separated into two or more component waveforms. The duty cycle of the pulses of the component waveforms and the number of electrodes recruited are controlled so that the component waveforms recombine in the tissues to reconstruct composite pulses forming the composite waveform in the desired location over a desired coverage area.

The simplest example is a linear array, such as a percutaneous or paddle lead (figure 9a, 23 and 25). Figure 10a shows a linear array of eight contacts labelled A to H, each represented by a circle in the figure, together with the basic component waveforms with the aforementioned low amplitude recharge pulse or return pulse not shown for clarity.

With such an array, it is desirable that the centre of the area of stimulation is controllable seamlessly from top to bottom of the array. In figure 10a, the centre point is at approximately 3/10ths of the distance from electrode F to electrode E, indicated by the cross, 33 which shows the desired centre of stimulation. In practice, the stimulation is perceived over a diffuse area (the "stimulation field") indicated by the shading, 34. In most cases the cathode is preferred electrode for nerve stimulation (although it should be noted that sensation can occur at both cathode and anode). This example uses a waveform of the type illustrated in figure 7, consisting of a forward pulse delivered at the cathode (indicated by the minus signs over electrodes E and F in figure 10a), with a low amplitude reverse charge which is not shown but would be similar to that illustrated in figure 7.

The anodes in figure 10a are electrodes H and C in the array, marked with a plus sign. The desired composite stimulus waveform is a square wave pulse, 35. In order to derive component waveforms, 36 and 37, some assumption about the electrical characteristics of the tissues must be made. In the simplest case we could, for example, reasonably assume that the perceived point of stimulation is proportional to the duty cycle of the two cathodes, E and F. Hence, the component waveforms, 36 and 37 respectively in figure 10a are active for 30% and 70% of the forward stimulus pulse time,  $t_{fp}$ .

Figure 10b illustrates a refinement whereby the component waveforms, 39 and 40, are further subdivided into higher frequency pulse trains with the same 30% and 70% duty cycles. As previously discussed, with long composite

pulses, this is the preferred method of applying component pulses as it tends to reduce the effects of tissue capacitance and ensures that the nerves in the region of electrodes E and F perceive the two component waveforms as one. In this example, the component waveform, 39 is applied to cathode E with both anodes C and H active, and component waveform, 40 is applied to cathode F also with anodes C and H. The choice of anode(s) has an influence on the current path and the current density in the region of the array; in some instances it may be appropriate to use the enclosure of the stimulator as the anode, or only one other electrode in the array to provide a more tightly controlled current path.

Using this arrangement, the centre of the stimulation field, 33, may be varied smoothly up and down the array, by controlling the relative duty cycle applied to each electrode. Furthermore, by recruiting additional cathodes, D and G, and sharing the duty cycle between four electrodes, it is possible to provide a more diffuse stimulation field, covering a wider area. It is also possible to extend this method to cover multiple electrodes implanted in a line.

Figure 10c illustrates a further variation in the component waveforms wherein delivery of component pulses is delayed by an inter-pulse period  $t_{ip}$ . As before, the sum of the component pulse widths, 42 and 43, ( $t_{cp1} + t_{cp2}$ ) is equal to the total length of the forward composite pulse,  $t_{fp}$ , 41, and the relative duty cycle is identical. The effect of the interpulse spacing,  $t_{ip}$ , is to increase the level of nerve activation for a given composite pulse duration and amplitude. The effect increases up to  $t_{ip} \approx$

20  $\mu$ s and is useful as it increases the battery life of the stimulator at a particular level of perceived sensation.

5 The method is also applicable to the high-frequency case wherein each component pulse is broken up into pulse trains as previously discussed, and is particularly advantageous if the pulse width of the resulting sub-component pulses are in the range 1  $\mu$ s to 5  $\mu$ s, because  
10 the effect of increasing interpulse spacing is maximized within this range. This is illustrated in figure 10d, wherein the high frequency component waveforms, 44 and 45, each have a pulse width of one third of the length of those illustrated in figure 10c, and the interpulse  
15 spacing is reduce to  $t_{ip}/3$  thereby completing the cycle in the same overall time.

Figure 10e illustrates a further variation in the application of component waveforms. In this example the  
20 notional composite stimulus waveform, 46, is the same as previously and the component waveforms, 47 and 48 are of the same duration and amplitude, but rather than be delivered in sequence they start at the same point in time, but end at different times.

25 Another variation is to fix the duty cycle, but vary the amplitude of the pulses to provide the desired sharing of the charge or energy of the composite pulse between the respective electrodes. This method has the disadvantage  
30 that it requires either multiple supplies, or one very high bandwidth supply.

Figure 10a-10e and figure 11 below do not show the reverse pulse for clarity, but such a reverse pulse,

either a low amplitude pulse similar to that illustrated in figure 7, or a balancing reverse pulse similar to that illustrated in figure 1 would typically form part of the waveform.

5

Figure 11 illustrates another arrangement of electrodes, consisting of two arrays of eight electrodes side by side. This arrangement is useful for instance as a treatment of bilateral pain in spinal cord stimulation applications. In the example, four cathodes: E1, F1, E2 and F2 are used with a duty cycle (percentage of the stimulus waveform, 50) of 35% on E1, 35% on F1, 15% on E2 and 15% on F2. The resulting bias towards a higher duty cycle on the left electrodes to produces a stimulation field with a centre of stimulation that lies in to the centre left of the geometric centre of the four cathodes. The selection of anodes has a lesser influence on the perceived stimulation pattern, in this example the anodes are C1, C2, H1 and H2, and are connected in parallel by the switching matrix in the stimulator device. The component waveforms, 51, 52, 53 and 54 are applied in sequence to the four cathodes. In this example, it can be seen that a similar result could be achieved by applying a 70% duty cycle waveform to E1 and F1 connected in parallel, and a 30% duty cycle waveform to E2 and F2. In practical applications, there is seldom a unique solution to the component waveforms and electrode pairing given a desired stimulation pattern and centre of stimulation.

30

The previous figures are based on the assumption of a waveform with a forward negative pulse and low amplitude recharge pulse as discussed. An alternative approach is to use a bi-directional balanced waveform consisting of



equal forward and reverse pulses as previously discussed and illustrated in figures 1 and 6. In these cases the anodes and cathodes effectively reverse every half cycle. Preferably, the waveform has an inter-pulse spacing ( $t_{ip}$  in figure 1) that is selected so that the reverse pulse and forward pulses are equally spaced in time. With a balanced bi-phasic waveform, the preferred method is also to couple pairs of electrodes, or small groups, rather than have a number of anodes connected in parallel at one time. This provides more precise definition of the current path between the electrodes and therefore better control of the location and coverage area of the composite waveform. Figures 12 to 15 show an example of such a system implemented in an array consisting of two rows of eight electrodes.

Referring to figure 12, the centre of the stimulation field, 55, is marked by the cross. The desired composite stimulus waveform, 56, is broken up into three component waveforms, 57, 58 and 59. As previously discussed, these waveforms may represent either current, voltage, energy or charge depending on the type of output driver used in the stimulator. The component waveforms are fed respectively to electrode pairs: D1-F2, E1-E2 and F1-D2. The target area of tissue is indicated by the shaded region, 60. The component waveforms in figure 12a illustrated are three pulses each accounting of 33% of the composite pulse. In practice, as previously discussed, it is preferable to further subdivide the component waveforms into a series of shorter pulses with the same total duty cycle, delivered in a train as illustrated in figure 12b.

Figure 12 illustrates a focused stimulation field; it has a relatively low coverage area as a proportion of the area of tissue covered by the entire array.

5 If a less focused stimulation field is appropriate, this may be achieved by recruitment of two additional electrode pairs, C1-G2 and G1-C2, as shown in figure 13. This causes the notional stimulation field to spread along the vertical axis. In this case, five component  
10 waveforms, figure 13, 66, are derived from the composite waveform, 65, and applied to the five electrode pairs: D1-F2, E1-E2, F1-D2, C1-G2 and G1-C2.

Now assume that the centroid of the stimulation field in  
15 figure 12 should be repositioned to the left. Figure 14 shows three component waveforms, similar to figure 12, but differs from the two previous figures in that one electrode, E1, is part of the electrode pairing in all three component waveforms. Consequently, this electrode  
20 carries current for the full duration of the composite pulse, 68, whereas the other three active electrodes, D2, E2 and F2 carry current for only 33% of the time.

The figures 12, 13 and 14 can be considered to be three  
25 "reference" stimulation patterns, representative of three specific cases, i.e. focused stimulation in mid-line of the array, distributed stimulation in the mid-line of the array and focused stimulation to one side of the array.

30 In practice, the surgeon or patient preferably should not be concerned with the specific electrodes and component waveforms that are used to generate the stimulation pattern. These should be derived automatically from high

level input of the desired location and coverage area of the stimulation field using an intuitive user interface.

In the case of sequential delivery of the component  
5 pulses, as illustrated in many of the preceding figures, it is reasonable to assume that the various reference stimulation fields described in figures 12, 13 and 14 can be added together or interpolated to produce a desired field that represents an intermediate case.

10

Figure 15 illustrates one such intermediate case. In this example, the surgeon has commanded the centre of stimulation, 73, to reposition along the midline of the array in the direction indicated by the arrow, 74. This  
15 may be achieved by duplicating the group of six electrodes first illustrated in figure 12 (electrode pairs D1-F2, E1-E2 and F1-D2 illustrated by the dotted lines showing current path) at a distance one pitch down on the array of electrodes (i.e. electrode pairs E1-G2,  
20 F1-F2 and G1-E2 illustrated by the dashed lines showing current paths). The duty cycle is then divided between these two respective groups in proportion to the desired displacement of the centre of stimulation. The resulting six component waveforms, 75, are shown in figure 15. It  
25 will be noted that as in the previous example, one electrode may form part of one or more pairings to produce the desired stimulation field. Furthermore, as before, if any component waveform contains pulses that exceed the maximum desired pulse width (typically 2  $\mu$ s,  
30 or 4  $\mu$ s, or 10  $\mu$ s, or 20  $\mu$ s, or 50  $\mu$ s) they are preferably further subdivided by breaking each component into equivalent sub-component pulse trains of the same duty cycle as shown in figure 12b.

The preceding figures deal with only one configuration of electrode array and a limited number of ways of pairing the electrodes within that array. Other combinations are possible, for example the current paths need not cross as  
5 in figures 12 to 15, but might consist of a ladder arrangement of electrode pairs such as D1-D2, E1-E2, and F1-F2. Furthermore, it is preferable in some instances to use the enclosure of the stimulator (figure 8, 19) as one of the electrode pairs. This produces a stimulation  
10 field that tends to penetrate further from the site of the electrodes thereby allowing tissues some distance from the implanted array to be stimulated. The described method of controlling the stimulation field by means of component waveforms is equally applicable to this  
15 configuration.

If available, the stimulator enclosure is also a useful electrode for measuring contact impedance. Typically, contact impedance is measured by applying a known current  
20 or voltage to the enclosure and measuring the corresponding voltage or current for each electrode in turn. Similarly, impedance can be measured between specific pairs of electrodes. One advantage of using the enclosure as one electrode for sensing impedance is that  
25 a high precision current sensor can be implemented on this one output, which does not need to be duplicated on the other multiple outputs. If the enclosure is not used in the array, a high value sense resistor is one option. The enclosure output may also employ AC sensing current,  
30 either sinusoidal or square wave. This eliminates measurement error due to differing electrode potentials of the metals in the enclosure and electrode contacts.

Contact impedance may change over time as scar tissues build up around the implanted electrodes. In the figures, component waveforms have been based on the assumption that each electrode has the same quality of contact with the tissues. Where variations in contact impedance are observed and in particular when the composite pulse is a voltage output, it may be appropriate to vary the ratio of applied duty cycles to the electrode outputs so that different impedances are compensated. This process is referred to as normalisation.

A further application of normalisation is related to sensation. In both current and voltage controlled systems, it is preferable that each electrode is calibrated with respect to the enclosure electrode, so that all electrodes produce a similar level of perceived sensation at maximum output. To achieve this, each output in turn is activated and the patient adjusts the output so that it feels similar to the others, these relative settings are stored and used to normalise the system by weighting the ratio of duty cycles of the component waveforms.

Preferably, the surgeon is provided with a computer based programming system that graphically depicts the electrode array(s) in use in their relative locations. The programming system should include a series of pages to facilitate set-up of the device, this should include as a minimum a set-up page, a diagnostics page, a stimulation page and a program creation page.

The set-up page allows basic parameters to be configured, such as: selection of pulse type (for example balanced

forward and reverse pulses, or forward pulses with a slow recharge); use of the stimulator enclosure as an electrode; and the configuration of the array (e.g. single in line, dual in line, side-by-side, wide or narrow spacing and the various types of paddle lead configurations).

The diagnostics page reports on the status of the stimulator device, including parameters such as battery status, error log, serial number etc. It allows contact impedance to be measured, relative to the stimulator enclosure or any other group of reference electrodes. This measurement may be achieved by applying a current or voltage to the enclosure, and measuring the corresponding voltage or current on the electrode in question.

The diagnostics page also includes the aforementioned sensation normalisation test mode. One method is to apply a reference waveform to each electrode contact in turn, with the stimulator enclosure acting as the anode. The amplitude of the reference waveform is increased slowly until the signal is just perceptible to the patient. The relative amplitude on each electrode is then available if required to adjust the duty cycles during stimulation so as to normalise the level of sensation from each electrode. A second method for bipolar balanced waveforms is to apply the reference waveform between appropriate pairs of electrodes that are used to build up stimulation patterns. This second method may produce a more accurate result, but may involve many pairs of electrodes.

The diagnostics screen should also be able to display historical impedance and sensation normalisation data

which is stored either on the programming system, the patient controller, or the stimulator. This allows changes over time can be tracked, which for example may be used to identify formation of up scar tissue around  
5 the electrodes.

The stimulation page allows the patient or surgeon real time control of the stimulation field and other key parameters. An example programming screen is illustrated  
10 in figure 16. This consists of a graphical representation of the array which changes to match the configuration of the implanted array, such as in-line and side-by-side. The page also allows control of often used parameters such as amplitude, composite pulse width,  
15 pulse rate and coverage area.

By means of a pointing device such as a mouse, touch screen, joystick or other such device the surgeon or patient directs the centre of the stimulation field, 77,  
20 on a graphical illustration of the array, using sliders, 78. The example shown is designed primarily for use on a touch screen but dedicated physical controls such as a joystick might also be used, with or without a display. The system provides a means of storing a series of  
25 stimulation points, 79, which are later combined using a program creation page into programs that define a particular set and sequence of stimulation points to achieve a desired therapeutic result.

30 The interface provides a graphical representation of the stimulation field, 80, and indicates which electrodes are active, 81. Optionally, the graphical display could use a external data source for the location of the array and the nearby tissue structures, for example an image of the

spinal column and the actual implanted electrodes produced from a medical imaging system such as a Computed Tomography (CT) scanner.

- 5 The programming page allows stimulation points to be combined into treatment programs, which are preferably given names that are meaningful for the patient.

Once programming is complete, control of the implanted  
10 stimulator is provided by means of a patient controller with a small LCD or OLED or other compact display screen that may provide only basic control, such as selection of a program by name and control of the amplitude of stimulation. The programming unit and patient controller  
15 communicate with the stimulator device via wireless telemetry. In a preferred embodiment the patient controller (or the charging device for an implant) is provided with a USB interface that plugs into the programming unit computer. The patient controller (or  
20 charging device) then provides the wireless bridge to the implanted stimulator unit. Storage of programs may either be on the patient controller or the stimulator device. In the preferred embodiment programs are stored on the patient controller and downloaded to the  
25 stimulator device for execution as required.

Component waveforms are derived from data entered by the surgeon or patient input into the programming system. Key user entered parameters are: composite pulse width,  
30 centre of the stimulation field, coverage of the stimulation field, type of waveform required (i.e. with balanced forward and reverse pulses or slow reverse recharge), configuration of the electrode array, and the use (or not) of the stimulator enclosure electrode. In



addition, the process requires assumptions to be made about electrical characteristics of the tissues.

Complexity of calculating component waveforms varies with  
5 the number of electrodes and physical arrangement of the array, the simplest being a linear array as illustrated in figure 10a with only the forward pulse to consider. In this case derivation of the component waveforms is a trivial task provided that the tissues are assumed to be  
10 homogeneous.

Complexity increases with the transcutaneous array illustrated in figure 3 and the implanted array illustrated in figures 11 and 12. In more complex cases,  
15 there may not be a unique solution to a particular set of inputs.

In the preceding text, one method for calculating component waveforms is to use a set of reference  
20 stimulation fields such as those described for a side-by-side array in figures 12, 13 and 14 which are added together or interpolated between to produce a desired field that represents an intermediate case. This method has a very low computational overhead, which is ideal for  
25 real-time control of the stimulation field such as required for the stimulation set-up page in the programming system described above.

An extension to the reference stimulation field method is  
30 to consider current paths from the electrodes in the array and arrive at combination of these paths that gives a best fit to the parameters input by the surgeon. Current paths may be calculated using a finite element model of the tissues, either in two or three dimensions.

By way of example, a finite element method for combinations of electrode pairs with sequential delivery of the pulses is described below. At its simplest, the finite element model consists of a two dimensional network of resistors of arbitrary value, either arranged as a series of squares or triangles with resistive elements on the sides of the elements and nodes at the  $n \times m$  vertices. For each electrode pair in an array, a nominal current is applied and the resulting two dimensional current distribution produced by iteration based on the assumption that the currents flowing into and out of each vertex sum to zero, with the exception of those vertices that represent active electrodes in the array. Solution of this by iteration produces an  $n \times m$  matrix which is a current distribution map containing current vectors at each point in the matrix for a specific electrode pair.

A pictorial example of this is shown in figures 17a and 17b. Figure 17a shows the voltage distribution between two electrodes, with a +1 and -1 (82 and 83 respectively) unit voltage applied to the electrodes, based on a 20 by 20 element model with unity element-to-element boundary resistance and an infinite resistance between the edge elements and the outside world. Figure 17b shows a vector plot of the current flow in the matrix, where each vector represents a direction and magnitude for the predicted current at the centre of each element. The two electrodes are denoted 84 and 85.

A library of matrices is produced for each electrode array, representing each pairing that may be employed. These matrices need not be calculated in real-time while

the surgeon or patient moves the centre of stimulation, but can be pre-calculated and stored on the programming system computer. Derivation of the component waveforms is achieved by finding the values of the coefficients that define weighted sum of the available matrices that provide the best fit to the desired stimulation field. For example, if  $[d_{ij}]$  is a matrix of dimensions  $n \times m$  that defines the desired stimulation field and  $[a_{ij}]$ ,  $[b_{ij}]$  etc. are  $m \times n$  matrices that define current distribution maps in possible electrode pairings, we find the values of the coefficients  $x_1$ ,  $x_2$  etc. that satisfy:

$$[d_{ij}] \approx x_1[a_{ij}] + x_2[b_{ij}] + x_3[c_{ij}] \dots$$

The coefficients  $x_1$ ,  $x_2$  etc. represent the relative duty cycle or amplitude used for each corresponding component waveform. Modern microcomputers are sufficiently powerful to solve this using heuristic techniques in real-time.

It can be seen that this method is applicable to combinations of multiple electrodes as long as a current distribution matrix is produced for each combination, e.g. a single cathode and multiple anodes, or where multiple electrode arrays are used together, e.g. two linear arrays implanted in a line. It will also be appreciated that the above method is one of a number of analytical and numerical methods that may be employed to find a solution for the component pulses.

As discussed above, a diagnostic screen is provided in the programming system. One output from the diagnostic system is the electrode contact impedances with reference to the stimulator enclosure. In a system without closed

loop control of charge or current, the contact impedance may be included in the calculation of each current distribution map, these maps calculated by the programming system when the stimulation set-up page loads.

Also provided in the diagnostic screen is normalisation of sensation on each contact. As previously discussed this information can be used if desired to modify the various duty cycles in an attempt to normalise the sensation levels produced by each electrode pair. An alternative approach is to use the information to modify the matrices so that they represent "sensation maps" rather than current distribution maps.

The finite elements can be adapted so that they are not purely resistive, but include for instance the effects of polarisation of tissues. The resulting component waveforms may produce stimulation patterns where adjacent pairs are excited in alternate polarities to focus the desired current path.

Clearly, the finite element model can be extended further to include an anatomical model of the electrical characteristics of the tissues in two or three dimensions. This is achieved by mapping the electrical characteristics of the tissues onto each element in the model.

Figure 18 shows a block diagram of a typical implanted apparatus according to the invention. The apparatus consists of three sub-systems, the implanted stimulator device, 86, and patient controller, 87, and the configuration system, 88.

The stimulator device, 86, consists of a power supply, 89, controlled by a microprocessor system, 90. The power supply takes energy from the batteries, 108, and under control of the micro-processor, 90, produces an appropriate current pulse or voltage supply to produce the desired composite pulse, 107 (this example illustrating current from a unipolar supply). The power supply can be either a single polarity output (for example a current or voltage source) or it can be a dual polarity output able to sink and source current. In a preferred embodiment for an implanted device, the power supply is a switch-mode circuit operating from a rechargeable lithium ion battery of nominal voltage 3.6V, producing either a current or voltage controlled output. In the case of a current supply, the micro-processor commands the power supply to produce a composite current pulse, the amplitude of which may be variable up to a maximum typically 20 mA, but limited by a maximum output voltage of 15 V. In the case of a voltage supply, the micro-processor commands the power supply to produce a voltage which may be of variable amplitude up to a maximum of typically 15 V peak, but limited by a maximum output current of 20 mA. In the voltage controlled case, the voltage itself need not be pulsed - the composite pulse, 107, is a current pulse formed by the sum of all currents drawn by the output stages. In both cases, the microprocessor controls the power supply and the output stages so that its desired composite stimulus pulse appears on the output of the power supply.

A number of output stages (e.g. 91, 92 and 93) are provided to form the component pulses, 94. Typically, sixteen or seventeen outputs are provided, of which only

three are shown in the figure. Sixteen outputs (of which all are identical but only two, 92 and 93, are shown) are used to drive sixteen electrode contacts via two eight way connectors on the top of the stimulator device, and a  
5 seventeenth output, 91, is used to drive the stimulator enclosure. Each output stage consists of a high and low side switching element (termed a "totem-pole" output), 95 and 96, which is controlled by the microprocessor and provides a tri-state output: connected to the pulse  
10 generator, connected to ground, or high impedance with both switching elements off.

If the stimulator has a single polarity pulse generator, the high and low side switches only have to conduct  
15 current in one direction, so each may comprise a single transistor. With a bi-directional dual polarity supply, the switches need to conduct current in both directions and therefore may comprise back-to-back P and N channel transistors.

20 With a bidirectional supply, the seventeenth totem-pole output, 91, for the stimulator enclosure is not required. Instead, the enclosure is connected via the low pass or a band-reject filter, 10, and a single switching element,  
25 so that it may be high-impedance if required.

The output drivers (91, 92 and 93) synthesize component waveforms, 94, under control of the microprocessor, 90, by connecting the appropriate electrode pairs in turn in  
30 the appropriate polarity thereby directing the composite stimulus pulse, 107, to the electrode pairs in sequence. Individual component pulses are preferably short, less than a maximum of 50  $\mu$ s or 20  $\mu$ s or and more preferably

less than 10  $\mu$ s 4  $\mu$ s or 2  $\mu$ s, so high speed switching elements 95 and 96 are required.

The level of current,  $I_p$ , and voltage,  $V_p$ , applied to the  
5 outputs via their respective switching elements are measured by voltage and current sensors in the pulse generator circuitry, 89, and fed back to the microprocessor. Because the microprocessor controls the electrode pairs in use at any moment, this data may be  
10 used to calculate contact impedance, identify wire breaks, etc. It may also be used to check that forward and reverse current flows are matched, which is an important safety feature in a DC-coupled stimulator device. As previously discussed, unbalanced  
15 bidirectional waveforms may cause undesirable migration of ions in the tissues to one electrode; additionally this may also play a role in long term electrode decomposition. However, it should be noted that even though balanced forward and reverse charge is preferred,  
20 the invention is equally applicable to cases where there is a DC offset in the desired signal.

Each output stage may optionally be provided with an output sensor, 97, which measures output current,  $I_o$ , and  
25 output voltage,  $V_o$ , and feeds this back to the microprocessor. Typically the output sensor consists of a low ohm resistor in series with the output and a precision analogue to digital converter (A-D) which measures the voltage drop across the resistor thereby  
30 deriving current. For compactness, typically the A-D is multiplexed across the output channels.

In addition, the output sensor circuit may contain an integrator or a sample and hold circuit that measures the

net current, or charge, on the respective output. This circuit may take discrete readings once or more times per component pulse, or accumulate the charge over each cycle, recording the magnitude of forward and reverse  
5 delivered charge to higher resolution than is readily achievable by sampling directly from the microprocessor.

Measuring current or charge in this way using analogue electronics is convenient as it offloads the requirement  
10 for fast data acquisition from the microprocessor. The microprocessor can then acquire the data from each output after the end of the cycle, in the relatively long time period between each waveform. The data may be used to control current, charge, or make adjustments in forward  
15 and reverse pulse duty cycles to correct ensure net zero charge delivery over the long term. An alternate approach (not shown) is to put a series capacitor in each output.

20 A more compact alternative to individual output sensors is to put a single ground current sensor, 98, in the common ground connection of all output drivers. The ground current sensor measures current flowing through the return path of the active electrode pair at any  
25 particular moment. The advantage of the ground current sensor is that only one is required, rather than duplicating the circuit on each output. Synchronisation of the sampling of the current sensors, both at the pulse generator and the ground or output is desirable to  
30 prevent measurement errors. Because of the short (sub-microsecond) duration of some component pulses it is ideal to synchronise sampling to occur just after the leading edge of each pulse. This data may either be sampled and stored digitally, which requires fast



sampling and conversion, or a multiplexer may be used to store the data using analogue means for later conversion by the microprocessor.

- 5 Other methods are possible, such as a sensor in the ground leg of each totem-pole, this has the advantage that the sense resistors are referenced to ground, rather than floating as is the case with sense resistors in the outputs.

10

The microprocessor also compares measured currents (and voltages) on each output sensor, or the ground sensor, with those produced by the signal generator. This provides as a cross-check that the system is operating  
15 correctly, thereby providing an additional level of safety for the patient.

It has been noted that the sixteen outputs, e.g. 92 and 93 that drive the electrode array differ from the single  
20 output, 91, that drives the stimulator enclosure as the latter has a low pass or band-reject filter, 109, connected in series in the output. This is a passive resonant filter which is high-impedance to signals of the same frequency as the radio frequency (RF) signal  
25 produced by Magnetic Resonance Imaging (MRI) scanners, for instance 64 MHz for a 1.5 Tesla machine and 128 MHz for a 3 Tesla machine. The MRI RF signal causes a voltage to be developed along the stimulator leads that without the filter would induce current flow between the  
30 implanted electrode array and the stimulator case. These currents may be sufficient to cause heating of the tissues in the region of the electrode array well above the 2°C limit that is considered acceptable by the US Food and Drug Administration. The advantage of this over

filters in the outputs is that we only need one per stimulator, rather than one per output. However, in a variation of the apparatus, additional output filters are provided to isolate one of the eight way electrode  
5 connectors from the other, so that currents cannot also be induced to flow between the two leads during MRI.

The stimulator device also includes a battery, 108, and a battery control circuit, 99. If the battery is  
10 rechargeable, this circuit controls the charging sequence, using energy from magnetic, electromagnetic or direct electrical energy supplied to the implanted device by an external charging unit. The external charging device is not shown in the figure, but may be a separate  
15 unit, or form part of the patient controller, 87.

The patient controller is preferably pocket-sized and typically has deliberately limited functionality presented to the user. A small LCD or OLED display and  
20 keypad, 100, allows the patient to select one of a number of pre-defined treatment programs, start and stop treatment, control the overall amplitude of stimulation and check the battery status of the implant. The patient controller contains a wireless interface, 101, which can  
25 communicate with a similar interface on the stimulator device, 102. The wireless interface is preferably the established standard for communication with medical implants, the Medical Implant Communications Service (MICS). MICS is a low power radio service for  
30 transmitting data to and receiving data from implanted medical devices. In the preferred embodiment, treatment programs are stored in the patient controller processor, 103, and transmitted to the stimulator device only as

required, which simplifies the firmware in the stimulator device thereby increasing reliability.

5 The configuration system, 88, is a PC-based system with a graphical user interface, 105, that provides the surgeon and/or patient with diagnostic and programming functions such as the creation of treatment programs as previously described. The configuration system communicates with the patient controller via universal serial bus (USB),  
10 104. For simplicity, the patient controller is the only device that communicates directly with the implant. All instructions from the configuration system for the implant are interpreted by the patient controller microprocessor, 103, before transmission over the  
15 wireless interface.

It should be noted that the apparatus described in figure 18 cannot provide the full range of pulses that are possible according to this invention. The apparatus  
20 cannot produce component pulses that overlap as illustrated in figure 10e, for which an apparatus with one independent signal generator for each overlapping component pulse is preferred. An independent signal generator dedicated to each output is the most flexible  
25 configuration, but this is not the preferred approach for an implanted device because of size constraints. For an external stimulator, where size is less important, this may however be acceptable. The apparatus in figure 18 has the advantage for implanted applications that only  
30 one power supply is required, which can be designed to step up the battery voltage and synthesize the composite pulse in one step. The combined power supply and signal generator can be constructed using switch-mode techniques, which are energy efficient.

As previously mentioned, there are a number of options for the power supply. To summarise, these include:

- 5       a) Fixed voltage or fixed current with control of the output amplitude by modulation of the pulse width of the component or sub-component pulse as a proportion of the duty cycle available to each pulse.
- b) Variable voltage or variable current.
- 10       c) A combination of a) and b) above, such as with a limited dynamic range and relatively low bandwidth variable supply plus modulation of the component pulses and/or variation of the relatively duty cycles of these pulses.
- 15       d) Unipolar or bipolar versions of a), b) and c).

For an implanted device, where space is at a premium, the ideal high bandwidth switch-mode current source is not readily achievable.

20

A practical compromise is a variable voltage, switch mode supply of relatively low bandwidth, together with modulation of the pulse width of the component or sub-component pulses to provide additional high bandwidth of control of the effective amplitude of each pulse (option c) above). The system includes feedback of the current flowing in each component or sub-component pulse by either sampling the current at a particular point in the cycle (typically just after the leading edge) or  
25 accumulating the average current over the pulse by means of an integrator. The latter is preferable, and as previously discussed may be performed either in the output sensor, 97, or in the power supply, 89, or ground current sensor, 98. An alternative is a switch-mode  
30

voltage source driving an analogue high bandwidth current source. The switch mode voltage source is efficient but relatively low bandwidth, but provides only the minimum voltage headroom to the analogue current source which is  
5 able to provide a high-bandwidth, stable output within the confines of the headroom voltage available.

In a compact apparatus, duplication of the current sensing for every output may not be practical, so the  
10 output sensors, 97, are not implemented, but are replaced by the ground current sensor, 98, which is cross checked against an input sensor built into the power supply and pulse generator, 89. This allows current control to be implemented on a pulse-by-pulse basis, to compensate for  
15 changes in output impedance. It also allows contact impedance to be measured on an ongoing basis; this data is stored in the stimulator device and may be fed back to the programming system or used to raise an alarm in the event of a rapid change of impedance on a particular  
20 contact.

The power supply in the embodiment above is unipolar, the output switch matrix inverts the polarity of the output as required. Because of the unipolar supply, each totem-  
25 pole output driver need consist only of a high and low side mosfet driven via level translation circuitry from the microprocessor. Such a configuration has minimal component count. It is capable of non-overlapping component pulses, delivered sequentially, such as those  
30 illustrated in 10b. It will also produce component pulses with an interpulse spacing, such as illustrated in figure 10c. With voltage control, the signal generator maintains the desired output voltage for a period equal

to the sum of the component pulse and their interpulse spaces.

5 The bandwidth of the voltage controlled power supply does not have to be high enough to change amplitude which each component pulse, but should be sufficient to allow the output amplitude to be reduced so that the amplitude can be changed every cycle to allow cycle-by-cycle control of current or charge, and also to allow reverse recharge  
10 pulses of low amplitude to be produced, such as illustrated in figure 7.

Returning to figure 18, MRI is an extremely valuable diagnostic technique, but is contraindicated in many  
15 implanted stimulator applications because excessive electrode heating has been known to cause permanent injury or death. The degree of electrode heating is however difficult to predict since it varies with the physical arrangement of the lead wire, placement of  
20 stimulator unit, the characteristics of the tissues surrounding the electrodes, orientation of the patient to the magnetic and RF fields, and many other factors. For cases where MRI compatibility is considered to be of paramount importance, a pulse generator with precise  
25 current or voltage control, 89, together with output sensor, 97, or other precision sensing of current and voltage, may be used in combination with a specialised electrode lead to measure electrode temperature during MRI imaging.

30

To maintain connector compatibility with a standard eight contact lead, one embodiment of a specialised temperature sensing lead differs from a standard eight electrode lead in that it has fewer electrode outputs and dedicates the

remaining outputs from the stimulator unit to temperature sensing. For example, a paddle style lead might have four electrode contacts. Each electrode is formed from an inert biocompatible material such as Platinum-Iridium.

5 An insulating substrate, typically a ceramic material, is bonded on the underside of one or more of the electrodes. On the back of the substrate, a thin film of Platinum is deposited on the surface which is formed into a fine serpentine shape using photolithographic techniques to  
10 produce a resistance temperature detector (RTD). The RTD relies on the changing electrical resistance of platinum with temperature. Typically, it is laser trimmed so that nominal resistance at 0 °C is for example 100  $\Omega$ . The RTD exhibits an approximate change in resistance of 0.4  $\Omega/^{\circ}\text{C}$ ,  
15 but the relationship is not quite linear and results in a nominal resistance of 114.382  $\Omega$  at a body temperature of 37 °C. The RTD thus formed has the advantage that it may be constructed completely using known biocompatible materials.

20 An diagrammatic example of such a lead and its interface to the stimulator unit is shown in figure 19. Each of four electrodes, 112, has a ceramic substrate, 111, bonded on the back on which a thin-film platinum RTD, 110  
25 is constructed. The RTD is hermetically sealed to prevent moisture contamination by means of a ceramic or glass covering layer (not shown) which is fused in place. The electrode contacts are shown in the diagram with their tissue contact face facing downwards and out of  
30 view, and the four wires from each contact to the stimulator unit have been omitted for clarity.

The RTD may be present on just one of the four electrodes, or as illustrated may be repeated on each

electrode and connected together using wire links, 114, so that the average temperature of the four electrodes is measured. The paddle electrode assembly is held together by a flexible insulating carrier, 113, shown in outline.

5

The lead wire, 115, contains eight individual insulated wires (including the four electrode contact wires not shown). Each of the resistors, R1, R2, R3 and R4 are representative of the resistance of the sensing leads, which is typically 3-4  $\Omega$ .

10

A safe limit for electrode heating is 2 °C, so precision temperature measurement is desirable. To compensate for resistance of the wire that connects the RTD to the stimulator unit and also to compensate for contact resistance in connections between the two, a four wire connection to the RTD is used in this example. In a four wire arrangement, two wires are used to carry the sense current provided by the current source, 117, and two additional wires are used to measure the voltage across the sensor element, measured by an analogue to digital converter, 116. The sense current is typically 1 mA or less, as a higher current causes self-heating of the sensor. The voltage change on the sensor with a 1 mA sense current is small, nominally 386  $\mu$ V for a one degree change from 37 to 38 °C (assuming that the nominal resistance of the RTD at 0 °C is 100  $\Omega$ ).

15

20

25

30

Referring to figure 18, it is possible to use available stimulation outputs to make measurements with the temperature sensing lead by incorporating a precision analogue to digital converter for measurement of voltage and/or current (preferably synchronised acquisition of both) in the output stage, 97, or in the power supply,



89, preferably with 16-bit or better resolution,. This does however mean that precise control of the output current or voltage from the pulse generator is desirable, which may increase complexity.

5

In order to increase resolution, the sense current may be increased to 10 mA or more provided that current is only applied for a few microseconds each time a reading is taken, so that self-heating is minimised.

10

Wire wound platinum RTDs are also suitable temperature sensors for implanted leads. In these sensors very fine platinum wire is coiled over a glass rod, or a coil is preformed, inserted into a ceramic tube and sealed to prevent moisture ingress. The sensor may be produced in diameters small enough to fit inside the end of a percutaneous lead, such as illustrated in figure 9a, 23.

15

High frequency noise from the MRI RF subsystem (e.g. 64 MHz at 1.5 T) and lower frequency noise from the gradient coils (e.g. approximately audio frequency repetition rates with higher edge rates) may cause voltages to be induced on the wires connecting the RTD to the pulse generator. Therefore, it is preferable that low pass filters are provided on the inputs to the analogue to digital converter to remove these high frequency components.

20

25

Because of the small resistance change in the sensor that must be detected and the high level of electro-magnetic interference from the MRI system, an additional approach is to take readings only in quiet periods between RF bursts and when the gradient coils are inactive, or to sample continuously but ignore readings that are clearly

30

incorrect due to such noise. Consequently, during an MRI procedure, the stimulator device monitors induced voltages on the electrode leads by periodically sampling the voltage and takes temperature readings only during quiet periods. A series of readings are taken at each sample to allow averaging and as a cross-check that there is no significant electro-magnetic interference. The stimulator unit transmits the temperature information to the patient controller via wireless telemetry, or transmits an error message if no reading is possible after a specific timeout period. The patient controller either displays electrode temperature or transmits this information to another device that is visible to the MRI operator. In the event of a dangerous rise in electrode temperature, an alarm may be sounded and the MRI procedure terminated, the procedure interrupted to allow the implanted electrodes to cool to a safe temperature, or the patient repositioned in the scanner so that coupling between the MRI RF fields and the leads is minimised.

As discussed, four wires provide the highest precision for a single RTD sensor. Typically, a specialised temperature sensing lead has eight contacts on the stimulator connector for compatibility with non-sensing leads, but has only four electrode contacts, with four wires reserved for the sensor. In addition, a fifth wire may be provided by utilising the clamp contact (figure 9b, 29). With five leads available it is possible to independently sample two RTDs connected in series. These may be used to measure the temperature of two of the four electrodes in the array, or four series-connected RTDs on the back of each electrode contact may be used, with the

stimulator device sensing the average temperature on two groups of two electrodes.

An alternative arrangement is a three wire configuration, where two wires are connected to one side of the RTD and this is used to make a correction for wire resistance on the assumption that the wire that connects to the other side of the device is similar.

Another alternative is a two wire arrangement in which the sense current is supplied and the voltage measurement is made on the same two wires. The disadvantage of this approach is that absolute temperature measurement of the electrode tip temperature is not as reliable because the resistance of the leads and electrical contacts are not easily compensated. Nevertheless, this circuit can provide high resolution information concerning the change in the temperature of the electrode tip during an MRI procedure, provided lead and contact resistance can be assumed to be constant, which is a reasonable assumption over the short time periods of interest. The two wire arrangement is the preferred embodiment for the reasons described below.

As previously discussed, it is desirable that connector compatibility is maintained with a standard eight contact leads, so a standard stimulator device may be used with sensing and non-sensing leads. Therefore, the standard non-sensing lead, illustrated in figure 9b, is arranged so that the free end is long enough to incorporate one additional contact.

Figure 20a illustrates an example of a percutaneous lead with embedded temperature sensor with a two wire sensing

arrangement. A ninth contact, the RTD connection, 122, is added to the end of the lead. The clamp, 121, is used as the other RTD connection. Consequently there are ten connections in total to the lead wire, 123, and eight contacts are now available for stimulation electrodes, 124. Because two additional wires are dedicated to the RTD interface, no internal isolation or switching circuitry is required in the stimulator unit.

In this example of a percutaneous lead with temperature sensing, a wire wound platinum RTD is employed. Figure 20b shows a section through the end of the lead. The eight electrode wires, 127, and two sensor wires, 128, are embedded in the lead. The lead itself is hollow so that a stiffening guide wire can be inserted to aid positioning during implantation. At the end of the lead the electrode wires (of which four of the eight are shown in the sectional diagram) are welded to the inside of each electrode contact, 125. A coiled platinum RTD, 126, sealed from moisture ingress, is positioned inside the electrode array in good thermal contact so that it can measure heating of the contacts. The entire assembly is approximately 1.3mm in diameter.

Prior to an MRI procedure, the two wire RTD circuit is calibrated against another temperature sensor internal to the stimulator unit, or zeroed on the assumption that normal body temperature is stable, or calibrated against a reading of body temperature taken by the clinician.

During the procedure, the change in RTD value is used to trigger an alarm if the tip temperature rises by a preset amount, typically 2°C. Because the RTD in this example measures the average temperature of all eight electrodes, the alarm may be set at a lower value in case of one

electrode changes temperature more rapidly than the others, although generally this is not the case as all electrodes and their corresponding wires have a similar coupling to the external fields.

5

Figure 21 illustrates an example implementation of an interface to the RTD sensor in the stimulator unit. This circuit uses two current sources, 129, to apply a known sense current in both forward and reverse directions across the RTD, 130. Differencing forward and reverse voltages compensates for low frequency induced noise and DC offset due, for example, to dissimilar metal junctions in the connectors or wiring.

15 In this example circuit, the two current sources are provided by two high precision (0.1%) 15 k $\Omega$  resistors connected to a stabilised 3.0 V supply. The RTD has a nominal resistance of 500  $\Omega$  at 0 °C, which corresponds to 571.91  $\Omega$  at 37 °C. The current in the RTD is nominally 20 193  $\mu$ A. A 1 °C increase gives a change of 1.932  $\Omega$  in the value of the RTD, corresponding to a voltage change of about 360  $\mu$ V on a DC level of about 110 mV.

With transistor Q1 off and Q2 on, current flows "downwards" through the RTD, 130. With Q1 on and Q2 off, current flows "upwards". Thus by acquiring the voltage at the analogue to digital converter (ADC), 131, under both conditions and adding them digitally, any DC offset in the circuit and any standing current in the RTD leads 30 is eliminated.

Low pass RC filters (R1, C1 and R2, C2) reduce the effect of high frequency noise due to MRI RF and gradient coils. The ADC, 131, is a 16-bit sigma delta device with a

programmed input gain of 8 so that 1 LSB corresponds to about 5.7  $\mu$ V.

Typically, the temperature change due to RF heating and  
5 like effects is relatively slow (in the order of a few  
seconds or minutes) and therefore the sample acquisition  
rate for temperature readings may typically be less than  
10Hz. Digital filtering in the ADC is used to remove any  
noise in the 50 Hz and 60 Hz region caused by mains  
10 electrical supplies.

Other types of temperature sensors are possible such as  
other RTD materials or thermocouples. The platinum RTD  
is preferred because of long term stability, relative  
15 sensitivity and biocompatibility.

As mentioned above, the stimulator system is able to  
sense electromagnetically induced currents in the  
stimulator leads, this data being transmitted to the MRI  
20 operator. Due to electro-magnetic interference,  
intermediate storage and/or an error correcting wireless  
transmission protocol is required. The information may  
be used by the operator to position the patient in the  
field so that coupling between the MRI system and the  
25 stimulator leads is minimised. Furthermore, in leads not  
adapted for temperature measurement, the stimulator  
device may provide a limited form of protection for the  
patient by monitoring the level of electrical noise on  
the lead system and alerting the MRI operator if this  
30 exceeds limits that are known to cause electrode heating.

In an implanted system, an embodiment of the invention  
comprises the elements described below.

A programming system, with a graphical user interface, provides users and surgeons with an easy to use method of controlling the location and area of coverage of desired stimulus pulse with respect to an array of eight or sixteen electrodes. The user interface provides of a method of normalisation of sensation between electrodes. This may be achieved by slowly increasing the stimulus output on a subset of the electrodes, one electrode at a time, until the user reports first sensation. This data may then be automatically interpolated to derive data for all electrodes.

The transformation element in the controller has as its input the desired location and focus of the stimulus pulse from the graphical user interface and takes account of normalisation data to calculate the respective duty cycle and electrode pairing for a series of trains of sub-component pulses. The pulses should have a resolution on their duration of preferably 0.1  $\mu$ s or better, such that by varying the respective duty cycles, the perceived stimulation on the electrode array can be controlled accurately and moved smoothly around the array. Preferably the sub-component pulses are constant current pulses of maximum duration of 10  $\mu$ s or less and minimum duration of 0.5  $\mu$ s or less. Preferably, during configuration of the stimulation patterns, the component pulse data is transmitted in real time over the MICS wireless channel to the implant, so that the user can report to the surgeon as he adjusts the stimulation field.

The implant preferably has a rechargeable battery which supplies a variable voltage switch mode supply, which feeds a high bandwidth analogue current source. This is

turn supplies a series of 34 output switches that allow any of 16 electrodes and the stimulator case to be connected to the supply or to ground. The output switches should be high speed devices capable of producing component pulses of minimum 0.5  $\mu$ s duration or less, of maximum amplitude 20 mA and maximum voltage 20 V. A microprocessor coupled with a high-speed programmable logic device controls the switching matrix, synthesizing the sub-component pulses as commanded. To facilitate real-time update of the stimulation pattern, the microprocessor may implement a copy of the transformation element from the programming system, thereby deriving the sub-component pulses internally by interpolation from table based reference data on the basis of high-level information describing the parameters of the electrode array and desired stimulus pulse. Preferably, the sub-component pulses are delivered in sequence, so that they do not overlap but may have a space between each pulse of zero to up to 20  $\mu$ s.

## REFERENCES

Johnson MI, Ashton CH, Thompson JW (1991) An in-depth study of long-term users of transcutaneous electrical stimulation (TENS). Implications for clinical use of TENS. Pain 44:221-229.

Macdonald AJR, Coates TW (1995) The discovery of transcutaneous spinal electroanalgesia and its relief of chronic pain. Physiotherapy 81:653-661.

Melzack R, Wall PD (1965) Pain Mechanisms: a new theory. Science 150:971-979.



Palmer ST, Martin DJ, Steedman WM, Ravey J (1999)  
Alteration of interferential current and transcutaneous  
electrical nerve stimulation frequency: effects on nerve  
excitation. Arch Phys Med Rehabil 80: 1065-1071.

5

Radhakrishnan R, Sluka KA (2005) Deep tissue afferents,  
but not cutaneous afferents, mediate TENS-induced  
antihyperalgesia. J Pain 10:673-680.

10 Salar G, Job I, Mingrino S, Bosio A, Trabucchi M (1981)  
Effect of transcutaneous electrotherapy on CSF  $\beta$ -  
endorphin content in patients without pain problems.  
Pain 10:169-172.

15 Shealy CN, Mortimer JT, Reswick JB (1967) Electrical  
inhibition of pain by stimulation of the dorsal columns:  
preliminary clinical report. Anesthesia & Analgesia  
46:489-491.

20 Shealy CN, Mortimer JT (1971) Dorsal column  
electroanalgesia. In: (Eds) Reynolds DV, Sjoberg AE.  
Neuroelectric Research. Charles C Thomas. pp146-150.

Wall PD (1986) The discovery of Transcutaneous Electrical  
25 Nerve Stimulation. Journal of Orthopaedic Medicine 3:  
26-28.

**CLAIMS:**

1. An apparatus for applying electrical pulses to a patient, the apparatus being either implantable in the patient or applicable transcutaneously to the patient, the apparatus comprising a plurality of electrodes arranged in an array, the electrodes forming a plurality of electrode pairs wherein each pair comprises an anode and a cathode which are made up of one or more electrodes from the array electrically connected in parallel, and a signal generator for generating signals to said electrodes so as to form said electrical pulses, the signal generator being arranged to generate said signals such that the signals are either sequentially transmitted to successive electrode pairs in a cycle so the respective electrode pairs receive the corresponding signals at different times, or alternatively so that the signals are received by the electrode pairs such that they do not all start and end at the same point in time, wherein said electrical pulses form by addition a composite pulse which has a duration between 4 $\mu$ s and 1500 $\mu$ s and a maximum voltage between 2v and 50v when said apparatus is implantable and 15v to 500v when said apparatus is applicable transcutaneously.

2. An apparatus according to claim 1, wherein the signal generator is arranged to generate said signals such that, throughout the duration of said composite pulse, successive electrode pairs receive the  
5 corresponding signals.

3. An apparatus according to claim 1, wherein the signal generator is arranged to generate said signals such that there are gaps between said signals of a  
10 duration not greater than 200 $\mu$ s during said composite pulse.

4. An apparatus according to any one of the preceding claims, wherein said signal generator is arranged to  
15 generate said signals such that said signals are each pulse trains with a minimum pulse width of 0.1 $\mu$ s and a maximum pulse width of 50 $\mu$ s.

5. An apparatus according to any one of the preceding  
20 claims wherein said composite pulse has a duration between 20 $\mu$ s and 1000 $\mu$ s.

6. An apparatus according to any one of the previous claims, wherein said signal generator has a housing  
25 forming one of said electrodes.

7. An apparatus according to any one of the preceding claims, wherein said signal generator has a plurality of signal generation devices, each signal generation device  
5 being associated with a corresponding one of said plurality of electrodes.

8. An apparatus according to any one of claims 1 to 6,  
10 wherein said signal generator has at least one signal generation device and a network of high speed switching elements, the network of switching elements being arranged to direct the output of said at least one generation device to said electrode pairs.

15

9. An apparatus according to one of the preceding claims, wherein the signal generator is arranged to generate said signals such that said composite pulse has  
20 a notional pulse width and a notional voltage, current or charge, and which is arranged to generate a stimulation field of a desired location and area in the patient.

25 10. An apparatus according to claim 9, wherein said signal generator is arranged to control the relative duty

signals of said signals, so as to vary said desired location and/area.

5 11. An apparatus according to claim 10, wherein said signal generator is further arranged to control the number, distribution and/or configuration of electrode pairs receiving said corresponding signals.

10 12. An apparatus according to claim 10 or claim 11, having an operator interface for controlling said signal generator so as to vary said desired location and/area.

13. An apparatus according to any one of the preceding  
15 claims, wherein each of the said signals comprises a plurality of sub-components.

14. An apparatus according to claim 13, where the signal generator is arranged to separate said sub-components  
20 such that there are gaps between said sub-components and further gaps between said electrical pulses, said gaps and said further gaps each having a duration not greater than 200 $\mu$ s, and the sum of the durations of said sub-components, excluding said gaps and said further gaps, is  
25 equal to the duration of said composite pulse.

15. An apparatus according to any one of the preceding claims, wherein said signal generator is arranged to generate said signals such that said electrical pulses have a maximum pulse width of 10 $\mu$ s.

5

16. An apparatus according to claim 14, wherein said electrical pulses have a maximum pulse width of 2 $\mu$ s.

17. An apparatus according to any one of the preceding  
10 claims, wherein said composite pulse has a duration between 20 $\mu$ s and 1000 $\mu$ s.

18. An apparatus according to any one of the preceding claims, wherein the signal generator includes a power  
15 supply, a controller arranged to generate a composite signal corresponding to said composite pulse, and a converter arranged to convert the composite signal into said signals using a network of high speed switching elements.

20

19. An apparatus according to any one of the preceding claims wherein the signal generator includes a power supply, a controller storing data representing said composite pulse, and a network of high speed switching  
25 elements, the controller being arranged to control the

power supply and said switching elements so as to generate said signals.

20. An apparatus according to any one of the preceding  
5 claims, having a controller arranged to control,  
represent or store a desired notional voltage, current,  
charge or energy distribution in a mathematical or  
empirically derived model of human or animal tissue in  
the region of the array, and said signal generator  
10 includes a transformation element arranged to reduce said  
notional voltage, current charge or energy distribution  
into said signals and a stimulator arranged to send said  
signals to the array of electrodes, said stimulator being  
arranged to transmit said signals sequentially to said  
15 electrodes at different times such that successive  
electrode pairs are arranged to generate said pulses in a  
cycle, or to transmit said signals so that said pulses do  
not all start and end at the same point in time.

20 21. An apparatus according to claim 20, wherein said  
controller includes an operator interface for selectively  
controlling said notional voltage, current charge or  
energy distribution.

25 22. An apparatus according to any one of the preceding  
claims, wherein said signal generator is arranged to

generate said signals such that said electrical pulses have little or no activation of afferent fibres but said composite pulse is sufficient to cause an action potential in such fibres.

5

23. An apparatus according to any one of the preceding claims, wherein the signal generator is arranged to generate said signals such that the relative pulse widths and plurality of said electrical pulses vary with respect  
10 to each other.

24. An apparatus according to any one of the preceding claims, wherein the signal generator is arranged to generate said signals such that the relative pulse widths  
15 of said electrical pulses are determined with respect to each other to normalise the sensation at each electrode.



Figure 1




Figure 2




Figure 3




Figure 4




Figure 5




Figure 6




Figure 7




Figure 8




Figure 9a




Figure 9b




Figure 10a




Figure 10b




Figure 10c




Figure 10d




Figure 10e






Figure 11




Figure 12a




Figure 12b




Figure 13




Figure 14




Figure 15




Figure 16




Figure 17a




Figure 17b




Figure 18






Figure 19




Figure 20a




Figure 20b





Figure 21



# INTERNATIONAL SEARCH REPORT

International application No  
PCT/GB2008/001723

<b>A. CLASSIFICATION OF SUBJECT MATTER</b> INV. A61N1/05 A61N1/34		
According to International Patent Classification (IPC) or to both national classification and IPC		
<b>B. FIELDS SEARCHED</b> Minimum documentation searched (classification system followed by classification symbols) A61N		
Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched		
Electronic data base consulted during the international search (name of data base and, where practical, search terms used) EPO-Internal		
<b>C. DOCUMENTS CONSIDERED TO BE RELEVANT</b>		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 2007/073354 A1 (KNUDSON MARK B [US] ET AL) 29 March 2007 (2007-03-29)	1-5, 9, 14, 17, 20, 24
Y	paragraphs [0063], [0066], [0068], [0074], [0076]; figure 8	6-8, 10-13, 15, 16, 18, 19, 21-23
Y	US 2003/139781 A1 (BRADLEY KERRY [US] ET AL) 24 July 2003 (2003-07-24) paragraph [0027]	6, 7
Y	US 6 684 104 B2 (GORDON PAT L [US] ET AL) 27 January 2004 (2004-01-27) column 3, lines 28-38; figures 7a,b,17 column 9, lines 8-42	8, 18, 19, 23
-/--		
<input checked="" type="checkbox"/> Further documents are listed in the continuation of Box C. <input checked="" type="checkbox"/> See patent family annex.		
* Special categories of cited documents : *A* document defining the general state of the art which is not considered to be of particular relevance *E* earlier document but published on or after the international filing date *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified) *O* document referring to an oral disclosure, use, exhibition or other means *P* document published prior to the international filing date but later than the priority date claimed *T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art. *Z* document member of the same patent family		
Date of the actual completion of the international search  4 September 2008		Date of mailing of the international search report  17/09/2008
Name and mailing address of the ISA/ European Patent Office, P.B. 5818 Patentlaan 2 NL - 2280 HV Rijswijk Tel. (+31-70) 340-2040, Tx. 31 651 epo nl, Fax: (+31-70) 340-3016		Authorized officer  Schöffmann

# INTERNATIONAL SEARCH REPORT

International application No  
PCT/GB2008/001723

C(Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y	WO 2005/115536 A (BIOINDUCTION LTD [GB]; LITTLEWOOD ROGER KENNETH [GB]; MACDONALD ALEXAN) 8 December 2005 (2005-12-08) page 38, line 25 - page 45, line 18; figures 9,14	10,15, 16,22
Y	US 2004/034394 A1 (WOODS CARLA MANN [US] ET AL) 19 February 2004 (2004-02-19) paragraphs [0084] - [0087], [0090], [0091], [0098], [0149]; figure 12E	11-13,21
X,P	WO 2008/012523 A (GILLBE IVOR STEPHEN [GB]) 31 January 2008 (2008-01-31) page 6, line 7 - page 17, line 19; figures 14-17 page 29, line 5 - page 42, line 35 page 45, line 18 - page 50, line 6	1-24

# INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/GB2008/001723

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 2007073354 A1	29-03-2007	US 2008154333 A1 WO 2007038200 A1	26-06-2008 05-04-2007
US 2003139781 A1	24-07-2003	US 2006122653 A1 US 2006122654 A1	08-06-2006 08-06-2006
US 6684104 B2	27-01-2004	AT 377440 T DE 60037015 T2 EP 1171196 A1 WO 0061224 A1 US 2003055463 A1 US 2003114895 A1 US 6542776 B1	15-11-2007 21-02-2008 16-01-2002 19-10-2000 20-03-2003 19-06-2003 01-04-2003
WO 2005115536 A	08-12-2005	CN 1956749 A EP 1758644 A1 GB 2414410 A JP 2008500086 T US 2007299482 A1	02-05-2007 07-03-2007 30-11-2005 10-01-2008 27-12-2007
US 2004034394 A1	19-02-2004	NONE	
WO 2008012523 A	31-01-2008	NONE	