

(19) World Intellectual Property
Organization
International Bureau



(43) International Publication Date
21 July 2005 (21.07.2005)

PCT

(10) International Publication Number
WO 2005/065122 A2

(51) International Patent Classification: Not classified

(21) International Application Number:
PCT/US2004/040808

(22) International Filing Date: 7 December 2004 (07.12.2004)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
60/531,943 23 December 2003 (23.12.2003) US
10/960,808 7 October 2004 (07.10.2004) US

(71) Applicant (for all designated States except US): **MO-TOROLA, INC.** [US/US]; 1303 East Algonquin Road, Schaumburg, IL 60196 (US).

(72) Inventors; and

(75) Inventors/Applicants (for US only): **STRATIS, Glafkos** [US/US]; 6077 Oak Bluff Way, Lake Worth, FL 33467 (US). **EMRICK, Rudy, M.** [US/US]; 1617 E. Heather Avenue, Gilbert, AZ 85233 (US). **CORRAL, Celestino, A.** [US/US]; 7584 Northtree Club Drive, Lake Worth, FL

33467 (US). **EMAMI, Shahriar** [IR/US]; 2431 Westmont Drive, Royal Palm Beach, FL 33411 (US). **SIBECAS, Salvador** [US/US]; 7181 Lockwood Road, Lake Worth, FL 33467 (US).


(74) Agents: **JACOBS, Jeffrey, K.** et al.; 1303 East Algonquin Road, Schaumburg, IL 60196 (US).

(81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BW, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NA, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, YU, ZA, ZM, ZW.

(84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LS, MW, MZ, NA, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IS, IT, LT, LU, MC, NL, PL, PT, RO,

[Continued on next page]

(54) Title: ADAPTIVE DIVERSITY ANTENNA SYSTEM



(57) Abstract: An antenna system (205) includes an antenna structure (215), a receiver (220), and an antenna system controller (225). The antenna structure includes an arrangement of antennas (237), a signal combiner (240), and a switching matrix (235). The arrangement of antennas is designed to have a set of antenna element separations that are optimized to provide lowest correlation coefficients of intercepted radio signals for a corresponding set of electromagnetic environment types that vary from a very low density scattering environment to a maximum density scattering environment. The antennas (230), (231), (232), (233), (234) in the antenna arrangement each include at least one element that has a common polarization. There is at least one antenna that is a dual polarized antenna. The antenna system selects an antenna element pair that corresponds to the environment type which it is operating and thereby receives a best combined signal.



SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

Published:

— *without international search report and to be republished upon receipt of that report*

ADAPTIVE DIVERSITY ANTENNA SYSTEM

Background

5

It is well known that a radio signal arriving at a receiving antenna location can be scattered by objects in the environment, resulting in a signal at the receiver that is a combination of signals reflected or transmitted by the objects, diffracted by the objects, and/or attenuated through the objects.

Such environments are called electromagnetic scattering environments. Conventional radio signal receivers sometimes employ antenna diversity to improve the received signal quality of such scattered signals, typically employing two antennas having different polarizations or two antennas separated, for example, by a wavelength of the carrier frequency. Different methods are used to combine the signals intercepted by the two antennas. A low cost method of switching between them can provide substantial improvement in some situations. A higher cost method of combining the signals that uses a radio frequency combiner will typically provide equal or better results. In conventional diversity antenna systems, a separation between two antennas is typically chosen to minimize the correlation of the signals being received at each antenna. Some cellular systems employ two antenna diversity systems for fixed equipment, in which a separation of two antennas that is determined by the carrier wavelength provide improved performance. Another example of separation diversity is found in wireless routers that operate according to the 802.11(b) standard promulgated by the Institute of Electrical and Electronic Engineers (IEEE). In some of these systems, the fixed router unit has two antennas at fixed distances, but the antennas can be rotated, thereby changing their relative polarization. Polarization diversity can be obtained by using dual polarized antennas, which can require less enclosed volume and has provided improved performance in portable radios. Such approaches utilize fixed physical arrangements that are chosen to provide good improvement over non-diversity antennas in many

30

situations. However, as the carrier frequencies that are used for new radio communication systems increase, the scattering of electromagnetic energy by objects in the environment has a more degrading impact on the received radio signal and the electromagnetic scattering environment can differ substantially
5 between fixed locations that are not far apart. In these situations, the improvements afforded by a fixed physical arrangement of two diversity antennas diminished, and a better approach is needed.

Brief Description of the Drawings

10

The present invention is illustrated by way of example and not limitation in the accompanying figures, in which like references indicate similar elements, and in which:

FIG. 1 is a simplified plot of correlation coefficients for pairs of antenna elements for a set of five electromagnetic environment (EME) types, in
15 accordance with embodiments of the present invention;

FIG. 2 is a block diagram of a portion of an electronic device that uses antenna diversity, in accordance with the preferred embodiment of the present invention; and

FIG. 3 is a plan view drawing of a portion of a story of a building in
20 which electronic devices using diversity are used, in accordance with an embodiment of the present invention.

Skilled artisans will appreciate that elements in the figures are illustrated for simplicity and clarity and have not necessarily been drawn to
25 scale. For example, the dimensions of some of the elements in the figures may be exaggerated relative to other elements to help to improve understanding of embodiments of the present invention.

Detailed Description of the Drawings

30

Before describing in detail the particular antenna diversity technique in accordance with the present invention, it should be observed that the present

CML00925U

invention resides primarily in combinations of method steps and apparatus components related to diversity antenna systems. Accordingly, the apparatus components and method steps have been represented where appropriate by conventional symbols in the drawings, showing only those specific details that are pertinent to understanding the present invention so as not to obscure the disclosure with details that will be readily apparent to those of ordinary skill in the art having the benefit of the description herein.

As is known in the art, signals from elements of two antennas that are separated can sometimes be combined in a technique known as antenna diversity, and the combined signal might be a better signal from which to recover the original information than the signal intercepted by either antenna. The separation of conventional diversity antennas is typically fixed and is typically based on a simplified theoretical conclusion, such as one that the scattering environment is homogeneous. The present invention uses new understanding recently gained that a scattering environment is in fact inhomogeneous and a diversity antenna separation determined by conventional techniques that rely only on environmental models such as line of sight, Rician, or Rayleigh, do not always predict optimum antenna diversity arrangements, particularly in scattering environments. It has been recently determined that antenna arrangements for achieving diversity improvement for a given frequency band can be better optimized using signal correlation measurements made in actual or modeled electromagnetic environments of distinctly differing types that are characterized by the density and type of scatterers that are significant at the given frequency band. It has also been determined that the selection of antenna elements of such an optimized antenna arrangement for providing optimized combining of diversity signals can be done either by identifying the type of electromagnetic environment or by correlation measurements made at the site using the antenna arrangement. Identifying the type of electromagnetic environment can be done using environmental modeling of the actual site where the antenna arrangement is being used, or by a site type determination based on measurements made on site by an experienced RF technologist.

CML00925U

Referring to **FIG. 1**, a simplified plot of correlation coefficients for pairs of antenna elements is shown for a set of five electromagnetic environment (EME) types, and will be used to describe a method of establishing an optimum diversity antenna arrangement for recovering a modulated radio signal that is intercepted by the antenna arrangement. It will be appreciated that diversity combining of two versions of a radio signal transmitted by one transmitter and intercepted by two antenna elements provides better improvement over receiving either one of the two signals when the phase and amplitude correlation between the two signals is minimum. This can be characterized by the correlation coefficient of the two signals, which varies from a value of 0 to 1.0, with lower values indicating less correlation (and therefore better results). For some frequency bands, up to seven distinct EME types have been identified, but the principles of the present invention are equally applicable in cases using seven or less than seven EME types. The EME types in the example described with reference to **FIG. 1** are identified as High Scattering, I, II, III, and IV. EME type IV represents an electromagnetic environment having few scattering objects that are effective (at the frequency band of transmission) near a receiver that is using the antenna arrangement to intercept energy from the transmitter. For a wide area network, this may represent a rural situation, and is a situation in which nulls in the electromagnetic field are far apart. EME types III, II, and I represent electromagnetic environments of increasingly effective and dense scattering objects near the receiver, where nulls in the electromagnetic field are distinct and closer together. High Scattering represents an electromagnetic environment wherein the radio signal at the receiver is formed by many scattered components where the nulls are very closely spaced.

A set of optimum antenna element separations is determined for a set of EME types by determining for each EME type a minimum correlation coefficient (CC) of a radio signal that is intercepted by an antenna element of each of a pair of antennas, wherein the antenna elements have the same (a common) polarization. The optimum spacing is determined by finding the separation of the pair of antennas (and therefore the separation of the

CML00925U

elements) at which a minimum value of the CC occurs. This can be done by electromagnetic modeling techniques or by field tests. Both methods have been shown to provide the same results. It has been found that distinct EME types have different values of CCs at the optimum antenna spacing for the
5 EME type, and that the optimum antenna separation is different for each EME type. This is indicated in **FIG. 1** by correlation coefficients **409, 410, 411, 412, 413**, which are optimum CC's for the EME types High Scattering, I, II, III, and IV, as indicated on the horizontal axis.

Each measured or modeled correlation coefficient is indicated in **FIG. 1**
10 by nomenclature that indicates an element combination (pair). For this example the element combinations are A-A_p, A-B, A-C, A-D, and A-E. The combination A-A_p indicates a pair of polarized elements of a dual polarized antenna (antenna A), which, for example, may be polarized 90 or 120 degrees apart. Combinations A-B, A-C, A-D, and A-E indicate antenna element
15 combinations having a common polarization and increasing separations. For example, A-C indicates a combination of antenna elements having the same polarization – an element from antenna A and an element from antenna C. For each of the EME types other than the High Scattering environment, there is a range of correlation coefficient values **410, 411, 412, 413** that represents
20 an optimum (lowest) attainable range of correlation coefficients (CCs). The optimum attainable range of CC for each EME type is obtained at an optimum spacing of antenna elements that have the same polarization, which is identified by the nomenclature described above. The CCs can be determined either by electromagnetic modeling or field testing, and they are ranges
25 because they are statistical measurements of values that vary. The ranges are represented in **FIG. 1** by the height of the ellipses for the optimum values. It will be appreciated that the optimum CC values **410, 411, 412, 413** decrease as the EME type changes from the rural/low scattering to urban. When a combination of elements of the same polarization is used to measure
30 a CC for an environment other than the one for which the combination is ideal, the resulting CC (actually, range of CC's) is, of course, worse than the optimum value attained with the elements at the optimum separation. As an

CML00925U

example, the CC's **414**, **415**, **416** for separations A-B, A-D, and A-E are greater than the optimum CC for antenna element separation A-C in EME type II. For EME type IV, the antenna element separations A-B, A-C, and A-D are all deteriorated to a CC value **417** near 1.0 in this example. However, when scattering becomes severe, no particular separation of elements having the same polarization is effective to reduce the correlation coefficient **410** substantially below a value of 1. This may be due to the impracticality of providing two elements at a very small separation to intercept what should be independent versions of a signal. In these circumstances, it has been found that changing to two elements that have orthogonal polarization will often provide improved signal recovery. This is indicated by the correlation coefficient value **409**. In general, the separations A-B, A-C, A-D, and A-E for the optimum CCs are not necessarily linearly related to each other or to the wavelength of the frequency band, as is the case in conventional antenna arrays and conventional diversity antenna arrangements.

Once a set of optimum antenna separations for a set of electromagnetic environment types has been determined, an antenna arrangement may be devised for a receiver type and used for operational installations. Although optimum performance may be obtained using the separations obtained by the electromagnetic modeling and/or field testing, physical constraints may necessitate a variation to these ideal separations; in particular, it may be necessary to reduce (or possibly eliminate) the separation of the maximum optimum separation to avoid unduly enlarging a product's size.

In summary, a method for establishing an optimum diversity antenna arrangement for recovering a modulated radio signal that is intercepted by the diversity antenna arrangement includes 1) identifying a set of electromagnetic environment types that comprises distinct radio environments for a particular frequency range, 2) determining a set of optimum antenna separations for the set of electromagnetic environment types, wherein each optimum antenna separation provides a minimum correlation coefficient, and 3) establishing the optimum diversity antenna arrangement by determining an arrangement of

CML00925U

antennas that provides a plurality of antenna separations determined from the set of optimum antenna separations and includes at least one dual polarized antenna. The set of separations are not necessarily linearly related with the frequency or wavelength.

5 Referring to **FIG. 2**, a block diagram of a portion of an electronic device **200** that uses antenna diversity is shown, in accordance with the preferred embodiment of the present invention. The electronic device **200** may be any electronic device that communicates using radio frequency (RF) signals and that is stationary or relatively stationary (i.e., moving slowly
10 relative to a wavelength of the frequency at which the device is operating). A few examples are a network receiving antenna arrangement, a cellular telephone, a personal digital assistant, a local area network or personal area network wireless router, and an appliance control receiver. Although the benefits of the present invention may accrue to devices operating below 1
15 GHz, they are more likely to be realized in electronic devices that operate above 1 GHz, because such devices are more likely to be moved from place, and to be in electromagnetic scattering environments that change while the electronic device is stationary. The portion of the electronic device **200** shown in **FIG. 2** comprises an antenna system **205** coupled bi-directionally to
20 a device controller **210** by antenna controller input signals **211**, **227**. The electronic device **200** will typically comprise other components, such as a display, keys, switches, external connectors, and batteries - depending on the type of electronic device **200**. The device controller **210** may be a stored program controller processor or a state machine, or a portion of a stored
25 program controller processor or a state machine. The device controller **210** may include applications, such as user interface functions, location finding functions, speed detecting functions, handoff algorithms, games, and internet browsing functions. The antenna controller input signal **227** comprises a demodulated signal obtained from RF signals intercepted by the antenna
30 system **205**. The antenna controller input signal **211** may include an identification of an application that uses information included in the

demodulated signal included in signal **227**, and in some embodiments may also include an identification of an EME type.

The antenna system **205** comprises an antenna structure **215**, a receiver **220**, and an antenna controller (antenna system controller) **225**. In one embodiment the antenna controller **225** is a digital signal processor, but in others it may be any combination of processing apparatus, such as a stored program controlled microprocessor, a computer, a neural network processor, and it may be combined with the device controller **210** or another controller in the electronic device **200**. The antenna structure **215** comprises an arrangement of antennas **237**, which in the embodiment shown in **FIG. 2** comprises dual polarized antennas **230, 231, 232, 233, 234**; a switching matrix **235** to which the arrangement of antennas **237** and the antenna system controller **225** are coupled; and a combiner **240** to which the switching matrix **235** and the antenna system controller **225** may be coupled. The switching matrix **235** couples a subset of the signals generated by a selected subset of the elements of the arrangement of antennas to the combiner **240** and rejects signals not from the selected subset of elements. The rejection may be, for example, by grounding the rejected signal or by causing an essentially open circuit to the rejected signal. The subset is selected by a subset selection signal **226** coupled from the antenna controller system. In some embodiments a subset is either one or two antenna elements, where the two elements are also referred to as a combination of antenna elements, or an element combination. The antenna system controller **225** selects just one antenna element at a time when a correlation coefficient is being measured.

The combiner **240** may be a non-configurable device (i.e., it may not need control signals to accomplish combining the subset of signals selected by the switching matrix **235**), in which case it may not be coupled to the antenna controller **225**. The switching matrix **235** and the combiner **240** may be combined into one functional component. The combiner **240** combines the signals from the selected antenna elements into a combined RF signal **241**. (If only one signal is selected, then of course there is no combining). Each

individual dual polarized antenna **230, 231, 232, 233, 234**, the switching matrix **235**, and the combiner **240** may be designed and fabricated using conventional or other techniques. For example, the antennas of the antenna structure **215** may be of any conventional structure such as wire or tube elements (particularly at frequencies below 1 GHz), printed circuit board runners, or metal depositions in an integrated circuit. Each antenna has at least one element that has a polarization that is common (the same) in the plurality of the antennas in the antenna arrangement **237**. The maximum number of antennas may be limited by space in the electronic device and/or cost/benefit considerations. It may be that not all of the antennas in the antenna arrangement **237** are dual polarized (polarimetric) antennas, but it is preferable that at least one is a dual polarized antenna. The spacing of the antennas in the arrangement of antennas **237** in the present invention is uniquely determined, as described above with reference to **FIG. 1**. The arrangement of antennas **237** in the electronic device **200** illustrated in **FIG. 2** comprises five antennas, which could be spaced to provide the separations A-B, A-C, A-D, A-E described above with reference to **FIG. 1**. The receiver **220** is coupled to the combined RF signal **241** generated by the combiner **240**. The combined RF signal **241** is coupled to a band pass filter **245** that eliminates out of band energy. The filtered signal is then coupled to an amplifier **250** that amplifies the filtered signal. A complex mixer **255** mixes the amplified signal with in-phase and quadrature phase local oscillator signals generated by phase shifter **265** from a local oscillator signal generated by local oscillator **260**. The complex mixer **255** generates analog baseband in-phase (I) and quadrature (Q) signals that are coupled to dual analog-to-digital converter **270**, which generates digitally sampled in-phase (I') and quadrature (Q') signals that are coupled to a demodulator **228**, which generates a demodulated signal **227** that is coupled to the antenna controller **225** and the device controller **210**. The antenna controller **225** use the demodulated signal **227** to evaluate characteristics of the combined RF signal, such as the envelope, that are used as one basis for determining the subset selection signal **226**. In some embodiments, the functions of the demodulator **228** and

CML00925U

antenna controller **225** are performed by the same processor or intelligent network. In other embodiments, the I' and Q' signals may be coupled to the antenna controller **225**, where they are used for subset selection, and to the device controller **210** wherein they are demodulated. The device controller

5 **210** extracts digital information from the demodulated signal. Thus, information is extracted from the combined RF signal **241**. Other components of the receiver **220**, for example, filters and power distribution circuits, are not shown in **FIG. 2**. Many other types of receivers may be used in other

10 embodiments of the present invention to generate a signal or signals from the combined RF signal that can be analyzed by an antenna controller **225** for envelope evaluation of the combined RF signal. The antenna controller **225** may only evaluate the envelope of the combined RF signal; the digital information may be extracted in another controller of the electronic device

15 **200**. In the example described, five antennas are used to provide four spacings, such as the spacings A-B, A-C, A-D, and A-E described with reference to **FIG. 1**. It will be appreciated that in this example, the antenna spacing A-D might be very nearly the same as the spacing B-E that results from the placement of antenna B to obtain the optimum spacing A-B. In this situation, antenna D may not be necessary; the element combination B-E

20 could be used instead. Thus, in general, the number of antennas in the antenna arrangement may be able to provide more separations than those obtained by always including one "base" antenna (i.e., antenna A) in every element combination.

Referring to **FIG. 3**, a plan view drawing of a portion of a story of a

25 building **300** in which electronic devices using antenna diversity is shown, in accordance with an embodiment of the present invention. In the portion of the building **300** is located a transmitting antenna **315** that transmits a radio frequency (RF) signal that is modulated to include information within an RF bandwidth. The portion of the building **300** includes structures such as offices

30 and cubicles (some offices **310** and cubicles **305** are identified in **FIG. 3**) that act, along with other items, such as ductwork and wiring, as electromagnetic scatterers for the frequencies within the RF bandwidth. Electronic devices

320, 325 are located at two different locations in the portion of the building **300**. Each of the electronic devices **320, 325** includes an arrangement of antennas in antenna systems that are used to intercept the RF radio signal and thereby facilitate recovery of the information in the modulated RF signal (also described as simply recovering the modulated radio signal). The RF frequencies within the RF bandwidth are preferably such that the arrangement of antennas can include effective antennas and such that the arrangement of antennas does not substantially increase the volume occupied by the electronic devices **320, 325** above that needed for one efficient antenna. For example, at 5 GHz and above, an arrangement of antennas having antennas at separations up to one wavelength may be smaller than 6 centimeters in a longest dimension. The antenna system **205** illustrated in **FIG. 2** (showing dual polarized antennas at five positions), is a example of a system that may be used in the electronic devices **320, 325**, but the arrangements of antennas could have more or fewer antennas in them.

The present invention includes unique techniques for selecting antenna element combinations from the arrangement of antennas that optimize a combined signal that is recovered using the selected element combinations. For receivers **320, 325** that are intended to be used in a variety of locations, the ability to optimize the selection of antenna elements is advantageous because the receivers of one type of equipment (including the arrangement of antennas) can be manufactured identically and do not require manual settings. The present invention is of course also applicable at lower frequencies where the arrangement of antennas may be physically large in comparison to the receiver, and may provide distinct advantages in some circumstances (for example, when the scattering environment is expected to change substantially with time).

One technique for selecting the optimum set of antenna elements uses external information **212 (FIG. 2)** that is received by the device **320, 325**. The external information **212** identifies the electromagnetic scattering environment (EME) type. Two examples of such external information **212** are an operator input an a simulation input, which are classifications of external information

according to the source that makes the determination. The external information may be conveyed by local means such as a keyboard or by a message sent to the electronic device **320, 325**. The external information is accepted by the device controller **210** and passed to the antenna system controller **225** in antenna controller signal **211**, which uses the external information **212** and a table that stores information that correlates an EME type to a best antenna element combination. The best antenna element combination has a separation closest to the optimum separation of antenna elements described with reference to **FIG. 1** and is preferably equal to the optimum separation, but may have to be different due to physical design constraints for the device **320, 325**. Radio signals from the antenna elements of the best element combination are combined and used to generate a demodulated signal **227**. The demodulated signal **227** is used in most devices **320, 325** to recover information that is used by at least one application that is run by the device controller. Examples of applications are direction detection, location finding, speed detection and handoff algorithms. The selection of the best antennas elements can be beneficially modified according to which application is using the demodulated radio signal **227**, so in some embodiments the device controller **210** identifies the application using the demodulated radio signal **227** to the antenna system controller **225** and the antenna system controller **225** uses the identification of the one application and the electromagnetic scattering environment type to select the best element combination.

Another technique for selecting the best set of antenna elements uses correlation coefficient measurements determined from the demodulated radio signal **227** as it is received at each element combination of a set of element combinations. For the antenna arrangement of the example described above with reference to FIGS. 1 and 2, this amounts to measuring the correlation coefficients for the antenna elements having the same polarization in antennas A-B, A-C, A-D, and A-E. The antenna system controller **225** then selects an element combination that has a lowest correlation coefficient of elements having the same polarization when the lowest correlation coefficient

CML00925U

is below a threshold value and otherwise selects an orthogonally polarized element combination. The threshold value may be, for example, 0.80

In yet another technique for selecting the best set of antenna elements, current correlation coefficient measurements determined from the

5 demodulated radio signal **227** are measured as in the previously described technique. However, in this technique, the device controller **210** identifies an application to the antenna system controller **225** that is using the demodulated radio signal **227**, and the antenna system controller **225** uses the identified application in combination with the measured correlation coefficients and prior
10 information to determine the best element combination. For this technique, the antenna controller may comprise an intelligent network, such as a fuzzy logic processor or a neural network to provide speedier and better selections, and prior information comprising all the measured or simulated correlation coefficients determined for each EME type during a design phase are used to
15 select the best element combination.

In the foregoing specification, the invention and its benefits and advantages have been described with reference to specific embodiments. However, one of ordinary skill in the art appreciates that various modifications and changes can be made without departing from the scope of the present
20 invention as set forth in the claims below. Accordingly, the specification and figures are to be regarded in an illustrative rather than a restrictive sense, and all such modifications are intended to be included within the scope of present invention. The benefits, advantages, solutions to problems, and any element(s) that may cause any benefit, advantage, or solution to occur or
25 become more pronounced are not to be construed as a critical, required, or essential features or elements of any or all the claims.

As used herein, the terms "comprises," "comprising," or any other variation thereof, are intended to cover a non-exclusive inclusion, such that a process, method, article, or apparatus that comprises a list of elements does
30 not include only those elements but may include other elements not expressly listed or inherent to such process, method, article, or apparatus.

CML00925U

The term "plurality", as used herein, is defined as two or more than two. The term "another", as used herein, is defined as at least a second or more. The terms "including" and/or "having", as used herein, are defined as comprising. The term "coupled", as used herein with reference to electro-
5 optical technology, is defined as connected, although not necessarily directly, and not necessarily mechanically. The term "program", as used herein, is defined as a sequence of instructions designed for execution on a computer system. A "program", or "computer program", may include a subroutine, a function, a procedure, an object method, an object implementation, an
10 executable application (an application), an applet, a servlet, a source code, an object code, a shared library/dynamic load library and/or other sequence of instructions designed for execution on a computer system. A "set" as used herein, means a non-empty set (i.e., for the sets defined herein, comprising at least one member)

15 What is claimed is:

CLAIMS

1. A method for using a arrangement of antennas to recover a modulated radio signal, comprising:

- 5 identifying an electromagnetic scattering environment type as one of a set of electromagnetic scattering environment types;
 selecting a best element combination from the arrangement of antennas based on the electromagnetic scattering environment type; and
 combining radio signals intercepted by the best element combination.

10

2. The method according to claim 1, wherein the identifying of the electromagnetic scattering environment type comprises using a current set of correlation coefficient measurements made using a radio signal received at each best element combination of a set of element combinations and prior
15 information obtained using the set of electromagnetic scattering environment types.

3. A method for using an arrangement of antennas to recover a modulated radio signal, comprising:

- 20 measuring a set of correlation coefficients, each correlation coefficient determined using a radio signal intercepted at each element of a corresponding element combination having a first polarization orientation, each corresponding element combination formed from two elements in the arrangement of antennas;
25 determining a lowest correlation coefficient of the set of correlation coefficients; and
 combining radio signals intercepted by the element combination corresponding to the lowest correlation coefficient when the lowest correlation coefficient has a value below a threshold value;
30 combining radio signals intercepted by two orthogonally oriented elements of the arrangement of antennas when the lowest correlation coefficient has a value above the threshold value.

4. An antenna system, comprising:
 an antenna structure, comprising
 an arrangement of antennas, each antenna comprising at least
5 one element that has a common polarization, and at least one antenna that is
a dual polarized antenna;
 a signal combiner that combines radio signals intercepted by an
element combination into a combined radio signal; and
 a switching matrix that selects a best element combination of the
10 arrangement of antennas.
5. The antenna system according to claim 4, wherein the arrangement of
antennas is characterized by a set of antenna separations that are optimized
to provide lowest correlation coefficients for a corresponding set of
15 electromagnetic environment types.
6. The antenna system according to claim 4, wherein the best element
combination is one of a dual polarized element combination and a separated
element combination, and wherein the dual polarized element combination
20 comprises two orthogonal elements of an antenna in the arrangement of
antennas that is a dual polarized antenna, and wherein the separated element
combination comprises two elements having the same polarization selected
from two antennas of the arrangement of antennas.
- 25 7. The antenna system according to claim 4, further comprising:
 a signal receiver, coupled to the arrangement of antennas, that
generates a demodulated signal from the combined radio signal; and
 an antenna system controller coupled to the signal receiver and
antenna structure that selects the best element combination based on an
30 electromagnetic scattering environment type identified from a set of
electromagnetic scattering environment types.

8. The antenna system according to claim 7, further comprising:
a device controller, coupled to the signal receiver, that processes the demodulated signal to recover information that is used by at least one application that is run by the device controller.

5

9. The antenna system according to claim 4, further comprising:
a signal receiver, coupled to the arrangement of antennas, that generates a demodulated signal from the combined radio signal; and
an antenna system controller coupled to the signal receiver and
10 antenna structure that selects the best element combination based on correlation coefficient measurements made using a radio signal received at each element combination of a set of element combinations.

10. A method for establishing an optimum diversity antenna arrangement for
15 recovering a modulated radio signal that is intercepted by the diversity antenna arrangement, comprising:

identifying a set of electromagnetic environment types that comprises distinct radio environments for a particular frequency range;

determining a set of optimum antenna separations for the set of
20 electromagnetic environment types, wherein each optimum antenna separation provides a minimum correlation coefficient; and

establishing the optimum diversity antenna arrangement by
determining an arrangement of antennas that provides a plurality of antenna separations determined from the set of optimum antenna separations and
25 includes at least one dual polarized antenna.





FIG. 1

FIG. 2






FIG. 3