



(22) Date de dépôt/Filing Date: 1992/11/18

(41) Mise à la disp. pub./Open to Public Insp.: 1993/05/27

(45) Date de délivrance/Issue Date: 2007/06/05

(62) Demande originale/Original Application: 2 339 887

(30) Priorité/Priority: 1991/11/19 (US07/792,869)

(51) Cl.Int./Int.Cl. *H04Q 7/30* (2006.01),
H04B 7/005 (2006.01)


(72) Inventeur/Inventor:
SCHILLING, DONALD L., US

(73) Propriétaire/Owner:
INTERDIGITAL TECHNOLOGY CORPORATION, US

(74) Agent: SIM & MCBURNEY

(54) Titre : DISPOSITIF ET METHODE DE COMMANDE D'ALIMENTATION ADAPTATIVE POUR SYSTEME DE COMMUNICATION A ETALEMENT DU SPECTRE

(54) Title: ADAPTIVE POWER CONTROL FOR A SPREAD SPECTRUM COMMUNICATIONS SYSTEM AND METHOD



(57) Abrégé/Abstract:

An apparatus and method for adaptive-power control of a spread-spectrum transmitter of a mobile station operating in a cellular-communications network using spread-spectrum modulation. A base station transmits a first spread-spectrum signal. A mobile station has an automatic-gain-control circuit for generating an AGC-output signal, from a received signal. The received signal includes the first spread-spectrum signal and an interfering signal. The mobile station also has a correlator for despreading the AGC-output signal, a power-measurement circuit responsive to processing the received signal with the despread AGC-output signal for generating a received-power level, a comparator coupled to the power-measurement circuit for generating a comparison signal by comparing the received-power level to a threshold level, a transmitter for transmitting a second spread-spectrum signal, an antenna, and a variable-gain device responsive to the comparison signal for adjusting a transmitter-power level of the second spread-spectrum signal.

-19-

Abstract

An apparatus and method for adaptive-power control of a spread-spectrum transmitter of a mobile station operating in a cellular-communications network using spread-spectrum modulation. A base station transmits a first spread-spectrum signal. A mobile station has an automatic-gain-control circuit for generating an AGC-output signal, from a received signal. The received signal includes the first spread-spectrum signal and an interfering signal. The mobile station also has a correlator for despreading the AGC-output signal, a power-measurement circuit responsive to processing the received signal with the despread AGC-output signal for generating a received-power level, a comparator coupled to the power-measurement circuit for generating a comparison signal by comparing the received-power level to a threshold level, a transmitter for transmitting a second spread-spectrum signal, an antenna, and a variable-gain device responsive to the comparison signal for adjusting a transmitter-power level of the second spread-spectrum signal.

-1-

ADAPTIVE POWER CONTROL FOR A SPREAD
SPECTRUM COMMUNICATIONS SYSTEM AND METHOD

BACKGROUND OF THE INVENTION

5 This invention relates to spread-spectrum
communications, and more particularly to an apparatus and
method for adaptive power control of a spread-spectrum
signal in a cellular, personal communications environment.

DESCRIPTION OF THE PRIOR ART

10 A spread-spectrum signal typically is generated by
modulating an information-data signal with a chip-code
signal. The information-data signal may come from a data
device such as a computer, or an analog device which outputs
an analog signal which has been digitized to an
information-data signal, such as voice or video. The
15 chip-code signal is generated by a chip-code where the time
duration, T_c , of each chip is substantially less than a data
bit or data symbol.

Spread-spectrum modulation provides means for
communicating in which a spread-spectrum signal occupies a
20 bandwidth in excess of the minimum bandwidth necessary to
send the same information. The band spread is accomplished
using a chip code which is independent of an
information-data signal. A synchronized reception with the
chip-code at a receiver is used for despreading the
25 spread-spectrum signal and subsequent recovery of data from
the spread-spectrum signal.

Spread-spectrum modulation offers many advantages as a
communications system for an office or urban environment.
These advantages include reducing intentional and
30 unintentional interference, combating multipath problems,
and providing multiple access to a communications system
shared by multiple users. Commercially, these applications
include, but are not limited to, local area networks for
computers and personal communications networks for
35 telephone, as well as other data applications.

-2-

A cellular communications network using spread-spectrum modulation for communicating between a base station and a multiplicity of users, requires control of the power level of a particular mobile user station. Within a particular cell, a mobile station near the base station of the cell may be required to transmit with a power level less than that when the mobile station is near an outer perimeter of the cell. This is done to ensure a constant power level at the base station, received from each mobile station.

In a first geographical region, such as an urban environment, the cellular architecture within the first geographical region may have small cells which are close to each other, requiring a low power level from each mobile user. In a second geographical region, such as a rural environment, the cellular architecture within the region may have large cells which are spread apart, requiring a relatively high power level from each mobile user. A mobile user who moves from the first geographical region to the second geographical region must adjust the power level of his transmitter, for meeting the requirements of a particular geographic region. Otherwise, if the mobile user travels from a sparsely populated region with fewer spread out cells using the relatively higher power level with his spread-spectrum transmitter, to a densely populated region with many cells without reducing the power level of his spread-spectrum transmitter, his spread-spectrum transmitter may cause undesirable interference within the cell in which he is located and/or to adjacent cells.

Accordingly, there is a need to have a spread-spectrum apparatus and method for automatically controlling a mobile user's spread-spectrum transmitter power level when operating in a cellular communications network.

A general object of an aspect of the invention is an apparatus and a method which results in maximization of user density within

-3-

a cell domain while minimizing mobile user transmitted power.

An object of an aspect of the invention is to provide an apparatus and method which controls the power level of a mobile station so that the power level received at the base station of each cell is the same for each mobile station.

Another object of an aspect of the invention is to provide an apparatus and method for automatically and adaptively controlling the power level of a mobile user in a cellular communications network.

Another object of an aspect of the invention is to provide a spread-spectrum apparatus and method which allows operating a spread-spectrum transmitter in different geographic regions, wherein each geographic region has a multiplicity of cells, and cells within a geographic region may have different size cells and transmitter power requirements.

A further object of an aspect of the invention is a spread-spectrum apparatus and method which allows a large number of mobile users to interactively operate in a mobile cellular environment having different size cells and transmitter power requirements.

A still further object of an aspect of the invention is a spread-spectrum apparatus and method which controls the power level of a mobile user in a cellular communications network using a simple circuit.

An additional further object of an aspect of the invention is a spread spectrum apparatus and method which controls the power level of a mobile user even when the mobile user's receiver receives interference from a intentional or unintentional jammer.

An additional object of an aspect of the invention is an apparatus and method for automatically controlling a power level of a mobile user which is easy to implement.

35 SUMMARY OF THE INVENTION

According to the present invention, as embodied and broadly described herein, an apparatus for adaptive-power

-4-

control (APC) of a spread-spectrum transmitter is provided. A plurality of mobile stations operate in a cellular-communications network using spread-spectrum modulation. A base station transmits a first
5 spread-spectrum signal and an APC-data signal. The APC-data signal may be transmitted with or separate from the first spread-spectrum signal.

Each mobile station includes AGC means, correlator means, power means, comparator means, transmitter means, an
10 antenna, variable-gain means, and optionally decoder means. The correlator means is coupled to the AGC means. The power means is coupled to the AGC means and to the correlator means. The comparator means is coupled to the power means and the decoder means. The antenna is coupled to the
15 transmitter means. The variable-gain means is coupled to the comparator means and between the transmitter means and the antenna.

A received signal is defined herein to include the first spread-spectrum signal and an interfering signal. The
20 interfering signal is defined herein to include an noise and/or signals which are coexistent in frequency with the first spread-spectrum signal.

The decoder means decodes the APC-data signal from the first spread-spectrum signal as a threshold level. For each
25 received signal, the AGC means generates an AGC-output signal. The correlator means despreads the AGC-output signal. The power means processes the received signal with the despread AGC-output signal for generating a received-power level. The comparator means generates a
30 comparison signal by comparing the received-power level to the threshold level. The comparison signal may be an analog or digital data signal. The transmitter means at the mobile station transmits a second spread-spectrum signal. The variable-gain means uses the comparison signal as a basis
35 for adjusting a transmitter-power level of the second spread-spectrum signal transmitted from the transmitter means.

-5-

The present invention also includes a method for automatic-power control of a spread-spectrum transmitter for a mobile station operating in a cellular-communications network using spread-spectrum modulation. A base station
5 transmits a first spread-spectrum signal and an APC-data signal. The APC-data signal typically is a spread-spectrum signal. Each mobile station performs the steps of acquiring the first spread-spectrum signal transmitted from the base station, and detecting a received power level of the first
10 spread-spectrum signal plus any interfering signal including noise. The steps also include decoding the APC-data signal as a threshold level, from the first spread-spectrum signal, or from a signal or channel separate from the first spread-spectrum signal. The method generates an AGC-output signal
15 from the received signal, and despreads the AGC-output signal. The despread AGC-output signal is processed with the received signal to generate a received-power level. The method further includes comparing the received-power level to the threshold level, and adjusting a transmitter power
20 level of a second spread-spectrum signal in response to the comparison.

Additional advantages and objects of aspects of the invention are set forth in part in the description which follows, and in part are obvious from the description, or
25 may be learned by practice of the invention. The advantages and objects of aspects of the invention also may be realized and attained by means of the instrumentalities and combinations particularly pointed out in the appended claims.

30 In accordance with one aspect of the present invention, there is provided a spread spectrum base station comprising:

an automatic gain control (AGC) circuit having an input configured to receive a received spread spectrum
35 signal and gain control the received spread spectrum signal to produce a gain controlled signal;

a correlation circuit having an input configured to receive the gain controlled signal and correlate the gain

-5a-

controlled signal with a code to produce a despread signal;

a power measurement and comparator circuit configured to receive the despread signal and a control level of the AGC circuit and processing at least the despread signal and

5 the control level to produce a processed signal and comparing the processed signal with a threshold to produce a comparison signal, the comparison signal used to produce a power command; and

10 a multiplexer for multiplexing the power command with a signal for transmission over an antenna.

In accordance with another aspect of the present invention, there is provided a method comprising:

receiving a spread spectrum signal;

15 gain controlling the received spread spectrum signal by an automatic gain control (AGC) circuit to produce a gain controlled signal;

correlating the gain controlled signal with a code to produce a despread signal;

20 processing at least the despread signal and a control level of the AGC circuit producing a processed signal;

comparing the processed signal with a threshold to produce a comparison signal;

producing a power command using the comparison signal; and

25 multiplexing the power command with a signal for transmission over an antenna.

In accordance with yet another aspect of the present invention, there is provided a spread spectrum base station comprising:

30 an automatic gain control (AGC) circuit having an input configured to receive a received spread spectrum signal and gain control the received spread spectrum signal to produce a gain controlled signal;

35 a correlation circuit having an input configured to receive the gain controlled signal and correlate the gain controlled signal with a code to produce a despread signal;

a power measurement circuit configured to receive the despread signal and a control level of the AGC circuit

-5b-

and processing at least the despread signal and the control level to produce a processed signal;

5 a comparator circuit configured to compare the processed signal with a threshold to produce a comparison signal, the comparison signal used to produce a power control word; and

a voltage controlled attenuator for adjusting a transmission power level of a signal for transmission over an antenna in response to the power control word.

10 In accordance with still another aspect of the present invention, there is provided a method comprising:

receiving a spread spectrum signal by an automatic gain control circuit;

15 gain controlling the received spread spectrum signal by an AGC circuit to produce a gain controlled signal;

correlating by a correlation circuit the gain controlled signal with a code to produce a despread signal;

20 processing by a power measurement at least the despread signal and a control level of the AGC circuit producing a processed signal;

comparing by a comparator circuit the processed signal with a threshold to produce a comparison signal;

25 producing by a control word generator a power control word using the comparison signal; and

adjusting by a voltage controlled attenuator a transmission power level of a signal for transmission over an antenna in response to the power control word.

30 BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which are incorporated in and constitute a part of the specification, illustrate preferred embodiments of the invention, and together with the description serve to explain the principles of the invention.

35 FIG. 1 shows an adaptive power control receiver and transmitter according to the present invention;

-6-

FIG. 2 shows an adaptive power control receiver and transmitter according to the present invention;

FIG. 3 is a block diagram of an automatic power control circuit with interference rejection;

5 FIG. 4 is a block diagram of an open loop automatic power control system;

FIG. 5 is a block diagram of an open loop automatic power control system with interference rejection;

10 FIG. 6 shows the relative effect of a multiplicity of users communicating with spread-spectrum in a cellular environment with and without using adaptive power control; and

FIG. 7 is a flow chart of the method of the present invention.

15 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

Reference is now made in detail to the present preferred embodiments of the invention, examples of which are illustrated in the accompanying drawings, wherein like reference numerals indicate like elements throughout the
20 several views.

The present invention assumes that a plurality of mobile stations operate in a cellular-communications network using spread-spectrum modulation. The cellular communications network has a plurality of geographical
25 regions, with a multiplicity of cells within a geographical region. The size of the cells in a first geographical region may differ from the size of the cells in a second geographical region. In a first geographical region such as an urban environment, a cellular architecture within the
30 region may have a large number of cells of small area which are close to each other. In a second geographical region such as a rural environment, a cellular architecture within the region may have cells of larger area.

A mobile station while in the first geographical region
35 may be required to transmit a lower power level than while in the second geographical region. This requirement might

-7-

be due to a decreased range of the mobile station from the base station. Within a particular cell, a mobile station near the base station of the cell may be required to transmit with a power level less than that when the mobile station is near an outer perimeter of the cell. This is done to ensure a constant power level at the base station, received from each mobile station.

In the present invention, a base station within a particular cell transmits a first spread-spectrum signal and optionally an APC-data signal. The APC-data signal may be transmitted as part of the first spread-spectrum signal, on a separate spread-spectrum channel, or as a totally separate signal. The APC-data signal includes information on the threshold level each mobile station is to use when communicating with the base station. If an APC-data signal were not used, then the threshold level may be fixed at a preset level for each mobile station communicating with the base station.

The APC-data signal may be transmitted with or separate from the first spread-spectrum signal. For example, a spread-spectrum signal using a first chip codeword may be considered a first spread-spectrum channel having the first spread-spectrum signal, and a spread-spectrum signal using a second chip codeword may be considered a second spread-spectrum channel. The APC-data signal may be transmitted in the same spread-spectrum channel, i.e. the first spread-spectrum channel, as the first spread-spectrum signal, or in a second spread-spectrum channel which is different from the first spread-spectrum signal.

In the exemplary arrangement shown in FIG. 1, an apparatus for adaptive-power control of a spread-spectrum transmitter is provided. Each mobile station comprises correlator means, detector means, decoder means, comparator means, transmitter means, an antenna, and first variable-gain means. The apparatus, by way of example, may have the correlator means embodied as a first product device 101, a first chip-code generator 102, and a bandpass filter

-8-

103. Alternatively, the correlator means may be realized as a matched filter such as a surface-acoustic-wave device. In general, the correlator means uses or is matched to the chip codeword of the spread-spectrum signal being received.

5 The detector means may be embodied as envelope detector 104. Other type detectors may be used with the present invention, such as square law detectors or coherent detectors, as is well known in the art. The decoder means may be embodied as decoder 105. The comparator means may be embodied as differential amplifier 106, the transmitter means as transmitter 112 and the first variable gain means as first variable-gain device 111. The first variable-gain device 111 may be a variable-gain amplifier, a variable-gain attenuator or any device which performs the same function as the first variable-gain device 111 and described herein.

15 The first product device 101 is coupled to the first chip-code generator 102 and to the bandpass filter 103. The envelope detector 104 is coupled between the bandpass filter 103 and the differential amplifier 106. The decoder 105 is coupled between the bandpass filter 103 and the differential amplifier 106. The decoder 105 alternatively may be coupled to the output of the envelope detector 104. The variable-gain device 111 is coupled to the differential amplifier 106 and between the transmitter 112 and antenna.

25 The decoder 105, as illustratively shown in FIG. 2, alternatively may be coupled between a second bandpass filter 203 and differential amplifier 106. In this particular embodiment, the second bandpass filter 203 is coupled to a second product device 201. The second product device 201 is connected to a second chip-code generator 202. The embodiment of FIG. 2 could be used where the APC-data signal is transmitted over the second spread-spectrum channel simultaneously while the first spread-spectrum signal is transmitted over the first spread-spectrum channel. The second channel uses a spread-spectrum signal with a second chip code, and the second chip-code generator

-9-

202 generates a second chip-code signal using the second chip code.

5 The product device 101, FIGS. 1 or 2, using a first chip-code signal from the first chip-code generator 102 acquires the first spread-spectrum signal transmitted from the base station. The first chip-code signal has the same chip code as the first spread-spectrum signal. The envelope detector 104 detects a received power level of the first spread-spectrum signal. The received power level may be measured at the detector.

10 The decoder 105 decodes the APC-data signal from the first spread-spectrum signal as a threshold level. More particularly, data which establishes or sets the threshold level for differential amplifier 106 is sent with the APC-data signal.

15 The differential amplifier 106 generates a comparison signal by comparing the received power level of the first spread-spectrum signal to the threshold level. The differential amplifier 106 may employ a differential amplifier or other circuits for performing the comparison function.

20 The transmitter 112 transmits a second spread-spectrum signal. The variable-gain device 111 using the comparison signal, adjusts a transmitter-power level of the second spread-spectrum signal from the transmitter. The variable-gain device 111 may be realized with a variable-gain amplifier, a variable-gain attenuator, or an equivalent device which can adjust the power level of the second spread-spectrum signal.

25 As illustratively shown in FIG. 3, a block diagram of a power measurement circuit with interference rejection is shown for use with a mobile station. A correlator is shown with the mixer 67 coupled between the chip-code generator 75 and filter 68. Additionally, AGC means and power means are included. The AGC means is embodied as an automatic-gain-control (AGC) circuit 61, and the power means is embodied as a power measurement circuit 75. As shown in FIG. 3, the AGC


circuit 61 is connected to the mixer 67, and the output of the filter 68 is connected to the power measurement circuit 75. Additionally, the input to the AGC circuit 61 is connected to the power measurement circuit 75.

A received signal includes a first spread-spectrum signal with power P_C and an interfering signal with power at the input to the circuit of FIG. 3. The interfering signal may come from one or more nondesirable signals, noise, multipath signals, and any other source which would serve as an interfering signal to the first spread-spectrum signal. The received signal is normalized by the AGC circuit 61. Thus, by way of example, the AGC circuit 61 can have the power output, $P_C + P_J = 1$. The normalized received signal is despread by the correlator, which in this case is shown by way of example the mixer 67, chip-code generator 65 and filter 68. The chip-code generator 65 generates a chip-code signal using the same chip-codeword as the first spread-spectrum signal. The despread signal is filtered by filter 68, and the output of the filter 68 is the normalized power of the first spread-spectrum signal plus the normalized power of the interfering signal divided by the processing gain, P_G of the spread-spectrum system. The power measurement circuit 75 can process the despread-received signal with the received signal and output the received-power level of the first spread-spectrum signal. The power level of the interfering signal is reduced by the processing gain, P_G .

The power measurement circuit 75 can process the received signal with the despread, normalized received signal by multiplying the two signals together, or by logarithmically processing the received signal with the despread received signal. In the latter case, the

- 10a-

logarithm is taken of the power of the received signal, $P_c + P_J$, and the logarithm is taken of the despread, normalized received signal. The two logarithms are added together to produce the received-power level. This received-power level maybe multiplexed with a signal for subsequent transmission over an antenna.



-11-

A key element for the present invention to work is the circuitry of FIG. 3. FIG. 3 shows a way for determining at the mobile station the power of the first spread-spectrum signal when it is mixed with noise. If the circuitry of FIG. 3 were not used, then it is possible that the interfering signal, which may include noise, multipath signals, and other undesirable signals, may raise the power level measured at the input to the receiver of the remote station, giving an undesirable power level. The undesirable power level measured may cause the remote station to transmit more power than required, increasing the amount of power received at the base station 50.

FIG. 4 shows a block diagram of an open loop automatic power control processing unit, where the comparator receives the threshold level information provided by the cell. More particularly, antenna 55 is coupled to an RF filter 57. An intermediate frequency (IF) down-converter 59 is coupled between the RF filter 57 and an AGC amplifier 71. The output of the AGC amplifier 71 is passed to receiver processing.

The AGC amplifier 71 can have its output or a voltage level used as an AGC-control voltage. A control-voltage mapping 73 is coupled between the AGC amplifier 71 and a comparator 70. The comparator 70 is coupled to the demultiplexer 69 and to a control-word generator 59. A voltage-controlled amplifier 77 is coupled to the control-word generator 59, transmitter and power amplifier 58. The power amplifier 58 is coupled to an antenna 56.

In FIG. 4, a received spread-spectrum signal from antenna 55 is bandpass filtered by RF filter 57 and converted to an IF by down-converter 59. The AGC amplifier 71 normalizes the voltage of the received spread-spectrum signal, and also generates an AGC-control voltage. The control-voltage mapping 73 maps the AGC-control voltage for comparator 70. The comparator 70 compared the mapped-AGC-control voltage to a threshold level, which is provided by demultiplexer 69.

-12-

The comparison signal generated by comparator 70 is converted by control word generator 59 to control voltage-controlled attenuator 77. Accordingly, the voltage-controlled attenuator 77 adjusts the power level from the transmitter and inputted to power amplifier 58 and radiated by antenna 56.

FIG. 5 illustrates the open loop automatic power control circuit of FIG. 4, with the concepts from FIG. 3 added thereto. Shown in FIG. 5 are power means, comparator means, transmitter means, an antenna, variable-gain means and decoder means. The AGC means is shown as an automatic-gain-control (AGC) amplifier 72, correlator means is shown as correlator 74 with filter 76, and power means is shown as power measurement device 78. The comparator means is shown as comparator 70, the transmitter means is shown as power amplifier 58 coupled to the antenna 56. The variable gain means is embodied as voltage controlled attenuator 77 and the decoder means is illustrated as demultiplexer 69. Also illustrated is a control word generator 59 coupled between comparator 70 and voltage controlled attenuator 77.

The AGC amplifier 72 is coupled between the bandpass filter 60 and the correlator 74. The filter 76 is coupled to the output of the correlator 74. The power measurement device 78 is coupled to the AGC amplifier 72 and the filter 76. The comparator 70 is coupled to the output of the power measurement device 78 and to the demultiplexer 69. The control word generator 59 is coupled between the comparator 70 and the voltage controlled attenuator 77. The power amplifier 58 is coupled to the output of the voltage controlled attenuator 77 and the antenna 56.

The demultiplexer 69 decodes the APC-data signal, which is received with the first spread-spectrum signal, as a threshold level. The threshold level is used by the comparator 70 as a comparison for the received-power level measured by the power measurement device 78.

For each received signal, the AGC amplifier 72 generates an AGC-output signal. The AGC-output signal is

-13-

despread using correlator 74 and filter 76. The despread-AGC-output signal from the filter 76 is processed with the received signal from the AGC amplifier 72, by the power measurement device 78. The received signal to the power measurement device 78 may be a AGC-control-voltage level from the AGC amplifier 72.

The power measurement device 78 processes the received signal with the despread-AGC-output signal, for generating a received-power level. As mentioned previously for FIG. 3, the power measurement device 78 can process the received signal with the despread-AGC-output signal by multiplying the two signals together, or by logarithmically processing the received signal with the despread-AGC-output signal.

The comparator 70 generates a comparison signal by comparing the received-power level generated by the power measurement device 78, to the threshold level provided by the demultiplexer 69. The comparison signal may be an analog or digital data signal. Broadly, the control word generator 59 can convert the comparison signal to a digital data signal for controlling the voltage controlled attenuator 77. The voltage controlled attenuator 77 uses the comparison signal, as processed by the control word generator 59, as a basis for adjusting a transmitter-power level of a second spread-spectrum signal transmitted by the power amplifier 58, and radiated by the antenna 56.

In operation, a base station in a cell may transmit the first spread-spectrum signal on a continuous basis or on a repetitive periodic basis. Mobile stations within the cell receive the first spread-spectrum signal. The received first spread-spectrum signal is acquired and despread with the first chip-code signal from first chip-code generator 102 and first product device 101. The despread first spread-spectrum signal is filtered through bandpass filter 103. The mobile station detects the despread first spread-spectrum signal using envelope detector 104, and measures the received power level of the first spread-spectrum signal.

-14-

The APC-data signal may be transmitted on the same channel as the first spread-spectrum signal using the same chip codeword as the first spread-spectrum signal. In this case, the APC-data signal is transmitted at a different time interval from when the first spread-spectrum signal is transmitted. This format allows the mobile station to acquire synchronization with the first chip-code, using the first spread-spectrum signal.

As an alternative, the APC-data signal may be transmitted on a different coded channel using a second chip codeword. In the latter case, the second spread-spectrum signal having the APC-data signal would be acquired by the second chip-code generator 202 and second product device 201. In either case, the APC-data signal is decoded using decoder 105. Further, the APC-data signal may be time division multiplexed or frequency division multiplexed with the first spread-spectrum signal.

The decoder 105 decodes from the APC-data signal the value of the threshold level for use by differential amplifier 106. For example, if there were eight levels for which to set the threshold level, then at minimum, a three bit word may be used with the APC-data signal to transmit the threshold level to the mobile station. The threshold level is used to adjust and or set the threshold of the differential amplifier 106. Accordingly, the received power level from envelope detector 104 is compared to the threshold of the differential amplifier 106.

If the received power level is greater than the threshold level, then the first variable-gain device 111 would decrement or decrease the second spread-spectrum power level. If the received power level is less than the threshold at differential amplifier 106, then the first variable-gain device 111 increases the second spread-spectrum power.

The APC circuit 110 of FIGS. 1 and 2 may be built on a digital signal processor (DSP) chip. An analog to digital converter located at the output of the bandpass filter 103

-15-

would convert the received signal to a data signal. The envelope detector 104, decoder 105 and differential amplifier 106 may be implemented as part of digital signal processing functions on the DSP chip. The analog to digital converters may be included on the DSP chip.

FIG. 7 shows the advantage of using an adaptive power control apparatus with a mobile station in a personal communications network. The number of adaptive power control mobile stations, $N(\text{APC})$, versus the number of mobile stations which can be used in a similar region, N , is plotted with respect to an inner radius, R_i , and an outer radius, R_o . When the inner radius goes to zero, using spread-spectrum as code division multiplex, the number of users with adaptive power control who can operate within a cell, is approximately ten times the number of users without adaptive power control who can operate within the cell.

The present invention also includes a method for automatic-power control of a spread-spectrum transmitter for a mobile station operating in a cellular-communications network using spread-spectrum modulation. Referring to FIG. 8, a base station transmits 701 a first spread-spectrum signal and optionally an APC information-data signal. Each mobile base station performs the steps of acquiring 702 the first spread-spectrum signal transmitted from the base station, and detecting 703 a received power level of the first spread-spectrum signal. The steps also include decoding 704 the APC-data signal as a threshold level, from the first spread-spectrum signal, or from a separate signal from the first spread-spectrum signal. A threshold level is set 705 from the APC-data signal. A preset threshold level may be employed if the APC-data signal is not used. The method further includes comparing 706 the received power level to the threshold level, and adjusting 707 a transmitter power level of a second spread-spectrum signal in response to the comparison.

The method may additionally include generating from a received signal an AGC-output signal, and despreading the

-16-

AGC-output signal. The received signal includes the first spread-spectrum signal and an interfering signal. The received signal is processed with the despread AGC-output signal to generate a received-power-level. The method then
5 generates a comparison signal by comparing the received-power level to the threshold level. While transmitting a second spread-spectrum signal, the method adjusts a transmitter-power level of the second spread-spectrum signal from the transmitter using the
10 comparison signal.

It will be apparent to those skilled in the art that various modifications can be made to the method and apparatus for adaptively controlling a power level of a spread-spectrum signal in a cellular environment of the
15 instant invention without departing from the scope or spirit of the invention, and it is intended that the present invention cover modifications and variations of the method and apparatus for adaptively controlling a power level of a spread-spectrum signal in a cellular environment provided
20 they come in the scope of the appended claims and their equivalents.

-17-

WE CLAIM:

1. A spread spectrum base station comprising:
 - an automatic gain control (AGC) circuit having an
5 input configured to receive a received spread spectrum
signal and gain control the received spread spectrum
signal to produce a gain controlled signal;
 - a correlation circuit having an input configured to
receive the gain controlled signal and correlate the gain
10 controlled signal with a code to produce a despread
signal;
 - a power measurement and comparator circuit
configured to receive the despread signal and a control
level of the AGC circuit and processing at least the
15 despread signal and the control level to produce a
processed signal and comparing the processed signal with
a threshold to produce a comparison signal, the
comparison signal used to produce a power command; and
 - a multiplexer for multiplexing the power command
20 with a signal for transmission over an antenna.
2. A method comprising:
 - receiving a spread spectrum signal;
 - gain controlling the received spread spectrum signal
25 by an automatic gain control (AGC) circuit to produce a
gain controlled signal;
 - correlating the gain controlled signal with a code
to produce a despread signal;
 - processing at least the despread signal and a
30 control level of the AGC circuit producing a processed
signal;
 - comparing the processed signal with a threshold to

produce a comparison signal;

producing a power command using the comparison signal; and

multiplexing the power command with a signal for transmission over an antenna.

3. A spread spectrum base station comprising:

an automatic gain control (AGC) circuit having an input configured to receive a received spread spectrum signal and gain control the received spread spectrum signal to produce a gain controlled signal;

a correlation circuit having an input configured to receive the gain controlled signal and correlate the gain controlled signal with a code to produce a despread signal;

a power measurement circuit configured to receive the despread signal and a control level of the AGC circuit and processing at least the despread signal and the control level to produce a processed signal;

a comparator circuit configured to compare the processed signal with a threshold to produce a comparison signal, the comparison signal used to produce a power control word; and

a voltage controlled attenuator for adjusting a transmission power level of a signal for transmission over an antenna in response to the power control word.

4. A method comprising:

receiving a spread spectrum signal by an automatic gain control circuit;

gain controlling the received spread spectrum signal by an AGC circuit to produce a gain controlled signal;

correlating by a correlation circuit the gain controlled signal with a code to produce a despread

signal;

processing by a power measurement at least the despread signal and a control level of the AGC circuit producing a processed signal;

comparing by a comparator circuit the processed signal with a threshold to produce a comparison signal;

producing by a control word generator a power control word using the comparison signal; and

adjusting by a voltage controlled attenuator a transmission power level of a signal for transmission over an antenna in response to the power control word.







Fig. 3








Fig. 5

Fig. 6




Fig. 7