

(43) International Publication Date
3 September 2015 (03.09.2015)(51) International Patent Classification:
H03M 3/00 (2006.01)(21) International Application Number:
PCT/EP2015/053088(22) International Filing Date:
13 February 2015 (13.02.2015)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
14156565.5 25 February 2014 (25.02.2014) EP

(71) Applicant: AMS AG [AT/AT]; Schloss Premstätten, Tobelbader Str. 30, A-8141 Unterpremstätten (AT).

(72) Inventors: CHRISTEN, Thomas; Limmattalstrasse 406, CH-8049 Zürich (CH). FRÖHLICH, Thomas; Kratzgasse 14, CH-8307 Ottikon (CH). FITZI, Andreas; Rohrhaldenstr. 23, CH-8712 Stäfa (CH). PRELOG, Dusan; Mele 18a, 9252 Radenci (SI).

(74) Agent: EPPING HERMANN FISCHER PATENTANWALTSGESELLSCHAFT MBH; Schloßschmidstr. 5, 80639 München (DE).

(81) Designated States (unless otherwise indicated, for every kind of national protection available): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY, BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT, HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC, SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.


(84) Designated States (unless otherwise indicated, for every kind of regional protection available): ARIPO (BW, GH, GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ, TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU, TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK, SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, KM, ML, MR, NE, SN, TD, TG).

Published:

— with international search report (Art. 21(3))

(54) Title: DELTA-SIGMA MODULATOR AND METHOD FOR SIGNAL CONVERSION

FIG 1A



(57) Abstract: A delta-sigma modulator (10) comprises a modulator loop (11) and a code generator (12). The modulator loop (11) comprises a loop filter (18). The code generator (12) is configured to generate a generator signal (BS) that is realized as an extended Barker code. The code generator (12) comprises a generator output (23) that is coupled to the loop filter (18).

Description

DELTA-SIGMA MODULATOR AND METHOD FOR SIGNAL CONVERSION

- 5 The present invention relates to a delta-sigma modulator, an arrangement with two delta-sigma modulators and to a method for signal conversion.

A delta-sigma modulator typically comprises a loop-filter, a quantizer and a feedback digital-to-analog converter. A single-bit delta-sigma modulator is popular primarily
10 because of the inherent linearity of a single-bit feedback digital-to-analog converter. On the other hand, a single-bit quantizer makes the delta-sigma modulator a strongly non-linear system. The single-bit delta-sigma modulator consequently produces very large tones near the half of a sampling frequency, also referred to as idle tones, as a result of limit cycles. The idle tones are particularly relevant, if another signal near the half of the
15 sampling frequency interferes with a bit stream of the delta-sigma modulator. In this case, a tone gets folded down, for example, in the baseband.

Document US 2013/0135131 A1 refers to an idle tone suppression circuit comprising a sigma-delta analog-to-digital converter.

20

Publication Y. Matsuya et al, "A 16-bit Oversampling A-to-D Conversion Technology Using Triple-Integration Noise Shaping", IEEE Journal of Solid-State Circuits, Vol. SC-22, pp. 921-929, 1987, describes a monolithic audio analog-to-digital converter.

- 25 It is an object of the present invention to provide a delta-sigma modulator, an arrangement with two delta-sigma modulators and a method for signal conversion with a reduced probability for intermodulation of the idle tone with another signal.

The object will be achieved by the subject matter of the independent claims. Embodiments
30 and developments of the invention are defined in the dependent claims.

In an embodiment, a delta-sigma modulator comprises a modulator loop and a code generator. The modulator loop comprises a loop filter. The code generator is configured to

generate a generator signal that is an extended Barker code. The code generator comprises a generator output. The generator output is coupled to the loop filter.

Advantageously, the autocorrelation function of the generator signal realized as an extended Barker code shows very low off-peak values. Thus, the idle tone content within an output signal of the delta-sigma modulator has a low correlation, for example with an output signal of another delta-sigma modulator or a clock signal.

The code generator provides the generator signal via the generator output to the loop filter.

In an embodiment, every code of the extended Barker code contains at least the bits of a Barker code.

In an embodiment, the extended Barker code comprises a code out of a Barker code set.

The Barker code set consists of the code [1 -1], the code [1 1], the code [1 1 -1], the code [1 -1 1 1], the code [1 -1 -1 -1], the code [1 1 1 -1 1], the code [1 1 1 -1 -1 1 -1], the code [1 1 1 -1 -1 1 -1 -1 1 -1] and the code [1 1 1 1 1 -1 -1 1 1 -1 1 1]. The codes have the length of 2, 3, 4, 5, 7, 11 or 13 bit.

Two codes are considered to be identical even if the sequence starts with a different phase that is with a different initial value. For example, the code [1 1 -1] is equal to the codes [1 -1 1] and [-1 1 1].

In another way of writing the codes, the above-mentioned codes may obtain a [0] instead of a [-1].

In an alternative embodiment, the extended Barker code comprises a reversed code of a code of the Barker code set. A reversed code is achieved by changing the order of the bits of the above-mentioned codes such that the first bit becomes the last bit and the last bit of the above-mentioned codes becomes the first bit of the reversed code.

In an alternative embodiment, the extended Barker code comprises a negated code of a code of the Barker code set. A negated code is defined in such a manner that in the above-

mentioned Barker code set a [1] is replaced by a [-1], and a [-1] is replaced by a [1]. The extended Barker code also comprises the reversed form of the negated code of a code of the Barker code set. The codes of the Barker code set, the reversed codes and the negated codes result in very low values of the autocorrelation function.

5

In an alternative embodiment, the extended Barker code comprises a code achieved by adding a bit [1] or [-1] to one of the above-mentioned codes, that means the Barker code set as well as the reversed codes and the negated codes of the Barker code set. Optionally, the code having five bits, seven bits, eleven bits and thirteen bits are enlarged by one
10 further bit. A code generator for providing such a code can be obtained in an easier way in comparison to a code generator for a Barker code without an odd number of bits.

In an alternative embodiment, the extended Barker code comprises a compound Barker code. The compound Barker code is realized by a combination of one of the above-
15 mentioned codes with another of one of the above-mentioned codes. Thus, the length of the extended Barker code can be increased arbitrarily. For example, a compound Barker code can be realized by setting two different Barker codes in a series.

In an embodiment, every code of the extended Barker code is generated by using the bits
20 of a Barker code or reverting or negating or reverting and additionally negating the bits of a Barker code or combining at least two Barker codes into a compound Barker code. In a further development, a bit [1] or a bit [0] is added at any place in the sequence of bits of the code.

25 In an embodiment, the code generator comprises logic gates. The logic gates may dynamically store the extended Barker code.

In an embodiment, the code generator comprises a counter. For the realization of a Barker code having a first number N bits, a counter with N bits is realized.

30

In an embodiment, the counter comprises at least one memory unit and a logic circuit. An input of the logic circuit is coupled to an output of the at least one memory unit. An output

of the logic circuit is coupled to the output of the code generator. The at least one memory unit may be implemented as flip-flop.

In an embodiment, the modulator loop comprises a modulator input at which an input
5 signal is received and a modulator output at which an output signal of the delta-sigma modulator is provided. The loop filter is arranged between the modulator input and the modulator output.

In an embodiment, the code generator provides a constant signal as the generator signal,
10 when the input signal is higher than a predetermined value, and provides the extended Barker code signal, when the input signal is less than or equal to the predetermined value. Thus, the code generator only provides the extended Barker code in case of a low input signal at the modulator input.

In an alternative embodiment, the code generator provides a constant signal as the
15 generator signal, when the output signal is higher than a predetermined value, and provides the extended Barker code signal, when the output signal is less than or equal to the predetermined value. Thus, the code generator only provides the extended Barker code in case of a low output signal at the modulator output.

In an embodiment, the constant signal is equal to zero. Thus, it is avoided to add the
20 generator signal realized as the extended Barker code to existing signals of the modulator loop in case the input signal and/or the output signal obtain high values. Thus, the signals inside the modulator loop do not rise above a limit for operation.

In an embodiment, the delta-sigma modulator comprises a comparator having a first and a
25 second comparator input and a comparator output. The first comparator input is coupled to the modulator input and/or to the modulator output. The predetermined value is provided to the second comparator input. The comparator output is coupled to an enable input of the
30 code generator. The comparator may be implemented as a window comparator. A comparator signal provided by the comparator is applied to the enable input of the code generator. The code generator provides the constant signal, in case the comparator signal indicates that the signal at the first comparator input is larger than the signal at the second

comparator input. Consequently, the code generator is designed for providing the extended Barker code, in case the signal at the first comparator input is equal or less than the predetermined value. Thus, only at a small input signal or a small output signal, the generator signal is implemented as the extended Barker code.

5

In an embodiment, the modulator loop comprises an adder. The adder comprises a first and a second adder input and an adder output. The first adder input is coupled to the modulator input. The second adder input is coupled to the modulator output. The adder output is coupled to an input of the loop filter. The first adder input may be implemented as a non-inverting input. The second adder input can be realized as an inverting input. Thus, the adder can be designed as a subtracting circuit.

10

In an embodiment, the modulator loop comprises a quantizer having an input coupled to an output of the loop filter and an output coupled to the modulator output. The quantizer can be implemented as a one-bit quantizer. The quantizer can be realized as a comparator, for example as a single-bit comparator. Alternatively, the quantizer is designed as a multi-bit quantizer.

15

In an embodiment, the modulator loop comprises a code adder. The code adder comprises a first and a second input and an output. The first input of the code adder is coupled to the output of the loop filter. The second input of the code adder is coupled to the signal generator. The output of the code adder is coupled to the input of the quantizer. Thus, the code generator is coupled to the loop filter via the code adder connected downstream of the loop filter.

20

25

In an embodiment, an input signal of the quantizer is a function of at least the generator signal. The generator signal may be used as a dithering code at the input of the quantizer.

Thus, the extended Barker code may generate dithering in a delta-sigma modulator. The extended Barker code may provide a decorrelation to another signal such as a clock or data signal. Advantageously, an intermodulation with another signal or a base band convolution may be avoided for example.

30

In an alternative embodiment, the loop filter comprises a further input that is coupled to the generator output. The loop filter may comprise more than one stage. The further input of the loop filter may be coupled to a node between two stages of the loop filter.

- 5 In an embodiment, an analog-to-digital converter comprises the delta-sigma modulator and a digital filter connected to the modulator output. Thus, the input signal is implemented as an analog signal and the output signal as a digital signal.

10 In an alternative embodiment, a digital-to-analog converter comprises the delta-sigma modulator and an analog filter connected to the modulator output. In this case, the input signal is realized as a digital signal and the output signal as an analog signal.

In an embodiment, a microphone arrangement comprises a first and a second microphone. The first microphone comprises a first transducer and a first read-out circuit comprising a first delta-sigma modulator. Moreover, the second microphone comprises a second transducer and a second read-out circuit comprising a second delta-sigma modulator. Additionally, the first and the second read-out circuit may each comprise an amplifier and a voltage reference source. The first and the second delta-sigma modulator is realized as the analog-to-digital converter. The generator signal that is realized as the extended Barker code signal of the first microphone is shifted in phase in respect to the generator signal that is realized as the extended Barker code signal of the second microphone.

25 In an embodiment, a data signal of the first microphone is a function of the output signal of the first delta-sigma modulator. Correspondingly, a data signal of the second microphone is a function of the output signal of the second delta-sigma modulator. Advantageously, the two idle tones within the data signals of the two microphones do not correlate, since the extended Barker code has a small off-peak value of an autocorrelation and the two extended Barker code signals of the two microphones are shifted in phase to each other. The shift is at least one bit.

30

In an embodiment, an arrangement comprises a first and a second delta-sigma modulator. The first and the second delta-sigma modulator each comprises a modulator loop and a code generator. The modulator loop comprises a loop filter. The code generator is

configured to generate a generator signal that is realized as an extended Barker code. The code generator comprises a generator output that is coupled to the loop filter. The extended Barker code of the first delta-sigma modulator is shifted in phase with respect to the extended Barker code of the second delta-sigma modulator.

5

The generator signal of the first delta-sigma modulator may be identical to the generator signal of the second delta-sigma modulator besides a temporal non-zero shift.

10 In an embodiment, the arrangement comprises a digital signal processor. A data input of the digital signal processor is connected to a first data output of the first delta-sigma modulator and to a second data output of the second delta-sigma modulator.

15 In an embodiment, the first and the second delta-sigma modulator use a shared data line that connects the data outputs of the first and the second delta-sigma modulator to the data input of the digital signal processor.

In an embodiment, a clock output of the digital signal processor is connected to a clock input of the first delta-sigma modulator and to a clock input of the second delta-sigma modulator.

20

The arrangement may be realized as the microphone arrangement or another arrangement.

25 In an embodiment, a method for signal conversion comprises performing a delta-sigma modulation by a modulator loop of a delta-sigma modulator, wherein the modulator loop comprises a loop filter. A generator signal that is an extended Barker code is generated by a code generator and provided to the modulator loop.

Advantageously, the idle tone content within an output signal of the delta-sigma modulator has a low correlation to other signals.

30

In an embodiment, the generator signal is provided to a further input of the loop-filter or to a second input of a code adder of the modulator loop, wherein a first input of the code adder is coupled to an output of the loop-filter.

The invention will be described in detail below for several exemplary embodiments with reference to the figures. Components and circuit parts that are functionally identical or have the identical effect bear identical reference numbers. Insofar as components or circuit parts correspond to one another in function, a description of them will not be repeated in each of the following figures. Therein:

FIGs. 1A to 1C show exemplary embodiments of a delta-sigma modulator.

FIG. 2 shows an alternative embodiment of a delta-sigma modulator.

FIGs. 3A to 3D show embodiments of a code generator, an autocorrelation function and a table of an extended Barker code.

FIGs. 4A to 4G show an exemplary embodiment of a microphone arrangement and of signals that can be detected in the microphone arrangement.

FIGs. 5A to 5D show further exemplary embodiments of the delta-sigma modulator.

FIGs. 6A and 6B show an additional exemplary embodiment of the delta-sigma modulator.

FIG. 1A shows an exemplary embodiment of a delta-sigma modulator 10. The delta-sigma modulator 10 comprises a modulator loop 11 and a code generator 12. The modulator loop 11 comprises an adder 13 having a first adder input 14 coupled to a modulator input 15 of the delta-sigma modulator 10. The delta-sigma modulator 10 comprises a modulator output 16 that is coupled to a second adder input 17 of the adder 13. Moreover, the modulator loop 11 comprises a loop filter 18 that is coupled on its input side to an adder output 19 of the adder 13. The loop filter 18 may comprise an integrator. The loop filter 18 has a filter characteristic $H[z]$ or $H(s)$. The loop-filter 18 may be implemented as a discrete-time filter, a continuous-time filter or a combined discrete-time and continuous-time filter.

Furthermore, the modulator loop 11 comprises a quantizer 20 that is coupled on its input side to a loop filter output 21 of the loop filter 18. The quantizer 20 can be implemented as comparator. An output of the quantizer 20 is coupled to the modulator output 16.

5 Moreover, the modulator loop 11 comprises a code adder 22. The code adder 22 is located between the loop filter 18 and the quantizer 20. A first input of the code adder 22 is coupled to the loop filter output 21. A second input of the code adder 22 is coupled to the code generator 12 via a generator output 23. An output of the code adder 22 is coupled to the input of the quantizer 20. Thus, the modulator loop 11 comprises a series circuit of the
10 adder 13, the loop filter 18, the code adder 22 and the quantizer 20, wherein the quantizer 20 is connected again to the adder 13 for closing the modulator loop 11. The delta-sigma modulator 10 may be of the single-bit type.

The code generator 12 generates a generator signal BS that is applied to the second input of
15 the code adder 22. The generator signal BS is formed using a binary code. The generator signal BS comprises an extended Barker code. The loop filter 18 generates a filter output signal X that is applied to the first input of the code adder 22. The adder 22 performs a summing of the generator signal BS and of the filter output signal X and provides the sum of the signals to the input of the quantizer 20. The quantizer 20 generates an output signal
20 D that can be tapped at the modulator output 16. The output signal D is provided to the second adder input 17. An input signal U is applied via the modulator input 15 to the first adder input 14. The adder 14 generates an adder output signal SLI by summing the input signal U and the output signal D. The adder output signal SLI is provided to the loop filter 18.

25 Advantageously, a binary code sequence such as the Barker code sequence is added in front of the quantizer 20 into the delta-sigma modulator 10. The output signal D is gained by delta-sigma modulation of the input signal U. The output signal D mainly depends on the input signal U and to a small extent also to the generator signal BS. Since the generator
30 signal BS realized as an extended Barker code has a small autocorrelation value, it decorrelates the idle tone with respect to other signals.

In an alternative embodiment, not shown, the modulator loop 11 comprises a feedback filter, an analog-to-digital converter, a digital-to-analog converter and/or a delay element that is arranged between the modulator output 16 and the second adder input 17. The digital-to-analog converter may be realized as a single-bit digital-to-analog converter.

5

FIG. 1B shows an alternative embodiment of the delta-sigma modulator 10 which is a further development of the delta-sigma modulator shown in FIG. 1A. The delta-sigma modulator 10 comprises a comparator 30. A comparator output 36 of the comparator 30 is coupled to an enable input 31 of the code generator 12. The comparator 30 comprises a first comparator input 32 that is coupled to the modulator input 15. A second comparator input 33 is coupled to a reference potential terminal 34 via a comparator reference source 35.

The input signal U is provided to the first comparator input 32. The comparator reference source 35 generates a predetermined value UP. The predetermined value UP is applied to the second comparator input 33. The comparator 30 provides a comparator signal SC that is tapped at the comparator output 36. The comparator signal SC is a function of a comparison of the input signal U and the predetermined value UP. The comparator signal SC is applied to the enable input 31 of the code generator 12. When the input signal U is larger than the predetermined value UP, the comparator signal SC sets the code generator 12 in such a mode that the generator signal BS of the code generator 12 is constant. The constant value of the generator signal BS may be zero. When the input signal U is equal or less than the predetermined value UP, the comparator signal SC sets the code generator 12 in such a mode that the generator signal BS is the extended Barker code.

25

The adding of a code such as the extended Barker code into the modulator loop 11 may reduce the useable input signal range, since the modulator 10 gets unstable earlier because the code uses part of the stable input range. This issue can be mitigated by the adaptive code amplitude as shown in FIG. 1B. The extended Barker code is switched on only for small input signals U, where the idle tone issue exists. For larger input signals U, there is typically no idle tone, and, therefore, the extended Barker code can be disabled. Thus, the code generator 12 generates an adaptive binary code.

30

In an alternative embodiment, the comparator 30 is realized as a window comparator.

When the input signal U is in a range between minus the predetermined value UP and plus the predetermined value UP, then the generator signal BS comprises the extended Barker code. When the input signal U is higher than the predetermined value UP or less than
5 minus the predetermined value UP, then the generator signal BS is constant, optionally zero. Instead of a window comparator, two comparators can be coupled to the modulator input 15.

FIG. 1C shows a further exemplary embodiment of the delta-sigma modulator 10 which is
10 a further development of the delta-sigma modulator shown in FIGs. 1A and 1B. The comparator 30 is coupled to the modulator output 16 on its input side. Thus, the first comparator input 32 is connected to the modulator output 16. In case the output signal D is a digital signal, the comparator 30 is implemented as a digital comparator. Then, the comparator 30 compares the digital output signal D with a digital predetermined value UP.

15 FIG. 2A shows a further exemplary embodiment of the delta-sigma modulator 10 which is a further development of the delta-sigma modulator shown in FIGs. 1A to 1C. The loop filter 18 comprises a further input 40. The code generator 12 is coupled via the generator output 23 to the further input 40 of the loop filter 18. Thus, the code adder 22 is omitted
20 and replaced by a direct connection of the loop filter output 21 to the input of the quantizer 20. The loop filter 18 comprises a first and a second filter stage 41, 42. The first and the second filter stage 41, 42 are arranged in series. The first filter stage 41 is coupled to the input of the loop filter 18, whereas the second filter stage 42 is coupled to the loop filter output 21. The loop filter 18 comprises an internal adder 43 that is arranged between the
25 first filter stage 41 and the second filter stage 42. The further input 40 of the loop filter 18 is connected to an input of the internal adder 43. An output of the first filter stage 41 is coupled to a further input of the internal adder 43. An output of the internal adder 43 is coupled to the second filter stage 42. Thus, the generator signal BS influences a signal that can be tapped inside of the loop filter 18.

30 In an alternative, not shown embodiment, the loop filter 18 comprises further stages that are connected in series to the first filter stage 41 or/and the second filter stage 42.

In an alternative, not shown embodiment, the delta-sigma modulator 10 comprises the comparator 30. The comparator 30 is connected on its input side either to the modulator input 15 as shown in FIG. 1B or to the modulator output 16 as shown in FIG. 1C. The comparator 30 is connected via the comparator output 36 to the enable input 31 of the code generator 12 as shown in FIGs. 1B and 1C.

Advantageously, a binary code such as the extended Barker code is injected into the modulator loop 11. The code is chosen so that it has minimum correlation to the disturbance. For example, code sequences with small off-peaks in the autocorrelation function and different start values can be used for two microphones in stereo mode. The binary code is disabled for larger input signals U to mitigate a reduction in the stable input range of the delta-sigma modulator 10.

FIG. 3A shows an exemplary embodiment of the code generator 12. The code generator 12 comprises a counter 50. The counter 50 at least comprises one memory unit 51. The counter 50 is realized by a series of memory units 51, 52. At least one memory unit 51, 52 may be implemented as a flip-flop. The flip-flop may be designed as a D-flip-flop. The delta-sigma modulator 10 comprises a logic circuit 54 coupled on its input side to the series of memory units 51, 52. The delta-sigma modulator 10 comprises a clock generator 53. The clock generator 53 generates a clock signal CLK. The clock generator 53 is coupled to a clock input C of the first memory unit 51. An inverted data output $\bar{Q}$ of the first memory unit 51 is coupled to a clock input C of the second memory unit 52. The inverted data output $\bar{Q}$ of the first memory unit 51 is also connected to a data input DI of the first memory unit 51. An inverted data output $\bar{Q}$ of the second memory unit 52 is connected to a data input DI of the second memory unit 51. A data output Q of the first memory unit 51 and a data output Q of the second memory unit 52 are coupled to the logic circuit 54. The logic circuit 54 comprises a NOR gate 55 having two inputs that are connected to the data outputs Q of the first and the second memory unit 51, 52. An output of the logic circuit 54 is connected via the generator output 23 to the modulator loop 11. The generator signal BS can be tapped at the output of the logic circuit 54. The extended Barker code has the sequence [1 0 0 0] which corresponds to the sequence [1 -1 -1 -1].

In an alternative embodiment, not shown, the clock generator 53 is connected to each of the clock inputs C of the series of memory units 51, 52.

5 In an alternative embodiment, not shown, the clock signal CLK is provided by an external circuit such as a digital signal processor 79 as shown in FIG. 4A. The delta-sigma modulator 10 may be free of an oscillator or clock generator.

FIG. 3B shows a further exemplary embodiment of the code generator 12 that is a further development of the code generator shown in FIG. 3A. The code generator 12 can be
10 inserted in the delta-sigma modulator 10 illustrated in FIG. 1B and 1C. The code generator 12 comprises a generator logic 60. The generator logic 60 is connected on its input side to the output of the logic circuit 54 and to the enable input 31 of the code generator 12. The generator logic 60 is connected on its output side to the generator output 23.

15 The generator logic 60 may, for example, comprise an AND gate 61 that is coupled on its input side to the output of the logic 54 and to the enable input 31. An inverter 62 of the generator logic 60 is arranged between the enable input 31 and the AND gate 61. An output of the AND gate 61 is connected via an output of the generator logic 60 to the generator output 23.

20 The generator logic 60 provides an output signal of the logic 54 to the generator output 23 as a function of the comparator signal SC. When the input signal U is equal or less than the predetermined value UP, the signal at the output of the logic 54 is provided to the generator output 23 by the generator logic 60, resulting in the generator signal BS having
25 the values +1 and -1. When the input signal U is higher than the predetermined value UP, the generator signal BS is constant and, for example, has the value zero. To summarize, the generator signal BS may have the values 1, 0 and -1.

FIG. 3C shows an exemplary embodiment of an autocorrelation function of an extended
30 Barker code signal with length 7. A value of the autocorrelation function AF versus a shift SHI is illustrated. Thus, for the calculation, a seven bit Barker code signal was used. The Barker code signal has the values [1 1 1 -1 -1 1 -1]. The autocorrelation function AF has the values 0 or -1 for any shift SHI besides the shift 0 and the value 7 for the shift SHI

having the value 0. Therefore, a minimum correlation is achieved for any phase shift between two codes.

In an alternative embodiment, not shown, other sequences might be used as well, as long as they achieve small off-peaks in the autocorrelation function. Thus, the generator signal BS may be formed by other codes besides the extended Barker codes. The generator signal BS may comprise a pseudo-random sequence. However, the autocorrelation function of the pseudo-random sequence may have higher values.

FIG. 3D shows a table of the extended Barker code. The extended Barker code comprises the codes of the Barker code set, the reversed codes, the negated codes and the reversed and negated codes.

The Barker code is defined such that the amount of the value of the autocorrelation function AF has at most the value 1 in case of a shift SHI different from 0.

Thus, the generator signal BS that implements a code of the Barker code set, a reversed code, a negated code or a reversed and negated code of the Barker code set follows the equation:

$$-1 \leq AF(BS) \leq +1 \quad \text{for } SHI \neq 0,$$

wherein AF(BS) is the value of the autocorrelation function of the generator signal BS and SHI is the value of a shift.

In addition, the extended Barker code may comprise one of the codes shown in the table, wherein a bit [1] or a bit [0] is added at any place in the sequence of bits of the code. In this case, the autocorrelation function AF may obtain values more than 1 or less than -1. Optionally, only one bit is added. Alternatively, more than one bit are added.

Furthermore, the extended Barker code comprises a compound Barker code that is generated by combining one of the codes listed in the table with another code listed in the table. A compound Barker code is achieved by setting two different Barker codes one after

the other. For generating the compound Barker code, also codes generated by adding a bit [1] or a bit [-1] to one of the codes shown in the table can be used. Two different Barker codes may be serially added to form the compound Barker code.

- 5 Optionally, the extended Barker code has a length of more than two. Optionally, the extended Barker code has a length of more than four.

10 However, the two-bit codes [1 -1] and [1 1] can be added in series to another Barker code for generating a compound Barker code. Even if these two-bit codes seem to be less efficient than longer codes if used alone, they can be part of a compound Barker code implemented by the code generator 12.

15 In an embodiment, the extended Barker code is not implemented by the codes [1 1] and [-1 -1].

20 Optionally, the extended Barker code is chosen such that an average value of the bits of the extended Barker code is zero or nearly zero. The seven-bit and eleven-bit Barker codes have a nearly zero average value.

25 In an embodiment, every code of the extended Barker code contains at least the bits of a Barker code.

30 In an embodiment, every code of the extended Barker code is set by using the bits of a Barker code or reverting or negating or reverting and additionally negating the bits of a Barker code or combining at least two Barker codes to a compound Barker code.

35 In a further development, a bit [1] or a bit [0] is added at any place in the sequence of bits of the code.

40 FIG. 4A shows an exemplary microphone arrangement 70 having a first and a second microphone 71, 72. Each of the microphones 71, 72 comprises a transducer 73, 74 and a read-out circuit 75, 76 which comprises a delta-sigma modulator 75', 76'. The delta-sigma modulators 75', 76' are realized as one of the delta-sigma modulators shown in the FIGs.

1A to 1C, 2, 5A to 5D and 6A. The first transducer 73 of the first microphone 71 is coupled via the first read-out circuit 75 of the first microphone 71 to a first data output 77 of the first microphone. Correspondingly, the second transducer 74 of the second microphone 72 is coupled via the second read-out circuit 76 of the second microphone 72 to a second data output 78 of the second microphone 72. The microphone arrangement 70 comprises a digital signal processor 79. The digital signal processor 79 may be implemented as a coding-decoding circuit, abbreviated to codec circuit. A data input of the digital signal processor 79 is connected to the first data output 77 and to the second data output 78. Both microphones 71, 72 use a shared data line 68 that connects the data outputs 77, 78 to the data input of the digital signal processor 79. A clock output of the digital signal processor 79 is connected to a clock input of the first microphone 71 and to a clock input of the second microphone 72 and, thus, to the clock inputs of the first and the second delta-sigma modulator 75', 76'. Both microphones 71, 72 are connected to a supply terminal 69 and to the reference potential terminal 34. The first microphone 71 is called a left-channel microphone. Consequently, the second microphone 72 is named a right-channel microphone. Both transducers 73, 74 are realized as micro-electro-mechanical system transducers, abbreviated MEMS transducers. Thus, the microphones 71, 72 can be named MEMS microphones. Alternatively, the first and the second transducer 73, 74 are implemented as electret microphone.

The digital signal processor 79 generates the clock signal CLK for the first and the second microphone 71, 72. The first microphone 71 drives data on the negative clock signal CLK, whereas the second microphone 72 drives data on the positive clock signal CLK.

The first and the second microphone 71, 72 each provide a pulse density modulated data signal at the respective data output 77, 78. The first microphone 71 provides data at the falling edge of the clock signal CLK, whereas the second microphone 72 provides data at the rising edge of the clock signal CLK. The digital signal processor 79 separately decodes the data of the first and of the second microphone 71, 72. The digital signal processor 79 filters the modulated data which have a high sample rate back to an audio frequency band. The first microphone 71 represents a left channel and the second microphone 72 correspondingly represents a right channel.

Advantageously, the number of connecting lines between the two microphones 71, 72 and the digital signal processor 79 can be kept low.

Advantageously, the idle tone in the modulator spectrum is reduced by the first delta-sigma modulator 75' comprising a code generator 12 and also by the second delta-sigma modulator 76' comprising a further code generator 12. Moreover, the intermodulation product between the idle tones of the two bit-streams of the two delta-sigma modulators 75', 76' is reduced. Two sequences which have minimum correlation between each other are used for each microphone 71, 72. Barker codes are well suited for this purpose. Barker codes are finite binary code sequences with minimum off-peak autocorrelation coefficients. It is conjectured that only seven known binary Barker codes exist. Using a Barker binary sequence with different start values for each microphone 71, 72, depending on the left or right channel of the two microphones 71, 72 sharing the same data bus 68, guarantees minimum correlation between the idle tones in the two output bit-streams. The microphone arrangement 70 achieves a lower idle tone intermodulation at less degradation in the noise floor compared to conventional techniques, such as dithering.

The code generator 12 of the first delta-sigma modulator 75' and the code generator 12 of the second delta-sigma modulator 76' may use the same extended Barker code, but with a shift in the extended Barker code. For example, the first delta-sigma modulator 75' may use the sequence [1 1 1 -1 -1 1 -1], whereas the second delta-sigma modulator 76' may use the sequence [1 -1 -1 1 -1 1 1]. Using different start values depending whether the microphone 71, 72 is used for the left or right channel (stereo configuration with two microphones 71, 72 on the same data bus), minimum correlation is achieved between the two code sequences.

FIG. 4B shows an exemplary characteristic of a microphone such as a first and a second microphone 71, 72. In FIG. 4B, the frequency spectrum of a microphone is shown, wherein a DC input is provided to the modulator input 15 of the delta-sigma modulator 75'. A magnitude MA of the output signal U versus a frequency f is illustrated. FIG. 4B is achieved by a Matlab simulation.

FIG 4C shows an exemplary characteristic of two microphones 71, 72. The magnitude MA versus the frequency f is shown. A measured output bitstream of the first MEMS microphone 71 is illustrated with the second microphone 72 sharing the same data bus 68 without using a code generator 12. The tone at 2.75 kHz, which is the difference between the tones around the half of the sampling frequency $f_s/2$ of the two microphones 71, 72, is clearly visible in the spectrum. In spite of being close to the noise floor, this baseband tone is perceived as a whistling and, therefore, also referred to as bird noise. A limit cycle becomes particularly troublesome, if another signal near the half of the sampling frequency $f_s/2$ interferes with the delta-sigma modulator bit-stream. In this case, the tone gets folded down into the baseband. This can be observed with two digital MEMS microphones 71, 72 with pulse-density modulated outputs sharing the common data line 68 (stereo configuration). Because the microphones 71, 72 use a non-return-to-zero (NRZ) scheme for the data output, the frequency conversion product ($|f_{s,mic2} - f_{s,mic1}|$) of the two tones appears in the signal-band, if the code generator 12 is omitted.

In FIGs. 4D to 4G, a comparison of the microphone arrangement 70 using the extended Barker code with conventional dithering is elucidated.

FIGs. 4D and 4E show exemplary characteristics of the output signal D of a delta-sigma modulator. The magnitude MA of the output signal D as a function of the frequency f is shown. Whereas in FIG. 4D an output spectrum of a single delta-sigma modulator with dithering is shown, the output spectrum of the single delta-sigma modulator 10 using a modified 3 bit Barker code sequence is illustrated in FIG. 4E. The dithering is achieved by adding a pseudo-random noise sequence to the input of the quantizer 20 or an integrator stage of the loop filter 18. The dithering aims at de-correlating the quantization error from the input. In FIG. 4E, the noise floor is less degraded compared to FIG. 4D and the magnitude MA of the idle tone at 1100 kHz is reduced more efficiently. The additional peaks in the output spectrum shown in FIG. 4E are located at known frequencies such that the influence of the additional peaks can be reduced and can be filtered by a sinc filter comprised by a decimation filter of the digital signal processor 79. The parameters of the sinc filter are chosen such that the additional peaks are reduced.

FIG. 4F and 4G show an intermodulation product of the first and the second microphone 71, 72. Whereas dithering is used to achieve the intermodulation product shown in FIG. 4F, the modified 3 bit Barker code sequence is applied for achieving the intermodulation product shown in FIG. 4G. The high peak at about 10 kHz shown in FIG. 4F is very much reduced by the use of the modified 3 bit Barker code sequence as shown in FIG. 4G. FIGs. 4F and 4G are results of a Matlab simulation of the intermodulation of two delta-sigma modulator bit-streams which are generated by two digital pulse density modulated MEMS microphones 71, 72 sharing the same data bus 68. The Barker code sequence results in an 8 dB lower intermodulation product at 1.5 dB less quantization noise degradation compared to the dithering shown in FIGs. 4D and 4F. Advantageously, the first and the second delta-sigma modulators 75', 76' perform an idle tone intermodulation suppression. The first and the second delta-sigma modulators 75', 76' are realized as single-bit modulators.

FIG. 5A shows a further exemplary embodiment of the delta-sigma modulator 10 which is a further development of the delta-sigma modulator shown in FIGs. 1A to 1C and 2. The delta-sigma modulator 10 is implemented as a chain of integrators with distributed feedback, abbreviated to CIFB. The delta-sigma modulator 10 is of an even order, namely of the second order. Thus, the delta-sigma modulator 10 comprises the loop filter 18 and a further loop filter 81. The loop filter 18 comprises a first delaying integrator 82 and a first filter 83 that are arranged in series. The further loop filter 81 comprises a second delaying integrator 84 and a second filter 85 which are connected in series.

The modulator input 15 is coupled via a first input filter 86 to the first adder input 14. The adder output 19 is coupled via the loop filter 18 to a further adder 87. An output of the further adder 87 is coupled via the further loop filter 81 to the code adder 22. The code generator 12 is coupled to a further input of the code adder 22. The modulator input 15 is coupled via a second input filter 88 to a further input of the further adder 87. A third input filter 89 couples the modulator input 15 to a further input of the code adder 22. The output of the code adder 22 is coupled to the input of the quantizer 20. The output of the quantizer 20 is coupled to the modulator output 16 and via a digital-to-analog converter 90 to the second adder input 17. A first feedback filter 91 is arranged between the digital-to-analog converter 90 and the second adder input 17. The output of the digital-to-analog converter 90 is additionally coupled via a second feedback filter 92 to a further input of the further

adder 87. A node between the second delaying integrator 84 and the second filter 85 is coupled via a feedback filter 93 to a further input of the adder 13. The loop filter 18 and the further loop filter 81 form a resonator.

- 5 The generator signal BS is provided to the input of the code adder 22 that is arranged between the further loop filter 81 and the quantizer 20.

In an alternative, not shown embodiment, the code generator 12 is coupled to another circuit of the delta-sigma modulator 10. The generator signal BS can be added to another
10 node in the delta-sigma modulator 10, for example to a further input of the adder 13 or the further adder 87.

FIG. 5B shows an exemplary embodiment of the delta-sigma modulator 10 which is a further development of the delta-sigma modulators shown in FIGs. 1A to 1C, 2 and 5A.
15 The delta-sigma modulator 10 as shown in FIG. 5B is also realized as a chain of integrators with distributed feedback. Whereas in FIG. 5A, an even order delta-sigma modulator is shown, an odd order delta-sigma converter is illustrated in FIG. 5B. The delta-sigma modulator 10 comprises an additional loop filter 100 and an additional adder 101. An output of the further adder 87 is coupled via the additional loop filter 100 to an input of the
20 additional adder 101. The modulator input 15 is coupled via an additional input filter 102 to a further input of the additional adder 101. The modulator output 16 is coupled via the digital-to-analog converter 90 and a third filter 103 to an additional input of the additional adder 101. The additional loop filter 100 comprises an additional delaying integrator 104 and an additional filter 105 that are connected in series. A node between the second
25 delaying integrator 84 and the second filter 85 is coupled via the feedback filter 93 to an input of the further adder 87.

In an alternative embodiment, not shown, the generator signal BS can be added to another node of the delta-sigma modulator 10, for example, to the adder 13, the further adder 87 or
30 the additional adder 101.

FIGs. 5C and 5D show exemplary embodiments of the delta-sigma modulator 10 which are further developments of the delta-sigma modulators shown in FIGs. 1A to 1C, 2, 5A and

5B. The delta-sigma modulators 10 elucidated in FIGs. 5C and 5D are realized as a chain of integrators with feed-forward summation, abbreviated to CIFF. Whereas in FIG. 5C a delta-sigma modulator 10 having an even order is shown, a delta-sigma modulator 10 with an odd order is illustrated in FIG. 5D. The delta-sigma modulator 10 of FIG. 5C has the second order, whereas the delta-sigma modulator 10 of FIG. 5D is of the third order.

The delta-sigma modulator 10 of FIG. 5C comprises the loop filter 18 and the further loop filter 81. The loop filter 18 is coupled between the adder output 19 and the input of the further adder 87. The output of the further adder 87 is coupled via the further loop filter 81 to the input of the code adder 22, corresponding to the circuit structure shown in FIG. 5A. The modulator input 15 is coupled via the first, the second and the third input filter 86, 88, 89 to inputs of the adder 13, the further adder 87 and the code adder 22. The modulator output 16 is coupled via the digital-to-analog converter 90 and the first feedback filter 91 to the further input of the adder 13. The modulator output 16 is not coupled to the further adder 87, contrary to FIG. 5A.

A node between the second delaying integrator 84 and the second filter 85 is coupled via the feedback filter 93 to the input of the adder 13. Moreover, a node between the delaying integrator 82 and the first filter 83 is coupled via a further filter 110 to a further input of the code adder 22. The code generator 12 is coupled to the input of the code adder 22. The code adder 22 is coupled via the quantizer 20 to the modulator output 16.

In an alternative embodiment, not shown, the code generator 12 is coupled to another node of the delta-sigma modulator 10 such as, for example, to an input of the adder 13 or the further adder 87.

Additionally to the delta-sigma modulator 10 as shown in FIG. 5C, the delta-sigma modulator 10 as illustrated in FIG. 5D comprises the additional loop filter 100, the additional adder 101 and the additional input filter 102. The additional loop filter 100 and the additional adder 101 are connected in series and couple the further adder 87 the further loop filter 81. The modulator input 15 is coupled to the additional adder 101 via the additional input filter 102. A node between the additional delaying integrator 104 and the additional filter 105 is coupled via an additional forward filter 111 to a further input of the

code adder 22. A node between the second delaying integrator 84 and the second filter 85 is coupled via the feedback filter 93 to an input of the further adder 87.

The filters 83, 85, 86, 88, 89, 91, 92, 93, 102, 103, 105, 110, 111 of the delta-sigma modulator 10 shown in FIGs. 5A to 5D may be implemented as passive or active filters. In case of a negative filter coefficient such as $-a_1$, $-a_2$, $-a_3$ and $-c_1$, the filters may be implemented as active filters using an amplifier for inverting a signal provided to the filter. The passive filters may be designed as resistive voltage dividers. The adders 13, 22, 87, 101 may be realized as subtracting circuits. Thus, a filter with a negative filter coefficient and an adder can be replaced by a filter with a positive filter coefficient and a subtracting circuit.

In an alternative embodiment, not shown, the code generator 12 is coupled to another node of the delta-sigma modulator 10 instead of the code adder 22.

FIG. 6A shows an exemplary embodiment of the delta-sigma modulator 10 which is a further development of one of the delta-sigma modulators described above. The delta-sigma modulator 10 is of an even order, namely of a fourth order. The delta-sigma modulator 10 has a feed forward structure. The delta-sigma modulator 10 is realized as a chain of integrators with feed forward summation, similarly to FIGs. 5C and 5D. The delta-sigma modulator 10 is implemented by a switched capacitor circuit.

The delta-sigma modulator 10 comprises the loop filter 18, the further loop filter 81, the additional loop filter 100 and a fourth loop filter 108 which are connected in series between the adder 13 and the code adder 22. The code adder 22 is coupled via the quantizer 20 to the modulator output 16. The quantizer 20 can be implemented as 1-bit quantizer. The quantizer 20 may be realized as comparator. The additional loop filter 100 is coupled to the fourth loop filter 108 via a fourth adder 109. The fourth loop filter 108 is coupled via the additional adder 101 to the further loop filter 81.

Each of the loop filters 18, 81, 100, 108 comprises an input capacitor 112 and an integrator 113. The integrator 113 is implemented by an amplifier 114 and an integrating capacitor 115 that is arranged between an output of the amplifier 114 and an inverting input of the

amplifier 114. The output of the amplifier 114 is connected to the loop filter output. A non-inverting input of the amplifier 114 is connected to the reference potential terminal 34. An input of the loop filter is connected to a first electrode of the input capacitor 112. A charging switch 116 connects a second electrode of the input capacitor 112 to the inverting input of the amplifier 114. A node between the input capacitor 112 and the charging switch 116 is connected via a reference switch 117 to the reference potential terminal 34.

Each of the adders 22, 87, 101, 109 comprises an input switch 118 that connects the output of the upstream loop filter to an input of the downstream loop filter. A ground switch 119 connects the input of the downstream loop filter to the reference potential terminal 34. In case of the code adder 22, the input switch 118 connects the output of the further loop filter 81 to an input node 120. The input node 120 is connected via the ground switch 119 to the reference potential terminal 34. An adder capacitor 121 couples the input node 120 of the code adder 22 to an output node 122 of the code adder 22. The output node 122 is connected to the input of the quantizer 20. The output node 122 is coupled via an output ground switch 123 to the reference potential terminal 34.

Several nodes of the loop filters 18, 81, 100, 108 are coupled via capacitors 124, 125, 126, 127 to the code adder 22. Thus, a first capacitor 124 is arranged between the input of the additional loop filter 100 and the output node 122 of the code adder 22. Furthermore, a second capacitor 125 couples the input of the fourth loop filter 108 to the output node 122 of the code adder 22. Further on, a third capacitor 126 is located between the input of the further loop filter 81 and the output node 122 of the code adder 22. In addition, a capacitor arrangement 127 is arranged between a node of the additional loop filter 100 and the input node 120 of the code adder 22. The capacitor arrangement 127 comprises a first to a third capacitor element 128 to 130, whereas a series circuit of the first and the second capacitor element 128, 129 couples the node in the additional loop filter 100 to the input node 120. A node between the first and the second capacitor element 128, 129 is connected via the third capacitor element 130 to the reference potential terminal 34. The node is connected by an additional ground switch 131 to the reference potential terminal 34.

The code generator 12 is connected to the output node 122 of the code adder 22. The code generator 12 comprises a first and a second voltage source 140, 141 that are coupled to the

code adder 22 by a switch arrangement. The switch arrangement comprise a first and a second generator switch 142, 143. The first generator switch 142 and a generator output capacitor 144 are connected in series and are arranged between the first voltage source 140 and the code adder 22. The second voltage source 141 is coupled via the second generator switch 143 and the generator output capacitor 144 to the code adder 22. The first voltage source 140 provides a positive reference voltage VRP, whereas the second voltage source 141 generates a negative reference voltage VRM. A third generator switch 145 couples a node between the switch arrangement and the generator output capacitor 144 to the reference potential terminal 34. A generator driver logic 146 is connected on its input side to the code generator 12 and to a clock circuit 147 and on its output side to the control terminals of the first to the third generator switch 142, 143, 145.

The modulator output 16 is coupled via the digital-to-analog converter 90 to the adder 13. The digital-to-analog converter 90 comprises a first and a second converter switch 148, 149 and a first and a second reference source 150, 151. A node of the adder 13 is connected via the first converter switch 148 to the first reference source 150 and via the second converter switch 149 to the second reference source 151. A converter logic 152 of the digital-to-analog converter 90 is connected on its input side to the modulator output 16 and to the clock circuit 147 and on its output side to the control terminals of the first and the second converter switch 148, 149.

A modulator input switch 153 is arranged between the modulator input 15 and the adder 13. The delta-sigma modulator 10 is designed for an analog-to-digital converter.

FIG. 6B shows an exemplary embodiment of timing signals of the delta-sigma modulator 10 as shown in FIG. 6A. The timing of the switches is achieved by the clock circuit 147. The clock circuit 147 is triggered by the clock signal CLK. The clock circuit 147 generates signals for a first phase A and a second phase B. Moreover, the clock circuit 147 generates signals for a delayed first phase AD that is delayed in respect to the first phase A and a delayed second phase BD that is delayed in respect to the second phase B. The second phase B follows the first phase A. The signals for the four phases A, AD, B, BD are shown in Figure 6B.

Since the delta-sigma modulator 10 is implemented as a switched capacitor circuit, some of the switches are in a conducting state in the first phase A, whereas other switches are in a conducting state in the second phase B. In addition, some of the switches are in a conducting state in the delayed first phase AD and other in the delayed second phase BD.

5 In FIG 6A, the signals A, AD, B, BD received by the different switches are indicated.

In an example, the code generator 12 may generate the generator signal BS with the extended Barker code [1 -1 -1 -1]. Thus, a negated generator signal $\overline{BS}$ is achieved by negation of the generator signal BS. The negated generator signal $\overline{BS}$ has the sequence [-1
10 1 1 1]. In FIG. 6B, the logical AND combination BD&BS of the delayed second phase BD and the generator signal BS and the logical AND combination BD& $\overline{BS}$ of the delayed second phase BD and the negated generator signal $\overline{BS}$ are also shown. These signals BD&BS, BD& $\overline{BS}$ are provided to the first and the second generator switch 142, 143.

15 The first generator switch 142 is in a conducting state in the second delayed phase BD and when the generator signal BS has the value 1. In all other cases, the first generator switch 142 is in a non-conducting state. Consequently, the second generator switch 143 is in a conducting state in the second delayed phase BD when the generator signal BS has the value -1. In all other cases, the second generator switch 143 is in a non-conducting state.
20 Thus, in the first case the positive reference voltage VRP and in the second case the negative reference voltage VRM is provided to the code adder 22 as a function of the generator signal BS. The positive reference voltage VRP and the negative reference voltage VRM are selectively provided to the modulator loop 11 depending on the generator signal BS.

25 The first reference source 150 provides a positive reference source voltage VRP' and the second reference source 151 provides a negative reference source voltage VRM'. The first converter switch 148 is closed in the second delayed phase BD, when the output signal D has the logical value 0. Consequently, the second converter switch 149 is closed in the
30 second delayed phase BD, when the output signal D has the logical value 1. Thus, in the first case the positive reference source voltage VRP' and in the second case the negative reference source voltage VRM' is provided to the code adder 22 as a function of the output

signal D. Thus, the delta-sigma modulator 10 comprises a single-bit quantizer 20 and a single-bit digital-to-analog converter 90.

In an alternative embodiment, not shown, the delta-sigma modulator 10 comprises the
5 comparator 30 as shown in FIGs. 1B and 1C. When a signal at the first comparator input
32 is higher than the predetermined value UP, than the first and the second generator
switch 142, 143 are in a non-conducting state and neither the positive reference voltage
VRP nor the negative reference voltage VRM are provided to the modulator loop 11.
When the signal at the first comparator input 32 is equal or less than the predetermined
10 value UP, the positive reference voltage VRP and the negative reference voltage VRM are
selectively provided to the modulator loop 11 depending on the generator signal BS.

In an alternative, not shown embodiment, the first and the second voltage source 140, 141
are omitted and the first and the second reference source 150, 151 are connected to the
15 code generator 12 for providing the positive and the negative voltage reference VRP,
VRM.

Reference Numerals

	10	delta-sigma modulator
	11	modulator loop
5	12	code generator
	13	adder
	14	first adder input
	15	modulator input
	16	modulator output
10	17	second adder input
	18	loop filter
	19	adder output
	20	quantizer
	21	loop filter output
15	22	code adder
	23	generator output
	30	comparator
	31	enable input
	32	first comparator input
20	33	second comparator input
	34	reference potential terminal
	35	comparator reference source
	36	comparator output
	40	further input
25	41	first filter stage
	42	second filter stage
	43	internal adder
	50	counter
	51	first memory unit
30	52	second memory unit
	53	clock generator
	54	logic circuit
	55	NOR gate

	60	generator output logic
	61	AND gate
	62	inverter
	68	data line
5	69	supply terminal
	70	microphone arrangement
	71	first microphone
	72	second microphone
	73	first transducer
10	74	second transducer
	75	first read-out circuit
	76	second read-out circuit
	75'	first delta-sigma modulator
	76'	second delta-sigma modulator
15	77	first data output
	78	second data output
	79	digital signal processor
	81	further loop filter
	82	first delaying integrator
20	83	first filter
	84	second delaying integrator
	85	second filter
	86	first input filter
	87	further adder
25	88	second input filter
	89	third input filter
	90	digital-to-analog converter
	91	first feedback filter
	92	second feedback filter
30	93	feedback filter
	100	additional loop filter
	101	additional adder
	102	additional input filter

	103	third filter
	104	additional delaying integrator
	105	additional filter
	108	fourth loop filter
5	109	fourth adder
	110	further filter
	111	additional forward filter
	112	input capacitor
	113	integrator
10	114	amplifier
	115	integrating capacitor
	116	charging switch
	117	reference switch
	118	input switch
15	119	ground switch
	120	input node
	121	adder capacitor
	122	output node
	123	output ground switch
20	124	first capacitor
	125	second capacitor
	126	third capacitor
	127	capacitor arrangement
	128 - 130	capacitor element
25	131	additional ground switch
	140	first voltage source
	141	second voltage source
	142	first generator switch
	143	second generator switch
30	144	generator output capacitor
	145	third generator switch
	146	generator driver logic
	147	clock circuit

	148	first converter switch
	149	second converter switch
	150	first reference source
	151	second reference source
5	152	converter logic
	153	modulator input switch
	A	first phase
	AD	first phase with delay
	AF	autocorrelation function
10	B	second phase
	BD	second phase with delay
	BS	generator signal
	C	clock input
	CLK	clock signal
15	D	output signal
	DI	data input
	f	frequency
	GND	ground potential
	MA	magnitude
20	Q	data output
	$\bar{Q}$	inverted data output
	RES	reset signal
	SC	comparator signal
	SHI	shift
25	SLI	adder output signal
	t	time
	U	input signal
	UP	predetermined value
	VRM	negative reference voltage
30	VRP	positive reference voltage
	VRM'	negative reference source voltage
	VRP'	positive reference source voltage
	X	filter output signal

Claims

1. Delta-sigma modulator, comprising:
 - a modulator loop (11) comprising a loop filter (18) and
 - 5 - a code generator (12) that is configured to generate a generator signal (BS) that is realized as an extended Barker code and wherein the code generator (12) comprises a generator output (23) that is coupled to the loop filter (18).
2. Delta-sigma modulator according to Claim 1,
 - 10 wherein the extended Barker code comprises a code out of
 - a Barker code set comprising the code [1 -1], the code [1 1], the code [1 1 -1], the code [1 -1 1 1], the code [1 -1 -1 -1], the code [1 1 1 -1 1], the code [1 1 1 -1 -1 1 -1], the code [1 1 1 -1 -1 1 -1 1 -1 1 -1] and the code [1 1 1 1 1 -1 -1 1 1 -1 1 -1 1], or
 - a reversed code, a negated code or a reversed and negated code of a code of the
 - 15 Barker code set or
 - a code achieved by adding a bit [1] or [-1] to one of the codes comprised by the Barker code set or to the reversed code, the negated code or the reversed and negated code of a code of the Barker code set or
 - a compound Barker code realized by a combination of said codes.
 - 20
3. Delta-sigma modulator according to Claim 1 or 2,
 - wherein the code generator (12) comprises a counter (50).
4. Delta-sigma modulator according to Claim 3,
 - 25 wherein the counter (50) comprises at least one memory unit (51) and a logic circuit (54) with an output that is coupled to the generator output (23).
5. Delta-sigma modulator according to one of Claims 1 to 4,
 - wherein the modulator loop (11) comprises
 - 30 - a modulator input (15) for receiving an input signal (U) and
 - a modulator output (16) for providing an output signal (D) of the delta-sigma modulator (10), wherein the loop filter (18) is arranged between the modulator input (15) and the modulator output (16).

6. Delta-sigma modulator according to Claim 5,
wherein the generator signal (BS) is
- a constant signal when the input signal (U) and/or the output signal (D) is higher than
 - 5 a predetermined value (UP) and
 - the extended Barker code when the input signal (U) and/or the output signal (D) is less or equal than the predetermined value (UP).
7. Delta-sigma modulator according to Claim 5 or 6,
- 10 wherein the delta-sigma modulator (10) comprises a comparator (30) having
- a first comparator input (32) coupled to the modulator input (15) or to the modulator output (16),
 - a second comparator input (33) to which a predetermined value (UP) is provided and
 - a comparator output (36) coupled to an enable input (31) of the code generator (12).
- 15
8. Delta-sigma modulator according to one of Claims 5 to 7,
wherein the modulator loop (11) comprises
- an adder (13) with a first adder input (14) coupled to the modulator input (15), a second adder input (17) coupled to the modulator output (16) and an adder output
 - 20 (19) coupled to an input of the loop-filter (18) and
 - a quantizer (20) with an input coupled to a loop filter output (21) of the loop-filter (18) and an output coupled to the modulator output (16).
9. Delta-sigma modulator according to Claim 8,
- 25 wherein a code adder (22) of the modulator loop (11) comprises
- a first input that is coupled to the loop filter output (21),
 - a second input that is coupled to the generator output (23) and
 - an output that is coupled to the input of the quantizer (20).
- 30 10. Delta-sigma modulator according to Claim 8,
wherein the loop-filter (18) comprises a further input (40) that is coupled to the generator output (23).

11. Delta-sigma modulator according to Claim 10,
wherein the loop filter (18) comprises more than one stage (41, 42) and the further
input (40) of the loop filter (18) is coupled to a node between two stages (41, 42) of
the loop filter (18).
- 5 12. Analog-to-digital converter, comprising the delta-sigma modulator according to one
of Claims 1 to 11,
wherein the input signal (U) is an analog signal and the output signal (D) is a digital
signal.
- 10 13. Microphone arrangement (70), comprising
- a first microphone (71) that comprises a first transducer (73) and a first delta-sigma
modulator (75') and
 - a second microphone (72) that comprises a second transducer (74) and a second
delta-sigma modulator (76'), wherein the first and the second delta-sigma modulators
(75', 76') are realized according to one of Claims 1 to 11 and the extended Barker
code of the first delta-sigma modulator (75') is shifted in phase with respect to the
extended Barker code of the second delta-sigma modulator (76').
- 15 14. Method for signal conversion, comprising:
- performing a delta-sigma modulation by a modulator loop (11) of a delta-sigma
modulator (10), wherein the modulator loop (11) comprises a loop filter (18) and
 - generating a generator signal (BS) that is an extended Barker code by a code
generator (12) and providing the generator signal (BS) to the modulator loop (11).
- 20 15. Method according to Claim 14,
wherein the generator signal (BS) is provided to a further input (40) of the loop-filter
(18) or to a second input of a code adder (22) of the modulator loop (11), wherein a
first input of the code adder (22) is coupled to a loop-filter output (21) of the loop-
filter (18).
- 25 30 16. Method according to Claim 14 or 15,
wherein the extended Barker code comprises a code out of

- a Barker code set comprising the code [1 -1], the code [1 1], the code [1 1 -1], the code [1 -1 1 1], the code [1 -1 -1 -1], the code [1 1 1 -1 1], the code [1 1 1 -1 -1 1 -1], the code [1 1 1 -1 -1 -1 1 -1 -1 -1], the code [1 1 1 1 -1 -1 1 1 -1 1 -1 1], or
- a reversed code, a negated code or a reversed and negated code of a code of the Barker code set or
- a code achieved by adding an bit [1] or [-1] to one of the codes comprised by the Barker code set or to the reversed code, the negated code or the reversed and negated code of a code of the Barker code set or
- a compound Barker code realized by a combination of said codes.

10

17. An arrangement, comprising

- a first delta-sigma modulator (75') and
 - a second delta-sigma modulator (76'),
- wherein the first and the second delta-sigma modulator (75', 76') each comprises:
- a modulator loop (11) comprising a loop filter (18) and
 - a code generator (12) that is configured to generate a generator signal (BS) that is realized as an extended Barker code,
- wherein the code generator (12) comprises a generator output (23) that is coupled to the loop filter (18), and wherein the extended Barker code of the first delta-sigma modulator (75') is shifted in phase with respect to the extended Barker code of the second delta-sigma modulator (76').

15

20

FIG 1A




FIG 1B




FIG 1C




FIG 2




FIG 3A




FIG 3B




FIG 3C




FIG 3D

length	Barker code	reversed Barker code	negated Barker code	negated and reversed Barker code
2	[1 -1]	[-1 1]	[-1 1]	[1 -1]
2	[1 1]	[1 1]	[-1 -1]	[-1 -1]
3	[1 1 -1]	[-1 1 1]	[-1 -1 1]	[1 -1 -1]
4	[1 -1 1 1]	[1 1 -1 1]	[-1 1 -1 -1]	[-1 -1 1 -1]
4	[1 -1 -1 -1]	[-1 -1 -1 1]	[-1 1 1 1]	[1 1 1 -1]
5	[1 1 1 -1 1]	[1 -1 1 1 1]	[-1 -1 -1 1 -1]	[-1 1 -1 -1 -1]
7	[1 1 1 -1 -1 1 -1]	[-1 1 -1 -1 1 1 1]	[-1 -1 -1 1 1 -1 1]	[1 -1 1 1 -1 -1 -1]
11	[1 1 1 -1 -1 1 -1 -1 1 -1 -1]	[-1 1 -1 -1 1 -1 -1 1 1 1 1]	[-1 -1 -1 -1 -1 1 1 1 -1 1 1]	[1 -1 1 1 -1 1 1 1 -1 -1 -1]
13	[1 1 1 1 1 -1 -1 1 1 -1 1 -1 -1]	[1 -1 1 -1 1 1 1 -1 -1 1 1 1 1]	[-1 -1 -1 -1 -1 1 1 1 -1 1 1 -1 1]	[-1 1 -1 1 -1 -1 1 1 -1 -1 -1 -1 -1]
	[1]	[1]	1 -1]	-1 -1]

FIG 4A




FIG 4B




FIG 4C




FIG 4D




FIG 4E




FIG 4F




FIG 4G




FIG 5A





FIG 5B



10

FIG 5C




FIG 5D




FIG 6A





FIG 6B



INTERNATIONAL SEARCH REPORT

International application No
PCT/EP2015/053088

A. CLASSIFICATION OF SUBJECT MATTER
INV. H03M3/00
ADD.

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
H03M

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

EPO-Internal

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	TRICK U: "EIN VERGLEICH VON INTEGRIERTEN SCHALTUNGEN FÜR DIE U-SCHNITTSTELLE IM DIGITALISIERTEN ORTSNETZ", NTZ ARCHIV, VDE VERLAG GMBH. BERLIN, DE, vol. 11, no. 5, September 1989 (1989-09), pages 211-219, XP000067725, Section 3.3 Section 3.5 figures 4,5 ----- -/--	1-5,8, 10-12, 14,16,17



Further documents are listed in the continuation of Box C.



See patent family annex.

* Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier application or patent but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

27 February 2015

Date of mailing of the international search report

06/03/2015

Name and mailing address of the ISA/

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040,
Fax: (+31-70) 340-3016

Authorized officer

Rocha, Daniel

INTERNATIONAL SEARCH REPORT

International application No
PCT/EP2015/053088

C(Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	RUDOLF KOCH ET AL: "A 12-bit Sigma-Delta Analog-to-Digital Converter with a 15-MHz Clock Rate", IEEE JOURNAL OF SOLID-STATE CIRCUITS, IEEE SERVICE CENTER, PISCATAWAY, NJ, USA, vol. SC-21, no. 6, December 1986 (1986-12), pages 1003-1010, XP001404397, ISSN: 0018-9200 figure 8	1-17
A	K. SZECHENYI ET AL: "Integrated Full-Digital U-Interface Circuit for ISDN Subscriber Loops", IEEE JOURNAL ON SELECTED AREAS IN COMMUNICATIONS, vol. 4, no. 8, November 1986 (1986-11), pages 1337-1349, XP055136345, ISSN: 0733-8716, DOI: 10.1109/JSAC.1986.1146463 Section IV.F figure 20	1-17
A	SAILER H ET AL: "A VLSI TRANCEIVER FOR THE ISDN CUSTOMER ACCESS", INTERNATIONAL CONFERENCE ON COMMUNICATIONS. CHICAGO, JUNE 23 - 26, 1985; [INTERNATIONAL CONFERENCE ON COMMUNICATIONS], NEW YORK, IEEE, US, vol. 3, June 1985 (1985-06), pages 1448-1451, XP000795175, Section "DIGITAL SIGNAL PROCESSING"	1-17
A	US 5 144 308 A (NORSWORTHY STEVEN R [US]) 1 September 1992 (1992-09-01) column 7, lines 27-31 column 7, lines 36-41	1-17
A	Abhijit Mitra: "On Pseudo-Random and Orthogonal Binary Spreading Sequences", 2008, XP055136333, Retrieved from the Internet: URL:http://waset.org/publications/13716/on-pseudo-random-and-orthogonal-binary-spreading-sequences [retrieved on 2014-08-25] Section II	1-17

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/EP2015/053088

Patent document cited in search report		Publication date	Patent family member(s)		Publication date
US 5144308	A	01-09-1992	DE	69215271 D1	02-01-1997
			DE	69215271 T2	05-06-1997
			DE	69231317 D1	07-09-2000
			DE	69231317 T2	28-12-2000
			EP	0515154 A1	25-11-1992
			EP	0709969 A2	01-05-1996
			HK	42997 A	11-04-1997
			JP	H0793582 B2	09-10-1995
			JP	H05160736 A	25-06-1993
			US	5144308 A	01-09-1992
