



(22) **Date de dépôt/Filing Date:** 2010/11/05

(41) **Mise à la disp. pub./Open to Public Insp.:** 2011/12/09

(45) **Date de délivrance/Issue Date:** 2016/05/10

(30) **Priorité/Priority:** 2010/06/09 (US12/797,066)

(51) **Cl.Int./Int.Cl.** *H04B 7/185* (2006.01)

(72) **Inventeurs/Inventors:**

CHEN, WEIGUO, CA;
MACIKUNAS, ARUNAS GABRIEL, CA


(73) **Propriétaire/Owner:**

EXACTEARTH LTD., CA

(74) **Agent:** BERESKIN & PARR LLP/S.E.N.C.R.L.,S.R.L.

(54) **Titre : SYSTEMES ET PROCEDES VISANT A SEGMENTER LE CHAMP DE VISION D'UN SATELLITE POUR DETECTER DES SIGNAUX RF**

(54) **Title: SYSTEMS AND METHODS FOR SEGMENTING A SATELLITE FIELD OF VIEW FOR DETECTING RADIO FREQUENCY SIGNALS**



(57) **Abrégé/Abstract:**

A satellite system for detecting radio frequency signals from space including at least two sensors, a processing unit and at least one receiver. Each sensor receives a plurality of radio frequency signals containing messages and outputs a sensor signal that is representative of the plurality of radio frequency signals. The processing unit selects a predetermined number of mathematical combinations of the sensor signals and combines the sensor signals into the predetermined number of mathematical combinations to produce a plurality of zone signals. The characteristics of each zone signal are undefined at the time the predetermined number of mathematical combinations is selected. The receiver extracts the messages contained in the zone signals.

ABSTRACT OF THE DISCLOSURE

A satellite system for detecting radio frequency signals from space including at least two sensors, a processing unit and at least one receiver. Each sensor receives a plurality of radio frequency signals containing messages and outputs a sensor signal that is representative of the plurality of radio frequency signals. The processing unit selects a predetermined number of mathematical combinations of the sensor signals and combines the sensor signals into the predetermined number of mathematical combinations to produce a plurality of zone signals. The characteristics of each zone signal are undefined at the time the predetermined number of mathematical combinations is selected. The receiver extracts the messages contained in the zone signals.

- 1 -

**Title: SYSTEMS AND METHODS FOR SEGMENTING A SATELLITE FIELD OF VIEW
FOR DETECTING RADIO FREQUENCY SIGNALS**

FIELD

[0001] Embodiments described herein relate to systems and methods for segmenting a satellite field of view for detecting radio frequency signals. More particularly, embodiments described herein relate to systems and methods for segmenting a low earth orbit satellite field of view for receiving Automatic Identification System signals.

BACKGROUND

[0002] The Automatic Identification System (AIS) is a short-range (typically 20-46 nautical miles) tracking system used by ships and terrestrial marine traffic monitoring stations for identifying and locating ships. Each ship has an AIS transponder that automatically broadcasts short messages (up to 256 bits) at regular intervals. These messages may include information about the ship's identity, such as IMO number, call sign and name, UTC time, length, location, course over ground, speed over ground, and other details about the ship, its movement or cargo. The messages are received by AIS transponders fitted on other ships or land-based monitoring stations. The frequency at which a ship transmits AIS messages is based on the state of the ship's motion. For example, ships that are anchored or are moving slowly transmit less frequently than those that are moving faster or are maneuvering.

[0003] AIS messages are typically transmitted on one or both of two Very High Frequency (VHF) channels centered at 161.975 MHz and 162.025 MHz and use 9600 bits/s Gaussian minimum shift keying (GMSK) modulation over 25 or 12.5 kHz channels using the High-level Data Link Control (HDLC) protocol. However, it will be evident to a person of skill in the art that future global and regional AIS systems may make use of additional frequencies. In the usual mode of operation, ship transmissions alternate between the two channels on a per transmission basis.

- 2 -

[0004] To ensure that VHF transmissions of different AIS transponders do not occur at the same time, the signals are time multiplexed using a technology called Self-Organizing Time Division Multiple Access (SOTDMA). Under SOTDMA each minute of time is divided into 2,250 equal time slots of 26.67 ms each. With a transmission speed of 9600 bits/s this translates into 256 bits per timeslot.

[0005] The time slots are typically synchronized accurately to Coordinated Universal Time (UTC) typically using Global Positioning System (GPS). Each AIS transponder determines its own transmission slot based upon the signal levels of AIS messages received from other ships and knowledge of future actions by other ships. Specifically, slot selection by an AIS transponder is randomized within a defined interval, and tagged with a random timeout of between 0 and 8 frames. When a ship changes its slot assignment, it announces both the new location and the timeout for that location. This self-organizing feature avoids signal collisions over the short ranges involved in surface transmissions and permits many ships to share the AIS frequencies efficiently.

[0006] The use of two AIS channels allows for up to 4500 messages per one-minute time frame. This capacity is relevant for a self-organized region determined by the broadcast range of the ship transponders (typically 20-46 nautical miles in radius). Where there are more ships in a particular broadcast range, the transponders will automatically reduce their receive range to reduce the size of the SOTDMA region. Specifically, under the SOTDMA CS protocol used with Class-B AIS transponders, a ship's transponder will start-up with a low signal level threshold of -107 dB. This means that the ship will accept or receive AIS signals with a signal level of -107 dB or greater. If a ship is unable to find an empty slot with this particular low signal level threshold (e.g. there are too many ships in this receive range), then the ship's transponder will incrementally step up the low signal level threshold until the transponder is able to find a free slot, or the low signal level threshold reaches -77 dB. In practice, this threshold is offset by a further 10 dB from the actual measured signal level. Class-A AIS transponders also co-ordinate their transmissions in a similar fashion, using received

- 3 -

transmissions from other ships as well as shore-based AIS stations to utilize pre-allocated time slots that assigned to particular ships while within range of the shore-based AIS station. It should be noted that changes to the low signal level threshold do not affect the transmit range, as transmit power level is not changed. In most cases the transmitter power is fixed at about 2 W for Class-B, and 12.5 W for Class-A AIS transponders.

[0007] The use of AIS is now mandatory on all ships with a gross tonnage of 300 or more tons engaged on international voyages, and all passenger ships regardless of size or tonnage. It is estimated that more than 40,000 ships carry AIS equipment. AIS was originally conceived as an aid to navigation and safety, and also has potential security applications for monitoring maritime traffic. AIS signal detection could be achieved using coastal/ground stations, but the limited range of the VHF signals would require such coastal/ground stations to be situated at many locations along the coast, and even then, they could only monitor the immediate coastal region.

SUMMARY

[0008] Embodiments described herein relate generally systems and methods for segmenting a satellite field of view for detecting radio frequency signals. More particularly, embodiments described herein relate to systems and methods for segmenting a low earth orbit satellite field of view for receiving Automatic Identification System signals.

[0009] In one broad aspect there is provided a system for detecting radio frequency signals from space using a satellite, the system comprising:

- (a) at least two sensors, each sensor for
 - (i) receiving a plurality of radio frequency signals, each radio frequency signal comprising at least one message; and
 - (ii) outputting a sensor signal that is representative of the plurality of radio frequency signals;

- 4 -

(b) a processing unit for:

selecting a predetermined number of mathematical combinations of the sensor signals; and

combining the sensor signals into the predetermined number of mathematical combinations to produce a plurality of zone signals, the characteristics of each zone signal being undefined at the time the predetermined number of mathematical combinations is selected; and

at least one receiver for extracting the at least one message contained in the zone signals.

[0010] In one aspect there is provided a method for detecting radio frequency signals from space using a satellite, the method comprising:

a) each of a plurality of sensors receiving a plurality of radio frequency signals, each radio frequency signal comprising at least one message;

b) each of the plurality of sensors outputting a sensor signal representative of the received AIS signals;

c) selecting a predetermined number of mathematical combinations of the sensor signals;

d) combining the sensor signals into the predetermined number of mathematical combinations to produce a plurality of zone signals, the characteristics of each zone signal being undefined at the time the predetermined number of mathematical combinations is selected; and

e) extracting the at least one message contained in the zone signals.

[0011] Further aspects and advantages of the embodiments described herein will appear from the following description taken together with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

[0012] For a better understanding of embodiments of the systems and methods described herein, and to show more clearly how they may be carried into effect, reference will be made, by way of example, to the accompanying drawings in which:

[0013] FIG. 1 is a schematic diagram of an AIS processing system including a low earth orbit satellite and a ground station;

[0014] FIG. 2 is schematic diagram illustrating exemplary low earth orbit satellite fields of view;

[0015] FIG. 3 is a schematic diagram illustrating an exemplary low earth orbit satellite field of view covering multiple SOTDMA cells;

[0016] FIG. 4 is a graph illustrating the probability of a ship being detected by a low earth orbit satellite using a standard AIS receiver as a function of the number of ships in the field of view during a 10 minute period;

[0017] FIG. 5 a block diagram of the low earth orbit satellite of FIG. 1 including a processing unit and a controller in accordance with a first embodiment;

[0018] FIG. 6 is a graph illustrating a first non-linear function;

[0019] FIG. 7 is a graph illustrating a second non-linear function;

[0020] FIG. 8 is a schematic diagram illustrating a first exemplary zone pattern generated by the low earth orbit satellite of FIG. 5;

[0021] FIG. 9 is a schematic diagram illustrating a second exemplary zone pattern generated by the low earth orbit satellite of FIG. 5;

[0022] FIG. 10 is a schematic diagram illustrating a low earth orbit satellite with three sensors;

[0023] FIG. 11 is a schematic diagram illustrating a zone pattern generated from the sensors signals output by the three sensors of FIG. 10;

- 6 -

[0024] FIG. 12 is a block diagram of the processing unit of FIG. 5 including a zone generator in accordance with an embodiment;

[0025] FIG. 13 is a block diagram of the zone generator of FIG. 12 in accordance with an embodiment;

[0026] FIG. 14 is a block diagram of the controller of FIG. 5 in accordance with a first embodiment;

[0027] FIG. 15 is a block diagram of the controller of FIG. 5 in accordance with a second embodiment;

[0028] FIG. 16 is a block diagram of the low earth orbit satellite of FIG. 1 in accordance with a second embodiment; and

[0029] FIG. 17 is a flowchart diagram of a method for segmenting a low earth orbit satellite field of view in accordance with at least one embodiment.

[0030] It will be appreciated that for simplicity and clarity of illustration, elements shown in the figures have not necessarily been drawn to scale. For example, the dimensions of some of the elements may be exaggerated relative to other elements for clarity. Further, where considered appropriate, reference numerals may be repeated among the figures to indicate corresponding or analogous elements.

DETAILED DESCRIPTION

[0031] It will be appreciated that numerous specific details are set forth in order to provide a thorough understanding of the exemplary embodiments described herein. However, it will be understood by those of ordinary skill in the art that the embodiments described herein may be practiced without these specific details. In other instances, well-known methods, procedures and components have not been described in detail so as not to obscure the embodiments described herein. Furthermore, this description is not to be considered as limiting the scope of the embodiments described herein in any

- 7 -

way, but rather as merely describing the implementation of the various embodiments described herein.

[0032] Standard AIS transponders typically have a horizontal range that is highly variable but is typically limited to about 46 nautical miles (85 km). The vertical range of standard AIS transponders is, however, much greater and typically extends beyond the 400 km orbit of the International Space Station (ISS). Accordingly, AIS signals can be received and detected using low earth orbit (LEO) satellites.

[0033] Reference is now made to FIG. 1, which illustrates an AIS processing system **10** including a LEO satellite **12** and a ground station **14** for receiving and decoding AIS signals in accordance with an embodiment. FIG. 1 illustrates numerous ships **16** that each has an AIS transponder **18** for transmitting AIS signals that are received by the LEO satellite **12**.

[0034] Typically, a given ship **16** will transmit AIS signals over two or more narrowband (i.e. 25 kHz) VHF channels. Examples of AIS VHF channels include AIS 1 at 161.975 MHz, AIS 2 at 162.025 MHz, and US AIS at 157.375 MHz. However, a person of skill in the art will understand that various other radio frequency channels could be used. For example, various regulatory bodies are currently studying new AIS frequencies for potential space-based and regional use.

[0035] To transmit the signal, the transmitting unit of the AIS transponder **18** employs a 9.6 kbps Gaussian minimum shift keying (GMSK) modulation, which is commonly known to imply that the AIS signal will be contained within a 14 kHz bandwidth. The LEO satellite **12** is equipped with at least one VHF antenna and receives the AIS signal transmitted by the ship **16**. The LEO satellite **12** travels at a high velocity and consequently the AIS signal received by the LEO satellite **12** undergoes a Doppler shift. For example, a LEO satellite in a 700 km circular orbit travels at about 7,500 m/s resulting in a Doppler shift of up to +/- 3.64 kHz at VHF frequencies.

[0036] The AIS signals received by the LEO satellite **12** will have a range of amplitudes, depending on the location of the ship **16** and its angular position as seen by

- 8 -

the LEO satellite **12**. Generally, the transmitting antenna used in the AIS transponder **18** of a given ship **16** does not radiate directly upwards, and this creates a reception hole directly underneath the LEO satellite **12**. However, for most of the FOV (field of view) of the LEO satellite **12**, the radiation patterns of the transmitting antenna of the AIS transponder **18** tend to balance the reduced signal strength caused by increased range, and the range of received signal amplitudes is relatively modest, and is most likely less than 10 dB for most of the FOV of the LEO satellite **12**.

[0037] In some embodiments, the received AIS signals are processed at the LEO satellite **12** by an on-board receiver unit. The extracted messages are then downlinked to the ground station **14**. In other embodiments, the LEO satellite **12** pre-processes all of the received AIS signals to create digital input data, which is downlinked to the ground station **14** where the digital input data is processed by a receiver unit.

[0038] In alternative embodiments, there may be more than one LEO satellite **12** that receives and pre-processes, or detects and decodes, the AIS signals. In addition, or alternatively, one or more ground stations **14** may be used to decode the pre-processed AIS signals. In another alternative, the processing required for detection and decoding can be separated between the LEO satellite **12** and the ground station **14**; this scheme can also be extended to the cases in which there is more than one LEO satellite **12** and one ground station **14**, one LEO satellite **12** and more than one ground station **14**, or more than one LEO satellite **12** and more than one ground station **14**. Accordingly, in these cases, data can be transmitted between the LEO satellite(s) and ground station(s) for processing in a variety of fashions. For simplicity, the embodiments described herein are with regards to a system with one LEO satellite **12** and one ground station **14**, but the processing methodology can be extended to several LEO satellites and/or several ground stations. It is also conceivable that data inter-satellite links (ISL) amongst a constellation of LEO satellites could be employed. However, this is a very costly and complex approach, and, in practice, distribution of data via the terrestrial network is likely to be employed.

- 9 -

[0039] The AIS was initially designed for ship-to-ship and ship-to-shore aid to navigation and communication. Accordingly, satellite-based AIS systems have a unique set of issues. Specifically, the large field of view (FOV) of a LEO satellite means that the LEO satellite may receive signals from a large number of ships at once. This is particularly true as the LEO satellite passes over high volume shipping areas, which typically results in a large number of AIS signals colliding or overlapping with one another. Furthermore, the large FOV of a LEO satellite means that ships in the FOV may be very far from each other and at great distances the SOTDMA communication method is not effective at avoiding signal collisions. Propagation delays also affect accurate time synchronization.

[0040] Reference is now made to FIGS. 2 and 3. FIG. 2 illustrates typical fields of view **202** and **204** of LEO satellites. FIG. 3 illustrates a typical field of view **302** of a LEO satellite covering multiple SOTDMA cells **304**.

[0041] Therefore, one problem encountered in LEO satellite-based AIS detection is that many of the AIS signals sent by ships will collide or overlap with one another. For example, it is estimated that there may be 2,000 ships in the FOV of a LEO satellite in moderate traffic areas. Each ship will typically send 10 AIS position reports per minute so for 2,000 ships a LEO satellite will receive 20,000 AIS signals per minute. This is a very large number compared to the number of available time slots (i.e. 4,500 across both VHF channels) and as a result, many AIS signals will collide with one another. Accordingly, the higher number of ships in the FOV, the higher number of collisions, and the more difficult it is for the LEO satellite to accurately detect the AIS signals.

[0042] Reference is now made to FIG. 4 which illustrates the probability of a ship being detected by a LEO satellite using a standard AIS receiver as a function of the number of ships in the FOV during a 10 minute period. It can be seen from FIG. 4 that the detection performance drops to 35% where there are about 1,100 ships in the FOV during a 10-minute period. Accordingly, it appears that the detection threshold for a standard AIS receiver is 800 to 1000 ships in the FOV. Once this threshold is exceeded, the probability of detection drops dramatically. In busy shipping areas of the ocean, the

- 10 -

number of ships in the FOV can easily exceed this number. For example, it is estimated that even for the mid-Atlantic area, which is characterized as having a moderate amount of shipping traffic, there are approximately 2,500 to 3,000 ships in a typical LEO satellite's FOV.

[0043] Accordingly, the performance of satellite-based AIS processing systems may be enhanced by dividing the large satellite FOV into a number of smaller segments so that the number of ships in each segment is less than the threshold. The segments are designed to cover the entire FOV so that the coverage area of the satellite is not reduced.

[0044] One known method of segmenting a satellite's FOV is to use classic phased arrays or feed arrays to form a large number of non-ambiguous spot beams. The goal is for each spot beam to have as uniform a radiation pattern as possible, typically maximizing energy received in the main lobe of each beam and reducing or eliminating side lobe energy. Major disadvantages of this solution include the high complexity and cost, and specifically for spaced-based applications, the size and mass.

[0045] Accordingly, there is a need for cost-effective and simple systems and methods for segmenting a satellite's FOV.

[0046] Reference is now made to FIG. 5 which is a block diagram of a LEO satellite **12** in accordance with a first embodiment. The LEO satellite **12** has a plurality of sensors and each sensor receives AIS signals transmitted by a plurality of ships **16** and outputs a sensor signal representative of the received AIS signals. The sensor signals are mathematically combined to produce a plurality of zone signals. The zone signals segment the satellite's FOV into a plurality of zones. The zone signals are then separately processed to extract the AIS messages contained therein. In the embodiment shown in FIG. 5, the LEO satellite **12** includes two sensors **502** and **504**, a processing unit **506**, a receiver **508** and a transmitter unit **510**.

[0047] Each sensor **502** and **504** receives a plurality of AIS signals from the ships **16** and produces a sensor signal that is representative of the received AIS signals. The

- 11 -

sensor signal is then forwarded to the processing unit **506** for zone processing. In some embodiments, the sensors **502** and **504** are RF (radio frequency) antennas. In these embodiments, the sensors **502** and **504** may be any type of RF antenna suitable for use on a LEO satellite. For example, the sensors **502** and **504** may be monopole antennas, patch antennas or helical antennas. Each antenna may be of the same type or different types. For example, one sensor (i.e. sensor **502**) may be a patch antenna, and another sensor (i.e. sensor **504**) may be a helical antenna.

[0048] In one embodiment, the sensors **502** and **504** are Very High Frequency (VHF) antennas configured to receive all AIS channel signals. In one embodiment, each sensor **502** and **504** is configured to receive AIS signals transmitted over AIS 1, AIS 2 and US AIS channels. In other embodiments, each sensor **502** and **504** is configured to receive AIS signals transmitted over AIS 1 and AIS 2 channels and one or more dedicated satellite AIS channels to be allocated.

[0049] In some embodiments, the sensors **502** and **504** are spatially separated from one another so that they receive different versions of the same signal. In some cases the sensors **502** and **504** are spatially separated on the same LEO satellite (i.e. LEO satellite **12**). In other cases the sensors **502** and **504** are situated on at least two different satellites that form a satellite cluster.

[0050] In other embodiments, the sensors **502** and **504** may be polarized in a different manner. In some cases, the antennas may have different circular polarizations. For example, one sensor (i.e. first sensor **502**) may be an antenna that has a right circular polarization, and another sensor (i.e. second sensor **504**) may be an antenna that has a left circular polarization. In other cases, the antennas may have different linear polarizations. For example, one sensor (i.e. first sensor **502**) may be an antenna that has a linear vertical polarization, and another sensor (i.e. sensor **504**) may be an antenna that has a linear horizontal polarization. In still other cases, the sensors **502** and **504** may be antennas that have a mix of linear, elliptical (between linear and circular) and circular polarizations.

- 12 -

[0051] The processing unit **506** receives the plurality of sensor signals generated by the sensors **502** and **504** and mathematically combines them to produce a plurality of zone signals. The phrase “mathematical combination” will be used herein to describe a simple mathematical combination of two or more sensor signals. Each mathematical combination may be formed by (i) weighting or amplifying one or more of the sensor signals; and/or (ii) adjusting the phase of one or more of the sensor signals; and/or (iii) applying a delay to one or more of the sensor signals; and/or (iv) applying a transfer function to one or more of the sensor signals; and (v) summing the amplified, phase shifted, delayed, and/or transferred sensor signals to produce a zone signal.

[0052] A transfer function is any function that has a defined output for a given input. The transfer function may apply linear or non-linear polynomials or algorithms such as a neural network. Reference is now made to FIGS. 6 and 7, which illustrate exemplary non-linear transfer functions that may be applied by the processing unit **506**. Specifically, FIG. 6 illustrates a first exemplary non-linear transfer function **602** and FIG. 7 illustrates a second exemplary non-linear transfer function **702**.

[0053] Where there are more than two sensors, thus more than two sensor signals, each mathematical combination does not have to include all of the sensor signals. For example, where there are four sensors, and thus four sensor signals, some mathematical combinations may be formed from only two of the sensor signals, whereas other mathematical combinations may be formed from all four sensor signals.

[0054] Unlike typical phased-arrays, which have a fixed number of valid signal combinations, there is virtually an unlimited number of suitable mathematical combinations for the systems and methods described herein. In some embodiments, the processing unit **506** may start with an initial number of mathematical combinations and increase or decrease the number of mathematical combinations based on the performance of the initial number of mathematical combinations. The processing unit **506** typically generates at least two mathematical combinations.

- 13 -

[0055] Each zone signal represents a portion of the FOV of the LEO satellite **12**. Specifically, each zone signal represents a zone that is a segment of the FOV of the LEO satellite **12**. In some embodiments, the zones segment the FOV of view by area such that the area of each zone is less than the area of the FOV. In other embodiments, the zones may segment the FOV by polarization, or any other suitable characteristic.

[0056] In traditional beam-forming (typically done using classic phased arrays) the objective is to form one or more beams with well defined characteristics. For example, the beams may be formed to have a consistent gain and polarization. In some cases one beam is formed and the weighting is adjusted for tracking purposes. In other cases multiple beams are formed through phasing (i.e. phase offsets). This can be contrasted from the zone-forming described herein. Specifically, the purpose of the zone-forming is not to define a particular beam or to track a particular signal, but to create a strong set of zone signals that will increase the number of AIS messages decoded. Accordingly, it can be said that zone-forming is results-based.

[0057] In most traditional phased array applications it is important that the characteristics (i.e. shape, size, coverage area) of each beam be well defined. For example, if the characteristics of the beams are well defined, knowing which beam the received signal came from may indicate the location of the source of the signal. Since AIS messages typically include information indicating the location of the transmitting ship it is not important to be able to determine the location of the source of the signal from the zone characteristics. Accordingly, in the systems and methods described herein the exact characteristics (i.e. shape, size, coverage area) of each zone need not be well defined. More particularly, in the systems and methods described herein the goal of the zone-forming process is not to generate zones with certain predetermined characteristics (e.g. shape, directivity, etc.), nor is it to generate a number of well-defined and non-overlapping zones. In contrast, the goal of the zone-forming processing is to segment the FOV into a plurality of zones that will maximize (or at least increase) the decoding capability of the satellite.

- 14 -

[0058] The zones generated by the processing unit **506** may be regular or irregular, overlapping or non-overlapping, unique or ambiguous, deterministic or random, static or adaptive, so long as the number of ships in each zone is less than the receiver detection threshold (i.e. 800-1000). This allows the processing unit **506** to be more compact and less expensive than a classic phased array and hence more compatible with small satellite usage.

[0059] Preferably, each zone signal is at least partially statistically independent from the other zone signals. Two zone signals are said to be statistically independent if knowing something about one zone signal does not yield any information about the other zone signal. The more statistically independent the zone signals, the more unique each zone. The more unique each zone, the greater number of unique messages being detected. The statistical independence of two signals can be determined by assessing the statistical similarity of the two signals. The statistical similarity of two zone signals may be assessed, for example, using time domain signal cross-correlation, or cross-covariance of the two signals. The assessment may also be performed, for example, on the phase or the frequency spectrum of the zone signals.

[0060] Reference is now made to FIGS. 8 and 9 which illustrate exemplary zone patterns **800** and **900**. Zone pattern **800** is comprised of zones **802**, **804**, **806**, **808**, **810**, **812**, and **814**, and zone pattern **900** is comprised of zones **902**, **904** and **906**. In these exemplary zone patterns **800** and **900**, the FOV is segmented by area. Specifically, it can be seen that each zone (i.e. zones **802**, **804**, **806**, **808**, **810**, **812**, and **814**) has an area that is less than the FOV area. It also can be seen, however, that each zone does not have to be of equal size. For example, zone **810** is larger than zone **814**.

[0061] Furthermore, it can be seen that a zone can be a combination of a set of sub-zones. For example, zone **804** is comprised of two sub-zones **816** and **818**, and zone **902** is comprised of two sub-zones **908** and **910**. Accordingly, each zone does not have to be contiguous. Non-contiguous zones or zones with ambiguities may be formed, by example, by a thinned sensor array, where a thinned sensor array is defined as a sensor array in which the spacing between elements is greater than the

- 15 -

wavelength of the microwave signal. Specifically, the wide spacing of the thinned array elements causes constructive and destructive interference producing nulls in the radiation pattern. This is contrasted to a classic phased array where the distance between array elements is limited to half a wavelength to minimize (i) the effect of side lobes and (ii) ambiguities.

[0062] The goal is to select the mathematical combinations so that the number of ships in each zone is less than the receiver detection threshold (i.e. 800-1000 ships). In this manner it can be said that the mathematical combinations are selected to increase the probability of recovering AIS messages.

[0063] In some embodiments, in addition to segmenting the FOV into a plurality of zones, one or more nulls (a low gain area) are introduced into the zone pattern to further improve the detection capability of the LEO satellite **12**. Specifically, if a particular area has a high number of ships, the sensor signals can be mathematically combined to create a null in that area. If such a null is not inserted, the high number of ships may jeopardize detection of ships in an entire zone or FOV. It is not necessary to know the exact position of the null. Once a null is created, its position and/or other characteristics may be adaptively adjusted to improve the overall detection capability of the LEO satellite **12**.

[0064] Since the LEO satellite **12** acts as a scanner as it moves over the earth, any nulls created in a zone pattern will also move. Accordingly, ships that fall within a particular null at a specific point in time will eventually be picked up by the LEO satellite **12** as the nulls are moved over the earth. Since a ship typically sends more AIS messages than are needed by the LEO satellite **12** to accurately detect and monitor the ship, it is not necessary for the LEO satellite **12** to receive every AIS message transmitted by the ship. For example, a ship typically sends one AIS message per 10 seconds whereas only one message per 10 minutes is required to accurately detect and monitor the location of a ship.

- 16 -

[0065] Reference is now made to FIGS. 10 and 11 which illustrate the nulling principle. Specifically, FIG. 10 illustrates a LEO satellite **12** with three sensors **1002**, **1004**, and **1006**. Each sensor **1002**, **1004** and **1006** has an associated radiation pattern **1008**, **1010** and **1012**. The sensor signals generated by the three sensors **1002**, **1004** and **1006** are mathematically combined by a processing unit (i.e. processing unit **506**) to generate a plurality of zone signals, each zone signal defining a zone.

[0066] FIG. 11 illustrates an exemplary zone **1102** with a plurality of nulls **1104** and **1106**. In this example, the nulls **1104** and **1106** are generated by subtracting the second sensor signal (i.e. the sensor signal generated by the second sensor **1004**) from the combination of the first and third sensor signals (i.e. the sensor signals generated by the first and second sensors **1002** and **1006**). The strength of the nulls **1104** and **1106** may be adjusted by applying a gain to the second sensor signal before it is subtracted from the first and third sensor signals.

[0067] In the embodiment shown in FIG. 5, the processing of the sensor signals to produce the zone signals is performed at radio frequencies. However, in other embodiments the processing may be performed at intermediate frequencies or at baseband. In these other embodiments, the processing unit **506** may include a pre-processing unit to bring the sensor signals down to intermediate frequencies or baseband for processing. Processing may be performed by either analog or digital means.

[0068] In some embodiments, the mathematical combinations implemented by the processing unit **506** are stored in a memory unit (not shown) of the processing unit **506**. In some cases the memory unit may have one set of mathematical combinations that are always implemented by the processing unit **506**. In other cases, the memory unit may have sets of mathematical combinations that correspond to the trajectory of the LEO satellite **12** and the set of mathematical combinations used at a particular time is selected based on the position of the LEO satellite **12** in its orbit. The mathematical combinations may be selected through testing and simulation on the ground. In some cases the ground testing and simulation may be supplemented with testing or

- 17 -

experimentation performed in orbit. An exemplary processing unit **506** will be described in reference to FIGS. 12 and 13.

[0069] In other embodiments, the LEO satellite **12** may include a controller **512** that selects the mathematical combinations and supplies them to the processing unit **506**. In some cases the controller **512**, like the memory unit of the processing unit **506**, may have one static set of mathematical combinations that are always implemented by the processing unit **506**. In other cases, the controller **512** may have sets of mathematical combinations that correspond to the trajectory of the LEO satellite **12** and the set of mathematical combinations used at a particular time is selected based on the position of the LEO satellite **12** in its orbit. In still other cases, the controller **512** may adaptively select the mathematical combinations to optimize the detection performance.

[0070] In the cases where the controller **512** adaptively selects the mathematical combinations, an initial set of mathematical combinations may be first selected. The initial set of mathematical combinations may be selected through ground testing and simulation, testing and experimentation performed in orbit, or both. Where, however, it is not possible to perform ground or orbit testing, an initial set of “safe” mathematical combinations may be selected to create a plurality of zones wherein each zone covers a smaller area than the FOV and together the zones cover the entire FOV.

[0071] Once the initial set of mathematical combinations have been selected, they may then be adaptively adjusted to optimize the detection performance of the satellite. In optimization of a system with multiple parameters, besides the optimal solution (i.e. the global minimum) often there exist multiple suboptimal solutions (i.e. local minimums). These local minimums are typically acceptable for the systems and methods described herein. Which suboptimal solution (i.e. local minimum) is reached during the adaptive process generally depends on the initial set of mathematical combinations. Accordingly, to ensure that the adaptive process does not get stuck using a particular suboptimal solution (i.e. local minimum), it may be advantageous to apply a sufficiently strong perturbation in the adaptive process to force the optimization trajectory to jump out of the converging region associated with a particular local

- 18 -

minimum. Depending on definition of the optimization cost function, the optimization problem may also equivalently be interpreted as that of finding local or global maximums instead of minimums.

[0072] In some embodiments, the controller **512** adaptively selects the mathematical combinations based on the characteristics of the zone signals produced by the processing unit **506**. For example, the controller **512** may select the mathematical combinations based on one or more of the following: (1) the number of messages extracted from the zone signals; (2) the total power of the zone signals; (3) the bandwidth variations of the zone signals; (4) the amplitude distribution of the zone signals; (5) time slot boundaries; (6) the phase distribution of the zone signals; (7) the error rate (i.e. bit error rate) of the zone signals; (8) an eye diagram of the zone signals; (9) the phase trajectory of the zone signals; (10) cross-correlation or cross covariance between zone signals; and (11) coherency analysis of the zone signals. A person of skill in the art will understand that these are simply examples of suitable zone signal characteristics and other zone signal characteristics may also be used.

[0073] The total power of the zone signals may indicate the density of ships in each zone, the potential collision probability, and the interference level. The bandwidth variations of the zone signals may be useful to distinguish interference from the AIS signals, or to perform zoning according to Doppler offsets.

[0074] The amplitude (or power) distribution in each zone signal may indicate the density of ships in each zone and the collision level in each zone. Specifically, amplitude (or power) distribution analysis is the examination of the signal level variations in the time domain. Typically a “bad” zone signal (a zone signal comprising multiple interfering/colliding AIS GMSK signals/messages) will exhibit a lower peak to average amplitude or power ratio than a “good” zone signal (a zone signal comprising only a single AIS GMSK signal/message per message time slot).

[0075] Time slot boundaries occur in AIS signals (and thus zone signals) due to the SOTDMA time slot structure described above. In a “good” zone signal, the

- 19 -

consistency of the average signal power in each slot is expected to vary from slot-to-slot in a different manner. Typically “good” zone signals will have a higher ratio of maximum to minimum slot power than “bad” zone signals. Similarly, the regions of overlap between adjacent slot signals is expected to be different for “good” and “bad” zone signals. The time slot boundary analysis may be performed on the zone signal as it is received, or block wise in segments which represent the time period of a single AIS message. Where the analysis is done on a segment basis, the segmenting may be started at an assumed or analyzed estimated slot boundary location. The result of the analysis can be based on a single time slot or a number of time slots.

[0076] The phase distribution of a zone signal may indicate the quality of the zone signal. In some embodiments, the phase distribution of a particular zone signal may be assessed using a histogram of phase values. Specifically, a “good” zone signal comprising a single valid AIS message may cluster (show a higher histogram frequency) around a number of distinct phase values. Conversely, a “bad” zone signal comprising a plurality of collided messages may not show such clustering and typically distributed over a wider range. This analysis can be performed on the complete zone signal, or smaller time segments (or slots).

[0077] An eye diagram of a zone signal may also be useful in detecting collisions in a particular zone. Specifically, an eye diagram, following an assumed symbol timing recovery may be analyzed to determine the quality of the eye opening (a figure of merit of the signal to noise ratio (SNR) and the signal to interference ratio (SIR)). A closed or non-distinct eye may indicate undecodable and/or collided AIS signals. Collided AIS signals are defined as two or more AIS signals in the same time slot at similar power levels making error free detection of even the stronger AIS signal challenging or impossible.

[0078] The phase trajectory of a zone signal is the unwrapped phase angle of the zone signal or the sample by sample variations in the unwrapped phase angle. A “good” zone signal comprised of a single well-defined AIS signal is expected to have a phase trajectory with a number of well-defined transitions equal to the GMSK phase

- 20 -

modulation. Conversely, a “poor” zone signal comprised of multiple interfering AIS signals will typically produce a phase trajectory that is more random, and includes many, less distinct phase transitions caused by the interference. This analysis can be performed on the complete zone signal, or smaller time segments (or slots).

[0079] The mathematical combinations may also be selected based on the statistical independence of the zone signals. As described above, the statistical independence of a particular zone signal may be measured by performing a cross-correlation or a cross covariance of the zone signal and each of the other zone signals. The cross-correlations or cross covariances may be performed in sequence or simultaneously. Generally a zone signal having a lower cross-correlation with other zone signals has a high statistical independence from the other zone signals. This analysis can be performed on the complete zone signal, or smaller time segments (or slots).

[0080] Coherency analysis, such as via an autocorrelation, may yield similar results to the phase trajectory analysis described above. Specifically, a “good” zone signal comprised of only a single AIS signal/message is expected to have a certain shape (1% to 10% to 50% to 90% amplitude probability distribution), peak, standard deviation, etc. Conversely, a “bad” zone signal comprised of a plurality of interfering AIS signals/messages will have statistics of the autocorrelation function that differ from those of the single AIS signal/message. This analysis can be performed on the complete zone signal, or smaller time segments (or slots).

[0081] Based on the characteristics of the zone signals the controller **512** may adjust or fine-tune the mathematical combinations. The controller **512** may, for example, increase the size of certain zones and decrease the size of other zones, or adjust the amplification of certain zone signals until the characteristics improve. The controller **512** may also adjust the polarization, ambiguity patterns, or the zone distribution relative to the direction the satellite is moving.

- 21 -

[0082] The receiver **508** receives the plurality of zone signals from the processing unit **506** and extracts the messages contained therein. The receiver **508** may be a standard AIS receiver, such as the EURONAV™ AI3000 or the Smart Radio Holdings Limited™ SR162 Professional AIS Receiver, or a proprietary receiver, such as that described in U.S. Published Patent Application No. 2008/0304597 to Peach, incorporated herein by reference. In some embodiments, such as that shown in FIG. 5, the LEO satellite **12** includes a single receiver **508** that sequentially processes the zone signals. In these embodiments the LEO satellite **12** may include a sampler (not shown) for sampling each of the zone signals and a memory module (not shown) for storing the samples. In other embodiments, the LEO satellite **12** includes multiple receivers (i.e. receiver **508**) and each zone signal is provided to a separate receiver for parallel or concurrent processing of the zone signals.

[0083] In some embodiments, the LEO satellite **12** may also include a screening unit **514** that receives the plurality of messages extracted by the receiver **508** and reduces the message count. Typically this is done to reduce the amount of bandwidth required to transmit the extracted messages from the LEO satellite **12** to the ground station **14**. In some embodiments, this involves eliminating any duplicate messages. Due to the fact that each zone signal is a combination of the same sensor signals, many messages will be detected multiple times.

[0084] The screening unit **514** sorts the messages in time order so that any duplicates can be easily identified. AIS messages typically include a time stamp that provides information on when the signal was generated. This time stamp, however, is not typically sufficient to accurately sort the messages. Accordingly, the time sorting performed by the screening unit **514** is typically based on the reception time of the signal as determined by the receiver **508**.

[0085] The receiver **508** will typically have a time reference (i.e. clock) that may or may not be derived from GPS (Global Positioning System) or other source of accurate timing information. Each message extracted by the receiver **508** will be tagged with a time stamp that indicates the time at which it was decoded. This will then

- 22 -

facilitate sorting of the messages by the screening unit **514**. Where there are multiple receivers that operate in parallel, the time reference (i.e. clock) of each of the receivers will typically be synchronized. Where there is only a single receiver that processes multiple zone signals serially, the time stamp may be a measure of the delta from the start of the zone signal, and the time reference (i.e. clock) may be reset each time a new zone signal is processed.

[0086] Once the messages have been sorted in time order the screening unit **514** identifies duplicate messages by comparison of message content, and modifies the message list so there are no duplicates. In some embodiments, the screening unit **514** modifies the message list as follows: (1) if two or more of the duplicate messages are identical (e.g. neither has a bit error) then one or more of the duplicate messages are deleted; (2) if one of the duplicate messages has no bit error, and one or more of the duplicate messages has a bit error, the duplicate message with the bit error is deleted; and (3) if all of the duplicate messages have a bit error, the duplicate messages may be combined to form a single message with a better bit error rate.

[0087] In other embodiments, the screening unit **514** modifies the message list based on historical data related to the ships from which the duplicate messages were sent. In some cases, the screening unit **514** may select a particular duplicate message to retain based on which of the duplicate messages is consistent with the historical data related to the ship. In this manner, the screening unit **514** is attempting to identify and remove any outliers. For example, ships typically travel along a specific advertised path, or shipping lane. The screening unit **514** may select a particular message to retain based on which message is consistent with the path advertised by the corresponding ship. In other cases, the screening unit **514** may combine the duplicate messages to generate a message that is consistent with the historical voyage trend data associated with the corresponding ship.

[0088] In some embodiments, the screening unit **514**, in addition to removing duplicate messages from the message list, may also reduce the number of messages by removing non-duplicate messages which do not improve the ability to detect and

- 23 -

monitor the location of ships from space. Specifically, as described above, the rate at which ships transmit AIS messages is related to the rate at which they are moving. Typically the faster a ship is moving, the more messages it generates per second. This scheme was developed for collision avoidance purposes. However, when a ship is moving at high speeds, the rate at which ships transmit AIS messages may exceed the rate required to monitor a ship's movement from space. Accordingly, the screening unit **514** may eliminate a number of non-duplicate messages from the same ship to reduce the number of messages from that ship down to a number required for space-monitoring purposes.

[0089] The screening unit **514** may be implemented in software on, for example, a general-purpose computer or a dedicated processor.

[0090] The transmitter unit **510** receives the messages from either the receiver **508** or the screening unit **514** (depending on whether the LEO satellite **12** includes a screening unit **514**) and transmits or downlinks them to the ground station **14**. The transmitter unit **510** typically includes a modulator (not shown) and a transmitter antenna (not shown). The modulator modulates the messages onto a carrier signal for transmission to the ground station **14**. The modulator may employ various modulation techniques, such as phase-shift keying (PSK) which modulates the message data onto the carrier in such a way that the sequence of zeros and ones making up the messages is represented by phase shifts in the carrier signal. Examples of suitable PSK techniques include binary PSK, quadrature PSK, or a higher-order PSK such as 8-PSK. Quadrature PSK uses four possible phase values and can therefore transmit two bits of data per symbol on the carrier. 8-PSK uses eight phase values and thus can transmit three bits of data per symbol on the carrier.

[0091] The modulator may be implemented by either digital or analog circuits. In digital implementation, the modulations are typically performed in the digital domain with a constellation mapper. The output of the constellation mapper may then be passed through a digital pulse shaping filter followed by a digital to analog converter to convert the digital modulated signal to an analog modulated signal for further processing.

- 24 -

[0092] To reduce the transmission errors between the LEO satellite **12** and the ground station **14**, the modulator may be configured to implement forward error correction (FEC), using, for example, Reed-Solomon codes, convolutional codes, Turbo codes, or Low Density Parity Check codes. As is known to those of skill in the art, forward error correction is where redundant data, also known as an error-correction code, is added to a message prior to transmission. This allows the receiver to detect and correct errors without the need to ask the sender for retransmissions or for additional data.

[0093] The modulated signal(s) are then sent to the transmitter which up-converts them to the frequency range required for transmission, and amplifies these signals so that they have the required signal strength needed for transmission to the ground station **14**. The transmitter may also include an output filter to limit the out of band signals generated by the amplification to control the potential interference with users in nearby frequency bands.

[0094] Since the decoded or extracted messages may include classified information that must be kept secure, encryption can also be employed by the transmitter unit **510** prior to preparing the messages for transmission to a ground station. In these cases, the transmitter unit **510** may also include an encryption module (not shown) for encrypting the plurality of messages received from the receiver **508** or the screening unit **514**.

[0095] Reference is now made to FIG. 12, which is a block diagram of a processing unit **506** in accordance with an embodiment. The processing unit **506** comprises three zone generators **1202**, **1204** and **1206**. Each zone generator **1202**, **1204** and **1206** receives the sensor signals output by the sensors **502** and **504** and mathematically combines them to produce a zone signal. As described above, although each zone generator **1202**, **1204** and **1206** receives each of the sensor signals, each zone generator **1202**, **1204** and **1206** may not mathematically combine all of the sensor signals. For example, if there are three sensor signals, some zone generators may only mathematically combine two of the three sensor signals, and some zone generators

- 25 -

may mathematically combine all three sensor signals. Although the processing unit **506** illustrated in FIG. 12 includes three zone generators **1202**, **1204** and **1206** it will be evident to a person of skill in the art that the processing unit may have other numbers of zone generators. Typically, a processing unit will have at least two zone generators to segment the FOV into at least two zones. An exemplary zone generator **1202** will be described in reference to FIG. 13.

[0096] Reference is now made to FIG. 13, which is a block diagram of a zone generator **1202** in accordance with an embodiment. As described above, the zone generator **1202** receives a copy of each of the sensor signals generated by the sensors **502** and **504** and mathematically combines them to produce a zone signal.

[0097] The zone generator **1202** comprises a signal path for each of the sensor signals. In the embodiment shown in FIG. 13, the zone generator **1202** receives two sensor signals, thus there are two signal paths. Each signal path modifies or adjusts one of the sensor signals. In some embodiments, each signal path may include one or more of the following adjustment blocks: (a) an amplifier or gain adjuster **1302** or **1304**; (b) a phase shifter **1306** or **1308**; (c) a delay block **1310** or **1312**; and (d) a transfer function block **1314** or **1316**. The order of the adjustment blocks within a particular signal path is not typically important. However, since the transfer function blocks **1314** and **1316** may introduce a non-linearity, it may be beneficial to place transfer blocks later in the signal path.

[0098] Each amplifier or gain adjuster **1302** and **1304** applies amplitude or gain scaling to one of the sensor signals. For example, the first amplifier **1302** may apply a gain of k_1 to the first sensor signal, and the second amplifier **1304** may apply a gain of k_2 to the second sensor signal.

[0099] Each phase shifter **1306** and **1308** applies a phase shift between 0° and 360° to one of the sensor signals. For example, the first phase shifter **1306** may apply a phase shift of Φ_1 to the first sensor signal, and the second phase shifter **1308** may apply

- 26 -

a phase shift of Φ_2 to the second sensor signal. As is known to a person of skill in the art, a phase shift of 180° will invert the sensor signal.

[00100] Each delay block **1310** and **1312** applies a delay to one of the sensor signals. For example, the first delay block **1310** may apply a delay D_1 to the first sensor signal, and the second delay block **1312** may apply a delay D_2 to the second sensor signal. The delays implemented by the delay blocks **1310** and **1312** are typically in the microsecond (μs) range, but may be smaller or larger.

[00101] Each transfer function block **1314** and **1316** applies a transfer function to the one of the sensor signals. For example, the first transfer function block **1314** may apply a first transfer function F_{n1} to the first sensor signal, and the second transfer function block **1316** may apply a second transfer function F_{n2} to the second sensor signal. Typically each transfer function adjusts the amplitude of one of the sensor signals as a function of the input amplitude. The most trivial (yet completely valid) transfer function is purely linear, in which the input and output are identical. In some embodiments, the transfer functions (i.e. F_{n1} and F_{n2}) implemented by the transfer function blocks **1314** and **1316** are non-linear, such as the transfer functions shown in FIGS. 6 and 7.

[00102] In other embodiments, one or more signal paths may include a filter transfer function block wherein the output of the filter transfer function block is a function of the input signal frequency. Such a frequency transfer function block provides for frequency selective filtering or equalization of the sensor signal.

[00103] The adjustment block coefficients (k_1 , k_2 , Φ_1 , Φ_2 , D_1 , D_2 , F_{n1} and F_{n2}) define a “mathematical combination” as that term is used herein. As described above in reference to FIG. 5, the mathematical combinations (i.e. the adjustment block coefficients) may be static, or they may be dynamically selected by the controller **512**. In some embodiments, the controller **512** selects the mathematical combinations (i.e. the adjustment block coefficients) based on the position of the satellite **12** in its orbit. In other embodiments, the controller **512** adaptively selects the mathematical

- 27 -

combinations (i.e. the adjustment block coefficients) based on characteristics of the zone signals.

[00104] Once each of the sensor signals has been adjusted by the adjustment blocks in the corresponding signal path, the modified zone signals are combined using a combiner or summer **1318** to produce a zone signal.

[00105] Reference is now made to FIG. 14, which is a block diagram of a controller **512** in accordance with a first embodiment. The controller **512** receives the plurality of zone signals produced by the processing unit **506**, analyzes the received zone signals, selects or modifies the coefficients corresponding to the zone signals, and outputs a control signal that relays the selected coefficients to the processing unit **506**. The processing unit **506** then modifies the adjustment block coefficients based on the received control signal.

[00106] The controller **512** comprises a plurality of zone signal analyzers **1402**, **1404** and **1406** and a plurality of coefficient selectors **1408**, **1410** and **1412**. Typically there is one zone signal analyzer **1402**, **1404** or **1406** and one coefficient selector **1408**, **1410** or **1410** for each zone signal received. For example, in the embodiment shown in FIG. 14, the controller **512** receives three zone signals, thus there are three zone signal analyzers **1402**, **1404** and **1406**, and three coefficient selectors **1408**, **1410** and **1412**.

[00107] Each zone signal analyzer **1402**, **1404** and **1406** receives one of the zone signals, analyzes the received signal, and outputs a metric indicative of the analysis. Specifically, the first zone signal analyzer **1402** analyzes the first zone signal, the second zone signal analyzer **1404** analyzes the second zone signal, and the third zone signal analyzer **1406** analyzes the third zone signal. The analysis performed by each zone signal analyzer **1402**, **1404** and **1406** may include analyzing one of the zone signal characteristics described above in relation to FIG. 5. For example, each zone signal analyzer **1402**, **1404** and **1406** may analyze, for example, the total power of the zone signal, the bandwidth variations of the zone signal, the amplitude distribution of the zone signal or the phase trajectory of the zone signal.

- 28 -

[00108] Each coefficient selector **1408**, **1410** and **1412** receives the metric indicative of the analysis performed by one of the zone signal analyzers **1402**, **1404** and **1406**, and selects and outputs new adjustment block coefficients based on the received metric. Specifically, the first coefficient selector **1408** receives the output metric from the first zone signal analyzer **1402** and selects new adjustment block coefficients for generating the first zone signal; the second coefficient selector **1410** receives the output metric from the second zone signal analyzer **1404** and selects new adjustment block coefficients for generating the second zone signal; and the third coefficient selector **1412** receives the output from the third zone signal analyzer **1406** and selects new adjustment block coefficients for generating the third zone signal. The specific adjustment block coefficients selected/adjusted by the coefficient selectors **1408**, **1410** and **1412** will be based on the particular coefficients implemented by the corresponding processing unit **506**.

[00109] The operation of the zone signal analyzers **1402**, **1404** and **1406** and the coefficient selectors **1408**, **1410** and **1412** will be further described using an example configuration. In the example configuration, there are three sensor signals, and the three sensor signals are each amplitude adjusted and then combined by a zone generator (e.g. zone generator **1202**) to form a first zone signal. Specifically, a first gain k_1 is applied to the first sensor signal, a second gain k_2 is applied to the second sensor signal, and a third gain k_3 is applied to the third sensor signal.

[00110] When a zone signal analyzer **1402**, **1404** or **1406** receives the zone signal it analyzes the received zone signal and outputs a metric representative of the analysis. As described above, the analysis may involve analyzing a particular characteristic of the zone signal, such as the phase trajectory of the zone signal.

[00111] When a coefficient selector **1408**, **1410** or **1412** receives the metric it may select the coefficients k_1 , k_2 and k_3 according to a simple linear optimization described using Table 1. First, a number of start and trial values are applied (these could be pre-defined based on knowledge of the sensors (e.g. sensors **502** and **504**), past values known to be effective, or a simple set of values). The trial value with the highest metric

- 29 -

is then used as a starting point for optimization. In this example, Trial 1 (when k_3 is -1) has the highest metric.

Table 1

		k_1	k_2	k_3	Metric
Start		1	1	1	0.1
Trial	1	1	1	-1	0.8
Trial	2	1	-1	1	0.7
Trial	3	-1	1	1	0.3
Optimization	1,1	1	1	-0.9	0.75
Optimization	1,2	1	1	-1.1	0.82
Optimization	1,3	1	1	-1.2	0.95
Optimization	1,4	1	1	-1.3	0.92
Optimization	1,5	1	1	-1.2	0.95

[00112] The first optimization step is to set k_3 to values above -1 and then below -1, and depending on the change in the metric, proceed in the same direction until it is found that the metric does not improve. In the example shown in Table 1, the values selected were -0.9 then, -1.1, -1.2, -1.3 and then back to -1.2 when demonstrated to be the value with the best metric.

[00113] Next, optimization could proceed to selecting k_2 , and/or another of the other coefficients. Note that k_1 does not need to be optimized if k_2 and k_3 are optimized. Specifically, varying k_2 and k_3 cover all potential amplitude (or equivalently power) ratios of k_1 , k_2 and k_3 .

[00114] Following such an optimization in the amplitude scaling factor k , a similar optimization may be applied to one or more of the other coefficient sets (phase, delay,

- 30 -

transfer function) using the initially optimized gain factor coefficients (k_1 , k_2 , k_3) as a starting point.

[00115] In some embodiments, the process may be repeated after each of the coefficients has been optimized since it is generally true that the coefficients interact. For example, optimization for coefficient k_3 may be affected by optimization for coefficient k_2 , or the phase, delay or transfer function optimizations.

[00116] In other embodiments, the optimization process may be repeated using smaller step sized to further optimize the results. When changes to the metric become acceptably small, a decision can be made to stop optimization. In other embodiments, instead of making small step changes, the size of changes in the metric can be used to scale the step changes, improving the rate of convergence of the optimization.

[00117] Although the example was described using a simple linear optimization process, it will be evident to a person of skill in the art that any number of standard optimization methodologies may be employed to select the coefficients.

[00118] Reference is now made to FIG. 15, which is a block diagram of a controller **512'** in accordance with a second embodiment. The controller **512'** of FIG. 15 differs from the controller **512** of FIG. 14 in that instead of analyzing each zone signal independently and then selecting the coefficients for a particular zone signal based on the analysis of that zone signal, an analysis of the zone signals is done collectively and the coefficients for all of the zone signals are selected based on the collective analysis.

[00119] Specifically, the controller **512'** of FIG. 15 comprises a signal analyzer **1502** which receives all of the zone signals, performs an analysis on one or more of the zone signals, selects coefficients for the zone signals based on the analysis, and outputs the coefficients as a control signal. Since the signal analyzer **1502** receives all of the zone signals, the signal analyzer may perform a comparison of zone signals. For example, the signal analyzer **1502** may perform a cross-correlation or a cross covariance of the zone signals to determine their statistical independence. In another example, the analysis may involve determining the ratio of the average signal strength

- 31 -

of a zone signal (e.g. the mean square amplitude or power, computed as the mean power calculated from the mean square voltage in each slot) over many message slots (e.g. 50) divided by the average mean squared power in the corresponding slots of all other zone signals, or other analyses that indicate that overall detection performance of the satellite has improved through selection of the coefficients to form zone signals. One such metric could be the maximization of the total number of uniquely received AIS messages from all individual zone receivers.

[00120] Where the analysis involves ratios or information from multiple zone signals, it may still be beneficial to perform some optimization on each zone signal independently first, before refining the optimization over multiple zone signals.

[00121] As shown in FIG. 15, the signal analyzer **1502** may also receive the output of the receiver **508**, or the screening unit **514**, or both and use this information to select the coefficients for the zone signals.

[00122] Reference is now made to FIG. 16 which is a block diagram of a LEO satellite **12'** in accordance with a second embodiment. The LEO satellite **12'**, like the LEO satellite **12** of FIG. 5, has a plurality of sensors that each receives AIS signals transmitted by a plurality of ships **16** and output a sensor signal. The sensor signals are mathematically combined to produce a plurality of zone signals. The zone signals segment the satellite's FOV into a plurality of zones. The zone signals are then separately processed to extract the AIS messages contained therein. In the embodiment shown in FIG. 16, The LEO satellite **12'** includes two sensors **1602** and **1604**, a multiple channel radio frequency receiver **1606**, a digital processing unit **1608**, a receiver **1610** and a transmitter unit **1612**. Similar to the LEO satellite **12** of FIG. 5, the LEO satellite **12'** may also include a controller **1614**, and a screening unit **1616**.

[00123] The sensors **1602** and **1604** of FIG. 16 correspond to the sensors **502** and **504** of FIG. 5. Specifically, each sensor **1602** and **1604** receives a plurality of AIS signals from the ships **16** and generates a sensor signal that is representative of the received AIS signals. The description of the sensors **502** and **504** given above with

- 32 -

respect to FIG. 5 applies equally to the sensors **1602** and **1604**. For example, the sensors **1602** and **1604** may be Very High Frequency (VHF) antennas configured to receive AIS signals. The antennas may be physically separated; they may be of different polarizations; and may be of different types.

[00124] The multiple channel radio frequency receiver **1606** receives the analog sensor signals from the sensors **1602** and **1604** and converts them into digital sensor signals. This allows the processing unit **1608** to perform the zoning operation in the digital domain. As discussed below, this improves the flexibility and control of the zoning operation. The analog to digital conversion performed by the multiple channel radio frequency receiver **1606** may include, for example, amplification, filtering, down conversion, sampling, frequency recovery, and/or phase offset recovery of the sensor signals.

[00125] The processing unit **1608** performs the same function as the processing unit **506** of FIG. 5. Specifically, the processing unit **1608** of FIG. 16 receives the plurality of digital sensor signals from the multiple channel radio frequency receiver **1606** and mathematically combines them to produce a plurality of zone signals. Each zone signal represents a portion of the FOV of the LEO satellite **12'**. Accordingly, the zone signals segment the FOV of the LEO satellite **12'** into a plurality of smaller zones. In some embodiments, each zone signal represents a zone and the area of the zone is less than the area of the FOV.

[00126] The description of the functions performed by the processing unit **506** given above with respect to FIG. 5 applies equally to the processing unit **1608** of FIG. 16. However, since the processing unit **1608** receives digital sensor signals from the multiple channel radio frequency receiver **1606**, and the processing unit **506** of FIG. 5 receives analog sensor signals directly from the sensors **502** and **504** there are a few differences between the two processing units **506** and **1608**.

[00127] The main differences between the processing unit **1608** and the processing unit **506** of FIG. 5 are: (i) the processing unit **506** of FIG. 5 is typically

- 33 -

implemented using analog components such as amplifiers and phase shifters, whereas the processing unit **1608** is typically implemented digitally by, for example, a digital signal processing (DSP) unit; and (ii) the processing unit **506** of FIG. 5 typically has a fixed configuration (e.g. it typically has a fixed number of amplifiers and phase shifters), whereas the processing unit **1608** of FIG. 16 typically has a flexible configuration. Accordingly, the number of zones and/or the parameters used to mathematically combine the sensor signals may be adaptively adjusted or fine-tuned during flight of the satellite **12'** to optimize the detection performance of the satellite **12'**.

[00128] The receiver **1610** of FIG. 16 corresponds to the receiver **508** of FIG. 5. Specifically, the receiver **1610** receives the plurality of zone signals from the processing unit **1608** and extracts the messages contained therein. The description of the receiver **508** given above with respect to FIG. 5 applies equally to the receiver **1610**. For example, the receiver **1610** may be a standard AIS receiver, such as the EURONAV™ AI3000 or the Smart Radio Holdings Limited™ SR162 Professional AIS Receiver, or a proprietary receiver, such as that described in U.S. Published Patent Application No. 2008/0304597 to Peach.

[00129] The transmitter unit **1612** of FIG. 16 corresponds to the transmitter unit **510** of FIG. 5. Specifically, the transmitter unit **1612** receives the messages from either the receiver **1610** or the screening unit **1616** (depending on whether the LEO satellite **12'** includes a screening unit **1616**) and transmits or downlinks them to the ground station. The description of the transmitter unit **510** given above with respect to FIG. 5 applies equally to the transmitter unit **1612**. For example, the transmitter unit **1612** typically includes a modulator (not shown) and a transmitter antenna (not shown).

[00130] The controller **1614** of FIG. 16 corresponds to the controller **512** of FIG. 5. Specifically, the controller **1614** selects the mathematical combinations and supplies them to the processing unit **1608**. The description of the controller **512** given above with respect to FIG. 5 applies equally to the controller **1614**. For example, like the controller **512** of FIG. 5, the controller **1614** of FIG. 16 may, for example, select the mathematical combinations based on the trajectory of the LEO satellite, or it may

- 34 -

adaptively select the mathematical combinations based on the characteristics of the zone signals to improve the detection capability of the LEO satellite **12'**.

[00131] The screening unit **1616** of FIG. 16 corresponds to the screening unit **514** of FIG. 5. Specifically, the screening unit **1616** receives the plurality of messages extracted by the receiver **1610** and eliminates any duplicate messages. The description of the screening unit **514** given above with respect to FIG. 5 applies equally to the screening unit **1616**. For example, the screening unit **1616**, like screening unit **514**, typically sorts the messages in time order and eliminates any duplicate messages.

[00132] Reference is now made to FIG. 17, which is a flowchart that illustrates a method **1700** of segmenting a LEO satellite FOV for receiving radio frequency signals in accordance with an embodiment. At **(1702)** a plurality of AIS signals are received at the LEO satellite by a plurality of sensors, such as sensors **502** and **504** or sensors **1602** and **1604**. Each sensor then outputs a sensor signal representative of the received AIS signals. The method **1700** then proceeds to **(1704)**.

[00133] At **(1704)** the plurality of sensor signals are mathematically combined to produce a plurality of zone signals. As described above, the phrase "mathematical combination" is used herein to describe a simple mathematical combination of two or more sensor signals. Each mathematical combination may be formed by (i) weighting or amplifying one or more of the sensor signals; and/or (ii) adjusting the phase of one or more of the sensor signals; and/or (iii) applying a delay to one or more of the sensor signals; and/or (iv) applying a transfer function to one or more of the sensor signals; and (v) summing the amplified, phase shifted, delayed, and/or transferred sensor signals to produce a zone signal.

[00134] Each zone signal represents a portion of the FOV of the LEO satellite. In one embodiment, each zone signal represents a zone and the area of the zone is less than the area of the FOV. Accordingly, in this embodiment, the zone signals segment the FOV of the LEO satellite into a plurality of smaller zones.

- 35 -

[00135] The mathematical combinations may be fixed or may be adaptively selected based on (i) the trajectory of the satellite; and/or (ii) the characteristics of the zone signals. Methods for adaptively selecting the mathematical combinations have been described in detail above with respect to FIG. 5.

[00136] The sensor signals may be mathematically combined by a processing unit, such as processing unit **506** or processing unit **1608**. Once the plurality of sensor signals have been mathematically combined to produce the plurality of zone signals, the method **1700** proceeds to **(1706)**.

[00137] At **(1706)**, the plurality of zone signals are decoded to extract the AIS messages contained therein. The plurality of zone signals are typically decoded by a receiver, such as receiver **508** or receiver **1610**. In some embodiments, the zone signals are processed in parallel, each zone signal being processed by a separate receiver. In other embodiments, a single receiver sequentially processes the zone signals.

[00138] Once the plurality of zone signals have been decoded, the method **1700** may proceed to **(1708)** or **(1710)** depending on whether the LEO satellite includes a screening unit, such as screening unit **514** or screening unit **1616**. If the LEO satellite includes a screening unit, the method **1700** typically proceeds to **(1708)**. If the LEO satellite does not include a screening unit, the method **1700** typically proceeds directly to **(1710)**.

[00139] At **(1708)** the AIS messages decoded at **(1706)** are filtered or screened to remove any duplicates. In some embodiments, the AIS messages may be time-ordered to identify any duplicates. Once the duplicates are identified the message list is modified so that there are no duplicates. This may involve removing the duplicates or combining duplicate messages to get an improved message. This process has been described above in detail in relation to FIG. 5. The screening may be performed by a screening unit, such as screening unit **514** or screening unit **1616**. Once the messages have been screened the method **1700** proceeds to **(1710)**.

- 36 -

[00140] At (1710) the messages are transmitted to a ground station (i.e. ground station 14). A method for transmitting the messages to a ground station has been described in detail in reference to FIG. 5. The transmission may be performed by a transmitter unit, such as transmitter unit 510, or transmitter unit 1612. Once the messages have been transmitted, the method 1700 is complete.

[00141] While the methods and systems described herein have been discussed as methods and systems for receiving AIS signals at a LEO satellite, it will be evident to a person of skill in the art that the methods and systems described herein may also be used to transmit AIS or AIS-like signals from a LEO satellite.

[00142] Specifically, a reverse process may be used to transmit a message back to the same zone in which a message was received. For example, once a particular set of mathematical combinations has been selected, those mathematical combinations can be reversed to send a message back to a particular zone or zones defined by the mathematical combinations. It should be noted, however, that due to the speed at which a typical LEO satellite (i.e. LEO satellite 12 or LEO satellite 12') moves over the earth, a particular set of mathematical combinations is typically only valid for a short period of time (i.e. seconds to a minute). Using such a reverse process allows one to achieve the same performance advantage of the forward direction (earth to LEO satellite) in the return direction (LEO satellite to earth).

[00143] While the above description provides examples of the embodiments, it will be appreciated that some features and/or functions of the described embodiments are susceptible to modification without departing from the principles of operation of the described embodiments. Accordingly, what has been described above has been intended to be illustrative of the invention and non-limiting and it will be understood by persons skilled in the art that other variants and modifications may be made without departing from the scope of the invention as defined in the claims appended hereto.

1. A satellite system for detecting radio frequency signals from space, the system comprising:

- a) at least two sensors, each sensor configured to:
 - (i) receive a plurality of radio frequency signals, each radio frequency signal comprising at least one message; and
 - (ii) output a sensor signal that is representative of the plurality of radio frequency signals;
- b) a controller configured to:
 - (i) select a predetermined number of mathematical combinations of the sensor signals; and
- c) a processing unit configured to:
 - (i) combine the sensor signals into the predetermined number of mathematical combinations to produce a plurality of zone signals, each zone signal covering a zone that is a portion of the field of view of the satellite system;
- d) at least one receiver configured to extract the at least one message contained in the zone signals;
- e) a screening unit coupled to the at least one receiver configured to eliminate duplicate messages and decimate non-duplicate messages from the same source.

2. The satellite system of claim 1, wherein each of the zone signals is at least partially statistically independent from the other zone signals.

3. The satellite system of claim 1, wherein the controller is further configured to adaptively select the mathematical combinations based on (1) at least one of the following: (a) total signal power of at least one zone signal, (b) bandwidth variations of at least one zone signal, (c) the amplitude distribution of at least one zone signal, (d) the phase distribution of at least one zone signal, (e) an eye diagram of at least one zone signal, (f) the phase trajectory of at least one zone signal, (g) cross-correlation of at least two zone signals, (h) cross covariance of at least two zone signals, and (i)

coherency analysis of at least one zone signal, (2) selected time segments of the zone signal, representing one or more message segments, (3) the number of messages extracted from at least one zone signal, and (4) the error rate of at least one zone signal.

4. The satellite system of claim 1, wherein the controller is further configured to select the mathematical combinations from a predefined list of mathematical combinations.

5. The satellite system of claim 1, wherein the screening unit is further configured to select a particular duplicate message for elimination based on the bit error rate of the particular duplicate message.

6. The satellite system of claim 1, wherein the screening unit is further configured to select a particular duplicate message for elimination based on historical data related to the source of the duplicate message.

7. The satellite system of claim 1, further comprising a memory unit configured to store the zone signals prior to sequential processing of the zone signals by the at least one receiver.

8. The satellite system of claim 7, further comprising at least one analog to digital converter configured to convert the zone signals into digital zone signals, the digital zone signals being stored in the memory unit.

9. The satellite system of claim 1, further comprising a plurality of receivers, each receiver configured to extract the at least one message contained in one of the zone signals.

10. The satellite system of claim 1, wherein the at least two sensors have different polarizations.

11. The satellite system of claim 1, wherein the at least two sensors have a field of view and the coverage of each zone signal is less than the field of view of the satellite.

12. The satellite system of claim 1, wherein each sensor is configured to receive radio frequency signals that are automatic identification system (AIS) signals or AIS-like signals sent by ships.

13. The system of claim 12, wherein each zone of the zone signals produced by mathematically combining the sensor signals have a number of ships less than a receiver detection threshold.

14. The system of claim 13, wherein the receiver detection threshold is in a range of 800 to 1000 ships.

15. The satellite system of claim 1, wherein the at least two sensors are chosen from monopole antennas, patch antennas, helical antennas or a mixture thereof.

16. A method for detecting radio frequency signals from space using a satellite, the method comprising:

- a) each of a plurality of sensors receiving a plurality of radio frequency signals, each radio frequency signal comprising at least one message;

- b) each of the plurality of sensors outputting a sensor signal representative of the received plurality of radio frequency signals;

- c) selecting by a controller a predetermined number of mathematical combinations of the sensor signals;

- d) combining by a processing unit the sensor signals into the predetermined number of mathematical combinations to produce a plurality of zone signals, each zone signal covering a zone that is a portion of the field of view of the satellite system;

- e) extracting by a receiver the at least one message contained in the zone signals; and

- f) decimating non-duplicate messages from the same source.

17. The method of claim 16, wherein each of the zone signals is at least partially statistically independent from the other zone signals.

18. The method of claim 16, wherein the mathematical combinations are adaptively selected based on (1) at least one of: (a) total signal power of at least one zone signal, (b) bandwidth variations of at least one zone signal, (c) the amplitude distribution of at least one zone signal, (d) the phase distribution of at least one zone signal, (e) an eye diagram of at least one zone signal, (f) the phase trajectory of at least one zone signal, (g) cross-correlation of at least two zone signals, (h) cross covariance of at least two zone signals, and (i) coherency analysis of at least one zone signal, (2) selected time segments of the zone signal, representing one or more message segments, (3) the number of messages extracted from at least one zone signal, and (4) the error rate of at least one zone signal.

19. The method of claim 16, wherein the mathematical combinations are selected from a predefined list of mathematical combinations.

20. The method of claim 16, further comprising eliminating duplicate messages.

21. The method of claim 20, wherein a particular duplicate message is selected for elimination based on the bit error rate of the particular duplicate message.

22. The method of claim 20, wherein a particular duplicate message is selected for elimination based on historical data related to the source of the duplicate message.

23. The method of claim 16, wherein the zone signals are sequentially processed by a single receiver to extract at least one message contained therein.

24. The method of claim 16, wherein the zone signals are concurrently processed by a plurality of receivers to extract the at least one message contained therein.

25. The method of claim 16, wherein the at least two sensors have different polarizations.

26. The method of claim 16, wherein the satellite has a field of view and the coverage of each zone signal is less than the field of view of the satellite.

27. The method of claim 16, wherein the radio frequency signals are automatic identification system (AIS) signals or AIS-like signals sent by ships.

28. The method of claim 27, wherein each zone of the zone signals produced by mathematically combining the sensor signals have a number of ships less than a receiver detection threshold.

29. The method of claim 28, wherein the receiver detection threshold is in a range of 800 to 1000 ships.

30. The method of claim 16, wherein the plurality of sensors are chosen from monopole antennas, patch antennas, helical antennas or a mixture thereof.

31. A satellite system for detecting radio frequency signals to produce a plurality of zone signals, the system comprising:

- a) at least two sensors, each sensor configured to:
 - (i) receive a plurality of radio frequency signals, each radio frequency signal comprising a plurality of messages; and
 - (ii) output a sensor signal that is representative of the received plurality of radio frequency signals;
- b) a processing unit configured to:
 - (iii) combine the sensor signals into an initial set of mathematical combinations to produce a plurality of zone signals representing zones that segment the field of view of the satellite system; and
 - (iv) combine the sensor signals into adjusted mathematical combinations to produce a plurality of zone signals representing zones having adjusted characteristics;
- c) a controller configured to:
 - (v) adaptively select the adjusted mathematical combinations based on characteristics of the zone signals produced by the processing unit; and
 - (vi) output a control signal relaying the adaptively selected adjusted mathematical combinations to the processing unit; and

- d) at least one receiver configured to extract one or more of the plurality of messages contained in the zone signals produced by combining the sensor signals into the adjusted mathematical combinations.

32. The satellite system of claim 31, wherein the controller is configured to adaptively select the adjusted mathematical combinations based on at least a number of messages extracted from at least one zone signal.

33. The satellite system of claim 31, wherein each of the zone signals is statistically independent from the other zone signals.

34. The satellite system of claim 31, wherein the controller selects the initial set of mathematical combinations.

35. The satellite system of any one of claims 31 to 34, wherein the controller is configured to adaptively select the adjusted mathematical combinations based on at least one of: a number of messages extracted from at least one zone signal, total power of the zone signals, bandwidth variations of at least one zone signal, amplitude distribution of at least one zone signal; time slot boundaries; phase distribution of at least one zone signal, error rate of at least one zone signal, an eye diagram of at least one zone signal, phase trajectory of at least one zone signal; cross-correlation of at least two zone signals, covariance of at least two zone signals, and coherence analysis of at least one zone signal.

36. The satellite system of any one of claims 31 to 35, wherein the controller selects the mathematical combinations from a predefined list of mathematical combinations.

37. The satellite system of any one of claims 31 to 36, further comprising a screening unit coupled to the at least one receiver for eliminating duplicate messages.

38. The satellite system of claim 37, wherein the screening unit selects a particular duplicate message for elimination based on one or both of bit error rate of the duplicate message and historical data related to the source of the duplicate message.

39. The satellite system of claims 37 or 38, wherein the screening unit is further for decimation of non-duplicate messages from the same source.

40. The satellite system of any one of claims 31 to 39, further comprising a memory unit for storing the zone signals prior to sequential processing of the zone signals by the at least one receiver.

41. The satellite system of claim 40, further comprising at least one analog to digital converter for converting the zone signals into digital zone signals, the digital zone signals being stored in the memory unit.

42. The satellite system of any one of claims 31 to 41, further comprising a plurality of receivers, each receiver for extracting the plurality of messages contained in one of the zone signals.

43. The satellite system of any one of claims 31 to 42, wherein the at least two sensors have different polarizations.

44. The satellite system of any one of claims 31 to 43, wherein the at least two sensors have a field of view and the coverage of each zone signal is less than the field of view of the satellite.

45. The satellite system of any one of claims 31 to 44, wherein each sensor is configured to receive radio frequency signals that are automatic identification system (AIS) signals or AIS-like signals sent by ships and wherein each zone of the zone signals that are produced by mathematically combining the sensor signals have a number of ships less than a receiver detection threshold.

46. The satellite system of claim 31 to 45, wherein each sensor is configured to receive radio frequency signals that are automatic identification system (AIS) signals or AIS-like signals sent by ships and wherein the controller adaptively selects the adjusted mathematical combinations based on characteristics of the zone signals to maintain a number of ships in each zone of the zone signals below a receiver detection threshold.

47. The system of claim 45, wherein the receiver detection threshold is in a range of 800 to 1000 ships.

48. The system of claim 47, wherein once the threshold is exceeded, the probability of detecting the radio frequency signal drops substantially.

49. The system of claim 46, wherein the receiver detection threshold is in a range of 800 to 1000 ships.

50. The system of claim 49, wherein once the threshold is exceeded, the probability of detecting the radio frequency signal drops substantially.

51. The system of any one of claims 31 to 50, wherein the at least two sensors are chosen from monopole antennas, patch antennas, helical antennas or a mixture thereof.

52. A method for detecting radio frequency signals using a satellite to produce a plurality of zone signals, the method comprising:

- a) each of a plurality of sensors receiving a plurality of radio frequency signals, each radio frequency signal comprising a plurality of messages;
- b) each of the plurality of sensors outputting a sensor signal representative of the received plurality of radio frequency signals;
- c) selecting an initial set of mathematical combinations of the sensor signals;
- d) combining the sensor signals into the initial set of mathematical combinations to produce a plurality of zone signals representing zones that segment the field of view of the satellite;
- e) adaptively selecting adjusted mathematical combinations based on the characteristics of the zone signals produced by combining the sensor signals into the initial set of mathematical combinations;
- f) combining the sensor signals into the adjusted mathematical combinations to produce a plurality of zone signals representing zones having adjusted characteristics; and

g) extracting one or more of the plurality of messages contained in the zone signals produced by combining the sensor signals into the adjusted mathematical combinations;

53. The method of claim 52, wherein the controller is configured to adaptively select the adjusted mathematical combinations based on at least a number of messages extracted from at least one zone signals.

54. The method of claim 52, wherein each of the zone signals is statistically independent from the other zone signals.

55. The method of claim 52, wherein the controller selects the initial set of mathematical combinations.

56. The method of any one of claims 52 to 55, wherein the controller is configured to adaptively select the adjusted mathematical combinations based on at least one of: a number of messages extracted from at least one zone signal, total power of the zone signals, bandwidth variations of at least one zone signal, amplitude distribution of at least one zone signal; time slot boundaries; phase distribution of at least one zone signal, error rate of at least one zone signal, an eye diagram of at least one zone signal, phase trajectory of at least one zone signal; cross-correlation of at least two zone signals, covariance of at least two zone signals, and coherence analysis of at least one zone signal.

57. The method of any one of claims 52 to 56, wherein the mathematical combinations are selected from a predefined list of mathematical combinations.

58. The method of any one of claims 52 to 57, further comprising eliminating duplicate messages.

59. The method of claim 58, wherein a particular duplicate message is selected for elimination based on one or both of bit error rate of the duplicate message and historical data related to the source of the duplicate message.

60. The method of claims 58 or 59, further comprising decimating non-duplicate messages from the same source.

61. The method of any one of claims 52 to 60, wherein the zone signals are sequentially processed by a single receiver to extract at least one message contained therein.

62. The method of any one of claims 52 to 61, wherein the zone signals are concurrently processed by a plurality of receivers to extract the at least one message contained therein.

63. The method of any one of claims 52 to 62, wherein the at least two sensors have different polarizations.

64. The method of any one of claims 52 to 63, wherein the satellite has a field of view and the coverage of each zone signal is less than the field of view of the satellite.

65. The method of any one of claims 52 to 64, wherein each sensor is configured to receive radio frequency signals that are automatic identification system (AIS) signals or AIS-like signals sent by ships and wherein each zone of the zone signals that are produced by mathematically combining the sensor signals have a number of ships less than a receiver detection threshold.

66. The method of any one of claims 52 to 65, wherein each sensor is configured to receive radio frequency signals that are automatic identification system (AIS) signals or AIS-like signals sent by ships and wherein the controller adaptively selects the adjusted mathematical combinations based on characteristics of the zone signals to maintain a number of ships in each zone of the zone signals below a receiver detection threshold.

67. The method of claim 65, wherein the receiver detection threshold is in a range of 800 to 1000 ships.

68. The method of claim 67, wherein once the threshold is exceeded, the probability of detecting the radio frequency signal drops substantially.

69. The method of claim 66, wherein the receiver detection threshold is in a range of 800 to 1000 ships.

70. The method of claim 69, wherein once the threshold is exceeded, the probability of detecting the radio frequency signal drops substantially.

71. The method of any one of claims 52 to 70, wherein the at least two sensors are chosen from monopole antennas, patch antennas, helical antennas or a mixture thereof.




FIG. 1
PRIOR ART

2/15




FIG. 2
PRIOR ART

3/15





FIG. 3
PRIOR ART

4/15

FIG. 4




FIG. 5

6/15




FIG. 6






FIG. 7

7/15

FIG. 8

8/15

FIG. 9

9/15




FIG. 10




FIG. 11




FIG. 12




FIG. 13





FIG. 14

13/15

FIG. 15





FIG. 16

15/15

FIG. 17

