




(86) Date de dépôt PCT/PCT Filing Date: 2008/02/19
(87) Date publication PCT/PCT Publication Date: 2008/09/04
(45) Date de délivrance/Issue Date: 2015/11/03
(85) Entrée phase nationale/National Entry: 2009/08/25
(86) N° demande PCT/PCT Application No.: JP 2008/052742
(87) N° publication PCT/PCT Publication No.: 2008/105267
(30) Priorités/Priorities: 2007/02/28 (JP2007-050837);
2007/03/19 (JP2007-071589)

(51) Cl.Int./Int.Cl. *H04J 11/00* (2006.01)
(72) Inventeurs/Inventors:
ISHII, HIROYUKI, JP;
HIGUCHI, KENICHI, JP
(73) Propriétaire/Owner:
NTT DOCOMO, INC., JP
(74) Agent: OYEN WIGGS GREEN & MUTALA LLP

(54) Titre : DISPOSITIF DE STATION DE BASE, DISPOSITIF D'UTILISATEUR, ET PROCEDE UTILISE DANS UN
SYSTEME DE COMMUNICATION MOBILE
(54) Title: BASE STATION APPARATUS, USER APPARATUS AND METHOD USED IN MOBILE COMMUNICATION
SYSTEM



(57) Abrégé/Abstract:

A base station device is used in a mobile communication system which employs the OFDM method for the downstream link. The base station device includes: means for creating a transmission signal by performing the inverse Fourier transform on a signal obtained by mapping the first signal and the second signal to a subcarrier with different transmission power densities; and means for transmitting the transmission signal to a user device. A subcarrier to which mapping of a second signal is inhibited (inhibited subcarrier) is decided so as to maintain the transmission power density of the second signal between a plurality of OFDM symbols, which does not depend on whether the OFDM symbol which contains the second signal also contains a first signal. The inhibit subcarrier is decided according to the subcarrier to which the first signal is to be mapped.

(12) 特許協力条約に基づいて公開された国際出願

(19) 世界知的所有権機関
国際事務局

PCT

(43) 国際公開日
2008年9月4日 (04.09.2008)(10) 国際公開番号
WO 2008/105267 A1(51) 国際特許分類:
H04J 11/00 (2006.01)

(21) 国際出願番号: PCT/JP2008/052742

(22) 国際出願日: 2008年2月19日 (19.02.2008)

(25) 国際出願の言語: 日本語

(26) 国際公開の言語: 日本語

(30) 優先権データ:
特願2007-050837 2007年2月28日 (28.02.2007) JP
特願2007-071589 2007年3月19日 (19.03.2007) JP

(71) 出願人 (米国を除く全ての指定国について): 株式会社 エヌ・ティ・ティ・ドコモ (NTT DOCOMO, INC.) [JP/JP]; 〒1006150 東京都千代田区永田町2丁目11番1号 Tokyo (JP).

(72) 発明者; および

(75) 発明者/出願人 (米国についてのみ): 石井 啓之 (ISHII, Hiroyuki) [JP/JP]; 〒1006150 東京都千代田区永田町2丁目11番1号 山王パークタワー 株式会社エヌ・ティ・ティ・ドコモ 知的財産部内 Tokyo (JP). 樋口 健一 (HIGUCHI, Kenichi) [JP/JP]; 〒1006150 東京都千代田区永田町2丁目11番1号 山王パークタワー 株式会社エヌ・ティ・ティ・ドコモ 知的財産部内 Tokyo (JP).


(74) 代理人: 伊東 忠彦 (ITO, Tadahiko); 〒1506032 東京都渋谷区恵比寿4丁目20番3号 恵比寿ガーデンプレイスタワー32階 Tokyo (JP).

(81) 指定国 (表示のない限り、全ての種類の国内保護が可能): AE, AG, AL, AM, AO, AT, AU, AZ, BA, BB, BG, BH, BR, BW, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH,

[続葉有]

(54) Title: BASE STATION DEVICE, USER DEVICE, AND METHOD USED IN MOBILE COMMUNICATION SYSTEM

(54) 発明の名称: 移動通信システムで使用する基地局装置、ユーザ装置及び方法



208102 DATA SIGNAL PROCESSING UNIT
 208102A ENCODER
 208102B DATA CONVERTER
 208102C INTERLEAVER
 208110 CP ADDITION UNIT
 208114 REFERENCE SIGNAL GENERATION UNIT
 AA REFERENCE SEQUENCE
 BB RANDOM SEQUENCE
 CC ORTHOGONAL SEQUENCE
 DD FROM SUBCARRIER MAPPING DECISION UNIT 2084

(57) Abstract: A base station device is used in a mobile communication system which employs the OFDM method for the downstream link. The base station device includes: means for creating a transmission signal by performing the inverse Fourier transform on a signal obtained by mapping the first signal and the second signal to a subcarrier with different transmission power densities; and means for transmitting the transmission signal to a user device. A subcarrier to which mapping of a second signal is inhibited (inhibited subcarrier) is decided so as to maintain the transmission power density of the second signal between a plurality of OFDM symbols, which does not depend on whether the OFDM symbol which contains the second signal also contains a first signal. The inhibit subcarrier is decided according to the subcarrier to which the first signal is to be mapped.

(57) 要約: 基地局装置は、下りリンクにOFDM方式を用いる移動通信システムで使用する。基地局装置は、第1の信号及び第2の信号が異なる送信電力密度でサブキャリアにマッピングされた信号を逆フーリエ変換し、送信信号を作成する手段と、送信信号をユーザ装置に送信す

る送信手段とを有する。第2の信号を含むOFDMシンボルに第1の信号が

[続葉有]

WO 2008/105267 A1

WO 2008/105267 A1



GM, GT, HN, HR, HU, ID, IL, IN, IS, JP, KE, KG, KM, KN, KP, KR, KZ, LA, LC, LK, LR, LS, LT, LU, LY, MA, MD, ME, MG, MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM, PG, PH, PL, PT, RO, RS, RU, SC, SD, SE, SG, SK, SL, SM, SV, SY, TJ, TM, TN, TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

SL, SZ, TZ, UG, ZM, ZW), ユーラシア (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), ヨーロッパ (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU, LV, MC, MT, NL, NO, PL, PT, RO, SE, SI, SK, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

(84) 指定国 (表示のない限り、全ての種類の広域保護が可能): ARIPO (BW, GH, GM, KE, LS, MW, MZ, NA, SD,

添付公開書類:
— 国際調査報告書

含まれるか否かによらず、第 2 の信号の送信電力密度が複数の OFDM シンボル間で一定に維持されるように、第 2 の信号のマッピングが禁止されるサブキャリア（禁止サブキャリア）が決定される。禁止サブキャリアは、第 1 の信号のマッピングされるサブキャリアに基づいて決定される。

-1-

SPECIFICATION

TITLE OF THE INVENTION

BASE STATION APPARATUS, USER APPARATUS AND
METHOD USED IN MOBILE COMMUNICATION SYSTEM

5

TECHNICAL FIELD

The present invention relates to a mobile communication system to which orthogonal frequency division multiplexing (OFDM) is applied in downlink.
10 More particularly, the present invention relates to a base station apparatus and a communication control method.

BACKGROUND ART

15 3GPP that is a standardization group of W-CDMA is studying a communication scheme that becomes a successor to W-CDMA and HSDPA, that is, 3GPP is studying Long Term Evolution (LTE). As radio access schemes, OFDM (Orthogonal Frequency Division
20 Multiplexing) is being studied for downlink, and SC-FDMA (Single-Carrier Frequency Division Multiple Access) is being studied for uplink (refer to non-patent document 1, for example).

OFDM is a scheme for dividing a frequency
25 band into a plurality of narrow frequency bands (subcarriers) so as to perform transmission by carrying data on each subcarrier. By arranging the subcarriers on frequencies densely without interfering with each other while a part of them
30 overlap, high speed transmission is realized so that efficiency of use of frequency increases.

SC-FDMA is a transmission scheme that can decrease interference among terminals by dividing frequency band and performing transmission using
35 frequency bands that are different among a plurality of terminals. Since the SC-FDMA has characteristics that variation of transmission power becomes small,

low power consumption in the terminal and wide coverage can be realized.

Generally, in mobile communications, pilot signals are used for channel estimation and radio
 5 quality measurement. The pilot signal is called Downlink Reference Signal (DL RS) in LTE.

The downlink reference signal in LTE is represented as a two dimensional sequence, and is formed by a two dimensional orthogonal sequence and
 10 a two dimensional pseudo random sequence. Mapping (subcarrier number) of the reference signal to physical resources can be represented by the following equation (non patent document 2):

$$k = 6m + (v + f_{\text{hop}}(\lfloor i/2 \rfloor)) \bmod 6$$

$$l = \begin{cases} 0 & n = 0 \\ N_{\text{symp}}^{\text{DL}} - 3 & n = 1 \end{cases}$$

15 wherein k indicates a subcarrier number, l indicates an OFDM symbol number, and i indicates a slot number, and m is an integer value as follows.

$$m = 0, 1, \dots, \left\lfloor \frac{N_{\text{BW}}^{\text{DL}}}{N_{\text{BW}}^{\text{RB}}/2} \right\rfloor$$

$$n = \begin{cases} 0, 1 & \text{for } p = 0, 1 \\ 0 & \text{for } p = 2, 3 \text{ and the generic frame structure} \\ 0, 1 & \text{for } p = 2, 3 \text{ and the alternative frame structure} \end{cases}$$

$$N_{\text{BW}}^{\text{RB}} = 12, \quad N_{\text{symp}}^{\text{DL}} = 7$$

$N_{\text{BW}}^{\text{DL}}$ indicates the number of subcarriers in the
 20 whole system band. $N_{\text{BW}}^{\text{DL}}$ is 300 when the system bandwidth is 5 MHz, is 600 when the system bandwidth is 10 MHz, and is 1200 when the system bandwidth is

-3-

20 MHz. P indicates an antenna port number. When only one antenna is used, $p=0$. When four antennas can be used, $p=0, 1, 2$ or 3 .

5 In the above-mentioned equation, v is determined by the following equation.

$$v = \begin{cases} 3n & \text{for } p=0 \\ 3+3n & \text{for } p=1 \\ 1+3(i \bmod 2) & \text{for } p=2 \\ 2+3(i \bmod 2) & \text{for } p=3 \end{cases}$$

10 In the before-mentioned equation, $f_{\text{hop}}(j)$ is a cell-specific integer sequence indicating a hopping pattern which changes for each subframe or each slot of the downlink reference signal. That is, by changing $f_{\text{hop}}(j)$ for each cell, it becomes possible to map the downlink reference signal to a subcarrier which is different for each cell.

15 The value $f_{\text{hop}}(j)$ may be a fixed value independent of time. When such a fixed value is set to each cell, the downlink reference signal is mapped while being shifted by the fixed value which is different for each cell.

20 Fig.1 shows a mapping example of the reference signal. Fig.1 shows mapping (left side) to physical resources when the antenna port number is 0 ($p=0$) and $f_{\text{hop}}(j)$ is always 0, and shows mapping (right side) to physical resources when the antenna port number is 0 ($p=0$) and $f_{\text{hop}}(j)$ is always 2.

25 As shown in the figure, in the former case, the downlink reference signal is mapped to k -th ($k = 6 \times j$ (j is an integer equal to or greater than 0)) subcarrier in the first OFDM symbol ($l=0$). However, in the latter case, the downlink reference signal is mapped to k -th ($k = 6 \times j + 2$ (j is an integer equal to or greater than 0)) subcarrier in the first OFDM symbol ($l=0$). Accordingly, the downlink reference signal in LTE is mapped to subcarriers which are

30

different for each cell by properly setting $f_{hop}(j)$.

By the way, it is being studied that the user apparatus performs demodulation of 16 QAM and 64 QAM by using information of a fixed value which is a ratio between transmission power per one subcarrier (transmission power density per unit frequency) of the downlink reference signal and transmission power per one subcarrier (transmission power density per unit frequency) of normal data signal (refer to non-patent document 3, for example). The normal data signal is, as a physical channel, the physical downlink shared channel (PDSCH). It is necessary to perform amplitude estimation for demodulation of 16 QAM and 64 QAM. It can be expected to improve estimation accuracy by performing demodulation by using the knowledge that power density difference between the reference signal and the data signal is a fixed value. In this case, since transmission power per one subcarrier of the downlink reference signal is always constant, transmission power per one subcarrier of the normal data signal is also always constant.

Since the downlink reference signal is not transmitted in all OFDM symbols, there is a time range in which the downlink reference signal is transmitted and a time range in which the downlink reference signal is not transmitted. Therefore, if total transmission power of the base station is set to be constant, transmission power density of the data signal may vary for each OFDM symbol. Then, there is fear that the amplitude estimation accuracy is susceptible to deterioration. Methods are proposed for setting transmission power of normal data signal to be constant in the both time ranges regardless of whether the reference signal is included in the OFDM symbol.

In one of the methods, the normal data signal is prohibited from being mapped to a predetermined subcarrier in a time range in which the downlink reference signal is transmitted. Any data is not mapped to the predetermined subcarrier. By reducing subcarriers where the data signal can be mapped, transmission power density of the data signal can be increased by that. Thus, transmission power density of the data signal can be kept constant regardless of whether the reference signal is transmitted. This technique is described in the non-patent document 3, for example..

[Non-patent document 1] 3GPP TR 25.814 (V7.0.0),
"Physical Layer Aspects for Evolved UTRA," June 2006

[Non-patent document 2] 3GPP TR 36.211 (V0.3.1),
"Physical Channels and Modulation," November 2006

[Non-patent document 3] R1-070088, Power Boosting
of Reference Signal in E-UTRA Downlink

DISCLOSURE OF THE INVENTION

PROBLEM TO BE SOLVED BY THE INVENTION

As mentioned above, the reference signal is mapped to a specific subcarrier in a specific OFDM symbol. Since channel estimation in the reception side (user apparatus, typically) is based on the reference signal, the mapping position has large effects on channel estimation accuracy. Therefore, it is necessary to properly set the position of the subcarrier (prohibited subcarrier) to which mapping of the data signal is prohibited in response to shift of mapping position of the reference signal in frequency direction and in response to hopping of the reference signal in time axis direction. However, such a mapping method is not adequately studied currently.

An object of the present invention is to provide a base station, a user apparatus and a

-6-

method used for them for properly placing prohibited subcarriers such that transmission power density of the data signal becomes constant in terms of time, in a next generation mobile communication system in which mapping position of the reference signal
5 changes in frequency direction and in time direction.

MEANS FOR SOLVING THE PROBLEM

A base station apparatus used in the
10 present invention is used in a mobile communication system that uses an OFDM scheme in a downlink. The base station apparatus includes: a unit configured to perform inverse Fourier transform on a signal in which a first signal and a second signal is mapped
15 to subcarriers with different transmission power density, and to generate a transmission signal; and a transmission unit configured to transmit the transmission signal to a user apparatus. A subcarrier (prohibited subcarrier) in which mapping
20 of the second signal is prohibited is determined such that transmission power density of the second signal is kept constant among a plurality of OFDM symbols regardless of whether the first signal is included in an OFDM symbol including the second
25 signal. The prohibited subcarrier is determined based on a subcarrier to which the first signal is mapped.

EFFECT OF THE INVENTION

30 According to the present invention, prohibited subcarriers can be properly arranged such that transmission power density of non-reference signals (typically, data signal) becomes temporally constant, in a next generation mobile communication
35 system in which mapping positions of the reference signal changes in the frequency direction and the time direction.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig.1 is a diagram showing a mapping example of the downlink reference signal;

5 Fig.2 is a block diagram showing a configuration of a mobile communication system according to an embodiment of the present invention;

Fig.3 is a schematic diagram showing a configuration of a subframe;

10 Fig.4 is a diagram showing a mapping example of subcarriers for two OFDM symbols;

Fig.5 is a partial block diagram showing a base station apparatus according to an embodiment of the present invention;

15 Fig.6A is a block diagram showing a baseband signal processing unit of the base station apparatus according to an embodiment of the present invention;

20 Fig.6B is a block diagram showing detailed configuration of a layer 1 processing unit of the baseband signal processing unit;

Fig.7 is a diagram showing a mapping example of subcarriers in the case when transmission power density of the downlink reference signal is the same as transmission power density of PDSCH;

25 Fig.8 is a diagram showing a mapping example of subcarriers in the case when transmission power density of the downlink reference signal is greater than transmission power density of PDSCH, and is a diagram showing a mapping example of subcarriers for an OFDM symbol;

30 Fig.9A is a diagram showing correspondence relationship between the number of puncturing subcarriers and their subcarrier numbers;

35 Fig.9B is a diagram showing correspondence relationship between the number of puncturing subcarriers and their subcarrier numbers;

-8-

Fig.9C is a diagram showing a mapping example of the downlink reference signal;

Fig.10 is a diagram showing correspondence relationship between offset power between the
 5 reference signal and other signal, and the number of puncturing subcarriers (when the system bandwidth is 5 MHz);

Fig.11 is a diagram showing correspondence relationship between offset power between the
 10 reference signal and other signal, and the number of puncturing subcarriers (when the system bandwidth is 10 MHz);

Fig.12A is a diagram showing correspondence relationship between offset power
 15 between the reference signal and other signal, and the number of puncturing subcarriers (when the system bandwidth is 20 MHz);

Fig.12B is a diagram showing correspondence relationship between the number of
 20 puncturing subcarriers and transmission power value (offset value) of the reference signal;

Fig.13A is a partial block diagram showing a user apparatus according to an embodiment of the present invention; and

25 Fig.13B is a diagram showing details of the baseband processing unit.

Description of reference signs

50 cell
 30 100₁, 100₂, 100₃, 100_n user apparatus
 102 transmit and receive antenna
 104 amplifying unit
 106 transmit and receive unit
 108 baseband signal processing unit
 35 110 call processing unit
 112 application unit
 200 base station apparatus

-9-

202 transmit and receive antenna
 204 amplifying unit
 206 transmit and receive unit
 208 baseband signal processing unit
 5 210 call processing unit
 212 transmission line interface
 2081 layer 1 processing unit
 2082 MAC processing unit
 2083 RLC processing unit
 10 2084 subcarrier mapping determination unit
 2085 DL transmission power control unit
 300 access gateway apparatus
 400 core network

15 PREFERRED EMBODIMENTS FOR CARRYING OUT THE INVENTION

Next, preferred embodiments for carrying out the present invention are described with reference to figures based on the following embodiments. In all of the figures for explaining
 20 embodiments, the same reference symbols are used for parts having the same function, and repeated descriptions are not given.

A mobile communication system to which the base station apparatus of an embodiment of the present invention is applied is described with
 25 reference to Fig.2.

The radio communication system 1000 is a system to which Evolved UTRA and UTRAN (Another name: Long Term Evolution, or Super 3G) is applied, for
 30 example. The radio communication system 1000 includes a base station apparatus (eNB: eNode B) 200 and a plurality of user apparatuses (UE: User Equipment) 100_n (100₁, 100₂, 100₃, ...100_n, n is an integer and n>0). The base station apparatus 200 is
 35 connected to an upper station, that is, an access gateway apparatus 300, for example, and the access gateway apparatus 300 is connected to a core network

-10-

400. The user apparatus 100_n is communicating with the base station apparatus 200 by Evolved UTRA and UTRAN in a cell 50.

In the following, since the user
5 apparatuses ($100_1, 100_2, 100_3, \dots, 100_n$) have the same configurations, functions and states, a user apparatus 100_n is described unless otherwise mentioned. For the sake of convenience of
10 explanation, although the entity which communicates with the base station apparatus by radio is the user apparatus, it includes a mobile terminal and a fixed terminal more generally.

The mobile communication system 1000 can operate with a plurality of variable bandwidths. As
15 an example, 5MHz, 10MHz and 20MHz are prepared as the variable bandwidths. An operator can operate one or more bandwidths of the variable bandwidths as system band, and in the system, a user can perform communication using one or more resource blocks (25
20 resource blocks are prepared in the 5 MHz system band, for example).

In the following, since the user
apparatuses 100_n ($100_1, 100_2, 100_3, \dots, 100_n$) have the same configurations, functions and states, a user
25 apparatus 100_n is described unless otherwise mentioned.

As radio access schemes, the radio communication system 1000 uses OFDM (orthogonal frequency division multiplexing) in downlink, and
30 uses SC-FDMA (single carrier - frequency division multiple access) in uplink. As mentioned above, OFDM is a scheme in which a frequency band is divided into a plurality of narrow frequency bands (subcarriers) so that transmission is performed by
35 carrying data on each frequency band. SC-FDMA is a transmission scheme that can decrease interference among terminals by dividing a frequency band and by

transmitting signals using different frequency bands among a plurality of terminals.

As mentioned above, in the downlink, a physical downlink shared channel (PDSCH) that is shared and used by each user apparatus 100_n, and a downlink control channel for LTE are used. The downlink control channel for LTE is called physical downlink control channel (PDCCH). The physical downlink control channel is also called downlink (DL) L1/L2 control channel.

In the uplink, a physical uplink shared channel (PUSCH) that is shared and used by each user apparatus 100_n and a control channel for LTE are used. There are two types of uplink control channels, which are a channel that is time-division multiplexed to the physical uplink shared channel and a channel that is frequency-multiplexed to the physical uplink shared channel. The latter is transmitted by a band specifically prepared separately from the physical uplink shared channel.

In the uplink, the uplink control channel for LTE transmits downlink quality information (CQI: Channel Quality Indicator) and acknowledgement information (HARQ ACK information) for the physical downlink shared channel (Downlink Shared Channel (DL-SCH) as transport channel). The downlink quality information (CQI) is also used for resource assignment (scheduling) of the physical downlink shared channel, and for determining transport format in adaptive modulation and coding (AMC).

As shown in Fig.3 as an example, one subframe is 1 ms, for example, and one subframe includes 14 OFDM symbols, for example. The physical downlink control channel is mapped to some OFDM symbols from the top of the one subframe. The maximum number of the OFDM symbols to which the

-12-

physical downlink control channel is mapped is 3. There are three kinds of methods for mapping the physical downlink control channel, which are mapping to an OFDM symbol #1, mapping to OFDM symbols #1 and #2, and mapping to OFDM symbols #1, #2 and #3. In Fig.3, the physical downlink control channel is mapped to two OFDM symbols (#1, #2) of the top of the one subframe. Then, in OFDM symbols to which the physical downlink control channel is not mapped, a data signal (physical downlink shared channel PDSCH as a physical channel, DL-SCH as a transport channel), a synchronization channel (SCH or synchronization signal), a broadcast channel (BCH) or the like is transmitted. In the frequency direction, M resource blocks (RB) are prepared. As an example, the frequency band per one resource block is 180 kHz, and there are 12 subcarriers in one resource block. For the sake of convenience of explanation, a resource occupying a band of one subcarrier and a period of one OFDM symbol is called "resource element". The number M of the resource blocks is 25 when the system bandwidth is 5 MHz, is 50 when the system bandwidth is 10 MHz, and is 100 when the system bandwidth is 20 MHz.

Fig.4 shows a subcarrier mapping example as to OFDM symbols #4 and #5 in the case of the subframe configuration shown in Fig.3. In Fig.4, the total number of subcarriers in one OFDM symbol is L, and the subcarriers are numbered in ascending frequency order as subcarriers #1, #2, ..., and #L. When the system bandwidth is 5 MHz, L=300, when the system bandwidth is 10 MHz, L=600, and when the system bandwidth is 20 MHz, L=1200. As shown in the figure, the downlink reference signal (DL RS) and the physical downlink shared channel (PDSCH) are mapped to subcarriers in the OFDM symbol #4. The DL RS is transmitted at a rate of one per six

-13-

subcarriers. In Fig.4, the DL RS is mapped to subcarriers of subcarrier numbers of $6 \times m + 1$ ($m: 0, 1, 2, \dots$).

Next, an outline of information items that
5 may be included in the physical downlink control channel is described. The physical downlink control channel may include physical downlink control channel format indicator, control information for downlink communication which is downlink scheduling
10 information, and/or control information for uplink communication. The physical downlink control channel format indicator indicates that the number of symbols occupied by the physical downlink control channel in one subframe. The physical downlink
15 control channel format indicator may be called Physical Control Format Indicator Channel (PCFICH). The control information for downlink communication, that is, the downlink scheduling information may include downlink resource assignment information,
20 downlink MIMO information, transmission format information, retransmission control information and user identification information.

The control information for downlink communication may be called Downlink Scheduling
25 Grant or Downlink Assignment Information. The downlink resource assignment information represents which resource block is used for transmission of a downlink data signal. The downlink MIMO information includes information relating to the number of
30 streams, precoding vector and the like when multiple-input multiple-output communication or multi-antenna communication is performed. The transmission format information specifies a combination of data modulation scheme, data size and
35 channel coding scheme. The retransmission control information (HARQ: Hybrid Automatic Repeat reQuest) indicates information when hybrid ARQ is performed.

The retransmission control information may include process number, new data indicator, and the number of times of retransmission sequence.

Control information for uplink
5 communication may include uplink resource assignment information, transmission format information, demodulation reference signal information, transmission power control information, user identification information, acknowledgement
10 information (ACK/NACK) for uplink, overload indicator, and transmission power control command bit.

The uplink resource assignment information indicates which resource block is available for
15 uplink data transmission. The transmission format information specifies a combination of data modulation scheme, data size and channel coding scheme used for uplink communication. The information of the demodulation reference signal
20 indicates what signal is used for the reference signal. The transmission power control information indicates how much transmission power of the physical uplink shared channel is different from transmission power of sounding reference signal.
25 The above-mentioned uplink resource assignment information, transmission format information, information of demodulation reference signal and transmission power control information are collectively called Uplink Scheduling Grant.

30 The acknowledgement information (ACK/NACK) indicates whether data transmitted from the user apparatus in the uplink in the past was properly received by the base station. The acknowledgement information (ACK/NACK) for uplink may be called
35 Physical Hybrid ARQ Indicator Channel (PHICH). The overload indicator is reported to neighbor cells when other cell interference due to user apparatuses

of other cell exceeds a predetermined value. The report is a signal requesting the user apparatus of the other cell to reduce transmission power. The transmission power control command bit indicates
5 that next transmission power of the sounding reference signal periodically transmitted from the user apparatus should be increased or decreased from the current value.

The physical downlink control channel
10 format indicator, acknowledgement information (ACK/NACK) for uplink, and the transmission power control command bit may not be included in the physical downlink control channel, and may be defined as a different physical channel which is
15 parallel to the physical downlink control channel.

The base station apparatus 200 of the embodiment of the present invention is described with reference to Fig.5.

The base station apparatus 200 of the
20 present embodiment includes a transmit and receive antenna 202, an amplifier unit 204, a transmit and receive unit 206, a baseband signal processing unit 208, a call processing unit 210, and a transmission line interface 212.

25 Packet data to be transmitted from the base station apparatus 200 to the user apparatus 100_n in the downlink is input to the baseband signal processing unit 208 from an upper station placed in the upper layer of the base station apparatus 200,
30 that is, from an access gateway apparatus 300, for example, via the transmission line interface 212.

The baseband signal processing unit 208 performs segmentation processing and concatenation processing for packet data, transmission processing
35 in the RLC layer such as transmission processing of RLC (radio link control) retransmission control, and MAC (Medium Access Control) retransmission control

-16-

processing, and the like, so that the processed signal is transferred to the transmit and receive unit 206. Processing in the baseband signal processing unit 208 includes transmission processing of HARQ, scheduling, transmission format selection, channel coding, and inverse fast Fourier transform (IFFT) and the like. As mentioned later, the baseband signal processing unit 208 determines the number of OFDM symbols to which the physical downlink control channel is mapped for each subframe, and performs mapping of the physical downlink control channel and the physical downlink shared channel to subcarriers, and performs transmission power control for the physical downlink control channel and the physical downlink shared channel, and the like.

The transmit and receive unit 206 performs frequency conversion processing for converting the baseband signal output from the baseband signal processing unit 208 into a radio frequency signal. After that, the radio frequency signal is amplified by the amplifier unit 204 so that the signal is transmitted by the transmit and receive antenna 202.

On the other hand, as to data to be transmitted from the user apparatus 100_n to the base station apparatus 200 in the uplink, a radio frequency signal received by the transmit and receive antenna 202 is amplified by the amplification unit 204, and is frequency-converted by the transmit and receive unit 206 so that the signal is converted to a baseband signal, and the baseband signal is input into the baseband signal processing unit 208.

The baseband signal processing unit 208 performs FFT processing, IDFT processing, error correction decoding, reception processing of MAC

-17-

retransmission control, reception processing of RLC layer for the input baseband signal, so that the processed signal is transferred to the access gateway apparatus 300 via the transmission line interface 212.

The call processing unit 210 performs call processing such as setup or release of a communication channel, management of state of the radio base station 200, and resource assignment.

The configuration of the baseband signal processing unit 208 is described with reference to Fig.6A.

The baseband signal processing unit 208 includes a layer 1 processing unit 2081, a MAC (Medium Access Control) processing unit 2082, an RLC processing unit 2083, a subcarrier mapping determination unit 2084, and a DL transmission power control unit 2085.

The layer 1 processing unit 2081, the MAC processing unit 2082, the subcarrier mapping determination unit 2084, and the DL transmission power control unit 2085 in the baseband signal processing unit 208, and the call processing unit 210 are connected with each other.

The layer 1 processing unit 2081 performs channel coding and IFFT processing for data transmitted by downlink, and performs channel decoding, IDFT processing and FFT processing and the like for data transmitted by the uplink. The layer 1 processing unit 2081 maps information of the physical downlink control channel and the physical downlink shared channel to subcarriers based on subcarrier information reported from the subcarrier mapping determination unit 2084. In an OFDM symbol where DL RS is transmitted, the DL RS is mapped to predetermined subcarriers.

Processing in the layer 1 processing unit

-18-

2081 for multiplexing the physical downlink control channel, the physical downlink shared channel and the DL RS, and mapping them to subcarriers is described in more detail with reference to Fig.6B.

5 The layer 1 processing unit 2081 includes a data signal processing unit 208102, a serial parallel conversion unit (S/P) 20814, a multiplexing unit (MUX) 20816, an inverse fast Fourier transform unit (IFFT) 20818, a cyclic prefix (CP) adding unit
10 208110, a digital analog conversion unit (D/A) 208112, and a reference signal generation unit 208114.

 The data signal processing unit 20812 includes an encoder 208102A, a data modulator
15 208102B, and an interleaver 208102C. The reference signal generation unit 208114 includes a multiplier 208114A and a multiplier 208114B.

 The data signal processing unit 208102 performs processing for data signals transmitted in
20 the downlink. The encoder 208102A performs channel coding for enhancing error tolerance for the data signal. Encoding may be performed using various methods such as convolution coding and Turbo coding and the like which are well known in the technical
25 field. In the present embodiment, adaptive modulation and coding (AMC) control is performed for data signals, and channel coding rate is adaptively changed according to an instruction from the MAC processing unit 2082. The data modulator 208102B
30 performs data modulation for data signals using a proper modulation scheme such as QPSK, 16 QAM and 64 QAM. In the present embodiment, AMC control is performed for data signals, and modulation scheme is adaptively changed according to an instruction from
35 the MAC processing unit 2082. The interleaver 208102C permutes arranging order of bits included in the data signal according to a predetermined pattern.

By the way, although Fig.6B does not show process elements for control channels, processing similar to that of data signal processing unit 208102 is performed also for control channels.

5 However, AMC control may not be performed for control channels.

The serial parallel conversion unit (S/P) 208104 converts a serial signal sequence (stream) into parallel signal sequences. The number of
10 parallel signal sequences may be determined according to the number of subcarriers.

The multiplexing unit (MUX) 208106 multiplexes a data sequence which represent an output signal from the serial parallel conversion
15 unit (S/P) 208104 with the reference signal. Multiplexing can be performed in any scheme of time multiplexing, frequency multiplexing, time and frequency multiplexing. In addition to the data sequence and the reference signal, a broadcast
20 channel may be multiplexed. The multiplexing unit (MUX) 208106 receives mapping information of the reference signal, the physical downlink control channel and the physical downlink shared channel of the subframe from the subcarrier mapping
25 determination unit 2084, so that the multiplexing unit (MUX) 208106 multiplexes the data sequence and the reference signal based on the mapping information. That is, the multiplexing unit (MUX) 208106 maps the data sequence and the reference
30 signal to the subcarrier based on the mapping information. The mapping information of the reference signal, the physical downlink control channel and the physical downlink shared channel includes information of after-mentioned DTX
35 subcarrier. That is, the multiplexing unit (MUX) 208106 does not map any signal in the DTX subcarrier.

The inverse fast Fourier transform unit

-20-

(IFFT) 208108 performs inverse fast Fourier transform on an input signal to perform modulation of the OFDM scheme.

5 The CP adding unit 208110 generates a transmission symbol by adding Cyclic Prefix (CP) to a symbol modulated by the OFDM scheme. There are two types of CP lengths which are Long CP and Short CP, and one of them is selected for each cell.

10 The digital analog conversion unit (D/A) 208112 converts a baseband digital signal into an analog signal.

The reference signal generation unit 208114 multiplies a reference signal by a random code sequence which is a first sequence and an
15 orthogonal code sequence which is a second sequence to prepare the reference signal.

In addition, the layer 1 processing unit 2081 sets transmission power (transmission power density per unit band or power density per one
20 subcarrier) of a subcarrier to which the physical downlink control channel and the physical downlink shared channel are mapped based on transmission power information reported from the DL transmission power control unit 2085. Further, the layer 1
25 processing unit 2081 sets transmission power of a subcarrier to which the DL RS is mapped. The transmission power of the subcarrier to which the DL RS is mapped may be set by being signaled from an upper node, or may be set by referring to a value
30 stored in the base station apparatus 200 as a parameter.

The MAC processing unit 2082 performs downlink data MAC retransmission control such as HARQ transmission processing, scheduling, selection
35 of transmission format, assignment of frequency resources, and the like. The scheduling indicates processing for selecting a user apparatus which

performs data signal transmission by using a shared channel in the subframe. For example, as an algorithm for the selection, round robin or proportional fairness may be used. In addition, selection of transmission format indicates determining a modulation scheme, a coding rate and a data size for a data signal to be transmitted to the user apparatus selected by the scheduling. The determination of the modulation scheme, the coding rate and the data size is performed based on CQI that is reported from the user apparatus in the uplink. Further, assignment of the frequency resources indicates processing for determining resource blocks (RB) used for transmitting a data signal to the user apparatus selected in the scheduling. The determination of the resource blocks is performed based on CQI reported from the user apparatus in the uplink, for example.

In addition, the MAC processing unit 2082 performs reception processing of MAC retransmission control for uplink data, scheduling, selection of transmission format, assignment of frequency resources and the like.

The RLC processing unit 2083 performs segmentation/concatenation, transmission processing in RLC layer such as transmission processing of RLC retransmission control and the like for downlink packet data, and performs segmentation/concatenation, reception processing of RLC layer such as reception processing of RLC retransmission control and the like for uplink data. In addition, the RLC processing unit 2083 may perform PDCP layer processing in uplink and downlink.

The subcarrier mapping determination unit 2084 determines subcarriers to which the physical downlink shared channel (PDSCH) is mapped for each subframe. The determined subcarrier number to which

-22-

PDSCH and the like is mapped is reported to the layer 1 processing unit 2081 as subcarrier information.

The subcarrier mapping determination unit
5 2084 stores, in a memory, information representing correspondence relationship among subcarrier numbers of the reference signal, number of after-mentioned DTX subcarriers and the subcarrier numbers (alternatively, the information may be provided from
10 other processing element as necessary). Concrete examples for the correspondence relationship are described later with reference to Fig.9A and the like.

In the following description, OFDM symbol
15 #4 is presented as an example of an OFDM symbol to which the downlink reference signal and the physical downlink shared channel (PDSCH) are mapped, and OFDM symbol #5 is presented as an example of an OFDM symbol to which only the physical downlink shared
20 channel (PDSCH) is mapped. Similar explanation is applied to other OFDM symbols to which the downlink reference signal and the physical downlink shared channel (PDSCH) are mapped, and other OFDM symbols to which only the physical downlink shared channel
25 (PDSCH) is mapped.

Fig.7 shows a subcarrier mapping example of an OFDM symbol (OFDM symbol #4) to which the downlink reference signal and the physical downlink shared channel (PDSCH) are mapped, and an OFDM
30 symbol (OFDM symbol #5) to which only the physical downlink shared channel (PDSCH) is mapped. In this example, transmission power per one subcarrier of the downlink reference signal is the same as transmission power per one subcarrier of the
35 physical downlink shared channel (PDSCH).

In this case, even though a part of subcarriers, in the OFDM symbol #4, where the DL RS

is not mapped are not set to be subcarriers in which mapping of any data is prohibited, transmission power per one subcarrier of the physical downlink shared channel (PDSCH) in the OFDM symbol #4 becomes the same as transmission power per one subcarrier of the physical downlink shared channel (PDSCH) in the OFDM symbol #5. That is, as shown in the figure, the subcarrier mapping determination unit 2084 can map PDSCH to all subcarriers to which the reference signal (DL RS) is not mapped in the OFDM symbol #4.

Fig.8 shows a subcarrier mapping example of an OFDM symbol (OFDM symbol #4) to which the downlink reference signal and the physical downlink shared channel (PDSCH) are mapped, and an OFDM symbol (OFDM symbol #5) to which only the physical downlink shared channel (PDSCH) is mapped. In this example, transmission power of the downlink reference signal per one subcarrier is 3dB greater than (twice as large as) transmission power of the physical downlink shared channel (PDSCH) per one subcarrier.

In this case, a part of subcarriers in the OFDM symbol #4 to which DL RS is not mapped is set to be subcarriers where mapping of any data is prohibited, so that transmission power of the physical downlink shared channel (PDSCH) per one subcarrier in the OFDM symbol #4 is set to be the same as the transmission power of the physical downlink shared channel (PDSCH) per one subcarrier in the OFDM symbol #5. That is, as shown in the figure, the subcarrier mapping determination unit 2084 sets subcarriers to which any of the downlink reference signal (DLRS) and the physical downlink shared channel (PDSCH) is not mapped.

For example, in the figure, subcarriers of $6 \times n + 2$ (n is an integer equal to or greater than 0) become the subcarriers to which any of the

downlink reference signal (DLRS) and the physical downlink shared channel (PDSCH) is not mapped. The subcarrier may be called "prohibited subcarrier" in the sense that mapping of any data is prohibited, or
 5 may be called "puncturing subcarrier" in the sense that puncturing is performed. Or, the subcarrier may be called "DTX subcarrier" in the sense that data transmission is not performed by the subcarrier. That is, no signal is transmitted by the DTX
 10 subcarrier. Then, in the OFDM symbol #4, the physical downlink shared channel is mapped to a subcarrier, which is not the DTX subcarrier, to which the downlink reference signal is not mapped. In the OFDM symbol #5, the physical downlink shared
 15 channel PDSCH is mapped to every subcarrier.

By providing the DTX subcarrier, as a result, the number of subcarriers in the OFDM symbol #4 in Fig.8 where PDSCH is mapped becomes less than the number of subcarriers in the OFDM symbol #4
 20 where downlink PDSCH is mapped in Fig.7. Instead, when total transmission power assigned per one OFDM symbol is the same between Figs.7 and 8, transmission power density of the physical downlink shared channel can be set to be the same in any OFDM
 25 symbol (#4 in Fig.7, #4 and #5 in Fig.8) (however, the reference signal is transmitted with greater power than that of other signals).

More detailed description is given as follows. It is assumed that the maximum
 30 transmission power of the base station is 20 W and that the number of all subcarriers in one OFDM symbol is 300. At this time, assuming that transmission power of each subcarrier is the same, transmission power $P_{\text{subcarrier}}$ per one subcarrier is
 35 represented as follows.

$$P_{\text{subcarrier}} = 20/300 = 0.066666 \text{ (W)}$$

It is assumed that 50 DTX subcarriers and 50

-25-

subcarriers for DL RS are prepared in the OFDM symbol # 4, and that transmission power P_{DLRS} per one subcarrier of the DL RS is $P_{DLRS}=2 \times 0.066666=0.133333$ (W). In this case, the number of subcarriers in the OFDM symbol #4 to which the physical downlink shared channel (PDSCH) can be mapped is $300-50-50 = 200$. This calculation indicates subtracting the number of subcarriers of the DL RS and the number of DTX subcarriers from the number of all subcarriers. In this case, assuming that transmission power of each subcarrier to which PDSCH is mapped in the OFDM symbol #4 is the same, transmission power $P_{subcarrier}^{(1)}$ per one subcarrier in the OFDM symbol #4 becomes as follows.

$$P_{subcarrier}^{(1)} = (20 - 0.133333 \times 50) / 200 = 0.066666.$$

On the other hand, in the OFDM symbol #5 following the OFDM symbol #4, the reference signal is not mapped, and PDSCH is mapped to all subcarriers. Therefore, assuming that transmission power of each subcarrier to which PDSCH is mapped in the OFDM symbol #5 is the same, transmission power $P_{subcarrier}^{(2)}$ per one subcarrier in the OFDM symbol #5 becomes as follows.

$$P_{subcarrier}^{(2)} = P_{subcarrier} = 20 / 300 = 0.066666$$

That is, when PDSCH is mapped to two OFDM symbols, transmission power (density) of PDSCH in the first OFDM symbol #4 can be set to be the same as transmission power (density) of PDSCH in the following OFDM symbol #5. That is, when the number of OFDM symbols to which PDSCH is mapped is two or more, by decreasing the number of subcarriers (by setting DTX subcarriers) to which PDSCH is mapped in the OFDM symbol #4 in which the DL RS is transmitted, transmission power density of PDSCH can be kept constant in any OFDM symbols, so that amplitude estimation accuracy can be improved.

Next, it is described in more detail how

-26-

the reference signal and the DTX subcarriers are mapped. Generally, in an OFDM symbol to which the reference signal is mapped, the reference signal is mapped at a rate of one signal per a predetermined
5 number of subcarriers (every six subcarriers, for example). Assuming that a subcarrier number to which the reference signal is mapped is X , X can be represented as follows.

$$X = 6m + n_{\text{shift}}$$

10 In the equation, m is an integer equal to or greater than 0, n_{shift} is an amount set for each cell, and is a value of 0, 1, ... and 5. More generally, as described in the "background art", n_{shift} is represented as $[v + f_{\text{hop}}(j)] \bmod 6$ (j is the maximum
15 number in integers that does not exceed $i/2$). The physical downlink shared channel (PDSCH) is mapped to subcarriers other than subcarriers to which the reference signal is mapped. As mentioned later, the puncturing subcarrier may be included.

20 The transmission power per one subcarrier (transmission power density per unit band) of the physical downlink shared channel (PDSCH) is set to be a predetermined value regardless of whether the downlink reference signal is mapped in the OFDM
25 symbol to which PDSCH is mapped. The predetermined value is the same as the transmission power density in the case where the base station performs transmission with maximum transmission power (rated power) and power is evenly distributed in all
30 subcarriers in the system band. Therefore, in the OFDM symbol in which the downlink reference signal is transmitted, subcarriers to which PDSCH can be mapped are reduced according to transmission power density of the downlink reference signal (Offset
35 value with respect to other signal). In other words, prohibited subcarrier (DRX subcarrier or puncturing subcarrier) to which mapping of PDSCH is prohibited

is set.

In the above-mentioned example,
transmission power per one subcarrier (transmission
power density per unit band) of the physical
5 downlink shared channel (PDSCH) is set to be
transmission power density of a case where the base
station performs transmission with maximum
transmission power (rated power) and power is evenly
distributed in all subcarriers in the system band.
10 But, transmission power per one subcarrier
(transmission power density per unit band) of the
physical downlink shared channel (PDSCH) is not
limited to be the above value. Other fixed value
may be used.

15 Fig.9A shows correspondence relationship
between the number of puncturing subcarriers and the
subcarrier number. In the figure, X indicates a
subcarrier number of a subcarrier to which a
reference signal is mapped, wherein the reference
20 signal corresponds to a smaller subcarrier number in
two reference signals in one resource block ($X = 6m + n_{\text{shift}}$). Twelve subcarriers are included in one
resource block, and subcarrier numbers (0, 1, 2, ...,
11) are set in ascending order of frequency from the
25 low frequency side.

When a plurality of puncturing subcarriers
are set per one resource block, mapping is carried
out such that puncturing subcarriers are evenly
distributed as much as possible. For example, when
30 $X = 0$ and the number of puncturing subcarriers is 4,
the subcarrier number is set every three subcarriers,
like 1, 4, 7, 10. Or, when more than two puncturing
subcarriers are set in an OFDM symbol in a resource
block, at least three puncturing subcarriers are set
35 at even subcarrier intervals.

The mapping example shown in the figure is
merely an example. For example, when the number of

puncturing subcarriers per one resource block is small (when the number is 1, 2 or 3, for example), the puncturing subcarrier may be set such that the puncturing subcarrier is not adjacent to the reference signal. This is because channel estimation accuracy for signals near the reference signal is expected to be relatively good.

For example, when the number of puncturing subcarriers is 2, the puncturing subcarriers may be placed at positions of $(X+3) \bmod 12$ and $(X+10) \bmod 12$. More generally, it is preferable that signals other than the reference signal are mapped to subcarriers existing between a subcarrier to which the reference signal is mapped and a puncturing subcarrier as much as possible.

Or, the subcarrier to which the reference signal is mapped and the puncturing subcarrier can be placed such that position relationship of them or distance between them (subcarrier interval) is constant. For example, as shown in Fig.9A, by defining the subcarrier number as $(X+a) \bmod 12$ (a is an integer from 0 to 11), the distance (subcarrier interval) becomes a value based on a . Thus, by fixing the value of a , position relationship between the subcarrier to which the reference signal is mapped and the puncturing subcarrier or the distance (subcarrier interval) of them becomes constant regardless of the value of X . In this case, since channel estimation accuracy for demodulating PDSCH becomes constant, more stable transmission characteristics can be obtained.

Alternatively, assuming that the base station apparatus 200 includes a plurality of transmission antennas, the subcarrier number of the puncturing subcarrier may include a subcarrier number of a subcarrier to which a reference signal is mapped, which reference signal is transmitted

from a transmission antenna which is different from a transmission antenna relating to the puncturing subcarrier.

For example, in the case of $P = 0, 1$ described in the background art, subcarrier numbers of puncturing subcarriers when $P = 0$ may include a subcarrier number of a subcarrier to which the reference signal is mapped when $p = 1$. More particularly, assuming that a subcarrier number $X1$ of the reference signal when $p = 0$ is $X1 = 6m + n_{\text{shift}}$, a subcarrier number $X2$ of the reference signal when $p=1$ is $X2 = 6m+3+ n_{\text{shift}}$. Thus, subcarrier numbers of the puncturing subcarriers when $p = 0$ include $6m+3+ n_{\text{shift}}$. Fig.9B shows correspondence relationship between the number of puncturing subcarriers and the subcarrier number in that case.

In the above-mentioned example, numbers of puncturing subcarriers when $p = 0$ include a subcarrier number of a subcarrier to which the reference signal is mapped when $p = 1$. Instead of that, subcarrier numbers of puncturing subcarriers when $p = 1$ may include a subcarrier number of a subcarrier to which the reference signal is mapped when $p = 0$.

When the number of transmission antennas is actually two, as shown in Fig.9C, in order to improve reception SIR of the reference signal, no signal is transmitted from a first transmission antenna in a subcarrier of a reference signal which is transmitted from a second antenna regardless of transmission power of the reference signal. In addition, no signal is transmitted from the second transmission antenna in a subcarrier of a reference signal which is transmitted from the first antenna. Thus, as shown in Fig.9B, by configuring the system such that subcarrier numbers of subcarriers to which

the reference signal transmitted by a different transmission antenna is mapped include a puncturing subcarrier number, it can be avoided that the number of physical resources, more particularly, the number of resource elements is decreased due to puncturing.

Also, when the number of transmission antenna is one, as shown in Fig.9B, puncturing subcarrier numbers can be set by assuming that there are reference signals transmitted from the second transmission antenna. Accordingly, similar processing can be performed between the case when the number of antenna is one and the case when the number is two. Thus, it becomes possible to reduce complexity of the base station apparatus performing transmission processing and the mobile station performing reception processing.

The relationship between the first antenna and the second antenna can be applied to relationship between a third antenna and a fourth antenna.

Fig.10 shows how many puncturing subcarriers are provided in what resource block RB for various offset values when the system bandwidth is 5MHz. The offset value indicates how much decibel by which the reference signal is stronger than other signal for transmission. For example, when the reference signal is transmitted 3 dB more strongly than other signal, two subcarriers of twelve subcarriers are set as puncturing subcarriers in every resource block. When the reference signal is transmitted 1 dB more strongly than other signal, one puncturing subcarrier is set for each even number resource block, and no puncturing subcarrier is set in other resource blocks (odd number resource blocks).

Figs.11 and 12 show how many puncturing subcarriers are provided in what resource block RB

for various offset values when the system bandwidth is 10MHz and 20MHz respectively. Configurations of the tables are similar to that in Fig.10.

In Figs.10 - 12, since puncturing
5 subcarriers are set such that the offset value becomes 0, 1, 2, ..., 6dB, the number of puncturing subcarriers is not necessarily the same among resource blocks. However, such a setting method is not essential for the present invention. The system
10 may be configured such that the number of puncturing subcarriers is the same among all resource blocks, and instead, the offset value can be set as a non-integer value. For example, Fig.12B shows transmission power value (offset value) of the
15 reference signal when the number of puncturing subcarriers set in each resource block is 1, 2, 3, 4, 5 or 6.

The example is described in more detail. A case is considered in which the system bandwidth
20 is 5MHz (the number of subcarriers is 300, the number of subcarriers of the reference signal is 50, and the number of resource blocks is 25), and in which the number of puncturing subcarrier set in each resource block is 1. In this case, since the
25 number of puncturing subcarrier of each resource block (the number of subcarriers per one resource block is 12) is 1, the number of mapping subcarriers of PDSCH becomes 225. In this case, assuming that the absolute value of transmission power of one
30 subcarrier of PDSCH is 1, total transmission power of an OFDM symbol in which the reference signal is transmitted is $50 \times 1 \times 10^{1.76/10} + 225 \times 1 = 299.98$, and total transmission power in an OFDM symbol in which the reference signal is not transmitted is $300 \times 1 = 300$.
35 Thus, total transmission power in an OFDM symbol in which the reference signal is transmitted can be set to be almost the same as total transmission power in

-32-

an OFDM symbol in which the reference signal is not transmitted. Although a case where the number of puncturing subcarrier is 1 in each RB is described in the above-mentioned example, total transmission power in an OFDM symbol in which the reference signal is transmitted can be set to be almost the same as total transmission power in an OFDM symbol in which the reference signal is not transmitted similarly when the number of puncturing subcarriers is 2, 3, 4, 5 or 6 in each RB. In addition, total transmission power in an OFDM symbol in which the reference signal is transmitted can be set to be almost the same as total transmission power in an OFDM symbol in which the reference signal is not transmitted similarly when the system bandwidth is other than 5 MHz, for example, when the system bandwidth is 10 MHz or 20 MHz.

In this case, since the number of subcarriers to be punctured becomes constant in each resource block, it becomes possible to reduce complexity of the base station apparatus for performing transmission processing and the mobile station for performing reception processing.

The DL transmission power control unit 2085 determines transmission power of the physical downlink control channel and the physical downlink shared channel, and reports the transmission power to the layer 1 processing unit 2081. Transmission power per one subcarrier (transmission power density per unit band) of the physical downlink shared channel is set to be a predetermined value regardless of whether the downlink reference signal is mapped to an OFDM symbol to which PDSCH is mapped. The predetermined value is equal to transmission power density obtained when the base station performs transmission using the maximum transmission power (rated power) and power is evenly distributed

-33-

to all subcarriers in the system band. Or, the transmission power per one subcarrier (transmission power density per unit band) of the physical downlink shared channel may be a value other than
5 the transmission power density obtained when the base station performs transmission using the maximum transmission power (rated power) and power is evenly distributed to all subcarriers in the system band, as long as the transmission power per one subcarrier
10 (transmission power density per unit band) of the physical downlink shared channel is constant regardless of whether the downlink reference signal is mapped.

The user apparatus 100_n of an embodiment
15 of the present invention is described with reference to Fig.13A.

As shown in Fig.13A, the user apparatus 100_n includes a transmit and receive antenna 102, an amplifier unit 104, a transmit and receive unit
20 106, a baseband signal processing unit 108, a call processing unit 112, and an application unit 112.

As to downlink data, a radio frequency signal received by the transmit and receive antenna 102 is amplified by the amplifier unit 104, and is
25 frequency-converted by the transmit and receive unit 106 so that the signal is converted into a baseband signal. The baseband signal processing unit 108 performs, on the baseband signal, FFT processing, error correction decoding, reception processing of
30 retransmission control, and the like. After that, the processed signal is transferred to the application unit 112.

On the other hand, uplink packet data is input to the baseband signal processing unit 108
35 from the application unit 112. The baseband signal processing unit 108 performs transmission processing of retransmission control (HARQ), transmission

-34-

format selection, channel coding, DFT processing, IFFT processing and the like, then, the processed signal is transferred to the transmit and receive unit 106.

5 The transmit and receive unit 106 performs frequency conversion processing for converting the baseband signal output from the baseband signal processing unit 108 into radio frequency band. After that, the processed signal is amplified in the
10 amplifier unit 104 and transmitted from the transmit and receive antenna 102.

 In addition, the baseband signal processing unit 108 performs demodulation and decoding for the physical downlink control channel,
15 and performs processing for obtaining information of the physical downlink control channel and the physical downlink shared channel. The user apparatus 100_n obtains beforehand information (including information specifying where prohibited
20 subcarriers are placed) indicating subcarriers where the information of the physical downlink shared channel is mapped. The processing for obtaining information of the physical downlink shared channel is performed based on the information indicating
25 subcarriers to which the physical downlink shared channel is mapped.

 More detailed explanation is given with reference to Fig.13B for explaining processing, in the baseband signal processing unit 108, for
30 performing demodulation/decoding of the physical downlink control channel and obtaining information of the physical downlink control channel and the physical downlink shared channel and the like.

 The baseband signal processing unit 108
35 includes analog digital converter (A/D) 10802, a CP removing unit 10804, a fast Fourier transform unit (FFT) 10806, a demultiplexing unit (DeMUX) 10808, a

-35-

multiplying unit 10810, a multiplying unit 10812, a channel estimation unit 10814, a demodulation unit 10816, and a subcarrier mapping information management unit 10818.

5 The analog digital converter (A/D) 10802 converts an analog signal of the received baseband signal into a digital signal.

 The CP removing unit 10804 removes CP from a received signal to obtain an effective symbol part.

10 The fast Fourier transform unit (FFT) 10806 performs fast Fourier transform on an input signal to perform demodulation of OFDM scheme.

 The demultiplexing unit (DeMUX) 10808 demultiplexes the reference signal, the data signal
15 (user data or control data) from the received signal. The demultiplexing unit (DeMUX) 10808 receives, from the subcarrier mapping information management unit 118, mapping information of the reference signal, the physical downlink control channel and the
20 physical downlink shared channel. That is, the demultiplexing unit (DeMUX) 10808 receives information indicating which subcarrier the reference signal is mapped to in the subframe, and which subcarrier the physical downlink control
25 channel (control data) and the physical downlink shared channel (user data) are mapped to. Then, the demultiplexing unit (DeMUX) 10808 demultiplexes the reference signal and the data signal (user data or control data) from the received signal based on the
30 information.

 The multiplying units 10810, 10812 multiply the reference signal by a random code sequence which is a first sequence and an orthogonal code sequence which is a second sequence.

35 The channel estimation unit 10814 performs channel estimation based on the reference signal, and determines how channel compensation should be

-36-

applied to the received data signal.

The demodulation unit 10816 compensates for the data signal based on the channel estimation result, and restores the data signal transmitted from the base station apparatus 200, that is, restores user data or control data.

The subcarrier mapping information management unit 10818 stores mapping information of the reference signal, the physical downlink control channel and the physical downlink shared channel, that is, the subcarrier mapping information management unit 10818 stores information indicating which subcarrier the reference signal is mapped to in the subframe, and which subcarrier the physical downlink control channel (control data) and the physical downlink shared channel (user data) are mapped to. The subcarrier mapping information management unit 10818 reports the mapping information to the demultiplexing unit (DeMUX) 10808. The mapping information may be system specific information, or may be broadcast information, or information reported from the base station apparatus 200 by individual signaling which is RRC message, for example.

The information on DTX subcarrier is included in the mapping information of the reference signal, the physical downlink control channel and the physical downlink shared channel stored in the subcarrier mapping information management unit 10818. That is, the demultiplexing unit (DeMUX) 10808 performs processing for demultiplexing the reference signal and the data signal (user data or control data) while regarding that no signal is mapped in the DTX subcarrier.

The information indicating which subcarrier the physical downlink shared channel is mapped to (including information for specifying the

-37-

position of the prohibited subcarrier) corresponds to the subcarrier number of the puncturing subcarrier described with reference to Figs.9A, 9B, 9C, 10, 11, 12A and 12B in the explanation of the base station apparatus 200, for example. In other words, the user apparatus 100_n performs demodulation and decoding for the physical downlink shared channel in consideration of the puncturing subcarrier described with reference to Figs.9A, 9B, 9C, 10, 11, 12A and 12B in the explanation of the base station apparatus 200. In other words, the user apparatus 100_n performs demodulation and decoding for the physical downlink shared channel by considering that the physical downlink shared channel is not transmitted in the puncturing subcarrier described with reference to Figs.9A, 9B, 9C, 10, 11, 12A and 12B in the explanation of the base station apparatus 200. The demodulation and decoding include FFT processing of the baseband signal processing unit 108, error correction decoding, reception processing of retransmission control, and the like.

That is, as mentioned above, in the case when the puncturing subcarrier number is set by assuming that there is the reference signal transmitted from the second transmission antenna, as shown in Fig.9B, even when the base station apparatus has only one transmission antenna, the baseband signal processing unit 108 performs demodulation and decoding of the physical downlink shared channel by assuming that there is the reference signal transmitted from the second transmission antenna as shown in Fig.9B even when the number of transmission antenna is actually 1, that is, by regarding that the subcarrier to which the reference signal transmitted from the second transmission antenna is mapped is the puncturing

subcarrier.

The call processing unit 110 performs management of communication with the base station 200, and the application unit 112 performs
5 processing on an upper layer higher than the physical layer and the MAC layer.

In the above-mentioned example, the puncturing subcarrier is set in the OFDM symbol in which the physical downlink shared channel (PDSCH)
10 is transmitted, and the subcarrier of the puncturing subcarrier is determined based on the subcarrier position of the downlink reference signal. Instead of that, the puncture subcarrier may be set in the OFDM symbol in which the physical downlink control
15 channel (PDCCH) is transmitted, and the subcarrier of the puncturing subcarrier may be determined based on the subcarrier position of the downlink reference signal. Or, the puncturing subcarrier may be set in the OFDM symbol in which PCFICH or PHICH is
20 transmitted, and the subcarrier of the puncturing subcarrier may be determined based on the subcarrier position of the downlink reference signal.

Since the subcarrier number of the puncturing subcarrier is associated with the
25 subcarrier number to which the downlink reference signal is mapped on a one-to-one basis as shown in Figs.9A and 9B, the base station apparatus, the user apparatus and the method of the present embodiment can be applied for any sequence of $f_{hop}(j)$ described
30 in the background art. That is, the base station apparatus, the user apparatus and the method of the above embodiments can be applied even when hopping is applied to the downlink reference signal and even when fixed shifting is applied.

35 In the above embodiments, although examples are described in a system to which Evolved UTRA and UTRAN (another name: Long Term Evolution or

-39-

Super 3G) is applied, the base station apparatus, the user apparatus and the method of the present invention can be applied to every system using the OFDM scheme in the downlink.

5 According to the embodiment of the present invention, by preparing correspondence relationship among number, location, offset value and the like of the reference signal and the prohibited subcarrier, changes in hopping and offset value of the reference
10 signal can be flexibly supported while transmission power density of non-reference signal (typically, data signal) is kept constant temporally.

 As described above, while the present invention is described with reference to specific
15 embodiments, the respective embodiments are merely exemplary, so that a skilled person will understand variations, modifications, alternatives, and replacements. While specific numerical value examples are used to facilitate understanding of the
20 present invention, such numerical values are merely examples, so that any appropriate value may be used unless specified otherwise. Classification into each embodiment is not essential in the present invention, and equal to or more than two embodiments
25 may be used as necessary. For convenience of explanation, while the apparatus according to the embodiments of the present invention is explained using functional block diagrams, such an apparatus as described above may be implemented in hardware,
30 software, or a combination thereof.

35

-40-

WHAT IS CLAIMED IS:

1. A base station apparatus that performs communication with a user
apparatus using orthogonal frequency division multiplexing (OFDM)
5 in a downlink, comprising:
a generation unit configured to perform inverse Fourier transform on
a signal to which a first signal and a second signal are mapped
so as to generate a transmission signal; and
a transmission unit configured to transmit the transmission signal to
10 the user apparatus,
wherein, when the number of transmission antennas of the base
station apparatus is two, mapping of the second signal to a
subcarrier to which the first signal is to be mapped in a first
transmission antenna is prohibited in a second transmission
15 antenna, and
wherein, even when the number of transmission antennas of the base
station apparatus is one, a particular subcarrier in which
mapping of the second signal is prohibited is determined by
assuming that the number of transmission antennas of the base
20 station apparatus is two such that the particular subcarrier
becomes the same as the subcarrier in which mapping of the
second signal is prohibited in the second transmission antenna
which is used when the number of transmission antennas of
the base station apparatus is two, and

-41-

wherein the first signal is a downlink reference signal, and the second signal is a downlink control channel.

2. The base station apparatus as claimed in claim 1, wherein, when the number of the transmission antenna of the base station apparatus is one, the base station apparatus punctures a subcarrier of the downlink reference signal to be transmitted from the second transmission antenna by assuming that the downlink reference signal transmitted from the second transmission antenna exists.
 3. A method for use in a base station apparatus that performs communication with a user apparatus using orthogonal frequency division multiplexing (OFDM) in a downlink, comprising the steps of:
 - performing inverse Fourier transform on a signal to which a first signal and a second signal are mapped so as to generate a transmission signal; and
 - transmitting the transmission signal to the user apparatus,wherein, when the number of transmission antennas of the base station apparatus is two, mapping of the second signal to a subcarrier to which the first signal is to be mapped in a first transmission antenna is prohibited in a second transmission antenna, and
- wherein, even when the number of transmission antennas of the base station apparatus is one, a particular subcarrier in which

-42-

mapping of the second signal is prohibited is determined by assuming that the number of transmission antennas of the base station apparatus is two such that the particular subcarrier becomes the same as the subcarrier in which mapping of the second signal is prohibited in the second transmission antenna which is used when the number of transmission antennas of the base station apparatus is two, and wherein the first signal is a downlink reference signal, and the second signal is a downlink control channel.

10

4. A mobile communication system comprising a user apparatus and a base station apparatus that performs communication with the user apparatus using orthogonal frequency division multiplexing (OFDM) in a downlink, the base station apparatus comprising:

15

a generation unit configured to perform inverse Fourier transform on a signal to which a first signal and a second signal are mapped so as to generate a transmission signal; and a transmission unit configured to transmit the transmission signal to the user apparatus,

20


wherein, when the number of transmission antennas of the base station apparatus is two, mapping of the second signal to a subcarrier to which the first signal is to be mapped in a first transmission antenna is prohibited in a second transmission antenna, and

-43-

wherein, even when the number of transmission antennas of the base station apparatus is one, a particular subcarrier in which mapping of the second signal is prohibited is determined by assuming that the number of transmission antennas of the base station apparatus is two such that the particular subcarrier becomes the same as the subcarrier in which mapping of the second signal is prohibited in the second transmission antenna which is used when the number of transmission antennas of the base station apparatus is two, and

wherein the first signal is a downlink reference signal, and the second signal is a downlink control channel.

FIG.1



[WHEN $f_{hop}(j)=0, p=0$]

[WHEN $f_{hop}(j)=2, p=0$]




FIG.3




FIG.4




FIG.5




FIG.6A




FIG.6B




FIG.7




FIG.8





FIG.9A

NUMBER OF PUNCTURING SUBCARRIERS PER 1 RESOURCE BLOCK	PUNCTURING SUBCARRIER NUMBER
1	$(X+1) \bmod 12$
2	$(X+1) \bmod 12, (X+7) \bmod 12$
3	$(X+1) \bmod 12, (X+5) \bmod 12, (X+9) \bmod 12$
4	$(X+1) \bmod 12, (X+4) \bmod 12, (X+7) \bmod 12, (X+10) \bmod 12$
5	$(X+1) \bmod 12, (X+3) \bmod 12, (X+5) \bmod 12, (X+7) \bmod 12, (X+9) \bmod 12$
6	$(X+1) \bmod 12, (X+3) \bmod 12, (X+5) \bmod 12, (X+7) \bmod 12, (X+9) \bmod 12, (X+11) \bmod 12$


FIG.9B

NUMBER OF PUNCTURING SUBCARRIERS PER 1 RESOURCE BLOCK	PUNCTURING SUBCARRIER NUMBER
1	$(X+3) \bmod 12$
2	$(X+3) \bmod 12, (X+9) \bmod 12$
3	$(X+3) \bmod 12, (X+9) \bmod 12, (X+1) \bmod 12$
4	$(X+3) \bmod 12, (X+9) \bmod 12, (X+1) \bmod 12, (X+7) \bmod 12$
5	$(X+3) \bmod 12, (X+9) \bmod 12, (X+1) \bmod 12, (X+7) \bmod 12, (X+5)$
6	$(X+3) \bmod 12, (X+9) \bmod 12, (X+1) \bmod 12, (X+7) \bmod 12, (X+5), (X+11)$

FIG.9C



WHEN ANTENNA PORT NUMBER
IS 0 AND $f_{\text{hop}}(j)$ IS ALWAYS 0



WHEN ANTENNA PORT NUMBER
IS 1 AND $f_{\text{hop}}(j)$ IS ALWAYS 0

- 1 SUBCARRIER OF REFERENCE SIGNAL TRANSMITTED FROM FIRST ANTENNA
- X SUBCARRIER BY WHICH NO SIGNAL IS TRANSMITTED FROM FIRST ANTENNA SINCE THE SUBCARRIER OVERLAPS WITH SUBCARRIER OF REFERENCE SIGNAL TRANSMITTED FROM SECOND ANTENNA
- 2 SUBCARRIER OF REFERENCE SIGNAL TRANSMITTED FROM SECOND ANTENNA
- X SUBCARRIER BY WHICH NO SIGNAL IS TRANSMITTED FROM SECOND ANTENNA SINCE THE SUBCARRIER OVERLAPS WITH SUBCARRIER OF REFERENCE SIGNAL TRANSMITTED FROM FIRST ANTENNA

FIG. 10

[illegible]

FIG. 11

[illegible]

FIG. 12A

[illegible]

FIG.12B

NUMBER OF PUNCTURING SUBCARRIERS IN EACH RB	TRANSMISSION POWER VALUE (OFFSET VALUE) OF DL RS (DOWNLINK REFERENCE SIGNAL)
0	0.00 dB
1	1.76 dB
2	3.01 dB
3	3.97 dB
4	4.77 dB
5	5.44 dB
6	6.02 dB

FIG. 13A




FIG.13B

