



US 20060152955A1

(19) **United States**(12) **Patent Application Publication**  
**Shimada et al.**(10) **Pub. No.: US 2006/0152955 A1**(43) **Pub. Date: Jul. 13, 2006**(54) **PULSE POWER SUPPLY FOR  
REGENERATING MAGNETIC ENERGY****Publication Classification**(51) **Int. Cl.**  
**H02M 7/5387** (2006.01)(52) **U.S. Cl.** ..... **363/132**(76) Inventors: **Ryuichi Shimada**, Tokyo (JP); **Taku Takaku**, Tokyo (JP)(57) **ABSTRACT**

Correspondence Address:

**Richard P. Berg****Ladas & Parry****5670 Wilshire Boulevard****Suite 2100****Los Angeles, CA 90036-5679 (US)**

In order to provide a pulse power supply device using regenerating magnetic energy stored in a discharge circuit to a capacitor so as to use it as next discharge energy and supplying a bipolar pulse current with high repetition, a bridge circuit is composed of four inverse-conductive semiconductor switches, a charged energy source capacitor is connected to a DC terminal of the bridge circuit, and an inductive load is connected to its AC terminal. A control signal is supplied to gates of the inverse-conductive semiconductor switches, and a control is made so that when a discharge current rises, is maintained or is reduced, all the gates are turned off, and the magnetic energy of the electric current can be automatically regenerated to the energy source capacitor by a diode function of the switches. Further, a large-current power supply is inserted into a discharge circuit so as to replenish energy loss due to discharge, thereby enabling high-repetition discharge.

(21) Appl. No.: **10/524,893**(22) PCT Filed: **Aug. 18, 2003**(86) PCT No.: **PCT/JP03/10414**(30) **Foreign Application Priority Data**

Aug. 19, 2002 (JP) ..... 2002-278148




FIG.1




FIG.2




FIG.3




FIG.4





FIG.5



## PULSE POWER SUPPLY FOR REGENERATING MAGNETIC ENERGY

### TECHNICAL FIELD

[0001] The present invention relates to a pulse power supply device for supplying pulse current to an inductive load.

### BACKGROUND ART

[0002] When a large electric current is supplied to an inductive load, pulse power supply devices, in which normally an energy source capacitor charged with high voltage is connected to the load by using switches such as an ignitron, a discharge gap switch and a thyristor so that a capacitor discharge is started, are generally used.

[0003] In these discharge switches, diodes called clamp circuits are generally connected to loads in parallel or to capacitors in parallel. After the electric current becomes maximum, a capacitor voltage is inverted and simultaneously the diodes are turned on, and the load current reflows to the diodes. As a result, reverse charging of the capacitor is prevented, and the clamped electric current continuously flows while being attenuated with time constant  $L/R$  due to electric resistance of the load.

[0004] On the other hand, in the applications of the pulse current, frequently rise time is more important than an attenuated waveform. Pulse high-magnetic field bending magnets of compact medical synchrotron accelerators and the like do not use the maximum magnetic field but require an operation such that the magnetic field is raised with time. For this reason, it is demanded that the electric current is attenuated quickly and a pulse rate is heightened. Further, gas excitation laser power supply requires high speed rise of a voltage and high repetition, and thus high repetition control is required as discharge power supply.

[0005] In order that the rise of the discharge current is stopped by controlling switches when the discharge current reaches a necessary current value, switches are switched from those only for ON control such as an ignitron, a discharge gap switch and a thyristor to semiconductor switches having self arc-suppressing ability using a gate signal such as a GTO thyristor and an IGBT (Insulated-gate Bipolar Transistor).

[0006] An inductive current on the load side, however, is clamped at a voltage of 0, and is only attenuated by the diodes at long time constant  $L/R$  in a freewheeling state. The energy is wasted and time to wait for the attenuation is required, thereby raising a technical problem of the pulse power supply devices requiring increased capacity and high repetition.

[0007] When the electric current in the freewheeling state is cut off and its magnetic energy can be regenerated to the capacitor, the wasted energy is reduced and further the energy returned to the capacitor is regenerated as next-time energy, so the pulse current generating power supply which has high energy efficiency and high repetition can be realized.

### DISCLOSURE OF THE INVENTION

[0008] FIG. 2 is a diagram explaining a basic operation of the present invention. A power supply side has a constitution

of a current switch of a snubber energy regenerating system. A capacitor which temporarily stores snubber energy corresponds to an energy source capacitor of the present invention. The current switch of the snubber energy regenerating system is disclosed in Japanese Patent Application Laid-Open No. 2000-358359 "FORWARD AND BACKWARD DIRECTION CURRENT SWITCH FOR REGENERATING SNUBBER ENERGY" (Patent Document 1). The present invention utilizes the constitution of the above-mentioned current switch for regenerating the snubber energy, but the Patent Document 1 describes the current switch for temporarily storing magnetic energy of a breaking current circuit into a snubber capacitor and discharging it into a load at the time of next energizing. On the contrary, the present invention is different from the invention in the Patent Document 1 in that the energy source capacitor is charged with full energy, and the load is driven only by the energy, and further, when the pulse is ended, the magnetic energy remaining in the load is regenerated to the energy source capacitor.

[0009] In an example of FIG. 2, a load is an inductive load and is represented by a resistor  $R$  and an inductance  $L$ . In the case of gas laser, however, the load is a discharge electrode, and in the case of an accelerator bending magnet, the load is a dipole coil which is transformer-coupled. In both cases, the load is regarded as a load where  $L$  and  $R$  are connected in series. When the time of a discharge pulse is sufficiently shorter than the time constant  $L/R$ , the energy is mostly supplied by magnetic energy of the inductance.

[0010] An operating sequence of FIG. 2 is explained with reference to FIG. 3. Firstly a capacitor 1 is charged so as to have polarity of FIG. 2 (a charging circuit is not shown), and when switches  $S1$  and  $S2$  are turned on, electric charges of the capacitor start to flow to the load. When an electric current becomes maximum and the voltage of the capacitor is negative (forward-direction voltage of a diode), the load current ref lows via the diode and is brought into a freewheeling state, and the load current continues to flow in two parallel lines in a direction where "a path where a main current flows" is written. The characteristics of the switch constitution and the operation are that the electric current in the freewheeling state continuously flows in two parallel lines. As a result, a current carrying capacity of the switches is only half, and thus this example is economical.

[0011] When the switches  $S1$  and  $S2$  are turned off, the electric current in the freewheeling state is cut off, and the capacitor 1 is recharged into the same polarity via two diodes. As a result, the electric current is quickly reduced and when it becomes zero, the diodes prevent reverse current, thereby stopping the electric current.

[0012] After the switches  $S1$  and  $S2$  are turned on, when any one of the switches  $S1$  and  $S2$  is turned off while the capacitor voltage remains, the load current is brought into the freewheeling state, and the capacitor voltage is maintained. When the switch is turned on again, the electric current restarts to rise. The high-speed on/off operation of the switches possibly enables PWM control of the capacitor discharge current. This function cannot be realized by the simple current switches of the snubber regenerating system.

[0013] When the switches and the diodes in the constitution of FIG. 2 are used, discharge can be started, maintained and reduced by turning on/off the switches at arbitrary

timing. Further, the magnetic energy with the same polarity is regenerated to the capacitor.

[0014] **FIG. 4** is a principle diagram for developing the present invention in both directions of the electric current.

[0015] A difference of this drawing from **FIG. 2** is that four units where diodes and switches are connected in parallel are installed in inverse-series and in inverse-parallel as shown in **FIG. 4**, so that a bidirectional electric current is allowed to flow in the load. The same point is that when the switches are turned off, the magnetic energy is regenerated to the capacitor **1** (as in **FIG. 2**, the charging circuit is not shown).

[0016] In order to change the direction of the electric current to the load, selection from an operating switch group is brought into a "cross state", namely, the switches **S1** and **S2** are turned on in a current forward direction and the switches **S3** and **S4** are turned on in a current backward direction. "A pair of the switches are selected in the cross state" means that when the four switches are arranged into a quadrangular shape, two of them positioned on a diagonal line are selected. A rational design is made preferably in a manner that the switches and capacities of the diodes according to a level of the maximum electric current in the forward and backward directions are selected.

[0017] **FIG. 5** is a diagram illustrating a simulation circuit showing that the energy source capacitor **1** can be replenished with energy by a low-voltage large-current power supply **5** inserted into the discharge circuit, and a waveform as its result. According to the waveform of **FIG. 5**, the capacitor voltage and the load current rise according to the number of discharges, but this is because when a voltage which is not less than a voltage of a DC resistance is injected from an external power supply, the discharge current rises. When the voltage of the external power supply is increased or decreased in such a manner, the value of the pulse current can be controlled.

[0018] Prior to the operation, when a voltage is applied to a circuit by the low-voltage large-current power supply **5**, an electric current which is determined by a resistor flows. Since the magnetic energy is regenerated to the capacitor **1** and the capacitor **1** is charged by cutting off the electric current using a current switch, the pulse current for high-speed boot can be obtained only by the low-voltage power supply without preparing a high-voltage power supply for charging the capacitor.

#### BRIEF DESCRIPTION OF THE DRAWINGS

[0019] **FIG. 1** is a diagram explaining an embodiment of the present invention;

[0020] **FIG. 2** is a diagram explaining a basic principle of the present invention;

[0021] **FIG. 3** is a diagram explaining a sequence of an electric current, a voltage and switches in **FIG. 2**;

[0022] **FIG. 4** is a diagram explaining a basic principle of bidirectional current of the present invention; and

[0023] **FIG. 5** is a model diagram of a calculator simulation for analyzing a basic principle of a method of supporting a capacitor voltage, and a simulation waveform of a load current and the capacitor voltage of the present invention.

#### BEST MODE FOR CARRYING OUT THE INVENTION

[0024] **FIG. 1** is a circuit diagram illustrating an embodiment of the present invention. A difference of **FIG. 1** from **FIG. 4** is that when an accelerator bending magnet **6** as a concrete example of a load is excited by a pulse current via a current transformer **3**, four power MOSFETs are connected in inverse-series and in inverse-parallel. As a result, the four power MOSFETs compose a bridge circuit.

[0025] It is assumed that power MOSFETs used here are made of silicon carbide (SiC), and are quickly turned on/off with high withstand voltage, have less conducting loss, and can effectively utilize body diodes (also called parasitic diodes) as a substitution of parallel diodes.

[0026] Even when present power MOSFETs made of silicon which cannot practically use body diodes are used, they can be used by forcibly bringing them into an ON state by means of gate control when they are in an inverse conducting state. An inverse conductive type GTO thyristor or a unit in which diodes are connected to semiconductor switches such as IGBT and the like in parallel can produce the effect of the present invention.

[0027] In the present invention, a switch, which prevents an electric current from flowing in a forward direction when the switches are off but conducts in a backward direction, is called an inverse-conductive type semiconductor switch. Its examples are the power MOSFET, the inverse-conductive type GTO thyristor, and the unit in which the diodes are connected to the semiconductor switches such as IGBT and the like in parallel.

[0028] A gate signal is supplied to the power MOSFET switches **G1** to **G4** from a control device **7** shown in **FIG. 1**. A pair of the switches **G1** and **G2** are selected "in a cross state" so that a direction of the electric current is a forward direction, and when a pair of the switches **G3** and **G4** are selected, the direction of the electric current is the backward direction. This is necessary for enabling a flow of a magnetization reset current for improving an exciting property of a current transformer for pulse operation of a compact medical accelerator bending magnet.

[0029] In **FIG. 1**, a low-voltage large-current power supply **5** is inserted between an inductive load **6** and the switch **2**, and when its voltage is applied to a discharge current in series, energy can be replenished at every discharge. Further, at the first time, the low-voltage large-current power supply **5** allows an electric current **4** in the circuit, and by cutting off the electric current **4** by the current switch **2**, the capacitor **1** can be charged like a snubber capacitor, and thus a pulse current for high-speed boot can be obtained only by the low-voltage power supply without preparing a separate high-voltage power supply for charging the capacitor. Needless to say, a general method of connecting a charging power supply to the capacitor **1** so as to charge the capacitor is effective.

#### INDUSTRIAL APPLICABILITY

[0030] According to the present invention, the gate signals of bidirectional current switches having a bridge constitution composed of four semiconductor switches connected to diodes in parallel as the switch of the energy source capacitor for generating an electric current are controlled, so that

the electric current to the inductive load can be started, maintained and stopped at a high speed. At this time, when the electric current is reduced, the magnetic energy is regenerated with the same polarity as that of the capacitor. As shown in **FIG. 5**, when the low-voltage large-current power supply **5** is inserted into the current circuit, the charging voltage of the capacitor can be increased or decreased while a discharge cycle is being repeated.

[0031] When the two power MOSFETs in series have the withstand voltage, a total capacity of the four switch elements may be basically half, and further when it is considered that a pulse conductive current flows in two arms in parallel, the total capacity is half. For this reason, the present invention can be applied basically without increasing voltage-current capacity in comparison with conventional pulse power supply.

1. A pulse power supply device for supplying a bipolar pulse current to an inductive load with high repetition and regenerating residual magnetic energy of a system so as to use it for next discharge, wherein

an energy source capacitor initially charged is connected to a DC terminal of a bridge circuit composed of four inverse-conductive semiconductor switches, and the inductive load is connected to its AC terminal,

a control circuit for giving a control signal to gates of the inverse-conductive semiconductor switches and controlling an on/off state of the semiconductor switches is further provided,

the control circuit controls pairs of the four inverse-conductive semiconductor switches composing the bridge circuit positioned on diagonal lines, respectively, so that the pairs are turned on simultaneously or alternately, and controls the pairs so that when at least

one of the paired two inverse-conductive semiconductor switches is on, the other paired inverse-conductive semiconductor switches are off.

2. The pulse power supply device using regenerating magnetic energy according to claim 1, wherein a low-voltage large-current power supply is inserted in series with the inductive load so as to replenish lost energy due to discharge so as to increase or decrease next discharge current.

3. The pulse power supply device using regenerating magnetic energy according to claim 1, wherein the inverse-conductive semiconductor switches are any one kind of power MOSFETs, inverse-conductive GTO thyristors and units constituted so that diodes and semiconductor switches such as IGBT and the like are connected in parallel.

4. The pulse power supply device using regenerating magnetic energy according to claims 1, wherein one of the two pairs of inverse-conductive semiconductor switches is replaced by diodes.

5. The pulse power supply device using regenerating magnetic energy according to claim 2, wherein the inverse-conductive semiconductor switches are any one kind of power MOSFETs, inverse-conductive GTO thyristors and units constituted so that diodes and semiconductor switches such as IGBT and the like are connected in parallel.

6. The pulse power supply device using regenerating magnetic energy according to 2, wherein one of the two pairs of inverse-conductive semiconductor switches is replaced by diodes.

7. The pulse power supply device using regenerating magnetic energy according to 3, wherein one of the two pairs of inverse-conductive semiconductor switches is replaced by diodes.

\* \* \* \* \*