




INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : H05B 6/44, 6/06		A1	(11) International Publication Number: WO 99/03308 (43) International Publication Date: 21 January 1999 (21.01.99)
(21) International Application Number: PCT/US98/14125 (22) International Filing Date: 8 July 1998 (08.07.98)		(81) Designated States: JP, KR, US, European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE).	
(30) Priority Data: 60/052,029 9 July 1997 (09.07.97) US		Published <i>With international search report.</i>	
(63) Related by Continuation (CON) or Continuation-in-Part (CIP) to Earlier Application US 60/052,029 (CIP) Filed on 9 July 1997 (09.07.97)			
(71) Applicant (for all designated States except US): ADVANCED ENERGY INDUSTRIES, INC. [US/US]; 1625 Sharp Point Drive, Fort Collins, CO 80525 (US).			
(72) Inventors; and (75) Inventors/Applicants (for US only): SCHATZ, Douglas, S. [US/US]; 1009 Lochland Court, Fort Collins, CO 80524 (US). DORRENBACHER, John, M. [US/US]; 1806 Effingham, Fort Collins, CO 80526 (US).			
(74) Agents: SANTANGELO, Luke et al.; Santangelo Law Offices, P.C., 3rd floor, 125 South Howes, Fort Collins, CO 80521 (US).			

(54) Title: FREQUENCY SELECTED, VARIABLE OUTPUT INDUCTOR HEATER SYSTEM AND METHOD



(57) Abstract

An induction heating system using a plurality of zones (7, 8, and 9) in a coil (1) provides selective heating control for better uniformity especially for semiconductor and other thin film processing applications. By arranging the zones (7, 8, and 9) to have different resonance frequencies, the power supply (20) may control the various zones (7, 8, and 9) by altering its frequency output. The power supply (20) may also act to control the differential heating by switching among zones in conjunction with the frequency control, by sweeping through a variety of frequencies, by simultaneously providing power over different frequencies, by altering the residence time at each frequency, or by outputting different powers to each frequency or the like. Each zone may thus be tuned as appropriate to achieve the desired induction heating characteristic.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakhstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

FREQUENCY SELECTED, VARIABLE OUTPUT INDUCTOR HEATER SYSTEM AND METHOD

Technical Field

This invention relates to heating systems using high frequency energy to
5 induce currents in objects to heat them directly or indirectly (“induction heating
systems”). In particular it relates to heating systems for semiconductor processing
equipment in which layers are formed on heated semiconductor wafers by Chemical
Vapor Deposition.

Equipment for the formation of layers, such as epitaxial silicon or polysilicon,
10 on semiconductor wafers is well known. One of the problems in forming layers of
materials on a semiconductor wafer is ensuring that the temperature of the
semiconductor wafer is kept uniform across the wafer during the deposition process,
i.e., during heat-up, processing, and cool-down. Since the deposition rate of a layer of
material upon the wafer is dependent on the temperature of the wafer, any temperature
15 variations between the center and edge of a wafer will undesirably result in the
deposition of a layer of non-uniform thickness on the wafer. In addition, non-uniform
temperatures during heat-up, processing, and cool-down can cause stress on the wafer,
undesirably resulting in slip. Accordingly, it is important during the deposition of a
layer of material on a silicon wafer to minimize temperature variations across the
20 surface of the wafer.

Some earlier systems developed to achieve temperature uniformity across a
wafer teach applying heat in a uniform manner across all portions of a wafer.
However, since heat loss is typically greater at the edge of a wafer than at the center,
such earlier systems may result in significant temperature differences between the
25 center and outer portions of the wafer and, thus, may be largely ineffective in
minimizing temperature gradient across the surface of a wafer.

Some more recent heating schemes employ lamp assemblies having heating
lamps arranged in a plurality of independently controlled zones to allow differing

amounts of heat to be applied to the outer and center portions of the wafer. In this manner, variations of heat loss on a wafer can be compensated by applying differing amounts of heat to various portions of the wafer in order to achieve greater temperature uniformity across the wafer. Such techniques are typically able to 5 maintain temperature differences of less than 10 °C across the wafer.

The heating lamps employed in such multiple-zone heating assemblies may result in several disadvantages. Each of these lamps, which is typically of the tungsten halogen type, has a finite useful life and thus must be periodically replaced. The replacement of such lamps, as well as the periodic adjustment of the lamps due to 10 their aging, not only increases manufacturing cost but also decreases the throughput of the chemical vapor deposition (CVD) system.

Furthermore, the use of such heating lamps in a radiantly heated CVD system undesirably requires periodically cleaning of the quartz walls of the reaction chamber to remove deposited material from the chamber walls. Recall that since the walls in a 15 lamp heated CVD reaction chamber become heated, layers of material deposit not only on the wafer but also on the chamber walls. The resulting film formed on the chamber walls then absorbs some of the radiant energy emitted from the heating lamps and thereby locally increases the temperature of the chamber walls. As a result, layers of material deposit on the chamber walls at an ever increasing rate, creating a 20 “snowball” effect. It is therefore critical, in a lamp heated CVD chamber, that the walls be kept meticulously clean. This requires that the walls be etched frequently, in some cases after every run. Cleaning the walls typically takes between two and four minutes after depositing an epitaxial layer, and longer after depositing a polysilicon layer. Since the entire cycle in warm wall CVD systems may be between five and ten 25 minutes, cleaning the walls accounts for a significant portion of the total cycle time and, therefore, can severely reduce throughput of the CVD system.

Disclosure of Invention

Accordingly, it is desirable to provide a heating system for chemical vapor deposition systems which uniformly and precisely heats a semiconductor wafer without the above mentioned deficiencies.

5 It is an object of the present invention, therefore, to permit control of the power delivered to each of a plurality of zones of an object to be heated by an induction heating system.

It is a further object of the invention to allow delicate and precise control over the temperature profile of an object being heated by an induction heating system.

10 It is another object of the invention to permit rapid temperature changes in an object being heated by an induction heating system while simultaneously maintaining the temperatures of a plurality of zones of said object in exact proportion to one another.

15 It is yet a further object of the invention to permit rapid temperature changes in an object being heated by an induction heating system while simultaneously holding the temperatures of a plurality of zones of said object precisely equal.

It is a further object of the present invention to maintain the temperatures of a plurality of zones of said object in exact proportion to one another as the object is cooled from a heated state.

20 It is another object of the invention to permit rapid cooling of an object in an induction heating system while simultaneously maintaining the temperatures of a plurality of zones of said object in exact proportion to one another.

It is yet another object of the present invention to eliminate the need for high current switches in a multi-zone induction heating system.

It is another object of the invention to permit the use of a single power supply in a multi-zone induction heating system.

5 It is a further object of the invention to eliminate or greatly reduce the interaction between zones of a multi-zone induction heating system.

It is yet a further object of the invention to obtain high power supply utilization in a multi-zone induction heating system.

10 It is still a further object of the present invention to permit rapid heating of a semiconductor wafer or other single crystal object without "slip", or dislocation of the crystal lattice.

15 Accordingly, one embodiment of the present invention is directed to a system for producing heating in an object such that precise control is possible of the energy deposited in a plurality of zones of the object to be heated through precise control of the power delivered to sections of a nearby induction coil which induces circulating currents in either the object to be heated or a susceptor placed in close proximity to the object to be heated.

20 One embodiment accomplishes these objects by utilizing an induction coil split into sections (a "tapped" induction coil), and selecting resonating capacitors for each section such that the frequency of resonance is different for each section. A frequency agile power supply is connected to the coil and the frequency of the output of the power supply is switched from the resonance frequency for the first section to the resonance frequency of the second section, to the resonant frequency of the third section, and so on until power has been applied to all (or all desired) sections.

Brief Description of Drawings

Figure 1 shows circulating current in a resonant circuit.

Figure 2 shows a system involving switched power to a tapped coil.

5 Figure 3 shows an alternative arrangement for a system involving switched power to a tapped coil.

Figure 4 shows a frequency agile power supply system.

Figure 5 shows a system with a multiple tapped coil configuration with switches.

Mode(s) for Carrying Out the Invention

10 In general, an induction heating system is comprised of a power supply, an induction coil, an object to be heated and, if necessary, a "susceptor" to absorb energy from the magnetic field of the coil and retransmit that energy to the object to be heated. The system operates on the principle of induction of circulating currents in the object to be heated or the susceptor, if present. Generally a susceptor is used if the
15 object to be heated is not adequately conductive (and thus cannot support the induced heating currents) or would be damaged in some way by such currents. The currents required to obtain substantial heating in large objects or rapid heating of small objects are large. A coil carrying large currents creates a large magnetic field in its vicinity, and energy is stored in this field. While much of the field may be canceled by the
20 induced current in the susceptor or object to be heated, there remains enough to store appreciable energy. This energy is represented electrically as inductance, and to create large currents in an inductor requires high voltages. The presence of high voltage and high current requires a great deal of power from the supply unless the energy represented by the magnetic field is stored elsewhere in the system when the

current collapses on each cycle of the current. If an electrical capacitance is placed in series or parallel with the coil, and the frequency of the alternating current is properly chosen, energy can be stored in the capacitance, and the power supply can be made much smaller than would be required without the capacitor. Thus it is typical for an induction heating system to be arranged so that the coil is “resonated” with a capacitor. That is, a capacitor is placed in series or parallel with a value such that the electrical circuit is resonant at the operating frequency of the power supply. Such an arrangement is shown in Figure 1. Here coil 1 has a capacitor 2 connected in parallel with it. Resistor 3 represents the equivalent resistor resulting from the energy loss in the heated body or susceptor and the coil and capacitor. Energy is stored alternatively in the coil and the capacitor, with the energy exchanging between the two twice every cycle of the alternating output of the power supply. This system permits the power supply to deliver only the losses of the resonant circuit, which are principally the energy lost in the object to be heated (or the susceptor, if present) and the coil itself, which is heated by the current flowing through it. Representing the “quality factor”, or “Q”, by

$$Q = \frac{\omega L}{R},$$

where L is the inductance of the coil 1, R is the equivalent resistor 3, and ω is the angular frequency, equal to 2 times pi times the frequency in Hz, the current 4 is Q times higher than the current 5, provided a resonant condition is established, by selecting the capacitance value C of the capacitor 2 in accordance with the formula

$$\omega = \frac{1}{\sqrt{LC}}$$

Typically the Q is about 10 for an induction heating system, and so the power supply need deliver only 1/10 of the circulating current. Said conversely, one can obtain coil currents easily 10 times the power supply current by this method. This "resonant" system is well known and has been used successfully for many years in induction

5 heating applications, including semiconductor processing systems.

In the present situation, it is desired to heat multiple areas of a susceptor in such a way as to produce a high degree of temperature uniformity. To this end, a multiple coil is employed, i.e., a coil with electrical taps so that the currents in various portions of it can be made different. The different currents in the different sections of the coil

10 may then induce different currents in physical zones of the susceptor or object to be heated, giving one the ability to deposit energy into those zones selectively and in precise amounts. A problem arises when such a system is made resonant, however, because of the mutual coupling of the various portions of the coil.

When a current is induced in one section of a multiple section coil, a magnetic field is created by the current. The lines of this magnetic field will intercept the object to be heated and the susceptor if present, producing the desired circulating currents and resultant desired heating in the physical zone of the object to be heated or the susceptor associated with that section of the multiple section coil. These lines will also intersect the other portions of the coil, however, inducing currents in those other

20 coil segments, and this will in turn create heating in unwanted physical zones of the object to be heated or the susceptor, if present. Because not all of the magnetic field lines intersect the other portions of the coil, the heating will be greatest in the desired zone (i.e., the zone associated with the driven portion of the coil), but the undesired heating in the other zones interferes with one's ability to control the temperature

25 distribution precisely. As the object to be heated or the susceptor is moved further from the coil, the interaction between the various segments of the coil will increase and the ability to control the energy deposited in the various zones will deteriorate.

It might be practical to use electronic switches to switch a power supply from one tap of the coil to another to force the power supply current to flow only through the desired segment of the coil. In Figure 2 is shown a tapped coil with resonating capacitors and power supplies 17, 18 and 19 with switches. Assume switches 13 and 5 14 are closed, connecting power supply 17 to coil section 7 of coil 1. Even if switches 15 and 16 are open circuited, mutual coupling between coil sections 7 and 8 and also between coil sections 7 and 9, caused by the magnetic field lines of coil section 7 cutting through the turns of coil sections 8 and 9 may create circulating currents in the coupled coil sections 8 and 9. These currents can flow because of the capacitors 11 10 and 12 across those coil sections 8 and 9, which form a resonant loop with their respective coil section. While it is possible to move the switch locations to break the circulating currents induced in the undriven coil sections as shown in Figure 3, this means that the switches might now carry the full value of the circulating currents, which can be thousands of amperes due to the multiplying effect of the resonance as 15 described above. Also, for practical reasons the capacitors may need to be located very close to the coil, to lower the inductance of the leads between the capacitors and the coils. If this is not done the large currents may cause high voltages to appear across the capacitors and losses to appear in local conducting surfaces due to the high magnetic fields surrounding the connecting leads. This may leave no space to mount 20 the switching devices, even if such robust switches could be found.

In instances in which the circuit of Figure 2 provides inadequate isolation of the sections and therefore inadequate control of the energy deposition in the object to be heated or the susceptor if present, and the circuit of Figure 3 requiring an impractical selection and location of semiconductor switches, an alternative approach may be 25 needed. In this situation, what may be needed is a method of depositing energy selectively into separate sections of an induction heating coil, which method permits delicate control over the amounts of energy deposited into each section, while permitting rapid switching between the various sections of the coil, to permit overall delicate and precise control of the temperature of the object to be heated.

It is also possible to permit the deposition of precise amounts of energy into zones of a wafer using a multizone induction coil and "spot" temperature monitoring system. The multiple zone coil may involve several sections which must be separately powered to effect the transfer of precise amounts of energy to the various 5 parts of the susceptor which in turn heats the wafer. The separate powering of these coil segments may, however, require a novel approach to power supply design for reasons discussed herein.

In one embodiment, shown in Figure 4, coil 1 is segmented into sections 7, 8, and 9, by taps. Capacitors 10, 11, and 12, are placed in parallel with coil sections 7, 8, and 9 respectively, and a frequency agile power supply 20 is placed in parallel with the entire coil 1. The capacitor values of the capacitors 10, 11, and 12 are chosen so that they are resonant with coil sections 7, 8, and 9 at frequencies f_1 , f_2 , and f_3 , respectively. That is, the capacitance of capacitor 10 is chosen in accordance with the formula

$$15 \quad \omega_1 = 2\pi f_1 = \frac{1}{\sqrt{L_7 C_{10}}} ,$$

where L_7 is the inductance of coil section 7 and C_{10} is the capacitance of capacitor 10.

Capacitance values for capacitors 11 and 12 are chosen similarly so that coil section 8 and capacitor 11 are resonant at a frequency f_2 preferably different from f_1 , 20 and so that coil section 9 and capacitor 12 are resonant at a frequency f_3 preferably different from f_1 and f_2 . Of course, more taps may be provided on the coil and or less more sections of said coil created thereby, and possibly each of these sections would be resonant at a different frequency.

With each of the sections of the coil 1 resonant at a different frequency, it is possible then to select the frequency of the power supply 20 at frequencies f_1 , f_2 , f_3 ,, to excite currents in coil sections 7, 8, and 9 respectively. If the control system is so arranged it may be that the frequency of the power supply is cycled from f_1 to f_2 to f_3 and back to f_1 in an continuous manner. Thus each coil segment is excited in turn, and energy selectively deposited in turn into the corresponding zones of the susceptor or object to be heated.

There are at least several methods available in such an arrangement to control the power delivered to each of the zones relative to the rest. In one embodiment, the time the power supply rests at each frequency may be varied to determine the energy deposited in each zone on each cycle. In another embodiment, the power delivered by the power supply during the period the supply is resting at each frequency may be varied while the time during which the supply rests at any given frequency may be held constant. In yet another embodiment, the frequency of the power supply may be deviated from exact resonance to affect the circulating current in the resonant elements, while the power and the time for each zone is held constant. It will be obvious that such control methods may be combined, with the resting time of each step of a cycle, the power delivered during each step of the cycle, and the exact frequency generated at each step of a cycle all being varied as appropriate to obtain the desired energy (and therefore temperature) profile.

It will be recognized by those skilled in the art that it may be desirable to maintain the frequency at each step such that the voltage and current of the power supply are nearly in phase with one another to prevent the necessity of delivering excess voltage or current from the power supply for a given amount of power. To the extent this is desirable in a given case the ability to control power by adjusting the frequency may be limited, and adjustment of the timing or power level of each step may be required to obtain the desired temperature or energy profile.

It is also possible to combine the approaches of Figure 2 and Figure 4. It will be recognized by those skilled in the art that there is a limit to the number of discrete frequency bands into which the frequency range of power supply 20 may be divided. This limit is established by the fact that the energy from the power supply is delivered 5 to a resonant section of a small range of frequencies determined by the circuit "Q" as described above. As it is not possible or desirable to establish a circuit "Q" much higher than 10 or 20, and a section with a circuit "Q" of 10 will absorb energy in a band of frequencies roughly bounded by $(1-1/Q)f_r < f < (1+1/Q)f_r$, where f_r is the resonant frequency of the section of the coil and its corresponding capacitor. Thus it 10 may be necessary to separate the resonant frequencies of each of the coil sections by enough to prevent unwanted excitation of other sections with a resonant frequency adjacent to the driven section.

Should the number of zones be large and the frequency range of the power supply 20 be inadequate to cover all of the zones, it is possible to combine the 15 approaches indicated by Figures 2 and 4. That is, as shown in Figure 5, it is possible to arrange two (or more) coils 21 and 22, each tapped in the manner of Figures 2 or 4, but separated by switches 23 and 24 from power supply 20 so that the power supply 20 is connected to only one of the coils 21 or 22 at a time. This arrangement permits the use of a single frequency agile power supply with limited frequency range to 20 control a plurality of zones with a high degree of precision.

Claims

We claim:

1. A multizone induction heating system comprising:
 - a. a coil system divided into a plurality of zones, at least two of said zones having an electrical resonance frequency, said resonance frequencies having at least two different values;
 - b. a power supply having an output frequency; and
 - c. a control system to control the power delivered to each of said zones comprising a control circuit to change said output frequency of said power supply.
2. A multizone induction heating system as described in claim 1 wherein said coil system comprises a plurality of coils.
3. A multizone induction heating system as described in claim 1 wherein said coil system comprises at least one coil divided into a plurality of sections.
- 15 4. A multizone induction heating system as described in claim 2 or 3 wherein said control system further comprises a circuit to switch said output frequency among at least two operating frequencies.
5. A multizone induction heating system as described in claim 4 wherein said control system further comprises a circuit to vary the output power of said power supply while said output frequency is switched among said operating frequencies.
- 20 6. A multizone induction heating system as described in claim 4 wherein said control system further comprises a circuit to vary the residence times at each of said operating frequencies of said power supply.

7. A multizone induction heating system as described in claim 2 or 3 wherein said control system further comprises a circuit to vary said output frequency continuously over a range of frequencies.
8. A multizone induction heating system comprising:
 - 5 a. a coil system divided into a plurality of zones, at least two of said zones having an electrical resonance frequency, said resonance frequencies having at least two different values;
 - b. a power supply having at least two simultaneously emitted output frequencies;
 - 10 c. a control system to control the power delivered to each of said zones wherein said at least two output frequencies are established to cause differentiated amounts of inductive heating by said zones.
9. A multizone induction heating system as described in claim 8 wherein said coil system comprises a plurality of coils.
- 15 10. A multizone induction heating system as described in claim 8 wherein said coil system comprises at least one coil divided into a plurality of sections.
11. A multizone induction heating system as described in claim 8, 9 or 10 wherein at least one of said simultaneously emitted output frequencies operates at about the resonance frequency of one of said plurality of zones of said coil 20 system.
12. A multizone induction heating system as described in claim 8, 9, 10 or 11 wherein at least one of said simultaneously emitted output frequencies operates at other than a resonance frequency of one any of said zones.

13. A multizone induction heating system as described in claim 8, 9, 10, 11 or 12 wherein said control system to control the power delivered to each of said zones further comprises variable tuning circuitry configured to alter the amount of inductive heating caused by at least one of said zones.

5 14. A multizone induction heating system comprising:

- a. a coil system divided into a plurality of zones, at least two of said zones having an electrical resonance frequency, said resonance frequencies having at least two different values;
- b. at least one power supply having at least one output frequency; and
- 10 c. a control system to control the power delivered to each of said zones comprising unswitched resonant circuitry which establishes the resonance frequency of each of said zones and which establishes differentiated amounts of inductive heating by said zones.

15. A multizone induction heating system as described in claim 14 wherein said 15 coil system comprises a plurality of coils.

16. A multizone induction heating system as described in claim 14 wherein said coil system comprises at least one coil divided into a plurality of sections.

17. A multizone induction heating system as described in claim 14, 15 or 16 20 wherein said output frequency operates at about the resonance frequency of one of said plurality of zones of said coil system.

18. A multizone induction heating system as described in claim 14, 15, 16 or 17 wherein said control system to control the power delivered to each of said zones further comprises variable tuning circuitry configured to alter the amount of inductive heating caused by at least one of said zones.

19. A multizone induction heating system as described in claim 14, 15, 16, 17 or 18 wherein said unswitched resonant circuitry which establishes the resonance frequency of each of said zones comprises:

- a. a first group of unswitched resonant circuitry which establishes resonance frequencies of a first group of zones; and
- b. a second group of unswitched resonant circuitry which establishes resonance frequencies of a second group of zones;

and wherein said control system further comprises switching circuitry which is configured to selectively provide power to each of said groups of unswitched resonant circuitries.

10

20. A method of induction heating comprising the steps of:

- a. dividing a coil system into a plurality of zones;
- b. establishing at least two of said zones with different resonance frequencies;
- c. supplying power having an output frequency;
- d. adjusting said output frequency to control the power to said zones.

15

21. A method of induction heating as described in claim 20 wherein said step of dividing a coil system into a plurality of zones comprises the step of dividing the coil system into a plurality of coils.

20 22. A method of induction heating as described in claim 20 wherein said step of dividing a coil system into a plurality of zones comprises the step of dividing at least one coil of said coil system into a plurality of sections.

23. A method of induction heating as described in claims 21 or 22 wherein said step of adjusting said output frequency further comprises the step of switching said output frequency among at least two output frequencies.

25

24. A method of induction heating as described in claim 23 wherein said step of switching further comprises the step of adjusting the power output of said power supply at each of said output frequencies.
25. A method of induction heating as described in claim 23 wherein said step of switching further comprises the step of adjusting the residence times at each of said output frequencies.
5
26. A method of induction heating as described in claims 21 or 22 wherein said step of adjusting said operating frequency comprises the step of varying said output frequency continuously over a range of frequencies.
10 and said step of adjusting said operating frequency comprises the step of adjusting the output power of said power supply at each of said operating frequencies.
27. A method of induction heating comprising the steps of:
 - a. dividing a coil system into a plurality of zones;
 - b. establishing at least two of said zones with different resonance frequencies;
 - c. producing power having at least two simultaneously emitted output frequencies wherein said at least two simultaneously emitted output frequencies are established to cause differentiated amounts of inductive heating by said zones.
15
28. A method of induction heating as described in claim 27 wherein said step of dividing a coil system into a plurality of zones comprises the step of dividing the coil system into a plurality of coils.
20
29. A method of induction heating as described in claim 27 wherein said step of dividing a coil system into a plurality of zones comprises the step of dividing at least one coil of said coil system into a plurality of sections.
25

30. A method of induction heating as described in claim 27, 28, or 29 wherein said step of producing power having at least two simultaneously emitted output frequencies wherein said at least two simultaneously emitted output frequencies are established to cause differentiated amounts of inductive heating by said zones comprises the step of simultaneously emitting at least one output frequency which is at about the resonance frequency of one of at least one of said plurality of zones of said coil system.

5

31. A method of induction heating as described in claim 27, 28, 29, or 30 wherein said step of producing power having at least two simultaneously emitted output frequencies wherein said at least two simultaneously emitted output frequencies are established to cause differentiated amounts of inductive heating by said zones comprises the step of simultaneously emitting at least one output frequency which is at other than a resonance frequency of any of said plurality of zones of said coil system.

10

15 32. A method of induction heating as described in claim 27, 28, 29, 30, or 31 and further comprising the step of providing adjustable circuitry which alters the amount of inductive heating caused by at least one of said zones.

33. A method of induction heating comprising the steps of:

20

- a. dividing a coil system into a plurality of zones;
- b. establishing at least two of said zones with different resonance frequencies;
- c. supplying power having an output frequency through unswitched resonant circuitry which establishes the resonance frequency of each of said zones and which establishes differentiated amounts of inductive heating by said zones.



25



34. A method of induction heating as described in claim 33 wherein said step of dividing a coil system into a plurality of zones comprises the step of dividing the coil system into a plurality of coils.
35. A method of induction heating as described in claim 33 wherein said step of dividing a coil system into a plurality of zones comprises the step of dividing at least one coil of said coil system into a plurality of sections.
5
36. A method of induction heating as described in claim 33, 34, or 35 wherein said step of supplying power having an output frequency through unswitched resonant circuitry which establishes the resonance frequency of each of said zones and which establishes differentiated amounts of inductive heating by said zones comprises the step of emitting an output frequency which is at about the resonance frequency of one of at least one of said plurality of zones of said coil system.
10
37. A method of induction heating as described in claim 33, 34, 35, or 36 and further comprising the step of providing adjustable circuitry which alters the amount of inductive heating caused by at least one of said zones.
15
38. A method of induction heating as described in claim 33, 34, 35, 36, or 37 wherein said step of establishing at least two of said zones with different resonance frequencies comprises the steps of:
20
 - a. establishing a first group of unswitched resonant circuitry which establishes resonance frequencies of a first group of zones; and
 - b. establishing a second group of unswitched resonant circuitry which establishes resonance frequencies of a second group of zones;and further comprising the step of switching to selectively provide power to each of said groups of unswitched resonant circuitries.
25


39. A multizone induction heating system as described in claim 18 wherein said variable tuning circuitry comprises frequency switching circuitry.
40. A method of induction heating as described in claim 32 or 37 wherein said step of providing adjustable circuitry comprises the step of providing frequency switching circuitry.
5
41. A multizone induction heating system as described in claim 13 or 18 wherein said variable tuning circuitry comprises multiple frequency circuitry.
42. A method of induction heating as described in claim 32 or 37 wherein said step of providing adjustable circuitry comprises the step of providing multiple frequency circuitry.
10
43. A multizone induction heating system as described in claim 13 or 18 wherein said variable tuning circuitry comprises resonance frequency variation circuitry.
44. A method of induction heating as described in claim 32 or 37 wherein said step of providing adjustable circuitry comprises the step of providing resonance frequency variation circuitry.
15
45. A multizone induction heating system as described in claim 43 wherein said resonance frequency variation circuitry comprises at least one variable impedance element.
- 20 46. A method of induction heating as described in claim 44 wherein said step of providing resonance frequency variation circuitry comprises the step of providing at least one variable impedance element.

47. A multizone induction heating system as described in claim 14 wherein said unswitched resonant circuitry comprises unswitched resonance frequency circuitry which primarily affects one of said zones.
48. A method of induction heating as described in claim 33 wherein said step of supplying power having an output frequency through unswitched resonant circuitry comprises the step of supplying power having an output frequency through unswitched resonance frequency circuitry which primarily affects one of said zones.

1/3

**FIG. 1****FIG. 2**

**FIG. 3****FIG. 4**

**FIG. 5**

INTERNATIONAL SEARCH REPORT

International application No. PCT/US98/14125

A. CLASSIFICATION OF SUBJECT MATTER

IPC(6) :H05B 6/44, 6/06

US CL :219/656, 662, 674, 638

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

U.S. : 219/656, 655, 662, 671, 666, 674, 672, 635, 638; 148/567, 572; 266/129

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched


Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 4,755,648 A (SAWA) 05 July 1988, see Figures 1-3 and 6, col. 1, line 7 - col. 2, line 59 and col. 3, line 15 - col. 4, line 20.	1-11, 14-17, 20-30, 33-36, 47 and 48
X	US 2,669,647 A (SEGSWORTH) 16 February 1954, see Figure 1 and col. 1, line 1 - col. 2, line 41.	8-11, 14-17, 27-30, 33-36, 47 and 48
A	US 4,093,839 A (MOLITERNO et al) 06 June 1978, see Figures 1 and 2.	8, 9, 14, 15, 27, 28, 33, 34
A	US 4,506,131 A (BOEHM et al) 19 March 1985, see Figure 1.	3, 10, 16, 22, 29, 35

Further documents are listed in the continuation of Box C. See patent family annex.

* Special categories of cited documents:	"T"	later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
"A" document defining the general state of the art which is not considered to be of particular relevance	"X"	document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
"E" earlier document published on or after the international filing date	"Y"	document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)	"&"	document member of the same patent family
"O" document referring to an oral disclosure, use, exhibition or other means		
"P" document published prior to the international filing date but later than the priority date claimed		

Date of the actual completion of the international search 27 AUGUST 1998	Date of mailing of the international search report OCT 13 1998
Name and mailing address of the ISA/US Commissioner of Patents and Trademarks Box PCT Washington, D.C. 20231 Facsimile No. (703) 305-3230	Authorized officer  PHILIP H. LEUNG Telephone No. (703) 308-1710

INTERNATIONAL SEARCH REPORT

International application No.
PCT/US98/14125

C (Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US 4,788,394 A (VANNESTE et al) 29 November 1988, see Figures 1 and 8-11.	-----

INTERNATIONAL SEARCH REPORT

International application No.
PCT/US98/14125

Box I Observations where certain claims were found unsearchable (Continuation of item 1 of first sheet)

This international report has not been established in respect of certain claims under Article 17(2)(a) for the following reasons:

1. Claims Nos.: because they relate to subject matter not required to be searched by this Authority, namely:

2. Claims Nos.: because they relate to parts of the international application that do not comply with the prescribed requirements to such an extent that no meaningful international search can be carried out, specifically:

3. Claims Nos.: 12, 13, 18, 19, 31, 32 and 37-46 because they are dependent claims and are not drafted in accordance with the second and third sentences of Rule 6.4(a).

Box II Observations where unity of invention is lacking (Continuation of item 2 of first sheet)

This International Searching Authority found multiple inventions in this international application, as follows:

1. As all required additional search fees were timely paid by the applicant, this international search report covers all searchable claims.

2. As all searchable claims could be searched without effort justifying an additional fee, this Authority did not invite payment of any additional fee.

3. As only some of the required additional search fees were timely paid by the applicant, this international search report covers only those claims for which fees were paid, specifically claims Nos.:

4. No required additional search fees were timely paid by the applicant. Consequently, this international search report is restricted to the invention first mentioned in the claims; it is covered by claims Nos.:

Remark on Protest

The additional search fees were accompanied by the applicant's protest.
 No protest accompanied the payment of additional search fees.