



(86) Date de dépôt PCT/PCT Filing Date: 2003/11/14
(87) Date publication PCT/PCT Publication Date: 2004/06/17
(45) Date de délivrance/Issue Date: 2011/06/07
(85) Entrée phase nationale/National Entry: 2005/05/31
(86) N° demande PCT/PCT Application No.: EP 2003/014863
(87) N° publication PCT/PCT Publication No.: 2004/051463
(30) Priorité/Priority: 2002/12/05 (US10/313,320)


(51) Cl.Int./Int.Cl. *G06F 9/46* (2006.01),
G06F 13/24 (2006.01), *G06F 9/30* (2006.01),
G06F 9/38 (2006.01)

(72) Inventeurs/Inventors:
ARIMILLI, RAVI KUMAR, US;
CARGNONI, ROBERT ALAN, US;
GUTHRIE, GUY LYNN, US;
STARKE, WILLIAM JOHN, US

(73) Propriétaire/Owner:
INTERNATIONAL BUSINESS MACHINES
CORPORATION, US

(74) Agent: WANG, PETER

(54) Titre : MECANISME DE VIRTUALISATION DE PROCESSEUR PAR RETABLISSEMENT AMELIORE DES ETATS
ARCHITECTURES DURS
(54) Title: PROCESSOR VIRTUALIZATION MECHANISM VIA AN ENHANCED RESTORATION OF HARD
ARCHITECTED STATES



(57) Abrégé/Abstract:

A method and system are disclosed for pre-loading a hard architected state of a next process from a pool of idle processes awaiting execution. When an executing process is interrupted on the processor, a hard architected state, which has been pre-

(57) **Abrégé(suite)/Abstract(continued):**

stored in the processor, of a next process is loaded into architected storage locations in the processor. The next process to be executed, and thus its corresponding hard architected state that is pre-stored in the processor, are determined based on priorities assigned to the waiting processes.

(12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property
Organization
International Bureau



(43) International Publication Date
17 June 2004 (17.06.2004)

PCT

(10) International Publication Number
WO 2004/051463 A3

(51) International Patent Classification⁷: **G06F 9/46**, 9/30

(21) International Application Number:
PCT/EP2003/014863

(22) International Filing Date:
14 November 2003 (14.11.2003)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
10/313,320 5 December 2002 (05.12.2002) US

(71) Applicant: **INTERNATIONAL BUSINESS MACHINES CORPORATION** [US/US]; New Orchard Road, Armonk, NY 10504 (US).

(71) Applicant (for MC only): **COMPAGNIE IBM FRANCE** [FR/FR]; Tour Descartes- La Défense 5, 2, avenue Gambetta, 92400 Courbevoie (FR).

(72) Inventors: **ARIMILLI, Ravi, Kumar**; 9221 Spicebrush Drive, Austin, TX 78759 (US). **CARGNONI, Robert**,

Alan; 1904 Key West Cove, Austin, TX 78746 (US). **GUTHRIE, Guy, Lynn**; 11145 Calavar Drive, Austin, TX 78726 (US). **STARKE, William, John**; 8612 Sea Ash Circle, Round Rock, TX 78681 (US).


(74) Agent: **ETORRE, Yves, Nicolas**; Compagnie IBM France, Direction de la Propriété Intellectuelle, F-06610 La Gaude (FR).

(81) Designated States (*national*): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, OM, PH, PL, PT, RO, RU, SC, SD, SE, SG, SK, SL, TJ, TM, TN, TR, TT, TZ, UA, UG, UZ, VC, VN, YU, ZA, ZM, ZW.

(84) Designated States (*regional*): ARIPO patent (BW, GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZM, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU, IE, IT, LU, MC, NL, PT, RO, SE, SI, SK, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

[Continued on next page]

(54) Title: METHOD AND APPARATUS FOR SWITCHING BETWEEN PROCESSES



(57) Abstract: A method and system are disclosed for pre-loading a hard architected state of a next process from a pool of idle processes awaiting execution. When an executing process is interrupted on the processor, a hard architected state, which has been pre-stored in the processor, of a next process is loaded into architected storage locations in the processor. The next process to be executed, and thus its corresponding hard architected state that is pre-stored in the processor, are determined based on priorities assigned to the waiting processes.

WO 2004/051463 A3



Published:

- *with international search report*
- *before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments*

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(88) Date of publication of the international search report:

2 June 2005

- 1 -

**PROCESSOR VIRTUALIZATION MECHANISM VIA AN ENHANCED
RESTORATION OF HARD ARCHITECTED STATES**

The present invention is related to the subject matter of the following commonly assigned document:

- 5 U.S. Patent No. 6,983,347, issued January 3, 2006;
U.S. Patent No. 7,039,832, issued May 2, 2006;
U.S. Patent No. 7,272,664, issued September 18, 2007;
U.S. Patent No. 7,117,319, issued October 3, 2006; and
Canadian application no. 2508551, filed November 14, 2003.

10 **BACKGROUND OF THE INVENTION**

Technical Field

The present invention relates in general to the field of data processing, and, in particular, to an improved data processing system and method for handling interrupts.

15 **Description of the Related Art**

When executing a set of computer instructions, a processor is frequently interrupted. This interruption may be caused by an interrupt or an exception.

20 An interrupt is an asynchronous interruption event that is not associated with the instruction that is executing when the interrupt occurs. That is, the interruption is often caused by some event outside the processor, such as an input from an input/output (I/O) device, a call for an operation from another processor, etc. Other interrupts may be caused internally, for

- 2 -

example, by the expiration of a timer that controls task switching.

An exception is a synchronous event that arises directly from the execution of the instruction that is executing when the exception occurs. That is, an exception is an event from within the processor, such as an arithmetic overflow, a timed maintenance check, an internal performance monitor, an on-board workload manager, etc. Typically, exceptions are far more frequent than interrupts.

The terms "interrupt" and "exception" are often interchanged. For the purposes of this disclosure, the term "interrupt" will be used to describe both "interrupt" and "exception" interruptions.

As computer software and hardware have become more complex, the number and frequency of interrupts has increased dramatically. These interrupts are necessary, in that they support the execution of multiple processes, handling of multiple peripherals, and performance monitoring of various components. While such features are beneficial, the consumption of computing power by interrupts is increasing so dramatically that it is outstripping processing speed improvements of the processor(s). Thus, in many cases system performance is actually decreasing in real terms despite increasing processor clock frequencies.

Figure 1 illustrates a conventional processor core **100**. Within processor core **100**, a Level 1 Instruction cache (L1 I-cache) **102** provides instructions to instruction sequencing logic **104**, which issues the instructions to the appropriate execution units **108** for execution. Execution units **108**, which may include a floating point execution unit, a fixed point execution unit, a branch execution unit, etc., include a load/store unit (LSU) **108a**. LSU **108a** executes load and store instructions, which load data from Level 1 Data cache (L1 D-cache) **112** into architected register **110** and store data from architected register **110** to L1 D-cache **112**, respectively.

- 3 -

Requests for data and instructions that miss L1 caches **102** and **112** can be resolved by accessing system memory **118** via memory bus **116**.

As noted above, processor core **100** is subject to
5 interrupts from a number of sources represented by external interrupt lines **114**. When an interrupt signal is received by processor core **100** (e.g., via one of the interrupt lines **114**), execution of current process(es) are suspended and the interrupt is handled by interrupt-specific software known as an interrupt
10 handler. Among other activities, the interrupt handler saves and restores the architected state of the process executing at the time of the interrupt through the execution of store and load instructions by LSU **108a**. This use of LSU **108a** to transfer the architected state to and from system memory **118** blocks execution
15 of other memory access instructions by the interrupt handler, (or another process in the case of a superscalar computer) until the state transfer is complete. Consequently, saving and subsequently restoring the architected states of a process through the execution units of the processor causes a delay in
20 execution of both the interrupted process as well as the interrupt handler. This delay results in a degradation of the overall performance of the processor. Thus, the present invention recognizes that there is a need for a method and system that minimize the processing delay incurred by saving and
25 restoring architected states, particularly in response to interrupt.

SUMMARY OF THE INVENTION

The present invention is directed to methods and systems for improving interrupt handling within a processor of a data processing system.

5 When an interrupt signal is received at the processor, a hard architected state of a currently executing process is loaded into one or more dedicated shadow registers. The hard architected state includes information within the processor that is essential for execution of the interrupted process. A
10 beneficial method of further saving this hard architected state includes the use of a high-bandwidth bus to directly transfer the hard architected state from the shadow register(s) to a system memory, without using (and thus tying up) the normal load/store pathway and execution units of the processor. After
15 the hard architected state has been loaded into the shadow register(s), the interrupt handler immediately begins to run, either on the processor that received the interrupt or another processor in a multiprocessor data processing system. The hard architecture of a next process scheduled for execution is stored
20 in a set of registers in the processor, so that the hard architecture of the next scheduled process is loaded into the processor's current process hard architecture registers such that the next process can rapidly begin execution.

 The soft state of the process, including cache contents, is
25 also at least partially saved to system memory. To accelerate the saving of the soft state, and to avoid data collisions with the executing interrupt handler, the soft state is preferably transferred from the processor using scan chain pathways, which in the prior art are normally used only during manufacturer
30 testing and are unused during normal operation.

 Upon completion of the interrupt handler, the hard architected state and soft state are restored for an interrupted process, which is able to run immediately upon loading of the hard architected state.

- 5 -

To afford access to other processors and other partitions possibly running different operating systems, both the hard and soft states may be stored in a reserved area of system memory that is accessible to any processor and/or partition.

5 The above, as well as additional objectives, features, and advantages of the present invention will become apparent in the following detailed written description.

BRIEF DESCRIPTION OF THE DRAWINGS

10 The novel features believed characteristic of the invention are set forth in the appended claims. The invention itself, however, as well as a preferred mode of use, further objects and advantages thereof, will best be understood by reference to the following detailed description of an illustrative embodiment when read in conjunction with the accompanying drawings,
15 wherein:

Figure 1 depicts a block diagram of a conventional computer system that employs a prior art method for saving the architected state of the processor using a load/store unit;

20 **Figure 2** illustrates a block diagram of an exemplary embodiment of a data processing system in accordance with the present invention;

Figures 3a and **3b** depict additional detail of a processing unit illustrated in Figure 2;

25 **Figure 4** illustrates a layer diagram of an exemplary software configuration in accordance with the present invention;

Figure 5a and **5b** together form a flowchart of an exemplary interrupt handling process in accordance with the present invention;

30 **Figures 6a** and **6b** are flowcharts showing further detail of the step shown in Figure 5a for saving a hard architected state and soft state in accordance with the present invention;

- 6 -

Figure 7 depicts scan chain pathways used by the present invention to communicate at least the soft state of a process to memory;

5 **Figures 8a-8c** illustrate additional detail of a flash ROM depicted in Figure 2 used in accordance with the present invention to store at least First Level Interrupt Handlers (FLIHs), Second Level Interrupt Handlers (SLIHs) and manufacturing-level test instructions;

10 **Figure 9** is a flow-chart describing jumping to a predicted SLIH upon receipt of an interruption by a processor in accordance with the present invention;

Figure 10 depicts the logical and communicative relationship between stored hard architected states, stored soft states, memory partitions and processors;

15 **Figure 11** illustrates an exemplary data structure for storing soft state in memory; and

Figure 12 is a flowchart of an exemplary method for testing a processor through execution of a manufacturing level test program during normal operation of a computer system.

20 **DETAILED DESCRIPTION OF ILLUSTRATIVE EMBODIMENT**

With reference now to **Figure 2**, there is depicted a high level block diagram of an exemplary embodiment of a multiprocessor (MP) data processing system **201**. While MP data processing system **201** is depicted as a symmetrical multiprocessor (SMP), the present invention may be utilized with any MP data processing system known to those skilled in the art of computer architecture, including but not limited to a non-uniform memory access (NUMA) MP or a Cache Only Memory Architecture (COMA) MP.

30 In accordance with the present invention, MP data processing system **201** includes a plurality of processing units **200**, depicted as processing units **200a** to **200n**, that are coupled for communication by an interconnect **222**. In a preferred

- 7 -

embodiment, it is understood that each processing unit **200**, including processing unit **200a** and processing unit **200n**, in MP data processing system **201** is architecturally similar or the same. Processing unit **200a** is a single integrated circuit superscalar processor, which, as discussed further below, includes various execution units, registers, buffers, memories, and other functional units that are all formed by integrated circuitry. In MP data processing system **201**, each processing unit **200** is coupled by a high bandwidth private bus **116** to respective system memory **118**, depicted as system memory **118a** for processing unit **200a** and system memory **118n** for processing unit **200n**.

Processing unit **200a** includes an instruction sequencing unit (ISU) **202**, which includes logic for fetching, scheduling and issuing instructions to be executed by execution unit (EU) **204**. Details of ISU **202** and EU **204** are given in exemplary form in **Figure 3**.

Associated with EU **204** are "hard" state registers **206** containing the information within processing unit **200a** that is essential for executing the currently executing process. Coupled to hard state register **206** are next hard state registers **210**, containing the hard state for the next process to be executed, for example, when the current process terminates or is interrupted. Also associated with hard state registers **206** are shadow registers **208**, which contain (or will contain) a copy of the contents of hard state registers **206** when the currently executing process terminates or is interrupted.

Each processing unit **200** further includes a cache hierarchy **212**, which may include multiple levels of cache memory. An on-chip storage of instructions and data loaded from system memories **118** may be accomplished by, for example, cache hierarchy **212**, which may comprise a Level one Instruction cache (L1 I-cache) **18**, a Level one Data cache (L1 D-cache) **20**, and a unified Level two cache (L2 cache) **16** as shown in **Figure 3**.

- 8 -

Cache hierarchy **212** is coupled to an on-chip integrated memory controller (IMC) **220** for system memory **118** via cache data path **218**, and in accordance with at least one embodiment, scan chain pathway **214**. As scan chain pathway **214** is a serial pathway,
5 serial-to-parallel interface **216** is coupled between scan chain pathway **214** and IMC **220**. The functions of the depicted components of processing unit **200a** are detailed below.

Reference is now made to **Figure 3a**, which shows additional detail for processing unit **200**. Processing unit **200** includes an
10 on-chip multi-level cache hierarchy including a unified level two (L2) cache **16** and bifurcated level one (L1) instruction (I) and data (D) caches **18** and **20**, respectively. As is well-known to those skilled in the art, caches **16**, **18** and **20** provide low
15 latency access to cache lines corresponding to memory locations in system memories **118**.

Instructions are fetched for processing from L1 I-cache **18** in response to the effective address (EA) residing in instruction fetch address register (IFAR) **30**. During each cycle, a new instruction fetch address may be loaded into IFAR **30** from
20 one of three sources: branch prediction unit (BPU) **36**, which provides speculative target path and sequential addresses resulting from the prediction of conditional branch instructions, global completion table (GCT) **38**, which provides flush and interrupt addresses, and branch execution unit (BEU)
25 **92**, which provides non-speculative addresses resulting from the resolution of predicted conditional branch instructions. Associated with BPU **36** is a branch history table (BHT) **35**, in which are recorded the resolutions of conditional branch instructions to aid in the prediction of future branch
30 instructions.

An effective address (EA), such as the instruction fetch address within IFAR **30**, is the address of data or an instruction generated by a processor. The EA specifies a segment register and offset information within the segment. To access

- 9 -

data (including instructions) in memory, the EA is converted to a real address (RA), through one or more levels of translation, associated with the physical location where the data or instructions are stored.

5 Within processing unit **200**, effective-to-real address translation is performed by memory management units (MMUs) and associated address translation facilities. Preferably, a separate MMU is provided for instruction accesses and data accesses. In **Figure 3a**, a single MMU **112** is illustrated, for
10 purposes of clarity, showing connections only to ISU **202**. However, it is understood by those skilled in the art that MMU **112** also preferably includes connections (not shown) to load/store units (LSUs) **96** and **98** and other components necessary for managing memory accesses. MMU **112** includes data translation
15 lookaside buffer (DTLB) **113** and instruction translation lookaside buffer (ITLB) **115**. Each TLB contains recently referenced page table entries, which are accessed to translate EAs to RAs for data (DTLB **113**) or instructions (ITLB **115**). Recently referenced EA-to-RA translations from ITLB **115** are
20 cached in EOP effective-to-real address table (ERAT) **32**.

 If hit/miss logic **22** determines, after translation of the EA contained in IFAR **30** by ERAT **32** and lookup of the real address (RA) in I-cache directory **34**, that the cache line of instructions corresponding to the EA in IFAR **30** does not reside
25 in L1 I-cache **18**, then hit/miss logic **22** provides the RA to L2 cache **16** as a request address via I-cache request bus **24**. Such request addresses may also be generated by prefetch logic within L2 cache **16** based upon recent access patterns. In response to a request address, L2 cache **16** outputs a cache line of
30 instructions, which are loaded into prefetch buffer (PB) **28** and L1 I-cache **18** via I-cache reload bus **26**, possibly after passing through optional predecode logic **144**. Once the cache line specified by the EA in IFAR **30** resides in L1 cache **18**, L1 I-cache **18** outputs the cache line to both branch prediction unit

(BPU) **36** and to instruction fetch buffer (IFB) **40**. BPU **36** scans the cache line of instructions for branch instructions and predicts the outcome of conditional branch instructions, if any. Following a branch prediction, BPU **36** furnishes a speculative
5 instruction fetch address to IFAR **30**, as discussed above, and passes the prediction to branch instruction queue **64** so that the accuracy of the prediction can be determined when the conditional branch instruction is subsequently resolved by branch execution unit **92**.

10 IFB **40** temporarily buffers the cache line of instructions received from L1 I-cache **18** until the cache line of instructions can be translated by instruction translation unit (ITU) **42**. In the illustrated embodiment of processing unit **200**, ITU **42** translates instructions from user instruction set architecture
15 (UISA) instructions into a possibly different number of internal ISA (IISA) instructions that are directly executable by the execution units of processing unit **200**. Such translation may be performed, for example, by reference to microcode stored in a read-only memory (ROM) template. In at least some embodiments,
20 the UISA-to-IISA translation results in a different number of IISA instructions than UISA instructions and/or IISA instructions of different lengths than corresponding UISA instructions. The resultant IISA instructions are then assigned by global completion table **38** to an instruction group, the
25 members of which are permitted to be dispatched and executed out-of-order with respect to one another. Global completion table **38** tracks each instruction group for which execution has yet to be completed by at least one associated EA, which is preferably the EA of the oldest instruction in the instruction
30 group.

Following UISA-to-IISA instruction translation, instructions are dispatched to one of latches **44**, **46**, **48** and **50**, possibly out-of-order, based upon instruction type. That is, branch instructions and other condition register (CR) modifying
35 instructions are dispatched to latch **44**, fixed-point and

- 11 -

load-store instructions are dispatched to either of latches **46** and **48**, and floating-point instructions are dispatched to latch **50**. Each instruction requiring a rename register for temporarily storing execution results is then assigned one or more rename registers by the appropriate one of CR mapper **52**, link and count (LC) register mapper **54**, exception register (XER) mapper **56**, general-purpose register (GPR) mapper **58**, and floating-point register (FPR) mapper **60**.

The dispatched instructions are then temporarily placed in an appropriate one of CR issue queue (CRIQ) **62**, branch issue queue (BIQ) **64**, fixed-point issue queues (FXIQs) **66** and **68**, and floating-point issue queues (FPIQs) **70** and **72**. From issue queues **62**, **64**, **66**, **68**, **70** and **72**, instructions can be issued opportunistically to the execution units of processing unit **10** for execution as long as data dependencies and antidependencies are observed. The instructions, however, are maintained in issue queues **62-72** until execution of the instructions is complete and the result data, if any, are written back, in case any of the instructions needs to be reissued.

As illustrated, the execution units of processing unit **204** include a CR unit (CRU) **90** for executing CR-modifying instructions, a branch execution unit (BEU) **92** for executing branch instructions, two fixed-point units (FXUs) **94** and **100** for executing fixed-point instructions, two load-store units (LSUs) **96** and **98** for executing load and store instructions, and two floating-point units (FPUs) **102** and **104** for executing floating-point instructions. Each of execution units **90-104** is preferably implemented as an execution pipeline having a number of pipeline stages.

During execution within one of execution units **90-104**, an instruction receives operands, if any, from one or more architected and/or rename registers within a register file coupled to the execution unit. When executing CR-modifying or CR-dependent instructions, CRU **90** and BEU **92** access the CR

- 12 -

register file **80**, which in a preferred embodiment contains a CR and a number of CR rename registers that each comprise a number of distinct fields formed of one or more bits. Among these fields are LT, GT, and EQ fields that respectively indicate if a value (typically the result or operand of an instruction) is less than zero, greater than zero, or equal to zero. Link and count register (LCR) register file **82** contains a count register (CTR), a link register (LR) and rename registers of each, by which BEU **92** may also resolve conditional branches to obtain a path address. General-purpose register files (GPRs) **84** and **86**, which are synchronized, duplicate register files, store fixed-point and integer values accessed and produced by FXUs **94** and **100** and LSUs **96** and **98**. Floating-point register file (FPR) **88**, which like GPRs **84** and **86** may also be implemented as duplicate sets of synchronized registers, contains floating-point values that result from the execution of floating-point instructions by FPUs **102** and **104** and floating-point load instructions by LSUs **96** and **98**.

After an execution unit finishes execution of an instruction, the execution notifies GCT **38**, which schedules completion of instructions in program order. To complete an instruction executed by one of CRU **90**, FXUs **94** and **100** or FPUs **102** and **104**, GCT **38** signals the execution unit, which writes back the result data, if any, from the assigned rename register(s) to one or more architected registers within the appropriate register file. The instruction is then removed from the issue queue, and once all instructions within its instruction group have completed, is removed from GCT **38**. Other types of instructions, however, are completed differently.

When BEU **92** resolves a conditional branch instruction and determines the path address of the execution path that should be taken, the path address is compared against the speculative path address predicted by BPU **36**. If the path addresses match, no further processing is required. If, however, the calculated path

- 13 -

address does not match the predicted path address, BEU **92** supplies the correct path address to IFAR **30**. In either event, the branch instruction can then be removed from BIQ **64**, and when all other instructions within the same instruction group have
5 completed, from GCT **38**.

Following execution of a load instruction, the effective address computed by executing the load instruction is translated to a real address by a data ERAT (not illustrated) and then provided to L1 D-cache **20** as a request address. At this point,
10 the load instruction is removed from FXIQ **66** or **68** and placed in load reorder queue (LRQ) **114** until the indicated load is performed. If the request address misses in L1 D-cache **20**, the request address is placed in load miss queue (LMQ) **116**, from which the requested data is retrieved from L2 cache **16**, and
15 failing that, from another processing unit **200** or from system memory **118** (shown in **Figure 2**). LRQ **114** snoops exclusive access requests (e.g., read-with-intent-to-modify), flushes or kills on interconnect **222** fabric (shown in **Figure 2**) against loads in flight, and if a hit occurs, cancels and reissues the load
20 instruction. Store instructions are similarly completed utilizing a store queue (STQ) **110** into which effective addresses for stores are loaded following execution of the store instructions. From STQ **110**, data can be stored into either or both of L1 D-cache **20** and L2 cache **16**.

25 PROCESSOR STATES

The state of a processor includes stored data, instructions and hardware states at a particular time, and are herein defined as either being "hard" or "soft." The "hard" state is defined as the information within a processor that is
30 architecturally required for a processor to execute a process from its present point in the process. The "soft" state, by contrast, is defined as information within a processor that would improve efficiency of execution of a process, but is not

- 14 -

required to achieve an architecturally correct result. In processing unit **200** of **Figure 3a**, the hard state includes the contents of user-level registers, such as CRR **80**, LCR **82**, GPRs **84** and **86**, FPR **88**, as well as supervisor level registers **51**.

5 The soft state of processing unit **200** includes both "performance-critical" information, such as the contents of L-1 I-cache **18**, L-1 D-cache **20**, address translation information such as DTLB **113** and ITLB **115**, and less critical information, such as BHT **35** and all or part of the content of L2 cache **16**.

10 REGISTERS

In the description above, register files of processing unit **200** such as GPR **86**, FPR **88**, CRR **80** and LCR **82** are generally defined as "user-level registers," in that these registers can be accessed by all software with either user or supervisor
15 privileges. Supervisor level registers **51** include those registers that are used typically by an operating system, typically in the operating system kernel, for such operations as memory management, configuration and exception handling. As such, access to supervisor level registers **51** is generally
20 restricted to only a few processes with sufficient access permission (i.e., supervisor level processes).

As depicted in **Figure 3b**, supervisor level registers **51** generally include configuration registers **302**, memory management registers **308**, exception handling registers **314**, and
25 miscellaneous registers **322**, which are described in more detail below.

Configuration registers **302** include a machine state register (MSR) **306** and a processor version register (PVR) **304**. MSR **306** defines the state of the processor. That is, MSR **306**
30 identifies where instruction execution should resume after an instruction interrupt (exception) is handled. PVR **304** identifies the specific type (version) of processing unit **200**.

- 15 -

Memory management registers **308** include block-address translation (BAT) registers **310**. BAT registers **310** are software-controlled arrays that store available block-address translations on-chip. Preferably, there are separate instruction and data BAT registers, shown as IBAT **309** and DBAT **311**. Memory management registers also include segment registers (SR) **312**, which are used to translate EAs to virtual addresses (VAs) when BAT translation fails.

Exception handling registers **314** include a data address register (DAR) **316**, special purpose registers (SPRs) **318**, and machine status save/restore (SSR) registers **320**. The DAR **316** contains the effective address generated by a memory access instruction if the access causes an exception, such as an alignment exception. SPRs are used for special purposes defined by the operating system, for example, to identify an area of memory reserved for use by a first-level exception handler (FLIH). This memory area is preferably unique for each processor in the system. An SPR **318** may be used as a scratch register by the FLIH to save the content of a general purpose register (GPR), which can be loaded from SPR **318** and used as a base register to save other GPRs to memory. SSR registers **320** save machine status on exceptions (interrupts) and restore machine status when a return from interrupt instruction is executed.

Miscellaneous registers **322** include a time base (TB) register **324** for maintaining the time of day, a decremter register (DEC) **326** for decrementing counting, and a data address breakpoint register (DABR) **328** to cause a breakpoint to occur if a specified data address is encountered. Further, miscellaneous registers **322** include a time based interrupt register (TBIR) **330** to initiate an interrupt after a pre-determined period of time. Such time based interrupts may be used with periodic maintenance routines to be run on processing unit **200**.

- 16 -

SOFTWARE ORGANIZATION

In a MP data processing system such as MP data processing system **201** of **Figure 2**, multiple applications can run simultaneously, possibly under different operating systems. **Figure 4** depicts a layer diagram of an exemplary software configuration of MP data processing system **201** in accordance with the present invention.

As illustrated, the software configuration includes a hypervisor **402**, which is supervisory software that allocates the resources of MP data processing system **201** into multiple partitions, and then coordinates execution of multiple (possibly different) operating systems within the multiple partitions. For example, hypervisor **402** may allocate processing unit **200a**, a first region of system memory **118a**, and other resources to a first partition in which operating system **404a** operates. Similarly, hypervisor **402** may allocate processing unit **200n**, a second region of system memory **118n**, and other resources to a second partition in which operating system **404n** operates.

Running under the control of an operating system **404** may be multiple applications **406**, such as a word processor, a spreadsheet, a browser, etc. For example, applications **406a** through **406x** all run under the control of operating system **404a**.

Each operating system **404** and application **406** typically comprise multiple processes. For example, application **406a** is shown having multiple processes **408a** through **408z**. Each processing unit **200** is capable of independently executing a process, assuming that the processing unit **200** has the requisite instructions, data and state information for the process.

INTERRUPT HANDLING

Referring now to **Figures 5a** and **5b**, there is depicted a flowchart of an exemplary method by which a processing unit, such as processing unit **200**, handles an interrupt in accordance with the present invention. As shown at block **502**, an interrupt

- 17 -

is received by the processor. This interrupt may be an exception (e.g., overflow), an external interrupt (e.g., from an I/O device) or an internal interrupt.

Upon receiving the interrupt, the hard architected state (block **504**) and soft state (block **505**) of the currently running process are saved. Details of preferred processes for saving and managing hard and soft states in accordance with the present invention are described below with reference to **Figure 6a** (hard) and **Figure 6b** (soft). After the hard state of the process is saved to memory, at least a First Level Interrupt Handler (FLIH) and Second Level Interrupt Handler (SLIH) are executed to service the interrupt.

The FLIH is a routine that receives control of the processor as a result of an interrupt. Upon notification of an interrupt, the FLIH determines the cause of the interrupt by reading an interrupt controller file. Preferably, this determination is made through the use of a vector register. That is, the FLIH reads a table to match an interrupt with an exception vector address that handles the initial processing of the interrupt.

The SLIH is a interrupt-dependent routine that handles the processing of an interrupt from a specific interrupt source. That is, the FLIH calls the SLIH, which handles the device interrupt, but is not the device driver itself.

In Figure **5a**, steps shown within circle **506** are performed by the FLIH. As illustrated at block **508**, the interrupt is uniquely identified, as described above, preferably using a vector register. This interrupt identification then causes the processor to jump to a particular address in memory, depending on which interrupt is received.

As is well understood by those skilled in the art, any SLIH may establish a communication procedure with an input/output (I/O) device or with another processor (external interrupt), or may execute a set of instructions under the control of the operating system or hypervisor controlling the interrupted

- 18 -

processor. For example, a first interrupt may cause the processor to jump to vector address 1, which results in the execution of SLIH A, as shown in blocks **510** and **516**. As shown, SLIH A completes the handling of the interrupt without calling
5 any additional software routine. Similarly, as illustrated in blocks **512**, **520** and **526**, a branch to vector address 3 results in the execution of exemplary SLIH C, which then executes one or more instructions belonging to the operating system **404** or hypervisor **402** (both shown in **Figure 4**) to service the
10 interrupt. Alternatively, if the interrupt instructs the processor to jump to vector address 2, then exemplary SLIH B is executed, as shown in blocks **514** and **518**. SLIH B then calls (block **524**) a device driver for the device that issued the interrupt.

15 Following any of block **516**, **524** or **526**, the process proceeds through page connector "A" to block **528** of **Figure 5b**. Once the interrupt has been serviced, then the SLIH and FLIH are resolved and re-established to reflect the execution and completion of the interrupt, as shown in blocks **528** and **530**.
20 Thereafter, a next process is loaded and run, as described in blocks **532-536**. The interrupt handling process then terminates.

A choice is made, typically by the operating system of the processor or by the hypervisor of the MP computer system of which the processor is a part, as to which process is run next
25 (block **532**) and on which processor (block **534**) (if in a MP computer system). The selected process may be the process that was interrupted on the present processor, or it may be another process that is new or was interrupted while executing on the present processor or on another processor.

30 As illustrated in block **536**, once the process and processor are selected, that chosen processor is initialized with the state of the next process to be run using the next hard state register **210** shown in **Figure 2**. Next hard state register **210** contains the hard architected state of the next "hottest"
35 process. Usually, this next hottest process is a process that

- 19 -

was previously interrupted, and is now being resumed. Rarely, the next hottest process may be a new process that had not been previously interrupted.

5 The next hottest process is the process that is determined to have the highest priority for execution. Priority may be based on how critical a process is to the overall application, a need for a result from the process, or any other reason for prioritization. As multiple processes are run, priorities of each process waiting to resume often change. Thus, the hard
10 architected states are dynamically assigned updated priority levels. That is, at any given moment, next hard state register **210** contains hard architected state that is continuously and dynamically updated from system memory **118** to contain the next "hottest" process that needs to be run.

15 SAVING HARD ARCHITECTED STATE

In the prior art, the hard architected state is stored to system memory through the load/store unit of the processor core, which blocks execution of the interrupt handler or another process for a number of processor clock cycles. In the present
20 invention, the step of saving a hard state as depicted in block **504** of **Figure 5a** is accelerated according to the method illustrated in **Figure 6a**, which is described with reference to hardware schematically illustrated in **Figure 2**.

Upon receipt of an interrupt, processing unit **200** suspends
25 execution of a currently executing process, as illustrated in block **602**. The hard architected state stored in hard state registers **206** is then copied directly to shadow register **208**, as illustrated in block **604**. (Alternatively, shadow registers **208** already have a copy of the hard architected state through a
30 process of continually updating shadow registers **208** with the current hard architected state.) The shadow copy of the hard architected state, which is preferably non-executable when viewed by the processing unit **200**, is then stored to system memory **118** under the control of IMC **220**, as illustrated at block

- 20 -

606. The shadow copy of the hard architected state is transferred to system memory 118 via high bandwidth memory bus 116. Since storing the copy of the current hard architected state into shadow register 208 takes only a few clock cycles at most, processing unit 200 is quickly able to begin the "real work" of handling the interrupt or executing a next process.

The shadow copy of the hard architected state is preferably stored in a special memory area within system memory 118 that is reserved for hard architected states, as described below with respect to **Figure 10**.

SAVING SOFT STATE

When an interrupt handler is executed by a conventional processor, the soft state of the interrupted process is typically polluted. That is, execution of the interrupt handler software populates the processor's caches, address translation facilities, and history tables with data (including instructions) that are used by the interrupt handler. Thus, when the interrupted process resumes after the interrupt is handled, the process will experience increased instruction and data cache misses, increased translation misses, and increased branch mispredictions. Such misses and mispredictions severely degrade process performance until the information related to interrupt handling is purged from the processor and the caches and other components storing the process' soft state are repopulated with information relating to the process. The present invention therefore saves and restores at least a portion of a process' soft state in order to reduce the performance penalty associated with interrupt handling.

With reference now to **Figure 6b** and corresponding hardware depicted in **Figures 2** and **3a**, the entire contents of L1 I-cache 18 and L1 D-cache 20 are saved to a dedicated region of system memory 118, as illustrated at block 610. Likewise, contents of BHT 35 (block 612), ITLB 115 and DTLB 113 (block 614), ERAT 32

- 21 -

(block **616**), and L2 cache **16** (block **618**) may be saved to system memory **118**.

Because L2 cache **16** may be quite large (e.g., several megabytes in size), storing all of L2 cache **16** may be prohibitive in terms of both its footprint in system memory and the time/bandwidth required to transfer the data. Therefore, in a preferred embodiment, only a subset (e.g., two) of the most recently used (MRU) sets are saved within each congruence class.

It should be understood that although **Figure 6b** illustrates the saving of each of a number of different components of the soft state of a process, the number of these components that is saved and the order in which the components are saved can vary between implementation and can be software programmable or controlled through hardware mode bits.

Thus, the present invention streams out soft states while the interrupt handler routines (or next process) are being executed. This asynchronous operation (independent of execution of the interrupt handlers) may result in an intermingling of soft states (those of the interrupted process and those of the interrupt handler). Nonetheless, such intermingling of data is acceptable because precise preservation of the soft state is not required for architected correctness and because improved performance is achieved due to the shorter delay in executing the interrupt handler.

Referring again to **Figure 2**, soft states from L1 I-cache **18**, L1 D-cache **20**, and L2 cache **16** are transmitted to IMC **220** via cache data path **218**, while other soft states such as BHT **35** are transmitted to IMC **220** via analogous internal data paths (not shown). Alternatively or additionally, in a preferred embodiment, at least some soft state components are transmitted to IMC **220** via scan chain pathway **214**.

SAVING SOFT STATES VIA A SCAN CHAIN PATHWAY

Because of their complexity, processors and other ICs typically include circuitry that facilitates testing of the IC.

- 22 -

The test circuitry includes a boundary scan chain as described in the Institute of Electrical and Electronic Engineers (IEEE) Standard 1149.1-1990, "Standard Test Access Port and Boundary Scan Architecture". The boundary scan chain which is typically
5 accessed through dedicated pins on a packaged integrated circuit, provides a pathway for test data between components of an integrated circuit.

With reference now to **Figure 7**, there is depicted a block in accordance with the diagram of an integrated circuit **700** in
10 accordance with the present invention. Integrated circuit **700** is preferably a processor, such as processing unit of **200** of **Figure 2**. Integrated circuit **700** contains three logical components (logic) **702**, **704** and **706**, which, for purposes of explaining the present invention, comprise three of the memory elements that
15 store the soft state of the process. For example, logic **702** may be L1 D-cache **20** shown in **Figure 3a**, logic **704** may be ERAT **32**, and logic **706** may be a portion of L2 cache **16** as described above.

During manufacturer testing of integrated circuit **700**, a
20 signal is sent through the scan chains boundary cells **708**, which are preferably clock controlled latches. A signal output by scan chain boundary cell **708a** provides a test input to logic **702**, which then outputs a signal to scan chain boundary cells **708b**, which in turn sends the test signal through other logic (**704** and
25 **706**) via other scan chain boundary cells **708** until the signal reaches scan chain boundary **708c**. Thus, there is a domino effect, in which logic **702** - **706** pass the test only if the expected output is received from scan chain boundary cell **708c**.

Historically, the boundary scan chain of an integrated
30 circuit is unused after manufacture. The present invention, however, utilizes the described test pathway as a pathway to transfer the soft architected state to IMC **220** of **Figure 2** in a manner that is non-blocking of cache/register ports. That is,

- 23 -

by using the scan chain test pathway, the soft architected state can be streamed out of the caches/registers while the IH or next process is executing without blocking access to the caches/registers by the next process or interrupt handler.

5 As scan chain **214** is a serial pathway, serial-to-parallel logic **216**, illustrated in **Figure 2**, provides parallel data to ICM **220** for proper transmission of the soft state to system memory **118**. In a preferred embodiment, serial-to-parallel logic **216** also includes logic for both identifying which data is from
10 which register/cache. Such identification may be by any method known to those skilled in the art, including identification of leading identification tags on the serial data, etc. After converting the soft state data to parallel format, IMC **220** then transmits the soft state to system memory **118** via high-bandwidth
15 memory bus **222**.

Note that these same scan chain pathways may be used further to transmit hard architected states such as contained in shadows register **208** depicted in **Figure 2**.

SLIH/FLIH FLASH ROM

20 In prior art systems, First Level Interrupt Handlers (FLIHs) and Second Level Interrupt Handlers (SLIHs) are stored in system memory, and populate the cache memory hierarchy when called. Initially calling a FLIH or SLIH from system memory in a conventional system result in a long access latency (to locate
25 and load the FLIH/SLIH from system memory after a cache miss). Populating cache memory with FLIH/SLIH instructions and data "pollutes" the cache with data and instructions that are not needed by subsequent processes.

To reduce the access latency of FLIHs and SLIHs and to
30 avoid cache pollution, processing unit **200** stores at least some FLIHs and SLIHs in a special on-chip memory (e.g., flash Read Only Memory (ROM) **802**), as depicted in **Figures 3a** and **8a**. FLIHs **804** and SLIHs **806** may be burned into flash ROM **802** at the time of manufacture, or may be burned in after manufacture by

- 24 -

flash programming techniques well known to those skilled in the art. When an interrupt is received by processing unit **200** (depicted in **Figure 2**), the FLIH/SLIH is directly accessed from flash ROM **802** rather than from system memory **118** or cache hierarchy **212**.

SLIH PREDICTION

Normally, when an interrupt occurs in processing unit **200**, a FLIH is called, which then calls a SLIH, which completes the handling of the interrupt. Which SLIH is called and how that SLIH executes varies, and is dependent on a variety of factors including parameters passed, conditions states, etc. For example, in **Figure 8b**, calling FLIH **812** results in the calling and execution of SLIH **814**, which results in executing instructions located at point **B**.

Because program behavior can be repetitive, it is frequently the case that an interrupt will occur multiple times, resulting in the execution of the same FLIH and SLIH (e.g., FLIH **812** and SLIH **814**). Consequently, the present invention recognizes that interrupt handling for subsequent occurrences of an interrupt may be accelerated by predicting that the control graph of the interrupt handling process will be repeated and by speculatively executing portions of the SLIH without first executing the FLIH.

To facilitate interrupt handling prediction, processing unit **200** is equipped with an Interrupt Handler Prediction Table (IHPT) **808**, shown in greater detail in **Figure 8c**. IHPT **808** contains a list of the base addresses **816** (interrupt vectors) of multiple FLIHs. In association with each FLIH address **816**, IHPT **808** stores a respective set of one or more SLIH addresses **818** that have previously been called by the associated FLIH. When IHPT **808** is accessed with the base address for a specific FLIH, prediction logic **820** selects a SLIH address **818** associated with the specified FLIH address **816** in IHPT **808** as the address of the

SLIH that will likely be called by the specified FLIH. Note that while the predicted SLIH address illustrated may be the base address of SLIH **814** as indicated in **Figure 8b**, the address may also be an address of an instruction within SLIH **814** subsequent to the starting point (e.g., at point B).

Prediction logic **820** uses an algorithm that predicts which SLIH will be called by the specified FLIH. In a preferred embodiment, this algorithm picks a SLIH, associated with the specified FLIH, that has been used most recently. In another preferred embodiment, this algorithm picks a SLIH, associated with the specified FLIH, that has historically been called most frequently. In either described preferred embodiment, the algorithm may be run upon a request for the predicted SLIH, or the predicted SLIH may be continuously updated and stored in IHPT **808**.

It is significant to note that the present invention is different from branch prediction methods known in the art. First, the method described above results in a jump to a specific interrupt handler, and is not based on a branch instruction address. That is, branch prediction methods used in the prior art predict the outcome of a branch operation, while the present invention predicts a jump to a specific interrupt handler based on a (possibly) non-branch instruction. This leads to a second difference, which is that a greater amount of code can be skipped by interrupt handler prediction as taught by the present invention as compared to prior art branch prediction, because the present invention allows bypassing any number of instructions (such as in the FLIH), while a branch prediction permits bypassing only a limited number of instructions before the predicted branch due to inherent limitations in the size of the instruction window that can be scanned by a conventional branch prediction mechanism. Third, interrupt handler prediction in accordance with the present invention is not constrained to a binary determination as are the taken/not taken branch predictions known in the prior art. Thus, referring again to

- 26 -

Figure 8c, prediction logic **820** may choose predicted SLIH address **822** from any number of historical SLIH addresses **818**, while a branch prediction scheme chooses among only a sequential execution path and a branch path.

5 Reference is now made to **Figure 9**, which illustrates a flowchart of an exemplary method of predicting an interrupt handler in accordance with the present invention. When an interrupt is received by a processor (block **902**), concurrent execution by simultaneous multithreading (SMT) begins on both
10 the FLIH called by the interrupt (block **904**) as well as a predicted SLIH (block **906**) indicated by IHPT **808** based upon prior execution history.

 In a preferred embodiment, jumping to the predicted SLIH (block **906**) may be performed in response to monitoring, upon
15 receipt of an interrupt, the called FLIH. For example, refer again to IHPT **808**, shown in **Figure 8**. When the interrupt is received, the FLIH is compared to FLIH addresses **816** stored in IHPT **808**. If a comparison of the stored FLIH addresses **816** in IHPT **808** reveals the same FLIH address called by the interrupt,
20 then IHPT **808** provides the predicted SLIH address **822**, and code execution starting at the address of the predicted SLIH address **822** immediately begins.

 Subsequent comparison of the known correct SLIH and the predicted SLIH is preferably performed by storing the predicted
25 SLIH address **822**, that was called using IHPT **808**, in a SLIH prediction register containing FLIH addresses with a prediction flag. In a preferred embodiment of the present invention, when a instruction known to call a SLIH from the FLIH, such as a "jump" instruction, is executed, the address called by the jump is
30 compared with address of the predicted SLIH address **822** located in the prediction register (and identified as having been predicted and currently executing by the prediction flag). The predicted SLIH address **822** from the prediction register and the SLIH selected to by the executing FLIH are compared (block **910**).

- 27 -

If the correct SLIH was predicted, then the predicted SLIH completes execution (block **914**), thus accelerating interrupt handling. If, however, the SLIH was mispredicted, then further execution of the predicted SLIH is cancelled, and the correct
5 SLIH is execution instead (block **916**).

STATE MANAGEMENT

Referring now to **Figure 10**, there is depicted a conceptual diagram that graphically illustrates the logical relationship between hard and soft states stored in system memory and various
10 processors and memory partitions of an exemplary MP data processing system. As shown in **Figure 10**, all hard architected states and soft states are stored in a special memory region allocated by hypervisor **402** that is accessible by processors within any partition. That is, Processor A and Processor B may
15 initially be configured by hypervisor **402** to function as an SMP within Partition X, while Processor C and Processor D are configured as an SMP within Partition Y. While executing, processors A-D may be interrupted, causing each of processors A-D to store a respective one of hard states A-D and soft states
20 A-D to memory in the manner discussed above. Unlike prior art systems that do not permit processors in different partitions to access the same memory space, any processor can access any of hard or soft states A-D to resume the associated interrupted process. For example, in addition to hard and soft states C and
25 D, which were created within its partition, Processor D can also access hard and soft states A and B. Thus, any process state can be accessed by any partition or processor(s). Consequently, hypervisor **402** has great freedom and flexibility in load balancing between partitions.

30 SOFT STATE CACHE COHERENCY

As discussed above, soft states of interrupted processes may include the contents of cache memory, such as L1 I-cache **18**, L2 D-cache **20** and L2 cache **16** illustrated in **Figure 3a**. While

these soft states are stored in system memory, as described above with reference to **Figure 6b**, it is likely that at least some of the data comprising the soft states will become stale due to data modifications made by other processes. The present invention therefore provides a mechanism to keep the soft states stored in system memory cache coherent.

As illustrated in **Figure 11**, the soft states stored in system memory **118** can be conceptualized as being stored in "virtual caches". For example, the soft state of L2 cache **16** is in L2 virtual cache **1102**. L2 virtual cache comprises an address portion including the tag **1104** and index **1106** of each cache line of data **1110** saved from L2 cache **16**. Similarly, L1 virtual I-cache **1112** comprises an address portion including the tag **1114** and index **1116**, of instructions **1120** saved from L1 I-cache **18**, and L1 virtual D-cache **1122** comprises an address portion, including a tag **1124** and index **1126** of each cache line of data **1130** saved from L1 D-cache **20**. Each of these "virtual caches" is managed via interconnect **222** by integrated memory controller (IMC) **220** to maintain coherency.

IMC **220** snoops each operation on system interconnect **222**. Whenever an operation is snooped that may require the invalidation of a cache line, IMC **220** snoops the operation against virtual cache directories **1132**. If a snoop hit is detected, IMC **220** invalidates the virtual cache line in system memory **118** by updating the appropriate virtual cache directory. Although it is possible to require exact address matches for snoop invalidates (i.e., matches of both tag and index), implementing a precise address match would require a large amount of circuitry in IMC **220** (particularly for 64-bit and larger addresses). Accordingly, in a preferred embodiment, snoop invalidations are imprecise, and all virtual cache lines having selected most significant bits (MSBs) matching the snooped address are invalidated. Which MSBs are used to determine which cache lines are invalidated in the virtual cache memories is

implementation-specific and may be software-controllable or hardware controllable via mode bits. Thus, addresses may be snooped against the tag or only a portion of the tag (such as the 10 most significant bits). Such an invalidation scheme of the virtual cache memory has an admitted disadvantage of invalidating cache lines that still contain valid data, but this disadvantage is outweighed by the performance advantage achieved by providing a very fast method of maintaining coherency of virtual cache lines.

10 MANUFACTURING LEVEL TEST

During manufacturing, integrated circuits are subjected to a battery of tests under a variety of operating conditions. One such test is a data test in which the internal gates of the integrated circuit are all tested with a test data stream using the IEEE 1149.1 test scan chain described above. In the prior art, after installation of the integrated circuit in an operating environment such test programs are not run again, in part because it is impractical in most operating environments to connect the integrated circuit to a test fixture to perform the test and because such testing prevents use of the integrated circuit for its intended purpose. For example, in processor 100 the hard architected state must be saved to and restored from system memory via the load/store execution path, preventing the accomplishment of substantive work during testing and introducing significant latency.

Using the hard architected state storage method described above, however, a processor can run a manufacturing-level test program routinely while the processor is installed in a normal operating environment (e.g., a computer system) since the time to save and restore the hard architected state is very short, preferably just a few clock cycles.

With reference now to **Figure 12**, there is depicted a flow-chart of an exemplary method of manufacturing-level test program in accordance with the present invention. Test programs

- 30 -

are preferably run periodically. Thus, as depicted in blocks **1202** and **1204**, upon passage of a predetermined amount of time, an interrupt is initiated in the processor (block **1206**). As with any interrupt using the present invention, when the test program
5 begins running and issues the interrupt, the hard architected state of the currently executing process is immediately saved (generally within 2-3 clock cycles), using the preferred method described above for saving hard architected states, as depicted in block **1208**. Concurrently, at least a portion of the soft
10 state for the currently executing process is saved (block **1210**), preferably in a manner described above in **Figure 6b**.

The hard architected state for the manufacturing test program is optionally loaded into the processor, as described in block **1212**. In a preferred embodiment of the present invention,
15 the manufacturing-level test program is loaded from a manufacturing-level test program(s) **810** loaded from flash ROM **802**, depicted in **Figure 8a**. Manufacturing-level test program(s) **810** may be burned into flash ROM **802** when processing unit **200** is first manufactured, or the manufacturing-level test program(s)
20 **810** may be burned in subsequently. If multiple manufacturing-level test programs are stored in flash ROM **802**, then one of the manufacturing-level test programs is selected for execution. In a preferred embodiment of with the present invention, the manufacturing-level test program is run each time
25 a timer interrupt is executed, as described above for blocks **1202** and **1204**.

As soon as the hard architected state is loaded into the processor, the manufacturing level test program begins to run (block **1214**), preferably using the IEEE 1149.1 test scan chain
30 described above. Concurrently, the soft architected states flow into the processor (block **1216**), preferably in the manner described above for soft state updating (**Figure 6b**). Upon completion of the execution of the manufacturing level test program, the interrupt is complete, and a next process is

executed by loading the hard architected state and soft states for that process (block **1218**).

As the loading of the hard architected states require only a few clock cycles, the manufacturing level test program can be
5 run as often as the designer wishes, within the constraints of the time required to execute the test program itself. The execution of the manufacturing test program can be initiated by the user, the operating system, or the hypervisor.

Thus, the present invention provides a method and system to
10 address, among other matters, the problem of latency associated with interrupts. For example, in the prior art, if the interrupt handler is a process that is infrequently called, then typically there is a long latency as lower cache levels, and even system memory, are searched for the appropriate interrupt handler.
15 When the interrupt handler is executing, it populates the processor's cache hierarchy with instructions/data needed to handle the interrupt, thus "polluting" the cache hierarchy when the interrupted process is restored for execution. The present invention solves these problems utilizing the inventive
20 processes described herein.

Although aspects of the present invention have been described with respect to a computer processor and software, it should be understood that at least some aspects of the present invention may alternatively be implemented as a program product
25 for use with a data storage system or computer system. Programs defining functions of the present invention can be delivered to a data storage system or computer system via a variety of signal-bearing media, which include, without limitation, non-writable storage media (e.g. CD-ROM), writable storage media
30 (e.g. a floppy diskette, hard disk drive, read/write CD-ROM, optical media), and communication media, such as computer and telephone networks including Ethernet. It should be understood, therefore, that such signal-bearing media, when carrying or encoding computer readable instructions that direct method
35 functions of the present invention, represent alternative

embodiments of the present invention. Further, it is understood that the present invention may be implemented by a system having means in the form of hardware, software, or a combination of software and hardware as described herein or their equivalent.

5 While the invention has been particularly shown and described with reference to a preferred embodiment, it will be understood by those skilled in the art that various changes in form and detail may be made therein without departing from the spirit and scope of the invention.

- 33 -

CLAIMS

What is claimed is:

1. A method of operating a processor, said method comprising:
 - storing in a first set of storage locations in the processor a first hard architected state of a first process currently undergoing execution by the processor, wherein said first hard architected state represents one of multiple states encountered during execution of said first process;
 - storing in a second set of storage locations in the processor a second hard architected state of a second process that is idle, wherein said second hard architected state represents one of multiple states encountered during execution of said second process;
 - storing a shadow copy of the first hard architected state within the processor to a set of shadow registers, wherein the shadow copy is non-executable by the processor;
 - in response to receiving a process interrupt at the processor,
 - storing the shadow copy of the first hard architected state in a system memory through the use of an Integrated Memory Controller (ICM), thereby bypassing a load/store unit (LSU) in the processor, and
 - loading the second hard architected state from the second set of storage locations into the first set of storage locations; and
 - executing the second process.

2. The method of claim 1, further comprising dynamically replacing the second hard architected state with a third

AUS9-2002-0164CA1

- 34 -

architected state of another idle process while the first process is executing.

3. The method of claim 1, further comprising: selecting the second process, from a pool of idle processes, for storage of the second hard architected state into the processor, based on a priority of said second process.

4. The method of claim 1, further comprising: saving the first hard architected state in response to receiving the process interrupt.

5. A processor comprising:

means for storing in a first set of storage location in the processor a first hard architected state of a first process currently undergoing execution by the processor, wherein said first hard architected state represents one of multiple states encountered during execution of said first process;

means for storing in a second set of storage locations in the processor a second hard architected state of a second process that is idle, wherein said second hard architected state represents one of multiple states encountered during execution of said second process;

means for storing a non-executable shadow copy of the first hard architected state;

means, responsive to receiving a process interrupt at the processor, for:

storing the non-executable shadow copy of the first hard architected state in a system memory through the use of an Integrated Memory Controller (IMC), thereby bypassing a load/store unit (LSU) in the processor, and

- 35 -

loading to second hard architected state from the second set of storage locations into the first set of storage locations; and
means for executing the second process.

6. The processor of claim 5, further comprising means for dynamically replacing the second hard architected state with a third architected state of another idle process while the first process is executing.

7. The processor of claim 5, further comprising:
means for selecting the second process, from a pool of idle processes, for storage in the processor, based on a priority of said second process.

8. The processor of claim 5, further comprising:
means for saving the first hard architected state in response to receiving the process interrupt.

9. The method of claim 1, wherein the hard architected states comprise the contents of a Condition Register (CRR), a Link and Count Register (LCR), a General Purpose Register (GPR), a Floating Point Register (FPR), and a Supervisor Level Register (SLR) in a core of the processor.

10. The method of claim 1, wherein the shadow copy of the first hard architected state is stored in the set of shadow registers contemporaneously with a storing of the first hard architected state in a core of the processor.

- 36 -

11. The processor of claim 5, wherein the hard architected states comprise the contents of a Condition Register (CRR), a Link and Count Register (LCR), a General Purpose Register (GPR), a floating Point Register (FPR), and a Supervisor Level Register (SLR) in a core of the processor.

AUS9-2002-0164CA1

1/15





Fig. 1
Prior Art

Fig. 2



3/15





Fig. 3a

4/15

51

*Fig. 36*






Fig. 4



6/15

*Fig. 5a*

7/15

*Fig. 56*

8/15

*Fig. 6a**Fig. 6b*

9/15






Fig. 7

10/15

*Fig. 8a*

11/15







Fig. 8c

12/15

*Fig. 9*


13/15

*Fig. 10*



15/15

Fig. 12



201

Processing Unit
200 a

Registers for
next process
hard state
210

Registers for
current process
hard state
206

Shadow Registers
208

ISU
202

EU
204

Serial to
Parallel
Interface
216

Cache
Hierarchy
212

IMC
220

System
Memory
118 a

Processing
Unit
200 n

System
Memory
118 n

...

222

214

218

116

