



HU000025019T2

(19) **HU****MAGYARORSZÁG**
Szellemi Tulajdon Nemzeti Hivatala(11) Lajstromszám: **E 025 019**(13) **T2****EURÓPAI SZABADALOM**
SZÖVEGÉNEK FORDÍTÁSA(21) Magyar ügyszám: **E 09 792741**(22) A bejelentés napja: **2009. 09. 18.**(51) Int. Cl.: **H04B 7/06** (2006.01)**H04B 7/08** (2006.01)**H04L 5/00** (2006.01)

(96) Az európai bejelentés bejelentési száma:

EP 20090792741

(97) Az európai bejelentés közzétételi adatai:

EP 2345175 A2 **2010. 03. 25.**

(86) A nemzetközi (PCT) bejelentési szám:

PCT/US 09/057581

(97) Az európai szabadalom megadásának meghirdetési adatai:

EP 2345175 B1 **2015. 04. 08.**

(87) A nemzetközi közzétételi szám:

WO 10033869

(30) Elsőbbségi adatok:

98738 P **2008. 09. 19.** **US****108800 P** **2008. 10. 27.** **US****561984** **2009. 09. 17.** **US**

(73) Jogosult(ak):

QUALCOMM Incorporated, San Diego,
California 92121 (US)

(72) Feltaláló(k):

MONTOJO, Juan, San Diego, California 92121 (US)**PALANKI, Ravi, San Diego, California 92121 (US)****FARAJIDANA, Amir, San Diego, California 92121 (US)****BHATTAD, Kapil, San Diego, California 92121 (US)**

(74) Képviselő:

Sipos József, DANUBIA Szabadalmi és Jogi
Iroda Kft., Budapest

(54)

Referenciajel kialakítás LTE-Advanced mobiladatátvitelhez

Az európai szabadalom ellen, megadásának az Európai Szabadalmi Közlönyben való meghirdetésétől számított kilenc hónapon belül, felszólalást lehet benyújtani az Európai Szabadalmi Hivatalnál. (Európai Szabadalmi Egyezmény 99. cikk(1))

A fordítást a szabadalmas az 1995. évi XXXIII. törvény 84/H. §-a szerint nyújtotta be. A fordítás tartalmi helyességét a Szellemi Tulajdon Nemzeti Hivatala nem vizsgálta.



(11) **EP 2 345 175 B1**

(12) **EUROPEAN PATENT SPECIFICATION**

(45) Date of publication and mention
of the grant of the patent:
08.04.2015 Bulletin 2015/15

(51) Int Cl.:
H04B 7/06 ^(2006.01) **H04L 5/00** ^(2006.01)
H04B 7/08 ^(2006.01)

(21) Application number: **09792741.2**

(86) International application number:
PCT/US2009/057581

(22) Date of filing: **18.09.2009**

(87) International publication number:
WO 2010/033869 (25.03.2010 Gazette 2010/12)

(54) **REFERENCE SIGNAL DESIGN FOR LTE-ADVANCED**

REFERENZSIGNALGESTALTUNG FÜR LTE-ADVANCED

CONFIGURATION DU SIGNAL DE RÉFÉRENCE POUR LTE-ADVANCED

(84) Designated Contracting States:
**AT BE BG CH CY CZ DE DK EE ES FI FR GB GR
HR HU IE IS IT LI LT LU LV MC MK MT NL NO PL
PT RO SE SI SK SM TR**

(30) Priority: **19.09.2008 US 98738 P**
27.10.2008 US 108800 P
17.09.2009 US 561984

(43) Date of publication of application:
20.07.2011 Bulletin 2011/29

(73) Proprietor: **QUALCOMM Incorporated**
San Diego, California 92121 (US)

(72) Inventors:
• **MONTOJO, Juan**
San Diego, California 92121 (US)
• **PALANKI, Ravi**
San Diego, California 92121 (US)
• **FARAJIDANA, Amir**
San Diego, California 92121 (US)
• **BHATTAD, Kapil**
San Diego, California 92121 (US)

(74) Representative: **Howe, Steven**
Reddie & Grose LLP
16 Theobalds Road
London WC1X 8PL (GB)

(56) References cited:
WO-A-2008/103805

- **MOTOROLA: "Downlink Multiple Antenna Schemes for LTE-Advanced" 3GPP DRAFT; R1-083228 LTE-A DL MIMO MOTOROLA, 3RD GENERATION PARTNERSHIP PROJECT (3GPP), MOBILE COMPETENCE CENTRE ; 650, ROUTE DES LUCIOLES ; F-06921 SOPHIA-ANTIPOLIS CEDEX ; FRANCE, no. Jeju; 20080812, 12 August 2008 (2008-08-12), XP050316642**
- **MOTOROLA: "Common Reference Symbol Mapping/Signaling for 8 Transmit Antennas" 3GPP DRAFT; R1-083224 - 8 CRS TECHNIQUES, 3RD GENERATION PARTNERSHIP PROJECT (3GPP), MOBILE COMPETENCE CENTRE ; 650, ROUTE DES LUCIOLES ; F-06921 SOPHIA-ANTIPOLIS CEDEX ; FRANCE, no. Jeju; 20080812, 12 August 2008 (2008-08-12), XP050316638**

Note: Within nine months of the publication of the mention of the grant of the European patent in the European Patent Bulletin, any person may give notice to the European Patent Office of opposition to that patent, in accordance with the Implementing Regulations. Notice of opposition shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

EP 2 345 175 B1

Description

BACKGROUND

I. Field

[0001] The following description relates generally to wireless communications, and more particularly to reference signal design to support legacy user equipment in LTE A.

II. Background

[0002] Wireless communication systems are widely deployed to provide various types of communication; for instance, voice and/or data can be provided *via* such wireless communication systems. A typical wireless communication system, or network, can provide multiple users access to one or more shared resources (e.g., bandwidth, transmit power, ...). For instance, a system can use a variety of multiple access techniques such as Frequency Division Multiplexing (FDM), Time Division Multiplexing (TDM), Code Division Multiplexing (CDM), Orthogonal Frequency Division Multiplexing (OFDM), and others.

[0003] Generally, wireless multiple-access communication systems can simultaneously support communication for multiple mobile devices. Each mobile device can communicate with one or more base stations *via* transmissions on forward and reverse links. The forward link (or downlink) refers to the communication link from base stations to mobile devices, and the reverse link (or uplink) refers to the communication link from mobile devices to base stations.

[0004] Wireless communication systems oftentimes employ one or more base stations that provide a coverage area. A typical base station can transmit multiple data streams for broadcast, multicast and/or unicast services, wherein a data stream may be a stream of data that can be of independent reception interest to a mobile device. A mobile device within the coverage area of such base station can be employed to receive one, more than one, or all the data streams carried by the composite stream. Likewise, a mobile device can transmit data to the base station or another mobile device.

[0005] Having multiple transmit antennas in wireless systems helps in getting transmit diversity and/or higher data rate. Transmit diversity relates to the performance improvement obtained when a signal is sent multiple times over different transmit antennas. The key idea is that, when the channel gains from different transmit antennas are independent, the chances of the channel gain from different transmit antennas to the user equipments (UEs) being small simultaneously decreases exponentially as the number of transmit antennas is increased. Probability of failure in this case is approximately p^{N_t} where p is the probability of failure when only one transmit antenna is used and N_t is the number of transmit anten-

nas used. On the other hand if the signal was sent from the same antenna multiple times, if the channel was bad in the first instance, it is likely to be bad for the remaining transmissions and hence the probability of failure continues to be equal to p (approximately). R1-083228, entitled Downlink Multiple Antenna Schemes for LTE-Advanced, Motorola, August 18-22 2008, describes eNodeB transmit configurations with 8 transmit antennas for specific sub frames while still allowing backwards compatibility with release-8 User Equipment. For example, an antenna virtualization scheme can be exploited to make 8 antennas be seen as 4 at the User Equipment, for example, by forming 4 pairs of antennas and using a Cyclic Delay Diversity scheme to combine pairs of antennas.

SUMMARY

[0006] The invention is defined in the appended claims to which reference should now be made. The following presents a simplified summary of one or more examples in order to provide a basic understanding of such examples. This summary is not an extensive overview of all contemplated examples and is intended to neither identify key or critical elements of all examples nor delineate the scope of any or all examples. Its sole purpose is to present some concepts of one or more examples in a simplified form as a prelude to the more detailed description that is presented later.

[0007] According to related aspects, a method that facilitates optimizing Long Term Evolution Advance (LTE A). The method can include identifying at least two groups of user equipment (UEs). Further, the method can include signaling a different number of antennas ports to the least two group of UEs. Moreover, the method can comprise creating antenna ports corresponding to each group of UEs, wherein each antenna port includes a subset of a number of physical transmit antennas and the number of antenna ports is the number of signaled antenna ports to that group of UEs.

[0008] Another aspect relates to a wireless communications apparatus. The wireless communications apparatus can include at least one processor configured to identify at least two groups of user equipment (UEs), signal a different number of antennas ports to the least two group of UEs, and create antenna ports corresponding to each group of UEs, wherein each antenna port includes a subset of a number of physical transmit antennas and the number of antenna ports is the number of signaled antenna ports to that group of UEs. Further, the wireless communications apparatus can include memory coupled to the at least one processor.

[0009] Yet another aspect relates to a wireless communications apparatus that optimizes configuration of transmit antennas. The wireless communications apparatus can include means for identifying at least two groups of user equipment (UEs). Additionally, the wireless communications apparatus can comprise means for signaling a different number of antennas ports to the least

two group of UEs. Further, the wireless communications apparatus can comprise means for creating antenna ports corresponding to each group of UEs, wherein each antenna port includes a subset of a number of physical transmit antennas and the number of antenna ports is the number of signaled antenna ports to that group of UEs.

[0010] Still another aspect relates to a computer program product comprising a computer-readable medium having stored thereon code causing at least one computer to identify at least two groups of user equipment (UEs), signal a different number of antennas ports to the least two group of UEs, and create antenna ports corresponding to each group of UEs, wherein each antenna port includes a subset of a number of physical transmit antennas and the number of antenna ports is the number of signaled antenna ports to that group of UEs.

[0011] According to other aspects, a method that facilitates identifying a set of antenna ports. The method can comprise receiving a mapping information that includes at least one of a delay and a linear combination employed to transmit a reference signal related to the set of antenna ports. Further, the method can comprise receiving a reference signal related to the antenna ports. Moreover, the method can include decoding the reference signal related to the set in order to identify each antenna port, wherein the decoding utilizes the mapping information.

[0012] Another aspect relates to a wireless communications apparatus. The wireless communications apparatus can include at least one processor configured to receive a mapping information that includes at least one of a delay and a linear combination employed to transmit a reference signal related to the set of antenna ports, receive a reference signal related to the antenna ports, and decode the reference signal related to the set in order to identify each antenna port, wherein the decoding utilizes the mapping information. Further, the wireless communications apparatus can include memory coupled to the at least one processor.

[0013] Another aspect relates to a wireless communications apparatus that identifies a set of antenna ports within a wireless communications environment. The wireless communications apparatus can comprise means for receiving a mapping information that includes at least one of a delay and a linear combination employed to transmit a reference signal related to the set of antenna ports. Moreover, the wireless communications apparatus can comprise means for receiving a reference signal related to the antenna ports. Further, the wireless communications apparatus can include means for decoding the reference signal related to the set in order to identify each antenna port, wherein the decoding utilizes the mapping information.

[0014] Still another aspect relates to a computer program product comprising a computer-readable medium having stored thereon code for causing at least one computer to receive a mapping information that includes at least one of a delay and a linear combination employed

to transmit a reference signal related to the set of antenna ports, receive a reference signal related to the antenna ports, and decode the reference signal related to the set in order to identify each antenna port, wherein the decoding utilizes the mapping information.

[0015] According to other aspects, a method can be used within a wireless environment. The method can comprise utilizing a transmitted reference signal for antenna ports of a first group of UEs for at least one of a measurement, a feedback to a base station, or a demodulation technique. Further, the method can comprise utilizing a transmitted reference signals for antenna ports of a second group of UEs for a measurement and a feedback to a base station.

[0016] Another aspect relates to a wireless communications apparatus. The wireless communications apparatus can include at least one processor configured to utilize a transmitted reference signal for antenna ports of a first group of UEs for at least one of a measurement, a feedback to a base station, or a demodulation technique, and utilize a transmitted reference signals for antenna ports of a second group of UEs for a measurement and a feedback to a base station. Further, the wireless communications apparatus can include memory coupled to the at least one processor.

[0017] Another aspect relates to a wireless communications apparatus. The wireless communications apparatus can comprise means for utilizing a transmitted reference signal for antenna ports of a first group of UEs for at least one of a measurement, a feedback to a base station, or a demodulation technique. Moreover, the wireless communications apparatus can comprise means for utilizing a transmitted reference signals for antenna ports of a second group of UEs for a measurement and a feedback to a base station.

[0018] Still another aspect relates to a computer program product comprising a computer-readable medium having stored thereon code for causing at least one computer to utilize a transmitted reference signal for antenna ports of a first group of UEs for at least one of a measurement, a feedback to a base station, or a demodulation technique, and utilize a transmitted reference signals for antenna ports of a second group of UEs for a measurement and a feedback to a base station.

[0019] According to other aspects, a method can be used within a wireless environment. The method can comprise identifying at least two groups of user equipment (UEs). Further, the method can comprise creating UE specific antenna ports corresponding to a specific group of UEs. The method can comprise transmitting at least one reference signal related to the UE specific antenna ports in the Physical Downlink Shared Channel (PDSCH) region assigned to at least one specific group of UEs. The method can further comprise employing the UE specific antenna ports along with respective antenna ports defined for a disparate group of UEs to create beams for transmitting PDSCH to the specific group of UEs. The method can include estimating a channel from

the antenna ports based on at least one of the following: a reference signal related to at least one of the UE specific antenna ports or a disparate antenna port; or a mapping information that relates the reference signals to a beam direction used for transmission of PDSCH..

[0020] Another aspect relates to a wireless communications apparatus. The wireless communications apparatus can include at least one processor configured to identify at least two groups of user equipment (UEs), create UE specific antenna ports corresponding to a specific group of UEs, transmit at least one reference signal related to the UE specific antenna ports in the Physical Downlink Shared Channel (PDSCH) region assigned to at least one specific group of UEs, employ the UE specific antenna ports along with respective antenna ports defined for a disparate group of UEs to create beams for transmitting PDSCH to the specific group of UEs, estimate a channel from the antenna ports based on at least one of the following: a reference signal related to at least one of the UE specific antenna ports or a disparate antenna port; or a mapping information that relates the reference signals to a beam direction used for transmission of PDSCH. Further, the wireless communications apparatus can include memory coupled to the at least one processor.

[0021] Another aspect relates to a wireless communications apparatus. The wireless communications apparatus can comprise means for creating UE specific antenna ports corresponding to a specific group of UEs. Moreover, the wireless communications apparatus can comprise means for creating UE specific antenna ports corresponding to a specific group of UEs. Further, the wireless communications apparatus can include means for transmitting at least one reference signal related to the UE specific antenna ports in the Physical Downlink Shared Channel (PDSCH) region assigned to at least one specific group of UEs. Additionally, the wireless communications apparatus can comprise means for employing the UE specific antenna ports along with respective antenna ports defined for a disparate group of UEs to create beams for transmitting PDSCH to the specific group of UEs. Furthermore, the wireless communications apparatus can comprise means for estimating a channel from the antenna ports based on at least one of the following: a reference signal related to at least one of the UE specific antenna ports or a disparate antenna port; or a mapping information that relates the reference signals to a beam direction used for transmission of PDSCH.

[0022] Still another aspect relates to a computer program product comprising a computer-readable medium having stored thereon code for causing at least one computer to identify at least two groups of user equipment (UEs), create UE specific antenna ports corresponding to a specific group of UEs, transmit at least one reference signal related to the UE specific antenna ports in the Physical Downlink Shared Channel (PDSCH) region assigned to at least one specific group of UEs, employ the UE specific antenna ports along with respective antenna

ports defined for a disparate group of UEs to create beams for transmitting PDSCH to the specific group of UEs, estimate a channel from the antenna ports based on at least one of the following: a reference signal related to at least one of the UE specific antenna ports or a disparate antenna port; or a mapping information that relates the reference signals to a beam direction used for transmission of PDSCH.

[0023] To the accomplishment of the foregoing and related ends, the one or more embodiments comprise the features hereinafter fully described and particularly pointed out in the claims. The following description and the annexed drawings set forth in detail certain illustrative aspects of the one or more embodiments. These aspects are indicative, however, of but a few of the various ways in which the principles of various embodiments can be employed and the described embodiments are intended to include all such aspects and their equivalents.

BRIEF DESCRIPTION OF THE DRAWINGS

[0024]

FIG. 1 is an illustration of a wireless communication system in accordance with various aspects set forth herein.

FIG. 2 is an illustration of an example communications apparatus for employment within a wireless communications environment.

FIG. 3 is an illustration of an example wireless communications system that facilitates grouping transmit antennas to optimize legacy user equipment (UE).

FIG. 4 is an illustration of an example system that facilitates organizing transmit antenna.

FIG. 5 is an illustration of an example methodology that facilitates optimizing Long Term Evolution Advance (LTE A).

FIG. 6 is an illustration of an example methodology that facilitates identifying transmit antenna.

FIG. 7 is an illustration of an example mobile device that facilitates creating transmit antenna groups in a wireless communication system.

FIG. 8 is an illustration of an example system that facilitates enhancing transmit antenna utilization in a wireless communication environment.

FIG. 9 is an illustration of an example wireless network environment that can be employed in conjunction with the various systems and methods described herein.

FIG. 10 is an illustration of an example system that facilitates optimizing Long Term Evolution Advance (LTE A).

FIG. 11 is an illustration of an example system that facilitates identifying transmit antenna in a wireless communication environment.

DETAILED DESCRIPTION

[0025] Various embodiments are now described with reference to the drawings, wherein like reference numerals are used to refer to like elements throughout. In the following description, for purposes of explanation, numerous specific details are set forth in order to provide a thorough understanding of one or more embodiments. It may be evident, however, that such embodiment(s) may be practiced without these specific details. In other instances, well-known structures and devices are shown in block diagram form in order to facilitate describing one or more embodiments.

[0026] As used in this application, the terms "module," "carrier," "system," and the like are intended to refer to a computer-related entity, either hardware, firmware, a combination of hardware and software, software, or software in execution. For example, a component can be, but is not limited to being, a process running on a processor, a processor, an object, an executable, a thread of execution, a program, and/or a computer. By way of illustration, both an application running on a computing device and the computing device can be a component. One or more components can reside within a process and/or thread of execution and a component can be localized on one computer and/or distributed between two or more computers. In addition, these components can execute from various computer readable media having various data structures stored thereon. The components can communicate by way of local and/or remote processes such as in accordance with a signal having one or more data packets (*e.g.*, data from one component interacting with another component in a local system, distributed system, and/or across a network such as the Internet with other systems by way of the signal).

[0027] The techniques described herein can be used for various wireless communication systems such as code division multiple access (CDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal frequency division multiple access (OFDMA), single carrier-frequency division multiple access (SC-FDMA) and other systems. The terms "system" and "network" are often used interchangeably. A CDMA system can implement a radio technology such as Universal Terrestrial Radio Access (UTRA), CDMA2000, *etc.* UTRA includes Wideband-CDMA (W-CDMA) and other variants of CDMA. CDMA2000 covers IS-2000, IS-95 and IS-856 standards. A TDMA system can implement a radio technology such as Global System for Mobile Communications (GSM). An OFDMA system can implement a radio technology such as Evolved UTRA (E-UTRA), Ultra Mobile Broadband (UMB), IEEE 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), IEEE 802.20, Flash-OFDM, *etc.* UTRA and E-UTRA are part of Universal Mobile Telecommunication System (UMTS). 3GPP Long Term Evolution (LTE) is an upcoming release of UMTS that uses E-UTRA, which employs OFDMA on the downlink and SC-FDMA on the uplink.

[0028] Single carrier frequency division multiple access (SC-FDMA) utilizes single carrier modulation and frequency domain equalization. SC-FDMA has similar performance and essentially the same overall complexity as those of an OFDMA system. A SC-FDMA signal has lower peak-to-average power ratio (PAPR) because of its inherent single carrier structure. SC-FDMA can be used, for instance, in uplink communications where lower PAPR greatly benefits access terminals in terms of transmit power efficiency. Accordingly, SC-FDMA can be implemented as an uplink multiple access scheme in 3GPP Long Term Evolution (LTE) or Evolved UTRA.

[0029] Furthermore, various embodiments are described herein in connection with a mobile device. A mobile device can also be called a system, subscriber unit, subscriber station, mobile station, mobile, remote station, remote terminal, access terminal, user terminal, terminal, wireless communication device, user agent, user device, or user equipment (UE). A mobile device can be a cellular telephone, a cordless telephone, a Session Initiation Protocol (SIP) phone, a wireless local loop (WLL) station, a personal digital assistant (PDA), a handheld device having wireless connection capability, computing device, or other processing device connected to a wireless modem. Moreover, various embodiments are described herein in connection with a base station. A base station can be utilized for communicating with mobile device(s) and can also be referred to as an access point, Node B, or some other terminology.

[0030] Moreover, various aspects or features described herein can be implemented as a method, apparatus, or article of manufacture using standard programming and/or engineering techniques. The term "article of manufacture" as used herein is intended to encompass a computer program accessible from any computer-readable device, carrier, or media. For example, computer-readable media can include but are not limited to magnetic storage devices (*e.g.*, hard disk, floppy disk, magnetic strips, *etc.*), optical disks (*e.g.*, compact disk (CD), digital versatile disk (DVD), *etc.*), smart cards, and flash memory devices (*e.g.*, EPROM, card, stick, key drive, *etc.*). Additionally, various storage media described herein can represent one or more devices and/or other machine-readable media for storing information. The term "machine-readable medium" can include, without being limited to, wireless channels and various other media capable of storing, containing, and/or carrying instruction(s) and/or data.

[0031] Referring now to **Fig. 1**, a wireless communication system 100 is illustrated in accordance with various embodiments presented herein. System 100 comprises a base station 102 that can include multiple antenna groups. For example, one antenna group can include antennas 104 and 106, another group can comprise antennas 108 and 110, and an additional group can include antennas 112 and 114. Two antennas are illustrated for each antenna group; however, more or fewer antennas can be utilized for each group. Base station 102 can ad-

ditionally include a transmitter chain and a receiver chain, each of which can in turn comprise a plurality of components associated with signal transmission and reception (e.g., processors, modulators, multiplexers, demodulators, demultiplexers, antennas, etc.), as will be appreciated by one skilled in the art.

[0032] Base station 102 can communicate with one or more mobile devices such as mobile device 116 and mobile device 122; however, it is to be appreciated that base station 102 can communicate with substantially any number of mobile devices similar to mobile devices 116 and 122. Mobile devices 116 and 122 can be, for example, cellular phones, smart phones, laptops, handheld communication devices, handheld computing devices, satellite radios, global positioning systems, PDAs, and/or any other suitable device for communicating over wireless communication system 100. As depicted, mobile device 116 is in communication with antennas 112 and 114, where antennas 112 and 114 transmit information to mobile device 116 over a forward link 118 and receive information from mobile device 116 over a reverse link 120. Moreover, mobile device 122 is in communication with antennas 104 and 106, where antennas 104 and 106 transmit information to mobile device 122 over a forward link 124 and receive information from mobile device 122 over a reverse link 126. In a frequency division duplex (FDD) system, forward link 118 can utilize a different frequency band than that used by reverse link 120, and forward link 124 can employ a different frequency band than that employed by reverse link 126, for example. Further, in a time division duplex (TDD) system, forward link 118 and reverse link 120 can utilize a common frequency band and forward link 124 and reverse link 126 can utilize a common frequency band.

[0033] Each group of antennas and/or the area in which they are designated to communicate can be referred to as a sector of base station 102. For example, antenna groups can be designed to communicate to mobile devices in a sector of the areas covered by base station 102. In communication over forward links 118 and 124, the transmitting antennas of base station 102 can utilize beamforming to improve signal-to-noise ratio of forward links 118 and 124 for mobile devices 116 and 122. Also, while base station 102 utilizes beamforming to transmit to mobile devices 116 and 122 scattered randomly through an associated coverage, mobile devices in neighboring cells can be subject to less interference as compared to a base station transmitting through a single antenna to all its mobile devices.

[0034] Base station 102 (and/or each sector of base station 102) can employ one or more multiple access technologies (e.g., CDMA, TDMA, FDMA, OFDMA, ...). For instance, base station 102 can utilize a particular technology for communicating with mobile devices (e.g., mobile devices 116 and 122) upon a corresponding bandwidth. Moreover, if more than one technology is employed by base station 102, each technology can be associated with a respective bandwidth. The technologies

described herein can include following: Global System for Mobile (GSM), General Packet Radio Service (GPRS), Enhanced Data Rates for GSM Evolution (EDGE), Universal Mobile Telecommunications System (UMTS), Wideband Code Division Multiple Access (WCDMA), cdmaOne (IS-95), CDMA2000, Evolution-Data Optimized (EV-DO), Ultra Mobile Broadband (UMB), Worldwide Interoperability for Microwave Access (WiMAX), MediaFLO, Digital Multimedia Broadcasting (DMB), Digital Video Broadcasting - Handheld (DVB-H), etc. It is to be appreciated that the aforementioned listing of technologies is provided as an example and the claimed subject matter is not so limited; rather, substantially any wireless communication technology is intended to fall within the scope of the hereto appended claims.

[0035] Base station 102 can employ a first bandwidth with a first technology. Moreover, base station 102 can transmit a pilot corresponding to the first technology on a second bandwidth. According to an illustration, the second bandwidth can be leveraged by base station 102 and/or any disparate base station (not shown) for communication that utilizes any second technology. Moreover, the pilot can indicate the presence of the first technology (e.g., to a mobile device communicating via the second technology). For example, the pilot can use bit(s) to carry information about the presence of the first technology. Additionally, information such as a SectorID of the sector utilizing the first technology, a CarrierIndex indicating the first frequency bandwidth, and the like can be included in the pilot.

[0036] According to another example, the pilot can be a beacon (and/or a sequence of beacons). A beacon can be an OFDM symbol where a large fraction of the power is transmitted on one subcarrier or a few subcarriers (e.g., small number of subcarriers). Thus, the beacon provides a strong peak that can be observed by mobile devices, while interfering with data on a narrow portion of bandwidth (e.g., the remainder of the bandwidth can be unaffected by the beacon). Following this example, a first sector can communicate via CDMA on a first bandwidth and a second sector can communicate via OFDM on a second bandwidth. Accordingly, the first sector can signify the availability of CDMA on the first bandwidth (e.g., to mobile device(s) operating utilizing OFDM on the second bandwidth) by transmitting an OFDM beacon (or a sequence of OFDM beacons) upon the second bandwidth.

[0037] The subject innovation can organize a number of transmit antenna into a number of virtual antennas (e.g., also referred to as a group, a group of antenna, a group of transmit antenna, etc.) in order to allow legacy user equipment to utilize the entire number of transmit antenna. In particular, legacy user equipment may be able to utilize only up to four (4) transmit antenna ports (e.g., created antenna ports for a group of UEs). Within wireless communication systems that employ four or more transmit antenna, a legacy user equipment can not utilize more than four transmit antenna ports. The subject innovation can group the four or more transmit antenna

into virtual antennas by employing a linear combination (e.g., linear combination on physical antennas, etc.) for example and using the virtual antennas as transmit antenna ports that a legacy user equipment can utilize therefore allowing the legacy user equipment to leverage more than four transmit antenna. In other words, virtual antennas can be created such that legacy user equipment can leverage additional transmit antenna (e.g., more than four transmit antenna). The subject innovation can further communicate reference signals for the transmit antenna and/or delay related to the linear combination to non-legacy user equipment (e.g., user equipment compatible with four or more antenna). Based on such communicated reference signals and delay, the non-legacy user equipment can identify each transmit antenna from each created group of transmit antenna.

[0038] Turning to Fig. 2, illustrated is a communications apparatus 200 for employment within a wireless communications environment. The communications apparatus 200 can be a base station (e.g., an eNodeB, a NodeB, etc.) or a portion thereof, a network or a portion thereof, a mobile device or a portion thereof, or substantially any communications apparatus that receives data transmitted in a wireless communications environment. In communications systems, the communications apparatus 200 employ components described below to organizing and/or creating a group of transmit antenna, wherein the number of groups is a number of advertise antenna.

[0039] The communications apparatus 200 can include a group module 202. The group module 202 can identify a number of transmit antennas and organize such transmit antennas into groups. In general, the group module 202 can create N groups of transmit antennas, wherein N is a positive integers and is equal to a number of advertised antennas. It is to be appreciated that the group module can create any suitable number of groups with any suitable number of transmit antennas within each group.

[0040] The communications apparatus 200 can include a linear combination module 204 that can employ a linear combination technique to each antenna within a group. In other words, the linear combination is applied to all the transmit antennas in each group, wherein the linear combination can convert transmit diversity to frequency diversity for each of the two or more groups. It is to be appreciated and understood that any suitable linear combination can be employed such as, but not limited to, cyclic delay diversity (CDD). It is to be appreciated that the linear combination can be frequency dependent.

[0041] The communications apparatus 200 can include a reference signal module 206 that can communicate and/or receive pilot signals (e.g., reference signals) and/or delay utilized with the linear combination. The reference signal module 206 can further be utilized by a user equipment that is aware of the linear combination and delay to identify the transmit antennas within a group regardless of assignment to groups. In other words, the reference signal module 206 can decode or unprecoder

the reference signals from grouped antenna in order to identify each antenna within each of the groups.

[0042] It is to be appreciated that the communications apparatus 200 (and/or the group module 202, the linear combination module 204, and/or the reference signal module 206) can provide at least one of identifying at least two groups of user equipment (UEs), signaling a different number of antennas ports to the least two group of UEs, and/or creating antenna ports corresponding to each group of UEs, wherein each antenna port includes a subset of a number of physical transmit antennas and the number of antenna ports is the number of signaled antenna ports to that group of UEs.

[0043] It is to be appreciated that the communications apparatus 200 (and/or the group module 202, the linear combination module 204, and/or the reference signal module 206) can provide at least one of receiving a mapping information that includes at least one of a delay and a linear combination employed to transmit a reference signal related to the set of antenna ports, receiving a reference signal related to the antenna ports, decoding the reference signal related to the set in order to identify each antenna port, wherein the decoding utilizes the mapping information, utilizing a transmitted reference signal for antenna ports of a first group of UEs for at least one of a measurement, a feedback to a base station, or a demodulation technique, and/or utilizing a transmitted reference signals for antenna ports of a second group of UEs for a measurement and a feedback to a base station.

It is to be appreciated that the communication apparatus 200 can transmit a reference signal to a group of UEs, wherein the reference signals relates to at least one corresponding advertised antenna port and/or corresponding advertised antenna ports. It is to be further appreciated that the mapping information can include mapping between the physical transmit antennas and at least one antenna ports of a group of UEs.

[0044] It is to be appreciated that the communications apparatus 200 can created UE specific antenna ports dynamically over time and can be based upon feedback from the UE. The feedback can be at least one of a Channel quality, a precoding matrix, a rank information, a channel directionality information, and/or channel quality conditions for the antenna ports advertised to only a subset of group of UEs. Moreover, the group of UEs can have different patterns, different density and different periodicity.

[0045] Moreover, although not shown, it is to be appreciated that communications apparatus 200 can include memory that retains instructions with respect to identifying a number of transmit antennas, creating one or more groups that include a subset of the number of transmit antennas, wherein each group includes a subset of the number of transmit antennas and the number of groups is a number of advertised antennas, employing a linear combination to convert transmit diversity to frequency diversity for each of the two or more groups, identifying at least two groups of user equipment (UEs), sig-

nalizing a different number of antennas ports to the least two group of UEs, creating antenna ports corresponding to each group of UEs, wherein each antenna port includes a subset of a number of physical transmit antennas and the number of antenna ports is the number of signaled antenna ports to that group of UEs, and the like. Further, communications apparatus 200 can include a processor that may be utilized in connection with executing instructions (e.g., instructions retained within memory, instructions obtained from a disparate source, ...).

[0046] Additionally, although not shown, it is to be appreciated that communications apparatus 200 can include memory that retains instructions with respect to receiving a delay related to a linear combination to convert transmit diversity to frequency diversity for a group that includes two or more transmit antennas, receiving a reference signal related to the group, decoding the reference signal related to the group in order to identify each transmit antenna, wherein the decoding utilizes the received delay, receiving a mapping information that includes at least one of a delay and a linear combination employed to transmit a reference signal related to the set of antenna ports, receiving a reference signal related to the antenna ports, decoding the reference signal related to the set in order to identify each antenna port, wherein the decoding utilizes the mapping information, utilizing a transmitted reference signal for antenna ports of a first group of UEs for at least one of a measurement, a feedback to a base station, or a demodulation technique, utilizing a transmitted reference signals for antenna ports of a second group of UEs for a measurement and a feedback to a base station, and the like. Further, communications apparatus 200 can include a processor that may be utilized in connection with executing instructions (e.g., instructions retained within memory, instructions obtained from a disparate source, ...).

[0047] Now referring to **Fig. 3**, illustrated is a wireless communications system 300 that can group transmit antennas to optimize legacy user equipment (UE). The system 300 includes a base station 302 that communicates with a user equipment 304 (and/or any number of disparate user equipment (not shown)). Base station 302 can transmit information to user equipment 304 over a forward link channel; further base station 302 can receive information from user equipment 304 over a reverse link channel. Moreover, system 300 can be a MIMO system. Additionally, the system 300 can operate in an OFDMA wireless network, a 3GPP LTE wireless network, etc. Also, the components and functionalities shown and described below in the base station 302 can be present in the user equipment 304 as well and *vice versa*, in one example; the configuration depicted excludes these components for ease of explanation.

[0048] Base station 302 includes a group module 306 that can evaluate a number of available transmit antenna and organize such number of available transmit antenna into groups. The group module 306 can create a number of groups that include transmit antenna, wherein the

number of groups can be equal to a number of advertise antenna. For instance, there can be 8 transmit antenna and four advertised antenna ports, wherein the group module can create 8 groups, wherein each group can include at least one transmit antenna.

[0049] The base station 302 can further include a linear combination module 308 that can employ a linear combination to convert to convert transmit diversity to frequency diversity for each of the one or more groups that include at least two transmit antenna. It is to be appreciated that the linear combination module 308 can employ cyclic delay diversity (CDD) and/or any other suitable linear combination technique.

[0050] The base station 302 can further include a transmit module 310 that can communicate or convey a delay related to a linear combination technique. The transmit module 310 can further convey or communicate reference signals for each group of antenna and/or each individual antenna within each group. By conveying such reference signals and/or delay, a user equipment may be able to estimate the channel of each transmit antenna within each group.

[0051] It is to be appreciated that the base station 302 (and/or the group module 306, the linear combination module 308, and/or the transmit module 310) can provide at least one of identifying at least two groups of user equipment (UEs), signaling a different number of antennas ports to the least two group of UEs, and/or creating antenna ports corresponding to each group of UEs, wherein each antenna port includes a subset of a number of physical transmit antennas and the number of antenna ports is the number of signaled antenna ports to that group of UEs.

[0052] User equipment 304 can include a receive module 312 that can receive the reference signal and/or delay related to the linear combination technique. The user equipment 304 can further include a reference signal module 314. The reference signal module 314 can further be utilized by a user equipment to estimate the channel of the antennas within the group regardless of assignment to groups. In other words, the reference signal module 314 can decode or unprecoder the reference signals (utilizing the received delay) from grouped antenna in order to identify each antenna within each of the groups.

[0053] It is to be appreciated that the user equipment 304 (and/or the receive module 312 and/or the reference signal module 314) can provide at least one of receiving a mapping information that includes at least one of a delay and a linear combination employed to transmit a reference signal related to the set of antenna ports, receiving a reference signal related to the antenna ports, decoding the reference signal related to the set in order to identify each antenna port, wherein the decoding utilizes the mapping information, utilizing a transmitted reference signal for antenna ports of a first group of UEs for at least one of a measurement, a feedback to a base station, or a demodulation technique, and/or utilizing a transmitted reference signals for antenna ports of a second group of

UEs for a measurement and a feedback to a base station.

[0054] Moreover, although not shown, it is to be appreciated that base station 302 can include memory that retains instructions with respect to identifying a number of transmit antennas, creating one or more groups that include a subset of the number of transmit antennas, wherein each group includes a subset of the number of transmit antennas and the number of groups is a number of advertised antennas, employing a linear combination to convert transmit diversity to frequency diversity for each of the one or more groups, identifying at least two groups of user equipment (UEs), signaling a different number of antennas ports to the least two group of UEs, creating antenna ports corresponding to each group of UEs, wherein each antenna port includes a subset of a number of physical transmit antennas and the number of antenna ports is the number of signaled antenna ports to that group of UEs, and the like. Further, communications apparatus 200 can include a processor that may be utilized in connection with executing instructions (e.g., instructions retained within memory, instructions obtained from a disparate source, ...).

[0055] Additionally, although not shown, it is to be appreciated that base station 302 can include memory that retains instructions with respect to receiving a delay related to a linear combination to convert transmit diversity to frequency diversity for a group that includes two or more transmit antennas, receiving a reference signal related to the group, decoding the reference signal related to the group in order to identify each transmit antenna, wherein the decoding utilizes the received delay, receiving a mapping information that includes at least one of a delay and a linear combination employed to transmit a reference signal related to the set of antenna ports, receiving a reference signal related to the antenna ports, decoding the reference signal related to the set in order to identify each antenna port, wherein the decoding utilizes the mapping information, utilizing a transmitted reference signal for antenna ports of a first group of UEs for at least one of a measurement, a feedback to a base station, or a demodulation technique, utilizing a transmitted reference signals for antenna ports of a second group of UEs for a measurement and a feedback to a base station, and the like. Further, communications apparatus 200 can include a processor that may be utilized in connection with executing instructions (e.g., instructions retained within memory, instructions obtained from a disparate source, ...).

[0056] Multiple transmit antennas can also be used to increase the data rate. In MIMO systems with N_t transmit and N_r receive antennas the capacity scales linearly with $\min(N_t, N_r)$.

[0057] Cyclic delay diversity (CDD) is a scheme to convert transmit diversity to frequency diversity in OFDM systems. CDD schemes involve transmitting the same signal on different antennas with different delays. In the following example it is shown how CDD converts transmit diversity to frequency diversity. Consider the case when

the channel from two transmit antennas are $H_1(f) = H_1$ and $H_2(f) = H_2$, that is, the channels are not frequency selective. Since a delay corresponds to a multiplication by a phase ramp in the frequency domain, the effective channel realization after CDD is proportional to $H_1 + e^{j\theta D} H_2$ where D is proportional to the delay introduced on the 2nd antenna. Therefore, CDD schemes increase the frequency selectivity of the channel response. If the signal is sent on two OFDM subcarriers that are spaced far apart, there is a diversity of two.

[0058] LTE release 8 supports 1, 2, or 4 transmit antenna ports. The number of transmit antenna ports can be advertised through PBCH. A reference signal (RS) can be sent from each antenna port that is used for channel estimation purposes.

[0059] LTE-Advanced can have more transmit antennas (e.g., 8, more than 8, etc.) at the base station. Since legacy UEs can only support up to 4 transmit antenna ports, a smaller number of transmit antenna ports than that available in the system is advertised to legacy UEs through PBCH. Let "advertised antenna ports" refer to the antenna ports advertised to legacy UEs and let "all antenna ports" refer to all the antenna ports available in the system. New UEs can be made aware of all available antenna ports through a new mechanism (discussed below).

[0060] One technique to support legacy UEs in such a system would be to map one transmit antenna to one antenna port. This would fix the transmit antennas that can be used for transmissions monitored by legacy UEs and may allow use of all antennas only for transmissions monitored by new UEs. However, in such a technique the transmit diversity for legacy UEs is limited to the number of advertised antenna ports. The subject innovation transmit signals that are monitored by legacy UEs that enables legacy UEs to get a transmit diversity that is larger than the number of advertised antenna ports and that does not require any change in the way legacy UEs processes the received signal.

[0061] The subject innovation can enable the transmit antennas available in the system to be grouped into N groups, where N is equal to the number of advertised antenna ports. It is to be appreciated that the number of antennas in different groups could be different (e.g., group one has two antenna and group two has three antenna, etc.) and an antenna could belong to more than one group. On each such group, a cyclic delay diversity (CDD) scheme can be utilized to convert transmit diversity to frequency diversity. It is to be appreciated that any suitable linear or non-linear combination can be employed and CDD is just one example. At the receiver, all the antennas within a group can appear as a single transmit antenna port and processing at the receiver is unaffected as long as the delay introduced on different antennas is not too large. For example, consider the case with 8 transmit antennas where 4 transmit antenna ports are advertised to legacy UEs. Antenna 1 and 2 can be grouped to group 1, antenna 3 and 4 to group2, antenna

5 and 6 to group 3 and antenna 7 and 8 to group 4. All antennas in group N would act like a virtual antenna to the UE by transmitting the signal corresponding to advertised antenna N using CDD. For example, this could be done by transmitting a signal as is on the first antenna in the group and by transmitting the signal delayed by a chip in the second antenna of the group.

[0062] Some control channels in LTE Release 8 like PCFICH, PHICH, and PDCCH are spread across the frequency and hence using such a scheme helps improve the performance of legacy UEs. For example for PCFICH, PHICH, and PDCCH of legacy UEs, instead of transmitting on 4 transmit antennas, it can be transmitted on the 4 virtual antennas as done for reference signal (RS) in the previous example.

[0063] In order to make use of this diversity in data transmission, the scheduler could schedule UE on PDSCH resources distributed across the frequency. The PDSCH can be transmitted using the same virtual antenna scheme as RS to benefit from this additional diversity. In case of PDSCH transmissions with its own dedicated RS a similar virtual antenna scheme can be employed for the dedicated RS and the corresponding data transmission in PDSCH. The virtual antenna used for data transmission in this case could be different from those used for common RS.

[0064] The proposed virtual antenna technique can be employed for both legacy and new UEs for transmission of control for example. It is to be appreciated that a legacy UE can be a UE that is compatible with four or less transmit antennas and a new UE is a UE that is compatible with four or more transmit antenna. Alternately, the virtual antenna technique can be utilized for legacy UEs while for PHICH, PDCCH and PDSCH transmissions to new UEs can use a different approach to get the improved transmit diversity since they could have more pilots and could estimate the channel from the different antennas.

[0065] In order to get the higher data rates possible with all available antenna ports, new UEs need to be able to estimate the channel corresponding to all available antenna ports and report the channel quality (CQI, PMI, RI, CDI etc). New reference signals can be sent for all the antenna ports to be used by the new UEs in addition to the reference signals already being transmitted for legacy UEs. Alternately, new reference signals can be designed such that they can be used together with the legacy RS for channel estimation of all transmit antennas for feedback and measurement purposes. The reference signals can be unprecoded and can represent the directions not covered by the legacy RS. They can also be precoded and provide directions of the precoded channel not provided by the legacy RS.

[0066] For example, consider the same example as before where 8 Tx antennas are grouped into 4 group with group 1 corresponding to antenna 1 and 2, group 2 containing antenna 3, 4 and so on. Let $h_i(t)$ (for $i = 1$ to 8, t denotes time) denote the channel corresponding to the i -th transmit antenna. Due to the CDD scheme where the

transmit signal from one of the antennas is delayed by one chip, to UEs the effective antenna gain on the common RS appears to $h_1(t)+h_2(t-T_c)$ corresponding to RS of group 1, $h_3(t)+h_4(t-T_c)$ corresponding to group 2 and so on. T_c is the chip duration.

[0067] Four new sets of pilots can be transmitted such that the effective channel gain from pilot set 1 is $h_1(t)-h_2(t-T_c)$, from pilot set 2 is $h_3(t)-h_4(t-T_c)$ and so on. This could be done by transmitting $X(t)$ from one antenna and $-X(t-T_c)$ from the next antenna. It is therefore possible to get estimates of $h_i(t)$ by using the common RS and the new pilots. In this specific example, the common RS gives estimate of $h_{2i-1}(t)+h_{2i}(t-T_c)$ while the new pilots gives an estimate of $h_{2i-1}(t)-h_{2i}(t-T_c)$. The sum and difference of these estimates scaled and shifted suitably yield estimates of $h_{2i-1}(t)$ and $h_{2i}(t)$.

[0068] More generally, the new reference signals in conjunction with the legacy common RS can be able to detect the channel gains from all antennas efficiently. The new reference signals can be sent in directions orthogonal to the directions in common RS and should be orthogonal to each other.

[0069] In summary the subject innovation can provide the use of CDD (or any suitable linear combination) between antenna pairs in 8 Tx antenna system to provide additional diversity for legacy UEs with complete transparency to these UEs. Additionally, the subject innovation can provide new additional Reference Signals designed such that combined with the reference signals sent for legacy UEs can enable LTE-A UEs to estimate channel from all the antennas.

[0070] To support higher data rates, MIMO systems with large number of antennas (up to 8) are envisioned in LTE-A. Therefore, it is required to provide mechanisms by which UEs or a group of UEs can obtain estimates of all the antennas involved in transmission of different information. LTE standard currently supports Reference Signals for up to 4 antenna ports.

[0071] The subject innovation provides a scheme to support Reference signal for additional 4 antennas. Orthogonal multiplexing of the reference signals for different antenna ports can be provided using different time shifts. For example, RS of antenna 1 and 5 are sent on RS resource for antenna 1. RS of antenna 5 is delayed by some chip durations, for example CP/2 chips. In this case, reference signal of multiple antennas will be transmitted on same frequency-time resources. Transmitted reference signal corresponding to each antenna will have different phase ramps in frequency. The reference signal for all the antennas multiplexed onto the same set of resources will be different only in the frequency dependent phase shift.

[0072] To legacy UEs the multiple antennas that use the same time frequency resources for the RS would appear as one virtual antenna and if all their signals are sent in a similar fashion, they will not be impacted. If the delay spread of the channel from the antennas in a group is known to be small (e.g., within a fraction of the cyclic

prefix), the new UEs may be able to estimate the channels from different antennas within a group from the received signal corresponding to RS of this group.

[0073] The LTE-A UE can use the particular information on the multiplexing of the reference signals and phase ramps to estimate channel information for all the antennas. This information can be static and pre-configured or can be adaptive and configurable. LTE-A UE will be informed of this information by some mechanisms such as new system information block (SIB) sent on common channels.

[0074] Now referring to **Fig. 4**, an example wireless communications system 400 can organize two or more transmit antenna. The system 400 is utilized for exemplary purposes and is not to be limiting on the subject innovation. For example, the system 400 can utilize any suitable number of transmit antenna, any suitable number of groups for the transmit antenna, and any suitable number of transmit antenna within each group. The system 400 can include eight transmit antenna (e.g., transmit antenna 1, transmit antenna 2, transmit antenna 3, transmit antenna 4, transmit antenna 5, transmit antenna 6, transmit antenna 7, and transmit antenna 8), which can be organized into four groups such as group 1 402, group 2 404, group 3 406, and group 4 408.

[0075] Based on the grouping of the transmit antennas, each group of transmit antennas can employ a linear combination technique (e.g., cyclic delay diversity (CDD), etc.) to convert transmit diversity to frequency diversity for each of the two or more groups. Thus, a legacy user equipment (UE) 410 can identify each group of the transmit antennas (e.g., group 1 402, group 2 404, group 3 406, and group 4 408). This allows employment of each transmit antenna whether or not the legacy user equipment 410 is compatible with less than four transmit antennas. In other words, the legacy user equipment 410 detects four transmit antenna based on the four groups. A user equipment 412 (e.g., a non-legacy user equipment, a user equipment that is compatible to utilize four or more transmit antenna) can further utilize each of the transmit antenna regardless of the groupings of transmit antenna. The user equipment 412 can receive a delay related to the linear combination as well as reference signals for the groups of transmit antenna and/or each transmit antenna. Based on such received delay and/or reference signals, the user equipment 412 can decode or unprecoder and detect each transmit antenna- here all eight (8) transmit antenna.

[0076] According to one aspect, transmit antennas available in the wireless communication system are grouped into N groups, where N is equal to the number of advertised antennas. According to one aspect, the number of antennas in different groups may be different. Additionally, each of the N groups use cyclic delay diversity to convert transmit diversity to frequency diversity. At the receiver, e.g., UEs, all the antennas within a group appear as a single transmit antenna and the processing at the receiver is unaffected as long as the delay intro-

duced on different antennas is not too large. For example, in one aspect 8 transmit antennas are implemented and 4 transmit antennas are advertised to legacy UEs. Antenna 1 and 2 are grouped in group 1, antenna 3 and 4 are grouped in group 2, antenna 5 and 6 are grouped in group 3 and antenna 7 and 8 are grouped in group 4. All antennas in group N would act like a virtual antenna to the UE by transmitting the signal corresponding to advertised antenna N using CDD. For example, in one aspect, the signal is transmitted as-is on the first antenna in the group and the signal is transmitted delayed by a chip in the second antenna of the group.

[0077] It should be noted that some control channels in LTE Release 8 like Physical Control Format Indicator Channel (PCFICH), Physical H-ARQ Indication Channel (PHICH), and Physical Downlink Control Channel (PDCCH) are spread across the frequency and hence using the aspects herein described helps improve the performance of legacy UEs. For example for PCFICH, PHICH, and PDCCH of legacy UEs, instead of transmitting on 4 transmit antennas, we transmit on the 4 virtual antennas as done for the Reference Signal (RS) in the previous example. Thus, it is to be appreciated that the subject innovation can transmit at least one of Reference Signals (RS), Physical Control Format Indicator Channel (PCFICH), Physical Hybrid ARQ Channel (PHICH), and Physical Downlink Control Channel (PDCCH), and PDSCH to a group of UEs using the antenna ports advertised to the group of UEs.

[0078] In accordance with an aspect, in order to make use of the transmit diversity in data transmission, the scheduler may schedule UE on PDSCH resources distributed across the frequency. The PDSCH can be transmitted using the same virtual antenna scheme as RS to benefit from this additional diversity. In the case of PDSCH transmissions with their own dedicated RS a similar virtual antenna scheme can be employed for the dedicated RS and the corresponding data transmission in PDSCH. According to one aspect, the virtual antenna scheme in this case could be different from that for common RS.

[0079] In accordance with one or more aspects, the proposed virtual antenna technique may be employed for both legacy and new UEs. Alternately, the virtual antenna technique may be used for legacy UEs while for PHICH, PDCCH and PDSCH transmissions to non-legacy UEs could use a different approach to obtain the improved transmit diversity since the non-legacy UEs may have more pilots and may estimate the channel from the different antennas.

[0080] In order to obtain the higher data rates possible with all available transmit antennas, for data demodulation, non-legacy UEs need to be able to estimate the precoded channel corresponding to all transmitted beams. In one aspect, new pilots (dedicated reference signals) can be transmitted in the PDSCH region to aid in the precoded channel estimation. The new pilots can be precoded using the same beams as used for data

transmission and can provide the precoded channel estimate of all beams. Alternately the Reference Signal sent for legacy devices is implemented and new pilots (dedicated reference signals) can be designed such that they can be used together with the legacy RS for channel estimation for data demodulation. For example, the reference signals can be un-precoded or use fixed precoding independent of that used for data and can represent the directions not covered by the legacy RS. The precoded channel for data demodulation can then be estimated using the legacy RS as well as the new pilots and utilizing the mapping between the transmit beams and the directions of legacy RS and new pilots. In other aspects, the reference signals can also be precoded for specific UEs and provide directions of the precoded channel not provided by the legacy RS.

[0081] Therefore, according to some aspects, the channel estimation for demodulation can be done jointly with the use of the legacy RS and the new dedicated RS provided for non-legacy UEs. The new dedicated RS can provide information about channel along the direction of the beams used (and the precoding operation performed) in transmission to the UE. In some aspects, the dedicated RS may represent the entire precoded channel or, in the alternative, it may represent the direction of the precoded channel not represented by the legacy RS. The Precoded channel can correspond to the channel between the UE and the antennas at a single cell for higher order MIMO operation, or between the UE and the antennas from different cells cooperating in a network MIMO operation.

[0082] According to some aspects, DL control signaling to the UE may provide some information about the precoding matrix (or the beam directions) used for transmission to the UE. These beam directions can correspond to the beams formed by antennas of a single cell equipped with multiple antennas (possibly up to 8 for LTE-A) or the beams formed by the antennas of multiple cells (or sites) participating in cooperative transmission schemes involving the UE. These cooperative schemes can be in different forms such as, for example, distributed beam-forming or, alternatively, joint processing and signal processing.

[0083] According to some aspects, the information conveyed by the control signaling to the UE may be of different types:

[0084] A) Precoding matrix indicator corresponding to the entire channel. In this case the dedicated RS may represent the channel along directions not covered by the legacy RS and the UE can perform joint channel estimation using the legacy RS and the dedicated RS.

[0085] B) Precoding matrix indicators corresponding to the directions of the precoded channel represented by the legacy RS. In this case, dedicated RS represents the directions of the precoded channel not represented by the legacy RS. The UE obtains estimate of the entire precoded channels by using the precoding information corresponding to the legacy RS and the precoded dedicated RS.

[0086] C) Indicators to the precoding vectors used by all (or some) of the cells involved in cooperation scheme involving the UE.

[0087] In scenarios where frequency-dependent precoding operation is used, i.e. multiple precoding matrices are used for different parts of the band, the DL control signaling may convey information about some or all of them.

[0088] Referring to **Figs. 5-6**, methodologies relating to grouping transmit antenna for legacy user equipment and communicating delay information for user equipment (UE) are illustrated. While, for purposes of simplicity of explanation, the methodologies are shown and described as a series of acts, it is to be understood and appreciated that the methodologies are not limited by the order of acts, as some acts may, in accordance with one or more embodiments, occur in different orders and/or concurrently with other acts from that shown and described herein. For example, those skilled in the art will understand and appreciate that a methodology could alternatively be represented as a series of interrelated states or events, such as in a state diagram. Moreover, not all illustrated acts may be required to implement a methodology in accordance with one or more embodiments.

[0089] Turning to **Fig. 5**, illustrated is a methodology 500 that facilitates optimizing Long Term Evolution Advance (LTE A). At reference numeral 502, at least two groups of user equipment (UEs) can be identified. At reference numeral 504, a different number of antennas ports can be signaled to the least two group of UEs. At reference numeral 506, antenna ports corresponding to each group of UEs can be created, wherein each antenna port includes a subset of a number of physical transmit antennas and the number of antenna ports is the number of signaled antenna ports to that group of UEs.

[0090] Now referring to **Fig. 6**, a methodology 600 that facilitates identifying a set of antenna ports. At reference numeral 602, a mapping information can be received that includes at least one of a delay and a linear combination employed to transmit a reference signal related to the set of antenna ports. At reference numeral 604, a reference signal related to the antenna ports can be received. At reference numeral 608, the reference signal related to the set can be decoded in order to identify each antenna port, wherein the decoding utilizes the mapping information.

[0091] Moreover, although not shown, the methodology 600 can further comprise utilizing a transmitted reference signal for antenna ports of a first group of UEs for at least one of a measurement, a feedback to a base station, or a demodulation technique, and utilizing a transmitted reference signals for antenna ports of a second group of UEs for a measurement and a feedback to a base station.

[0092] **Fig. 7** is an illustration of a mobile device 700 that facilitates creating transmit antenna groups in a wireless communication system. Mobile device 700 compris-

es a receiver 702 that receives a signal from, for instance, a receive antenna (not shown), performs typical actions on (e.g., filters, amplifies, downconverts, etc.) the received signal, and digitizes the conditioned signal to obtain samples. Receiver 702 can comprise a demodulator 704 that can demodulate received symbols and provide them to a processor 706 for channel estimation. Processor 706 can be a processor dedicated to analyzing information received by receiver 702 and/or generating information for transmission by a transmitter 716, a processor that controls one or more components of mobile device 700, and/or a processor that both analyzes information received by receiver 702, generates information for transmission by transmitter 716, and controls one or more components of mobile device 700.

[0093] Mobile device 700 can additionally comprise memory 708 that is operatively coupled to processor 706 and that can store data to be transmitted, received data, information related to available channels, data associated with analyzed signal and/or interference strength, information related to an assigned channel, power, rate, or the like, and any other suitable information for estimating a channel and communicating via the channel. Memory 708 can additionally store protocols and/or algorithms associated with estimating and/or utilizing a channel (e.g., performance based, capacity based, etc.).

[0094] It will be appreciated that the data store (e.g., memory 708) described herein can be either volatile memory or nonvolatile memory, or can include both volatile and nonvolatile memory. By way of illustration, and not limitation, nonvolatile memory can include read only memory (ROM), programmable ROM (PROM), electrically programmable ROM (EPROM), electrically erasable PROM (EEPROM), or flash memory. Volatile memory can include random access memory (RAM), which acts as external cache memory. By way of illustration and not limitation, RAM is available in many forms such as synchronous RAM (SRAM), dynamic RAM (DRAM), synchronous DRAM (SDRAM), double data rate SDRAM (DDR SDRAM), enhanced SDRAM (ESDRAM), Synch-link DRAM (SLDRAM), and direct Rambus RAM (DR-RAM). The memory 708 of the subject systems and methods is intended to comprise, without being limited to, these and any other suitable types of memory.

[0095] Processor 706 can further be operatively coupled to a collect module 710 and/or a reference signal module 712. The collect module 710 can receive delays utilized for the linear combination techniques for each group that includes transmit antenna. The collect module 710 can further receive reference signals related to each create group of transmit antenna, wherein each group includes at least one transmit antenna from a number of available transmit antenna. The reference signal module 712 can leverage the collected data (e.g., the delay and/or the reference signals) to unprecode or decode and identify each transmit antenna included within each group. Thus, the reference signal module 710 can allow identification of available transmit antenna assigned to

the created groups.

[0096] Mobile device 700 still further comprises a modulator 714 and transmitter 716 that respectively modulate and transmit signals to, for instance, a base station, another mobile device, etc. Although depicted as being separate from the processor 606, it is to be appreciated that the collect module 710, reference signal module 712, demodulator 704, and/or modulator 714 can be part of the processor 706 or multiple processors (not shown).

[0097] Fig. 8 is an illustration of a system 800 that facilitates enhancing transmit antenna utilization in a wireless communication environment as described *supra*. The system 800 comprises a base station 802 (e.g., access point, ...) with a receiver 810 that receives signal(s) from one or more mobile devices 804 through a plurality of receive antennas 806, and a transmitter 824 that transmits to the one or more mobile devices 804 through a transmit antenna 808. Receiver 810 can receive information from receive antennas 806 and is operatively associated with a demodulator 812 that demodulates received information. Demodulated symbols are analyzed by a processor 814 that can be similar to the processor described above with regard to Fig. 7, and which is coupled to a memory 816 that stores information related to estimating a signal (e.g., pilot) strength and/or interference strength, data to be transmitted to or received from mobile device(s) 804 (or a disparate base station (not shown)), and/or any other suitable information related to performing the various actions and functions set forth herein.

[0098] Processor 814 is further coupled to a group module 818 and/or a linear combination module 820. The group module 818 can identify available transmit antenna and organize the available transmit antenna into N groups, where N is a positive integer and a number of advertise antenna. The linear combination module 820 can employ a linear combination technique such as, but not limited to, cyclic delay diversity to each antenna within a group. Furthermore, although depicted as being separate from the processor 814, it is to be appreciated that the group module 818, linear combination module 820, demodulator 812, and/or modulator 822 can be part of the processor 814 or multiple processors (not shown).

[0099] Fig. 9 shows an example wireless communication system 900. The wireless communication system 900 depicts one base station 910 and one mobile device 950 for sake of brevity. However, it is to be appreciated that system 900 can include more than one base station and/or more than one mobile device, wherein additional base stations and/or mobile devices can be substantially similar or different from example base station 910 and mobile device 950 described below. In addition, it is to be appreciated that base station 910 and/or mobile device 950 can employ the systems (Figs. 1-3 and 7-8), techniques/configurations (Fig. 4) and/or methods (Figs. 5-6) described herein to facilitate wireless communication there between.

[0100] At base station 910, traffic data for a number of

data streams is provided from a data source 912 to a transmit (TX) data processor 914. According to an example, each data stream can be transmitted over a respective antenna. TX data processor 914 formats, codes, and interleaves the traffic data stream based on a particular coding scheme selected for that data stream to provide coded data.

[0101] The coded data for each data stream can be multiplexed with pilot data using orthogonal frequency division multiplexing (OFDM) techniques. Additionally or alternatively, the pilot symbols can be frequency division multiplexed (FDM), time division multiplexed (TDM), or code division multiplexed (CDM). The pilot data is typically a known data pattern that is processed in a known manner and can be used at mobile device 950 to estimate channel response. The multiplexed pilot and coded data for each data stream can be modulated (e.g., symbol mapped) based on a particular modulation scheme (e.g., binary phase-shift keying (BPSK), quadrature phase-shift keying (QPSK), M-phase-shift keying (M-PSK), M-quadrature amplitude modulation (M-QAM), etc.) selected for that data stream to provide modulation symbols. The data rate, coding, and modulation for each data stream can be determined by instructions performed or provided by processor 930.

[0102] The modulation symbols for the data streams can be provided to a TX MIMO processor 920, which can further process the modulation symbols (e.g., for OFDM). TX MIMO processor 920 then provides N_T modulation symbol streams to N_T transmitters (TMTR) 922a through 922t. In various embodiments, TX MIMO processor 920 applies beamforming weights to the symbols of the data streams and to the antenna from which the symbol is being transmitted.

[0103] Each transmitter 922 receives and processes a respective symbol stream to provide one or more analog signals, and further conditions (e.g., amplifies, filters, and upconverts) the analog signals to provide a modulated signal suitable for transmission over the MIMO channel. Further, N_T modulated signals from transmitters 922a through 922t are transmitted from N_T antennas 924a through 924t, respectively.

[0104] At mobile device 950, the transmitted modulated signals are received by N_R antennas 952a through 952r and the received signal from each antenna 952 is provided to a respective receiver (RCVR) 954a through 954r. Each receiver 954 conditions (e.g., filters, amplifies, and downconverts) a respective signal, digitizes the conditioned signal to provide samples, and further processes the samples to provide a corresponding "received" symbol stream.

[0105] An RX data processor 960 can receive and process the N_R received symbol streams from N_R receivers 954 based on a particular receiver processing technique to provide N_T "detected" symbol streams. RX data processor 960 can demodulate, deinterleave, and decode each detected symbol stream to recover the traffic data for the data stream. The processing by RX data

processor 960 is complementary to that performed by TX MIMO processor 920 and TX data processor 914 at base station 910.

[0106] A processor 970 can periodically determine which precoding matrix to utilize as discussed above. Further, processor 970 can formulate a reverse link message comprising a matrix index portion and a rank value portion.

[0107] The reverse link message can comprise various types of information regarding the communication link and/or the received data stream. The reverse link message can be processed by a TX data processor 938, which also receives traffic data for a number of data streams from a data source 936, modulated by a modulator 980, conditioned by transmitters 954a through 954r, and transmitted back to base station 910.

[0108] At base station 910, the modulated signals from mobile device 950 are received by antennas 924, conditioned by receivers 922, demodulated by a demodulator 940, and processed by a RX data processor 942 to extract the reverse link message transmitted by mobile device 950. Further, processor 930 can process the extracted message to determine which precoding matrix to use for determining the beamforming weights.

[0109] Processors 930 and 970 can direct (e.g., control, coordinate, manage, etc.) operation at base station 910 and mobile device 950, respectively. Respective processors 930 and 970 can be associated with memory 932 and 972 that store program codes and data. Processors 930 and 970 can also perform computations to derive frequency and impulse response estimates for the uplink and downlink, respectively.

[0110] It is to be understood that the embodiments described herein can be implemented in hardware, software, firmware, middleware, microcode, or any combination thereof. For a hardware implementation, the processing units can be implemented within one or more application specific integrated circuits (ASICs), digital signal processors (DSPs), digital signal processing devices (DSPDs), programmable logic devices (PLDs), field programmable gate arrays (FPGAs), processors, controllers, micro-controllers, microprocessors, other electronic units designed to perform the functions described herein, or a combination thereof.

[0111] When the embodiments are implemented in software, firmware, middleware or microcode, program code or code segments, they can be stored in a machine-readable medium, such as a storage component. A code segment can represent a procedure, a function, a sub-program, a program, a routine, a subroutine, a module, a software package, a class, or any combination of instructions, data structures, or program statements. A code segment can be coupled to another code segment or a hardware circuit by passing and/or receiving information, data, arguments, parameters, or memory contents. Information, arguments, parameters, data, etc. can be passed, forwarded, or transmitted using any suitable means including memory sharing, message passing, to-

ken passing, network transmission, etc.

[0112] For a software implementation, the techniques described herein can be implemented with modules (e.g., procedures, functions, and so on) that perform the functions described herein. The software codes can be stored in memory units and executed by processors. The memory unit can be implemented within the processor or external to the processor, in which case it can be communicatively coupled to the processor via various means as is known in the art.

[0113] With reference to **Fig. 10**, illustrated is a system 1000 that optimizes Long Term Evolution Advance (LTE A). For example, system 1000 can reside at least partially within a base station, mobile device, etc. It is to be appreciated that system 1000 is represented as including functional blocks, which can be functional blocks that represent functions implemented by a processor, software, or combination thereof (e.g., firmware). System 1000 includes a logical grouping 1002 of electrical components that can act in conjunction. The logical grouping 1002 can include an electrical component for identifying at least two groups of user equipment (UEs) 1004. In addition, the logical grouping 1002 can comprise an electrical component for signaling a different number of antennas ports to the least two group of UEs 1006. Moreover, the logical grouping 1002 can include an electrical component for creating antenna ports corresponding to each group of UEs, wherein each antenna port includes a subset of a number of physical transmit antennas and the number of antenna ports is the number of signaled antenna ports to that group of UEs 1008. Additionally, system 1000 can include a memory 1010 that retains instructions for executing functions associated with electrical components 1004, 1006, and 1008. While shown as being external to memory 1010, it is to be understood that one or more of electrical components 1004, 1006, and 1008 can exist within memory 1010.

[0114] Turning to **Fig. 11**, illustrated is a system 1100 that identifying transmit antenna in a wireless communication environment. System 1100 can reside within a base station, mobile device, etc., for instance. As depicted, system 1100 includes functional blocks that can represent functions implemented by a processor, software, or combination thereof (e.g., firmware). Logical grouping 1102 can include an electrical component for receiving a mapping information that includes at least one of a delay and a linear combination employed to transmit a reference signal related to the set of antenna ports 1104. Moreover, logical grouping 1102 can include an electrical component for receiving a reference signal related to the antenna ports 1106. Further, logical grouping 1102 can comprise an electrical component for decoding the reference signal related to the set in order to identify each antenna port, wherein the decoding utilizes the mapping information 1108. Additionally, system 1100 can include a memory 1110 that retains instructions for executing functions associated with electrical components 1104, 1106, and 1108. While shown as being external to mem-

ory 1110, it is to be understood that electrical components 1104, 1106, and 1108 can exist within memory 1110.

[0115] What has been described above includes examples of one or more embodiments. It is, of course, not possible to describe every conceivable combination of components or methodologies for purposes of describing the aforementioned embodiments, but one of ordinary skill in the art may recognize that many further combinations and permutations of various embodiments are possible. Accordingly, the described embodiments are intended to embrace all such alterations, modifications and variations that fall within the scope of the appended claims. Furthermore, to the extent that the term "includes" is used in either the detailed description or the claims, such term is intended to be inclusive in a manner similar to the term "comprising" as "comprising" is interpreted when employed as a transitional word in a claim..

Claims

1. A method used in a wireless communications system for generation of a reference signal, comprising:

identifying (502) at least two groups of user equipment, UEs;

signaling (504) a different number of antenna ports to the at least two groups of UEs; and
creating (506) a number of antenna ports for each group of UEs;

wherein each antenna port corresponds to a linear combination of a subset of a number of physical transmit antennas and the number of created antenna ports is the number antenna ports signaled to each group of UEs, and wherein the linear combination employed for different antenna ports for a particular group of UEs is linearly independent; and

characterized by further comprising transmitting a first reference signal for each of the antenna ports signaled to the first group of UEs using the linearly independent combination of transmit antennas associated with each antenna port for the first group of UEs and transmitting a further reference signal for each of the antenna ports signaled to the other group of UEs using the linearly independent combination of transmit antennas associated with each antenna port for the other group of UEs.

2. The method of claim 1, wherein the linear combination is frequency dependent or wherein the linear combination is cyclic delay diversity, CDD.
3. The method of claim 1, wherein a linear combination of the antenna ports corresponding to the first group of UEs with a larger number of signaled antenna ports is used as an antenna port for the second group

- of UEs with a smaller number of antenna ports.
4. The method of claim 1, wherein the further reference signal relates to at least one corresponding antenna ports previously signaled to one of the groups of UEs. 5
 5. The method of claim 3, further comprising communicating the linear combination and a related delay to the first group of UEs. 10
 6. The method of claim 1, wherein the reference signals transmitted to different groups of UEs have different patterns, different density and different periodicity.
 7. The method of claim 1, further comprising: 15
 - transmitting at least one of the reference signals related to the antenna ports for one of the UE groups in a Physical Downlink Shared Channel, PDSCH, region assigned to at least one specific group of UEs; 20
 - employing the antenna ports for one of the UE groups along with respective antenna ports defined for the other group of UEs to create beams for transmitting PDSCH to the groups of UEs; 25
 - and
 - estimating a channel from the antenna ports based on at least one of the following:
 - a reference signal related to at least one of the UE antenna ports or a disparate antenna port; or 30
 - a mapping information that relates the reference signal to a beam direction used for transmission of PDSCH. 35
 8. A wireless communications apparatus that optimizes configuration of transmit antennas and generates a reference signal, comprising: 40
 - means for identifying (202) at least two groups of user equipment, UEs;
 - means for signaling (206) a different number of antenna ports to the at least two group of UEs; and 45
 - means for creating a number of antenna ports (308) for each group of UEs;
 - wherein each antenna port corresponds to a linear combination of a subset of a number of physical transmit antennas and the number of created antenna ports is the number of antenna ports signaled to that group of UEs, and wherein the linear combination employed for different antenna ports for a particular group of UEs is linearly independent; and 50
 - characterized by** further comprising
 - means for transmitting a first reference signal for each of the antenna ports signaled to the first 55
- group of UEs using the linearly independent combination of transmit antennas associated with each antenna port for the first group of UEs and for transmitting a further reference signal for each of the antenna ports signaled to the other group of UEs using the linearly independent combination of transmit antennas associated with each antenna port for the other group of UEs.
9. The wireless communications apparatus of claim 8, wherein some of the antenna ports for different groups of UEs are the same.
 10. The wireless communications apparatus of claim 8 further comprising at least one processor configured to transmit at least one of the Reference Signals, Physical Control Format Indicator Channel, PCFICH, Physical Hybrid ARQ Channel, PHICH, and Physical Downlink Control Channel, PDCCH, and PDSCH to one of the groups of UEs using the antenna ports previously signaled to the group of UEs.
 11. The wireless communications apparatus of claim 8, further comprising means for sending PCFICH, PHICH, PDCCH, to one of the groups of UEs using the antenna ports previously signaled to the other group of UEs.
 12. The wireless communications apparatus of claim 8 further arranged to receive a reference signal comprising feedback from one of the user equipment groups and wherein the feedback is related to at least one channel quality condition for the antenna ports previously signaled to the groups of user equipments.
 13. The wireless communications apparatus of claim 8, further comprising: 40
 - means for scheduling transmission to an UE on Physical Downlink Shared Channel, PDSCH, resources that are frequency distributed; and
 - means for transmitting PDSCH to a UE using the antenna ports corresponding to one of the groups of UEs to which the UE belongs.
 14. The wireless communications apparatus of claim 8, wherein the transmitted reference signal to different group of UEs have different patterns, density and different periodicity.
 15. A computer-readable medium embodying machine executable instructions for causing at least one computer to perform a method according to one of the claims 1 to 7 when executed.

Patentansprüche

1. Verfahren, das in einem drahtlosen Kommunikationssystem zum Erzeugen eines Referenzsignals angewendet wird und Folgendes beinhaltet:

Identifizieren (502) von wenigstens zwei Gruppen von Benutzergeräten (UE);
 Signalisieren (504) einer unterschiedlichen Anzahl von Antennenports zu den wenigstens zwei Gruppen von UEs; und
 Erzeugen (506) einer Anzahl von Antennenports für jede Gruppe von UEs;
 wobei jeder Antennenport einer linearen Kombination aus einem Teilsatz aus einer Anzahl von physikalischen Sendeantennen entspricht und die Anzahl von erzeugten Antennenports die jeder Gruppe von UEs signalisierte Anzahl von Antennenports ist, und wobei die für unterschiedliche Antennenports für eine bestimmte Gruppe von UEs verwendete lineare Kombination linear unabhängig ist; und
dadurch gekennzeichnet, dass es ferner Folgendes beinhaltet:

Senden eines ersten Referenzsignals für jeden der zur ersten Gruppe von UEs signalisierten Antennenports unter Verwendung der linear unabhängigen Kombination von Sendeantennen in Verbindung mit jedem Antennenport für die erste Gruppe von UEs und Senden eines weiteren Referenzsignals für jeden der zur anderen Gruppe von UEs signalisierten Antennenports unter Verwendung der linear unabhängigen Kombination von Sendeantennen in Verbindung mit jedem Antennenport für die andere Gruppe von UEs.

2. Verfahren nach Anspruch 1, wobei die lineare Kombination frequenzabhängig ist oder wobei die lineare Kombination CDD (Cyclic Delay Diversity) ist.
3. Verfahren nach Anspruch 1, wobei eine lineare Kombination aus der ersten Gruppe von UEs entsprechenden Antennenports mit einer größeren Anzahl von signalisierten Antennenports als Antennenport für die zweite Gruppe von UEs mit einer geringeren Anzahl von Antennenports benutzt wird.
4. Verfahren nach Anspruch 1, wobei sich das weitere Referenzsignal auf wenigstens einen der zuvor zu einer der Gruppen von UEs signalisierten entsprechenden Antennenports bezieht.
5. Verfahren nach Anspruch 3, das ferner das Kommunizieren der linearen Kombination und einer verwandten Verzögerung zu der ersten Gruppe von

UEs beinhaltet.

6. Verfahren nach Anspruch 1, wobei die zu unterschiedlichen Gruppen von UEs gesendeten Referenzsignale unterschiedliche Diagramme, unterschiedliche Dichte und unterschiedliche Periodizität haben.

7. Verfahren nach Anspruch 1, das ferner Folgendes beinhaltet:

Senden von wenigstens einem der Referenzsignale in Bezug auf die Antennenports für eine der UE-Gruppen in einer PDSCH-(Physical Downlink Shared Channel)-Region, die wenigstens einer spezifischen Gruppe von UEs zugeordnet ist;
 Benutzen der Antennenports für eine der UE-Gruppen zusammen mit jeweiligen Antennenports, die für die andere Gruppe von UEs definiert sind, um Strahlen zum Senden von PDSCH zu den Gruppen von UEs zu erzeugen; und
 Schätzen eines Kanals von den Antennenports auf der Basis von wenigstens einem der Folgenden:

einem Referenzsignal in Bezug auf wenigstens einen der UE-Antennenports oder eines disparaten Antennenports; oder
 einer Mapping-Information, die das Referenzsignal auf eine zum Senden von PDSCH benutzte Strahlenrichtung bezieht.

8. Drahtlose Kommunikationsvorrichtung, die die Konfiguration von Sendeantennen optimiert und ein Referenzsignal erzeugt und Folgendes umfasst:

Mittel zum Identifizieren (202) von wenigstens zwei Gruppen von Benutzergeräten UEs;
 Mittel zum Signalisieren (206) einer unterschiedlichen Anzahl von Antennenports zu den wenigstens zwei Gruppen von UEs; und
 Mittel zum Erzeugen einer Anzahl von Antennenports (308) für jede Gruppe von UEs;
 wobei jeder Antennenport einer linearen Kombination aus einem Teilsatz aus einer Anzahl von physikalischen Sendeantennen entspricht und die Anzahl von erzeugten Antennenports die Anzahl von zu dieser Gruppe von UEs signalisierten Antennenports ist, und wobei die für verschiedene Antennenports für eine bestimmte Gruppe von UEs verwendete lineare Kombination linear unabhängig ist; und
dadurch gekennzeichnet, dass sie ferner Folgendes umfasst:

Mittel zum Senden eines ersten Referenzsignals für jeden der zur ersten Gruppe von

UEs signalisierten Antennenports unter Verwendung der linear unabhängigen Kombination von Sendeantennen in Verbindung mit jedem Antennenport für die erste Gruppe von UEs und zum Senden eines weiteren Referenzsignals für jeden der zur anderen Gruppe von UEs signalisierten Antennenports unter Verwendung der linear unabhängigen Kombination von mit jedem Antennenport für die andere Gruppe von UEs assoziierten Sendeantennen.

9. Drahtlose Kommunikationsvorrichtung nach Anspruch 8, wobei einige der Antennenports für unterschiedliche Gruppen von UEs gleich sind.

10. Drahtlose Kommunikationsvorrichtung nach Anspruch 8, die ferner wenigstens einen Prozessor umfasst, der zum Senden von wenigstens einem der Referenzsignale: PCFICH (Physical Control Format Indicator Channel), PHICH (Physical Hybrid ARQ Channel), und PDCCH (Physical Downlink Control Channel) und PDSCH, zu einer der Gruppen von UEs unter Verwendung der zuvor zu der Gruppe von UEs signalisierten Antennenports konfiguriert ist.

11. Drahtlose Kommunikationsvorrichtung nach Anspruch 8, die ferner Mittel zum Senden von PCFICH, PHICH, PDCCH zu einer der Gruppen von UEs unter Verwendung der zuvor zu der anderen Gruppe von UEs signalisierten Antennenports umfasst.

12. Drahtlose Kommunikationsvorrichtung nach Anspruch 8, die ferner zum Empfangen eines Referenzsignals angeordnet ist, das Feedback von einer der Benutzergerätegruppen umfasst, und wobei sich das Feedback auf wenigstens eine Kanalqualitätsbedingung für die zuvor zu den Gruppen von Benutzergeräten signalisierten Antennenports bezieht.

13. Drahtlose Kommunikationsvorrichtung nach Anspruch 8, die ferner Folgendes umfasst:

Mittel zum Planen von Sendungen zu einem UE auf PDSCH-(Physical Downlink Shared Channel)-Ressourcen, die frequenzverteilt sind; und Mittel zum Senden von PDSCH zu einem UE unter Verwendung der Antennenports, die einer der Gruppen von UEs entsprechen, zu denen das UE gehört.

14. Drahtlose Kommunikationsvorrichtung nach Anspruch 8, wobei das gesendete Referenzsignal zu verschiedenen Gruppen von UEs unterschiedliche Diagramme, Dichte und unterschiedliche Periodizität haben.

15. Computerlesbares Medium, das maschinenausführ-

bare Befehle aufweist, um bei Ausführung zu bewirken, dass wenigstens ein Computer ein Verfahren nach einem der Ansprüche 1 bis 7 ausführt.

Revendications

1. Procédé utilisé dans un système de communications sans fil pour la génération d'un signal de référence, comprenant :

l'identification (502) d'au moins deux groupes d'équipement utilisateur, UE ;
la signalisation (504) d'un nombre différent de ports d'antenne aux au moins deux groupes d'UE ; et

la création (506) d'un nombre de ports d'antenne pour chaque groupe d'UE ;
dans lequel chaque port d'antenne correspond à une combinaison linéaire d'un sous-ensemble d'un nombre d'antennes d'émission physiques et le nombre de ports d'antenne créés est le nombre de ports d'antenne signalés à chaque groupe d'UE, et dans lequel la combinaison linéaire employée pour différents ports d'antenne pour un groupe particulier d'UE est linéairement indépendante ; et

caractérisé en ce qu'il comprend en outre la transmission d'un premier signal de référence pour chacun des ports d'antenne signalés au premier groupe d'UE en utilisant la combinaison linéairement indépendante d'antennes d'émission associée à chaque port d'antenne du premier groupe d'UE et la transmission d'un autre signal de référence pour chacun des ports d'antenne signalés à l'autre groupe d'UE en utilisant la combinaison linéairement indépendante d'antennes d'émission associées à chaque port d'antenne pour l'autre groupe d'UE.

2. Procédé selon la revendication 1, dans lequel la combinaison linéaire dépend de la fréquence ou dans lequel la combinaison linéaire est une diversité de retard cyclique, CDD.

3. Procédé selon la revendication 1, dans lequel une combinaison linéaire des ports d'antenne correspondant au premier groupe d'UE ayant un nombre supérieur de ports d'antennes signalés est utilisée comme port d'antenne pour le second groupe d'UE ayant un nombre inférieur de ports d'antenne.

4. Procédé selon la revendication 1, dans lequel l'autre signal de référence se rapporte à au moins un port d'antenne correspondant précédemment signalé à l'un des groupes d'UE.

5. Procédé selon la revendication 3, comprenant en

outre la communication de la combinaison linéaire et d'un retard connexe au premier groupe d'UE.

6. Procédé selon la revendication 1, dans lequel les signaux de référence transmis à différents groupes d'UE ont des formes différentes, une densité différente et une périodicité différente. 5

7. Procédé selon la revendication 1, comprenant en outre : 10

la transmission d'au moins l'un des signaux de référence relatifs aux ports d'antenne pour l'un des groupes d'UE dans une région de canal partagé de liaison descendante physique, PDSCH, attribuée à au moins un groupe spécifique d'UE ; l'emploi des ports d'antenne pour l'un des groupes d'UE avec des ports d'antenne respectifs définis pour l'autre groupe d'UE pour créer des faisceaux pour la transmission du PDSCH aux groupes d'UE ; et l'estimation d'un canal à partir des ports d'antenne en fonction d'au moins l'un des éléments suivants : 15

un signal de référence relatif à au moins l'un des ports d'antenne d'UE ou d'un port d'antenne différent ; et

une information de mappage qui associe le signal de référence à un sens de faisceau utilisé pour la transmission du PDSCH. 20

8. Appareil de communications sans fil qui optimise la configuration d'antennes d'émission et génère un signal de référence, comprenant : 25

un moyen d'identification (202) d'au moins deux groupes d'équipements utilisateurs, UE ; un moyen de signalisation (206) d'un nombre différent de ports d'antenne aux au moins deux groupes d'UE ; et 30

un moyen de création d'un nombre de ports d'antenne (308) pour chaque groupe d'UE ; dans lequel chaque port d'antenne correspond à une combinaison linéaire d'un sous-ensemble d'un nombre d'antennes d'émission physiques et le nombre de ports d'antenne créés est le nombre de ports d'antenne signalés à chaque groupe d'UE, et dans lequel la combinaison linéaire employée pour différents ports d'antenne pour un groupe particulier d'UE est linéairement indépendante ; et 35

caractérisé en ce qu'il comprend en outre

un moyen de transmission d'un premier signal de référence pour chacun des ports d'antenne signalés au premier groupe d'UE en utilisant la combinaison linéairement indépendante d'antennes d'émission associée à chaque port d'an- 40

tenne du premier groupe d'UE et de transmission d'un autre signal de référence pour chacun des ports d'antenne signalés à l'autre groupe d'UE en utilisant la combinaison linéairement indépendante d'antennes de transmission associées à chaque port d'antenne pour l'autre groupe d'UE.

9. Appareil de communications sans fil selon la revendication 8, dans lequel certains des ports d'antenne pour différents groupes d'UE sont les mêmes. 45

10. Appareil de communications sans fil selon la revendication 8, comprenant en outre au moins un processeur configuré pour transmettre au moins l'un des signaux de référence, canal indicateur de format de commande physique, PCFICH, canal ARQ hybride physique, PHICH, et canal de commande de liaison descendante physique, PDCCH, et PDSCH à l'un des groupes d'UE en utilisant les ports d'antenne précédemment signalés au groupe d'UE. 50

11. Appareil de communications sans fil selon la revendication 8, comprenant en outre un moyen pour envoyer PCFICH, PHICH, PDCCH, à l'un des groupes d'UE en utilisant les ports d'antenne précédemment signalés à l'autre groupe d'UE. 55

12. Appareil de communications sans fil selon la revendication 8, agencé en outre pour recevoir un signal de référence comprenant une contre-réaction depuis l'un des groupes d'équipements utilisateurs et dans lequel la contre-réaction est liée à au moins une condition de qualité de canal pour les ports d'antenne précédemment signalés aux groupes d'équipements utilisateurs. 60

13. Appareil de communications sans fil selon la revendication 8, comprenant en outre : 65

un moyen d'ordonnancement de la transmission à un UE sur un canal partagé de liaison descendante physique, PDSCH, de ressources distribuées en fréquence ; et

un moyen de transmission de PDSCH à un UE en utilisant les ports d'antenne correspondant à l'un des groupes d'UE auxquels appartient l'UE. 70

14. Appareil de communications sans fil selon la revendication 8, dans lequel le signal de référence transmis aux différents groupes d'UE ont des formes différentes, une densité différente et une périodicité différente. 75

15. Support lisible par ordinateur mettant en oeuvre des instructions exécutables par machine pour amener au moins un ordinateur à effectuer un procédé selon l'une quelconque des revendications 1 à 7 lorsqu'el- 80

les sont exécutées.

5

10

15

20

25

30

35

40

45

50

55




FIG. 1




FIG. 2




FIG. 3







FIG. 4

**FIG. 5**

**FIG. 6**

**FIG. 7**




FIG. 8




FIG. 9




FIG. 10




FIG. 11

REFERENCES CITED IN THE DESCRIPTION

This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.

Non-patent literature cited in the description

- Downlink Multiple Antenna Schemes for LTE-Advanced, Motorola. R1-083228. 18 August 2008
[0005]

Referenciajel kialakítás LTE-Advanced mobiladatátvitelhez

Szabadalmi igénypontok

1. Vezeték nélküli kommunikációs rendszerben alkalmazott eljárás egy referenciajel előállítására, az eljárás tartalmazza:

legalább két felhasználói készülék, UE, csoport azonosítását (502);

a legalább két UE csoporthoz különböző antenna port szám jelzését (504); és

minden egyes UE csoport számára egy antenna port szám létrehozását (506);

ahol minden egyes antenna port fizikai adóantennának szám alkészlete lineáris kombinációjának felel meg, és a létrehozott antenna portok száma a minden egyes UE csoport felé jelzett antenna portok száma, és ahol az egy meghatározott UE csoporthoz tartozó különböző antenna portokhoz alkalmazott lineáris kombináció lineárisan független; és

azzal jellemezve, hogy tartalmazza továbbá egy az UE-k első csoportja felé jelzett minden egyes antenna porthoz tartozó első referenciajel küldését, az első UE csoporthoz tartozó minden egyes antenna porttal társított adóantennának lineárisan független kombinációjának a felhasználásával, és egy a másik UE csoport felé jelzett minden egyes antenna porthoz tartozó további referenciajel küldését, a másik UE csoporthoz tartozó egyes antenna portokkal társított adóantennának lineárisan független kombinációjának felhasználásával.

2. Az 1. igénypont szerinti eljárás, ahol a lineáris kombináció frekvenciafüggő, vagy ahol a lineáris kombináció ciklikus késleltetés diverzitású, CDD.

3. Az 1. igénypont szerinti eljárás, ahol a nagyobb jelzett antenna port számú első UE csoporthoz tartozó antenna portok lineáris kombinációját egy kisebb antenna port számú második UE csoporthoz tartozó antenna portként használjuk.

4. Az 1. igénypont szerinti eljárás, ahol a további referenciajel egy előzőleg az UE csoportok egyike felé jelzett legalább egy hozzá tartozó antenna portra vonatkozik.

5. A 3. igénypont szerinti eljárás, amely tartalmazza továbbá a lineáris kombináció és egy vonatkozó késleltetés kommunikálását az első UE csoport felé.

6. Az 1. igénypont szerinti eljárás, ahol a különböző UE csoporthoz továbbított referenciajelek eltérő mintájúak, eltérő sűrűségűek és eltérő frekvenciájúak.

7. Az 1. igénypont szerinti eljárás, amely tartalmazza továbbá:

legalább egy, az UE csoportok egyikének antenna portjaira vonatkozó referenciajel küldését egy, legalább egy meghatározott UE csoporthoz hozzárendelt fizikai lefelé irányuló kapcsolati megosztott csatorna, PDSCH, régióban;

az UE csoportok egyikéhez tartozó antenna portok használatát a másik UE csoport számára definiált vonatkozó antenna portokkal, a PDSCH UE csoporthoz továbbítására szolgáló nyulábok létrehozásához; és

az antenna portokból egy csatorna becslését a következők legalább egyike alapján:

egy az UE antenna portok vagy egy külön antenna port legalább egyikére vonatkozó referenciajel; vagy

egy a referenciajelet a PDSCH továbbításához használt nyíláb irányra vonatkoztató leképezési információ.

8. Vezeték nélküli kommunikációs berendezés, amely adóantennák konfigurációját optimalizálja és egy referenciajelet állít elő, a berendezés tartalmaz:

eszközt (202) legalább két felhasználói készülék, UE, csoport azonosítására;

eszközt (206) a legalább két UE csoporthoz különböző antenna port szám jelzésére; és

eszközt (308) minden egyes UE csoport számára egy antenna port szám létrehozására;

ahol minden egyes antenna port fizikai adóantennák szám alkészlete lineáris kombinációjának felel meg, és a létrehozott antenna portok száma a minden egyes UE csoport felé jelzett antenna portok száma, és ahol az egy meghatározott UE csoporthoz tartozó különböző antenna portokhoz alkalmazott lineáris kombináció lineárisan független; és

azzal jellemezve, hogy tartalmaz továbbá eszközt egy az UE-k első csoportja felé jelzett minden egyes antenna porthoz tartozó első referenciajel küldésére az első UE csoporthoz tartozó minden egyes antenna porttal társított adóantennák lineárisan független kombinációjának a felhasználásával, és egy a másik UE csoport felé jelzett minden egyes antenna porthoz tartozó további referenciajel küldésére a másik UE csoporthoz tartozó egyes antenna portokkal társított adóantennák lineárisan független kombinációjának felhasználásával.

9. A 8. igénypont szerinti vezeték nélküli kommunikációs berendezés, ahol a különböző UE csoportokhoz tartozó antenna portok közül egyesek azonosak.

10. A 8. igénypont szerinti vezeték nélküli kommunikációs berendezés, amely továbbá legalább egy processzort tartalmaz, amely úgy van konfigurálva, hogy az előzőleg az UE csoport felé jelzett antenna portokat használva legalább egyet továbbít az UE csoportok egyikéhez referenciajelek, fizikai vezérlő formátum jelző csatorna, PCFICH, fizikai hibrid ARQ csatorna, PHICH, és fizikai lefelé irányuló kapcsolati vezérlőcsatorna, PDCCH, és PDSCH közül.

11. A 8. igénypont szerinti vezeték nélküli kommunikációs berendezés, amely tartalmaz továbbá eszközt az UE csoportok egyikéhez PCFICH, PHICH, PDCCH küldésére a másik UE csoport felé előzőleg jelzett antenna portok felhasználásával.

12. A 8. igénypont szerinti vezeték nélküli kommunikációs berendezés, amely alkalmassá van téve továbbá arra, hogy egy referenciajelet vegyen, amely visszacsatolást tartalmaz a felhasználói készülék csoportok egyikétől, és ahol a visszacsatolás legalább egy csatornaminőség kondícióra vonatkozik a felhasználói készülék csoportok felé előzőleg jelzett antenna portokhoz.

13. A 8. igénypont szerinti vezeték nélküli kommunikációs berendezés, amely tartalmaz továbbá:

eszközt egy UE-hez frekvenciában elosztott erőforrások küldésének ütemezésére egy fizikai lefelé irányuló kapcsolati megosztott csatormán, PDSCH-n; és

eszközt PDSCH egy UE-hez küldésére, ahhoz az UE csoporthoz tartozó antenna portok használatával, amelyhez az UE tartozik.

14. A 8. igénypont szerinti vezeték nélküli kommunikációs berendezés, ahol a különböző UE csoportokhoz

továbbított referencijel különböző mintájú, sűrűségű és különböző frekvenciájú.

15. Számítógéppel olvasható közeg, amely géppel végrehajtható utasításokat testesít meg, amelyek legalább egy számítógépet arra készítenek, hogy az végrehajtásuk során megvalósítsa az 1-7. igénypontok bármelyike szerinti eljárást.