

[54] **METHOD OF MAKING HUMIDITY SENSOR**

[75] Inventors: **Lawrence E. Frazee**, Huntington, N.Y.; **Anthony V. Fraioli**, Essexfells, N.J.

[73] Assignee: **Plessey Incorporated**, Melville, N.Y.

[22] Filed: **Feb. 19, 1974**

[21] Appl. No.: **443,436**

[52] U.S. Cl. **29/621; 29/620; 252/518; 338/35**

[51] Int. Cl. **H01c 1/14; H01c 17/00**

[58] Field of Search **29/620, 621, 610; 73/335, 73/336.5; 252/518; 338/35; 117/201; 148/13, 129**

[56] **References Cited**

UNITED STATES PATENTS

3,345,596	10/1967	Delaney et al.	338/35
3,369,880	2/1968	Mochel	338/35 X
3,607,386	9/1971	Galla	29/620 X

3,703,697 11/1972 Nicholas 338/35

FOREIGN PATENTS OR APPLICATIONS

795,031 5/1958 United Kingdom..... 338/35

Primary Examiner—Richard J. Herbst


Assistant Examiner—Victor A. DiPalma




Attorney, Agent, or Firm—James J. Burke, II

[57] **ABSTRACT**

The operation of relative humidity sensors made from cobalt oxide on a non-conductive ceramic substrate is improved by heating the sensor for a short period to a high temperature in a reducing atmosphere. This reduces the specific resistance of the device. With a lower resistivity, it is possible to reduce the size of the sensor to the point where it can be included along with a semiconductive device in standard hermetic packages. This makes possible the continuous, on-line monitoring of hermeticity for the life of the circuit without the necessity of applying a load to the circuit.

5 Claims, 3 Drawing Figures





METHOD OF MAKING HUMIDITY SENSOR

BACKGROUND OF THE INVENTION

The present invention relates in general to relative humidity sensors and, more particularly, the invention relates to sensors made from cobalt oxide as the active element. Humidity sensors of this type are also referred to as hygrometers or humistors, as it is their electrical resistivity which changes with humidity.

Procedures for manufacturing cobalt oxide humidity sensors or hygrometers are well known. The starting material is a cobalt oxide powder. As pure CoO powder is very expensive, the starting material is generally a mixture of CoO with some Co₃O₄, but the latter compound dissociates at about 900°C. so the completed sensor will be essentially CoO, the cobaltous oxide. This compound is stable up to its melting point, which is above 1800°C.

The finely divided powder, preferably minus 325 mesh, is mixed with an inert liquid vehicle and viscosifiers to form a screen-printable paste. A thin layer of the paste is then screen-printed in a desired pattern onto a dielectric, high-temperature resistant substrate, typically a high-alumina ceramic. The screened pattern is then dried and fired in air at a temperature in the range of 1350°C. to 1550°C. Electrodes can be preformed on the substrate, co-fired with the paste, or applied in a subsequent operation. The latter is the more common approach, as it is generally desired to have the electrodes in a rather elaborate, interdigitated pattern on the top surface. Conductive inks or pastes (platinum-gold, palladium-gold, etc.) are used in the conventional manner.

Before such a sensor can be put to use, it must be accurately calibrated to determine the change in electrical resistance with relative humidity.

The very high specific resistivity of cobalt oxide, which is 10⁶ ohms per square or higher, requires that humidity sensors made therefrom be relatively large in order to produce suitable output. Typically, prior art humidity sensors of this type are manufactured on one inch square substrates. This is of course much too large to be included in integrated circuit packages.

The desirability of having a humidity sensor within a hermetically sealed semiconductor package is manifest. Essentially all semiconductive devices are humidity-sensitive to a greater or lesser degree. As a result, specifications on hermeticity for packages are most stringent. But, while technology for producing hermetic packages is well developed and tests therefor standardized, the fact that a package is hermetic initially says nothing about whether it will remain so after months or years of service, often under severe conditions of shock and vibration. Further, the failure of a seal in service can now be detected only by a malfunction or failure of the circuit.

PRIOR ART

The production of cobalt oxide hygrometers is disclosed by Delaney et al in U.S. Pat. No. 3,345,596. The two U.S. Pat. Nos. of Nicholas, 3,703,697 and 3,715,702, disclose the use of humectants to increase water absorption on hygrometer surfaces of this same type. In one instance the oxide is converted in part to the oxychloride, and in the other, a coating of lithium chloride or polyethylene glycol is provided. Blythe et

al, U.S. Pat. No. 3,105,214, disclose the use of a vapor-permeable ion-selective membrane on the sensor surface. This will swell up in a humid environment and transport water but not ions to the sensor surface.

OBJECT OF THE INVENTION

A general object of the present invention is to provide improved humidity sensors of the cobalt oxide type.

Another object of the present invention is to provide a cobalt oxide humidity sensor which is smaller than prior art sensors.

A further object of the present invention is to provide a cobalt oxide humidity sensor within a hermetically sealed semiconductor package.

A still further object of the present invention is to provide a cobalt oxide humidity sensor having a lower resistivity than prior art sensors of the same general type.

Yet another object of the present invention is to provide a cobalt oxide humidity sensor very sensitive in the low-ppm range.

A still further object of the present invention is to provide a semiconductor package with a built-in or integral humidity sensor.

Various other objects and advantages of the invention will become clear from the following description of embodiments thereof, and the novel features will be particularly pointed out in connection with the appended claims.

THE DRAWINGS

Reference will hereinafter be made to the accompanying drawings wherein:

FIG. 1 is a plan view of a typical humidity sensor;

FIG. 2 is a perspective view of a portion of an integrated circuit package including an integral humidity sensor in accordance with this invention; and

FIG. 3 is an enlarged view of a portion of the sensor of FIG. 1, illustrating resistivity calculations.

DESCRIPTION OF EMBODIMENTS

The present invention comprises, in essence, lowering the specific-resistivity of the cobalt oxide film by heating the previously fired film to a high temperature in a reducing atmosphere for a brief period. The atmosphere is preferably hydrogen. This treatment has been observed to reduce the resistivity of the film by 1 to 1.25 orders of magnitude. Thus, an air-fired CoO film with a resistivity of 3.76×10^6 ohms/square has a resistivity of 6.3×10^4 ohms per square after firing in hydrogen at 1500°C. for 15 minutes.

The reasons why this treatment reduces resistivity are unclear, just as the mechanism of conduction in cobalt oxide is unclear. It is possible that the reducing gas attacks the CoO crystallite boundaries preferentially and exposes more surface with a higher surface energy. It is not known whether CoO conducts with surface electrons or "holes" in the bulk material; it is felt to be possible that the hydrogen firing could contribute to bulk conductivity because of the higher surface energy conditions.

It is believed that the prior-art (Delaney et al) teaching of firing the cobalt oxide for a brief period only and at a high temperature (1500°C.) is designed to provide a large number of very small CoO crystals and prevent crystal growth. The hydrogen treatment of the present

invention may significantly increase the population-density of exposed crystal edges and corners. Because of the interrupted lattice periodicity at these locations, and resultant dangling or broken bonds, these sites should be preferred locations for gas adsorption-desorption phenomena involved in the relative humidity equilibration process.

The hydrogen firing process has been optically observed to produce etch pits on the CoO surface which are quasi-hexagonal in plan view and conical in cross-section, with terraced walls. Etch lines about larger, pyramidal-shaped crystals parallel to a base plane have also been observed. It is believed that such exposed crystal surfaces should enhance gas-surface interaction phenomena.

The lowering of the CoO resistivity is desirable for several reasons, the most important of which is that it permits a substantial reduction in the size of the humistor. Thus, heretofore a typical humistor had to be mounted on a 1 inch square substrate, to allow for device and conductive geometry that would give a suitable output. In accordance with the present invention, humistors of the same resistance are produced on 0.20 by 0.20 inch substrates with the same (1-5 volt) outputs and improved linearity of response.

This permits humistors of the present invention to be used for the first time as hermeticity detectors within semiconductive device packages. As noted hereinabove, stringent hermeticity requirements are imposed in both military and commercial electronics specifications, because humidity has a disastrous effect on the operation of both active and passive microcircuit elements. Heretofore, it has not been possible to detect hermeticity failures, i.e., leaks, except through circuit mal-functions. With the miniaturized humidity sensors produced in accordance with the present invention, it becomes possible to include the device on the substrate within the can or package. In operation with a nominal bias, it will be essentially non-conductive. If the package fails and even a few ppm of moisture are encountered, the sensor will be rendered sufficiently conductive to trigger an alarm. Thus, with the present invention it is possible to continuously monitor hermeticity without waiting for circuit damage, mal-function or failure, and hermeticity monitoring is carried out without loading the main circuit. More particularly, humistors of the present invention may have a total wet-to-dry resistance change of as much as six or seven orders of magnitude. This very great change is believed to account for the substantial sensitivity in the very low ppm (high resistivity) range.

Humistors made in accordance with the present invention resemble prior art devices except insofar as the hydrogen firing tends to change the normally rather glossy CoO surface to a more matte-like appearance. As shown in FIG. 1, a ceramic substrate 10 has a layer of cobalt oxide 12 screened and fired over its entire surface (or less than the entire surface, as desired). First and second electrode patterns 14, 16 which terminate in bonding pads 18, 20 are then screened and fired. After firing in a reducing atmosphere (which may occur before or after application of electrodes) the device is complete.

FIG. 2 illustrates a humidity sensor of the present invention incorporated into a standard dual in-line 14-lead package. The substrate 22 first has a cobalt oxide area 24 screened and fired thereon. Thereafter, the in-

tegrated circuit leads 26, the humistor electrodes 28, and leads therefore 30 are all screened and fired simultaneously. The entire unit is then fired in hydrogen, since this will not effect the metallic patterns. Installation of the integrated circuit 32 or other semiconductive device, sealing and testing follow conventional procedures, except that further exposure to reducing atmospheres should be avoided.

Understanding of the invention will be facilitated by reference to the following specific example, which is to be construed as illustrative only and not in a limiting sense.

EXAMPLE

In humistors (or resistors) of the general type described, calculation of resistivity in ohms/square is more complex than for simple thick film geometries, and depends on the space between respective interdigitated electrodes and their length. With reference to FIG. 3, the number of squares is calculated according to the following formula:

$$\text{No. of squares} = \frac{L}{W} \times \frac{1}{(N-1)} \quad [1]$$

In Equation 1, N is the total number of conductor lines, so N-1 is the number of resistor lines. The factor L/W is multiplied by the reciprocal of N-1 because, while L is constant throughout the pattern, W is lengthened by each pair of conductors, and it is this which must be multiplied by N-1. As will be apparent from the data hereinbelow, this produces resistors with very small numbers of squares.

Cobalt oxide paste was screened and fired onto one inch substrates in a 950 mil square pattern and fired. One group of substrates was fired in hydrogen and all substrates had identical conductives applied, wherein

$$L = 15$$

$$W = 800$$

$$N = 26$$

(all dimension being in mils). In accordance with equation 1, the number of squares was 7.5×10^{-4} . At 100 percent relative humidity, the resistors that were not hydrogen fired had resistances of $3.2 \times 10^6 \Omega$ and those that were so treated measured $1.9 \times 10^5 \Omega$. In terms of ohms/square, these figures convert to 4.26×10^9 and 2.53×10^8 , respectively.

The same paste was screened in 200 mil square patterns and, again one group was fired in hydrogen and another was not. Conductives were applied in a pattern where

5

L = 15
W = 180
N = 8

The number of squares in this pattern is 1.19047×10^{-22} . During processing, film thickness, firing parameters etc. were all closely controlled so that the films were comparable except for size and conductive geometry. On these units, at 100 percent R.H., resistance of the non-hydrogen fired units was $5.07 \times 10^7 \Omega$ and those that were so treated measured $3.01 \times 10^6 \Omega$. Resistance of 200 mil square humistors treated in accordance with the present invention is thus seen to be substantially the same as 950 mil square units that were not so treated (i.e., $3.2 \times 10^6 \Omega$).

Humistors are calibrated by plotting log R vs. relative humidity over the entire humidity range. A problem with known humistors has been an asymptotic resistance change (or other anomalies) as R.H. approaches 0 percent. An advantage of humistors made in accordance with the present invention is a substantially linear response over the entire R.H. range. This greatly simplifies required circuitry and makes the devices useful as hermeticity detectors, where R.H. must be measured in parts-per-million. The reason why the reducing-gas treatment brings about this desirable improvement is not understood.

It will be appreciated by those skilled in the art that FIG. 2 is illustrative only and is not to be construed in a limiting sense, since many variations are possible. Thus, a discrete humistor as shown in FIG. 1 could be incorporated into a semiconductor package rather than having the package manufactured with an integral device. The humistor could be wired in the main circuit if that condition could be tolerated. Different package designs offer varying opportunities for placement of the sensor. In packages having glass-sealed ceramic lids for example, it would be possible to have the sensor printed on the under-side of the lid. Discrete or integral sensors could be incorporated into header cans. In laminated packages having leads on a raised step section surrounding the device in a central cavity, the sensor could be placed on either level.

It will be further appreciated that the small size of hu-

6

mistors of the present invention permits their incorporation in a variety of other devices where hermeticity is important. Image intensifier tubes or other electronic tubes are one example. Optical systems where hermeticity is required to avoid condensation of optical elements in another example.

Various other changes in the details, steps, materials and arrangements of parts, which have been herein described and illustrated in order to explain the nature of the invention, may be made by those skilled in the art within the principle and scope of the invention as defined in the appended claims.

What is claimed is:

1. The method of forming a humidity sensor comprising:
 - 15 ing:
 - mixing cobalt oxide powder with an inert vehicle to form a paste;
 - applying a layer of said paste onto a major surface of a high-temperature resistant dielectric substrate;
 - 20 firing said paste in an oxidizing atmosphere at a temperature of about 1350°C. to 1550°C. to form a hygroscopic element; and
 - firing said hygroscopic element at a temperature of about 1500°C. for a few minutes in a reducing atmosphere, whereby the resistivity of said element is reduced.
 2. The method as claimed in claim 1, and additionally comprising applying a pair of electrodes to said element.
 - 30 3. The method as claimed in claim 1, wherein said reducing atmosphere comprises hydrogen.
 4. In the method of producing a humidity sensor by firing a layer of a cobalt oxide paste onto a high-temperature resistant, dielectric substrate to produce a hygroscopic element, the improvement comprising firing said element a second time for a short period at a temperature of about 1500°C. in a reducing atmosphere, whereby the resistivity of said element is lowered.
 5. The method as claimed in claim 4, wherein said reducing atmosphere is hydrogen.

* * * * *

45

50

55

60

65

UNITED STATES PATENT OFFICE
CERTIFICATE OF CORRECTION

Patent No. 3,890,703

Dated 24 June 1975

Inventor(s) LAWRENCE E. FRAZEE et al

It is certified that error appears in the above-identified patent and that said Letters Patent are hereby corrected as shown below:

Column 1, line 40: "suitable suitalbe" should be
--a suitable--; line 61: "u.S." should be --U.S.--

Column 3, line 13: "be" should be --been--

Column 5, line 5: "10⁻²²" should be --10⁻²--;
lines 6 and 14 should not be indented; line 18: "anomalides"
should be --anomalies--; line 33: "inot" should be --into--

Signed and Sealed this

ninth Day of September 1975

[SEAL]

Attest:

RUTH C. MASON
Attesting Officer

C. MARSHALL DANN
Commissioner of Patents and Trademarks